(old) htmldiff from- (new)

Proprietary Notice

This document is protected by copyright and other related rights and the practice or implementation of the information contained in this document may be protected by one or more patents or pending patent applications. No part of this document may be reproduced in any form by any means without the express prior written permission of Arm. No license, express or implied, by estoppel or otherwise to any intellectual property rights is granted by this document unless specifically stated.

Your access to the information in this document is conditional upon your acceptance that you will not use or permit others to use the information for the purposes of determining whether implementations infringe any third party patents.

THIS DOCUMENT IS PROVIDED “AS IS”. ARM PROVIDES NO REPRESENTATIONS AND NO WARRANTIES, EXPRESS, IMPLIED OR STATUTORY, INCLUDING, WITHOUT LIMITATION, THE IMPLIED WARRANTIES OF MERCHANTABILITY, SATISFACTORY QUALITY, NON-INFRINGEMENT OR FITNESS FOR A PARTICULAR PURPOSE WITH RESPECT TO THE DOCUMENT. For the avoidance of doubt, Arm makes no representation with respect to, and has undertaken no analysis to identify or understand the scope and content of, patents, copyrights, trade secrets, or other rights.

This document may include technical inaccuracies or typographical errors.

TO THE EXTENT NOT PROHIBITED BY LAW, IN NO EVENT WILL ARM BE LIABLE FOR ANY DAMAGES, INCLUDING WITHOUT LIMITATION ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, ARISING OUT OF ANY USE OF THIS DOCUMENT, EVEN IF ARM HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

This document consists solely of commercial items. You shall be responsible for ensuring that any use, duplication or disclosure of this document complies fully with any relevant export laws and regulations to assure that this document or any portion thereof is not exported, directly or indirectly, in violation of such export laws. Use of the word “partner” in reference to Arm’s customers is not intended to create or refer to any partnership relationship with any other company. Arm may make changes to this document at any time and without notice.

If any of the provisions contained in these terms conflict with any of the provisions of any click through or signed written agreement covering this document with Arm, then the click through or signed written agreement prevails over and supersedes the conflicting provisions of these terms. This document may be translated into other languages for convenience, and you agree that if there is any conflict between the English version of this document and any translation, the terms of the English version of the Agreement shall prevail.

The Arm corporate logo and words marked with ® or ™ are registered trademarks or trademarks of Arm Limited (or its subsidiaries) in the US and/or elsewhere. All rights reserved. Other brands and names mentioned in this document may be the trademarks of their respective owners. Please follow Arm’s trademark usage guidelines at http://www.arm.com/company/policies/trademarks.

Copyright © 2019 Arm Limited (or its affiliates). All rights reserved.

Arm Limited. Company 02557590 registered in England.

110 Fulbourn Road, Cambridge, England CB1 9NJ.

LES-PRE-20349

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AArch64 System Registers

ACTLR_EL1: Auxiliary Control Register (EL1)

ACTLR_EL2: Auxiliary Control Register (EL2)

ACTLR_EL3: Auxiliary Control Register (EL3)

AFSR0_EL1: Auxiliary Fault Status Register 0 (EL1)

AFSR0_EL2: Auxiliary Fault Status Register 0 (EL2)

AFSR0_EL3: Auxiliary Fault Status Register 0 (EL3)

AFSR1_EL1: Auxiliary Fault Status Register 1 (EL1)

AFSR1_EL2: Auxiliary Fault Status Register 1 (EL2)

AFSR1_EL3: Auxiliary Fault Status Register 1 (EL3)

AIDR_EL1: Auxiliary ID Register

AMAIR_EL1: Auxiliary Memory Attribute Indirection Register (EL1)

AMAIR_EL2: Auxiliary Memory Attribute Indirection Register (EL2)

AMAIR_EL3: Auxiliary Memory Attribute Indirection Register (EL3)

AMCFGR_EL0: Activity Monitors Configuration Register

AMCG1IDR_EL0: Activity Monitors Counter Group 1 Identification Register

AMCGCR_EL0: Activity Monitors Counter Group Configuration Register

AMCNTENCLR0_EL0: Activity Monitors Count Enable Clear Register 0

AMCNTENCLR1_EL0: Activity Monitors Count Enable Clear Register 1

AMCNTENSET0_EL0: Activity Monitors Count Enable Set Register 0

AMCNTENSET1_EL0: Activity Monitors Count Enable Set Register 1

AMCR_EL0: Activity Monitors Control Register

AMEVCNTR0<n>_EL0: Activity Monitors Event Counter Registers 0

AMEVCNTR1<n>_EL0: Activity Monitors Event Counter Registers 1

AMEVCNTVOFF0<n>_EL2: Activity Monitors Event Counter Virtual Offset Registers 0

AMEVCNTVOFF1<n>_EL2: Activity Monitors Event Counter Virtual Offset Registers 1

AMEVTYPER0<n>_EL0: Activity Monitors Event Type Registers 0

AMEVTYPER1<n>_EL0: Activity Monitors Event Type Registers 1

AMUSERENR_EL0: Activity Monitors User Enable Register

APDAKeyHi_EL1: Pointer Authentication Key A for Data (bits[127:64])

APDAKeyLo_EL1: Pointer Authentication Key A for Data (bits[63:0])

APDBKeyHi_EL1: Pointer Authentication Key B for Data (bits[127:64])

APDBKeyLo_EL1: Pointer Authentication Key B for Data (bits[63:0])

APGAKeyHi_EL1: Pointer Authentication Key A for Code (bits[127:64])

APGAKeyLo_EL1: Pointer Authentication Key A for Code (bits[63:0])

APIAKeyHi_EL1: Pointer Authentication Key A for Instruction (bits[127:64])

APIAKeyLo_EL1: Pointer Authentication Key A for Instruction (bits[63:0])

APIBKeyHi_EL1: Pointer Authentication Key B for Instruction (bits[127:64])

APIBKeyLo_EL1: Pointer Authentication Key B for Instruction (bits[63:0])

CCSIDR2_EL1: Current Cache Size ID Register 2

CCSIDR_EL1: Current Cache Size ID Register

CLIDR_EL1: Cache Level ID Register

CNTFRQ_EL0: Counter-timer Frequency register

CNTHCTL_EL2: Counter-timer Hypervisor Control register

CNTHPS_CTL_EL2: Counter-timer Secure Physical Timer Control register (EL2)

CNTHPS_CVAL_EL2: Counter-timer Secure Physical Timer CompareValue register (EL2)

CNTHPS_TVAL_EL2: Counter-timer Secure Physical Timer TimerValue register (EL2)

CNTHP_CTL_EL2: Counter-timer Hypervisor Physical Timer Control register

CNTHP_CVAL_EL2: Counter-timer Physical Timer CompareValue register (EL2)

CNTHP_TVAL_EL2: Counter-timer Physical Timer TimerValue register (EL2)

CNTHVS_CTL_EL2: Counter-timer Secure Virtual Timer Control register (EL2)

CNTHVS_CVAL_EL2: Counter-timer Secure Virtual Timer CompareValue register (EL2)

CNTHVS_TVAL_EL2: Counter-timer Secure Virtual Timer TimerValue register (EL2)

CNTHV_CTL_EL2: Counter-timer Virtual Timer Control register (EL2)

CNTHV_CVAL_EL2: Counter-timer Virtual Timer CompareValue register (EL2)

CNTHV_TVAL_EL2: Counter-timer Virtual Timer TimerValue Register (EL2)

CNTKCTL_EL1: Counter-timer Kernel Control register

CNTPCTSS_EL0: Counter-timer Self-Synchronized Physical Count register

CNTPCT_EL0: Counter-timer Physical Count register

CNTPOFF_EL2: Counter-timer Physical Offset register

CNTPS_CTL_EL1: Counter-timer Physical Secure Timer Control register

CNTPS_CVAL_EL1: Counter-timer Physical Secure Timer CompareValue register

CNTPS_TVAL_EL1: Counter-timer Physical Secure Timer TimerValue register

CNTP_CTL_EL0: Counter-timer Physical Timer Control register

CNTP_CVAL_EL0: Counter-timer Physical Timer CompareValue register

CNTP_TVAL_EL0: Counter-timer Physical Timer TimerValue register

CNTVCTSS_EL0: Counter-timer Self-Synchronized Virtual Count register

CNTVCT_EL0: Counter-timer Virtual Count register

CNTVOFF_EL2: Counter-timer Virtual Offset register

CNTV_CTL_EL0: Counter-timer Virtual Timer Control register

CNTV_CVAL_EL0: Counter-timer Virtual Timer CompareValue register

CNTV_TVAL_EL0: Counter-timer Virtual Timer TimerValue register

CONTEXTIDR_EL1: Context ID Register (EL1)

CONTEXTIDR_EL2: Context ID Register (EL2)

CPACR_EL1: Architectural Feature Access Control Register

CPTR_EL2: Architectural Feature Trap Register (EL2)

CPTR_EL3: Architectural Feature Trap Register (EL3)

CSSELR_EL1: Cache Size Selection Register

CTR_EL0: Cache Type Register

CurrentEL: Current Exception Level

DACR32_EL2: Domain Access Control Register

DAIF: Interrupt Mask Bits

DBGAUTHSTATUS_EL1: Debug Authentication Status register

DBGBCR<n>_EL1: Debug Breakpoint Control Registers

DBGBVR<n>_EL1: Debug Breakpoint Value Registers

DBGCLAIMCLR_EL1: Debug CLAIM Tag Clear register

DBGCLAIMSET_EL1: Debug CLAIM Tag Set register

DBGDTRRX_EL0: Debug Data Transfer Register, Receive

DBGDTRTX_EL0: Debug Data Transfer Register, Transmit

DBGDTR_EL0: Debug Data Transfer Register, half-duplex

DBGPRCR_EL1: Debug Power Control Register

DBGVCR32_EL2: Debug Vector Catch Register

DBGWCR<n>_EL1: Debug Watchpoint Control Registers

DBGWVR<n>_EL1: Debug Watchpoint Value Registers

DCZID_EL0: Data Cache Zero ID register

DISR_EL1: Deferred Interrupt Status Register

DIT: Data Independent Timing

DLR_EL0: Debug Link Register

DSPSR_EL0: Debug Saved Program Status Register

ELR_EL1: Exception Link Register (EL1)

ELR_EL2: Exception Link Register (EL2)

ELR_EL3: Exception Link Register (EL3)

ERRIDR_EL1: Error Record ID Register

ERRSELR_EL1: Error Record Select Register

ERXADDR_EL1: Selected Error Record Address Register

ERXCTLR_EL1: Selected Error Record Control Register

ERXFR_EL1: Selected Error Record Feature Register

ERXMISC0_EL1: Selected Error Record Miscellaneous Register 0

ERXMISC1_EL1: Selected Error Record Miscellaneous Register 1

ERXMISC2_EL1: Selected Error Record Miscellaneous Register 2

ERXMISC3_EL1: Selected Error Record Miscellaneous Register 3

ERXPFGCDN_EL1: Selected Pseudo-fault Generation Countdown register

ERXPFGCTL_EL1: Selected Pseudo-fault Generation Control register

ERXPFGF_EL1: Selected Pseudo-fault Generation Feature register

ERXSTATUS_EL1: Selected Error Record Primary Status Register

ESR_EL1: Exception Syndrome Register (EL1)

ESR_EL2: Exception Syndrome Register (EL2)

ESR_EL3: Exception Syndrome Register (EL3)

FAR_EL1: Fault Address Register (EL1)

FAR_EL2: Fault Address Register (EL2)

FAR_EL3: Fault Address Register (EL3)

FPCR: Floating-point Control Register

FPEXC32_EL2: Floating-Point Exception Control register

FPSR: Floating-point Status Register

GCR_EL1: Tag Control Register.

GMID_EL1: Multiple tag transfer ID register

HACR_EL2: Hypervisor Auxiliary Control Register

HAFGRTR_EL2: Hypervisor Activity Monitors Fine-Grained Read Trap Register

HCR_EL2: Hypervisor Configuration Register

HDFGRTR_EL2: Hypervisor Debug Fine-Grained Read Trap Register

HDFGWTR_EL2: Hypervisor Debug Fine-Grained Write Trap Register

HFGITR_EL2: Hypervisor Fine-Grained Instruction Trap Register

HFGRTR_EL2: Hypervisor Fine-Grained Read Trap Register

HFGWTR_EL2: Hypervisor Fine-Grained Write Trap Register

HPFAR_EL2: Hypervisor IPA Fault Address Register

HSTR_EL2: Hypervisor System Trap Register

ICC_AP0R<n>_EL1: Interrupt Controller Active Priorities Group 0 Registers

ICC_AP1R<n>_EL1: Interrupt Controller Active Priorities Group 1 Registers

ICC_ASGI1R_EL1: Interrupt Controller Alias Software Generated Interrupt Group 1 Register

ICC_BPR0_EL1: Interrupt Controller Binary Point Register 0

ICC_BPR1_EL1: Interrupt Controller Binary Point Register 1

ICC_CTLR_EL1: Interrupt Controller Control Register (EL1)

ICC_CTLR_EL3: Interrupt Controller Control Register (EL3)

ICC_DIR_EL1: Interrupt Controller Deactivate Interrupt Register

ICC_EOIR0_EL1: Interrupt Controller End Of Interrupt Register 0

ICC_EOIR1_EL1: Interrupt Controller End Of Interrupt Register 1

ICC_HPPIR0_EL1: Interrupt Controller Highest Priority Pending Interrupt Register 0

ICC_HPPIR1_EL1: Interrupt Controller Highest Priority Pending Interrupt Register 1

ICC_IAR0_EL1: Interrupt Controller Interrupt Acknowledge Register 0

ICC_IAR1_EL1: Interrupt Controller Interrupt Acknowledge Register 1

ICC_IGRPEN0_EL1: Interrupt Controller Interrupt Group 0 Enable register

ICC_IGRPEN1_EL1: Interrupt Controller Interrupt Group 1 Enable register

ICC_IGRPEN1_EL3: Interrupt Controller Interrupt Group 1 Enable register (EL3)

ICC_PMR_EL1: Interrupt Controller Interrupt Priority Mask Register

ICC_RPR_EL1: Interrupt Controller Running Priority Register

ICC_SGI0R_EL1: Interrupt Controller Software Generated Interrupt Group 0 Register

ICC_SGI1R_EL1: Interrupt Controller Software Generated Interrupt Group 1 Register

ICC_SRE_EL1: Interrupt Controller System Register Enable register (EL1)

ICC_SRE_EL2: Interrupt Controller System Register Enable register (EL2)

ICC_SRE_EL3: Interrupt Controller System Register Enable register (EL3)

ICH_AP0R<n>_EL2: Interrupt Controller Hyp Active Priorities Group 0 Registers

ICH_AP1R<n>_EL2: Interrupt Controller Hyp Active Priorities Group 1 Registers

ICH_EISR_EL2: Interrupt Controller End of Interrupt Status Register

ICH_ELRSR_EL2: Interrupt Controller Empty List Register Status Register

ICH_HCR_EL2: Interrupt Controller Hyp Control Register

ICH_LR<n>_EL2: Interrupt Controller List Registers

ICH_MISR_EL2: Interrupt Controller Maintenance Interrupt State Register

ICH_VMCR_EL2: Interrupt Controller Virtual Machine Control Register

ICH_VTR_EL2: Interrupt Controller VGIC Type Register

ICV_AP0R<n>_EL1: Interrupt Controller Virtual Active Priorities Group 0 Registers

ICV_AP1R<n>_EL1: Interrupt Controller Virtual Active Priorities Group 1 Registers

ICV_BPR0_EL1: Interrupt Controller Virtual Binary Point Register 0

ICV_BPR1_EL1: Interrupt Controller Virtual Binary Point Register 1

ICV_CTLR_EL1: Interrupt Controller Virtual Control Register

ICV_DIR_EL1: Interrupt Controller Deactivate Virtual Interrupt Register

ICV_EOIR0_EL1: Interrupt Controller Virtual End Of Interrupt Register 0

ICV_EOIR1_EL1: Interrupt Controller Virtual End Of Interrupt Register 1

ICV_HPPIR0_EL1: Interrupt Controller Virtual Highest Priority Pending Interrupt Register 0

ICV_HPPIR1_EL1: Interrupt Controller Virtual Highest Priority Pending Interrupt Register 1

ICV_IAR0_EL1: Interrupt Controller Virtual Interrupt Acknowledge Register 0

ICV_IAR1_EL1: Interrupt Controller Virtual Interrupt Acknowledge Register 1

ICV_IGRPEN0_EL1: Interrupt Controller Virtual Interrupt Group 0 Enable register

ICV_IGRPEN1_EL1: Interrupt Controller Virtual Interrupt Group 1 Enable register

ICV_PMR_EL1: Interrupt Controller Virtual Interrupt Priority Mask Register

ICV_RPR_EL1: Interrupt Controller Virtual Running Priority Register

ID_AA64AFR0_EL1: AArch64 Auxiliary Feature Register 0

ID_AA64AFR1_EL1: AArch64 Auxiliary Feature Register 1

ID_AA64DFR0_EL1: AArch64 Debug Feature Register 0

ID_AA64DFR1_EL1: AArch64 Debug Feature Register 1

ID_AA64ISAR0_EL1: AArch64 Instruction Set Attribute Register 0

ID_AA64ISAR1_EL1: AArch64 Instruction Set Attribute Register 1

ID_AA64MMFR0_EL1: AArch64 Memory Model Feature Register 0

ID_AA64MMFR1_EL1: AArch64 Memory Model Feature Register 1

ID_AA64MMFR2_EL1: AArch64 Memory Model Feature Register 2

ID_AA64PFR0_EL1: AArch64 Processor Feature Register 0

ID_AA64PFR1_EL1: AArch64 Processor Feature Register 1

ID_AA64ZFR0_EL1: SVE Feature ID register 0

ID_AFR0_EL1: AArch32 Auxiliary Feature Register 0

ID_DFR0_EL1: AArch32 Debug Feature Register 0

ID_DFR1_EL1: Debug Feature Register 1

ID_ISAR0_EL1: AArch32 Instruction Set Attribute Register 0

ID_ISAR1_EL1: AArch32 Instruction Set Attribute Register 1

ID_ISAR2_EL1: AArch32 Instruction Set Attribute Register 2

ID_ISAR3_EL1: AArch32 Instruction Set Attribute Register 3

ID_ISAR4_EL1: AArch32 Instruction Set Attribute Register 4

ID_ISAR5_EL1: AArch32 Instruction Set Attribute Register 5

ID_ISAR6_EL1: AArch32 Instruction Set Attribute Register 6

ID_MMFR0_EL1: AArch32 Memory Model Feature Register 0

ID_MMFR1_EL1: AArch32 Memory Model Feature Register 1

ID_MMFR2_EL1: AArch32 Memory Model Feature Register 2

ID_MMFR3_EL1: AArch32 Memory Model Feature Register 3

ID_MMFR4_EL1: AArch32 Memory Model Feature Register 4

ID_MMFR5_EL1: AArch32 Memory Model Feature Register 5

ID_PFR0_EL1: AArch32 Processor Feature Register 0

ID_PFR1_EL1: AArch32 Processor Feature Register 1

ID_PFR2_EL1: AArch32 Processor Feature Register 2

IFSR32_EL2: Instruction Fault Status Register (EL2)

ISR_EL1: Interrupt Status Register

LORC_EL1: LORegion Control (EL1)

LOREA_EL1: LORegion End Address (EL1)

LORID_EL1: LORegionID (EL1)

LORN_EL1: LORegion Number (EL1)

LORSA_EL1: LORegion Start Address (EL1)

MAIR_EL1: Memory Attribute Indirection Register (EL1)

MAIR_EL2: Memory Attribute Indirection Register (EL2)

MAIR_EL3: Memory Attribute Indirection Register (EL3)

MDCCINT_EL1: Monitor DCC Interrupt Enable Register

MDCCSR_EL0: Monitor DCC Status Register

MDCR_EL2: Monitor Debug Configuration Register (EL2)

MDCR_EL3: Monitor Debug Configuration Register (EL3)

MDRAR_EL1: Monitor Debug ROM Address Register

MDSCR_EL1: Monitor Debug System Control Register

MIDR_EL1: Main ID Register

MPAM0_EL1: MPAM0 Register (EL1)

MPAM1_EL1: MPAM1 Register (EL1)

MPAM2_EL2: MPAM2 Register (EL2)

MPAM3_EL3: MPAM3 Register (EL3)

MPAMHCR_EL2: MPAM Hypervisor Control Register (EL2)

MPAMIDR_EL1: MPAM ID Register (EL1)

MPAMVPM0_EL2: MPAM Virtual PARTID Mapping Register 0

MPAMVPM1_EL2: MPAM Virtual PARTID Mapping Register 1

MPAMVPM2_EL2: MPAM Virtual PARTID Mapping Register 2

MPAMVPM3_EL2: MPAM Virtual PARTID Mapping Register 3

MPAMVPM4_EL2: MPAM Virtual PARTID Mapping Register 4

MPAMVPM5_EL2: MPAM Virtual PARTID Mapping Register 5

MPAMVPM6_EL2: MPAM Virtual PARTID Mapping Register 6

MPAMVPM7_EL2: MPAM Virtual PARTID Mapping Register 7

MPAMVPMV_EL2: MPAM Virtual Partition Mapping Valid Register

MPIDR_EL1: Multiprocessor Affinity Register

MVFR0_EL1: AArch32 Media and VFP Feature Register 0

MVFR1_EL1: AArch32 Media and VFP Feature Register 1

MVFR2_EL1: AArch32 Media and VFP Feature Register 2

NZCV: Condition Flags

OSDLR_EL1: OS Double Lock Register

OSDTRRX_EL1: OS Lock Data Transfer Register, Receive

OSDTRTX_EL1: OS Lock Data Transfer Register, Transmit

OSECCR_EL1: OS Lock Exception Catch Control Register

OSLAR_EL1: OS Lock Access Register

OSLSR_EL1: OS Lock Status Register

PAN: Privileged Access Never

PAR_EL1: Physical Address Register

PMBIDR_EL1: Profiling Buffer ID Register

PMBLIMITR_EL1: Profiling Buffer Limit Address Register

PMBPTR_EL1: Profiling Buffer Write Pointer Register

PMBSR_EL1: Profiling Buffer Status/syndrome Register

PMCCFILTR_EL0: Performance Monitors Cycle Count Filter Register

PMCCNTR_EL0: Performance Monitors Cycle Count Register

PMCEID0_EL0: Performance Monitors Common Event Identification register 0

PMCEID1_EL0: Performance Monitors Common Event Identification register 1

PMCNTENCLR_EL0: Performance Monitors Count Enable Clear register

PMCNTENSET_EL0: Performance Monitors Count Enable Set register

PMCR_EL0: Performance Monitors Control Register

PMEVCNTR<n>_EL0: Performance Monitors Event Count Registers

PMEVTYPER<n>_EL0: Performance Monitors Event Type Registers

PMINTENCLR_EL1: Performance Monitors Interrupt Enable Clear register

PMINTENSET_EL1: Performance Monitors Interrupt Enable Set register

PMMIR_EL1: Performance Monitors Machine Identification Register

PMOVSCLR_EL0: Performance Monitors Overflow Flag Status Clear Register

PMOVSSET_EL0: Performance Monitors Overflow Flag Status Set register

PMSCR_EL1: Statistical Profiling Control Register (EL1)

PMSCR_EL2: Statistical Profiling Control Register (EL2)

PMSELR_EL0: Performance Monitors Event Counter Selection Register

PMSEVFR_EL1: Sampling Event Filter Register

PMSFCR_EL1: Sampling Filter Control Register

PMSICR_EL1: Sampling Interval Counter Register

PMSIDR_EL1: Sampling Profiling ID Register

PMSIRR_EL1: Sampling Interval Reload Register

PMSLATFR_EL1: Sampling Latency Filter Register

PMSWINC_EL0: Performance Monitors Software Increment register

PMUSERENR_EL0: Performance Monitors User Enable Register

PMXEVCNTR_EL0: Performance Monitors Selected Event Count Register

PMXEVTYPER_EL0: Performance Monitors Selected Event Type Register

REVIDR_EL1: Revision ID Register

RGSR_EL1: Random Allocation Tag Seed Register.

RMR_EL1: Reset Management Register (EL1)

RMR_EL2: Reset Management Register (EL2)

RMR_EL3: Reset Management Register (EL3)

RNDR: Random Number

RNDRRS: Reseeded Random Number

RVBAR_EL1: Reset Vector Base Address Register (if EL2 and EL3 not implemented)

RVBAR_EL2: Reset Vector Base Address Register (if EL3 not implemented)

RVBAR_EL3: Reset Vector Base Address Register (if EL3 implemented)

S3_<op1>_<Cn>_<Cm>_<op2>: IMPLEMENTATION DEFINED registers

SCR_EL3: Secure Configuration Register

SCTLR_EL1: System Control Register (EL1)

SCTLR_EL2: System Control Register (EL2)

SCTLR_EL3: System Control Register (EL3)

SCXTNUM_EL0: EL0 Read/Write Software Context Number

SCXTNUM_EL1: EL1 Read/Write Software Context Number

SCXTNUM_EL2: EL2 Read/Write Software Context Number

SCXTNUM_EL3: EL3 Read/Write Software Context Number

SDER32_EL2: AArch32 Secure Debug Enable Register

SDER32_EL3: AArch32 Secure Debug Enable Register

SPSel: Stack Pointer Select

SPSR_abt: Saved Program Status Register (Abort mode)

SPSR_EL1: Saved Program Status Register (EL1)

SPSR_EL2: Saved Program Status Register (EL2)

SPSR_EL3: Saved Program Status Register (EL3)

~~SPSR_abt: Saved Program Status Register (Abort mode)~~

SPSR_fiq: Saved Program Status Register (FIQ mode)

SPSR_irq: Saved Program Status Register (IRQ mode)

SPSR_und: Saved Program Status Register (Undefined mode)

SPSel: Stack Pointer Select

SP_EL0: Stack Pointer (EL0)

SP_EL1: Stack Pointer (EL1)

SP_EL2: Stack Pointer (EL2)

SP_EL3: Stack Pointer (EL3)

SSBS: Speculative Store Bypass Safe

TCO: Tag Check Override

TCR_EL1: Translation Control Register (EL1)

TCR_EL2: Translation Control Register (EL2)

TCR_EL3: Translation Control Register (EL3)

TFSRE0_EL1: Tag FaultFail Status Register (EL0).

TFSR_EL1: Tag FaultFail Status Register (EL1)

TFSR_EL2: Tag FaultFail Status Register (EL2)

TFSR_EL3: Tag FaultFail Status Register (EL3)

TPIDRRO_EL0: EL0 Read-Only Software Thread ID Register

TPIDR_EL0: EL0 Read/Write Software Thread ID Register

TPIDR_EL1: EL1 Software Thread ID Register

TPIDR_EL2: EL2 Software Thread ID Register

TPIDR_EL3: EL3 Software Thread ID Register

TRFCR_EL1: Trace Filter Control Register (EL1)

TRFCR_EL2: Trace Filter Control Register (EL2)

TTBR0_EL1: Translation Table Base Register 0 (EL1)

TTBR0_EL2: Translation Table Base Register 0 (EL2)

TTBR0_EL3: Translation Table Base Register 0 (EL3)

TTBR1_EL1: Translation Table Base Register 1 (EL1)

TTBR1_EL2: Translation Table Base Register 1 (EL2)

UAO: User Access Override

VBAR_EL1: Vector Base Address Register (EL1)

VBAR_EL2: Vector Base Address Register (EL2)

VBAR_EL3: Vector Base Address Register (EL3)

VDISR_EL2: Virtual Deferred Interrupt Status Register

VMPIDR_EL2: Virtualization Multiprocessor ID Register

VNCR_EL2: Virtual Nested Control Register

VPIDR_EL2: Virtualization Processor ID Register

VSESR_EL2: Virtual SError Exception Syndrome Register

VSTCR_EL2: Virtualization Secure Translation Control Register

VSTTBR_EL2: Virtualization Secure Translation Table Base Register

VTCR_EL2: Virtualization Translation Control Register

VTTBR_EL2: Virtualization Translation Table Base Register

ZCR_EL1: SVE Control Register for EL1

ZCR_EL2: SVE Control Register for EL2

ZCR_EL3: SVE Control Register for EL3

Copyright Â© 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AArch64 System Instructions

AT S12E0R: Address Translate Stages 1 and 2 EL0 Read

AT S12E0W: Address Translate Stages 1 and 2 EL0 Write

AT S12E1R: Address Translate Stages 1 and 2 EL1 Read

AT S12E1W: Address Translate Stages 1 and 2 EL1 Write

AT S1E0R: Address Translate Stage 1 EL0 Read

AT S1E0W: Address Translate Stage 1 EL0 Write

AT S1E1R: Address Translate Stage 1 EL1 Read

AT S1E1RP: Address Translate Stage 1 EL1 Read PAN

AT S1E1W: Address Translate Stage 1 EL1 Write

AT S1E1WP: Address Translate Stage 1 EL1 Write PAN

AT S1E2R: Address Translate Stage 1 EL2 Read

AT S1E2W: Address Translate Stage 1 EL2 Write

AT S1E3R: Address Translate Stage 1 EL3 Read

AT S1E3W: Address Translate Stage 1 EL3 Write

CFP RCTX: Control Flow Prediction Restriction by Context

CPP RCTX: Cache Prefetch Prediction Restriction by Context

DC CGDSW: Data, Allocation Tag or unified Cache line Clean of Data and Allocation Tags by Set/Way

DC CGDVAC: Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoC

DC CGDVADP: Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoDP

DC CGDVAP: Data, Allocation Tag or unified Cache line Clean of Data and Allocation Tags by VA to PoP

DC CGSW: Data, Allocation Tag or unified Cache line Clean of Allocation Tags by Set/Way

DC CGVAC: Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoC

DC CGVADP: Data, Allocation Tag or unified Cache line Clean of Data and Allocation Tags by VA to PoDP

DC CGVAP: Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoP

DC CIGDSW: Data, Allocation Tag or unified Cache line Clean and Invalidate of Data and Allocation Tags by Set/Way

DC CIGDVAC: Data, Allocation Tag or unified Cache line Clean and Invalidate of Data and Allocation Tags by VA to PoC

DC CIGSW: Data, Allocation Tag or unified Cache line Clean and Invalidate of Allocation Tags by Set/Way

DC CIGVAC: Data, Allocation Tag or unified Cache line Clean and Invalidate of Allocation Tags by VA to PoC

DC CISW: Data or unified Cache line Clean and Invalidate by Set/Way

DC CIVAC: Data or unified Cache line Clean and Invalidate by VA to PoC

DC CSW: Data or unified Cache line Clean by Set/Way

DC CVAC: Data or unified Cache line Clean by VA to PoC

DC CVADP: Data or unified Cache line Clean by VA to PoDP

DC CVAP: Data or unified Cache line Clean by VA to PoP

DC CVAU: Data or unified Cache line Clean by VA to PoU

DC GVA: Data Cache set Allocation Tag by VA

DC GZVA: Data Cache set Allocation Tags and Zero by VA

DC IGDSW: Data, Allocation Tag or unified Cache line Invalidate of Data and Allocation Tags by Set/Way

DC IGDVAC: Data, Allocation Tag or unified Cache line Invalidate of Allocation Tags by VA to PoC

DC IGSW: Data, Allocation Tag or unified Cache line Invalidate of Allocation Tags by Set/Way

DC IGVAC: Data, Allocation Tag or unified Cache line Invalidate of Allocation Tags by VA to PoC

DC ISW: Data or unified Cache line Invalidate by Set/Way

DC IVAC: Data or unified Cache line Invalidate by VA to PoC

DC ZVA: Data Cache Zero by VA

DVP RCTX: Data Value Prediction Restriction by Context

IC IALLU: Instruction Cache Invalidate All to PoU

IC IALLUIS: Instruction Cache Invalidate All to PoU, Inner Shareable

IC IVAU: Instruction Cache line Invalidate by VA to PoU

S1_<op1>_<Cn>_<Cm>_<op2>: IMPLEMENTATION DEFINED maintenance instructions

TLBI ALLE1: TLB Invalidate All, EL1

TLBI ALLE1IS: TLB Invalidate All, EL1, Inner Shareable

TLBI ALLE1OS: TLB Invalidate All, EL1, Outer Shareable

TLBI ALLE2: TLB Invalidate All, EL2

TLBI ALLE2IS: TLB Invalidate All, EL2, Inner Shareable

TLBI ALLE2OS: TLB Invalidate All, EL2, Outer Shareable

TLBI ALLE3: TLB Invalidate All, EL3

TLBI ALLE3IS: TLB Invalidate All, EL3, Inner Shareable

TLBI ALLE3OS: TLB Invalidate All, EL3, Outer Shareable

TLBI ASIDE1: TLB Invalidate by ASID, EL1

TLBI ASIDE1IS: TLB Invalidate by ASID, EL1, Inner Shareable

TLBI ASIDE1OS: TLB Invalidate by ASID, EL1, Outer Shareable

TLBI IPAS2E1: TLB Invalidate by Intermediate Physical Address, Stage 2, EL1

TLBI IPAS2E1IS: TLB Invalidate by Intermediate Physical Address, Stage 2, EL1, Inner Shareable

TLBI IPAS2E1OS: TLB Invalidate by Intermediate Physical Address, Stage 2, EL1, Outer Shareable

TLBI IPAS2LE1: TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1

TLBI IPAS2LE1IS: TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Inner Shareable

TLBI IPAS2LE1OS: TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Outer Shareable

TLBI RIPAS2E1: TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1

TLBI RIPAS2E1IS: TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1, Inner Shareable

TLBI RIPAS2E1OS: TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1, Outer Shareable

TLBI RIPAS2LE1: TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1

TLBI RIPAS2LE1IS: TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Inner Shareable

TLBI RIPAS2LE1OS: TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Outer Shareable

TLBI RVAAE1: TLB Range Invalidate by VA, All ASID, EL1

TLBI RVAAE1IS: TLB Range Invalidate by VA, All ASID, EL1, Inner Shareable

TLBI RVAAE1OS: TLB Range Invalidate by VA, All ASID, EL1, Outer Shareable

TLBI RVAALE1: TLB Range Invalidate by VA, All ASID, Last level, EL1

TLBI RVAALE1IS: TLB Range Invalidate by VA, All ASID, Last Level, EL1, Inner Shareable

TLBI RVAALE1OS: TLB Range Invalidate by VA, All ASID, Last Level, EL1, Outer Shareable

TLBI RVAE1: TLB Range Invalidate by VA, EL1

TLBI RVAE1IS: TLB Range Invalidate by VA, EL1, Inner Shareable

TLBI RVAE1OS: TLB Range Invalidate by VA, EL1, Outer Shareable

TLBI RVAE2: TLB Range Invalidate by VA, EL2

TLBI RVAE2IS: TLB Range Invalidate by VA, EL2, Inner Shareable

TLBI RVAE2OS: TLB Range Invalidate by VA, EL2, Outer Shareable

TLBI RVAE3: TLB Range Invalidate by VA, EL3

TLBI RVAE3IS: TLB Range Invalidate by VA, EL3, Inner Shareable

TLBI RVAE3OS: TLB Range Invalidate by VA, EL3, Outer Shareable

TLBI RVALE1: TLB Range Invalidate by VA, Last level, EL1

TLBI RVALE1IS: TLB Range Invalidate by VA, Last level, EL1, Inner Shareable

TLBI RVALE1OS: TLB Range Invalidate by VA, Last level, EL1, Outer Shareable

TLBI RVALE2: TLB Range Invalidate by VA, Last level, EL2

TLBI RVALE2IS: TLB Range Invalidate by VA, Last level, EL2, Inner Shareable

TLBI RVALE2OS: TLB Range Invalidate by VA, Last level, EL2, Outer Shareable

TLBI RVALE3: TLB Range Invalidate by VA, Last level, EL3

TLBI RVALE3IS: TLB Range Invalidate by VA, Last level, EL3, Inner Shareable

TLBI RVALE3OS: TLB Range Invalidate by VA, Last level, EL3, Outer Shareable

TLBI VAAE1: TLB Invalidate by VA, All ASID, EL1

TLBI VAAE1IS: TLB Invalidate by VA, All ASID, EL1, Inner Shareable

TLBI VAAE1OS: TLB Invalidate by VA, All ASID, EL1, Outer Shareable

TLBI VAALE1: TLB Invalidate by VA, All ASID, Last level, EL1

TLBI VAALE1IS: TLB Invalidate by VA, All ASID, Last Level, EL1, Inner Shareable

TLBI VAALE1OS: TLB Invalidate by VA, All ASID, Last Level, EL1, Outer Shareable

TLBI VAE1: TLB Invalidate by VA, EL1

TLBI VAE1IS: TLB Invalidate by VA, EL1, Inner Shareable

TLBI VAE1OS: TLB Invalidate by VA, EL1, Outer Shareable

TLBI VAE2: TLB Invalidate by VA, EL2

TLBI VAE2IS: TLB Invalidate by VA, EL2, Inner Shareable

TLBI VAE2OS: TLB Invalidate by VA, EL2, Outer Shareable

TLBI VAE3: TLB Invalidate by VA, EL3

TLBI VAE3IS: TLB Invalidate by VA, EL3, Inner Shareable

TLBI VAE3OS: TLB Invalidate by VA, EL3, Outer Shareable

TLBI VALE1: TLB Invalidate by VA, Last level, EL1

TLBI VALE1IS: TLB Invalidate by VA, Last level, EL1, Inner Shareable

TLBI VALE1OS: TLB Invalidate by VA, Last level, EL1, Outer Shareable

TLBI VALE2: TLB Invalidate by VA, Last level, EL2

TLBI VALE2IS: TLB Invalidate by VA, Last level, EL2, Inner Shareable

TLBI VALE2OS: TLB Invalidate by VA, Last level, EL2, Outer Shareable

TLBI VALE3: TLB Invalidate by VA, Last level, EL3

TLBI VALE3IS: TLB Invalidate by VA, Last level, EL3, Inner Shareable

TLBI VALE3OS: TLB Invalidate by VA, Last level, EL3, Outer Shareable

TLBI VMALLE1: TLB Invalidate by VMID, All at stage 1, EL1

TLBI VMALLE1IS: TLB Invalidate by VMID, All at stage 1, EL1, Inner Shareable

TLBI VMALLE1OS: TLB Invalidate by VMID, All at stage 1, EL1, Outer Shareable

TLBI VMALLS12E1: TLB Invalidate by VMID, All at Stage 1 and 2, EL1

TLBI VMALLS12E1IS: TLB Invalidate by VMID, All at Stage 1 and 2, EL1, Inner Shareable

TLBI VMALLS12E1OS: TLB Invalidate by VMID, All at Stage 1 and 2, EL1, Outer Shareable

1327/1209/2019 1518:1349

Copyright Â© 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ACTLR_EL3, Auxiliary Control Register (EL3)

The ACTLR_EL3 characteristics are:

Purpose

Provides IMPLEMENTATION DEFINED configuration and control options for EL3.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to ACTLR_EL3 are UNDEFINED.

Attributes

ACTLR_EL3 is a 64-bit register.

Field descriptions

The ACTLR_EL3 bit assignments are:



IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the ACTLR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, ACTLR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return ACTLR_EL3;
```

```
MSR ACTLR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    ACTLR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AFSR0_EL1, Auxiliary Fault Status Register 0 (EL1)

The AFSR0_EL1 characteristics are:

Purpose

Provides additional IMPLEMENTATION DEFINED fault status information for exceptions taken to EL1.

Configuration

AArch64 System register AFSR0_EL1 bits [31:0] are architecturally mapped to AArch32 System register ADFSR[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AFSR0_EL1 is a 64-bit register.

Field descriptions

The AFSR0_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
IMPLEMENTATION DEFINED																															
IMPLEMENTATION DEFINED																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the AFSR0_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic AFSR0_EL1 or AFSR0_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, AFSR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.AFSR0_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x128];
    else
        return AFSR0_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return AFSR0_EL2;
    else
        return AFSR0_EL1;
elsif PSTATE.EL == EL3 then
    return AFSR0_EL1;
```

MSR AFSR0_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.AFSR0_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x128] = X[t];
    else
        AFSR0_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        AFSR0_EL2 = X[t];
    else
        AFSR0_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    AFSR0_EL1 = X[t];
```

MRS <Xt>, AFSR0_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0101	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x128];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return AFSR0_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return AFSR0_EL1;
    else
        UNDEFINED;
```

```
MSR AFSR0_EL12, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b0101	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x128] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        AFSR0_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        AFSR0_EL1 = X[t];
    else
        UNDEFINED;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AFSR0_EL3, Auxiliary Fault Status Register 0 (EL3)

The AFSR0_EL3 characteristics are:

Purpose

Provides additional IMPLEMENTATION DEFINED fault status information for exceptions taken to EL3.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to AFSR0_EL3 are UNDEFINED.

Attributes

AFSR0_EL3 is a 64-bit register.

Field descriptions

The AFSR0_EL3 bit assignments are:



IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the AFSR0_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, AFSR0_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0101	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return AFSR0_EL3;
```

```
MSR AFSR0_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0101	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    AFSR0_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AFSR1_EL1, Auxiliary Fault Status Register 1 (EL1)

The AFSR1_EL1 characteristics are:

Purpose

Provides additional IMPLEMENTATION DEFINED fault status information for exceptions taken to EL1.

Configuration

AArch64 System register AFSR1_EL1 bits [31:0] are architecturally mapped to AArch32 System register AIFSR[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AFSR1_EL1 is a 64-bit register.

Field descriptions

The AFSR1_EL1 bit assignments are:



IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the AFSR1_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic AFSR1_EL1 or AFSR1_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, AFSR1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.AFSR1_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x130];
    else
        return AFSR1_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return AFSR1_EL2;
    else
        return AFSR1_EL1;
elsif PSTATE.EL == EL3 then
    return AFSR1_EL1;
```

MSR AFSR1_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.AFSR1_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x130] = X[t];
    else
        AFSR1_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        AFSR1_EL2 = X[t];
    else
        AFSR1_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    AFSR1_EL1 = X[t];
```

MRS <Xt>, AFSR1_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0101	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x130];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return AFSR1_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return AFSR1_EL1;
    else
        UNDEFINED;
```

```
MSR AFSR1_EL12, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b0101	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x130] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        AFSR1_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        AFSR1_EL1 = X[t];
    else
        UNDEFINED;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AFSR1_EL3, Auxiliary Fault Status Register 1 (EL3)

The AFSR1_EL3 characteristics are:

Purpose

Provides additional IMPLEMENTATION DEFINED fault status information for exceptions taken to EL3.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to AFSR1_EL3 are UNDEFINED.

Attributes

AFSR1_EL3 is a 64-bit register.

Field descriptions

The AFSR1_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
IMPLEMENTATION DEFINED																															
IMPLEMENTATION DEFINED																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the AFSR1_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, AFSR1_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0101	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return AFSR1_EL3;
```

```
MSR AFSR1_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0101	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    AFSR1_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMAIR_EL1, Auxiliary Memory Attribute Indirection Register (EL1)

The AMAIR_EL1 characteristics are:

Purpose

Provides IMPLEMENTATION DEFINED memory attributes for the memory regions specified by MAIR_EL1.

Configuration

AArch64 System register AMAIR_EL1 bits [31:0] are architecturally mapped to AArch32 System register AMAIR0[31:0] .

AArch64 System register AMAIR_EL1 bits [63:32] are architecturally mapped to AArch32 System register AMAIR1[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AMAIR_EL1 is a 64-bit register.

Field descriptions

The AMAIR_EL1 bit assignments are:



AMAIR_EL1 is permitted to be cached in a TLB.

IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the AMAIR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic AMAIR_EL1 or AMAIR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, AMAIR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1010	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.AMAIR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x148];
    else
        return AMAIR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return AMAIR_EL2;
    else
        return AMAIR_EL1;
elsif PSTATE.EL == EL3 then
    return AMAIR_EL1;
```

```
MSR AMAIR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1010	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.AMAIR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x148] = X[t];
    else
        AMAIR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        AMAIR_EL2 = X[t];
    else
        AMAIR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    AMAIR_EL1 = X[t];
```

```
MRS <Xt>, AMAIR_EL12
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b1010	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x148];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return AMAIR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return AMAIR_EL1;
    else
        UNDEFINED;
```

```
MSR AMAIR_EL12, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b1010	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x148] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        AMAIR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        AMAIR_EL1 = X[t];
    else
        UNDEFINED;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMAIR_EL3, Auxiliary Memory Attribute Indirection Register (EL3)

The AMAIR_EL3 characteristics are:

Purpose

Provides IMPLEMENTATION DEFINED memory attributes for the memory regions specified by MAIR_EL3.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to AMAIR_EL3 are UNDEFINED.

Attributes

AMAIR_EL3 is a 64-bit register.

Field descriptions

The AMAIR_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
IMPLEMENTATION DEFINED																															
IMPLEMENTATION DEFINED																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

AMAIR_EL3 is permitted to be cached in a TLB.

IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the AMAIR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, AMAIR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1010	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return AMAIR_EL3;
```

```
MSR AMAIR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1010	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    AMAIR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMCNTENCLR1_EL0, Activity Monitors Count Enable Clear Register 1

The AMCNTENCLR1_EL0 characteristics are:

Purpose

Disable control bits for the auxiliary activity monitors event counters, AMEVCNTR1<n>_EL0.

Configuration

AArch64 System register AMCNTENCLR1_EL0 bits [31:0] are architecturally mapped to AArch32 System register AMCNTENCLR1[31:0] .

AArch64 System register AMCNTENCLR1_EL0 bits [31:0] are architecturally mapped to External register AMCNTENCLR1[31:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMCNTENCLR1_EL0 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AMCNTENCLR1_EL0 is a 64-bit register.

Field descriptions

The AMCNTENCLR1_EL0 bit assignments are:



Bits [63:16]

Reserved, RES0.

P<n>, bit [n], for n = 0 to 15

Activity monitor event counter disable bit for AMEVCNTR1<n>_EL0.

Bits [31:16] are RES0. Bits [15:N] are RAZ/WI. N is the value in AMCGCR_EL0.CG1NC.

Possible values of each bit are:

P<n>	Meaning
0b0	When read, means that AMEVCNTR1<n>_EL0 is disabled. When written, has no effect.
0b1	When read, means that AMEVCNTR1<n>_EL0 is enabled. When written, disables AMEVCNTR1<n>_EL0.

On a Cold reset, this field resets to 0.

Accessing the AMCNTENCLR1_EL0

- ~~Accesses to the register are UNDEFINED.~~
- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If the number of auxiliary activity monitor event counters implemented is zero, reads and writes of AMCNTENCLR1_EL0 are UNDEFINED~~CONSTRAINED UNPREDICTABLE.~~~~, and the following behaviors are permitted:~~

Note

The number of auxiliary activity monitor event counters implemented is zero exactly when AMCFGR_EL0.NCG == 0b0000.

Accesses to this register use the following encodings:

MRS <Xt>, AMCNTENCLR1_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HAFGRTR_EL2.AMCNTEN1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMCNTENCLR1_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HAFGRTR_EL2.AMCNTEN1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMCNTENCLR1_EL0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMCNTENCLR1_EL0;
elsif PSTATE.EL == EL3 then
    return AMCNTENCLR1_EL0;
```

MSR AMCNTENCLR1_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b0011	0b000

```
if IsHighestEL(PSTATE.EL) then
    AMCNTENCLR1_EL0 = X[t];
else
    UNDEFINED;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMCNTENSET1_EL0, Activity Monitors Count Enable Set Register 1

The AMCNTENSET1_EL0 characteristics are:

Purpose

Enable control bits for the auxiliary activity monitors event counters, AMEVCNTR1<n>_EL0.

Configuration

AArch64 System register AMCNTENSET1_EL0 bits [31:0] are architecturally mapped to AArch32 System register AMCNTENSET1[31:0] .

AArch64 System register AMCNTENSET1_EL0 bits [31:0] are architecturally mapped to External register AMCNTENSET1[31:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMCNTENSET1_EL0 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AMCNTENSET1_EL0 is a 64-bit register.

Field descriptions

The AMCNTENSET1_EL0 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																P<n>, bit [n]															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:16]

Reserved, RES0.

P<n>, bit [n], for n = 0 to 15

Activity monitor event counter enable bit for AMEVCNTR1<n>_EL0.

Bits [31:16] are RES0. Bits [15:N] are RAZ/WI. N is the value in AMCGCR_EL0.CG1NC.

Possible values of each bit are:

P<n>	Meaning
0b0	When read, means that AMEVCNTR1<n>_EL0 is disabled. When written, has no effect.
0b1	When read, means that AMEVCNTR1<n>_EL0 is enabled. When written, enables AMEVCNTR1<n>_EL0.

On a Cold reset, this field resets to 0.

Accessing the AMCNTENSET1_EL0

- ~~Accesses to the register are UNDEFINED.~~
- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If the number of auxiliary activity monitor event counters implemented is zero, reads and writes of AMCNTENSET1_EL0 are UNDEFINED~~CONSTRAINED UNPREDICTABLE.~~, ~~and the following behaviors are permitted:~~

Note

The number of auxiliary activity monitor counters implemented is zero when AMCFGR_EL0.NCG == 0b0000.

Accesses to this register use the following encodings:

MRS <Xt>, AMCNTENSET1_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HAFGRTR_EL2.AMCNTEN1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMCNTENSET1_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HAFGRTR_EL2.AMCNTEN1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMCNTENSET1_EL0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMCNTENSET1_EL0;
elsif PSTATE.EL == EL3 then
    return AMCNTENSET1_EL0;
```

MSR AMCNTENSET1_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b0011	0b001

```
if IsHighestEL(PSTATE.EL) then
    AMCNTENSET1_EL0 = X[t];
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMEVCNTR0<n>_EL0, Activity Monitors Event Counter Registers 0, n = 0 - 15

The AMEVCNTR0<n>_EL0 characteristics are:

Purpose

Provides access to the architected activity monitor event counters.

Configuration

AArch64 System register AMEVCNTR0<n>_EL0 bits [63:0] are architecturally mapped to AArch32 System register AMEVCNTR0<n>[63:0] .

AArch64 System register AMEVCNTR0<n>_EL0 bits [63:0] are architecturally mapped to External register AMEVCNTR0<n>[63:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMEVCNTR0<n>_EL0 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AMEVCNTR0<n>_EL0 is a 64-bit register.

Field descriptions

The AMEVCNTR0<n>_EL0 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ACNT																															
ACNT																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

ACNT, bits [63:0]

Architected activity monitor event counter n.

Value of architected activity monitor event counter n, where n is the number of this register and is a number from 0 to 15.

If ARMv8.6-AMU is implemented, HCR_EL2.AMVOFFEN is 1, SCR_EL3.AMVOFFEN is 1~~0~~, HCR_EL2.{E2H, TGE} is not {1,1}, and EL2 is implemented in the current Security state, access to these registers at EL0 or EL1 return (PCount<63:0> - AMEVCNTVOFF0<n>_EL2<63:0>).

PCount is the physical count returned when AMEVCNTR0<n>_EL0 is read from EL2 or EL3.

If the counter is enabled, writes to this register have UNPREDICTABLE results.

On a Cold reset, this field resets to `0`.

Accessing the AMEVCNTR0<n>_EL0

- ~~Accesses to the register are UNDEFINED.~~

- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If <n> is greater than or equal to the number of architected activity monitor event counters, reads and writes of AMEVCNTR0<n>_EL0 are UNDEFINED~~CONSTRAINED UNPREDICTABLE.~~, ~~and the following behaviors are permitted:~~

Note

AMCGCR_EL0.CG0NC identifies the number of architected activity monitor event counters.

Accesses to this register use the following encodings:

MRS <Xt>, AMEVCNTR0<n>_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b010:n[3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HAFGRTR_EL2.AMEVCNTR0<n>_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMEVCNTR0_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HAFGRTR_EL2.AMEVCNTR0<n>_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMEVCNTR0_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMEVCNTR0_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL3 then
    return AMEVCNTR0_EL0[UInt(CRm<0>:op2<2:0>)];
```

MSR AMEVCNTR0<n>_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b010:n[3]	n[2:0]

```
if IsHighestEL(PSTATE.EL) then
    AMEVCNTR0_EL0[UInt(CRm<0>:op2<2:0>)] = X[t];
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMEVCNTR1<n>_EL0, Activity Monitors Event Counter Registers 1, n = 0 - 15

The AMEVCNTR1<n>_EL0 characteristics are:

Purpose

Provides access to the auxiliary activity monitor event counters.

Configuration

AArch64 System register AMEVCNTR1<n>_EL0 bits [63:0] are architecturally mapped to AArch32 System register AMEVCNTR1<n>[63:0] .

AArch64 System register AMEVCNTR1<n>_EL0 bits [63:0] are architecturally mapped to External register AMEVCNTR1<n>[63:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMEVCNTR1<n>_EL0 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AMEVCNTR1<n>_EL0 is a 64-bit register.

Field descriptions

The AMEVCNTR1<n>_EL0 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ACNT																															
ACNT																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

ACNT, bits [63:0]

Auxiliary activity monitor event counter n.

Value of auxiliary activity monitor event counter n, where n is the number of this register and is a number from 0 to 15.

If ARMv8.6-AMU is implemented, HCR_EL2.AMVOFFEN is 1, SCR_EL3.AMVOFFEN is 1~~0~~, HCR_EL2.{E2H, TGE} is not {1,1}, EL2 is implemented in the current Security state, and AMCR_EL0.CG1RZ is 0, reads to these registers at EL0 or EL1 return (PCount<63:0> - AMEVCNTVOFF1<n>_EL2<63:0>).

PCount is the physical count returned when AMEVCNTR1<n>_EL0 is read from EL2 or EL3.

If the counter is enabled, writes to this register have UNPREDICTABLE results.

On a Cold reset, this field resets to `0`.

Accessing the AMEVCNTR1<n>_EL0

- ~~Accesses to the register are UNDEFINED.~~

- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If <n> is greater than or equal to the number of auxiliary activity monitor event counters, reads and writes of AMEVCNTR1<n>_EL0 are UNDEFINED~~CONSTRAINED UNPREDICTABLE., and the following behaviors are permitted:~~

Note

AMCGCR_EL0.CG1NC identifies the number of auxiliary activity monitor event counters.

Accesses to this register use the following encodings:

MRS <Xt>, AMEVCNTR1<n>_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b110:n[3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HAFGRTR_EL2.AMEVCNTR1<n>_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !HighestELUsingAArch32() && AMCR_EL0.CG1RZ == '1' then
        Zeros();
    else
        return AMEVCNTR1_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HAFGRTR_EL2.AMEVCNTR1<n>_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !IsHighestEL(PSTATE.EL) && !HighestELUsingAArch32() && AMCR_EL0.CG1RZ == '1' then
        Zeros();
    else
        return AMEVCNTR1_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !IsHighestEL(PSTATE.EL) && !HighestELUsingAArch32() && AMCR_EL0.CG1RZ == '1' then
        Zeros();
    else
        return AMEVCNTR1_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL3 then
    return AMEVCNTR1_EL0[UInt(CRm<0>:op2<2:0>)];
```

MSR AMEVCNTR1<n>_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b110:n[3]	n[2:0]

```
if IsHighestEL(PSTATE.EL) then
    AMEVCNTR1_EL0[UInt(CRm<0>:op2<2:0>)] = X[t];
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMEVTYPER0<n>_EL0, Activity Monitors Event Type Registers 0, n = 0 - 15

The AMEVTYPER0<n>_EL0 characteristics are:

Purpose

Provides information on the events that an architected activity monitor event counter AMEVCNTR0<n>_EL0 counts.

Configuration

AArch64 System register AMEVTYPER0<n>_EL0 bits [31:0] are architecturally mapped to AArch32 System register AMEVTYPER0<n>[31:0] .

AArch64 System register AMEVTYPER0<n>_EL0 bits [31:0] are architecturally mapped to External register AMEVTYPER0<n>[31:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMEVTYPER0<n>_EL0 are UNDEFINED.

Attributes

AMEVTYPER0<n>_EL0 is a 64-bit register.

Field descriptions

The AMEVTYPER0<n>_EL0 bit assignments are:



Bits [63:16]

Reserved, RES0.

evtCount, bits [15:0]

Event to count. The event number of the event that is counted by the architected activity monitor event counter AMEVCNTR0<n>_EL0. The value of this field is architecturally mandated for each architected counter.

The following table shows the mapping between required event numbers and the corresponding counters:

evtCount	Meaning	Applies when
0x0011	Processor frequency cycles	When n == 0
0x4004	Constant frequency cycles	When n == 1
0x0008	Instructions retired	When n == 2
0x4005	Memory stall cycles	When n == 3

Accessing the AMEVTYPER0<n>_EL0

- ~~Accesses to the register are UNDEFINED.~~
- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If <n> is greater than or equal to the number of architected activity monitor event counters, reads and writes of AMEVTYPER0<n>_EL0 are UNDEFINED~~CONSTRAINED UNPREDICTABLE., and the following behaviors are permitted:~~

Note

AMCGCR_EL0.CG0NC identifies the number of architected activity monitor event counters.

Accesses to this register use the following encodings:

```
MRS <Xt>, AMEVTYPER0<n>_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b011:n[3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMEVTYPER0_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMEVTYPER0_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMEVTYPER0_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL3 then
    return AMEVTYPER0_EL0[UInt(CRm<0>:op2<2:0>)];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMEVTYPER1<n>_EL0, Activity Monitors Event Type Registers 1, n = 0 - 15

The AMEVTYPER1<n>_EL0 characteristics are:

Purpose

Provides information on the events that an auxiliary activity monitor event counter AMEVCNTR1<n>_EL0 counts.

Configuration

AArch64 System register AMEVTYPER1<n>_EL0 bits [31:0] are architecturally mapped to AArch32 System register AMEVTYPER1<n>[31:0] .

AArch64 System register AMEVTYPER1<n>_EL0 bits [31:0] are architecturally mapped to External register AMEVTYPER1<n>[31:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMEVTYPER1<n>_EL0 are UNDEFINED.

Attributes

AMEVTYPER1<n>_EL0 is a 64-bit register.

Field descriptions

The AMEVTYPER1<n>_EL0 bit assignments are:



Bits [63:16]

Reserved, RES0.

evtCount, bits [15:0]

Event to count. The event number of the event that is counted by the auxiliary activity monitor event counter AMEVCNTR1<n>_EL0.

It is IMPLEMENTATION DEFINED what values are supported by each counter.

If software writes a value to this field which is not supported by the corresponding counter AMEVCNTR1<n>_EL0, then:

- It is UNPREDICTABLE which event will be counted.
- The value read back is UNKNOWN.

The event counted by AMEVCNTR1<n>_EL0 might be fixed at implementation. In this case, the field is read-only and writes are UNDEFINED.

If the corresponding counter AMEVCNTR1<n>_EL0 is enabled, writes to this register have UNPREDICTABLE results.

Accessing the AMEVTYPER1<n>_EL0

- ~~Accesses to the register are UNDEFINED.~~
- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If <n> is greater than or equal to the number of auxiliary activity monitor event counters, reads and writes of AMEVTYPER1<n>_EL0 are UNDEFINED~~CONSTRAINED UNPREDICTABLE.~~, ~~and the following behaviors are permitted:~~

Note

AMCGCR_EL0.CG1NC identifies the number of auxiliary activity monitor event counters.

Accesses to this register use the following encodings:

MRS <Xt>, AMEVTYPER1<n>_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b111:n[3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HAFGRTR_EL2.AMEVTYPER1<n>_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMEVTYPER1_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HAFGRTR_EL2.AMEVTYPER1<n>_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMEVTYPER1_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMEVTYPER1_EL0[UInt(CRm<0>:op2<2:0>)];
elsif PSTATE.EL == EL3 then
    return AMEVTYPER1_EL0[UInt(CRm<0>:op2<2:0>)];
```

MSR AMEVTYPER1<n>_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b111:n[3]	n[2:0]

```
if IsHighestEL(PSTATE.EL) then
    AMEVTYPER1_EL0[UInt(CRm<0>:op2<2:0>)] = X[t];
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMUSERENR_EL0, Activity Monitors User Enable Register

The AMUSERENR_EL0 characteristics are:

Purpose

Global user enable register for the activity monitors. Enables or disables EL0 access to the activity monitors. AMUSERENR_EL0 is applicable to both the architected and the auxiliary counter groups.

Configuration

AArch64 System register AMUSERENR_EL0 bits [31:0] are architecturally mapped to AArch32 System register AMUSERENR[31:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMUSERENR_EL0 are UNDEFINED.

Attributes

AMUSERENR_EL0 is a 64-bit register.

Field descriptions

The AMUSERENR_EL0 bit assignments are:



Bits [63:1]

Reserved, RES0.

EN, bit [0]

Traps EL0 accesses to the activity monitors registers to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, as follows:

- In AArch64 state, accesses to the following registers are trapped, reported using EC syndrome value 0x18:
  - AMCFGR_EL0, AMCGCR_EL0, AMCNTENCLR0_EL0, AMCNTENCLR1_EL0, AMCNTENSET0_EL0, AMCNTENSET1_EL0, AMCR_EL0, AMEVCNTR0<n>_EL0, AMEVCNTR1<n>_EL0, AMEVTYPER0<n>_EL0, and AMEVTYPER1<n>_EL0.
- In AArch32 state, MRC and MCR accesses to the following registers are trapped and reported using EC syndrome value 0x03, MRRC and MCRR accesses are trapped and reported using EC syndrome value 0x04:
  - AMCFGR, AMCGCR, AMCNTENCLR0, AMCNTENCLR1, AMCNTENSET0, AMCNTENSET1, AMCR, AMEVCNTR0<n>, AMEVCNTR1<n>, AMEVTYPER0<n>, and AMEVTYPER1<n>.

EN	Meaning
0b0	EL0 accesses to the activity monitors registers are trapped.
0b1	This control does not cause any instructions to be trapped. Software can access all activity monitor registers at EL0.

Note

- AMUSERENR_EL0 can always be read at EL0 and is not governed by this bit.

Accessing the AMUSERENR_EL0

Accesses to this register use the following encodings:

```
MRS <Xt>, AMUSERENR_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b0010	0b011

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMUSERENR_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMUSERENR_EL0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return AMUSERENR_EL0;
elsif PSTATE.EL == EL3 then
    return AMUSERENR_EL0;
```

```
MSR AMUSERENR_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1101	0b0010	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        AMUSERENR_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        AMUSERENR_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    AMUSERENR_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S12E0R, Address Translate Stages 1 and 2 EL0 Read

The AT S12E0R characteristics are:

Purpose

Performs stage 1 and 2 address translations from EL0, with permissions as if reading from the given virtual address from EL0, using the following translation regime:

- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the EL2&0 translation regime.
- Otherwise, the EL1&0 translation regime.

Configuration

There are no configuration notes.

Attributes

AT S12E0R is a 64-bit System instruction.

Field descriptions

The AT S12E0R input value bit assignments are:



Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S12E0R instruction

Accesses to this instruction use the following encodings:

```
AT S12E0R, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b0111	0b1000	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.<E2H,TGE> == '11' || HCR_EL2.<DC,VM> == '00' then
        AT_S1E0R(X[t]);
    else
        AT_S12E0R(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        AT_S1E0R(X[t]);
    elsif EL2Enabled() && (HCR_EL2.<E2H,TGE> == '11' || HCR_EL2.<DC,VM> == '00') then
        AT_S1E0R(X[t]);
    else
        AT_S12E0R(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S12E0W, Address Translate Stages 1 and 2 EL0 Write

The AT S12E0W characteristics are:

Purpose

Performs stage 1 and 2 address translations from EL0, with permissions as if writing to the given virtual address from EL0, using the following translation regime:

- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the EL2&0 translation regime.
- Otherwise, the EL1&0 translation regime.

Configuration

There are no configuration notes.

Attributes

AT S12E0W is a 64-bit System instruction.

Field descriptions

The AT S12E0W input value bit assignments are:



Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S12E0W instruction

Accesses to this instruction use the following encodings:

```
AT S12E0W, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b0111	0b1000	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.<E2H,TGE> == '11' || HCR_EL2.<DC,VM> == '00' then
        AT_S1E0W(X[t]);
    else
        AT_S12E0W(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        AT_S1E0W(X[t]);
    elsif EL2Enabled() && (HCR_EL2.<E2H,TGE> == '11' || HCR_EL2.<DC,VM> == '00') then
        AT_S1E0W(X[t]);
    else
        AT_S12E0W(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S12E1R, Address Translate Stages 1 and 2 EL1 Read

The AT S12E1R characteristics are:

Purpose

Performs stage 1 and 2 address translation, with permissions as if reading from the given virtual address from EL1, or from EL2 if the Effective value of HCR_EL2.{E2H, TGE} is {1, 1}, using the following translation regime:

- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the EL1&0 translation regime, accessed from EL1.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the EL2&0 translation regime, accessed from EL2.
- Otherwise, the EL1&0 translation regime, accessed from EL1.

Configuration

There are no configuration notes.

Attributes

AT S12E1R is a 64-bit System instruction.

Field descriptions

The AT S12E1R input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Input address for translation																															
Input address for translation																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S12E1R instruction

Accesses to this instruction use the following encodings:

```
AT S12E1R, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b0111	0b1000	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.<E2H,TGE> == '11' || HCR_EL2.<DC,VM> == '00' then
        AT_S1E1R(X[t]);
    else
        AT_S12E1R(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        AT_S1E1R(X[t]);
    elsif EL2Enabled() && (HCR_EL2.<E2H,TGE> == '11' || HCR_EL2.<DC,VM> == '00') then
        AT_S1E1R(X[t]);
    else
        AT_S12E1R(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S12E1W, Address Translate Stages 1 and 2 EL1 Write

The AT S12E1W characteristics are:

Purpose

Performs stage 1 and 2 address translation, with permissions as if writing to the given virtual address from EL1, or from EL2 if the Effective value of HCR_EL2.{E2H, TGE} is {1, 1}, using the following translation regime:

- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the EL1&0 translation regime, accessed from EL1.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the EL2&0 translation regime, accessed from EL2.
- Otherwise, the EL1&0 translation regime, accessed from EL1.

Configuration

There are no configuration notes.

Attributes

AT S12E1W is a 64-bit System instruction.

Field descriptions

The AT S12E1W input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Input address for translation																															
Input address for translation																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S12E1W instruction

Accesses to this instruction use the following encodings:

```
AT S12E1W, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b0111	0b1000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.<E2H,TGE> == '11' || HCR_EL2.<DC,VM> == '00' then
        AT_S1E1W(X[t]);
    else
        AT_S12E1W(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        AT_S1E1W(X[t]);
    elsif EL2Enabled() && (HCR_EL2.<E2H,TGE> == '11' || HCR_EL2.<DC,VM> == '00') then
        AT_S1E1W(X[t]);
    else
        AT_S12E1W(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S1E0R, Address Translate Stage 1 EL0 Read

The AT S1E0R characteristics are:

Purpose

Performs stage 1 address translation from EL0, with permissions as if reading from the given virtual address from EL0, using the following translation regime:

- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the EL2&0 translation regime.
- Otherwise, the EL1&0 translation regime.

Configuration

There are no configuration notes.

Attributes

AT S1E0R is a 64-bit System instruction.

Field descriptions

The AT S1E0R input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Input address for translation																															
Input address for translation																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S1E0R instruction

Accesses to this instruction use the following encodings:

```
AT S1E0R, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b0111	0b1000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.AT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.ATS1E0R == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        AT_S1E0R(X[t]);
elsif PSTATE.EL == EL2 then
    AT_S1E0R(X[t]);
elsif PSTATE.EL == EL3 then
    AT_S1E0R(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S1E0W, Address Translate Stage 1 EL0 Write

The AT S1E0W characteristics are:

Purpose

Performs stage 1 address translation from EL0, with permissions as if writing to the given virtual address from EL0, using the following translation regime:

- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the EL2&0 translation regime.
- Otherwise, the EL1&0 translation regime.

Configuration

There are no configuration notes.

Attributes

AT S1E0W is a 64-bit System instruction.

Field descriptions

The AT S1E0W input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Input address for translation																															
Input address for translation																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S1E0W instruction

Accesses to this instruction use the following encodings:

```
AT S1E0W, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b0111	0b1000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.AT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.ATS1E0W == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        AT_S1E0W(X[t]);
elsif PSTATE.EL == EL2 then
    AT_S1E0W(X[t]);
elsif PSTATE.EL == EL3 then
    AT_S1E0W(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S1E1R, Address Translate Stage 1 EL1 Read

The AT S1E1R characteristics are:

Purpose

Performs stage 1 address translation, with permissions as if reading from the given virtual address from EL1, or from EL2 if the Effective value of HCR_EL2.{E2H, TGE} is {1, 1}, using the following translation regime:

- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the EL1&0 translation regime, accessed from EL1.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the EL2&0 translation regime, accessed from EL2.
- Otherwise, the EL1&0 translation regime, accessed from EL1.

Configuration

There are no configuration notes.

Attributes

AT S1E1R is a 64-bit System instruction.

Field descriptions

The AT S1E1R input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Input address for translation																															
Input address for translation																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S1E1R instruction

Accesses to this instruction use the following encodings:

```
AT S1E1R, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b0111	0b1000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.AT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.ATS1E1R == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        AT_S1E1R(X[t]);
elsif PSTATE.EL == EL2 then
    AT_S1E1R(X[t]);
elsif PSTATE.EL == EL3 then
    AT_S1E1R(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S1E1W, Address Translate Stage 1 EL1 Write

The AT S1E1W characteristics are:

Purpose

Performs stage 1 address translation, with permissions as if writing to the given virtual address from EL1, or from EL2 if the Effective value of HCR_EL2.{E2H, TGE} is {1, 1}, using the following translation regime:

- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the EL1&0 translation regime, accessed from EL1.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the EL2&0 translation regime, accessed from EL2.
- Otherwise, the EL1&0 translation regime, accessed from EL1.

Configuration

There are no configuration notes.

Attributes

AT S1E1W is a 64-bit System instruction.

Field descriptions

The AT S1E1W input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Input address for translation																															
Input address for translation																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S1E1W instruction

Accesses to this instruction use the following encodings:

```
AT S1E1W, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b0111	0b1000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.AT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.ATS1E1W == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        AT_S1E1W(X[t]);
elsif PSTATE.EL == EL2 then
    AT_S1E1W(X[t]);
elsif PSTATE.EL == EL3 then
    AT_S1E1W(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S1E2R, Address Translate Stage 1 EL2 Read

The AT S1E2R characteristics are:

Purpose

Performs stage 1 address translation as defined for EL2, with permissions as if reading from the given virtual address.

Configuration

There are no configuration notes.

Attributes

AT S1E2R is a 64-bit System instruction.

Field descriptions

The AT S1E2R input value bit assignments are:



Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S1E2R instruction

Accesses to this instruction use the following encodings:

```
AT S1E2R, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b0111	0b1000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    AT_S1E2R(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        UNDEFINED;
    else
        AT_S1E2R(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S1E2W, Address Translate Stage 1 EL2 Write

The AT S1E2W characteristics are:

Purpose

Performs stage 1 address translation as defined for EL2, with permissions as if writing to the given virtual address.

Configuration

There are no configuration notes.

Attributes

AT S1E2W is a 64-bit System instruction.

Field descriptions

The AT S1E2W input value bit assignments are:



Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S1E2W instruction

Accesses to this instruction use the following encodings:

```
AT S1E2W, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b0111	0b1000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    AT_S1E2W(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        UNDEFINED;
    else
        AT_S1E2W(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S1E3R, Address Translate Stage 1 EL3 Read

The AT S1E3R characteristics are:

Purpose

Performs stage 1 address translation as defined for EL3, with permissions as if reading from the given virtual address.

Configuration

There are no configuration notes.

Attributes

AT S1E3R is a 64-bit System instruction.

Field descriptions

The AT S1E3R input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Input address for translation																															
Input address for translation																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S1E3R instruction

Accesses to this instruction use the following encodings:

```
AT S1E3R, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b110	0b0111	0b1000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    AT_S1E3R(X[t]);
```

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AT S1E3W, Address Translate Stage 1 EL3 Write

The AT S1E3W characteristics are:

Purpose

Performs stage 1 address translation as defined for EL3, with permissions as if writing to the given virtual address.

Configuration

There are no configuration notes.

Attributes

AT S1E3W is a 64-bit System instruction.

Field descriptions

The AT S1E3W input value bit assignments are:



Bits [63:0]

Input address for translation. The resulting address can be read from the PAR_EL1.

If the address translation instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then VA[63:32] is RES0.

Executing the AT S1E3W instruction

Accesses to this instruction use the following encodings:

```
AT S1E3W, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b110	0b0111	0b1000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    AT_S1E3W(X[t]);
```

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CCSIDR2_EL1, Current Cache Size ID Register 2

The CCSIDR2_EL1 characteristics are:

Purpose

When ARMv8.3-CCIDX is implemented, provides the information about the architecture of the currently selected cache from bits[63:32] of CCSIDR_EL1.

When ARMv8.3-CCIDX is not implemented, this register is not implemented.

Configuration

AArch64 System register CCSIDR2_EL1 bits [31:0] are architecturally mapped to AArch32 System register CCSIDR2[31:0] .

This register is present only when ARMv8.3-CCIDX is implemented. Otherwise, direct accesses to CCSIDR2_EL1 are UNDEFINED.

InIf anAArch32 AArch64is onlynot implementationimplemented, it is IMPLEMENTATION DEFINED whether reading this register gives an UNKNOWN value or is UNDEFINED.

The implementation includes one CCSIDR2_EL1 for each cache that it can access. CSSELR_EL1 selects which Cache Size ID Register is accessible.

Attributes

CCSIDR2_EL1 is a 64-bit register.

Field descriptions

The CCSIDR2_EL1 bit assignments are:



Bits [63:24]

Reserved, RES0.

NumSets, bits [23:0]

(Number of sets in cache) - 1, therefore a value of 0 indicates 1 set in the cache. The number of sets does not have to be a power of 2.

Accessing the CCSIDR2_EL1

If CSSELR_EL1.Level is programmed to a cache level that is not implemented, then on a read of the CCSIDR2_EL1 the behavior is CONSTRAINED UNPREDICTABLE, and can be one of the following:

- The CCSIDR2_EL1 read is treated as NOP.
- The CCSIDR2_EL1 read is UNDEFINED.
- The CCSIDR2_EL1 read returns an UNKNOWN value.

Accesses to this register use the following encodings:

```
MRS <Xt>, CCSIDR2_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b001	0b0000	0b0000	0b010

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID4 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CCSIDR2_EL1;
elsif PSTATE.EL == EL2 then
    return CCSIDR2_EL1;
elsif PSTATE.EL == EL3 then
    return CCSIDR2_EL1;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707~~6134483bd14dc8e12a99e984cbfe3431cc1e9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CCSIDR_EL1, Current Cache Size ID Register

The CCSIDR_EL1 characteristics are:

Purpose

Provides information about the architecture of the currently selected cache.

Configuration

AArch64 System register CCSIDR_EL1 bits [31:0] are architecturally mapped to AArch32 System register CCSIDR[31:0] .

AArch64 System register CCSIDR_EL1 bits [63:32] are architecturally mapped to AArch32 System register CCSIDR2[31:0] .

The implementation includes one CCSIDR_EL1 for each cache that it can access. CSSELR_EL1 selects which Cache Size ID Register is accessible.

Attributes

CCSIDR_EL1 is a 64-bit register.

Field descriptions

The CCSIDR_EL1 bit assignments are:

When ARMv8.3-CCIDX is implemented:



Note

The parameters NumSets, Associativity, and LineSize in these registers define the architecturally visible parameters that are required for the cache maintenance by Set/Way instructions. They are not guaranteed to represent the actual microarchitectural features of a design. You cannot make any inference about the actual sizes of caches based on these parameters.

Bits [63:56]

Reserved, RES0.

NumSets, bits [55:32]

(Number of sets in cache) - 1, therefore a value of 0 indicates 1 set in the cache. The number of sets does not have to be a power of 2.

Bits [31:24]

Reserved, RES0.

Associativity, bits [23:3]

(Associativity of cache) - 1, therefore a value of 0 indicates an associativity of 1. The associativity does not have to be a power of 2.

LineSize, bits [2:0]

(Log_2(Number of bytes in cache line)) - 4. For example:

- For a line length of 16 bytes: $Log_2(16) = 4$, LineSize entry = 0. This is the minimum line length.
- For a line length of 32 bytes: $Log_2(32) = 5$, LineSize entry = 1.

When ARMv8.5-MemTag is implemented and enabled, where a cache only holds Allocation tags, this field is RES0.

Otherwise:



Note

The parameters NumSets, Associativity, and LineSize in these registers define the architecturally visible parameters that are required for the cache maintenance by Set/Way instructions. They are not guaranteed to represent the actual microarchitectural features of a design. You cannot make any inference about the actual sizes of caches based on these parameters.

Bits [63:32]

Reserved, RES0.

Bits [31:28]

Reserved, UNKNOWN.

NumSets, bits [27:13]

(Number of sets in cache) - 1, therefore a value of 0 indicates 1 set in the cache. The number of sets does not have to be a power of 2.

Associativity, bits [12:3]

(Associativity of cache) - 1, therefore a value of 0 indicates an associativity of 1. The associativity does not have to be a power of 2.

LineSize, bits [2:0]

(Log_2(Number of bytes in cache line)) - 4. For example:

- For a line length of 16 bytes: $Log_2(16) = 4$, LineSize entry = 0. This is the minimum line length.
- For a line length of 32 bytes: $Log_2(32) = 5$, LineSize entry = 1.

Accessing the CCSIDR_EL1

If CSSELR_EL1.Level is programmed to a cache level that is not implemented, then on a read of the CCSIDR_EL1 the behavior is CONSTRAINED UNPREDICTABLE, and can be one of the following:

- The CCSIDR_EL1 read is treated as NOP.

- The CCSIDR_EL1 read is UNDEFINED.
- The CCSIDR_EL1 read returns an UNKNOWN value.

Accesses to this register use the following encodings:

```
MRS <Xt>, CCSIDR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b001	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID4 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.CCSIDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CCSIDR_EL1;
elsif PSTATE.EL == EL2 then
    return CCSIDR_EL1;
elsif PSTATE.EL == EL3 then
    return CCSIDR_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CLIDR_EL1, Cache Level ID Register

The CLIDR_EL1 characteristics are:

Purpose

Identifies the type of cache, or caches, that are implemented at each level and can be managed using the architected cache maintenance instructions that operate by set/way, up to a maximum of seven levels. Also identifies the Level of Coherence (LoC) and Level of Unification (LoU) for the cache hierarchy.

Configuration

AArch64 System register CLIDR_EL1 bits [31:0] are architecturally mapped to AArch32 System register CLIDR[31:0] .

Attributes

CLIDR_EL1 is a 64-bit register.

Field descriptions

The CLIDR_EL1 bit assignments are:



Bits [63:47]

Reserved, RES0.

Ttype<n>, bits [2(n-1)+34:2(n-1)+33], for n = 1 to 7

~~**When ARMv8.5-MemTag is implemented:**~~

Tag cache type. Indicate the type of cache that is implemented and can be managed using the architected cache maintenance instructions that operate by set/way at each level, from Level 1 up to a maximum of seven levels of cache hierarchy.

Ttype<n>	Meaning
0b00	No Tag Cache.
0b01	Separate Allocation Tag Cache.
0b10	Unified Allocation Tag and Data cache, Allocation Tags and Data in unified lines.
0b11	Unified Allocation Tag and Data cache, Allocation Tags and Data in separate lines.

~~**Otherwise:**~~

~~Reserved, RES0.~~

ICB, bits [32:30]

Inner cache boundary. This field indicates the boundary for caching Inner Cacheable memory regions.

The possible values are:

ICB	Meaning
0b000	Not disclosed by this mechanism.
0b001	L1 cache is the highest Inner Cacheable level.
0b010	L2 cache is the highest Inner Cacheable level.
0b011	L3 cache is the highest Inner Cacheable level.
0b100	L4 cache is the highest Inner Cacheable level.
0b101	L5 cache is the highest Inner Cacheable level.
0b110	L6 cache is the highest Inner Cacheable level.
0b111	L7 cache is the highest Inner Cacheable level.

LoUU, bits [29:27]

Level of Unification Uniprocessor for the cache hierarchy.

LoC, bits [26:24]

Level of Coherence for the cache hierarchy.

LoUIS, bits [23:21]

Level of Unification Inner Shareable for the cache hierarchy.

Ctype<n>, bits [3(n-1)+2:3(n-1)], for n = 1 to 7

Cache Type fields. Indicate the type of cache that is implemented and can be managed using the architected cache maintenance instructions that operate by set/way at each level, from Level 1 up to a maximum of seven levels of cache hierarchy. Possible values of each field are:

Ctype<n>	Meaning
0b000	No cache.
0b001	Instruction cache only.
0b010	Data cache only.
0b011	Separate instruction and data caches.
0b100	Unified cache.

All other values are reserved.

If software reads the Cache Type fields from Ctype1 upwards, once it has seen a value of 000, no caches that can be managed using the architected cache maintenance instructions that operate by set/way exist at further-out levels of the hierarchy. So, for example, if Ctype3 is the first Cache Type field with a value of 000, the values of Ctype4 to Ctype7 must be ignored.

Accessing the CLIDR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, CLIDR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b001	0b0000	0b0000	0b001

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID4 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.CLIDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CLIDR_EL1;
elsif PSTATE.EL == EL2 then
    return CLIDR_EL1;
elsif PSTATE.EL == EL3 then
    return CLIDR_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHCTL_EL2, Counter-timer Hypervisor Control register

The CNTHCTL_EL2 characteristics are:

Purpose

Controls the generation of an event stream from the physical counter, and access from EL1 to the physical counter and the EL1 physical timer.

Configuration

AArch64 System register CNTHCTL_EL2 bits [31:0] are architecturally mapped to AArch32 System register CNTHCTL[31:0] .

If EL2 is not implemented, this register is RES0 from EL3.

This register has no effect if EL2 is not enabled in the current Security state.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHCTL_EL2 is a 64-bit register.

Field descriptions

The CNTHCTL_EL2 bit assignments are:

When ARMv8.1-VHE is implemented and HCR_EL2.E2H == 1:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40
RES0																							

39	38	37	36	35	34	33	32	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8
RES0																						EVNTIS	EL1NVVCT	EL1NVPCT	EL1TVCT	EL1TVT	ECV	EL1PTEN	EL1PCTEN	EL0PTEN	EL0VTE

Bits [63:18]

Reserved, RES0.

EVNTIS, bit [17]

When ARMv8.6-ECV is implemented:

Controls the scale of the generation of the event stream.

EVNTIS	Meaning
0b0	The CNTHCTL_EL2.EVNTI field applies to CNTPCT_EL0[15:0].
0b1	The CNTHCTL_EL2.EVNTI field applies to CNTPCT_EL0[23:8].

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EL1NVVCT, bit [16]

When ARMv8.6-ECV is implemented:

Traps EL1 accesses to the specified EL1 virtual timer registers using the EL02 descriptors to EL2, when EL2 is enabled for the current Security state.

EL1NVVCT	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	If ((HCR_EL2.E2H==1 && HCR_EL2.TGE==1) || HCR_EL2.NV2==0 || HCR_EL2.NV1==1 || HCR_EL2.NV==0), this control does not cause any instructions to be trapped. If ((HCR_EL2.E2H==0 || HCR_EL2.TGE==0) && HCR_EL2.NV2==1 && HCR_EL2.NV1==0 && HCR_EL2.NV==1), then EL1 accesses to CNTV_CTL_EL02 and CNTV_CVAL_EL02 are trapped to EL2.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 0 other than for the purpose of a direct read.

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EL1NVPCT, bit [15]

When ARMv8.6-ECV is implemented:

Traps EL1 accesses to the specified EL1 physical timer registers using the EL02 descriptors to EL2, when EL2 is enabled for the current Security state.

EL1NVPCT	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	If ((HCR_EL2.E2H==1 && HCR_EL2.TGE==1) || HCR_EL2.NV2==0 || HCR_EL2.NV1==1 || HCR_EL2.NV==0), this control does not cause any instructions to be trapped. If (HCR_EL2.E2H==0 || HCR_EL2.TGE==0) && HCR_EL2.NV2==1 && HCR_EL2.NV1==0 && HCR_EL2.NV==1, then EL1 accesses to CNTP_CTL_EL02 and CNTP_CVAL_EL02, are trapped to EL2.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 0 other than for the purpose of a direct read.

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EL1TVCT, bit [14]

When ARMv8.6-ECV is implemented:

Traps EL0 and EL1 accesses to the EL1 virtual counter registers to EL2, when EL2 is enabled for the current Security state.

EL1TVCT	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	If HCR_EL2.{E2H, TGE} is {1, 1}, this control does not cause any instructions to be trapped. If HCR_EL2.E2H is 0 or HCR_EL2.TGE is 0, then: • In AArch64 state, traps EL0 and EL1 accesses to CNTVCT_EL0 to EL2, unless they are trapped by CNTKCTL_EL1.EL0VCTEN. • In AArch32 state, traps EL0 and EL1 accesses to CNTVCT to EL2, unless they are trapped by CNTKCTL_EL1.EL0VCTEN or CNTKCTL.PL0VCTEN.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 0 other than for the purpose of a direct read.

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EL1TVT, bit [13]

When ARMv8.6-ECV is implemented:

Traps EL0 and EL1 accesses to the EL1 virtual timer registers to EL2, when EL2 is enabled for the current Security state.

EL1TVT	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	If HCR_EL2.{E2H, TGE} is {1, 1}, this control does not cause any instructions to be trapped. If HCR_EL2.E2H is 0 or HCR_EL2.TGE is 0, then: • In AArch64 state, traps EL0 and EL1 accesses to CNTV_CTL_EL0, CNTV_CVAL_EL0, and CNTV_TVAL_EL0 to EL2, unless they are trapped by CNTKCTL_EL1.EL0VTEN. • In AArch32 state, traps EL0 and EL1 accesses to CNTV_CTL, CNTV_CVAL, and CNTV_TVAL to EL2, unless they are trapped by CNTKCTL_EL1.EL0VTEN or CNTKCTL.PL0VTEN.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 0 other than for the purpose of a direct read.

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ECV, bit [12]

When ARMv8.6-ECV is implemented:

Enables the Enhanced Counter Virtualization functionality registers.

ECV	Meaning
0b0	Enhanced Counter Virtualization functionality is disabled.
0b1	When HCR_EL2.{E2H, TGE} == {1, 1} or SCR_EL3.{NS, EEL2} == {0, 0}, then Enhanced Counter Virtualization functionality is disabled. When SCR_EL3.NS or SCR_EL3.EEL2 are 1, and HCR_EL2.E2H or HCR_EL2.TGE are 0, then Enhanced Counter Virtualziation functionality is enabled when EL2 is enabled for the current Security state. This means that: • An MRS to CNTPCT_EL0 from either EL0 or EL1 that is not trapped will return the value (PCount<63:0> - CNTPOFF_EL2<63:0>). • The EL1 physical timer interrupt is triggered when ((PCount<63:0> - CNTPOFF_EL2<63:0>) - PCVal<63:0>) is greater than or equal to 0. PCount<63:0> is the physical count returned when CNTPCT_EL0 is read from EL2 or EL3. PCVal<63:0> is the EL1 physical timer compare value for this timer.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EL1PTEN, bit [11]

When HCR_EL2.TGE is 0, traps EL0 and EL1 accesses to the E1 physical timer registers to EL2 when EL2 is enabled in the current Security state.

EL1PTEN	Meaning
0b0	From AArch64 state: EL0 and EL1 accesses to the CNTP_CTL_EL0, CNTP_CVAL_EL0, and CNTP_TVAL_EL0 are trapped to EL2 when EL2 is enabled in the current Security state, unless they are trapped by CNTKCTL_EL1.EL0PTEN. From AArch32 state: EL0 and EL1 accesses to the CNTP_CTL, CNTP_CVAL, and CNTP_TVAL are trapped to EL2 when EL2 is enabled in the current Security state, unless they are trapped by CNTKCTL_EL1.EL0PTEN or CNTKCTL.PL0PTEN.
0b1	This control does not cause any instructions to be trapped.

When HCR_EL2.TGE is 1, this control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

EL1PCTEN, bit [10]

When HCR_EL2.TGE is 0, traps EL0 and EL1 accesses to the EL1 physical counter register to EL2 when EL2 is enabled in the current Security state, as follows:

- In AArch64 state, accesses to CNTPCT_EL0 are trapped to EL2, reported using EC syndrome value 0x18.
- In AArch32 state, MRRC or MCRR accesses to CNTPCT are trapped to EL2, reported using EC syndrome value 0x04.

EL1PCTEN	Meaning
0b0	From AArch64 state: EL0 and EL1 accesses to the CNTPCT_EL0 are trapped to EL2 when EL2 is enabled in the current Security state, unless they are trapped by CNTKCTL_EL1.EL0PCTEN. From AArch32 state: EL0 and EL1 accesses to the CNTPCT are trapped to EL2 when EL2 is enabled in the current Security state, unless they are trapped by CNTKCTL_EL1.EL0PCTEN or CNTKCTL.PL0PCTEN.
0b1	This control does not cause any instructions to be trapped.

When HCR_EL2.TGE is 1, this control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

EL0PTEN, bit [9]

When HCR_EL2.TGE is 0, this control does not cause any instructions to be trapped.

When HCR_EL2.TGE is 1, traps EL0 accesses to the physical timer registers to EL2.

EL0PTEN	Meaning
0b0	EL0 using AArch64: EL0 accesses to the CNTP_CTL_EL0, CNTP_CVAL_EL0, and CNTP_TVAL_EL0 registers are trapped to EL2. EL0 using AArch32: EL0 accesses to the CNTP_CTL, CNTP_CVAL and CNTP_TVAL registers are trapped to EL2.
0b1	This control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

EL0VTEN, bit [8]

When HCR_EL2.TGE is 0, this control does not cause any instructions to be trapped.

When HCR_EL2.TGE is 1, traps EL0 accesses to the virtual timer registers to EL2.

EL0VTEN	Meaning
0b0	EL0 using AArch64: EL0 accesses to the CNTV_CTL_EL0, CNTV_CVAL_EL0, and CNTV_TVAL_EL0 registers are trapped to EL2. EL0 using AArch32: EL0 accesses to the CNTV_CTL, CNTV_CVAL, and CNTV_TVAL registers are trapped to EL2.
0b1	This control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

EVNTI, bits [7:4]

Selects which bit (0 to 15) of the counter register CNTPCT_EL0 is the trigger for the event stream generated from that counter, when that stream is enabled.

This field resets to an architecturally UNKNOWN value.

EVNTDIR, bit [3]

Controls which transition of the counter register CNTPCT_EL0 trigger bit, defined by EVNTI, generates an event when the event stream is enabled:

EVNTDIR	Meaning
0b0	A 0 to 1 transition of the trigger bit triggers an event.
0b1	A 1 to 0 transition of the trigger bit triggers an event.

This field resets to an architecturally UNKNOWN value.

EVNTEN, bit [2]

Enables the generation of an event stream from the counter register CNTPCT_EL0:

EVNTEN	Meaning
0b0	Disables the event stream.
0b1	Enables the event stream.

This field resets to an architecturally UNKNOWN value.

EL0VCTEN, bit [1]

When HCR_EL2.TGE is 0, this control does not cause any instructions to be trapped.

When HCR_EL2.TGE is 1, traps EL0 accesses to the frequency register and virtual counter register to EL2.

EL0VCTEN	Meaning
0b0	EL0 using AArch64: EL0 accesses to the CNTVCT_EL0 are trapped to EL2. EL0 using AArch64: EL0 accesses to the CNTFRQ_EL0 register are trapped to EL2, if CNTHCTL_EL2.EL0PCTEN is also 0. EL0 using AArch32: EL0 accesses to the CNTVCT are trapped to EL2. EL0 using AArch32: EL0 accesses to the CNTFRQ register are trapped to EL2, if CNTHCTL.EL0PCTEN is also 0.
0b1	This control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

EL0PCTEN, bit [0]

When HCR_EL2.TGE is 0, this control does not cause any instructions to be trapped.

When HCR_EL2.TGE is 1, traps EL0 accesses to the frequency register and physical counter register to EL2.

EL0PCTEN	Meaning
0b0	EL0 using AArch64: EL0 accesses to the CNTPCT_EL0 are trapped to EL2. EL0 using AArch64: EL0 accesses to the CNTFRQ_EL0 register are trapped to EL2, if CNTHCTL_EL2.EL0VCTEN is also 0. EL0 using AArch32: EL0 accesses to the CNTPCT are trapped to EL2. EL0 using AArch32: EL0 accesses to the CNTFRQ and register are trapped to EL2, if CNTHCTL_EL2.EL0VCTEN is also 0.
0b1	This control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

Otherwise:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34
RES0																													

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0														EVNTIS	EL1NVVCT	EL1NVPCT	EL1TVCT	EL1TVT	ECV	RES0				EVNTI				EVNTDIR	EVNTEN	EI

This format applies in all Armv8.0 implementations, and it also contains a description of the behavior when EL3 is implemented and EL2 is not implemented.

Bits [63:18]

Reserved, RES0.

EVNTIS, bit [17]

When ARMv8.6-ECV is implemented:

Controls the scale of the generation of the event stream.

EVNTIS	Meaning
0b0	The CNTHCTL_EL2.EVNTI field applies to CNTPCT_EL0[15:0].
0b1	The CNTHCTL_EL2.EVNTI field applies to CNTPCT_EL0[23:8].

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EL1NVVCT, bit [16]

When ARMv8.6-ECV is implemented:

Traps EL1 accesses to the specified EL1 virtual timer registers using the EL02 descriptors to EL2, when EL2 is enabled for the current Security state.

EL1NVVCT	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	If ((HCR_EL2.E2H==1 && HCR_EL2.TGE==1) || HCR_EL2.NV2==0 || HCR_EL2.NV1==1 || HCR_EL2.NV==0), this control does not cause any instructions to be trapped. If ((HCR_EL2.E2H==0 || HCR_EL2.TGE==0) && HCR_EL2.NV2==1 && HCR_EL2.NV1==0 && HCR_EL2.NV==1), then EL1 accesses to CNTV_CTL_EL02 and CNTV_CVAL_EL02 are trapped to EL2.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 0 other than for the purpose of a direct read.

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EL1NVPCT, bit [15]

When ARMv8.6-ECV is implemented:

Traps EL1 accesses to the specified EL1 physical timer registers using the EL02 descriptors to EL2, when EL2 is enabled for the current Security state.

EL1NVPCT	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	If ((HCR_EL2.E2H==1 && HCR_EL2.TGE==1) || HCR_EL2.NV2==0 || HCR_EL2.NV1==1 || HCR_EL2.NV==0), this control does not cause any instructions to be trapped. If (HCR_EL2.E2H==0 || HCR_EL2.TGE==0) && HCR_EL2.NV2==1 && HCR_EL2.NV1==0 && HCR_EL2.NV==1, then EL1 accesses to CNTP_CTL_EL02 and CNTP_CVAL_EL02, are trapped to EL2.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 0 other than for the purpose of a direct read.

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EL1TVCT, bit [14]

When ARMv8.6-ECV is implemented:

Traps EL0 and EL1 accesses to the EL1 virtual counter registers to EL2, when EL2 is enabled for the current Security state.

EL1TVCT	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	If HCR_EL2.{E2H, TGE} is {1, 1}, this control does not cause any instructions to be trapped. If HCR_EL2.E2H is 0 or HCR_EL2.TGE is 0, then: In AArch64 state, traps EL0 and EL1 accesses to CNTVCT_EL0 to EL2, unless they are trapped by CNTKCTL_EL1.EL0VCTEN. In AArch32 state, traps EL0 and EL1 accesses to CNTVCT to EL2, unless they are trapped by CNTKCTL_EL1.EL0VCTEN or CNTKCTL.PL0VCTEN.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 0 other than for the purpose of a direct read.

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EL1TVT, bit [13]

When ARMv8.6-ECV is implemented:

Traps EL0 and EL1 accesses to the EL1 virtual timer registers to EL2, when EL2 is enabled for the current Security state.

EL1TVT	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	If HCR_EL2.{E2H, TGE} is {1, 1}, this control does not cause any instructions to be trapped. If HCR_EL2.E2H is 0 or HCR_EL2.TGE is 0, then: • In AArch64 state, traps EL0 and EL1 accesses to CNTV_CTL_EL0, CNTV_CVAL_EL0, and CNTV_TVAL_EL0 to EL2, unless they are trapped by CNTKCTL_EL1.EL0VTEN. • In AArch32 state, traps EL0 and EL1 accesses to CNTV_CTL, CNTV_CVAL, and CNTV_TVAL to EL2, unless they are trapped by CNTKCTL_EL1.EL0VTEN or CNTKCTL.PL0VTEN.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 0 other than for the purpose of a direct read.

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ECV, bit [12]

When ARMv8.6-ECV is implemented:

Enables the Enhanced Counter Virtualization functionality registers.

ECV	Meaning
0b0	Enhanced Counter Virtualization functionality is disabled.
0b1	When HCR_EL2.{E2H, TGE} == {1, 1} or SCR_EL3.{NS, EEL2} == {0, 0}, then Enhanced Counter Virtualization functionality is disabled. When SCR_EL3.NS or SCR_EL3.EEL2 are 1, and HCR_EL2.E2H or HCR_EL2.TGE are 0, then Enhanced Counter Virtualziation functionality is enabled when EL2 is enabled for the current Security state. This means that: • An MRS to CNTPCT_EL0 from either EL0 or EL1 that is not trapped will return the value (PCount<63:0> - CNTPOFF_EL2<63:0>). • The EL1 physical timer interrupt is triggered when ((PCount<63:0> - CNTPOFF_EL2<63:0>) - PCVal<63:0>) is greater than or equal to 0. PCount is the physical count returned when CNTPCT_EL0 is read from EL2 or EL3. PCVal<63:0> is the EL1 physical timer compare value for this timer.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [11:8]

Reserved, RES0.

EVNTI, bits [7:4]

Selects which bit (0 to 15) of the counter register CNTPCT_EL0 is the trigger for the event stream generated from that counter, when that stream is enabled.

This field resets to an architecturally UNKNOWN value.

EVNTDIR, bit [3]

Controls which transition of the counter register CNTPCT_EL0 trigger bit, defined by EVNTI, generates an event when the event stream is enabled:

EVNTDIR	Meaning
0b0	A 0 to 1 transition of the trigger bit triggers an event.
0b1	A 1 to 0 transition of the trigger bit triggers an event.

This field resets to an architecturally UNKNOWN value.

EVNTEN, bit [2]

Enables the generation of an event stream from the counter register CNTPCT_EL0:

EVNTEN	Meaning
0b0	Disables the event stream.
0b1	Enables the event stream.

This field resets to 0.

EL1PCEN, bit [1]

Traps EL0 and EL1 accesses to the EL1 physical timer registers to EL2 when EL2 is enabled in the current Security state, as follows:

- In AArch64 state, accesses to CNTP_CTL_EL0, CNTP_CVAL_EL0, CNTP_TVAL_EL0 are trapped to EL2, reported using EC syndrome value 0x18.
- In AArch32 state, MRC or MCR accesses to the following registers are trapped to EL2 reported using EC syndrome value 0x3 and MRRC and MCRR accesses are trapped to EL2, reported using EC syndrome value 0x04:
    - CNTP_CTL, CNTP_CVAL, CNTP_TVAL.

EL1PCEN	Meaning
0b0	From AArch64 state: EL0 and EL1 accesses to the CNTP_CTL_EL0, CNTP_CVAL_EL0, and CNTP_TVAL_EL0 are trapped to EL2 when EL2 is enabled in the current Security state, unless they are trapped by CNTKCTL_EL1.EL0PTEN. From AArch32 state: EL0 and EL1 accesses to the CNTP_CTL, CNTP_CVAL, and CNTP_TVAL are trapped to EL2 when EL2 is enabled in the current Security state, unless they are trapped by CNTKCTL_EL1.EL0PTEN or CNTKCTL.PL0PTEN.
0b1	This control does not cause any instructions to be trapped.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 1 other than for the purpose of a direct read.

This field resets to an architecturally UNKNOWN value.

EL1PCTEN, bit [0]

Traps EL0 and EL1 accesses to the EL1 physical counter register to EL2 when EL2 is enabled in the current Security state, as follows:

- In AArch64 state, accesses to CNTPCT_EL0 are trapped to EL2, reported using EC syndrome value 0x18.
- In AArch32 state, MRRC or MCRR accesses to CNTPCT are trapped to EL2, reported using EC syndrome value 0x04.

EL1PCTEN	Meaning
0b0	From AArch64 state: EL0 and EL1 accesses to the CNTPCT_EL0 are trapped to EL2 when EL2 is enabled in the current Security state, unless they are trapped by CNTKCTL_EL1.EL0PCTEN. From AArch32 state: EL0 and EL1 accesses to the CNTPCT are trapped to EL2 when EL2 is enabled in the current Security state, unless they are trapped by CNTKCTL_EL1.EL0PCTEN or CNTKCTL.PL0PCTEN.
0b1	This control does not cause any instructions to be trapped.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 1 other than for the purpose of a direct read.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHCTL_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic CNTHCTL_EL2 or CNTKCTL_EL1 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTHCTL_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTHCTL_EL2;
elsif PSTATE.EL == EL3 then
    return CNTHCTL_EL2;
```

```
MSR CNTHCTL_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTHCTL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    CNTHCTL_EL2 = X[t];
```

```
MRS <Xt>, CNTKCTL_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    return CNTKCTL_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return CNTHCTL_EL2;
    else
        return CNTKCTL_EL1;
elsif PSTATE.EL == EL3 then
    return CNTKCTL_EL1;
```

MSR CNTKCTL_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    CNTKCTL_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        CNTHCTL_EL2 = X[t];
    else
        CNTKCTL_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    CNTKCTL_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHP_CTL_EL2, Counter-timer Hypervisor Physical Timer Control register

The CNTHP_CTL_EL2 characteristics are:

Purpose

Control register for the EL2 physical timer.

Configuration

AArch64 System register CNTHP_CTL_EL2 bits [31:0] are architecturally mapped to AArch32 System register CNTHP_CTL[31:0] .

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHP_CTL_EL2 is a 64-bit register.

Field descriptions

The CNTHP_CTL_EL2 bit assignments are:



Bits [63:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTHP_TVAL_EL2 continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHP_CTL_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic CNTHP_CTL_EL2 or CNTP_CTL_EL0 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTHP_CTL_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTHP_CTL_EL2;
elsif PSTATE.EL == EL3 then
    return CNTHP_CTL_EL2;
```

```
MSR CNTHP_CTL_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTHP_CTL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    CNTHP_CTL_EL2 = X[t];
```

MRS <Xt>, CNTP_CTL_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CTL_EL2;
    else
        return CNTP_CTL_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x180];
    else
        return CNTP_CTL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CTL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHP_CTL_EL2;
    else
        return CNTP_CTL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTP_CTL_EL0;
```

MSR CNTP_CTL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CTL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CTL_EL2 = X[t];
    else
        CNTP_CTL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x180] = X[t];
    else
        CNTP_CTL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CTL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHP_CTL_EL2 = X[t];
    else
        CNTP_CTL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTP_CTL_EL0 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHP_CVAL_EL2, Counter-timer Physical Timer CompareValue register (EL2)

The CNTHP_CVAL_EL2 characteristics are:

Purpose

Holds the compare value for the EL2 physical timer.

Configuration

AArch64 System register CNTHP_CVAL_EL2 bits [63:0] are architecturally mapped to AArch32 System register CNTHP_CVAL[63:0] .

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHP_CVAL_EL2 is a 64-bit register.

Field descriptions

The CNTHP_CVAL_EL2 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CompareValue																															
CompareValue																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CompareValue, bits [63:0]

Holds the EL2 physical timer CompareValue.

When CNTHP_CTL_EL2.ENABLE is 1, the timer condition is met when (CNTPCT_EL0 - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTHP_CTL_EL2.ISTATUS is set to 1.
- If CNTHP_CTL_EL2.IMASK is 0, an interrupt is generated.

When CNTHP_CTL_EL2.ENABLE is 0, the timer condition is not met, but CNTPCT_EL0 continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHP_CVAL_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic CNTHP_CVAL_EL2 or CNTP_CVAL_EL0 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

MRS <Xt>, CNTHP_CVAL_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTHP_CVAL_EL2;
elsif PSTATE.EL == EL3 then
    return CNTHP_CVAL_EL2;
```

MSR CNTHP_CVAL_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTHP_CVAL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    CNTHP_CVAL_EL2 = X[t];
```

MRS <Xt>, CNTP_CVAL_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CVAL_EL2;
    else
        return CNTP_CVAL_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x178];
    else
        return CNTP_CVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHP_CVAL_EL2;
    else
        return CNTP_CVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTP_CVAL_EL0;
```

```
MSR CNTP_CVAL_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CVAL_EL2 = X[t];
    else
        CNTP_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x178] = X[t];
    else
        CNTP_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHP_CVAL_EL2 = X[t];
    else
        CNTP_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTP_CVAL_EL0 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHP_TVAL_EL2, Counter-timer Physical Timer TimerValue register (EL2)

The CNTHP_TVAL_EL2 characteristics are:

Purpose

Holds the timer value for the EL2 physical timer.

Configuration

AArch64 System register CNTHP_TVAL_EL2 bits [31:0] are architecturally mapped to AArch32 System register CNTHP_TVAL[31:0] .

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHP_TVAL_EL2 is a 64-bit register.

Field descriptions

The CNTHP_TVAL_EL2 bit assignments are:



Bits [63:32]

Reserved, RES0.

TimerValue, bits [31:0]

The TimerValue view of the EL2 physical timer.

On a read of this register:

- If CNTHP_CTL_EL2.ENABLE is 0, the value returned is UNKNOWN.
- If CNTHP_CTL_EL2.ENABLE is 1, the value returned is (CNTHP_CVAL_EL2 - CNTPCT_EL0).

On a write of this register, CNTHP_CVAL_EL2 is set to (CNTPCT_EL0 + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTHP_CTL_EL2.ENABLE is 1, the timer condition is met when (CNTPCT_EL0 - CNTHP_CVAL_EL2) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTHP_CTL_EL2.ISTATUS is set to 1.
- If CNTHP_CTL_EL2.IMASK is 0, an interrupt is generated.

When CNTHP_CTL_EL2.ENABLE is 0, the timer condition is not met, but CNTPCT_EL0 continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHP_TVAL_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic CNTHP_TVAL_EL2 or CNTP_TVAL_EL0 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTHP_TVAL_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTHP_TVAL_EL2;
elsif PSTATE.EL == EL3 then
    return CNTHP_TVAL_EL2;
```

```
MSR CNTHP_TVAL_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTHP_TVAL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    CNTHP_TVAL_EL2 = X[t];
```

```
MRS <Xt>, CNTP_TVAL_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_TVAL_EL2;
    else
        return CNTP_TVAL_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CNTP_TVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_TVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHP_TVAL_EL2;
    else
        return CNTP_TVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTP_TVAL_EL0;
```

MSR CNTP_TVAL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_TVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_TVAL_EL2 = X[t];
    else
        CNTP_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        CNTP_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_TVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHP_TVAL_EL2 = X[t];
    else
        CNTP_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTP_TVAL_EL0 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHPS_CTL_EL2, Counter-timer Secure Physical Timer Control register (EL2)

The CNTHPS_CTL_EL2 characteristics are:

Purpose

Control register for the Secure EL2 physical timer.

Configuration

AArch64 System register CNTHPS_CTL_EL2 bits [31:0] are architecturally mapped to AArch32 System register CNTHPS_CTL[31:0] .

This register is present only when ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHPS_CTL_EL2 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHPS_CTL_EL2 is a 64-bit register.

Field descriptions

The CNTHPS_CTL_EL2 bit assignments are:



Bits [63:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the CNTHPS_CTL_EL2.ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the CNTHPS_CTL_EL2.ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTHPS_TVAL_EL2 continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHPS_CTL_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTHPS_CTL_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0101	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        return CNTHPS_CTL_EL2;
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        return CNTHPS_CTL_EL2;
```

```
MSR CNTHPS_CTL_EL2, <Xt>
```

op0	op1	CRn	CRm	op2

0b11	0b100	0b1110	0b0101	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        CNTHPS_CTL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        CNTHPS_CTL_EL2 = X[t];
```

MRS <Xt>, CNTP_CTL_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CTL_EL2;
    else
        return CNTP_CTL_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x180];
    else
        return CNTP_CTL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CTL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHP_CTL_EL2;
    else
        return CNTP_CTL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTP_CTL_EL0;
```

MSR CNTP_CTL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CTL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CTL_EL2 = X[t];
    else
        CNTP_CTL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x180] = X[t];
    else
        CNTP_CTL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CTL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHP_CTL_EL2 = X[t];
    else
        CNTP_CTL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTP_CTL_EL0 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHPS_CVAL_EL2, Counter-timer Secure Physical Timer CompareValue register (EL2)

The CNTHPS_CVAL_EL2 characteristics are:

Purpose

Holds the compare value for the Secure EL2 physical timer.

Configuration

AArch64 System register CNTHPS_CVAL_EL2 bits [31:0] are architecturally mapped to AArch32 System register CNTHPS_CVAL[31:0] .

This register is present only when ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHPS_CVAL_EL2 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHPS_CVAL_EL2 is a 64-bit register.

Field descriptions

The CNTHPS_CVAL_EL2 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CompareValue																															
CompareValue																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CompareValue, bits [63:0]

Holds the EL2 physical timer CompareValue.

When CNTHPS_CTL_EL2.ENABLE is 1, the timer condition is met when (CNTPCT_EL0 - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTHPS_CTL_EL2.ISTATUS is set to 1.
- If CNTHPS_CTL_EL2.IMASK is 0, an interrupt is generated.

When CNTHPS_CTL_EL2.ENABLE is 0, the timer condition is not met, but CNTPCT_EL0 continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHPS_CVAL_EL2

Accesses to this register use the following encodings:

MRS <Xt>, CNTHPS_CVAL_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0101	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        return CNTHPS_CVAL_EL2;
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        return CNTHPS_CVAL_EL2;
```

MSR CNTHPS_CVAL_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0101	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        CNTHPS_CVAL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        CNTHPS_CVAL_EL2 = X[t];
```

MRS <Xt>, CNTP_CVAL_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CVAL_EL2;
    else
        return CNTP_CVAL_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x178];
    else
        return CNTP_CVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHP_CVAL_EL2;
    else
        return CNTP_CVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTP_CVAL_EL0;
```

```
MSR CNTP_CVAL_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CVAL_EL2 = X[t];
    else
        CNTP_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x178] = X[t];
    else
        CNTP_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHP_CVAL_EL2 = X[t];
    else
        CNTP_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTP_CVAL_EL0 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHPS_TVAL_EL2, Counter-timer Secure Physical Timer TimerValue register (EL2)

The CNTHPS_TVAL_EL2 characteristics are:

Purpose

Holds the timer value for the Secure EL2 physical timer.

Configuration

AArch64 System register CNTHPS_TVAL_EL2 bits [31:0] are architecturally mapped to AArch32 System register CNTHPS_TVAL[31:0] .

This register is present only when ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHPS_TVAL_EL2 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHPS_TVAL_EL2 is a 64-bit register.

Field descriptions

The CNTHPS_TVAL_EL2 bit assignments are:



Bits [63:32]

Reserved, RES0.

TimerValue, bits [31:0]

The TimerValue view of the EL2 physical timer.

On a read of this register:

- If CNTHPS_CTL_EL2.ENABLE is 0, the value returned is UNKNOWN.
- If CNTHPS_CTL_EL2.ENABLE is 1, the value returned is (CNTHPS_CVAL_EL2 - CNTPCT_EL0).

On a write of this register, CNTHPS_CVAL_EL2 is set to (CNTPCT_EL0 + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTHPS_CTL_EL2.ENABLE is 1, the timer condition is met when (CNTPCT_EL0 - CNTHPS_CVAL_EL2) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTHPS_CTL_EL2.ISTATUS is set to 1.
- If CNTHPS_CTL_EL2.IMASK is 0, an interrupt is generated.

When CNTHPS_CTL_EL2.ENABLE is 0, the timer condition is not met, but CNTPCT_EL0 continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHPS_TVAL_EL2

Accesses to this register use the following encodings:

MRS <Xt>, CNTHPS_TVAL_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        return CNTHPS_TVAL_EL2;
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        return CNTHPS_TVAL_EL2;
```

MSR CNTHPS_TVAL_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        CNTHPS_TVAL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        CNTHPS_TVAL_EL2 = X[t];
```

MRS <Xt>, CNTP_TVAL_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_TVAL_EL2;
    else
        return CNTP_TVAL_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CNTP_TVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_TVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHP_TVAL_EL2;
    else
        return CNTP_TVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTP_TVAL_EL0;
```

MSR CNTP_TVAL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_TVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_TVAL_EL2 = X[t];
    else
        CNTP_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        CNTP_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_TVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHP_TVAL_EL2 = X[t];
    else
        CNTP_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTP_TVAL_EL0 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHV_CTL_EL2, Counter-timer Virtual Timer Control register (EL2)

The CNTHV_CTL_EL2 characteristics are:

Purpose

Control register for the EL2 virtual timer.

Configuration

AArch64 System register CNTHV_CTL_EL2 bits [31:0] are architecturally mapped to AArch32 System register CNTHV_CTL[31:0] .

This register is present only when ARMv8.1-VHE is implemented. Otherwise, direct accesses to CNTHV_CTL_EL2 are UNDEFINED.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHV_CTL_EL2 is a 64-bit register.

Field descriptions

The CNTHV_CTL_EL2 bit assignments are:



Bits [63:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTHV_TVAL_EL2 continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHV_CTL_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic CNTHV_CTL_EL2 or CNTV_CTL_EL0 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTHV_CTL_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTHV_CTL_EL2;
elsif PSTATE.EL == EL3 then
    return CNTHV_CTL_EL2;
```

```
MSR CNTHV_CTL_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTHV_CTL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    CNTHV_CTL_EL2 = X[t];
```

MRS <Xt>, CNTV_CTL_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CTL_EL2;
    else
        return CNTV_CTL_EL0;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x170];
    else
        return CNTV_CTL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CTL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHV_CTL_EL2;
    else
        return CNTV_CTL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTV_CTL_EL0;
```

MSR CNTV_CTL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CTL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CTL_EL2 = X[t];
    else
        CNTV_CTL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x170] = X[t];
    else
        CNTV_CTL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CTL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHV_CTL_EL2 = X[t];
    else
        CNTV_CTL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTV_CTL_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHV_CVAL_EL2, Counter-timer Virtual Timer CompareValue register (EL2)

The CNTHV_CVAL_EL2 characteristics are:

Purpose

Holds the compare value for the EL2 virtual timer.

Configuration

AArch64 System register CNTHV_CVAL_EL2 bits [63:0] are architecturally mapped to AArch32 System register CNTHV_CVAL[63:0] .

This register is present only when ARMv8.1-VHE is implemented. Otherwise, direct accesses to CNTHV_CVAL_EL2 are UNDEFINED.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHV_CVAL_EL2 is a 64-bit register.

Field descriptions

The CNTHV_CVAL_EL2 bit assignments are:



CompareValue, bits [63:0]

Holds the EL2 virtual timer CompareValue.

When CNTHV_CTL_EL2.ENABLE is 1, the timer condition is met when (CNTVCT_EL0 - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTHV_CTL_EL2.ISTATUS is set to 1.
- If CNTHV_CTL_EL2.IMASK is 0, an interrupt is generated.

When CNTHV_CTL_EL2.ENABLE is 0, the timer condition is not met, but CNTVCT_EL0 continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHV_CVAL_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic CNTHV_CVAL_EL2 or CNTV_CVAL_EL0 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTHV_CVAL_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0011	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTHV_CVAL_EL2;
elsif PSTATE.EL == EL3 then
    return CNTHV_CVAL_EL2;
```

```
MSR CNTHV_CVAL_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0011	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTHV_CVAL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    CNTHV_CVAL_EL2 = X[t];
```

```
MRS <Xt>, CNTV_CVAL_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CVAL_EL2;
    else
        return CNTV_CVAL_EL0;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x168];
    else
        return CNTV_CVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHV_CVAL_EL2;
    else
        return CNTV_CVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTV_CVAL_EL0;
```

MSR CNTV_CVAL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CVAL_EL2 = X[t];
    else
        CNTV_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x168] = X[t];
    else
        CNTV_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHV_CVAL_EL2 = X[t];
    else
        CNTV_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTV_CVAL_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHV_TVAL_EL2, Counter-timer Virtual Timer TimerValue Register (EL2)

The CNTHV_TVAL_EL2 characteristics are:

Purpose

Holds the timer value for the EL2 virtual timer.

Configuration

AArch64 System register CNTHV_TVAL_EL2 bits [31:0] are architecturally mapped to AArch32 System register CNTHV_TVAL[31:0] .

This register is present only when ARMv8.1-VHE is implemented. Otherwise, direct accesses to CNTHV_TVAL_EL2 are UNDEFINED.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHV_TVAL_EL2 is a 64-bit register.

Field descriptions

The CNTHV_TVAL_EL2 bit assignments are:



Bits [63:32]

Reserved, RES0.

TimerValue, bits [31:0]

The TimerValue view of the EL2 virtual timer.

On a read of this register:

- If CNTHV_CTL_EL2.ENABLE is 0, the value returned is UNKNOWN.
- If CNTHV_CTL_EL2.ENABLE is 1, the value returned is (CNTHV_CVAL_EL2 - CNTVCT_EL0).

On a write of this register, CNTHV_CVAL_EL2 is set to (CNTVCT_EL0 + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTHV_CTL_EL2.ENABLE is 1, the timer condition is met when (CNTVCT_EL0 - CNTHV_CVAL_EL2) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTHV_CTL_EL2.ISTATUS is set to 1.
- If CNTHV_CTL_EL2.IMASK is 0, an interrupt is generated.

When CNTHV_CTL_EL2.ENABLE is 0, the timer condition is not met, but CNTVCT_EL0 continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHV_TVAL_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic CNTHV_TVAL_EL2 or CNTV_TVAL_EL0 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTHV_TVAL_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTHV_TVAL_EL2;
elsif PSTATE.EL == EL3 then
    return CNTHV_TVAL_EL2;
```

```
MSR CNTHV_TVAL_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTHV_TVAL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    CNTHV_TVAL_EL2 = X[t];
```

```
MRS <Xt>, CNTV_TVAL_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_TVAL_EL2;
    else
        return CNTV_TVAL_EL0;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CNTV_TVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_TVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHV_TVAL_EL2;
    else
        return CNTV_TVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTV_TVAL_EL0;
```

MSR CNTV_TVAL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_TVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_TVAL_EL2 = X[t];
    else
        CNTV_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        CNTV_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_TVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHV_TVAL_EL2 = X[t];
    else
        CNTV_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTV_TVAL_EL0 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHVS_CTL_EL2, Counter-timer Secure Virtual Timer Control register (EL2)

The CNTHVS_CTL_EL2 characteristics are:

Purpose

Control register for the Secure EL2 virtual timer.

Configuration

AArch64 System register CNTHVS_CTL_EL2 bits [31:0] are architecturally mapped to AArch32 System register CNTHVS_CTL[31:0] .

This register is present only when ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHVS_CTL_EL2 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHVS_CTL_EL2 is a 64-bit register.

Field descriptions

The CNTHVS_CTL_EL2 bit assignments are:



Bits [63:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the CNTHVS_CTL_EL2.ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the CNTHVS_CTL_EL2.ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTHVS_TVAL_EL2 continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHVS_CTL_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTHVS_CTL_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0100	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        return CNTHVS_CTL_EL2;
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        return CNTHVS_CTL_EL2;
```

```
MSR CNTHVS_CTL_EL2, <Xt>
```

op0	op1	CRn	CRm	op2

0b11	0b100	0b1110	0b0100	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        CNTHVS_CTL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        CNTHVS_CTL_EL2 = X[t];
```

MRS <Xt>, CNTV_CTL_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CTL_EL2;
    else
        return CNTV_CTL_EL0;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x170];
    else
        return CNTV_CTL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CTL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHV_CTL_EL2;
    else
        return CNTV_CTL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTV_CTL_EL0;
```

MSR CNTV_CTL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CTL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CTL_EL2 = X[t];
    else
        CNTV_CTL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x170] = X[t];
    else
        CNTV_CTL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CTL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHV_CTL_EL2 = X[t];
    else
        CNTV_CTL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTV_CTL_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHVS_CVAL_EL2, Counter-timer Secure Virtual Timer CompareValue register (EL2)

The CNTHVS_CVAL_EL2 characteristics are:

Purpose

Holds the compare value for the Secure EL2 virtual timer.

Configuration

AArch64 System register CNTHVS_CVAL_EL2 bits [63:0] are architecturally mapped to AArch32 System register CNTHVS_CVAL[63:0] .

This register is present only when ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHVS_CVAL_EL2 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHVS_CVAL_EL2 is a 64-bit register.

Field descriptions

The CNTHVS_CVAL_EL2 bit assignments are:



CompareValue, bits [63:0]

Holds the Secure EL2 virtual timer CompareValue.

When CNTHVS_CTL_EL2.ENABLE is 1, the timer condition is met when (CNTVCT_EL0 - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTHVS_CTL_EL2.ISTATUS is set to 1.
- If CNTHVS_CTL_EL2.IMASK is 0, an interrupt is generated.

When CNTHVS_CTL_EL2.ENABLE is 0, the timer condition is not met, but CNTVCT_EL0 continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHVS_CVAL_EL2

Accesses to this register use the following encodings:

MRS <Xt>, CNTHVS_CVAL_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0100	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        return CNTHVS_CVAL_EL2;
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        return CNTHVS_CVAL_EL2;
```

MSR CNTHVS_CVAL_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0100	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        CNTHVS_CVAL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        CNTHVS_CVAL_EL2 = X[t];
```

MRS <Xt>, CNTV_CVAL_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CVAL_EL2;
    else
        return CNTV_CVAL_EL0;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x168];
    else
        return CNTV_CVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHV_CVAL_EL2;
    else
        return CNTV_CVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTV_CVAL_EL0;
```

MSR CNTV_CVAL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CVAL_EL2 = X[t];
    else
        CNTV_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x168] = X[t];
    else
        CNTV_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHV_CVAL_EL2 = X[t];
    else
        CNTV_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTV_CVAL_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHVS_TVAL_EL2, Counter-timer Secure Virtual Timer TimerValue register (EL2)

The CNTHVS_TVAL_EL2 characteristics are:

Purpose

Holds the timer value for the Secure EL2 virtual timer.

Configuration

AArch64 System register CNTHVS_TVAL_EL2 bits [31:0] are architecturally mapped to AArch32 System register CNTHVS_TVAL[31:0] .

This register is present only when ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHVS_TVAL_EL2 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHVS_TVAL_EL2 is a 64-bit register.

Field descriptions

The CNTHVS_TVAL_EL2 bit assignments are:



Bits [63:32]

Reserved, RES0.

TimerValue, bits [31:0]

The TimerValue view of the EL2 virtual timer.

On a read of this register:

- If CNTHVS_CTL_EL2.ENABLE is 0, the value returned is UNKNOWN.
- If CNTHVS_CTL_EL2.ENABLE is 1, the value returned is (CNTHVS_CVAL_EL2 - CNTVCT_EL0).

On a write of this register, CNTHVS_CVAL_EL2 is set to (CNTVCT_EL0 + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTHVS_CTL_EL2.ENABLE is 1, the timer condition is met when ((CNTVCT_EL0 - CNTHVS_CVAL_EL2) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTHVS_CTL_EL2.ISTATUS is set to 1.
- If CNTHVS_CTL_EL2.IMASK is 0, an interrupt is generated.

When CNTHVS_CTL_EL2.ENABLE is 0, the timer condition is not met, but CNTVCT_EL0 continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHVS_TVAL_EL2

Accesses to this register use the following encodings:

MRS <Xt>, CNTHVS_TVAL_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        return CNTHVS_TVAL_EL2;
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        return CNTHVS_TVAL_EL2;
```

MSR CNTHVS_TVAL_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        CNTHVS_TVAL_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        CNTHVS_TVAL_EL2 = X[t];
```

MRS <Xt>, CNTV_TVAL_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_TVAL_EL2;
    else
        return CNTV_TVAL_EL0;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CNTV_TVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_TVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHV_TVAL_EL2;
    else
        return CNTV_TVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTV_TVAL_EL0;
```

MSR CNTV_TVAL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_TVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_TVAL_EL2 = X[t];
    else
        CNTV_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        CNTV_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_TVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHV_TVAL_EL2 = X[t];
    else
        CNTV_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTV_TVAL_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTKCTL_EL1, Counter-timer Kernel Control register

The CNTKCTL_EL1 characteristics are:

Purpose

When ARMv8.1-VHE is not implemented, or when HCR_EL2.{E2H, TGE} is not {1, 1}, this register controls the generation of an event stream from the virtual counter, and access from EL0 to the physical counter, virtual counter, EL1 physical timers, and the virtual timer.

When ARMv8.1-VHE is implemented and HCR_EL2.{E2H, TGE} is {1, 1}, this register does not cause any event stream from the virtual counter to be generated, and does not control access to the counters and timers. The access to counters and timers at EL0 is controlled by CNTHCTL_EL2.

Configuration

AArch64 System register CNTKCTL_EL1 bits [31:0] are architecturally mapped to AArch32 System register CNTKCTL[31:0] .

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTKCTL_EL1 is a 64-bit register.

Field descriptions

The CNTKCTL_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0														EVNTIS	RES0							EL0PTEN	EL0VTEN	EVNTI				EVNTDIR	EVNTEN	EL0VCTEN	EL0PCTEN

Bits [63:18]

Reserved, RES0.

EVNTIS, bit [17]

When ARMv8.6-ECV is implemented:

Controls the scale of the generation of the event stream.

EVNTIS	Meaning
0b0	The CNTKCTL_EL1.EVNTI field applies to CNTVCT_EL0[15:0].
0b1	The CNTKCTL_EL1.EVNTI field applies to CNTVCT_EL0[23:8].

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [16:10]

Reserved, RES0.

EL0PTEN, bit [9]

Traps EL0 accesses to the physical timer registers to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, as follows:

- In AArch64 state, the following registers are trapped, reported using EC syndrome value `0x18`:
  - CNTP_CTL_EL0, CNTP_CVAL_EL0, and CNTP_TVAL_EL0.
- In AArch32 state, MRC and MCR accesses to the following registers are trapped, reported using EC syndrome value `0x03`, MRRC and MCRR accesses are trapped, reported using EC syndrome value `0x04`:
  - CNTP_CTL, CNTP_CVAL, CNTP_TVAL.

EL0PTEN	Meaning
`0b0`	EL0 accesses to the physical timer registers are trapped to EL1.
`0b1`	This control does not cause any instructions to be trapped.

When ARMv8.1-VHE is implemented and HCR_EL2.{E2H, TGE} is {1, 1}, this control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

EL0VTEN, bit [8]

Traps EL0 accesses to the virtual timer registers to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, as follows:

- In AArch64 state, accesses to the following registers are trapped, reported using EC syndrome value `0x18`:
  - CNTV_CTL_EL0, CNTV_CVAL_EL0, and CNTV_TVAL_EL0.
- In AArch32 state, MRC and MCR accesses to the following registers are trapped and reported using EC syndrome value `0x03`, MRRC and MCRR accesses are trapped using EC syndrome value `0x04`:
  - CNTV_CTL, CNTV_CVAL, and CNTV_TVAL.

EL0VTEN	Meaning
`0b0`	EL0 accesses to the virtual timer registers are trapped.
`0b1`	This control does not cause any instructions to be trapped.

When ARMv8.1-VHE is implemented and HCR_EL2.{E2H, TGE} is {1, 1}, this control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

EVNTI, bits [7:4]

Selects which bit (0 to 15) of the counter register CNTVCT_EL0 is the trigger for the event stream generated from that counter, when that stream is enabled.

This field resets to an architecturally UNKNOWN value.

EVNTDIR, bit [3]

Controls which transition of the counter register CNTVCT_EL0 trigger bit, defined by EVNTI, generates an event when the event stream is enabled:

EVNTDIR	Meaning
0b0	A 0 to 1 transition of the trigger bit triggers an event.
0b1	A 1 to 0 transition of the trigger bit triggers an event.

This field resets to an architecturally UNKNOWN value.

EVNTEN, bit [2]

When ARMv8.1-VHE is not implemented, or when HCR_EL2.{E2H, TGE} is not {1, 1}, enables the generation of an event stream from the counter register CNTVCT_EL0:

EVNTEN	Meaning
0b0	Disables the event stream.
0b1	Enables the event stream.

When ARMv8.1-VHE is implemented and HCR_EL2.{E2H, TGE} is {1, 1}, this control does not enable the event stream.

This field resets to 0.

EL0VCTEN, bit [1]

Traps EL0 accesses to the frequency register and virtual counter register to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, as follows:

- In AArch64 state, accesses to the following registers are trapped and reported using EC syndrome value 0x18:
  - CNTVCT_EL0 and if CNTKCTL_EL1.EL0PCTEN is 0, CNTFRQ_EL0.
- In AArch32 state, MRC and MCR accesses to the following registers are trapped and reported using EC syndrome value 0x03, MRRC and MCRR accesses are trapped and reported using EC syndrome value 0x04:
  - CNTVCT and if CNTKCTL_EL1.EL0PCTEN is 0, CNTFRQ.

EL0VCTEN	Meaning
0b0	EL0 accesses to the frequency register and virtual counter registers are trapped.
0b1	This control does not cause any instructions to be trapped.

When ARMv8.1-VHE is implemented and HCR_EL2.{E2H, TGE} is {1, 1}, this control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

EL0PCTEN, bit [0]

Traps EL0 accesses to the frequency register and physical counter register to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, as follows:

- In AArch64 state, the following registers are trapped, reported using EC syndrome value 0x18:
  - CNTPCT_EL0 and if CNTKCTL_EL1.EL0VCTEN is 0, CNTFRQ_EL0.
- In AArch32 state, MCR or MRC accesses the following registers are trapped, reported using EC syndrome value 0x03, MCRR or MRRC accesses are trapped and reported using EC syndrome value 0x04:
  - CNTPCT~~CNTCT~~ and if CNTKCTL_EL1.EL0VCTEN is 0, CNTFRQ.

EL0PCTEN	Meaning
0b0	EL0 accesses to the frequency register and physical counter register are trapped.
0b1	This control does not cause any instructions to be trapped.

When ARMv8.1-VHE is implemented and HCR_EL2.{E2H, TGE} is {1, 1}, this control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTKCTL_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic CNTKCTL_EL1 or CNTKCTL_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTKCTL_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    return CNTKCTL_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return CNTHCTL_EL2;
    else
        return CNTKCTL_EL1;
elsif PSTATE.EL == EL3 then
    return CNTKCTL_EL1;
```

```
MSR CNTKCTL_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    CNTKCTL_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        CNTHCTL_EL2 = X[t];
    else
        CNTKCTL_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    CNTKCTL_EL1 = X[t];
```

```
MRS <Xt>, CNTKCTL_EL12
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return CNTKCTL_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return CNTKCTL_EL1;
    else
        UNDEFINED;
```

MSR CNTKCTL_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        CNTKCTL_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        CNTKCTL_EL1 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTP_CTL_EL0, Counter-timer Physical Timer Control register

The CNTP_CTL_EL0 characteristics are:

Purpose

Control register for the EL1 physical timer.

Configuration

AArch64 System register CNTP_CTL_EL0 bits [31:0] are architecturally mapped to AArch32 System register CNTP_CTL[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTP_CTL_EL0 is a 64-bit register.

Field descriptions

The CNTP_CTL_EL0 bit assignments are:



Bits [63:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTP_TVAL_EL0 continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTP_CTL_EL0

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic CNTP_CTL_EL0 or CNTP_CTL_EL02 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTP_CTL_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CTL_EL2;
    else
        return CNTP_CTL_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x180];
    else
        return CNTP_CTL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CTL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHP_CTL_EL2;
    else
        return CNTP_CTL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTP_CTL_EL0;
```

```
MSR CNTP_CTL_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CTL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CTL_EL2 = X[t];
    else
        CNTP_CTL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x180] = X[t];
    else
        CNTP_CTL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CTL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHP_CTL_EL2 = X[t];
    else
        CNTP_CTL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTP_CTL_EL0 = X[t];
```

MRS <Xt>, CNTP_CTL_EL02

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        if EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1NVPCT == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            return NVMem[0x180];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return CNTP_CTL_EL0;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return CNTP_CTL_EL0;
    else
        UNDEFINED;
```

MSR CNTP_CTL_EL02, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        if EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1NVPCT == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            NVMem[0x180] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        CNTP_CTL_EL0 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        CNTP_CTL_EL0 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTP_CVAL_EL0, Counter-timer Physical Timer CompareValue register

The CNTP_CVAL_EL0 characteristics are:

Purpose

Holds the compare value for the EL1 physical timer.

Configuration

AArch64 System register CNTP_CVAL_EL0 bits [63:0] are architecturally mapped to AArch32 System register CNTP_CVAL[63:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTP_CVAL_EL0 is a 64-bit register.

Field descriptions

The CNTP_CVAL_EL0 bit assignments are:



CompareValue, bits [63:0]

Holds the EL1 physical timer CompareValue.

When CNTP_CTL_EL0.ENABLE is 1, the timer condition is met when (CNTPCT_EL0 - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTP_CTL_EL0.ISTATUS is set to 1.
- If CNTP_CTL_EL0.IMASK is 0, an interrupt is generated.

When CNTP_CTL_EL0.ENABLE is 0, the timer condition is not met, but CNTPCT_EL0 continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTP_CVAL_EL0

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic CNTP_CVAL_EL0 or CNTP_CVAL_EL02 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

MRS <Xt>, CNTP_CVAL_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CVAL_EL2;
    else
        return CNTP_CVAL_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x178];
    else
        return CNTP_CVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHP_CVAL_EL2;
    else
        return CNTP_CVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTP_CVAL_EL0;
```

MSR CNTP_CVAL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CVAL_EL2 = X[t];
    else
        CNTP_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x178] = X[t];
    else
        CNTP_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHP_CVAL_EL2 = X[t];
    else
        CNTP_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTP_CVAL_EL0 = X[t];
```

MRS <Xt>, CNTP_CVAL_EL02

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        if EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1NVPCT == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            return NVMem[0x178];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return CNTP_CVAL_EL0;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return CNTP_CVAL_EL0;
    else
        UNDEFINED;
```

MSR CNTP_CVAL_EL02, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        if EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1NVPCT == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            NVMem[0x178] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        CNTP_CVAL_EL0 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        CNTP_CVAL_EL0 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTP_TVAL_EL0, Counter-timer Physical Timer TimerValue register

The CNTP_TVAL_EL0 characteristics are:

Purpose

Holds the timer value for the EL1 physical timer.

Configuration

AArch64 System register CNTP_TVAL_EL0 bits [31:0] are architecturally mapped to AArch32 System register CNTP_TVAL[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTP_TVAL_EL0 is a 64-bit register.

Field descriptions

The CNTP_TVAL_EL0 bit assignments are:



Bits [63:32]

Reserved, RES0.

TimerValue, bits [31:0]

The TimerValue view of the EL1 physical timer.

On a read of this register:

- If CNTP_CTL_EL0.ENABLE is 0, the value returned is UNKNOWN.
- If CNTP_CTL_EL0.ENABLE is 1, the value returned is (CNTP_CVAL_EL0 - CNTPCT_EL0).

On a write of this register, CNTP_CVAL_EL0 is set to (CNTPCT_EL0 + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTP_CTL_EL0.ENABLE is 1, the timer condition is met when (CNTPCT_EL0 - CNTP_CVAL_EL0) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTP_CTL_EL0.ISTATUS is set to 1.
- If CNTP_CTL_EL0.IMASK is 0, an interrupt is generated.

When CNTP_CTL_EL0.ENABLE is 0, the timer condition is not met, but CNTPCT_EL0 continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTP_TVAL_EL0

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic CNTP_TVAL_EL0 or CNTP_TVAL_EL02 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTP_TVAL_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_TVAL_EL2;
    else
        return CNTP_TVAL_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CNTP_TVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_TVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHP_TVAL_EL2;
    else
        return CNTP_TVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTP_TVAL_EL0;
```

```
MSR CNTP_TVAL_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_TVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_TVAL_EL2 = X[t];
    else
        CNTP_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        CNTP_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_TVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHP_TVAL_EL2 = X[t];
    else
        CNTP_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTP_TVAL_EL0 = X[t];
```

MRS <Xt>, CNTP_TVAL_EL02

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return CNTP_TVAL_EL0;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return CNTP_TVAL_EL0;
    else
        UNDEFINED;
```

```
MSR CNTP_TVAL_EL02, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        CNTP_TVAL_EL0 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        CNTP_TVAL_EL0 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTPOFF_EL2, Counter-timer Physical Offset register

The CNTPOFF_EL2 characteristics are:

Purpose

Holds the 64-bit physical offset. This is the offset for the AArch64 physical timers and counters when Enhanced Counter Virtualization is enabled.

Configuration

This register is present only when ARMv8.6-ECV is implemented. Otherwise, direct accesses to CNTPOFF_EL2 are UNDEFINED.

The offsetting of the timers and counters based on EL2 using AArch64 apply at:

- EL1 when EL1 is using AArch64 or AArch32.
- EL0 when EL0 is using AArch64 or AArch32.

When EL2 is implemented and enabled in the current Security state, the physical counter uses a fixed physical offset of zero if either of the following are true:

- CNTHCTL_EL2.ECV is 0.
- SCR_EL3.ECVEn is 0.
- HCR_EL2.{E2H, TGE} is {1, 1}.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTPOFF_EL2 is a 64-bit register.

Field descriptions

The CNTPOFF_EL2 bit assignments are:



Bits~~Physical offset, bits~~ [63:0]

Physical offset.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTPOFF_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTPOFF_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0000	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x1A8];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ECVEn == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return CNTPOFF_EL2;
elsif PSTATE.EL == EL3 then
    return CNTPOFF_EL2;
```

```
MSR CNTPOFF_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1110	0b0000	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x1A8] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ECVEn == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        CNTPOFF_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    CNTPOFF_EL2 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTPS_CTL_EL1, Counter-timer Physical Secure Timer Control register

The CNTPS_CTL_EL1 characteristics are:

Purpose

Control register for the secure physical timer, usually accessible at EL3 but configurably accessible at EL1 in Secure state.

Configuration

There are no configuration notes.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTPS_CTL_EL1 is a 64-bit register.

Field descriptions

The CNTPS_CTL_EL1 bit assignments are:



Bits [63:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTPS_TVAL_EL1 continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTPS_CTL_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTPS_CTL_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b111	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '0' then
        if SCR_EL3.EEL2 == '1' then
            UNDEFINED;
        elsif SCR_EL3.ST == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            return CNTPS_CTL_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return CNTPS_CTL_EL1;
```

```
MSR CNTPS_CTL_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b111	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '0' then
        if SCR_EL3.EEL2 == '1' then
            UNDEFINED;
        elsif SCR_EL3.ST == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            CNTPS_CTL_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    CNTPS_CTL_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTPS_CVAL_EL1, Counter-timer Physical Secure Timer CompareValue register

The CNTPS_CVAL_EL1 characteristics are:

Purpose

Holds the compare value for the secure physical timer, usually accessible at EL3 but configurably accessible at EL1 in Secure state.

Configuration

There are no configuration notes.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTPS_CVAL_EL1 is a 64-bit register.

Field descriptions

The CNTPS_CVAL_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CompareValue																															
CompareValue																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CompareValue, bits [63:0]

Holds the secure physical timer CompareValue.

When CNTPS_CTL_EL1.ENABLE is 1, the timer condition is met when (CNTPCT_EL0 - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTPS_CTL_EL1.ISTATUS is set to 1.
- If CNTPS_CTL_EL1.IMASK is 0, an interrupt is generated.

When CNTPS_CTL_EL1.ENABLE is 0, the timer condition is not met, but CNTPCT_EL0 continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTPS_CVAL_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTPS_CVAL_EL1
```

op0	op1	CRn	CRm	op2

0b11	0b111	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '0' then
        if SCR_EL3.EEL2 == '1' then
            UNDEFINED;
        elsif SCR_EL3.ST == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            return CNTPS_CVAL_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return CNTPS_CVAL_EL1;
```

MSR CNTPS_CVAL_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b111	0b1110	0b0010	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '0' then
        if SCR_EL3.EEL2 == '1' then
            UNDEFINED;
        elsif SCR_EL3.ST == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            CNTPS_CVAL_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    CNTPS_CVAL_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTPS_TVAL_EL1, Counter-timer Physical Secure Timer TimerValue register

The CNTPS_TVAL_EL1 characteristics are:

Purpose

Holds the timer value for the secure physical timer, usually accessible at EL3 but configurably accessible at EL1 in Secure state.

Configuration

There are no configuration notes.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTPS_TVAL_EL1 is a 64-bit register.

Field descriptions

The CNTPS_TVAL_EL1 bit assignments are:



Bits [63:32]

Reserved, RES0.

TimerValue, bits [31:0]

The TimerValue view of the secure physical timer.

On a read of this register:

- If CNTPS_CTL_EL1.ENABLE is 0, the value returned is UNKNOWN.
- If CNTPS_CTL_EL1.ENABLE is 1, the value returned is (CNTPS_CVAL_EL1 - CNTPCT_EL0).

On a write of this register, CNTPS_CVAL_EL1 is set to (CNTPCT_EL0 + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTPS_CTL_EL1.ENABLE is 1, the timer condition is met when (CNTPCT_EL0 - CNTPS_CVAL_EL1) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTPS_CTL_EL1.ISTATUS is set to 1.
- If CNTPS_CTL_EL1.IMASK is 0, an interrupt is generated.

When CNTPS_CTL_EL1.ENABLE is 0, the timer condition is not met, but CNTPCT_EL0 continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTPS_TVAL_EL1

Accesses to this register use the following encodings:

MRS <Xt>, CNTPS_TVAL_EL1

op0	op1	CRn	CRm	op2
0b11	0b111	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '0' then
        if SCR_EL3.EEL2 == '1' then
            UNDEFINED;
        elsif SCR_EL3.ST == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            return CNTPS_TVAL_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return CNTPS_TVAL_EL1;
```

MSR CNTPS_TVAL_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b111	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '0' then
        if SCR_EL3.EEL2 == '1' then
            UNDEFINED;
        elsif SCR_EL3.ST == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            CNTPS_TVAL_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    CNTPS_TVAL_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTV_CTL_EL0, Counter-timer Virtual Timer Control register

The CNTV_CTL_EL0 characteristics are:

Purpose

Control register for the virtual timer.

Configuration

AArch64 System register CNTV_CTL_EL0 bits [31:0] are architecturally mapped to AArch32 System register CNTV_CTL[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTV_CTL_EL0 is a 64-bit register.

Field descriptions

The CNTV_CTL_EL0 bit assignments are:



Bits [63:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTV_TVAL_EL0 continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTV_CTL_EL0

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic CNTV_CTL_EL0 or CNTV_CTL_EL02 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTV_CTL_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CTL_EL2;
    else
        return CNTV_CTL_EL0;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x170];
    else
        return CNTV_CTL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CTL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHV_CTL_EL2;
    else
        return CNTV_CTL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTV_CTL_EL0;
```

MSR CNTV_CTL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CTL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CTL_EL2 = X[t];
    else
        CNTV_CTL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x170] = X[t];
    else
        CNTV_CTL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CTL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHV_CTL_EL2 = X[t];
    else
        CNTV_CTL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTV_CTL_EL0 = X[t];
```

MRS <Xt>, CNTV_CTL_EL02

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        if EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1NVVCT == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            return NVMem[0x170];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return CNTV_CTL_EL0;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return CNTV_CTL_EL0;
    else
        UNDEFINED;
```

MSR CNTV_CTL_EL02, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        if EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1NVVCT == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            NVMem[0x170] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        CNTV_CTL_EL0 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        CNTV_CTL_EL0 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTV_CVAL_EL0, Counter-timer Virtual Timer CompareValue register

The CNTV_CVAL_EL0 characteristics are:

Purpose

Holds the compare value for the virtual timer.

Configuration

AArch64 System register CNTV_CVAL_EL0 bits [63:0] are architecturally mapped to AArch32 System register CNTV_CVAL[63:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTV_CVAL_EL0 is a 64-bit register.

Field descriptions

The CNTV_CVAL_EL0 bit assignments are:



CompareValue, bits [63:0]

Holds the EL1 virtual timer CompareValue.

When CNTV_CTL_EL0.ENABLE is 1, the timer condition is met when (CNTVCT_EL0 - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTV_CTL_EL0.ISTATUS is set to 1.
- If CNTV_CTL_EL0.IMASK is 0, an interrupt is generated.

When CNTV_CTL_EL0.ENABLE is 0, the timer condition is not met, but CNTVCT_EL0 continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTV_CVAL_EL0

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic CNTV_CVAL_EL0 or CNTV_CVAL_EL02 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

MRS <Xt>, CNTV_CVAL_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CVAL_EL2;
    else
        return CNTV_CVAL_EL0;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x168];
    else
        return CNTV_CVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHV_CVAL_EL2;
    else
        return CNTV_CVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTV_CVAL_EL0;
```

MSR CNTV_CVAL_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CVAL_EL2 = X[t];
    else
        CNTV_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x168] = X[t];
    else
        CNTV_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHV_CVAL_EL2 = X[t];
    else
        CNTV_CVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTV_CVAL_EL0 = X[t];
```

MRS <Xt>, CNTV_CVAL_EL02

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0011	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        if EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1NVVCT == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            return NVMem[0x168];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return CNTV_CVAL_EL0;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return CNTV_CVAL_EL0;
    else
        UNDEFINED;
```

```
MSR CNTV_CVAL_EL02, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0011	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        if EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1NVVCT == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            NVMem[0x168] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        CNTV_CVAL_EL0 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        CNTV_CVAL_EL0 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTV_TVAL_EL0, Counter-timer Virtual Timer TimerValue register

The CNTV_TVAL_EL0 characteristics are:

Purpose

Holds the timer value for the EL1 virtual timer.

Configuration

AArch64 System register CNTV_TVAL_EL0 bits [31:0] are architecturally mapped to AArch32 System register CNTV_TVAL[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTV_TVAL_EL0 is a 64-bit register.

Field descriptions

The CNTV_TVAL_EL0 bit assignments are:



Bits [63:32]

Reserved, RES0.

TimerValue, bits [31:0]

The TimerValue view of the EL1 virtual timer.

On a read of this register:

- If CNTV_CTL_EL0.ENABLE is 0, the value returned is UNKNOWN.
- If CNTV_CTL_EL0.ENABLE is 1, the value returned is (CNTV_CVAL_EL0 - CNTVCT_EL0).

On a write of this register, CNTV_CVAL_EL0 is set to (CNTVCT_EL0 + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTV_CTL_EL0.ENABLE is 1, the timer condition is met when (CNTVCT_EL0 - CNTV_CVAL_EL0) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTV_CTL_EL0.ISTATUS is set to 1.
- If CNTV_CTL_EL0.IMASK is 0, an interrupt is generated.

When CNTV_CTL_EL0.ENABLE is 0, the timer condition is not met, but CNTVCT_EL0 continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTV_TVAL_EL0

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic CNTV_TVAL_EL0 or CNTV_TVAL_EL02 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CNTV_TVAL_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_TVAL_EL2;
    else
        return CNTV_TVAL_EL0;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CNTV_TVAL_EL0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_TVAL_EL2;
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        return CNTHV_TVAL_EL2;
    else
        return CNTV_TVAL_EL0;
elsif PSTATE.EL == EL3 then
    return CNTV_TVAL_EL0;
```

```
MSR CNTV_TVAL_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_TVAL_EL2 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_TVAL_EL2 = X[t];
    else
        CNTV_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        CNTV_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' && SCR_EL3.NS == '0' && IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_TVAL_EL2 = X[t];
    elsif HCR_EL2.E2H == '1' && SCR_EL3.NS == '1' then
        CNTHV_TVAL_EL2 = X[t];
    else
        CNTV_TVAL_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    CNTV_TVAL_EL0 = X[t];
```

MRS <Xt>, CNTV_TVAL_EL02

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return CNTV_TVAL_EL0;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return CNTV_TVAL_EL0;
    else
        UNDEFINED;
```

MSR CNTV_TVAL_EL02, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        CNTV_TVAL_EL0 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        CNTV_TVAL_EL0 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CONTEXTIDR_EL1, Context ID Register (EL1)

The CONTEXTIDR_EL1 characteristics are:

Purpose

Identifies the current Process Identifier.

The value of the whole of this register is called the Context ID and is used by:

- The debug logic, for Linked and Unlinked Context ID matching.
- The trace logic, to identify the current process.

The significance of this register is for debug and trace use only.

This register is used when ARMv8.1-VHE is not implemented, or whenARMv8.1-VHE is implemented and HCR_EL2.E2H is set to 0.

Note

When ARMv8.1-VHE is implemented and HCR_EL2.E2H is set to 1, CONTEXTIDR_EL2 is used.

Configuration

AArch64 System register CONTEXTIDR_EL1 bits [31:0] are architecturally mapped to AArch32 System register CONTEXTIDR[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CONTEXTIDR_EL1 is a 64-bit register.

Field descriptions

The CONTEXTIDR_EL1 bit assignments are:



Bits [63:32]

Reserved, RES0.

PROCID, bits [31:0]

Process Identifier. This field must be programmed with a unique value that identifies the current process.

Note

In AArch32 state, when TTBCR.EAE is set to 0, CONTEXTIDR.ASID holds the ASID.

In AArch64 state, CONTEXTIDR_EL1 is independent of the ASID, and for the EL1&0 translation regime either TTBR0_EL1 or TTBR1_EL1 holds the ASID.

This field resets to an architecturally UNKNOWN value.

Accessing the CONTEXTIDR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic CONTEXTIDR_EL1 or CONTEXTIDR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CONTEXTIDR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.CONTEXTIDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x108];
    else
        return CONTEXTIDR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return CONTEXTIDR_EL2;
    else
        return CONTEXTIDR_EL1;
elsif PSTATE.EL == EL3 then
    return CONTEXTIDR_EL1;
```

```
MSR CONTEXTIDR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.CONTEXTIDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x108] = X[t];
    else
        CONTEXTIDR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        CONTEXTIDR_EL2 = X[t];
    else
        CONTEXTIDR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    CONTEXTIDR_EL1 = X[t];
```

MRS <Xt>, CONTEXTIDR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b1101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x108];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return CONTEXTIDR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return CONTEXTIDR_EL1;
    else
        UNDEFINED;
```

MSR CONTEXTIDR_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b1101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x108] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        CONTEXTIDR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        CONTEXTIDR_EL1 = X[t];
    else
        UNDEFINED;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CONTEXTIDR_EL2, Context ID Register (EL2)

The CONTEXTIDR_EL2 characteristics are:

Purpose

When HCR_EL2.E2H is set to 1, identifies the current Process Identifier.

The value of the whole of this register is called the Context ID and is used by:

- The debug logic, for Linked and Unlinked Context ID matching.
- The trace logic, to identify the current process.

The significance of this register is for debug and trace use only.

Note

When HCR_EL2.E2H is 0, CONTEXTIDR_EL2 replaces CONTEXTIDR_EL1 where CONTEXTIDR_EL1 would usually be used.

Configuration

This register is present only when ARMv8.1-VHE is implemented or ARMv8.2-Debug is implemented. Otherwise, direct accesses to CONTEXTIDR_EL2 are UNDEFINED.

If EL2 is not implemented, this register is RES0 from EL3.

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CONTEXTIDR_EL2 is a 64-bit register.

Field descriptions

The CONTEXTIDR_EL2 bit assignments are:



Bits [63:32]

Reserved, RES0.

PROCID, bits [31:0]

Process Identifier. This field must be programmed with a unique value that identifies the current process.

Note

In AArch32 state, when TTBCR.EAE is set to 0, CONTEXTIDR.ASID holds the ASID.

In AArch64 state, CONTEXTIDR_EL2 is independent of the ASID, and for the EL2&0 translation regime either TTBR0_EL2 or TTBR1_EL2 holds the ASID.

This field resets to an architecturally UNKNOWN value.

Accessing the CONTEXTIDR_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic CONTEXTIDR_EL2 or CONTEXTIDR_EL1 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CONTEXTIDR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CONTEXTIDR_EL2;
elsif PSTATE.EL == EL3 then
    return CONTEXTIDR_EL2;
```

```
MSR CONTEXTIDR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    CONTEXTIDR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    CONTEXTIDR_EL2 = X[t];
```

```
MRS <Xt>, CONTEXTIDR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.CONTEXTIDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x108];
    else
        return CONTEXTIDR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return CONTEXTIDR_EL2;
    else
        return CONTEXTIDR_EL1;
elsif PSTATE.EL == EL3 then
    return CONTEXTIDR_EL1;
```

```
MSR CONTEXTIDR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.CONTEXTIDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x108] = X[t];
    else
        CONTEXTIDR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        CONTEXTIDR_EL2 = X[t];
    else
        CONTEXTIDR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    CONTEXTIDR_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CPACR_EL1, Architectural Feature Access Control Register

The CPACR_EL1 characteristics are:

Purpose

Controls access to trace, SVE, Advanced SIMD and floating-point functionality.

Configuration

AArch64 System register CPACR_EL1 bits [31:0] are architecturally mapped to AArch32 System register CPACR[31:0] .

When HCR_EL2.{E2H, TGE} == {1, 1}, the fields in this register have no effect on execution at EL0 and EL1. In this case, the controls provided by CPTR_EL2 are used.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CPACR_EL1 is a 64-bit register.

Field descriptions

The CPACR_EL1 bit assignments are:



Bits [63:29]

Reserved, RES0.

TTA, bit [28]

Traps EL0 and EL1 System register accesses to all implemented trace registers to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, from both Execution states as follows:

- In AArch64 state, accesses to trace registers are trapped, reported using EC syndrome value `0x18`.
- In AArch32 state, MRC and MCR accesses to trace registers are trapped, reported using EC syndrome value `0x05`.
- In AArch32 state, MRRC and MCRR accesses to trace registers are trapped, reported using EC syndrome value `0x0C`.

TTA	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	This control causes EL0 and EL1 System register accesses to all implemented trace registers to be trapped.

Note

- The ETMv4 architecture does not permit EL0 to access the trace registers. If the Armv8-A architecture is implemented with an ETMv4 implementation, EL0 accesses to the trace registers are UNDEFINED, and any resulting exception is higher priority than an exception that would be generated because the value of CPACR_EL1.TTA is 1.
- The Armv8-A architecture does not provide traps on trace register accesses through the optional memory-mapped interface.

System register accesses to the trace registers can have side-effects. When a System register access is trapped, any side-effects that are normally associated with the access do not occur before the exception is taken.

If System register access to the trace functionality is not implemented, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

Bits [27:22]

Reserved, RES0.

FPEN, bits [21:20]

Traps EL0 and EL1 accesses to the SVE, Advanced SIMD, and floating-point registers to EL1, reported using EC syndrome value `0x07`, or to EL2 reported using EC syndrome value `0x00`, when EL2 is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, from both Execution states as follows:

- In AArch64 state, accesses to FPCR, FPSR, any of the SIMD and floating-point registers V0-V31, including their views as D0-D31 registers or S0-31 registers. See 'The SIMD and floating-point registers, V0-V31' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.
- FPCSR, and any of the SIMD and floating-point registers Q0-15, including their views as D0-D31 registers or S0-31 registers. See 'Advanced SIMD and floating-point System registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

FPEN	Meaning
`0b00`	This control causes any instructions at EL0 or EL1 that use the registers associated with SVE, Advanced SIMD and floating-point execution to be trapped, unless they are trapped by CPACR_EL1.ZEN.
`0b01`	This control causes any instructions at EL0 that use the registers associated with SVE, Advanced SIMD and floating-point execution to be trapped, unless they are trapped by CPACR_EL1.ZEN, but does not cause any instruction at EL1 to be trapped.
`0b10`	This control causes any instructions at EL0 or EL1 that use the registers associated with SVE, Advanced SIMD and floating-point execution to be trapped, unless they are trapped by CPACR_EL1.ZEN.
`0b11`	This control does not cause any instructions to be trapped.

Writes to MVFR0, MVFR1 and MVFR2 from EL1 or higher are CONSTRAINED UNPREDICTABLE and whether these accesses can be trapped by this control depends on implemented CONSTRAINED UNPREDICTABLE behavior.

Note

- Attempts to write to the FPSID count as use of the registers for accesses from EL1 or higher.
- Accesses from EL0 to FPSID, MVFR0, MVFR1, MVFR2, and FPEXC are UNDEFINED, and any resulting exception is higher priority than an exception that would be generated because the value of CPACR_EL1.FPEN is not `0b11`.

This field resets to an architecturally UNKNOWN value.

Bits [19:18]

Reserved, RES0.

ZEN, bits [17:16]

When SVE is implemented:

Traps SVE instructions and instructions that access SVE System registers at EL0 and EL1 to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1.

ZEN	Meaning
0b00	This control causes these instructions executed at EL0 or EL1 to be trapped.
0b01	This control causes these instructions executed at EL0 to be trapped, but does not cause any instruction at EL1 to be trapped.
0b10	This control causes these instructions executed at EL0 or EL1 to be trapped.
0b11	This control does not cause any instruction to be trapped.

If SVEis not implemented, this field is RES0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [15:0]

Reserved, RES0.

Accessing the CPACR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic CPACR_EL1 or CPACR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, CPACR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TCPAC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.CPACR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x100];
    else
        return CPACR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        return CPTR_EL2;
    else
        return CPACR_EL1;
elsif PSTATE.EL == EL3 then
    return CPACR_EL1;
```

MSR CPACR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TCPAC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.CPACR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x100] = X[t];
    else
        CPACR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        CPTR_EL2 = X[t];
    else
        CPACR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    CPACR_EL1 = X[t];
```

MRS <Xt>, CPACR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0001	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x100];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            return CPACR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return CPACR_EL1;
    else
        UNDEFINED;
```

MSR CPACR_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b0001	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x100] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            CPACR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        CPACR_EL1 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CPTR_EL3, Architectural Feature Trap Register (EL3)

The CPTR_EL3 characteristics are:

Purpose

Controls trapping to EL3 of access to CPACR_EL1, CPTR_EL2, trace functionality and registers associated with SVE, Advanced SIMD and floating-point execution. Also controls EL3 access to trace functionality and registers associated with SVE, Advanced SIMD and floating-point execution.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to CPTR_EL3 are UNDEFINED.

Attributes

CPTR_EL3 is a 64-bit register.

Field descriptions

The CPTR_EL3 bit assignments are:



Bits [63:32]

Reserved, RES0.

TCPAC, bit [31]

Traps all of the following to EL3, from both Security states and both Execution states.

- EL2 accesses to CPTR_EL2, reported using EC syndrome value `0x18`, or HCPTR, reported using EC syndrome value `0x03`.
- EL2 and EL1 accesses to CPACR_EL1 reported using EC syndrome value `0x18`, or CPACR reported using EC syndrome value `0x03`.

When CPTR_EL3.TCPAC is:

TCPAC	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	EL2 accesses to the CPTR_EL2 or HCPTR, and EL2 and EL1 accesses to the CPACR_EL1 or CPACR, are trapped to EL3, unless they are trapped by CPTR_EL2.TCPAC.

This field resets to an architecturally UNKNOWN value.

TAM, bit [30]

When AMUv1 is implemented:

Trap Activity Monitor access. Traps EL2, EL1 and EL0 accesses to all Activity Monitor registers to EL3.

Accesses to the Activity Monitors registers are trapped as follows:

- In AArch64 state, the following registers are trapped to EL3 and reported with EC syndrome value `0x18`:
  - AMUSERENR_EL0, AMCFGR_EL0, AMCGCR_EL0, AMCNTENCLR0_EL0, AMCNTENCLR1_EL0, AMCNTENSET0_EL0, AMCNTENSET1_EL0, AMCR_EL0, AMEVCNTR0<n>_EL0, AMEVCNTR1<n>_EL0, AMEVTYPER0<n>_EL0, and AMEVTYPER1<n>_EL0.
- In AArch32 state, accesses with MRC or MCR to the following registers reported with EC syndrome value `0x03`:
  - AMUSERENR, AMCFGR, AMCGCR, AMCNTENCLR0, AMCNTENCLR1, AMCNTENSET0, AMCNTENSET1, AMCR, AMEVTYPER0<n>, and AMEVTYPER1<n>.
- In AArch32 state, accesses with MRRC or MCRR to the following registers, reported with EC syndrome value `0x04`:
  - AMEVCNTR0<n>, AMEVCNTR1<n>.

TAM	Meaning
`0b0`	Accesses from EL2, EL1, and EL0 to Activity Monitor registers are not trapped.
`0b1`	Accesses from EL2, EL1, and EL0 to Activity Monitor registers are trapped to EL3.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [29:21]

Reserved, RES0.

TTA, bit [20]

Traps System register accesses. Accesses to the trace registers, from all Exception levels, both Security states, and both Execution states are trapped to EL3 as follows:

- In AArch64 state, Trace registers with op0=2, op1=1, are trapped to EL3 and reported using EC syndrome value `0x18`.
- In AArch32 state, accesses using MCR or MRC to the Trace registers with cpnum=14 and opc1=1 are reported using EC syndrome value `0x05`.
- In AArch32 state, accesses using MCRR or MRRC to the Trace registers with cpnum=14 and opc1=1 are reported using EC syndrome value `0x0C`.

TTA	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Any System register access to the trace registers is trapped to EL3, subject to the exception prioritization rules, unless it is trapped by CPACR.TRCDIS, CPACR_EL1.TTA or CPTR_EL2.TTA.

If System register access to trace functionality is not supported, this bit is RES0.

Note

The ETMv4 architecture does not permit EL0 to access the trace registers. If the Armv8-A architecture is implemented with an ETMv4 implementation, EL0 accesses to the trace registers are UNDEFINED, and any resulting exception is higher priority than this trap exception.

EL3 does not provide traps on trace register accesses through the Memory-mapped interface.

System register accesses to the trace registers can have side-effects. When a System register access is trapped, no side-effects occur before the exception is taken, see 'Register access instructions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Bits [19:11]

Reserved, RES0.

TFP, bit [10]

Traps all accesses to SVE, Advanced SIMD and floating-point functionality, from all Exception levels, both Security states, and both Execution states, to EL3. Defined values are:

This includes the following registers, all reported using EC syndrome value `0x07`:

- FPCR, FPSR, FPEXC32_EL2, any of the SIMD and floating-point registers V0-V31, including their views as D0-D31 registers or S0-31 registers. See 'The SIMD and floating-point registers, V0-V31' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.
- MVFR0, MVFR1, MVFR2, FPCSR, FPEXC, and any of the SIMD and floating-point registers Q0-15, including their views as D0-D31 registers or S0-31 registers. See 'Advanced SIMD and floating-point System registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Permitted VMSR accesses to FPSID are ignored, but for the purposes of this trap the architecture define a VMSR access to the FPSID from EL1 or higher as an access to a SIMD and floating-point register.

TFP	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Any attempt at any Exception level to execute an instruction that uses the registers associated with SVE, Advanced SIMD and floating-point is trapped to EL3, subject to the exception prioritization rules, unless it is trapped by CPTR_EL3.EZ.

Note

FPEXC32_EL2 is not accessible from EL0 using AArch64.

FPSID, MRFR0, MVFR1, and FPEXC are not accessible from EL0 using AArch32.

This field resets to an architecturally UNKNOWN value.

Bit [9]

Reserved, RES0.

EZ, bit [8]

When SVE is implemented:

Traps all accesses to SVE functionality and registers from all Exception levels, and both Security states, to EL3.

EZ	Meaning
0b0	This control causes these instructions executed at any Exception level to be trapped, subject to the exception prioritization rules.
0b1	This control does not cause any instruction to be trapped.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [7:0]

Reserved, RES0.

Accessing the CPTR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, CPTR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0001	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return CPTR_EL3;
```

```
MSR CPTR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0001	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    CPTR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CSSELR_EL1, Cache Size Selection Register

The CSSELR_EL1 characteristics are:

Purpose

Selects the current Cache Size ID Register, CCSIDR_EL1, by specifying the required cache level and the cache type (either instruction or data cache).

Configuration

AArch64 System register CSSELR_EL1 bits [31:0] are architecturally mapped to AArch32 System register CSSELR[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CSSELR_EL1 is a 64-bit register.

Field descriptions

The CSSELR_EL1 bit assignments are:



Bits [63:5]

Reserved, RES0.

TnD, bit [4]

~~When ARMv8.5-MemTag is implemented:~~

Allocation Tag not Data bit.

TnD	Meaning
0b0	Data, Instruction or Unified cache.
0b1	Separate Allocation Tag cache.

When CSSELR_EL1.InD == 1, this bit is RES0.

If CSSELR_EL1.Level is programmed to a cache level that is not implemented, then the value for this field on a read of CSSELR_EL1 is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

~~Otherwise:~~

~~Reserved, RES0.~~

Level, bits [3:1]

Cache level of required cache.

Level	Meaning
0b000	Level 1 cache.
0b001	Level 2 cache.
0b010	Level 3 cache.
0b011	Level 4 cache.
0b100	Level 5 cache.
0b101	Level 6 cache.
0b110	Level 7 cache.

All other values are reserved.

If CSSELR_EL1.Level is programmed to a cache level that is not implemented, then the value for this field on a read of CSSELR_EL1 is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

InD, bit [0]

Instruction not Data bit.

InD	Meaning
0b0	Data or unified cache.
0b1	Instruction cache.

If CSSELR_EL1.Level is programmed to a cache level that is not implemented, then a read of CSSELR_EL1 is CONSTRAINED UNPREDICTABLE, and returns UNKNOWN values for CSSELR_EL1.{Level, InD}.

This field resets to an architecturally UNKNOWN value.

Accessing the CSSELR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, CSSELR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b010	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID4 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.CSSELR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CSSELR_EL1;
elsif PSTATE.EL == EL2 then
    return CSSELR_EL1;
elsif PSTATE.EL == EL3 then
    return CSSELR_EL1;
```

```
MSR CSSELR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2

0b11	0b010	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID4 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.CSSELR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        CSSELR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    CSSELR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    CSSELR_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTR_EL0, Cache Type Register

The CTR_EL0 characteristics are:

Purpose

Provides information about the architecture of the caches.

Configuration

AArch64 System register CTR_EL0 bits [31:0] are architecturally mapped to AArch32 System register CTR[31:0] .

Attributes

CTR_EL0 is a 64-bit register.

Field descriptions

The CTR_EL0 bit assignments are:



Bits [63:38]

Reserved, RES0.

TminLine, bits [37:32]

~~**When ARMv8.5-MemTag is implemented:**~~

Tag minimum Line. Log_2 of the number of words covered by Allocation Tags in the smallest cache line of all caches which can contain Allocation tags that are controlled by the PE.

~~**Otherwise:**~~

~~Reserved, RES0.~~

Note

~~For an implementation with cache lines containing 64 bytes of data and 4 Allocation Tags this will be log_2(64/4) = 4.~~

~~For an implementation with Allocations Tags in separate cache lines of 128 Allocation Tags per line this will be log_2(128*16/4) = 9.~~

- For an implementation with cache lines containing 64 bytes of data and 4 Allocation Tags, this will be log_2(64/4) = 4.
- For an implementation with Allocations Tags in separate cache lines of 128 Allocation Tags per line, this will be log_2(128*16/4) = 9.

Bit [31]

Reserved, RES1.

Bit [30]

Reserved, RES0.

DIC, bit [29]

Instruction cache invalidation requirements for data~~instruction~~ to instruction~~data~~ coherence. ~~The meaning of this bit is:~~

DIC	Meaning
0b0	Instruction cache invalidation to the Point of Unification is required for data~~instruction~~ to instruction~~data~~ coherence.
0b1	Instruction cache invalidation~~cleaning~~ to the Point of Unification is not required for data~~instruction~~ to instruction~~data~~ coherence.

IDC, bit [28]

Data cache clean requirements for instruction to data coherence. The meaning of this bit is:

IDC	Meaning
0b0	Data cache clean to the Point of Unification is required for instruction to data coherence, unless CLIDR_EL1.LoC == 0b000 or (CLIDR_EL1.LoUIS == 0b000 && CLIDR_EL1.LoUU == 0b000).
0b1	Data cache clean to the Point of Unification is not required for instruction to data coherence.

CWG, bits [27:24]

Cache writeback granule. Log_2 of the number of words of the maximum size of memory that can be overwritten as a result of the eviction of a cache entry that has had a memory location in it modified.

A value of 0b0000 indicates that this register does not provide Cache writeback granule information and either:

- The architectural maximum of 512 words (2KB) must be assumed.
- The Cache writeback granule can be determined from maximum cache line size encoded in the Cache Size ID Registers.

Values greater than 0b1001 are reserved.

Arm recommends that an implementation that does not support cache write-back implements this field as 0b0001. This applies, for example, to an implementation that supports only write-through caches.

ERG, bits [23:20]

Exclusives reservation granule. Log_2 of the number of words of the maximum size of the reservation granule that has been implemented for the Load-Exclusive and Store-Exclusive instructions.

The use of the value 0b0000 is deprecated.

The value 0b0001 and values greater than 0b1001 are reserved.

DminLine, bits [19:16]

Log_2 of the number of words in the smallest cache line of all the data caches and unified caches that are controlled by the PE.

L1Ip, bits [15:14]

Level 1 instruction cache policy. Indicates the indexing and tagging policy for the L1 instruction cache. Possible values of this field are:

L1Ip	Meaning
0b00	VMID aware Physical Index, Physical tag (VPIPT)
0b01	ASID-tagged Virtual Index, Virtual Tag (AIVIVT)
0b10	Virtual Index, Physical Tag (VIPT)
0b11	Physical Index, Physical Tag (PIPT)

The value 0b01 is reserved in Armv8.

The value 0b00 is permitted only in an implementation that includes ARMv8.2-PIPTV, otherwise the value is reserved.

Bits [13:4]

Reserved, RES0.

IminLine, bits [3:0]

Log_2 of the number of words in the smallest cache line of all the instruction caches that are controlled by the PE.

Accessing the CTR_EL0

Accesses to this register use the following encodings:

```
MRS <Xt>, CTR_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b0000	0b0000	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && SCTLR_EL1.UCT ==
'0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HCR_EL2.TID2 == '1'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HFGRTR_EL2.CTR_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCTLR_EL2.UCT ==
'0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CTR_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.CTR_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return CTR_EL0;
elsif PSTATE.EL == EL2 then
    return CTR_EL0;
elsif PSTATE.EL == EL3 then
    return CTR_EL0;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CurrentEL, Current Exception Level

The CurrentEL characteristics are:

Purpose

Holds the current Exception level.

Configuration

There are no configuration notes.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CurrentEL is a 64-bit register.

Field descriptions

The CurrentEL bit assignments are:



Bits [63:4]

Reserved, RES0.

EL, bits [3:2]

Current Exception level. Possible values of this field are:

EL	Meaning
0b00	EL0
0b01	EL1
0b10	EL2
0b11	EL3

When the HCR_EL2.NV bit is 1, EL1 read accesses to the CurrentEL register return the value of 0b10 in this field.

This field resets to the highest implemented Exception Level.

Bits [1:0]

Reserved, RES0.

Accessing the CurrentEL

Accesses to this register use the following encodings:

MRS <Xt>, CurrentEL

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0010	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        return Zeros(60):'10':Zeros(2);
    else
        return Zeros(60):PSTATE.EL:Zeros(2);
elsif PSTATE.EL == EL2 then
    return Zeros(60):PSTATE.EL:Zeros(2);
elsif PSTATE.EL == EL3 then
    return Zeros(60):PSTATE.EL:Zeros(2);
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DACR32_EL2, Domain Access Control Register

The DACR32_EL2 characteristics are:

Purpose

Allows access to the AArch32 DACR register from AArch64 state only. Its value has no effect on execution in AArch64 state.

Configuration

AArch64 System register DACR32_EL2 bits [31:0] are architecturally mapped to AArch32 System register DACR[31:0] .

ThisIf registerEL1 isdoes presentnot only whensupport AArch32 is supported at any Exception level. Otherwise, directthis accessesregister to DACR32_EL2 areis UNDEFINED.

If EL2 is not implemented but EL3 is implemented, and EL1 is capable of using AArch32, then this register is not RES0.

RW fields in this register reset to architecturally UNKNOWN values.

Attributes

DACR32_EL2 is a 64-bit register.

Field descriptions

The DACR32_EL2 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
D15		D14		D13		D12		D11		D10		D9		D8		D7		D6		D5		D4		D3		D2		D1		D0	
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

D<n>, bits [2n+1:2n], for n = 0 to 15

Domain n access permission, where n = 0 to 15. Permitted values are:

D<n>	Meaning
0b00	No access. Any access to the domain generates a Domain fault.
0b01	Client. Accesses are checked against the permission bits in the translation tables.
0b11	Manager. Accesses are not checked against the permission bits in the translation tables.

The value 0b10 is reserved.

This field resets to an architecturally UNKNOWN value.

Accessing the DACR32_EL2

Accesses to this register use the following encodings:

MRS <Xt>, DACR32_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b0011	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return DACR32_EL2;
elsif PSTATE.EL == EL3 then
    return DACR32_EL2;
```

MSR DACR32_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0011	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    DACR32_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    DACR32_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DAIF, Interrupt Mask Bits

The DAIF characteristics are:

Purpose

Allows access to the interrupt mask bits.

Configuration

There are no configuration notes.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DAIF is a 64-bit register.

Field descriptions

The DAIF bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																						D	A	I	F	RES0					
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:10]

Reserved, RES0.

D, bit [9]

Process state D mask. The possible values of this bit are:

D	Meaning
0b0	Watchpoint, Breakpoint, and Software Step exceptions targeted at the current Exception level are not masked.
0b1	Watchpoint, Breakpoint, and Software Step exceptions targeted at the current Exception level are masked.

When the target Exception level of the debug exception is higher than the current Exception level, the exception is not masked by this bit.

This field resets to 1.

A, bit [8]

SError interrupt mask bit. The possible values of this bit are:

A	Meaning
0b0	Exception not masked.
0b1	Exception masked.

This field resets to 1.

I, bit [7]

IRQ mask bit. The possible values of this bit are:

I	Meaning
0b0	Exception not masked.
0b1	Exception masked.

This field resets to 1.

F, bit [6]

FIQ mask bit. The possible values of this bit are:

F	Meaning
0b0	Exception not masked.
0b1	Exception masked.

This field resets to 1.

Bits [5:0]

Reserved, RES0.

Accessing the DAIF

~~For details on the operation of the MSR (immediate) accessor, see MSR (immediate) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

```
MRS <Xt>, DAIF
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && ((EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') || SCTLR_EL1.UMA ==
'0') then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        return Zeros(54):PSTATE.<D,A,I,F>:Zeros(6);
elsif PSTATE.EL == EL1 then
    return Zeros(54):PSTATE.<D,A,I,F>:Zeros(6);
elsif PSTATE.EL == EL2 then
    return Zeros(54):PSTATE.<D,A,I,F>:Zeros(6);
elsif PSTATE.EL == EL3 then
    return Zeros(54):PSTATE.<D,A,I,F>:Zeros(6);
```

```
MSR DAIF, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && ((EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') || SCTLR_EL1.UMA ==
'0') then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        PSTATE.<D,A,I,F> = X[t]<9:6>;
elsif PSTATE.EL == EL1 then
    PSTATE.<D,A,I,F> = X[t]<9:6>;
elsif PSTATE.EL == EL2 then
    PSTATE.<D,A,I,F> = X[t]<9:6>;
elsif PSTATE.EL == EL3 then
    PSTATE.<D,A,I,F> = X[t]<9:6>;
```

MSR DAIFSet, #<imm>

op0	op1	CRn	op2
0b00	0b011	0b0100	0b110

MSR DAIFClr, #<imm>

op0	op1	CRn	op2
0b00	0b011	0b0100	0b111

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGBCR<n>_EL1, Debug Breakpoint Control Registers, n = 0 - 15

The DBGBCR<n>_EL1 characteristics are:

Purpose

Holds control information for a breakpoint. Forms breakpoint n together with value register DBGBVR<n>_EL1.

Configuration

AArch64 System register DBGBCR<n>_EL1 bits [31:0] are architecturally mapped to AArch32 System register DBGBCR<n>[31:0] .

AArch64 System register DBGBCR<n>_EL1 bits [31:0] are architecturally mapped to External register DBGBCR<n>_EL1[31:0] .

If breakpoint n is not implemented then accesses to this register are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGBCR<n>_EL1 is a 64-bit register.

Field descriptions

The DBGBCR<n>_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0								BT				LBN				SSC		HMC	RES0								BAS				RES0		PMC	E
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:24]

Reserved, RES0.

BT, bits [23:20]

Breakpoint Type. Possible values are:

BT	Meaning
0b0000	Unlinked instruction address match. DBGBVR<n>_EL1 is the address of an instruction.
0b0001	As 0b0000, but linked to a Context matching breakpoint.
0b0010	Unlinked Context ID match. When ARMv8.1-VHE is implemented, EL2 is using AArch64, and the Effective value of HCR_EL2.E2H is 1, if either the PE is executing at EL0 with HCR_EL2.TGE set to 1 or the PE is executing at EL2, then DBGBVR<n>_EL1.ContextID must match the CONTEXTIDR_EL2 value. Otherwise, DBGBVR<n>_EL1.ContextID must match the CONTEXTIDR_EL1 value
0b0011	As 0b0010, with linking enabled.
0b0110	Unlinked CONTEXTIDR_EL1 match. DBGBVR<n>_EL1.ContextID is a Context ID compared against CONTEXTIDR_EL1.
0b0111	As 0b0110, with linking enabled.
0b1000	Unlinked VMID match. DBGBVR<n>_EL1.VMID is a VMID compared against VTTBR_EL2.VMID.
0b1001	As 0b1000, with linking enabled.
0b1010	Unlinked VMID and Context ID match. DBGBVR<n>_EL1.ContextID is a Context ID compared against CONTEXTIDR_EL1, and DBGBVR<n>_EL1.VMID is a VMID compared against VTTBR_EL2.VMID.
0b1011	As 0b1010, with linking enabled.
0b1100	Unlinked CONTEXTIDR_EL2 match. DBGBVR<n>_EL1.ContextID2 is a Context ID compared against CONTEXTIDR_EL2.
0b1101	As 0b1100, with linking enabled.
0b1110	Unlinked Full Context ID match. DBGBVR<n>_EL1.ContextID is compared against CONTEXTIDR_EL1, and DBGBVR<n>_EL1.ContextID2 is compared against CONTEXTIDR_EL2.
0b1111	As 0b1110, with linking enabled.

All other values are reserved. Constraints on breakpoint programming mean other values are reserved under some conditions.

For more information on the operation of the SSC, HMC, and PMC fields, and on the effect of programming this field to a reserved value, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug) and 'Reserved DBGBCR<n>_EL1.BT values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

LBN, bits [19:16]

Linked breakpoint number. For Linked address matching breakpoints, this specifies the index of the Context-matching breakpoint linked to.

For all other breakpoint types this field is ignored and reads of the register return an UNKNOWN value.

This field is ignored when the value of DBGBCR<n>_EL1.E is 0.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

SSC, bits [15:14]

Security state control. Determines the Security states under which a Breakpoint debug event for breakpoint n is generated. This field must be interpreted along with the HMC and PMC fields, and there are constraints on the permitted values of the {HMC, SSC, PMC} fields.

For more information on the operation of the SSC, HMC, and PMC fields, and the effect of programming the fields to a reserved set of values, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug) and 'Reserved DBGBCR<n>_EL1.{SSC, HMC, PMC} values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

HMC, bit [13]

Higher mode control. Determines the debug perspective for deciding when a Breakpoint debug event for breakpoint n is generated. This field must be interpreted along with the SSC and PMC fields, and there are constraints on the permitted values of the {HMC, SSC, PMC} fields. For more information see the SSC, bits [15:14] description.

For more information on the operation of the SSC, HMC, and PMC fields, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Bits [12:9]

Reserved, RES0.

BAS, bits [8:5]

When AArch32 is supported at any Exception level:

Byte address select. Defines which half-words an address-matching breakpoint matches, regardless of the instruction set and Execution state.

~~Byte address select. Defines which half-words an address-matching breakpoint matches, regardless of the instruction set and Execution state. In an AArch64 only implementation, this field is reserved, RES1.~~

The permitted values depend on the breakpoint type.

For Address match breakpoints, the permitted values are:

BAS	Match instruction at	Constraint for debuggers
0b0011	DBGBVR<n>_EL1	Use for T32 instructions
0b1100	DBGBVR<n>_EL1 + 2	Use for T32 instructions
0b1111	DBGBVR<n>_EL1	Use for A64 and A32 instructions

All other values are reserved. For more information, see 'Reserved DBGBCR<n>_EL1.BAS values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

For more information on using the BAS field in address match breakpoints, see 'Using the BAS field in Address Match breakpoints' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

For Context matching breakpoints, this field is RES1 and ignored.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Otherwise:

Reserved, RES1.

Bits [4:3]

Reserved, RES0.

PMC, bits [2:1]

Privilege mode control. Determines the Exception level or levels at which a Breakpoint debug event for breakpoint n is generated. This field must be interpreted along with the SSC and HMC fields, and there are constraints on the permitted values of the {HMC, SSC, PMC} fields. For more information see the DBGBCR<n>_EL1.SSC description.

For more information on the operation of the SSC, HMC, and PMC fields, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

E, bit [0]

Enable breakpoint DBGBVR<n>_EL1. Possible values are:

E	Meaning
0b0	Breakpoint disabled.
0b1	Breakpoint enabled.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Accessing the DBGBCR<n>_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, DBGBCR<n>_EL1
```

op0	op1	CRn	CRm	op2
0b10	0b000	0b0000	n[3:0]	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.DBGBCRn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1'
then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBCR_EL1[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1'
then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBCR_EL1[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL3 then
    if !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBCR_EL1[UInt(CRm<3:0>)];
```

```
MSR DBGBCR<n>_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b10	0b000	0b0000	n[3:0]	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.DBGBCRn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1'
then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBCR_EL1[UInt(CRm<3:0>)] = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1'
then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBCR_EL1[UInt(CRm<3:0>)] = X[t];
elsif PSTATE.EL == EL3 then
    if !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBCR_EL1[UInt(CRm<3:0>)] = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGBVR<n>_EL1, Debug Breakpoint Value Registers, n = 0 - 15

The DBGBVR<n>_EL1 characteristics are:

Purpose

Holds a virtual address, or a VMID and/or a context ID, for use in breakpoint matching. Forms breakpoint n together with control register DBGBCR<n>_EL1.

Configuration

AArch64 System register DBGBVR<n>_EL1 bits [31:0] are architecturally mapped to AArch32 System register DBGBVR<n>[31:0] .

AArch64 System register DBGBVR<n>_EL1 bits [63:32] are architecturally mapped to AArch32 System register DBGBXVR<n>[31:0] .

AArch64 System register DBGBVR<n>_EL1 bits [63:0] are architecturally mapped to External register DBGBVR<n>_EL1[63:0] .

If breakpoint n is not implemented then accesses to this register are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

How this register is interpreted depends on the value of DBGBCR<n>_EL1.BT.

- When DBGBCR<n>_EL1.BT is 0b000x, this register holds a virtual address.
- When DBGBCR<n>_EL1.BT is 0b001x, 0b011x, or 0b110x, this register holds a Context ID.
- When DBGBCR<n>_EL1.BT is 0b100x, this register holds a VMID.
- When DBGBCR<n>_EL1.BT is 0b101x, this register holds a VMID and a Context ID.
- When DBGBCR<n>_EL1.BT is 0b111x, this register holds two Context ID values.

For other values of DBGBCR<n>_EL1.BT, this register is RES0.

Field descriptions

The DBGBVR<n>_EL1 bit assignments are:

When DBGBCR<n>_EL1.BT == 0b000x:



RESS[14:4], bits [63:53]

Reserved, Sign extended. Software must treat this field as RES0 if the most significant bit of VA is 0 or RES0, and as RES1 if the most significant bit of VA is 1.

It is IMPLEMENTATION DEFINED whether:

- Reads return the value of the most significant bit of the VA for every bit in this field.

- Reads return the last value written.

The PE ignores this field.

VA[52:49], bits [52:49]

When ARMv8.2-LVA is implemented:

Extension to VA[48:2]. See VA[48:2] for more details.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Otherwise:

Extension to RESS[14:4]. See RESS[14:4] for more details.

VA[48:2], bits [48:2]

Bits[48:2] of the address value for comparison.

When ARMv8.2-LVA is implemented, VA[52:49] forms the upper part of the address value. Otherwise, VA[52:49] are RESS.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Bits [1:0]

Reserved, RES0.

When DBGBCR<n>_EL1.BT == 0b001x:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
ContextID																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

ContextID, bits [31:0]

Context ID value for comparison.

The value is compared against CONTEXTIDR_EL2 when ARMv8.1-VHE is implemented, HCR_EL2.E2H is 1, and either:

- The PE is executing at EL2.
- HCR_EL2.TGE is 1, the PE is executing at EL0, and EL2 is enabled in the current Security state.

Otherwise, the value is compared against CONTEXTIDR_EL1.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

When DBGBCR<n>_EL1.BT == 0b011x:



Bits [63:32]

Reserved, RES0.

ContextID, bits [31:0]

Context ID value for comparison against CONTEXTIDR_EL1.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

When DBGBCR<n>_EL1.BT == 0b100x and ~~HaveEL(~~EL2 is implemented~~):~~



Bits [63:48]

Reserved, RES0.

VMID[15:8], bits [47:40]

When ARMv8.1-VMID16 is implemented and VTCR_EL2.VS == 1:

Extension to VMID[7:0]. See DBGBVR<n>_EL1.VMID~~VMID~~[7:0] for more details.

If EL2 is using AArch32, this field is RES0.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Otherwise:

Reserved, RES0.

VMID[7:0], bits [39:32]

VMID value for comparison.

The VMID is 8 bits when~~in~~ any of the following are true:~~cases.~~

- EL2 is using AArch32.
- VTCR_EL2.VS is 0.
- ARMv8.1-VMID16 is not implemented.

~~When ARMv8.1-VMID16 is implemented and EL2 is using AArch64, it is IMPLEMENTATION DEFINED whether the VMID is 8 bits or 16 bits.~~

VMID[15:8] is RES0 if any of the following applies:

- The implementation has an 8-bit VMID.
- VTCR_EL2.VS has a value of 0.
- EL2 is using AArch32.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Bits [31:0]

Reserved, RES0.

When DBGBCR<n>_EL1.BT == 0b101x and HaveEL(EL2 is implemented:):



Bits [63:48]

Reserved, RES0.

VMID[15:8], bits [47:40]

When ARMv8.1-VMID16 is implemented and VTCR_EL2.VS == 1:

Extension to VMID[7:0]. See DBGBVR<n>_EL1.VMIDVMID[7:0] for more details.

If EL2 is using AArch32, or if the implementation has an 8-bit VMID, this field is RES0.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Otherwise:

Reserved, RES0.

VMID[7:0], bits [39:32]

VMID value for comparison.

The VMID is 8 bits whenin any of the following are true:cases.

- EL2 is using AArch32.
- VTCR_EL2.VS is 0.
- ARMv8.1-VMID16 is not implemented.

When ARMv8.1-VMID16 is implemented and EL2 is using AArch64, it is IMPLEMENTATION DEFINED whether the VMID is 8 bits or 16 bits.

VMID[15:8] is RES0 if any of the following applies:

- The implementation has an 8-bit VMID.
- VTCR_EL2.VS has a value of 0.
- EL2 is using AArch32.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

ContextID, bits [31:0]

Context ID value for comparison against CONTEXTIDR_EL1.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

When DBGBCR<n>_EL1.BT == 0b110x, EL2 is implemented and HaveEL(ARMv8.1-VHE is implemented or ARMv8.2-Debug is implementedEL2):



ContextID2, bits [63:32]

When ARMv8.1-VHE is implemented:

Context ID value for comparison against CONTEXTIDR_EL2.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Otherwise:

Reserved, RES0.

Bits [31:0]

Reserved, RES0.

When DBGBCR<n>_EL1.BT == 0b111x, HaveEL(EL2) is implemented and (ARMv8.1-VHE is implemented or ARMv8.2-Debug is implemented)::



ContextID2, bits [63:32]

When ARMv8.1-VHE is implemented:

Context ID value for comparison against CONTEXTIDR_EL2.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Otherwise:

Reserved, RES0.

ContextID, bits [31:0]

Context ID value for comparison against CONTEXTIDR_EL1.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Accessing the DBGBVR<n>_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, DBGBVR<n>_EL1
```

op0	op1	CRn	CRm	op2
0b10	0b000	0b0000	n[3:0]	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.DBGBVRn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1'
then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBVR_EL1[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1'
then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBVR_EL1[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL3 then
    if !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBVR_EL1[UInt(CRm<3:0>)];
```

```
MSR DBGBVR<n>_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b10	0b000	0b0000	n[3:0]	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.DBGBVRn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1'
then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBVR_EL1[UInt(CRm<3:0>)] = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1'
then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBVR_EL1[UInt(CRm<3:0>)] = X[t];
elsif PSTATE.EL == EL3 then
    if !ELUsingAArch32(EL1) && OSLSR_EL1.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBVR_EL1[UInt(CRm<3:0>)] = X[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f211~~6134483bd14dc8c12a99c984cbfe3431cc1c9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGCLAIMCLR_EL1, Debug CLAIM Tag Clear register

The DBGCLAIMCLR_EL1 characteristics are:

Purpose

Used by software to read the values of the CLAIM tag bits, and to clear CLAIM tag bits to 0.

The architecture does not define any functionality for the CLAIM tag bits.

Note

CLAIM tags are typically used for communication between the debugger and target software.

Used in conjunction with the DBGCLAIMSET_EL1 register.

Configuration

AArch64 System register DBGCLAIMCLR_EL1 bits [31:0] are architecturally mapped to AArch32 System register DBGCLAIMCLR[31:0] .

AArch64 System register DBGCLAIMCLR_EL1 bits [31:0] are architecturally mapped to External register DBGCLAIMCLR_EL1[31:0] .

An implementation must include eight CLAIM tag bits.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGCLAIMCLR_EL1 is a 64-bit register.

Field descriptions

The DBGCLAIMCLR_EL1 bit assignments are:



Bits [63:32]

Reserved, RES0.

Bits [31:8]

Reserved, RAZ/SBZ. Software can rely on these bits reading as zero, and must use a should-be-zero policy on writes. Implementations must ignore writes.

CLAIM, bits [7:0]

Read or clear CLAIM tag bits. Reading this field returns the current value of the CLAIM tag bits.

Writing a 1 to one of these bits clears the corresponding CLAIM tag bit to 0. This is an indirect write to the CLAIM tag bits. A single write operation can clear multiple CLAIM tag bits to 0.

Writing 0 to one of these bits has no effect.

The following resets apply:

~~On a Cold reset, this field resets to 0.~~

- On a Cold reset, this field resets to `0`.
- On a Warm reset, the value of this field is unchanged.

Accessing the DBGCLAIMCLR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, DBGCLAIMCLR_EL1
```

op0	op1	CRn	CRm	op2
0b10	0b000	0b0111	0b1001	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.DBGCLAIM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return DBGCLAIMCLR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return DBGCLAIMCLR_EL1;
elsif PSTATE.EL == EL3 then
    return DBGCLAIMCLR_EL1;
```

```
MSR DBGCLAIMCLR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b10	0b000	0b0111	0b1001	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.DBGCLAIM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        DBGCLAIMCLR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        DBGCLAIMCLR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    DBGCLAIMCLR_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDTR_EL0, Debug Data Transfer Register, half-duplex

The DBGDTR_EL0 characteristics are:

Purpose

Transfers 64 bits of data between the PE and an external debugger. Can transfer both ways using only a single register.

Configuration

AArch64 System register DBGDTR_EL0 bits [63:32] are architecturally mapped to AArch32 System register DBGDTRRXint[31:0] when written.

AArch64 System register DBGDTR_EL0 bits [63:32] are architecturally mapped to External register DBGDTRRX_EL0[31:0] when written.

AArch64 System register DBGDTR_EL0 bits [63:32] are architecturally mapped to AArch64 System register DBGDTRRX_EL0[31:0] when written.

AArch64 System register DBGDTR_EL0 bits [31:0] are architecturally mapped to AArch32 System register DBGDTRTXint[31:0] when written.

AArch64 System register DBGDTR_EL0 bits [31:0] are architecturally mapped to External register DBGDTRTX_EL0[31:0] when written.

AArch64 System register DBGDTR_EL0 bits [31:0] are architecturally mapped to AArch64 System register DBGDTRTX_EL0[31:0] when written.

AArch64 System register DBGDTR_EL0 bits [63:32] are architecturally mapped to AArch32 System register DBGDTRTXint[31:0] when read.

AArch64 System register DBGDTR_EL0 bits [63:32] are architecturally mapped to External register DBGDTRTX_EL0[31:0] when read.

AArch64 System register DBGDTR_EL0 bits [63:32] are architecturally mapped to AArch64 System register DBGDTRTX_EL0[31:0] when read.

AArch64 System register DBGDTR_EL0 bits [31:0] are architecturally mapped to AArch32 System register DBGDTRRXint[31:0] when read.

AArch64 System register DBGDTR_EL0 bits [31:0] are architecturally mapped to External register DBGDTRRX_EL0[31:0] when read.

AArch64 System register DBGDTR_EL0 bits [31:0] are architecturally mapped to AArch64 System register DBGDTRRX_EL0[31:0] when read.

Attributes

DBGDTR_EL0 is a 64-bit register.

Field descriptions

The DBGDTR_EL0 bit assignments are:



HighWord, bits [63:32]

Writes to this register set DTRRX to the value in this field and do not change RXfull.

Reads of this register:

- If RXfull is set to 1, return the last value written to DTRTX.
- If RXfull is set to 0, return an UNKNOWN value.

After the read, RXfull is cleared to 0.

LowWord, bits [31:0]

Writes to this register set DTRTX to the value in this field and set TXfull to 1.

Reads of this register:

- If RXfull is set to 1, return the last value written to DTRRX.
- If RXfull is set to 0, return an UNKNOWN value.

After the read, RXfull is cleared to 0.

Accessing the DBGDTR_EL0

Accesses to this register use the following encodings:

```
MRS <Xt>, DBGDTR_EL0
```

op0	op1	CRn	CRm	op2
0b10	0b011	0b0000	0b0100	0b000

```
if Halted() then
    return DBGDTR_EL0;
elsif PSTATE.EL == EL0 then
    if !Halted() && !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' ||
MDCR_EL2.<TDE,TDA> != '00') then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return DBGDTR_EL0;
elsif PSTATE.EL == EL1 then
    if !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return DBGDTR_EL0;
elsif PSTATE.EL == EL2 then
    if !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return DBGDTR_EL0;
elsif PSTATE.EL == EL3 then
    return DBGDTR_EL0;
```

MSR DBGDTR_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b10	0b011	0b0000	0b0100	0b000

```
if Halted() then
    DBGDTR_EL0 = X[t];
elsif PSTATE.EL == EL0 then
    if !Halted() && !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' ||
MDCR_EL2.<TDE,TDA> != '00') then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        DBGDTR_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        DBGDTR_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        DBGDTR_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    DBGDTR_EL0 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDTRRX_EL0, Debug Data Transfer Register, Receive

The DBGDTRRX_EL0 characteristics are:

Purpose

Transfers data from an external debugger to the PE. For example, it is used by a debugger transferring commands and data to a debug target. See DBGDTR_EL0 for additional architectural mappings. It is a component of the Debug Communications Channel.

Configuration

AArch64 System register DBGDTRRX_EL0 bits [31:0] are architecturally mapped to AArch32 System register DBGDTRRXint[31:0] .

AArch64 System register DBGDTRRX_EL0 bits [31:0] are architecturally mapped to External register DBGDTRRX_EL0[31:0] .

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGDTRRX_EL0 is a 64-bit register.

Field descriptions

The DBGDTRRX_EL0 bit assignments are:



Bits [63:32]

Reserved, RES0.

Bits [31:0]

Update DTRRX.

Reads of this register:

- If RXfull is set to 1, return the last value written to DTRRX.
- If RXfull is set to 0, return an UNKNOWN value.

After the read, RXfull is cleared to 0.

For the full behavior of the Debug Communications Channel, see The Debug Communication Channel and Instruction Transfer Register.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.

- On a Warm reset, the value of this field is unchanged.

Accessing the DBGDTRRX_EL0

Accesses to this register use the following encodings:

```
MRS <Xt>, DBGDTRRX_EL0
```

op0	op1	CRn	CRm	op2
0b10	0b011	0b0000	0b0101	0b000

```
if Halted() then
    return DBGDTRRX_EL0;
elsif PSTATE.EL == EL0 then
    if !Halted() && !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' ||
MDCR_EL2.<TDE,TDA> != '00') then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return DBGDTRRX_EL0;
elsif PSTATE.EL == EL1 then
    if !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return DBGDTRRX_EL0;
elsif PSTATE.EL == EL2 then
    if !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return DBGDTRRX_EL0;
elsif PSTATE.EL == EL3 then
    return DBGDTRRX_EL0;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDTRTX_EL0, Debug Data Transfer Register, Transmit

The DBGDTRTX_EL0 characteristics are:

Purpose

Transfers data from the PE to an external debugger. For example, it is used by a debug target to transfer data to the debugger. See DBGDTR_EL0 for additional architectural mappings. It is a component of the Debug Communication Channel.

Configuration

AArch64 System register DBGDTRTX_EL0 bits [31:0] are architecturally mapped to AArch32 System register DBGDTRTXint[31:0] .

AArch64 System register DBGDTRTX_EL0 bits [31:0] are architecturally mapped to External register DBGDTRTX_EL0[31:0] .

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGDTRTX_EL0 is a 64-bit register.

Field descriptions

The DBGDTRTX_EL0 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
Return DTRTX																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

Bits [31:0]

Return DTRTX.

Writes to this register:

- If TXfull is set to 1, set DTRRX and DTRTX to UNKNOWN.
- If TXfull is set to 0, update the value in DTRTX.

After the write, TXfull is set to 1.

For the full behavior of the Debug Communications Channel, see The Debug Communication Channel and Instruction Transfer Register.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.

- On a Warm reset, the value of this field is unchanged.

Accessing the DBGDTRTX_EL0

Accesses to this register use the following encodings:

```
MSR DBGDTRTX_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b10	0b011	0b0000	0b0101	0b000

```
if Halted() then
    DBGDTRTX_EL0 = X[t];
elsif PSTATE.EL == EL0 then
    if !Halted() && !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' ||
MDCR_EL2.<TDE,TDA> != '00') then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        DBGDTRTX_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        DBGDTRTX_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        DBGDTRTX_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    DBGDTRTX_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGVCR32_EL2, Debug Vector Catch Register

The DBGVCR32_EL2 characteristics are:

Purpose

Allows access to the AArch32 register DBGVCR from AArch64 state only. Its value has no effect on execution in AArch64 state.

Configuration

AArch64 System register DBGVCR32_EL2 bits [31:0] are architecturally mapped to AArch32 System register DBGVCR[31:0] .

ThisIf registerEL1 isdoes presentnot only whensupport AArch32 is supported at any Exception level. Otherwise, directthis accessesregister to DBGVCR32_EL2 areis UNDEFINED.

If EL2 is not implemented but EL3 is implemented, and EL1 is capable of using AArch32, then this register is not RES0.

~~This register has no effect if EL2 is not enabled in the current Security state.~~

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGVCR32_EL2 is a 64-bit register.

Field descriptions

The DBGVCR32_EL2 bit assignments are:

When ~~HaveEL(~~EL3~~)~~ isand implemented:~~!ELUsingAArch32(EL3):~~

63	62	61	60	59	58	57	56 55 54 53 52 51 50 49 48 47 46 45 44 43 42 41 40 39 38	37	36	35	34	33	32
RES0													
NSF	NSI	RES0	NSD	NSP	NSS	NSU	RES0	SF	SI	RES0	SD	SP	SS	SU	RES0
31	30	29	28	27	26	25	24 23 22 21 20 19 18 17 16 15 14 13 12 11 10 9 8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

NSF, bit [31]

FIQ vector catch enable in Non-secure state.

The exception vector offset is 0x1C.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSI, bit [30]

IRQ vector catch enable in Non-secure state.

The exception vector offset is 0x18.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [29]

Reserved, RES0.

NSD, bit [28]

Data Abort vector catch enable in Non-secure state.

The exception vector offset is `0x10`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSP, bit [27]

Prefetch Abort vector catch enable in Non-secure state.

The exception vector offset is `0x0C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSS, bit [26]

Supervisor Call (SVC) vector catch enable in Non-secure state.

The exception vector offset is `0x08`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSU, bit [25]

Undefined Instruction vector catch enable in Non-secure state.

The exception vector offset is `0x04`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bits [24:8]

Reserved, RES0.

SF, bit [7]

FIQ vector catch enable in Secure state.

The exception vector offset is `0x1C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SI, bit [6]

IRQ vector catch enable in Secure state.

The exception vector offset is `0x18`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [5]

Reserved, RES0.

SD, bit [4]

Data Abort vector catch enable in Secure state.

The exception vector offset is `0x10`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SP, bit [3]

Prefetch Abort vector catch enable in Secure state.

The exception vector offset is `0x0C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SS, bit [2]

Supervisor Call (SVC) vector catch enable in Secure state.

The exception vector offset is `0x08`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SU, bit [1]

Undefined Instruction vector catch enable in Secure state.

The exception vector offset is `0x04`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [0]

Reserved, RES0.

When ~~!HaveEL(~~EL3 is not implemented:~~):~~

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																								F	I	RES0	D	P	S	U	RES0
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:8]

Reserved, RES0.

F, bit [7]

FIQ vector catch enable.

The exception vector offset is `0x1C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

I, bit [6]

IRQ vector catch enable.

The exception vector offset is `0x18`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [5]

Reserved, RES0.

D, bit [4]

Data Abort vector catch enable.

The exception vector offset is `0x10`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P, bit [3]

Prefetch Abort vector catch enable.

The exception vector offset `0x0C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

S, bit [2]

Supervisor Call (SVC) vector catch enable.

The exception vector offset is `0x08`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

U, bit [1]

Undefined Instruction vector catch enable.

The exception vector offset is `0x04`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [0]

Reserved, RES0.

Accessing the DBGVCR32_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, DBGVCR32_EL2
```

op0	op1	CRn	CRm	op2
0b10	0b100	0b0000	0b0111	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return DBGVCR32_EL2;
elsif PSTATE.EL == EL3 then
    return DBGVCR32_EL2;
```

MSR DBGVCR32_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b10	0b100	0b0000	0b0111	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        DBGVCR32_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    DBGVCR32_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DC CGDVADP, Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoDP

The DC CGDVADP characteristics are:

Purpose

Clean Allocation Tags and data in data cache by address to Point of Deep Persistence.

If the memory system does not identify a Point of Deep Persistence, then this instruction behaves as a DC CGDVAP~~DC CGVAP~~.

Configuration

This instruction is present only when ARMv8.2-DCCVADP is implemented and ARMv8.5-MemTag is implemented. Otherwise, direct accesses to DC CGDVADP are UNDEFINED.

Attributes

DC CGDVADP is a 64-bit System instruction.

Field descriptions

The DC CGDVADP input value bit assignments are:



Bits [63:0]

Virtual address to use. No alignment restrictions apply to this VA.

Executing the DC CGDVADP instruction

If EL0 access is enabled, when executed at EL0, this instruction requires read access permission to the VA, otherwise it generates a Permission Fault, see 'Permission fault' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Execution of this instruction might require an address translation from VA to PA, and that translation might fault. For more information, see 'The data cache maintenance instruction (DC)' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Accesses to this instruction use the following encodings:

```
DC CGDVADP, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b011	0b0111	0b1101	0b101

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && SCTLR_EL1.UCI ==
'0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HCR_EL2.TPCP == '1'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HFGITR_EL2.DCCVADP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCTLR_EL2.UCI ==
'0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        DC_CGDVADP(X[t]);
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TPCP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.DCCVADP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        DC_CGDVADP(X[t]);
elsif PSTATE.EL == EL2 then
    DC_CGDVADP(X[t]);
elsif PSTATE.EL == EL3 then
    DC_CGDVADP(X[t]);
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DC ZVA, Data Cache Zero by VA

The DC ZVA characteristics are:

Purpose

Zero data cache by address. Zeroes a naturally aligned block of N bytes, where the size of N is identified in DCZID_EL0.

Configuration

There are no configuration notes.

Attributes

DC ZVA is a 64-bit System instruction.

Field descriptions

The DC ZVA input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Virtual address to use																															
Virtual address to use																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Virtual address to use. There is no alignment restriction on the address within the block of N bytes that is used.

Executing the DC ZVA instruction

When this instruction is executed, it can generate memory faults or watchpoints which are prioritized in the same way as other memory-related faults or watchpoints. If a synchronous data abort fault or a watchpoint is generated, the CM bit in the ESR_ELx.ISS field is set to 0.

If the memory region being zeroed is any type of Device memory, this instruction can give an Alignment fault which is prioritized in the same way as other Alignment faults that are determined by the memory type.

This instruction applies to Normal memory regardless of cacheability attributes.

This instruction behaves as a set of Stores to each byte within the block being accessed, and so it:

- Generates a Permission Fault if the translation system does not permit writes to the locations.
- Requires the same considerations for ordering and the management of coherency as any other store instructions.

Accesses to this instruction use the following encodings:

```
DC ZVA, <Xt>
```

op0	op1	CRn	CRm	op2
0b01	0b011	0b0111	0b0100	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && SCTLR_EL1.DZE ==
'0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HCR_EL2.TDZ == '1'
then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HFGITR_EL2.DCZVA == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCTLR_EL2.DZE ==
'0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        DC_ZVA(X[t]);
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TDZ == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.DCZVA == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        DC_ZVA(X[t]);
elsif PSTATE.EL == EL2 then
    DC_ZVA(X[t]);
elsif PSTATE.EL == EL3 then
    DC_ZVA(X[t]);
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DCZID_EL0, Data Cache Zero ID register

The DCZID_EL0 characteristics are:

Purpose

Indicates the block size that is written with byte values of 0 by the DC ZVA (Data Cache Zero by Address) System instruction.

If ARMv8.5-MemTag is implemented, this register also indicates the granularity at which the DC GVA and DC GZVA instructions write.

Configuration

There are no configuration notes.

Attributes

DCZID_EL0 is a 64-bit register.

Field descriptions

The DCZID_EL0 bit assignments are:



Bits [63:5]

Reserved, RES0.

DZP, bit [4]

Data Zero Prohibited. This field indicates whether use of DC ZVA instructions is permitted or prohibited.

If ARMv8.5-MemTag is implemented, this field also indicates whether use of the DC GVA and DC GZVA instructions are permitted or prohibited.

DZP	Meaning
0b0	Instructions are permitted.
0b1	Instructions are prohibited.

The value read from this field is governed by the access state and the values of the HCR_EL2.TDZ and SCTLR_EL1.DZE bits.

BS, bits [3:0]

Log_2 of the block size in words. The maximum size supported is 2KB (value == 9).

Accessing the DCZID_EL0

Accesses to this register use the following encodings:

MRS <Xt>, DCZID_EL0

op0	op1	CRn	CRm	op2
0b11	0b011	0b0000	0b0000	0b111

```
if PSTATE.EL == EL0 then
    if EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HFGRTR_EL2.DCZID_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return DCZID_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.DCZID_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return DCZID_EL0;
elsif PSTATE.EL == EL2 then
    return DCZID_EL0;
elsif PSTATE.EL == EL3 then
    return DCZID_EL0;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DIT, Data Independent Timing

The DIT characteristics are:

Purpose

Allows access to the Data Independent Timing bit.

Configuration

This register is present only when ARMv8.4-DIT is implemented. Otherwise, direct accesses to DIT are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DIT is a 64-bit register.

Field descriptions

The DIT bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0							DIT	RES0																							
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:25]

Reserved, RES0.

DIT, bit [24]

Data Independent Timing.

DIT	Meaning
0b0	The architecture makes no statement about the timing properties of any instructions.
0b1	The architecture requires that: • The timing of every load and store instruction is insensitive to the value of the data being loaded or stored. • For certain data processing instructions, the instruction takes a time which is independent of: ◦ The values of the data supplied in any of its registers. ◦ The values of the NZCV flags. • For certain data processing instructions, the response of the instruction to asynchronous exceptions does not vary based on: ◦ The values of the data supplied in any of its registers. ◦ The values of the NZCV flags.

The data processing instructions affected by this bit are:

- All cryptographic instructions. These instructions are:

    - AESD, AESE, AESIMC, AESMC, SHA1C, SHA1H, SHA1M, SHA1P, SHA1SU0, SHA1SU1, SHA256H, SHA256H2, SHA256SU0, SHA256SU1, SHA512H, SHA512H2, SHA512SU0, SHA512SU1, EOR3, RAX1, XAR, BCAX, SM3SS1, SM3TT1A, SM3TT1B, SM3TT2A, SM3TT2B, SM3PARTW1, SM3PARTW2, SM4E, and SM4EKEY.

- A subset of those instructions which use the general-purpose register file. These instructions are:

    - ADC, ADCS, ADD, ADDS, AND, ANDS, ASR, ASRV, BFC, BFI, BFM, BFXIL, BIC, BICS, CCMN, CCMP, CFINV, CINC, CINV, CLS, CLZ, CMN, CMP, CNEG, CSEL, CSET, CSETM, CSINC, CSINV, CSNEG, EON, EOR, EXTR, LSL, LSLV, LSR, LSRV, MADD, MNEG, MOV, MOVK, MOVN, MOVZ, MSUB, MUL, MVN, NEG, NEGS, NGC, NGCS, NOP, ORN, ORR, RBIT, RET, REV, REV16, REV32, REV64, RMIF, ROR, RORV, SBC, SBCS, SBFIZ, SBFM, SBFX, SETF8, SETF16, SMADDL, SMNEGL, SMSUBL, SMULH, SMULL, SUB, SUBS, SXTB, SXTH, SXTW, TST, UBFIZ, UBFM, UBFX, UMADDL, UMNEGL, UMSUBL, UMULH, UMULL, UXTB, and UXTH.

- A subset of those instuctions which use the SIMD&FP register file. These instructions are:

    - ABS, ADD, ADDHN, ADDHN2, ADDP, ADDV, AND, BIC, BIF, BIT, BSL, CLS, CLZ, CMEQ, CMGE, CMGT, CMHI, CMHS, CMLE, CMLT, CMTST, CNT, CRC32B, CRC32H, CRC32W, CRC32X, CRC32CB, CRC32CH, CRC32CW, CRC32CX, DUP, EOR, EXT, FCSEL, INS, MLA, MLS, MOV, MOVI, MUL, MVN, MVNI, NEG, NOT, ORN, ORR, PMUL, PMULL, PMULL2, RADDHN, RADDHN2, RBIT, REV16, REV32, RSHRN, RSHRN2, RSUBHN, RSUBHN2, SABA, SABD, SABAL, SABAL2, SABDL, SABDL2, SADALP, SADDL, SADDL2, SADDLP, SADDLV, SADDW, SADDW2, SHADD, SHL, SHLL, SHLL2, SHRN, SHRN2, SHSUB, SLI, SMAX, SMAXP, SMAXV, SMIN, SMINP, SMINV, SMLAL, SMLAL2, SMLSL, SMLSL2, SMOV, SMULL, SMULL2, SRI, SSHL, SSHLL, SSHLL2, SSHR, SSRA, SSUBL, SSUBL2, SSUBW, SSUBW2, SUB, SUBHN, SUBHN2, SXTL, SXTL2, TBL, TBX, TRN1, TRN2, UABA, UABAL, UABAL2, UABD, UABDL, UABDL2, UADALP, UADDL, UADDL2, UADDLP, UADDLV, UADDW, UADDW2, UHADD, UHSUB, UMAX, UMAXP, UMAXV, UMIN, UMINP, UMINV, UMLAL, UMLAL2, UMLSL, UMOV, UMLSL2, UMULL, UMULL2, USHL, USHLL, USHLL2, USHR, USRA, USUBL, USUBL2, USUBW, USUBW2, UXTL, UXTL2, UZP1, UZP2, XTN, XTN2, ZIP1, and ZIP2.

Note

The architecture makes no statement about the timing properties when the PSTATE.DIT bit is not set. However, it is likely that many of these instructions have timing that is invariant of the data in many situations.

In particular, Arm strongly recommends that the Armv8.3 pointer authentication instructions do not have their timing dependent on the key value used in the pointer authentication in all cases, regardless of the PSTATE.DIT bit.

This field resets to 0.

Bits [23:0]

Reserved, RES0.

Accessing the DIT

~~For details on the operation of the MSR (immediate) accessor, see MSR (immediate) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

```
MRS <Xt>, DIT
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0010	0b101

```
if PSTATE.EL == EL0 then
    return Zeros(39):PSTATE.DIT:Zeros(24);
elsif PSTATE.EL == EL1 then
    return Zeros(39):PSTATE.DIT:Zeros(24);
elsif PSTATE.EL == EL2 then
    return Zeros(39):PSTATE.DIT:Zeros(24);
elsif PSTATE.EL == EL3 then
    return Zeros(39):PSTATE.DIT:Zeros(24);
```

MSR DIT, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0010	0b101

```
if PSTATE.EL == EL0 then
    PSTATE.DIT = X[t]<24>;
elsif PSTATE.EL == EL1 then
    PSTATE.DIT = X[t]<24>;
elsif PSTATE.EL == EL2 then
    PSTATE.DIT = X[t]<24>;
elsif PSTATE.EL == EL3 then
    PSTATE.DIT = X[t]<24>;
```

MSR DIT, #<imm>

op0	op1	CRn	op2
0b00	0b011	0b0100	0b010

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DSPSR_EL0, Debug Saved Program Status Register

The DSPSR_EL0 characteristics are:

Purpose

Holds the saved process state for Debug state. On entering Debug state, PSTATE information is written to this register. On exiting Debug state, values are copied from this register to PSTATE.

Configuration

AArch64 System register DSPSR_EL0 bits [31:0] are architecturally mapped to AArch32 System register DSPSR[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DSPSR_EL0 is a 64-bit register.

Field descriptions

The DSPSR_EL0 bit assignments are:

When AArch32 is supported at any Exception level and exiting Debug state to AArch32 state:



Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Copied to PSTATE.N on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Copied to PSTATE.Z on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Copied to PSTATE.C on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Copied to PSTATE.V on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Copied to PSTATE.Q on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Copied to PSTATE.IT[1:0] on exiting Debug state.

On exiting Debug state DSPSR_EL0.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

DIT, bit [24]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Copied to PSTATE.DIT on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Copied to PSTATE.SSBS on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Copied to PSTATE.PAN on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SS, bit [21]

Software Step. Copied to PSTATE.SS on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

IL, bit [20]

Illegal Execution state. Copied to PSTATE.IL on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Copied to PSTATE.GE on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Copied to PSTATE.IT[7:2] on exiting Debug state.

DSPSR_EL0.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Copied to PSTATE.E on exiting Debug state.

If the implementation does not support big-endian operation, DSPSR_EL0.E is RES0. If the implementation does not support little-endian operation, DSPSR_EL0.E is RES1. On exiting Debug state, if the implementation does not support big-endian operation at the Exception level being returned to, DSPSR_EL0.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, DSPSR_EL0.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Copied to PSTATE.A on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Copied to PSTATE.I on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Copied to PSTATE.F on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Copied to PSTATE.T on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

M[4], bit [4]

Execution state. Copied to PSTATE.nRW on exiting Debug state.

M[4]	Meaning
0b1	AArch32 execution state.

This field resets to an architecturally UNKNOWN value.

M[3:0], bits [3:0]

AArch32 Mode. Copied to PSTATE.M[3:0] on exiting Debug state.

M[3:0]	Meaning
0b0000	User.
0b0001	FIQ.
0b0010	IRQ.
0b0011	Supervisor.
0b0110	Monitor.
0b0111	Abort.
0b1010	Hyp.
0b1011	Undefined.
0b1111	System.

Other values are reserved. If DSPSR_EL0.M[3:0] has a Reserved value, or a value for an unimplemented Exception level, exiting Debug state is an illegal return event, as described in 'Illegal return events from AArch64 state' in the Arm®Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

When AArch64 is supported at any Exception level and entering Debug state from AArch64 state and exiting Debug state to AArch64 state:



Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on entering Debug state, and copied to PSTATE.N on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on entering Debug state, and copied to PSTATE.Z on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on entering Debug state, and copied to PSTATE.C on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on entering Debug state, and copied to PSTATE.V on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Bits [27:26]

Reserved, RES0.

TCO, bit [25]

When ARMv8.5-MemTag is implemented:

Tag Check Override. Set to the value of PSTATE.TCO on entering Debug state, and copied to PSTATE.TCO on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [24]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on entering Debug state, and copied to PSTATE.DIT on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

UAO, bit [23]

When ARMv8.2-UAO is implemented:

User Access Override. Set to the value of PSTATE.UAO on entering Debug state, and copied to PSTATE.UAO on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on entering Debug state, and copied to PSTATE.PAN on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SS, bit [21]

Software Step. Set to the value of PSTATE.SS on entering Debug state, and conditionally copied to PSTATE.SS on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on entering Debug state, and copied to PSTATE.IL on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Bits [19:13]

Reserved, RES0.

SSBS, bit [12]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on entering Debug state, and copied to PSTATE.SSBS on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

BTYPE, bits [11:10]

When ARMv8.5-BTI is implemented:

Branch Type Indicator. Set to the value of PSTATE.BTYPE on entering Debug state, and copied to PSTATE.BTYPE on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

D, bit [9]

Debug exception mask. Set to the value of PSTATE.D on entering Debug state, and copied to PSTATE.D on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on entering Debug state, and copied to PSTATE.A on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on entering Debug state, and copied to PSTATE.I on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on entering Debug state, and copied to PSTATE.F on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Bit [5]

Reserved, RES0.

M[4], bit [4]

When AArch32 is supported at any Exception level:

Execution state. Set to `0b0`, the value of PSTATE.nRW, on entering Debug state from AArch64 state, and copied to PSTATE.nRW on exiting Debug state.

M[4]	Meaning
`0b0`	AArch64 execution state.

~~If AArch32 is not supported at any Exception level, this bit is RES0.~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

M[3:0], bits [3:0]

AArch64 Exception level and selected Stack Pointer.

M[3:0]	Meaning
`0b0000`	EL0t.
`0b0100`	EL1t.
`0b0101`	EL1h.
`0b1000`	EL2t.
`0b1001`	EL2h.
`0b1100`	EL3t.
`0b1101`	EL3h.

Other values are reserved. If DSPSR_EL0.M[3:0] has a Reserved value, or a value for an unimplemented Exception level, exiting Debug state is an illegal return event, as described in 'Illegal return events from AArch64 state' in the Arm®Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The bits in this field are interpreted as follows:

- M[3:2] is set to the value of PSTATE.EL on entering Debug state and copied to PSTATE.EL on exiting Debug state.
- M[1] is unused and is 0 for all non-reserved values.
- M[0] is set to the value of PSTATE.SP on entering Debug state and copied to PSTATE.SP on exiting Debug state

This field resets to an architecturally UNKNOWN value.

Accessing the DSPSR_EL0

Accesses to this register use the following encodings:

```
MRS <Xt>, DSPSR_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0101	0b000

```
if !Halted() then
    UNDEFINED;
else
    return DSPSR_EL0;
```

```
MSR DSPSR_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0101	0b000

```
if !Halted() then
    UNDEFINED;
else
    DSPSR_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ELR_EL1, Exception Link Register (EL1)

The ELR_EL1 characteristics are:

Purpose

When taking an exception to EL1, holds the address to return to.

Configuration

There are no configuration notes.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ELR_EL1 is a 64-bit register.

Field descriptions

The ELR_EL1 bit assignments are:



Bits [63:0]

Return address.

An exception return from EL1 using AArch64 makes ELR_EL1 become UNKNOWN.

This field resets to an architecturally UNKNOWN value.

Accessing the ELR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic ELR_EL1 or ELR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, ELR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x230];
    else
        return ELR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return ELR_EL2;
    else
        return ELR_EL1;
elsif PSTATE.EL == EL3 then
    return ELR_EL1;
```

MSR ELR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x230] = X[t];
    else
        ELR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        ELR_EL2 = X[t];
    else
        ELR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ELR_EL1 = X[t];
```

MRS <Xt>, ELR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0100	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x230];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return ELR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return ELR_EL1;
    else
        UNDEFINED;
```

MSR ELR_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b0100	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x230] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        ELR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        ELR_EL1 = X[t];
    else
        UNDEFINED;
```

MRS <Xt>, ELR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return ELR_EL1;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return ELR_EL2;
elsif PSTATE.EL == EL3 then
    return ELR_EL2;
```

MSR ELR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        ELR_EL1 = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    ELR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    ELR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ELR_EL3, Exception Link Register (EL3)

The ELR_EL3 characteristics are:

Purpose

When taking an exception to EL3, holds the address to return to.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to ELR_EL3 are UNDEFINED.

Attributes

ELR_EL3 is a 64-bit register.

Field descriptions

The ELR_EL3 bit assignments are:



Bits [63:0]

Return address.

An exception return from EL3 using AArch64 makes ELR_EL3 become UNKNOWN.

This field resets to an architecturally UNKNOWN value.

Accessing the ELR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, ELR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0100	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return ELR_EL3;
```

```
MSR ELR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0100	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    ELR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRIDR_EL1, Error Record ID Register

The ERRIDR_EL1 characteristics are:

Purpose

Defines the highest numbered index of the error records that can be accessed through the Error Record System registers.

Configuration

AArch64 System register ERRIDR_EL1 bits [31:0] are architecturally mapped to AArch32 System register ERRIDR[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRIDR_EL1 are UNDEFINED.

Attributes

ERRIDR_EL1 is a 64-bit register.

Field descriptions

The ERRIDR_EL1 bit assignments are:



Bits [63:16]

Reserved, RES0.

NUM, bits [15:0]

Highest numbered index of the records that can be accessed through the Error Record System registers plus one. Zero indicates ~~that~~ no records can be accessed through the Error Record System registers.

Each implemented record is owned by a node. A node might own multiple records.

Accessing the ERRIDR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ERRIDR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERRIDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERRIDR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERRIDR_EL1;
elsif PSTATE.EL == EL3 then
    return ERRIDR_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRSELR_EL1, Error Record Select Register

The ERRSELR_EL1 characteristics are:

Purpose

Selects an error record to be accessed through the Error Record System registers.

Configuration

AArch64 System register ERRSELR_EL1 bits [31:0] are architecturally mapped to AArch32 System register ERRSELR[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRSELR_EL1 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

If ERRIDR_EL1 indicates that zero error records are implemented, then it is IMPLEMENTATION DEFINED whether ERRSELR_EL1 is UNDEFINED or RES0.

Attributes

ERRSELR_EL1 is a 64-bit register.

Field descriptions

The ERRSELR_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																SEL															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:16]

Reserved, RES0.

SEL, bits [15:0]

Selects the error record accessed through the ERX registers.

For example, if ERRSELR_EL1.SEL is set to 0x0004~~0~~x4, then direct reads and writes of ERXSTATUS_EL1 ~~, then direct reads and writes of ERXSTATUS_EL1~~ access ERR4STATUS.

If ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then all of the following apply:

- The value read back from ERRSELR_EL1.SEL is UNKNOWN.
- ~~The value read back from ERRSELR_EL1.SEL is UNKNOWN.~~
- ~~One of the following occurs:~~

One of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN error record is selected.~~
- ~~The ERX* registers are RAZ/WI.~~

The ERX*_EL1 registers are RAZ/WI.

- ~~ERX* register reads and writes are NOPs.~~

ERX*_EL1 register reads and writes are NOPs.

- ERX*_EL1 register reads and writes are UNDEFINED.
- ~~ERX* register reads and writes are UNDEFINED.~~

This field resets to an architecturally UNKNOWN value.

Accessing the ERRSELR_EL1

Accesses to this register use the following encodings:

MRS <Xt>, ERRSELR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERRSELR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERRSELR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERRSELR_EL1;
elsif PSTATE.EL == EL3 then
    return ERRSELR_EL1;
```

MSR ERRSELR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ERRSELR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERRSELR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERRSELR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ERRSELR_EL1 = X[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXADDR_EL1, Selected Error Record Address Register

The ERXADDR_EL1 characteristics are:

Purpose

Accesses ERR<n>ADDR for the error record <n> selected by ERRSELR_EL1.SEL.

Configuration

AArch64 System register ERXADDR_EL1 bits [31:0] are architecturally mapped to AArch32 System register ERXADDR[31:0] .

AArch64 System register ERXADDR_EL1 bits [63:32] are architecturally mapped to AArch32 System register ERXADDR2[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXADDR_EL1 are UNDEFINED.

Attributes

ERXADDR_EL1 is a 64-bit register.

Field descriptions

The ERXADDR_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ERR<n>ADDR																															
ERR<n>ADDR																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

ERXADDR_EL1 accesses ERR<n>ADDR, where <n> is the value in ERRSELR_EL1.SEL.

Accessing the ERXADDR_EL1

If ERRIDR_EL1.NUM == ~~0 or~~ 0x0000 or ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN record is selected.~~
- ~~ERXADDR_EL1 is RAZ/WI.~~

  ERXADDR_EL1 is RAZ/WI.
- ~~Direct reads and writes of ERXADDR_EL1 are NOPs.~~

  Direct reads and writes of ERXADDR_EL1 are NOPs.
- Direct reads and writes of ERXADDR_EL1 are UNDEFINED.
- ~~Direct reads and writes of ERXADDR_EL1 are UNDEFINED.~~

ERR<n>ADDR describes additional constraints that also apply when ERR<n>ADDR is accessed through ERXADDR_EL1.

Accesses to this register use the following encodings:

```
MRS <Xt>, ERXADDR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERXADDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXADDR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXADDR_EL1;
elsif PSTATE.EL == EL3 then
    return ERXADDR_EL1;
```

```
MSR ERXADDR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ERXADDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXADDR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXADDR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ERXADDR_EL1 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXCTLR_EL1, Selected Error Record Control Register

The ERXCTLR_EL1 characteristics are:

Purpose

Accesses ERR<n>CTLR for the error record <n> selected by ERRSELR_EL1.SEL.

Configuration

AArch64 System register ERXCTLR_EL1 bits [31:0] are architecturally mapped to AArch32 System register ERXCTLR[31:0] .

AArch64 System register ERXCTLR_EL1 bits [63:32] are architecturally mapped to AArch32 System register ERXCTLR2[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXCTLR_EL1 are UNDEFINED.

Attributes

ERXCTLR_EL1 is a 64-bit register.

Field descriptions

The ERXCTLR_EL1 bit assignments are:



Bits [63:0]

ERXCTLR_EL1 accesses ERR<n>CTLR, where <n> is the value in ERRSELR_EL1.SEL.

Accessing the ERXCTLR_EL1

If ERRIDR_EL1.NUM == ~~0 or~~ 0x0000 or ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN record is selected.~~
- ~~ERXCTLR_EL1 is RAZ/WI.~~

  ERXCTLR_EL1 is RAZ/WI.
- ~~Direct reads and writes of ERXCTLR_EL1 are NOPs.~~

  Direct reads and writes of ERXCTLR_EL1 are NOPs.
- Direct reads and writes of ERXCTLR_EL1 are UNDEFINED.
- ~~Direct reads and writes of ERXCTLR_EL1 are UNDEFINED.~~

If ERRSELR_EL1.SEL is not the index of the first error record owned by a node, then ERR<n>CTLR is not present, meaning reads and writes of ERXCTLR_EL1 are RES0.

Accesses to this register use the following encodings:

MRS <Xt>, ERXCTLR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERXCTLR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXCTLR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXCTLR_EL1;
elsif PSTATE.EL == EL3 then
    return ERXCTLR_EL1;
```

MSR ERXCTLR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ERXCTLR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXCTLR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXCTLR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ERXCTLR_EL1 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXFR_EL1, Selected Error Record Feature Register

The ERXFR_EL1 characteristics are:

Purpose

Accesses ERR<n>FR for the error record <n> selected by ERRSELR_EL1.SEL.

Configuration

AArch64 System register ERXFR_EL1 bits [31:0] are architecturally mapped to AArch32 System register ERXFR[31:0] .

AArch64 System register ERXFR_EL1 bits [63:32] are architecturally mapped to AArch32 System register ERXFR2[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXFR_EL1 are UNDEFINED.

Attributes

ERXFR_EL1 is a 64-bit register.

Field descriptions

The ERXFR_EL1 bit assignments are:



Bits [63:0]

ERXFR_EL1 accesses ERR<n>FR, where <n> is the value in ERRSELR_EL1.SEL.

Accessing the ERXFR_EL1

If ERRIDR_EL1.NUM == ~~0 or~~ 0x0000 or ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN record is selected.~~
- ~~ERXFR_EL1 is RAZ.~~

  ERXFR_EL1 is RAZ.
- ~~Direct reads of ERXFR_EL1 are NOPs.~~

  Direct reads of ERXFR_EL1 are NOPs.
- Direct reads of ERXFR_EL1 are UNDEFINED.
- ~~Direct reads of ERXFR_EL1 are UNDEFINED.~~

Accesses to this register use the following encodings:

MRS <Xt>, ERXFR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERXFR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXFR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXFR_EL1;
elsif PSTATE.EL == EL3 then
    return ERXFR_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC0_EL1, Selected Error Record Miscellaneous Register 0

The ERXMISC0_EL1 characteristics are:

Purpose

Accesses ERR<n>MISC0 for the error record <n> selected by ERRSELR_EL1.SEL.

Configuration

AArch64 System register ERXMISC0_EL1 bits [31:0] are architecturally mapped to AArch32 System register ERXMISC0[31:0] .

AArch64 System register ERXMISC0_EL1 bits [63:32] are architecturally mapped to AArch32 System register ERXMISC1[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXMISC0_EL1 are UNDEFINED.

~~For IMPLEMENTATION DEFINED fields in this register, writing zero must always be supported to return the error record to an initial state.~~

~~In particular, if any IMPLEMENTATION DEFINED syndrome fields might generate a Fault Handling or Error Recovery Interrupt request, writing zero is sufficient to deactivate the Interrupt request.~~

~~Fields that are read-only, non-zero and ignore writes are compliant with this requirement.~~

~~Note~~

~~Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL, where q is the index of the first error record owned by the same node as error record n. If the node owns a single record then q = n.~~

Attributes

ERXMISC0_EL1 is a 64-bit register.

Field descriptions

The ERXMISC0_EL1 bit assignments are:



Bits [63:0]

ERXMISC0_EL1 accesses ERR<n>MISC0, where <n> is the value in ERRSELR_EL1.SEL.

Accessing the ERXMISC0_EL1

If ERRIDR_EL1.NUM == ~~0 or~~ 0x0000 or ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - ~~An UNKNOWN record is selected.~~
  - ~~ERXMISC0_EL1 is RAZ/WI.~~

    ERXMISC0_EL1 is RAZ/WI.
  - ~~Direct reads and writes of ERXMISC0_EL1 are NOPs.~~

    Direct reads and writes of ERXMISC0_EL1 are NOPs.
- Direct reads and writes of ERXMISC0_EL1 are UNDEFINED.
  - ~~Direct reads and writes of ERXMISC0_EL1 are UNDEFINED.~~

ERR<n>MISC0 describes additional constraints that also apply when ERR<n>MISC0 is accessed through ERXMISC0_EL1.

Accesses to this register use the following encodings:

```
MRS <Xt>, ERXMISC0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERXMISCn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXMISC0_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXMISC0_EL1;
elsif PSTATE.EL == EL3 then
    return ERXMISC0_EL1;
```

```
MSR ERXMISC0_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ERXMISCn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXMISC0_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXMISC0_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ERXMISC0_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC1_EL1, Selected Error Record Miscellaneous Register 1

The ERXMISC1_EL1 characteristics are:

Purpose

Accesses ERR<n>MISC1 for the error record <n> selected by ERRSELR_EL1.SEL.

Configuration

AArch64 System register ERXMISC1_EL1 bits [31:0] are architecturally mapped to AArch32 System register ERXMISC2[31:0] .

AArch64 System register ERXMISC1_EL1 bits [63:32] are architecturally mapped to AArch32 System register ERXMISC3[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXMISC1_EL1 are UNDEFINED.

~~For IMPLEMENTATION DEFINED fields in this register, writing zero must always be supported to return the error record to an initial state.~~

~~In particular, if any IMPLEMENTATION DEFINED syndrome fields might generate a Fault Handling or Error Recovery Interrupt request, writing zero is sufficient to deactivate the Interrupt request.~~

~~Fields that are read-only, non-zero and ignore writes are compliant with this requirement.~~

~~Note~~

~~Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL, where q is the index of the first error record owned by the same node as error record n. If the node owns a single record then q = n.~~

Attributes

ERXMISC1_EL1 is a 64-bit register.

Field descriptions

The ERXMISC1_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ERR<n>MISC1																															
ERR<n>MISC1																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

ERXMISC1_EL1 accesses ERR<n>MISC1, where <n> is the value in ERRSELR_EL1.SEL.

Accessing the ERXMISC1_EL1

If ERRIDR_EL1.NUM == ~~0 or~~ 0x0000 or ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - ~~An UNKNOWN record is selected.~~
  - ~~ERXMISC1_EL1 is RAZ/WI.~~

    ERXMISC1_EL1 is RAZ/WI.
  - ~~Direct reads and writes of ERXMISC1_EL1 are NOPs.~~

    Direct reads and writes of ERXMISC1_EL1 are NOPs.
- Direct reads and writes of ERXMISC1_EL1 are UNDEFINED.
  - ~~Direct reads and writes of ERXMISC1_EL1 are UNDEFINED.~~

ERR<n>MISC1 describes additional constraints that also apply when ERR<n>MISC1 is accessed through ERXMISC1_EL1.

Accesses to this register use the following encodings:

```
MRS <Xt>, ERXMISC1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0101	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERXMISCn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXMISC1_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXMISC1_EL1;
elsif PSTATE.EL == EL3 then
    return ERXMISC1_EL1;
```

```
MSR ERXMISC1_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0101	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ERXMISCn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXMISC1_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXMISC1_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ERXMISC1_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC2_EL1, Selected Error Record Miscellaneous Register 2

The ERXMISC2_EL1 characteristics are:

Purpose

Accesses ERR<n>MISC2 for the error record <n> selected by ERRSELR_EL1.SEL.

Configuration

AArch64 System register ERXMISC2_EL1 bits [31:0] are architecturally mapped to AArch32 System register ERXMISC4[31:0] .

AArch64 System register ERXMISC2_EL1 bits [63:32] are architecturally mapped to AArch32 System register ERXMISC5[31:0] .

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERXMISC2_EL1 are UNDEFINED.

~~For IMPLEMENTATION DEFINED fields in this register, writing zero must always be supported to return the error record to an initial state.~~

~~In particular, if any IMPLEMENTATION DEFINED syndrome fields might generate a Fault Handling or Error Recovery Interrupt request, writing zero is sufficient to deactivate the Interrupt request.~~

~~Fields that are read-only, non-zero and ignore writes are compliant with this requirement.~~

~~Note~~

~~Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL, where q is the index of the first error record owned by the same node as error record n. If the node owns a single record then q = n.~~

Attributes

ERXMISC2_EL1 is a 64-bit register.

Field descriptions

The ERXMISC2_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ERR<n>MISC2																															
ERR<n>MISC2																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

ERXMISC2_EL1 accesses ERR<n>MISC2, where <n> is the value in ERRSELR_EL1.SEL.

Accessing the ERXMISC2_EL1

If ERRIDR_EL1.NUM == ~~0 or~~ 0x0000 or ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - ~~An UNKNOWN record is selected.~~
  - ~~ERXMISC2_EL1 is RAZ/WI.~~

    ERXMISC2_EL1 is RAZ/WI.
  - ~~Direct reads and writes of ERXMISC2_EL1 are NOPs.~~

    Direct reads and writes of ERXMISC2_EL1 are NOPs.
- Direct reads and writes of ERXMISC2_EL1 are UNDEFINED.
  - ~~Direct reads and writes of ERXMISC2_EL1 are UNDEFINED.~~

ERR<n>MISC2 describes additional constraints that also apply when ERR<n>MISC2 is accessed through ERXMISC2_EL1.

Accesses to this register use the following encodings:

```
MRS <Xt>, ERXMISC2_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0101	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERXMISCn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXMISC2_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXMISC2_EL1;
elsif PSTATE.EL == EL3 then
    return ERXMISC2_EL1;
```

```
MSR ERXMISC2_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0101	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ERXMISCn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXMISC2_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXMISC2_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ERXMISC2_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC3_EL1, Selected Error Record Miscellaneous Register 3

The ERXMISC3_EL1 characteristics are:

Purpose

Accesses ERR<n>MISC3 for the error record <n> selected by ERRSELR_EL1.SEL.

Configuration

AArch64 System register ERXMISC3_EL1 bits [31:0] are architecturally mapped to AArch32 System register ERXMISC6[31:0] .

AArch64 System register ERXMISC3_EL1 bits [63:32] are architecturally mapped to AArch32 System register ERXMISC7[31:0] .

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERXMISC3_EL1 are UNDEFINED.

~~For IMPLEMENTATION DEFINED fields in this register, writing zero must always be supported to return the error record to an initial state.~~

~~In particular, if any IMPLEMENTATION DEFINED syndrome fields might generate a Fault Handling or Error Recovery Interrupt request, writing zero is sufficient to deactivate the Interrupt request.~~

~~Fields that are read-only, non-zero and ignore writes are compliant with this requirement.~~

~~Note~~

~~Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL, where q is the index of the first error record owned by the same node as error record n. If the node owns a single record then q = n.~~

Attributes

ERXMISC3_EL1 is a 64-bit register.

Field descriptions

The ERXMISC3_EL1 bit assignments are:



Bits [63:0]

ERXMISC3_EL1 accesses ERR<n>MISC3, where <n> is the value in ERRSELR_EL1.SEL.

Accessing the ERXMISC3_EL1

If ERRIDR_EL1.NUM == ~~0 or~~ 0x0000 or ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - ~~An UNKNOWN record is selected.~~
  - ~~ERXMISC3_EL1 is RAZ/WI.~~

    ERXMISC3_EL1 is RAZ/WI.
  - ~~Direct reads and writes of ERXMISC3_EL1 are NOPs.~~

    Direct reads and writes of ERXMISC3_EL1 are NOPs.
- Direct reads and writes of ERXMISC3_EL1 are UNDEFINED.
  - ~~Direct reads and writes of ERXMISC3_EL1 are UNDEFINED.~~

ERR<n>MISC3 describes additional constraints that also apply when ERR<n>MISC3 is accessed through ERXMISC3_EL1.

Accesses to this register use the following encodings:

```
MRS <Xt>, ERXMISC3_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0101	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERXMISCn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXMISC3_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXMISC3_EL1;
elsif PSTATE.EL == EL3 then
    return ERXMISC3_EL1;
```

```
MSR ERXMISC3_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0101	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ERXMISCn_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXMISC3_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXMISC3_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ERXMISC3_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXPFGCDN_EL1, Selected Pseudo-fault Generation Countdown register

The ERXPFGCDN_EL1 characteristics are:

Purpose

Accesses the ERR<n>PFGCDN register for the error record <n> selected by ERRSELR_EL1.SEL.

Configuration

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERXPFGCDN_EL1 are UNDEFINED.

Attributes

ERXPFGCDN_EL1 is a 64-bit register.

Field descriptions

The ERXPFGCDN_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ERR<n>PFGCDN																															
ERR<n>PFGCDN																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

ERXPFGCDN_EL1 accesses ERR<n>PFGCDN, where <n> is the value in ERRSELR_EL1.SEL.

Accessing the ERXPFGCDN_EL1

If ERRIDR_EL1.NUM == 0 or 0x0000 or ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- An UNKNOWN record is selected.
- ERXPFGCDN_EL1 is RAZ/WI.

ERXPFGCDN_EL1 is RAZ/WI.

- Direct reads and writes of ERXPFGCDN_EL1 are NOPs.

Direct reads and writes of ERXPFGCDN_EL1 are NOPs.

- Direct reads and writes of ERXPFGCDN_EL1 are UNDEFINED.
- Direct reads and writes of ERXPFGCDN_EL1 are UNDEFINED.

If ERRSELR_EL1.SEL selects an error record owned by a node that does not implement the RAS Common Fault Injection Model Extension, then one of the following occurs:

- ERXPFGCDN_EL1 is RAZ/WI.

ERXPFGCDN_EL1 is RAZ/WI.

- ~~Direct reads and writes of ERXPFGCDN_EL1 are NOPs.~~

Direct reads and writes of ERXPFGCDN_EL1 are NOPs.

- Direct reads and writes of ERXPFGCDN_EL1 are UNDEFINED.

- ~~Direct reads and writes of ERXPFGCDN_EL1 are UNDEFINED.~~

Note

A~~A~~n node~~error record~~ does not implement the RAS Common Fault Injection Model Extension when ERR<q~~n~~>FR.INJ == 0b00. <q> is the index of the first error record owned by the same node as error record <n>, where <n> is the value in ERRSELR_EL1.SEL. If the node owns a single record, then q = n.

If ERRSELR_EL1.SEL is not the index of the first error record owned by a node, then ERR<n>PFGCDN is not present, meaning reads and writes of ERXPFGCDN_EL1 are RES0.

ERR<n>PFGCDN describes additional constraints that also apply when ERR<n>PFGCDN is accessed through ERXPFGCDN_EL1.

Accesses to this register use the following encodings:

```
MRS <Xt>, ERXPFGCDN_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FIEN == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERXPFGCDN_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIEN == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXPFGCDN_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIEN == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXPFGCDN_EL1;
elsif PSTATE.EL == EL3 then
    return ERXPFGCDN_EL1;
```

```
MSR ERXPFGCDN_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FIEN == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ERXPFGCDN_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIEN == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXPFGCDN_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIEN == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXPFGCDN_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ERXPFGCDN_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXPFGCTL_EL1, Selected Pseudo-fault Generation Control register

The ERXPFGCTL_EL1 characteristics are:

Purpose

Accesses the ERR<n>PFGCTL register for the error record <n> selected by ERRSELR_EL1.SEL.

Configuration

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERXPFGCTL_EL1 are UNDEFINED.

Attributes

ERXPFGCTL_EL1 is a 64-bit register.

Field descriptions

The ERXPFGCTL_EL1 bit assignments are:



Bits [63:0]

ERXPFGCTL_EL1 accesses ERR<n>PFGCTL, where <n> is the value in ERRSELR_EL1.SEL.

Accessing the ERXPFGCTL_EL1

If ERRIDR_EL1.NUM == 0 or 0x0000 or ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- An UNKNOWN record is selected.
- ERXPFGCTL_EL1 is RAZ/WI.

ERXPFGCTL_EL1 is RAZ/WI.

- Direct reads and writes of ERXPFGCTL_EL1 are NOPs.

Direct reads and writes of ERXPFGCTL_EL1 are NOPs.

- Direct reads and writes of ERXPFGCTL_EL1 are UNDEFINED.
- Direct reads and writes of ERXPFGCTL_EL1 are UNDEFINED.

If ERRSELR_EL1.SEL selects an error record owned by a node that does not implement the RAS Common Fault Injection Model Extension, then one of the following occurs:

- ERXPFGCTL_EL1 is RAZ/WI.

ERXPFGCTL_EL1 is RAZ/WI.

- ~~Direct reads and writes of ERXPFGCTL_EL1 are NOPs.~~

Direct reads and writes of ERXPFGCTL_EL1 are NOPs.

- Direct reads and writes of ERXPFGCTL_EL1 are UNDEFINED.

- ~~Direct reads and writes of ERXPFGCTL_EL1 are UNDEFINED.~~

Note

A~~An~~ node~~error record~~ does not implement the RAS Common Fault Injection Model Extension when ERR<q~~n~~>FR.INJ == 0b00. <q> is the index of the first error record owned by the same node as error record <n>, where <n> is the value in ERRSELR_EL1.SEL. If the node owns a single record, then q = n.

If ERRSELR_EL1.SEL is not the index of the first error record owned by a node, then ERR<n>PFGCTL is not present, meaning reads and writes of ERXPFGCTL_EL1 are RES0.

ERR<n>PFGCTL describes additional constraints that also apply when ERR<n>PFGCTL is accessed through ERXPFGCTL_EL1.

Accesses to this register use the following encodings:

```
MRS <Xt>, ERXPFGCTL_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FIEN == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERXPFGCTL_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIEN == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXPFGCTL_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIEN == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXPFGCTL_EL1;
elsif PSTATE.EL == EL3 then
    return ERXPFGCTL_EL1;
```

```
MSR ERXPFGCTL_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FIEN == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ERXPFGCTL_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIEN == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXPFGCTL_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIEN == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXPFGCTL_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ERXPFGCTL_EL1 = X[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXPFGF_EL1, Selected Pseudo-fault Generation Feature register

The ERXPFGF_EL1 characteristics are:

Purpose

Accesses the ERR<n>PFGF register for the error record <n> selected by ERRSELR_EL1.SEL.

Configuration

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERXPFGF_EL1 are UNDEFINED.

Attributes

ERXPFGF_EL1 is a 64-bit register.

Field descriptions

The ERXPFGF_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ERR<n>PFGF																															
ERR<n>PFGF																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

ERXPFGF_EL1 accesses ERR<n>PFGF, where <n> is the value in ERRSELR_EL1.SEL.

Accessing the ERXPFGF_EL1

If ERRIDR_EL1.NUM == 0 or 0x0000 or ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- An UNKNOWN record is selected.
- ERXPFGF_EL1 is RAZ.

ERXPFGF_EL1 is RAZ.

- Direct reads of ERXPFGF_EL1 are NOPs.

Direct reads of ERXPFGF_EL1 are NOPs.

- Direct reads of ERXPFGF_EL1 are UNDEFINED.
- Direct reads of ERXPFGF_EL1 are UNDEFINED.

If ERRSELR_EL1.SEL selects an error record owned by a node that does not implement the RAS Common Fault Injection Model Extension, then one of the following occurs:

- ERXPFGF_EL1 is RAZ.

ERXPFGF_EL1 is RAZ.

- ~~Direct reads of ERXPFGF_EL1 are NOPs.~~

Direct reads of ERXPFGF_EL1 are NOPs.

- Direct reads of ERXPFGF_EL1 are UNDEFINED.

- ~~Direct reads of ERXPFGF_EL1 are UNDEFINED.~~

Note

AAn node~~error record~~ does not implement the RAS Common Fault Injection Model Extension when ERR<qn>FR.INJ == 0b00. <q> is the index of the first error record owned by the same node as error record <n>, where <n> is the value in ERRSELR_EL1.SEL. If the node owns a single record, then q = n.

If ERRSELR_EL1.SEL is not the index of the first error record owned by a node, then ERR<n>PFGF is not present, meaning reads of ERXPFGF_EL1 are RES0.

ERR<n>PFGF describes additional constraints that also apply when ERR<n>PFGF is accessed through ERXPFGF_EL1.

Accesses to this register use the following encodings:

```
MRS <Xt>, ERXPFGF_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FIEN == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERXPFGF_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIEN == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXPFGF_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIEN == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXPFGF_EL1;
elsif PSTATE.EL == EL3 then
    return ERXPFGF_EL1;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXSTATUS_EL1, Selected Error Record Primary Status Register

The ERXSTATUS_EL1 characteristics are:

Purpose

Accesses ERR<n>STATUS for the error record <n> selected by ERRSELR_EL1.SEL.

Configuration

AArch64 System register ERXSTATUS_EL1 bits [31:0] are architecturally mapped to AArch32 System register ERXSTATUS[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXSTATUS_EL1 are UNDEFINED.

~~For IMPLEMENTATION DEFINED fields in this register, writing zero must always be supported to return the error record to an initial state.~~

~~In particular, if any IMPLEMENTATION DEFINED syndrome fields might generate a Fault Handling or Error Recovery Interrupt request, writing zero is sufficient to deactivate the Interrupt request.~~

~~Fields that are read-only, non-zero and ignore writes are compliant with this requirement.~~

~~Note~~

~~Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL, where q is the index of the first error record owned by the same node as error record n. If the node owns a single record then q = n.~~

Attributes

ERXSTATUS_EL1 is a 64-bit register.

Field descriptions

The ERXSTATUS_EL1 bit assignments are:



Bits [63:0]

ERXSTATUS_EL1 accesses ERR<n>STATUS, where <n> is the value in ERRSELR_EL1.SEL.

Accessing the ERXSTATUS_EL1

If ERRIDR_EL1.NUM == ~~0 or~~ 0x0000 or ERRSELR_EL1.SEL is set to a value greater than or equal to ERRIDR_EL1.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - ~~An UNKNOWN record is selected.~~
  - ~~ERXSTATUS_EL1 is RAZ/WI.~~

    ERXSTATUS_EL1 is RAZ/WI.
  - ~~Direct reads and writes of ERXSTATUS_EL1 are NOPs.~~

    Direct reads and writes of ERXSTATUS_EL1 are NOPs.
- Direct reads and writes of ERXSTATUS_EL1 are UNDEFINED.
  - ~~Direct reads and writes of ERXSTATUS_EL1 are UNDEFINED.~~

ERR<n>STATUS describes additional constraints that also apply when ERR<n>STATUS is accessed through ERXSTATUS_EL1.

Accesses to this register use the following encodings:

```
MRS <Xt>, ERXSTATUS_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ERXSTATUS_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXSTATUS_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ERXSTATUS_EL1;
elsif PSTATE.EL == EL3 then
    return ERXSTATUS_EL1;
```

```
MSR ERXSTATUS_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0100	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ERXSTATUS_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXSTATUS_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ERXSTATUS_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ERXSTATUS_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ESR_EL1, Exception Syndrome Register (EL1)

The ESR_EL1 characteristics are:

Purpose

Holds syndrome information for an exception taken to EL1.

Configuration

AArch64 System register ESR_EL1 bits [31:0] are architecturally mapped to AArch32 System register DFSR[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ESR_EL1 is a 64-bit register.

Field descriptions

The ESR_EL1 bit assignments are:



ESR_EL1 is made UNKNOWN as a result of an exception return from EL1.

When an UNPREDICTABLE instruction is treated as UNDEFINED, and the exception is taken to EL1, the value of ESR_EL1 is UNKNOWN. The value written to ESR_EL1 must be consistent with a value that could be created as a result of an exception from the same Exception level that generated the exception as a result of a situation that is not UNPREDICTABLE at that Exception level, in order to avoid the possibility of a privilege violation.

Bits [63:32]

Reserved, RES0.

EC, bits [31:26]

Exception Class. Indicates the reason for the exception that this register holds information about.

For each EC value, the table references a subsection that gives information about:

- The cause of the exception, for example the configuration required to enable the trap.
- The encoding of the associated ISS.

Possible values of the EC field are:

EC	Meaning	ISS	Applies when
0b000000	Unknown reason.	ISS encoding for exceptions with an unknown reason	
0b000001	Trapped WFI or WFE instruction execution. Conditional WFE and WFI instructions that fail their condition code check do not cause an exception.	ISS encoding for an exception from a WFI or WFE instruction	
0b000011	Trapped MCR or MRC access with (coproc==0b1111) that is not reported using EC 0b000000.	ISS encoding for an exception from an MCR or MRC access	When AArch32 is supported at any Exception level
0b000100	Trapped MCRR or MRRC access with (coproc==0b1111) that is not reported using EC 0b000000.	ISS encoding for an exception from an MCRR or MRRC access	When AArch32 is supported at any Exception level
0b000101	Trapped MCR or MRC access with (coproc==0b1110).	ISS encoding for an exception from an MCR or MRC access	When AArch32 is supported at any Exception level
0b000110	Trapped LDC or STC access. The only architected uses of these instruction are: • An STC to write data to memory from DBGDTRRXint. • An LDC to read data from memory to DBGDTRTXint.	ISS encoding for an exception from an LDC or STC instruction	When AArch32 is supported at any Exception level
0b000111	Access to SVE, Advanced SIMD, or floating-point functionality trapped by CPACR_EL1.FPEN, CPTR_EL2.FPEN, CPTR_EL2.TFP, or CPTR_EL3.TFP control. Excludes exceptions resulting from CPACR_EL1 when the value of HCR_EL2.TGE is 1, or because SVE or Advanced SIMD and floating-point are not implemented. These are reported with EC value 0b000000 as described in 'EC encodings when routing exceptions to EL2' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A	ISS encoding for an exception from an access to SVE, Advanced SIMD or floating-point functionality, resulting from CPACR_EL1.FPEN, CPTR_EL2.FPEN or CPTR_ELx.TFP	

	architecture profile, section D1.10.4.		
0b001100	Trapped MRRC access with (coproc==0b1110).	ISS encoding for an exception from an MCRR or MRRC access	When AArch32 is supported at any Exception level
0b001101	Branch Target Exception.	ISS encoding for an exception from Branch Target Identification instruction	When ARMv8.5-BTI is implemented
0b001110	Illegal Execution state.	ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault	
0b010001	SVC instruction execution in AArch32 state. This is reported in ESR_EL2 only when the exception is generated because the value of HCR_EL2.TGE is 1.	ISS encoding for an exception from HVC or SVC instruction execution	When AArch32 is supported at any Exception level
0b010101	SVC instruction execution in AArch64 state.	ISS encoding for an exception from HVC or SVC instruction execution	When AArch64 is supported at any Exception level
0b011000	Trapped MSR, MRS or System instruction execution in AArch64 state, that is not reported using EC 0b000000, 0b000001 or 0b000111. ~~If ARMv8.4-IDST is implemented, also exceptions generated by a read access to the feature ID space. If ARMv8.0-CSV2 is implemented, also Cache Speculation Variant exceptions. If ARMv8.2-EVT is implemented, also traps for EL1 and EL0 Cache controls.~~ This includes all instructions that cause exceptions that are part of the encoding space defined in 'System instruction class encoding overview' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section C5.2.2, except for those exceptions reported	ISS encoding for an exception from MSR, MRS, or System instruction execution in AArch64 state	When AArch64 is supported at any Exception level

	using EC values 0b000000, 0b000001, or 0b000111.		
0b011001	Access to SVE functionality trapped as a result of CPACR_EL1.ZEN, CPTR_EL2.ZEN, CPTR_EL2.TZ, or CPTR_EL3.EZ, that is not reported using EC 0b000000. ~~This EC is defined only if SVEis implemented.~~	ISS encoding for an exception from an access to SVE functionality, resulting from CPACR_EL1.ZEN, CPTR_EL2.ZEN, CPTR_EL2.TZ, or CPTR_EL3.EZ	When SVE is implemented
0b011100	Exception from a Pointer Authentication instruction authentication failure	ISS encoding for an exception from a Pointer Authentication instruction authentication failure	When ARMv8.3-FPAC is implemented
0b100000	Instruction Abort from a lower Exception level.~~level, that might be using AArch32 or AArch64.~~ Used for MMU faults generated by instruction accesses and synchronous External aborts, including synchronous parity or ECC errors. Not used for debug related exceptions.	ISS encoding for an exception from an Instruction Abort	
0b100001	Instruction Abort taken without a change in Exception level. Used for MMU faults generated by instruction accesses and synchronous External aborts, including synchronous parity or ECC errors. Not used for debug related exceptions.	ISS encoding for an exception from an Instruction Abort	
0b100010	PC alignment fault exception.	ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault	
0b100100	Data Abort from a lower Exception level.~~level, that might be using AArch32 or AArch64.~~ Used for MMU faults generated by data accesses, alignment faults other than those	ISS encoding for an exception from a Data Abort	

	caused by Stack Pointer misalignment, and synchronous External aborts, including synchronous parity or ECC errors. Not used for debug related exceptions.		
0b100101	Data Abort taken without a change in Exception level. Used for MMU faults generated by data accesses, alignment faults other than those caused by Stack Pointer misalignment, and synchronous External aborts, including synchronous parity or ECC errors. Not used for debug related exceptions.	ISS encoding for an exception from a Data Abort	
0b100110	SP alignment fault exception.	ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault	
0b101000	Trapped floating-point exception taken from AArch32 state. This EC value is valid if the implementation supports trapping of floating-point exceptions, otherwise it is reserved. Whether a floating-point implementation supports trapping of floating-point exceptions is IMPLEMENTATION DEFINED.	ISS encoding for an exception from a trapped floating-point exception	When AArch32 is supported at any Exception level
0b101100	Trapped floating-point exception taken from AArch64 state. This EC value is valid if the implementation supports trapping of floating-point exceptions, otherwise it is reserved. Whether a floating-point implementation supports trapping of floating-point exceptions is	ISS encoding for an exception from a trapped floating-point exception	When AArch64 is supported at any Exception level

	IMPLEMENTATION DEFINED.		
0b101111	SError interrupt.	ISS encoding for an SError interrupt	
0b110000	Breakpoint exception from a lower Exception level.~~level, that might be using AArch32 or AArch64.~~	ISS encoding for an exception from a Breakpoint or Vector Catch debug exception	
0b110001	Breakpoint exception taken without a change in Exception level.	ISS encoding for an exception from a Breakpoint or Vector Catch debug exception	
0b110010	Software Step exception from a lower Exception level.~~level, that might be using AArch32 or AArch64.~~	ISS encoding for an exception from a Software Step exception	
0b110011	Software Step exception taken without a change in Exception level.	ISS encoding for an exception from a Software Step exception	
0b110100	Watchpoint exception from a lower Exception level.~~level, that might be using AArch32 or AArch64.~~	ISS encoding for an exception from a Watchpoint exception	
0b110101	Watchpoint exception taken without a change in Exception level.	ISS encoding for an exception from a Watchpoint exception	
0b111000	BKPT instruction execution in AArch32 state.	ISS encoding for an exception from execution of a Breakpoint instruction	When AArch32 is supported at any Exception level
0b111100	BRK instruction execution in AArch64 state. This is reported in ESR_EL3 only if a BRK instruction is executed.	ISS encoding for an exception from execution of a Breakpoint instruction	When AArch64 is supported at any Exception level

All other EC values are reserved by Arm, and:

- Unused values in the range `0b000000` - `0b101100` (`0x00` - `0x2C`) are reserved for future use for synchronous exceptions.
- Unused values in the range `0b101101` - `0b111111` (`0x2D` - `0x3F`) are reserved for future use, and might be used for synchronous or asynchronous exceptions.

The effect of programming this field to a reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Reserved values in System and memory-mapped registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.1.11.

This field resets to an architecturally UNKNOWN value.

IL, bit [25]

Instruction Length for synchronous exceptions. Possible values of this bit are:

IL	Meaning
0b0	16-bit instruction trapped.
0b1	32-bit instruction trapped. This value is also used when the exception is one of the following: • An SError interrupt. • An Instruction Abort exception. • A PC alignment fault exception. • An SP alignment fault exception. • A Data Abort exception for which the value of the ISV bit is 0. • An Illegal Execution state exception. • Any debug exception except for Breakpoint instruction exceptions. For Breakpoint instruction exceptions, this bit has its standard meaning: ◦ 0b0: 16-bit T32 BKPT instruction. ◦ 0b1: 32-bit A32 BKPT instruction or A64 BRK instruction. • An exception reported using EC value 0b000000.

This field resets to an architecturally UNKNOWN value.

ISS, bits [24:0]

Instruction Specific Syndrome. Architecturally, this field can be defined independently for each defined Exception class. However, in practice, some ISS encodings are used for more than one Exception class.

Typically, an ISS encoding has a number of subfields. When an ISS subfield holds a register number, the value returned in that field is the AArch64 view of the register number.

~~Typically, an ISS encoding has a number of subfields. When an ISS subfield holds a register number, the value returned in that field is the AArch64 view of the register number. For an exception taken from AArch32 state, 'Mapping of the general-purpose registers between the Execution states' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

For an exception taken from AArch32 state, 'Mapping of the general-purpose registers between the Execution states'.

If the AArch32 register descriptor is 0b1111, then:

- If the instruction that generated the exception was not UNPREDICTABLE, the field takes the value 0b11111.
- If the instruction that generated the exception was UNPREDICTABLE, the field takes an UNKNOWN value that must be either:
  - The AArch64 view of the register number of a register that might have been used at the Exception level from which the exception was taken.
  - The value 0b11111.

When the EC field is 0b000000, indicating an exception with an unknown reason, the ISS field is not valid, RES0.

ISS encoding for exceptions with an unknown reason



Bits [24:0]

Reserved, RES0.

When an exception is reported using this EC code the IL field is set to 1.

This EC code is used for all exceptions that are not covered by any other EC value. This includes exceptions that are generated in the following situations:

- The attempted execution of an instruction bit pattern that has no allocated instruction or that is not accessible at the current Exception level and Security state, including:
  - A read access using a System register pattern that is not allocated for reads or that does not permit reads at the current Exception level and Security state.
  - A write access using a System register pattern that is not allocated for writes or that does not permit writes at the current Exception level and Security state.

    - Instruction encodings that are unallocated.
    - Instruction encodings for instructions or System registers that are not implemented in the implementation.
- In Debug state, the attempted execution of an instruction bit pattern that is not accessible in Debug state.
- In Non-debug state, the attempted execution of an instruction bit pattern that is not accessible in Non-debug state.
- In AArch32 state, attempted execution of a short vector floating-point instruction.
- In an implementation that does not include Advanced SIMD and floating-point functionality, an attempted access to Advanced SIMD or floating-point functionality under conditions where that access would be permitted if that functionality was present. This includes the attempted execution of an Advanced SIMD or floating-point instruction, and attempted accesses to Advanced SIMD and floating-point System registers.
- An exception generated because of the value of one of the SCTLR_EL1.{ITD, SED, CP15BEN} control bits.
- Attempted execution of:
    - An HVC instruction when disabled by HCR_EL2.HCD or SCR_EL3.HCE.
    - An SMC instruction when disabled by SCR_EL3.SMD.
    - An HLT instruction when disabled by EDSCR.HDE.
- Attempted execution of an MSR or MRS instruction to access SP_EL0 when the value of SPSel.SP is 0.
- Attempted execution, in Debug state, of:
    - A DCPS1 instruction when the value of HCR_EL2.TGE is 1 and EL2 is disabled or not implemented in the current Security state.
    - A DCPS2 instruction from EL1 or EL0 when EL2 is disabled or not implemented in the current Security state.
    - A DCPS3 instruction when the value of EDSCR.SDD is 1, or when EL3 is not implemented.
- When EL3 is using AArch64, attempted execution from Secure EL1 of an SRS instruction using R13_mon. See 'Traps to EL3 of monitor functionality from Secure EL1 using AArch32' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.
- In Debug state when the value of EDSCR.SDD is 1, the attempted execution at EL2, EL1, or EL0 of an instruction that is configured to trap to EL3.
- In AArch32 state, the attempted execution of an MRS (banked register) or an MSR (banked register) instruction to SPSR_mon, SP_mon, or LR_mon.
- An exception that is taken to EL2 because the value of HCR_EL2.TGE is 1 that, if the value of HCR_EL2.TGE was 0 would have been reported with an ESR_ELx.EC value of `0b000111`.
- ~~When SVE is not implemented, attempted execution of:~~
    - ~~An SVE instruction.~~
    - ~~An MSR or MRS instruction to access ZCR_EL1, ZCR_EL2, or ZCR_EL3.~~

ISS encoding for an exception from a WFI or WFE instruction

24	23 22 21 20	19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1	0
CV	COND	RES0	TI

CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
`0b0`	The COND field is not valid.
`0b1`	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to 0b1110.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to 0b1110.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to 0b1110, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to 0b1110, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Bits [19:1]

Reserved, RES0.

TI, bit [0]

Trapped instruction. Possible values of this bit are:

TI	Meaning
0b0	WFI trapped.
0b1	WFE trapped.

This field resets to an architecturally UNKNOWN value.

The following fields describe configuration settings for generating this exception:

- SCTLR_EL1.{nTWE, nTWI}.
- HCR_EL2.{TWE, TWI}.
- SCR_EL3.{TWE, TWI}.

ISS encoding for an exception from an MCR or MRC access



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to `0b1110`.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to `0b1110`.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to `0b1110`, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Opc2, bits [19:17]

The Opc2 value from the issued instruction.

For a trapped VMRS access, holds the value `0b000`.

This field resets to an architecturally UNKNOWN value.

Opc1, bits [16:14]

The Opc1 value from the issued instruction.

For a trapped VMRS access, holds the value `0b111`.

This field resets to an architecturally UNKNOWN value.

CRn, bits [13:10]

The CRn value from the issued instruction.

For a trapped VMRS access, holds the reg field from the VMRS instruction encoding.

This field resets to an architecturally UNKNOWN value.

Rt, bits [9:5]

The Rt value from the issued instruction, the general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states'~~ in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

This field resets to an architecturally UNKNOWN value.

CRm, bits [4:1]

The CRm value from the issued instruction.

For a trapped VMRS access, holds the value `0b0000`.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
`0b0`	Write to System register space. MCR instruction.
`0b1`	Read from System register space. MRC or VMRS instruction.

This field resets to an architecturally UNKNOWN value.

The following fields describe configuration settings for generating exceptions that are reported using EC value `0b000011`:

- CNTKCTL_EL1.{EL0PTEN, EL0VTEN, EL0PCTEN, EL0VCTEN}, for accesses to the Generic Timer Registers from EL0 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL1 or EL2.
- PMUSERENR_EL0.{ER, CR, SW, EN}, for accesses to Performance Monitor registers from EL0 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL1 or EL2.
- AMUSERENR_EL0.EN, for accesses to Activity Monitors registers from EL0 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL1 or EL2.
- HCR_EL2.{TRVM, TVM}, for accesses to virtual memory control registers from EL1 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- HCR_EL2.TTLB, for execution of TLB maintenance instructions at EL1 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- HCR_EL2.{TSW, TPC, TPU} for execution of cache maintenance instructions at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- HCR_EL2.TACR, for accesses to the Auxiliary Control Register at EL1 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- HCR_EL2.TIDCP, for accesses to lockdown, DMA, and TCM operations at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- HCR_EL2.{TID1, TID2, TID3}, for accesses to ID registers at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- CPTR_EL2.TCPAC, for accesses to CPACR_EL1 or CPACR using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- HSTR_EL2.T<n>, for accesses to System registers using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- CNTHCTL_EL2.EL1PCEN, for accesses to the Generic Timer registers from EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- MDCR_EL2.{TPM, TPMCR}, for accesses to Performance Monitor registers from EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- CPTR_EL2.TAM, for accesses to Activity Monitors registers from EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- CPTR_EL3.TCPAC, for accesses to CPACR from EL1 and EL2, and accesses to HCPTR from EL2 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL3.
- MDCR_EL3.TPM, for accesses to Performance Monitor registers from EL0, EL1 and EL2 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL3.
- CPTR_EL3.TAM, for accesses to Activity Monitors registers from EL0, EL1 and EL2 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL3.
- See 'Traps to EL3 of Secure monitor functionality from Secure EL1 using AArch32' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ for information on other traps using EC value `0b000011`.
- If ARMv8.6-FGT is implemented, MCR or MRC access to some registers at EL0, trapped to EL2.

The following fields describe configuration settings for generating exceptions that are reported using EC value `0b000101`:

- CPACR_EL1.TTA for accesses to trace registers, MCR or MRC access (coproc == `0b1110`) trapped to EL1 or EL2.
- MDSCR_EL1.TDCC, for accesses to the Debug Communications Channel (DCC) registers at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == `0b1110`) trapped to EL1 or EL2.

- If ARMv8.6-FGT is implemented, MDCR_EL2.TDCC and MDCR_EL3.TDCC, for accesses to the DCC registers at EL0 and EL1, trapped to EL2.
- HCR_EL2.TID0, for accesses to the JIDR register in the ID group 0 at EL0 and EL1 using AArch32, MRC access (coproc == `0b1110`) trapped to EL2.
- CPTR_EL2.TTA, for accesses to trace registers using AArch32, MCR or MRC access (coproc == `0b1110`) trapped to EL2.
- MDCR_EL2.TDRA, for accesses to Debug ROM registers DBGDRAR and AArch-DBGDSAR using AArch32, MCR or MRC access (coproc == `0b1110`) trapped to EL2.
- MDCR_EL2.TDOSA, for accesses to powerdown debug registers, using AArch32 state, MCR or MRC access (coproc == `0b1110`) trapped to EL2.
- MDCR_EL2.TDA, for accesses to other debug registers, using AArch32 state, MCR or MRC access (coproc == `0b1110`) trapped to EL2.
- CPTR_EL3.TTA, for accesses to trace registers using AArch32, MCR or MRC access (coproc == `0b1110`) trapped to EL3.
- MDCR_EL3.TDOSA, for accesses to powerdown debug registers using AArch32, MCR or MRC access (coproc == `0b1110`) trapped to EL3.
- MDCR_EL3.TDA, for accesses to other debug registers, using AArch32, MCR or MRC access (coproc == `0b1110`) trapped to EL3.

The following fields describe configuration settings for generating exceptions that are reported using EC value `0b001000`:

- HCR_EL2.TID0, for accesses to the FPSID register in ID group 0 at EL1 using AArch32 state, VMRS access trapped to EL2.
- HCR_EL2.TID3, for accesses to registers in ID group 3 including MVFR0, MVFR1 and MVFR2, VMRS access trapped to EL2.

ISS encoding for an exception from an MCRR or MRRC access

24	23 22 21 20	19 18 17 16	15	14 13 12 11 10	9 8 7 6 5	4 3 2 1	0
CV	COND	Opc1	RES0	Rt2	Rt	CRm	Direction

CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
`0b0`	The COND field is not valid.
`0b1`	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to `0b1110`.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to `0b1110`.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:

        - With COND set to `0b1110`, the value for unconditional.
        - With the COND value held in the instruction.
    - When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
        - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
        - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
    - For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Opc1, bits [19:16]

The Opc1 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Bit [15]

Reserved, RES0.

Rt2, bits [14:10]

The Rt2 value from the issued instruction, the second general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

This field resets to an architecturally UNKNOWN value.

Rt, bits [9:5]

The Rt value from the issued instruction, the first general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

This field resets to an architecturally UNKNOWN value.

CRm, bits [4:1]

The CRm value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
`0b0`	Write to System register space. MCRR instruction.
`0b1`	Read from System register space. MRRC instruction.

This field resets to an architecturally UNKNOWN value.

The following fields describe configuration settings for generating exceptions that are reported using EC value `0b000100`:

- CNTKCTL_EL1.{EL0PTEN, EL0VTEN, EL0PCTEN, EL0VCTEN}, for accesses to the Generic Timer Registers from EL0 using AArch32 state, MCRR or MRRC access (coproc == `0b1111`) trapped to EL1 or EL2.
- PMUSERENR_EL0.{CR, EN}, for accesses to Performance Monitor registers from EL0 using AArch32 state, MCRR or MRRC access (coproc == `0b1111`) trapped to EL1 or EL2.

- AMUSERENR_EL0.{EN}, for accesses to Activity Monitors registers AMEVCNTR0<n> and AMEVCNTR1<n> from EL0 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL1 or EL2.
- HCR_EL2.{TRVM, TVM}, for accesses to virtual memory control registers from EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- HSTR_EL2.T<n>, for accesses to System registers using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- CNTHCTL_EL2.{EL1PCEN, EL1PCTEN}, for accesses to the Generic Timer registers from EL0 and EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- MDCR_EL2.{TPM, TPMCR}, for accesses to Performance Monitor registers from EL0 and EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- CPTR_EL2.TAM, for accesses to Activity Monitors registers registers AMEVCNTR0<n> and AMEVCNTR1<n> from EL0 and EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- MDCR_EL3.TPM, for accesses to Performance Monitor registers from EL0, EL1 and EL2 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL3.
- CPTR_EL3.TAM, for accesses to Activity Monitors registers from EL0, EL1 and EL2 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL3.
- If ARMv8.6-FGT is implemented, HDFGRTR_EL2.PMCCNTR_EL0 for MRRC access and HDFGWTR_EL2.PMCCNTR_EL0 for MCRR access to PMCCNTR at EL0, trapped to EL2.

The following sections describe configuration settings for generating exceptions that are reported using EC value 0b001100:

- CPACR_EL1.TTA for accesses to trace registers using MCR or MRC instructions, MCRR or MRRC access (coproc == 0b1110) trapped to EL1 or EL2.
- MDSCR_EL1.TDCC, for accesses to the Debug Communications Channel (DCC) registers DBGDSAR and DBGDRAR at EL0 using AArch32 state, MCRR or MRRC access (coproc == 0b1110) trapped to EL1 or EL2.
- CPTR_EL2.TTA, for accesses to trace registers using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL2.
- MDCR_EL2.TDRA, for accesses to Debug ROM registers DBGDRAR and AArch-DBGDSAR using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL2.
- CPTR_EL3.TTA, for accesses to trace registers using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL3.
- MDCR_EL3.TDOSA, for traps to powerdown debug registers using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL3.
- MDCR_EL3.TDA, for accesses to other debug registers, using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL3.

ISS encoding for an exception from an LDC or STC instruction



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to `0b1110`.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to `0b1110`.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to `0b1110`, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

imm8, bits [19:12]

The immediate value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Bits [11:10]

Reserved, RES0.

Rn, bits [9:5]

The Rn value from the issued instruction, the general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

This field is valid only when AM[2] is 0, indicating an immediate form of the LDC or STC instruction. When AM[2] is 1, indicating a literal form of the LDC or STC instruction, this field is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

Offset, bit [4]

Indicates whether the offset is added or subtracted:

Offset	Meaning
`0b0`	Subtract offset.
`0b1`	Add offset.

This bit corresponds to the U bit in the instruction encoding.

This field resets to an architecturally UNKNOWN value.

AM, bits [3:1]

Addressing mode. The permitted values of this field are:

AM	Meaning
0b000	Immediate unindexed.
0b001	Immediate post-indexed.
0b010	Immediate offset.
0b011	Immediate pre-indexed.
0b100	For a trapped STC instruction or a trapped T32 LDC instruction this encoding is reserved.
0b110	For a trapped STC instruction, this encoding is reserved.

The values 0b101 and 0b111 are reserved. The effect of programming this field to a reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Reserved values in System and memory-mapped registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Bit [2] in this subfield indicates the instruction form, immediate or literal.

Bits [1:0] in this subfield correspond to the bits {P, W} in the instruction encoding.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
0b0	Write to memory. STC instruction.
0b1	Read from memory. LDC instruction.

This field resets to an architecturally UNKNOWN value.

The following fields describe the configuration settings for the traps that are reported using EC value 0b000110:

- MDSCR_EL1.TDCC, for accesses using AArch32 state, LDC access to DBGDTRTXint or STC access to DBGDTRRXint trapped to EL1 or EL2.
- MDCR_EL2.TDA, for accesses using AArch32 state, LDC access to DBGDTRTXint or STC access to DBGDTRRXint MCR or MRC access trapped to EL2.
- MDCR_EL3.TDA, for accesses using AArch32 state, LDC access to DBGDTRTXint or STC access to DBGDTRRXint MCR or MRC access trapped to EL3.
- If ARMv8.6-FGT is implemented, MDCR_EL2.TDCC and MDCR_EL3.TDCC, for accesses to the DCC registers at EL0 and EL1, trapped to EL2.

ISS encoding for an exception from an access to SVE, Advanced SIMD or floating-point functionality, resulting from CPACR_EL1.FPEN, CPTR_EL2.FPEN or CPTR_ELx.TFP



The accesses covered by this trap include:

- Execution of SVE or Advanced SIMD and floating-point instructions.
- Accesses to the Advanced SIMD and floating-point System registers.

For an implementation that does not include either SVE or support for floating-point and Advanced SIMD, the exception is reported using the EC value 0b000000.

CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to `0b1110`.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to `0b1110`.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to `0b1110`, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Bits [19:0]

Reserved, RES0.

The following sections describe the configuration settings for the traps that are reported using EC value `0b000111`:

- CPACR_EL1.FPEN, for accesses to SIMD and floating-point registers trapped to EL1.
- CPTR_EL2.TFP, for accesses to SIMD and floating-point registers trapped to EL2.
- CPTR_EL2.TFP, for accesses to SIMD and floating-point registers trapped to EL3.

ISS encoding for an exception from an access to SVE functionality, resulting from CPACR_EL1.ZEN, CPTR_EL2.ZEN, CPTR_EL2.TZ, or CPTR_EL3.EZ



Bits [24:0]

When SVE is implemented:

Reserved, RES0.

Otherwise:

Reserved, RES0.

The accesses covered by this trap include:

- Execution of SVE instructions.
- Accesses to the SVE system registers, ZCR_ELx and ID_AA64ZFR0_EL1.

For an implementation that does not include SVE, the exception is reported using the EC value `0b000000`.

ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault



Bits [24:0]

Reserved, RES0.

There are no configuration settings for generating Illegal Execution state exceptions and PC alignment fault exceptions. For more information about these exceptions see 'The Illegal Execution state exception' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ and 'PC alignment checking' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

'Stack pointer alignment checking' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ describes the configuration settings for generating SP alignment fault exceptions.

ISS encoding for an exception from HVC or SVC instruction execution



Bits [24:16]

Reserved, RES0.

imm16, bits [15:0]

The value of the immediate field from the HVC or SVC instruction.

For an HVC instruction, and for an A64 SVC instruction, this is the value of the imm16 field of the issued instruction.

For an A32 or T32 SVC instruction:

- If the instruction is unconditional, then:
  - For the T32 instruction, this field is zero-extended from the imm8 field of the instruction.
  - For the A32 instruction, this field is the bottom 16 bits of the imm24 field of the instruction.
- If the instruction is conditional, this field is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

In AArch32 state, the HVC instruction is unconditional, and a conditional SVC instruction generates an exception only if it passes its condition code check. Therefore, the syndrome information for these exceptions does not require conditionality information.

For T32 and A32 instructions, see 'SVC' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ and 'HVC' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

For A64 instructions, see 'SVC' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ and 'HVC' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

If ARMv8.6-FGT is implemented, HFGITR_EL2.{SVC_EL1, SVC_EL0} control fine-grained traps on SVC execution.

ISS encoding for an exception from SMC instruction execution in AArch32 state



For an SMC instruction that completes normally and generates an exception that is taken to EL3, the ISS encoding is RES0.

For an SMC instruction that is trapped to EL2 from EL1 because HCR_EL2.TSC is 1, the ISS encoding is as shown in the diagram.

CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field is only valid if CCKNOWNPASS is 1, otherwise it is RES0.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to 0b1110.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to 0b1110.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to 0b1110, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to 0b1110, or to the value of any condition that applied to the instruction.

This field is only valid if CCKNOWNPASS is 1, otherwise it is RES0.

This field resets to an architecturally UNKNOWN value.

CCKNOWNPASS, bit [19]

Indicates whether the instruction might have failed its condition code check.

CCKNOWNPASS	Meaning
0b0	The instruction was unconditional, or was conditional and passed its condition code check.
0b1	The instruction was conditional, and might have failed its condition code check.

Note

In an implementation in which an SMC instruction that fails it code check is not trapped, this field can always return the value 0.

This field resets to an architecturally UNKNOWN value.

Bits [18:0]

Reserved, RES0.

HCR_EL2.TSC describes the configuration settings for trapping SMC instructions to EL2.

See 'System calls' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ describes the case where these exceptions are trapped to EL3.

ISS encoding for an exception from SMC instruction execution in AArch64 state



Bits [24:16]

Reserved, RES0.

imm16, bits [15:0]

The value of the immediate field from the issued SMC instruction.

This field resets to an architecturally UNKNOWN value.

The value of ISS[24:0] described here is used both:

- When an SMC instruction is trapped from EL1 modes.
- When an SMC instruction is not trapped, so completes normally and generates an exception that is taken to EL3.

HCR_EL2.TSC describes the configuration settings for trapping SMC from EL1 modes.

'System calls' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ describes the case where these exceptions are trapped to EL3.

ISS encoding for an exception from MSR, MRS, or System instruction execution in AArch64 state



Bits [24:22]

Reserved, RES0.

Op0, bits [21:20]

The Op0 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Op2, bits [19:17]

The Op2 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Op1, bits [16:14]

The Op1 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

CRn, bits [13:10]

The CRn value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Rt, bits [9:5]

The Rt value from the issued instruction, the general-purpose register used for the transfer.

This field resets to an architecturally UNKNOWN value.

CRm, bits [4:1]

The CRm value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
0b0	Write access, including MSR instructions.
0b1	Read access, including MRS instructions.

This field resets to an architecturally UNKNOWN value.

For exceptions caused by System instructions, see 'System' subsection of 'Branches, exception generating and System instructions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile for the encoding values returned by an instruction.

The following fields describe configuration settings for generating the exception that is reported using EC value 0b011000:

- SCTLR_EL1.UCI, for execution of cache maintenance instructions using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- SCTLR_EL1.UCT, for accesses to CTR_EL0 using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- SCTLR_EL1.DZE, for execution of DC ZVA instructions using AArch64 state, MSR or MRS access trapped to EL1 or EL2.

- SCTLR_EL1.UMA, for accesses to the PSTATE interrupt masks using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- CPACR_EL1.TTA, for accesses to the trace registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- MDSCR_EL1.TDCC, for accesses to the Debug Communications Channel (DCC) registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- If ARMv8.6-FGT is implemented, MDCR_EL2.TDCC and MDCR_EL3.TDCC, for accesses to the DCC registers at EL0 and EL1, trapped to EL2.
- CNTKCTL_EL1.{EL0PTEN, EL0VTEN, EL0PCTEN, EL0VCTEN} accesses to the Generic Timer registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- PMUSERENR_EL0.{ER, CR, SW, EN}, for accesses to the Performance Monitor registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- AMUSERENR_EL0.EN, for accesses to Activity Monitors registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- HCR_EL2.{TRVM, TVM}, for accesses to virtual memory control registers using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TDZ, for execution of DC ZVA instructions using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TTLB, for execution of TLB maintenance instructions using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.{TSW, TPC, TPU}, for execution of cache maintenance instructions using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TACR, for accesses to the Auxiliary Control Register, ACTLR_EL1, using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TIDCP, for accesses to lockdown, DMA, and TCM operations using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.{TID1, TID2, TID3}, for accesses to ID group 1, ID group 2 or ID group 3 registers, using AArch64 state, MSR or MRS access trapped to EL2.
- CPTR_EL2.TCPAC, for accesses to CPACR_EL1, using AArch64 state, MSR or MRS access trapped to EL2.
- CPTR_EL2.TTA, for accesses to the trace registers, using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.TTRF, for accesses to the trace filter register, TRFCR_EL1, using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.TDRA, for accesses to Debug ROM registers, using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.TDOSA, for accesses to powerdown debug registers using AArch64 state, MSR or MRS access trapped to EL2.
- CNTHCTL_EL2.{EL1PCEN, EL1PCTEN}, for accesses to the Generic Timer registers using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.TDA, for accesses to debug registers using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.{TPM, TPMCR}, for accesses to Performance Monitor registers, using AArch64 state, MSR or MRS access trapped to EL2.
- CPTR_EL2.TAM, for accesses to Activity Monitors registers, using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.APK, for accesses to Pointer authentication key registers. using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.{NV, NV1}, for Nested virtualization register access, using AArch64 state, MSR or MRS access, trapped to EL2.
- HCR_EL2.AT, for execution of AT S1E* instructions, using AArch64 state, MSR or MRS access, trapped to EL2.
- HCR_EL2.{TERR, FIEN}, for accesses to RAS registers, using AArch64 state, MSR or MRS access, trapped to EL2.
- SCR_EL3.APK, for accesses to Pointer authentication key registers, using AArch64 state, MSR or MRS access trapped to EL3.
- SCR_EL3.ST, for accesses to the Counter-timer Physical Secure timer registers, using AArch64 state, MSR or MRS access trapped to EL3.
- SCR_EL3.{TERR, FIEN}, for accesses to RAS registers, using AArch64 state, MSR or MRS access trapped to EL3.
- CPTR_EL3.TCPAC, for accesses to CPTR_EL2 and CPACR_EL1 using AArch64 state, MSR or MRS access trapped to EL3.
- CPTR_EL3.TTA, for accesses to the trace registers, using AArch64 state, MSR or MRS access trapped to EL3.
- MDCR_EL3.TTRF, for accesses to the filter trace control registers, TRFCR_EL1 and TRFCR_EL2, using AArch64 state, MSR or MRS access trapped to EL3.
- MDCR_EL3.TDA, for accesses to debug registers, using AArch64 state, MSR or MRS access trapped to EL3.
- MDCR_EL3.TDOSA, for accesses to powerdown debug registers, using AArch64 state, MSR or MRS access trapped to EL3.

- MDCR_EL3.TPM, for accesses to Performance Monitor registers, using AArch64 state, MSR or MRS access trapped to EL3.
- CPTR_EL3.TAM, for accesses to Activity Monitors registers, using AArch64 state, MSR or MRS access, trapped to EL3.
- If ARMv8.2-EVT is implemented the following registers control traps for EL1 and EL0 Cache controls that use this EC value:~~,HCR_EL2.{TTLBOS, TTLBIS, TICAB, TOCU, TID4} and HCR2.{TTLBIS, TICAB, TOCU, TID4} control traps for EL1 and EL0 Cache controls that use this EC value.~~
  - HCR_EL2.{TTLBOS, TTLBIS, TICAB, TOCU, TID4}.
  - HCR2.{TTLBIS, TICAB, TOCU, TID4}.
- If ARMv8.6-FGT is implemented:
  - SCR_EL3.FGTEn, for accesses to the fine-grained trap registers, MSR or MRS access at EL2 trapped to EL3.
  - HFGRTR_EL2 for reads and HFGWTR_EL2 for writes of registers, using AArch64 state, MSR or MRS access at EL0 and EL1 trapped to EL2.
  - HFGITR_EL2 for execution of system instructions, MSR or MRS access trapped to EL2
  - HDFGRTR_EL2 for reads and HDFGWTR_EL2 for writes of registers, using AArch64 state, MSR or MRS access at EL0 and EL1 state trapped to EL2.
  - HAFGRTR_EL2 for reads of Activity Monitor counters, using AArch64 state, MRS access at EL0 and EL1 trapped to EL2.

ISS encoding for an IMPLEMENTATION DEFINED exception to EL3



IMPLEMENTATION DEFINED, bits [24:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

ISS encoding for an exception from an Instruction Abort



Bits [24:13]

Reserved, RES0.

SET, bits [12:11]

Synchronous Error Type. When the RAS Extension is implemented and IFSC is `0b010000`, describes the state of the PE after taking the Instruction Abort exception. The possible values of this field are:

SET	Meaning
`0b00`	Recoverable error (UER).
`0b10`	Uncontainable error (UC).
`0b11`	Restartable error (UEO) or Corrected error (CE).

All other values are reserved.

Note

Software can use this information to determine what recovery might be possible. Taking a synchronous External Abort exception might result in an unrecoverable PE state.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the IFSC field is not `0b010000`.

This field resets to an architecturally UNKNOWN value.

FnV, bit [10]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
0b0	FAR is valid.
0b1	FAR is not valid, and holds an UNKNOWN value.

This field is only valid if the IFSC code is 0b010000. It is RES0 for all other aborts.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

External abort type. This bit can provide an IMPLEMENTATION DEFINED classification of External aborts.

For any abort other than an External abort this bit returns a value of 0.

This field resets to an architecturally UNKNOWN value.

Bit [8]

Reserved, RES0.

S1PTW, bit [7]

For a stage 2 fault, indicates whether the fault was a stage 2 fault on an access made for a stage 1 translation table walk:

S1PTW	Meaning
0b0	Fault not on a stage 2 translation for a stage 1 translation table walk.
0b1	Fault on the stage 2 translation of an access for a stage 1 translation table walk.

For any abort other than a stage 2 fault this bit is RES0.

This field resets to an architecturally UNKNOWN value.

Bit [6]

Reserved, RES0.

IFSC, bits [5:0]

Instruction Fault Status Code. ~~Possible values of this field are:~~

IFSC	Meaning	Applies when
0b000000	Address size fault, level 0 of translation or translation table base register.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000100	Translation fault, level 0.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk or hardware update of translation table.	
0b010100	Synchronous External abort, on translation table walk or hardware update of translation table, level 0.~~0~~	
0b010101	Synchronous External abort, on translation table walk or hardware update of translation table, level 1.~~1~~	
0b010110	Synchronous External abort, on translation table walk or hardware update of translation table, level 2.~~2~~	
0b010111	Synchronous External abort, on translation table walk or hardware update of translation table, level 3.~~3~~	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011100	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 0.~~0~~	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 1.~~1~~	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 2.~~2~~	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 3.~~3~~	When RAS is not implemented
0b110000	TLB conflict abort.	
0b110001	Unsupported atomic hardware update fault. ~~Unsupported atomic hardware update fault, if the implementation includes ARMv8.1-TTHM].~~ ~~Otherwise reserved.~~	When ARMv8.1-TTHM is implemented

All other values are reserved.

~~When the RAS Extension is implemented, 0b011000, 0b011100, 0b011101, 0b011110, and 0b011111, are reserved.~~

Note

Armv8.2 requires the implementation of the RAS Extension.

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

Because Access flag faults and Permission faults can only result from a Block or Page translation table descriptor, they cannot occur at level 0.

If the S1PTW bit is set, then the level refers the level of the stage2 translation that is translating a stage 1 translation walk.

This field resets to an architecturally UNKNOWN value.

ISS encoding for an exception from a Data Abort



ISV, bit [24]

Instruction Syndromesyndrome Valid.valid. Indicates whether the syndrome information in ISS[23:14] is valid.

ISV	Meaning
0b0	No valid instruction syndrome. ISS[23:14] are RES0.
0b1	ISS[23:14] hold a valid instruction syndrome.

This bit is 0 for all faults reported in ESR_EL2 except the following stage 2 aborts:

- AArch64 loads and stores of a single general-purpose register (including the register specified with 0b11111, including those with Acquire/Release semantics, but excluding Load Exclusive or Store Exclusive and excluding those with writeback.
- AArch32 instructions where the instruction:
  - Is an LDR, LDA, LDRT, LDRSH, LDRSHT, LDRH, LDAH, LDRHT, LDRSB, LDRSBT, LDRB, LDAB, LDRBT, STR, STL, STRT, STRH, STLH, STRHT, STRB, STLB, or STRBT instruction.
  - Is not performing register writeback.
  - Is not using R15 as a source or destination register.

For these cases, ISV is UNKNOWN if the exception was generated in Debug state in memory access mode, and otherwise indicates whether ISS[23:14] hold a valid syndrome.

ISV is 0 for all faults reported in ESR_EL1 or ESR_EL3.

When the RAS Extension is implemented, ISV is 0 for any synchronous External abort.

For ISS reporting, a stage 2 abort on a stage 1 translation table walk does not return a valid instruction syndrome, and therefore ISV is 0 for these aborts.

When the RAS Extension is not implemented, the value of ISV on a synchronous External abort on a stage 2 translation table walk is IMPLEMENTATION DEFINED.

When ARMv8.5-MemTag is implemented, for a synchronous Tag Check Fault abort taken to ELx, ESR_ELx.FNV is 0 and FAR_ELx is valid.

This field resets to an architecturally UNKNOWN value.

SAS, bits [23:22]

Syndrome Access Size. When ISV is 1, indicates the size of the access attempted by the faulting operation.

SAS	Meaning
0b00	Byte
0b01	Halfword
0b10	Word
0b11	Doubleword

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

SSE, bit [21]

Syndrome Sign Extend. When ISV is 1, for a byte, halfword, or word load operation, indicates whether the data item must be sign extended. For these cases, the possible values of this bit are:

SSE	Meaning
0b0	Sign-extension not required.
0b1	Data item must be sign-extended.

For all other operations this bit is 0.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

SRT, bits [20:16]

Syndrome Register Transfer. When ISV is 1, the register number of the Rt operand of the faulting instruction.

~~Syndrome Register transfer. When ISV is 1, the register number of the Rt operand of the faulting instruction. If the exception was taken from an Exception level that is using AArch32 then this is the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

If the exception was taken from an Exception level that is using AArch32 then this is the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states'.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

SF, bit [15]

Width of the register accessed by the instruction is Sixty-Four. When ISV is 1, the possible values of this bit are:

SF	Meaning
0b0	Instruction loads/stores a 32-bit wide register.
0b1	Instruction loads/stores a 64-bit wide register.

Note

This field specifies the register width identified by the instruction, not the Execution state.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

AR, bit [14]

Acquire/Release. When ISV is 1, the possible values of this bit are:

AR	Meaning
0b0	Instruction did not have acquire/release semantics.
0b1	Instruction did have acquire/release semantics.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

VNCR, bit [13]

When ARMv8.4-NV is implemented:

Indicates that the fault came from use of VNCR_EL2 register by EL1 code.

VNCR	Meaning
0b0	The fault was not generated by the use of VNCR_EL2, by an MRS or MSR instruction executed at EL1.
0b1	The fault was generated by the use of VNCR_EL2, by an MRS or MSR instruction executed at EL1.

This field is 0 in ESR_EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SET, bits [12:11]

Synchronous Error Type. When the RAS Extension is implemented and DFSC is 0b010000, describes the state of the PE after taking the Data Abort exception. The possible values of this field are:

SET	Meaning
0b00	Recoverable error (UER).
0b10	Uncontainable error (UC).
0b11	Restartable error (UEO) or Corrected error (CE).

All other values are reserved.

Note

Software can use this information to determine what recovery might be possible. Taking a synchronous External Abort exception might result in an unrecoverable PE state.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the DFSC field is not 0b010000.

This field resets to an architecturally UNKNOWN value.

FnV, bit [10]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
0b0	FAR is valid.
0b1	FAR is not valid, and holds an UNKNOWN value.

This field is valid only if the DFSC code is 0b010000. It is RES0 for all other aborts.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

External abort type. This bit can provide an IMPLEMENTATION DEFINED classification of External aborts.

For any abort other than an External abort this bit returns a value of 0.

This field resets to an architecturally UNKNOWN value.

CM, bit [8]

Cache maintenance. Indicates whether the Data Abort came from a cache maintenance or address translation instruction:

CM	Meaning
0b0	The Data Abort was not generated by the execution of one of the System instructions identified in the description of value 1.
0b1	The Data Abort was generated by either the execution of a cache maintenance instruction or by a synchronous fault on the execution of an address translation instruction. The DC ZVA instruction is not classified as a cache maintenance instruction, and therefore its execution cannot cause this field to be set to 1.

This field resets to an architecturally UNKNOWN value.

S1PTW, bit [7]

For a stage 2 fault, indicates whether the fault was a stage 2 fault on an access made for a stage 1 translation table walk:

S1PTW	Meaning
0b0	Fault not on a stage 2 translation for a stage 1 translation table walk.
0b1	Fault on the stage 2 translation of an access for a stage 1 translation table walk.

For any abort other than a stage 2 fault this bit is RES0.

This field resets to an architecturally UNKNOWN value.

WnR, bit [6]

Write not Read. Indicates whether a synchronous abort was caused by an instruction writing to a memory location, or by an instruction reading from a memory location. The possible values of this bit are:

WnR	Meaning
0b0	Abort caused by an instruction reading from a memory location.
0b1	Abort caused by an instruction writing to a memory location.

For faults on cache maintenance and address translation instructions, this bit always returns a value of 1.

For faults from an atomic instruction that both reads and writes from a memory location, this bit is set to 0 if a read of the address specified by the instruction would have generated the fault which is being reported, otherwise it is set to 1. The architecture permits, but does not require, a relaxation of this requirement such that for all stage 2 aborts on stage 1 translation table walks for atomic instructions, the WnR bit is always 0.

This field is UNKNOWN for:

- An External abort on an Atomic access.
- A fault reported using a DFSC value of `0b110101` or `0b110001`, indicating an unsupported Exclusive or atomic access.

This field resets to an architecturally UNKNOWN value.

DFSC, bits [5:0]

Data Fault Status Code. ~~Possible values of this field are:~~

DFSC	Meaning	Applies when
0b000000	Address size fault, level 0 of translation or translation table base register.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000100	Translation fault, level 0.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk or hardware update of translation table.~~walk.~~	
0b010001	Synchronous Tag Check Fault.~~fail~~	When ARMv8.5-MemTag is implemented
0b010100	Synchronous External abort, on translation table walk or hardware update of translation table, level 0.	
0b010101	Synchronous External abort, on translation table walk or hardware update of translation table, level 1.	
0b010110	Synchronous External abort, on translation table walk or hardware update of translation table, level 2.	
0b010111	Synchronous External abort, on translation table walk or hardware update of translation table, level 3.	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011100	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 0.	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 1.	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 2.	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 3.	When RAS is not implemented
0b100001	Alignment fault.	
0b110000	TLB conflict abort.	
0b110001	Unsupported atomic hardware update fault. ~~Unsupported atomic hardware update fault, if the implementation includes ARMv8.1-TTHM]. Otherwise reserved.~~	When ARMv8.1-TTHM is implemented
0b110100	IMPLEMENTATION DEFINED fault (Lockdown).	

0b110101	IMPLEMENTATION DEFINED fault (Unsupported Exclusive or Atomic access).
0b111101	Section Domain Fault, used only for faults reported in the PAR_EL1.
0b111110	Page Domain Fault, used only for faults reported in the PAR_EL1.

All other values are reserved.

When the RAS Extension is implemented, 0b011000, 0b011100, 0b011101, 0b011110, and 0b011111, are reserved.

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

Because Access flag faults and Permission faults can only result from a Block or Page translation table descriptor, they cannot occur at level 0.

If the S1PTW bit is set, then the level refers the level of the stage2 translation that is translating a stage 1 translation walk.

This field resets to an architecturally UNKNOWN value.

ISS encoding for an exception from a trapped floating-point exception



Bit [24]

Reserved, RES0.

TFV, bit [23]

Trapped Fault Valid bit. Indicates whether the IDF, IXF, UFF, OFF, DZF, and IOF bits hold valid information about trapped floating-point exceptions. The possible values of this bit are:

TFV	Meaning
0b0	The IDF, IXF, UFF, OFF, DZF, and IOF bits do not hold valid information about trapped floating-point exceptions and are UNKNOWN.
0b1	One or more floating-point exceptions occurred during an operation performed while executing the reported instruction. The IDF, IXF, UFF, OFF, DZF, and IOF bits indicate trapped floating-point exceptions that occurred. For more information see 'Floating-point exception traps' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

It is IMPLEMENTATION DEFINED whether this field is set to 0 on an exception generated by a trapped floating point exception from a vector instruction.

Note

This is not a requirement. Implementations can set this field to 1 on a trapped floating-point exception from a vector instruction and return valid information in the {IDF, IXF, UFF, OFF, DZF, IOF} fields.

This field resets to an architecturally UNKNOWN value.

Bits [22:11]

Reserved, RES0.

VECITR, bits [10:8]

For a trapped floating-point exception from an instruction executed in AArch32 state this field is RES1.

For a trapped floating-point exception from an instruction executed in AArch64 state this field is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

IDF, bit [7]

Input Denormal floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

IDF	Meaning
0b0	Input denormal floating-point exception has not occurred.
0b1	Input denormal floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

Bits [6:5]

Reserved, RES0.

IXF, bit [4]

Inexact floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

IXF	Meaning
0b0	Inexact floating-point exception has not occurred.
0b1	Inexact floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

UFF, bit [3]

Underflow floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

UFF	Meaning
0b0	Underflow floating-point exception has not occurred.
0b1	Underflow floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

OFF, bit [2]

Overflow floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

OFF	Meaning
0b0	Overflow floating-point exception has not occurred.
0b1	Overflow floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

DZF, bit [1]

Divide by Zero floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

DZF	Meaning
0b0	Divide by Zero floating-point exception has not occurred.
0b1	Divide by Zero floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

IOF, bit [0]

Invalid Operation floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

IOF	Meaning
0b0	Invalid Operation floating-point exception has not occurred.
0b1	Invalid Operation floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

In an implementation that supports the trapping of floating-point exceptions:

- From an Exception level using AArch64, the FPCR.{IDE, IXE, UFE, OFE, DZE, IOE} bits enable each of the floating-point exception traps.
- From an Exception level using AArch32, the FPSCR.{IDE, IXE, UFE, OFE, DZE, IOE} bits enable each of the floating-point exception traps.

ISS encoding for an SError interrupt



IDS, bit [24]

IMPLEMENTATION DEFINED syndrome. Possible values of this bit are:

IDS	Meaning
0b0	Bits[23:0] of the ISS field holds the fields described in this encoding. **Note** If the RAS Extension is not implemented, this means that bits[23:0] of the ISS field are RES0.
0b1	Bits[23:0] of the ISS field holds IMPLEMENTATION DEFINED syndrome information that can be used to provide additional information about the SError interrupt.

Note

This field was previously called ISV.

This field resets to an architecturally UNKNOWN value.

Bits [23:14]

Reserved, RES0.

IESB, bit [13]

When ARMv8.2-IESB is implemented:

Implicit error synchronization event.

IESB	Meaning
0b0	The SError interrupt was either not synchronized by the implicit error synchronization event or not taken immediately.
0b1	The SError interrupt was synchronized by the implicit error synchronization event and taken immediately.

This field is RES0 if the value returned in the DFSC field is not 0b010001.

Note

Armv8.2 requires the implementation of the RAS Extension and ARMv8.2-IESB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

AET, bits [12:10]

When RAS is implemented:

Asynchronous Error Type.

When the RAS Extension is implemented and DFSC is 0b010001, describes the state of the PE after taking the SError interrupt exception. The possible values of this field are:

AET	Meaning
0b000	Uncontainable error (UC).
0b001	Unrecoverable error (UEU).
0b010	Restartable error (UEO).
0b011	Recoverable error (UER).
0b110	Corrected error (CE).

All other values are reserved.

If multiple errors are taken as a single SError interrupt exception, the overall state of the PE is reported. For example, if both a Recoverable and Unrecoverable error occurred, the state is Unrecoverable.

Note

Software can use this information to determine what recovery might be possible. The recovery software must also examine any implemented fault records to determine the location and extent of the error.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the DFSC field is not 0b010001.

Note

Armv8.2 requires the implementation of the RAS Extension.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

Otherwise:

Reserved, RES0.

EA, bit [9]

When RAS is implemented:

External abort type. When the RAS Extension is implemented, this bit can provide an IMPLEMENTATION DEFINED classification of External aborts.

For any abort other than an External abort this bit returns a value of 0.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the DFSC field is not `0b010001`.

~~Note~~

~~Armv8.2 requires the implementation of the RAS Extension.~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [8:6]

Reserved, RES0.

DFSC, bits [5:0]

When RAS is implemented:

Data Fault Status Code. ~~When the RAS Extension is implemented, possible values of this field are:~~

DFSC	Meaning
`0b000000`	Uncategorized.
`0b010001`	Asynchronous SError interrupt.

All other values are reserved.

~~If the RAS Extension is not implemented, this field is RES0.~~

~~Note~~

~~Armv8.2 requires the implementation of the RAS Extension.~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ISS encoding for an exception from a Breakpoint or Vector Catch debug exception



Bits [24:6]

Reserved, RES0.

IFSC, bits [5:0]

Instruction Fault Status Code.

~~Instruction Fault Status Code. This field is set to 0b100010, to indicate a Debug exception.~~

IFSC	Meaning
0b100010	Debug exception.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions:

- For exceptions from AArch64, see 'Breakpoint exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.
- For exceptions from AArch32, see 'Breakpoint exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ and 'Vector Catch exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

ISS encoding for an exception from a Software Step exception



ISV, bit [24]

Instruction syndrome valid. Indicates whether the EX bit, ISS[6], is valid, as follows:

ISV	Meaning
0b0	EX bit is RES0.
0b1	EX bit is valid.

See the EX bit description for more information.

This field resets to an architecturally UNKNOWN value.

Bits [23:7]

Reserved, RES0.

EX, bit [6]

Exclusive operation. If the ISV bit is set to 1, this bit indicates whether a Load-Exclusive instruction was stepped.

EX	Meaning
0b0	An instruction other than a Load-Exclusive instruction was stepped.
0b1	A Load-Exclusive instruction was stepped.

If the ISV bit is set to 0, this bit is RES0, indicating no syndrome data is available.

This field resets to an architecturally UNKNOWN value.

IFSC, bits [5:0]

Instruction Fault Status Code.

~~Instruction Fault Status Code. This field is set to 0b100010, to indicate a Debug exception.~~

IFSC	Meaning
0b100010	Debug exception.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see 'Software Step exceptions'~~ in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile,~~.

ISS encoding for an exception from a Watchpoint exception



Bits [24:14]

Reserved, RES0.

VNCR, bit [13]

When ARMv8.4-NV is implemented:

Indicates that the watchpoint came from use of VNCR_EL2 register by EL1 code.

VNCR	Meaning
0b0	The watchpoint was not generated by the use of VNCR_EL2 by EL1 code.
0b1	The watchpoint was generated by the use of VNCR_EL2 by EL1 code.

This field is 0 in ESR_EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [12:9]

Reserved, RES0.

CM, bit [8]

Cache maintenance. Indicates whether the Watchpoint exception came from a cache maintenance or address translation instruction:

CM	Meaning
0b0	The Watchpoint exception was not generated by the execution of one of the System instructions identified in the description of value 1.
0b1	The Watchpoint exception was generated by either the execution of a cache maintenance instruction or by a synchronous Watchpoint exception on the execution of an address translation instruction. The DC ZVA instruction is not classified as a cache maintenance instruction, and therefore its execution cannot cause this field to be set to 1.

This field resets to an architecturally UNKNOWN value.

Bit [7]

Reserved, RES0.

WnR, bit [6]

Write not Read. Indicates whether the Watchpoint exception was caused by an instruction writing to a memory location, or by an instruction reading from a memory location. The possible values of this bit are:

WnR	Meaning
0b0	Watchpoint exception caused by an instruction reading from a memory location.
0b1	Watchpoint exception caused by an instruction writing to a memory location.

For Watchpoint exceptions on cache maintenance and address translation instructions, this bit always returns a value of 1.

For Watchpoint exceptions from an atomic instruction, this field is set to 0 if a read of the location would have generated the Watchpoint exception, otherwise it is set to 1.

If multiple watchpoints match on the same access, it is UNPREDICTABLE which watchpoint generates the Watchpoint exception.

This field resets to an architecturally UNKNOWN value.

DFSC, bits [5:0]

Data Fault Status Code.

~~Data Fault Status Code. This field is set to 0b100010, to indicate a Debug exception.~~

DFSC	Meaning
0b100010	Debug exception.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see 'Watchpoint exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

ISS encoding for an exception from execution of a Breakpoint instruction



Bits [24:16]

Reserved, RES0.

Comment, bits [15:0]

Set to the instruction comment field value, zero extended as necessary. ~~For the AArch32 BKPT instructions, the comment field is described as the immediate field.~~

For the AArch32 BKPT instructions, the comment field is described as the immediate field.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see 'Breakpoint instruction exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

ISS encoding for an exception from ERET, ERETAA or ERETAB instruction



This EC value applies when ARMv8.6-FGT is implemented, or when HCR_EL2.NV is 1.

Bits [24:2]

Reserved, RES0.

ERET, bit [1]

Indicates whether an ERET or ERETA* instruction was trapped to EL2. Possible values are:

ERET	Meaning
0b0	ERET instruction trapped to EL2.
0b1	ERETAA or ERETAB instruction trapped to EL2.

If this bit is 0, the ERETA field is RES0.

This field resets to an architecturally UNKNOWN value.

ERETA, bit [0]

Indicates whether an ERETAA or ERETAB instruction was trapped to EL2. Possible values are:

ERETA	Meaning
0b0	ERETAA instruction trapped to EL2.
0b1	ERETAB instruction trapped to EL2.

When the ERET field is 0, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see HCR_EL2.NV.

If ARMv8.6-FGT is implemented, HFGITR_EL2.ERET controls fine-grained trap exceptions from ERET, ERETAA and ERETAB execution.

ISS encoding for an exception from Branch Target Identification instruction



Bits [24:2]

Reserved, RES0.

BTYPE, bits [1:0]

This field is set to the PSTATE.BTYPE value that generated the Branch Target Exception.

For more information about generating these exceptions, see 'The AArch64 application level programmers model' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section B1~~.

ISS encoding for an exception from a Pointer Authentication instruction when HCR_EL2.API == 0 || SCR_EL3.API == 0



Bits [24:0]

Reserved, RES0.

For more information about generating these exceptions, see:

- HCR_EL2.API, for exceptions from Pointer authentication instructions, using AArch64 state, trapped to EL2.
- SCR_EL3.API, for exceptions from Pointer authentication instructions, using AArch64 state, trapped to EL3.

ISS encoding for an exception from a Pointer Authentication instruction authentication failure



Bits [24:2]

Reserved, RES0.

Bit [1], bit [1]

This field indicates whether the exception is as a result of an Instruction key or a Data key.

	Meaning
0b0	Instruction Key.
0b1	Data Key.

This field resets to an architecturally UNKNOWN value.

Bit [0], bit [0]

This field indicates whether the exception is as a result of an A key or a B key.

	Meaning
0b0	A key.
0b1	B key.

This field resets to an architecturally UNKNOWN value.

The following instructions generate an exception when the Pointer Authentication Code (PAC) is incorrect:

- AUTIASP, AUTIAZ, AUTIA1716.
- AUTIBSP, AUTIBZ, AUTIB1716.
- AUTIA, AUTDA, AUTIB, AUTDB.
- AUTIZA, AUTIZB, AUTDZA, AUTDZB.

It is IMPLEMENTATION DEFINED whether the following instructions generate an exception directly from the authorization failure, rather than changing the address in a way that will generate a translation fault when the address is accessed:

- RETAA, RETAB.
- BRAA, BRAB, BLRAA, BLRAB.
- BRAAZ, BRABZ, BLRAAZ, BLRABZ.
- ERETAA, ERETAB.
- LDRAA, LDRAB, whether the authenticated address is written back to the base register or not.

Accessing the ESR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic ESR_EL1 or ESR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, ESR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ESR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x138];
    else
        return ESR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return ESR_EL2;
    else
        return ESR_EL1;
elsif PSTATE.EL == EL3 then
    return ESR_EL1;
```

```
MSR ESR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ESR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x138] = X[t];
    else
        ESR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        ESR_EL2 = X[t];
    else
        ESR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ESR_EL1 = X[t];
```

```
MRS <Xt>, ESR_EL12
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x138];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return ESR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return ESR_EL1;
    else
        UNDEFINED;
```

MSR ESR_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x138] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        ESR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        ESR_EL1 = X[t];
    else
        UNDEFINED;
```

MRS <Xt>, ESR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return ESR_EL1;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return ESR_EL2;
elsif PSTATE.EL == EL3 then
    return ESR_EL2;
```

```
MSR ESR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        ESR_EL1 = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    ESR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    ESR_EL2 = X[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f211~~6134483bd14dc8c12a99c984cbfe3431cc1c9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ESR_EL2, Exception Syndrome Register (EL2)

The ESR_EL2 characteristics are:

Purpose

Holds syndrome information for an exception taken to EL2.

Configuration

AArch64 System register ESR_EL2 bits [31:0] are architecturally mapped to AArch32 System register HSR[31:0] .

If EL2 is not implemented, this register is RES0 from EL3.

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ESR_EL2 is a 64-bit register.

Field descriptions

The ESR_EL2 bit assignments are:



ESR_EL2 is made UNKNOWN as a result of an exception return from EL2.

When an UNPREDICTABLE instruction is treated as UNDEFINED, and the exception is taken to EL2, the value of ESR_EL2 is UNKNOWN. The value written to ESR_EL2 must be consistent with a value that could be created as a result of an exception from the same Exception level that generated the exception as a result of a situation that is not UNPREDICTABLE at that Exception level, in order to avoid the possibility of a privilege violation.

Bits [63:32]

Reserved, RES0.

EC, bits [31:26]

Exception Class. Indicates the reason for the exception that this register holds information about.

For each EC value, the table references a subsection that gives information about:

- The cause of the exception, for example the configuration required to enable the trap.
- The encoding of the associated ISS.

Possible values of the EC field are:

EC	Meaning	ISS	Applies when
0b000000	Unknown reason.	ISS encoding for exceptions with an unknown reason	
0b000001	Trapped WFI or WFE instruction execution. Conditional WFE and WFI instructions that fail their condition code check do not cause an exception.	ISS encoding for an exception from a WFI or WFE instruction	
0b000011	Trapped MCR or MRC access with (coproc==0b1111) that is not reported using EC 0b000000.	ISS encoding for an exception from an MCR or MRC access	When AArch32 is supported at any Exception level
0b000100	Trapped MCRR or MRRC access with (coproc==0b1111) that is not reported using EC 0b000000.	ISS encoding for an exception from an MCRR or MRRC access	When AArch32 is supported at any Exception level
0b000101	Trapped MCR or MRC access with (coproc==0b1110).	ISS encoding for an exception from an MCR or MRC access	When AArch32 is supported at any Exception level
0b000110	Trapped LDC or STC access. The only architected uses of these instruction are: • An STC to write data to memory from DBGDTRRXint. • An LDC to read data from memory to DBGDTRTXint.	ISS encoding for an exception from an LDC or STC instruction	When AArch32 is supported at any Exception level
0b000111	Access to SVE, Advanced SIMD, or floating-point functionality trapped by CPACR_EL1.FPEN, CPTR_EL2.FPEN, CPTR_EL2.TFP, or CPTR_EL3.TFP control. Excludes exceptions resulting from CPACR_EL1 when the value of HCR_EL2.TGE is 1, or because SVE or Advanced SIMD and floating-point are not implemented. These are reported with EC value 0b000000 as described in 'EC encodings when routing exceptions to EL2' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A	ISS encoding for an exception from an access to SVE, Advanced SIMD or floating-point functionality, resulting from CPACR_EL1.FPEN, CPTR_EL2.FPEN or CPTR_ELx.TFP	

	architecture profile, section D1.10.4.		
0b001000	Trapped VMRS access, from ID group trap, that is not reported using EC 0b000111.	ISS encoding for an exception from an MCR or MRC access	When AArch32 is supported at any Exception level
0b001001	Trapped use of a Pointer authentication instruction because HCR_EL2.API == 0 || SCR_EL3.API == 0.	ISS encoding for an exception from a Pointer Authentication instruction when HCR_EL2.API == 0 || SCR_EL3.API == 0	When ARMv8.3-PAuth is implemented
0b001100	Trapped MRRC access with (coproc==0b1110).	ISS encoding for an exception from an MCRR or MRRC access	When AArch32 is supported at any Exception level
0b001101	Branch Target Exception.	ISS encoding for an exception from Branch Target Identification instruction	When ARMv8.5-BTI is implemented
0b001110	Illegal Execution state.	ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault	
0b010001	SVC instruction execution in AArch32 state. This is reported in ESR_EL2 only when the exception is generated because the value of HCR_EL2.TGE is 1.	ISS encoding for an exception from HVC or SVC instruction execution	When AArch32 is supported at any Exception level
0b010010	HVC instruction execution in AArch32 state, when HVC is not disabled.	ISS encoding for an exception from HVC or SVC instruction execution	When AArch32 is supported at any Exception level
0b010011	SMC instruction execution in AArch32 state, when SMC is not disabled. This is reported in ESR_EL2 only when the exception is generated because the value of HCR_EL2.TSC is 1.	ISS encoding for an exception from SMC instruction execution in AArch32 state	When AArch32 is supported at any Exception level
0b010101	SVC instruction execution in AArch64 state.	ISS encoding for an exception from HVC or SVC instruction execution	When AArch64 is supported at any Exception level
0b010110	HVC instruction execution in AArch64 state, when HVC is not disabled.	ISS encoding for an exception from HVC or SVC instruction execution	When AArch64 is supported at any Exception level
0b010111	SMC instruction execution in AArch64 state, when SMC is not disabled. This is reported in ESR_EL2 only when	ISS encoding for an exception from SMC instruction execution in AArch64 state	When AArch64 is supported at any Exception level

	the exception is generated because the value of HCR_EL2.TSC is 1.		
0b011000	Trapped MSR, MRS or System instruction execution in AArch64 state, that is not reported using EC 0b000000, 0b000001 or 0b000111. ~~If ARMv8.4-IDST is implemented, also exceptions generated by a read access to the feature ID space.~~ ~~If ARMv8.0-CSV2 is implemented, also Cache Speculation Variant exceptions.~~ ~~If ARMv8.2-EVT is implemented, also traps for EL1 and EL0 Cache controls.~~ This includes all instructions that cause exceptions that are part of the encoding space defined in 'System instruction class encoding overview' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section C5.2.2, except for those exceptions reported using EC values 0b000000, 0b000001, or 0b000111.	ISS encoding for an exception from MSR, MRS, or System instruction execution in AArch64 state	When AArch64 is supported at any Exception level
0b011001	Access to SVE functionality trapped as a result of CPACR_EL1.ZEN, CPTR_EL2.ZEN, CPTR_EL2.TZ, or CPTR_EL3.EZ, that is not reported using EC 0b000000. ~~This EC is defined only if SVEis implemented.~~	ISS encoding for an exception from an access to SVE functionality, resulting from CPACR_EL1.ZEN, CPTR_EL2.ZEN, CPTR_EL2.TZ, or CPTR_EL3.EZ	When SVE is implemented
0b011010	Trapped ERET, ERETAA, or ERETAB instruction execution.	ISS encoding for an exception from ERET, ERETAA or ERETAB instruction	When ARMv8.3-PAuth is implemented and ARMv8.3-NV is implemented
0b011100	Exception from a Pointer Authentication instruction authentication failure	ISS encoding for an exception from a Pointer Authentication instruction	When ARMv8.3-FPAC is implemented

		authentication failure
0b100000	Instruction Abort from a lower Exception level.~~level, that might be using AArch32 or AArch64.~~ Used for MMU faults generated by instruction accesses and synchronous External aborts, including synchronous parity or ECC errors. Not used for debug related exceptions.	ISS encoding for an exception from an Instruction Abort
0b100001	Instruction Abort taken without a change in Exception level. Used for MMU faults generated by instruction accesses and synchronous External aborts, including synchronous parity or ECC errors. Not used for debug related exceptions.	ISS encoding for an exception from an Instruction Abort
0b100010	PC alignment fault exception.	ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault
0b100100	Data Abort from a lower Exception level, excluding Data Aborts taken to EL2 as a result of accesses generated associated with VNCR_EL2 as part of nested virtualization support. These Data Aborts might be generated from Exception levels in~~using~~ anyAArch32 Execution~~or~~ state.~~AArch64.~~ Used for MMU faults generated by data accesses, alignment faults other than those caused by Stack Pointer misalignment, and synchronous External aborts, including synchronous parity or ECC errors. Not	ISS encoding for an exception from a Data Abort

	used for debug related exceptions.		
0b100101	Data Abort without a change in Exception level, or Data Aborts taken to EL2 as a result of accesses generated associated with VNCR_EL2 as part of nested virtualization support. Used for MMU faults generated by data accesses, alignment faults other than those caused by Stack Pointer misalignment, and synchronous External aborts, including synchronous parity or ECC errors. Not used for debug related exceptions.	ISS encoding for an exception from a Data Abort	
0b100110	SP alignment fault exception.	ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault	
0b101000	Trapped floating-point exception taken from AArch32 state. This EC value is valid if the implementation supports trapping of floating-point exceptions, otherwise it is reserved. Whether a floating-point implementation supports trapping of floating-point exceptions is IMPLEMENTATION DEFINED.	ISS encoding for an exception from a trapped floating-point exception	When AArch32 is supported at any Exception level
0b101100	Trapped floating-point exception taken from AArch64 state. This EC value is valid if the implementation supports trapping of floating-point exceptions, otherwise it is reserved. Whether a floating-point implementation supports trapping of floating-point exceptions is	ISS encoding for an exception from a trapped floating-point exception	When AArch64 is supported at any Exception level

	IMPLEMENTATION DEFINED.		
0b101111	SError interrupt.	ISS encoding for an SError interrupt	
0b110000	Breakpoint exception from a lower Exception level.~~level, that might be using AArch32 or AArch64.~~	ISS encoding for an exception from a Breakpoint or Vector Catch debug exception	
0b110001	Breakpoint exception taken without a change in Exception level.	ISS encoding for an exception from a Breakpoint or Vector Catch debug exception	
0b110010	Software Step exception from a lower Exception level.~~level, that might be using AArch32 or AArch64.~~	ISS encoding for an exception from a Software Step exception	
0b110011	Software Step exception taken without a change in Exception level.	ISS encoding for an exception from a Software Step exception	
0b110100	Watchpoint from a lower Exception level, excluding Watchpoint Exceptions taken to EL2 as a result of accesses generated associated with VNCR_EL2 as part of nested virtualization support. These Watchpoint Exceptions might be generated from Exception levels using any~~AArch32 Execution or~~ state.~~AArch64~~	ISS encoding for an exception from a Watchpoint exception	
0b110101	Watchpoint exceptions without a change in Exception level, or Watchpoint exceptions taken to EL2 as a result of accesses generated associated with VNCR_EL2 as part of nested virtualization support.	ISS encoding for an exception from a Watchpoint exception	
0b111000	BKPT instruction execution in AArch32 state.	ISS encoding for an exception from execution of a Breakpoint instruction	When AArch32 is supported at any Exception level
0b111010	Vector Catch exception from AArch32 state. The only case where a Vector Catch exception is taken to	ISS encoding for an exception from a Breakpoint or Vector Catch debug exception	When AArch32 is supported at any Exception level

	an Exception level that is using AArch64 is when the exception is routed to EL2 and EL2 is using AArch64.		
0b111100	BRK instruction execution in AArch64 state. This is reported in ESR_EL3 only if a BRK instruction is executed.	ISS encoding for an exception from execution of a Breakpoint instruction	When AArch64 is supported at any Exception level

All other EC values are reserved by Arm, and:

- Unused values in the range 0b000000 - 0b101100 (0x00 - 0x2C) are reserved for future use for synchronous exceptions.
- Unused values in the range 0b101101 - 0b111111 (0x2D - 0x3F) are reserved for future use, and might be used for synchronous or asynchronous exceptions.

The effect of programming this field to a reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Reserved values in System and memory-mapped registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.1.11.

This field resets to an architecturally UNKNOWN value.

IL, bit [25]

Instruction Length for synchronous exceptions. Possible values of this bit are:

IL	Meaning
0b0	16-bit instruction trapped.
0b1	32-bit instruction trapped. This value is also used when the exception is one of the following: • An SError interrupt. • An Instruction Abort exception. • A PC alignment fault exception. • An SP alignment fault exception. • A Data Abort exception for which the value of the ISV bit is 0. • An Illegal Execution state exception. • Any debug exception except for Breakpoint instruction exceptions. For Breakpoint instruction exceptions, this bit has its standard meaning: ◦ 0b0: 16-bit T32 BKPT instruction. ◦ 0b1: 32-bit A32 BKPT instruction or A64 BRK instruction. • An exception reported using EC value 0b000000.

This field resets to an architecturally UNKNOWN value.

ISS, bits [24:0]

Instruction Specific Syndrome. Architecturally, this field can be defined independently for each defined Exception class. However, in practice, some ISS encodings are used for more than one Exception class.

Typically, an ISS encoding has a number of subfields. When an ISS subfield holds a register number, the value returned in that field is the AArch64 view of the register number.

~~Typically, an ISS encoding has a number of subfields. When an ISS subfield holds a register number, the value returned in that field is the AArch64 view of the register number. For an exception taken from AArch32 state, 'Mapping of the general-purpose registers between the Execution states' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

For an exception taken from AArch32 state, 'Mapping of the general-purpose registers between the Execution states'.

If the AArch32 register descriptor is 0b1111, then:

- If the instruction that generated the exception was not UNPREDICTABLE, the field takes the value `0b11111`.
- If the instruction that generated the exception was UNPREDICTABLE, the field takes an UNKNOWN value that must be either:
  - The AArch64 view of the register number of a register that might have been used at the Exception level from which the exception was taken.
  - The value `0b11111`.

When the EC field is `0b000000`, indicating an exception with an unknown reason, the ISS field is not valid, RES0.

ISS encoding for exceptions with an unknown reason

24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								

Bits [24:0]

Reserved, RES0.

When an exception is reported using this EC code the IL field is set to 1.

This EC code is used for all exceptions that are not covered by any other EC value. This includes exceptions that are generated in the following situations:

- The attempted execution of an instruction bit pattern that has no allocated instruction or that is not accessible at the current Exception level and Security state, including:
  - A read access using a System register pattern that is not allocated for reads or that does not permit reads at the current Exception level and Security state.
  - A write access using a System register pattern that is not allocated for writes or that does not permit writes at the current Exception level and Security state.
  - Instruction encodings that are unallocated.
  - Instruction encodings for instructions or System registers that are not implemented in the implementation.
- In Debug state, the attempted execution of an instruction bit pattern that is not accessible in Debug state.
- In Non-debug state, the attempted execution of an instruction bit pattern that is not accessible in Non-debug state.
- In AArch32 state, attempted execution of a short vector floating-point instruction.
- In an implementation that does not include Advanced SIMD and floating-point functionality, an attempted access to Advanced SIMD or floating-point functionality under conditions where that access would be permitted if that functionality was present. This includes the attempted execution of an Advanced SIMD or floating-point instruction, and attempted accesses to Advanced SIMD and floating-point System registers.
- An exception generated because of the value of one of the SCTLR_EL1.{ITD, SED, CP15BEN} control bits.
- Attempted execution of:
  - An HVC instruction when disabled by HCR_EL2.HCD or SCR_EL3.HCE.
  - An SMC instruction when disabled by SCR_EL3.SMD.
  - An HLT instruction when disabled by EDSCR.HDE.
- Attempted execution of an MSR or MRS instruction to access SP_EL0 when the value of SPSel.SP is 0.
- Attempted execution, in Debug state, of:
  - A DCPS1 instruction when the value of HCR_EL2.TGE is 1 and EL2 is disabled or not implemented in the current Security state.
  - A DCPS2 instruction from EL1 or EL0 when EL2 is disabled or not implemented in the current Security state.
  - A DCPS3 instruction when the value of EDSCR.SDD is 1, or when EL3 is not implemented.
- When EL3 is using AArch64, attempted execution from Secure EL1 of an SRS instruction using R13_mon. See 'Traps to EL3 of monitor functionality from Secure EL1 using AArch32' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.
- In Debug state when the value of EDSCR.SDD is 1, the attempted execution at EL2, EL1, or EL0 of an instruction that is configured to trap to EL3.
- In AArch32 state, the attempted execution of an MRS (banked register) or an MSR (banked register) instruction to SPSR_mon, SP_mon, or LR_mon.
- An exception that is taken to EL2 because the value of HCR_EL2.TGE is 1 that, if the value of HCR_EL2.TGE was 0 would have been reported with an ESR_ELx.EC value of `0b000111`.
- ~~When SVE is not implemented, attempted execution of:~~
  - ~~An SVE instruction.~~
  - ~~An MSR or MRS instruction to access ZCR_EL1, ZCR_EL2, or ZCR_EL3.~~

ISS encoding for an exception from a WFI or WFE instruction



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to 0b1110.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to 0b1110.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to 0b1110, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to 0b1110, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Bits [19:1]

Reserved, RES0.

TI, bit [0]

Trapped instruction. Possible values of this bit are:

TI	Meaning
0b0	WFI trapped.
0b1	WFE trapped.

This field resets to an architecturally UNKNOWN value.

The following fields describe configuration settings for generating this exception:

- SCTLR_EL1.{nTWE, nTWI}.
- HCR_EL2.{TWE, TWI}.
- SCR_EL3.{TWE, TWI}.

ISS encoding for an exception from an MCR or MRC access



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to 0b1110.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to 0b1110.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to 0b1110, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to 0b1110, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Opc2, bits [19:17]

The Opc2 value from the issued instruction.

For a trapped VMRS access, holds the value 0b000.

This field resets to an architecturally UNKNOWN value.

Opc1, bits [16:14]

The Opc1 value from the issued instruction.

For a trapped VMRS access, holds the value 0b111.

This field resets to an architecturally UNKNOWN value.

CRn, bits [13:10]

The CRn value from the issued instruction.

For a trapped VMRS access, holds the reg field from the VMRS instruction encoding.

This field resets to an architecturally UNKNOWN value.

Rt, bits [9:5]

The Rt value from the issued instruction, the general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

CRm, bits [4:1]

The CRm value from the issued instruction.

For a trapped VMRS access, holds the value 0b0000.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
0b0	Write to System register space. MCR instruction.
0b1	Read from System register space. MRC or VMRS instruction.

This field resets to an architecturally UNKNOWN value.

The following fields describe configuration settings for generating exceptions that are reported using EC value 0b000011:

- CNTKCTL_EL1.{EL0PTEN, EL0VTEN, EL0PCTEN, EL0VCTEN}, for accesses to the Generic Timer Registers from EL0 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL1 or EL2.
- PMUSERENR_EL0.{ER, CR, SW, EN}, for accesses to Performance Monitor registers from EL0 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL1 or EL2.
- AMUSERENR_EL0.EN, for accesses to Activity Monitors registers from EL0 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL1 or EL2.
- HCR_EL2.{TRVM, TVM}, for accesses to virtual memory control registers from EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- HCR_EL2.TTLB, for execution of TLB maintenance instructions at EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- HCR_EL2.{TSW, TPC, TPU} for execution of cache maintenance instructions at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- HCR_EL2.TACR, for accesses to the Auxiliary Control Register at EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.

- HCR_EL2.TIDCP, for accesses to lockdown, DMA, and TCM operations at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- HCR_EL2.{TID1, TID2, TID3}, for accesses to ID registers at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- CPTR_EL2.TCPAC, for accesses to CPACR_EL1 or CPACR using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- HSTR_EL2.T<n>, for accesses to System registers using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- CNTHCTL_EL2.EL1PCEN, for accesses to the Generic Timer registers from EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- MDCR_EL2.{TPM, TPMCR}, for accesses to Performance Monitor registers from EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- CPTR_EL2.TAM, for accesses to Activity Monitors registers from EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- CPTR_EL3.TCPAC, for accesses to CPACR from EL1 and EL2, and accesses to HCPTR from EL2 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL3.
- MDCR_EL3.TPM, for accesses to Performance Monitor registers from EL0, EL1 and EL2 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL3.
- CPTR_EL3.TAM, for accesses to Activity Monitors registers from EL0, EL1 and EL2 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL3.
- See 'Traps to EL3 of Secure monitor functionality from Secure EL1 using AArch32' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ for information on other traps using EC value 0b000011.
- If ARMv8.6-FGT is implemented, MCR or MRC access to some registers at EL0, trapped to EL2.

The following fields describe configuration settings for generating exceptions that are reported using EC value 0b000101:

- CPACR_EL1.TTA for accesses to trace registers, MCR or MRC access (coproc == 0b1110) trapped to EL1 or EL2.
- MDSCR_EL1.TDCC, for accesses to the Debug Communications Channel (DCC) registers at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1110) trapped to EL1 or EL2.
- If ARMv8.6-FGT is implemented, MDCR_EL2.TDCC and MDCR_EL3.TDCC, for accesses to the DCC registers at EL0 and EL1, trapped to EL2.
- HCR_EL2.TID0, for accesses to the JIDR register in the ID group 0 at EL0 and EL1 using AArch32, MRC access (coproc == 0b1110) trapped to EL2.
- CPTR_EL2.TTA, for accesses to trace registers using AArch32, MCR or MRC access (coproc == 0b1110) trapped to EL2.
- MDCR_EL2.TDRA, for accesses to Debug ROM registers DBGDRAR and AArch-DBGDSAR using AArch32, MCR or MRC access (coproc == 0b1110) trapped to EL2.
- MDCR_EL2.TDOSA, for accesses to powerdown debug registers, using AArch32 state, MCR or MRC access (coproc == 0b1110) trapped to EL2.
- MDCR_EL2.TDA, for accesses to other debug registers, using AArch32 state, MCR or MRC access (coproc == 0b1110) trapped to EL2.
- CPTR_EL3.TTA, for accesses to trace registers using AArch32, MCR or MRC access (coproc == 0b1110) trapped to EL3.
- MDCR_EL3.TDOSA, for accesses to powerdown debug registers using AArch32, MCR or MRC access (coproc == 0b1110) trapped to EL3.
- MDCR_EL3.TDA, for accesses to other debug registers, using AArch32, MCR or MRC access (coproc == 0b1110) trapped to EL3.

The following fields describe configuration settings for generating exceptions that are reported using EC value 0b001000:

- HCR_EL2.TID0, for accesses to the FPSID register in ID group 0 at EL1 using AArch32 state, VMRS access trapped to EL2.
- HCR_EL2.TID3, for accesses to registers in ID group 3 including MVFR0, MVFR1 and MVFR2, VMRS access trapped to EL2.

ISS encoding for an exception from an MCRR or MRRC access



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to 0b1110.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to 0b1110.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to 0b1110, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to 0b1110, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Opc1, bits [19:16]

The Opc1 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Bit [15]

Reserved, RES0.

Rt2, bits [14:10]

The Rt2 value from the issued instruction, the second general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states'~~ in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

This field resets to an architecturally UNKNOWN value.

Rt, bits [9:5]

The Rt value from the issued instruction, the first general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

CRm, bits [4:1]

The CRm value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
0b0	Write to System register space. MCRR instruction.
0b1	Read from System register space. MRRC instruction.

This field resets to an architecturally UNKNOWN value.

The following fields describe configuration settings for generating exceptions that are reported using EC value 0b000100:

- CNTKCTL_EL1.{EL0PTEN, EL0VTEN, EL0PCTEN, EL0VCTEN}, for accesses to the Generic Timer Registers from EL0 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL1 or EL2.
- PMUSERENR_EL0.{CR, EN}, for accesses to Performance Monitor registers from EL0 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL1 or EL2.
- AMUSERENR_EL0.{EN}, for accesses to Activity Monitors registers AMEVCNTR0<n> and AMEVCNTR1<n> from EL0 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL1 or EL2.
- HCR_EL2.{TRVM, TVM}, for accesses to virtual memory control registers from EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- HSTR_EL2.T<n>, for accesses to System registers using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- CNTHCTL_EL2.{EL1PCEN, EL1PCTEN}, for accesses to the Generic Timer registers from EL0 and EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- MDCR_EL2.{TPM, TPMCR}, for accesses to Performance Monitor registers from EL0 and EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- CPTR_EL2.TAM, for accesses to Activity Monitors registers registers AMEVCNTR0<n> and AMEVCNTR1<n> from EL0 and EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- MDCR_EL3.TPM, for accesses to Performance Monitor registers from EL0, EL1 and EL2 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL3.
- CPTR_EL3.TAM, for accesses to Activity Monitors registers from EL0, EL1 and EL2 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL3.
- If ARMv8.6-FGT is implemented, HDFGRTR_EL2.PMCCNTR_EL0 for MRRC access and HDFGWTR_EL2.PMCCNTR_EL0 for MCRR access to PMCCNTR at EL0, trapped to EL2.

The following sections describe configuration settings for generating exceptions that are reported using EC value 0b001100:

- CPACR_EL1.TTA for accesses to trace registers using MCR or MRC instructions, MCRR or MRRC access (coproc == 0b1110) trapped to EL1 or EL2.
- MDSCR_EL1.TDCC, for accesses to the Debug Communications Channel (DCC) registers DBGDSAR and DBGDRAR at EL0 using AArch32 state, MCRR or MRRC access (coproc == 0b1110) trapped to EL1 or EL2.
- CPTR_EL2.TTA, for accesses to trace registers using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL2.
- MDCR_EL2.TDRA, for accesses to Debug ROM registers DBGDRAR and AArch-DBGDSAR using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL2.
- CPTR_EL3.TTA, for accesses to trace registers using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL3.

- MDCR_EL3.TDOSA, for traps to powerdown debug registers using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL3.
- MDCR_EL3.TDA, for accesses to other debug registers, using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL3.

ISS encoding for an exception from an LDC or STC instruction



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to 0b1110.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to 0b1110.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to 0b1110, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to 0b1110, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

imm8, bits [19:12]

The immediate value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Bits [11:10]

Reserved, RES0.

Rn, bits [9:5]

The Rn value from the issued instruction, the general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field is valid only when AM[2] is 0, indicating an immediate form of the LDC or STC instruction. When AM[2] is 1, indicating a literal form of the LDC or STC instruction, this field is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

Offset, bit [4]

Indicates whether the offset is added or subtracted:

Offset	Meaning
0b0	Subtract offset.
0b1	Add offset.

This bit corresponds to the U bit in the instruction encoding.

This field resets to an architecturally UNKNOWN value.

AM, bits [3:1]

Addressing mode. The permitted values of this field are:

AM	Meaning
0b000	Immediate unindexed.
0b001	Immediate post-indexed.
0b010	Immediate offset.
0b011	Immediate pre-indexed.
0b100	For a trapped STC instruction or a trapped T32 LDC instruction this encoding is reserved.
0b110	For a trapped STC instruction, this encoding is reserved.

The values 0b101 and 0b111 are reserved. The effect of programming this field to a reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Reserved values in System and memory-mapped registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Bit [2] in this subfield indicates the instruction form, immediate or literal.

Bits [1:0] in this subfield correspond to the bits {P, W} in the instruction encoding.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
0b0	Write to memory. STC instruction.
0b1	Read from memory. LDC instruction.

This field resets to an architecturally UNKNOWN value.

The following fields describe the configuration settings for the traps that are reported using EC value 0b000110:

- MDSCR_EL1.TDCC, for accesses using AArch32 state, LDC access to DBGDTRTXint or STC access to DBGDTRRXint trapped to EL1 or EL2.

- MDCR_EL2.TDA, for accesses using AArch32 state, LDC access to DBGDTRTXint or STC access to DBGDTRRXint MCR or MRC access trapped to EL2.
- MDCR_EL3.TDA, for accesses using AArch32 state, LDC access to DBGDTRTXint or STC access to DBGDTRRXint MCR or MRC access trapped to EL3.
- If ARMv8.6-FGT is implemented, MDCR_EL2.TDCC and MDCR_EL3.TDCC, for accesses to the DCC registers at EL0 and EL1, trapped to EL2.

ISS encoding for an exception from an access to SVE, Advanced SIMD or floating-point functionality, resulting from CPACR_EL1.FPEN, CPTR_EL2.FPEN or CPTR_ELx.TFP



The accesses covered by this trap include:

- Execution of SVE or Advanced SIMD and floating-point instructions.
- Accesses to the Advanced SIMD and floating-point System registers.

For an implementation that does not include either SVE or support for floating-point and Advanced SIMD, the exception is reported using the EC value `0b000000`.

CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
`0b0`	The COND field is not valid.
`0b1`	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to `0b1110`.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to `0b1110`.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to `0b1110`, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean

that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Bits [19:0]

Reserved, RES0.

The following sections describe the configuration settings for the traps that are reported using EC value `0b000111`:

- CPACR_EL1.FPEN, for accesses to SIMD and floating-point registers trapped to EL1.
- CPTR_EL2.TFP, for accesses to SIMD and floating-point registers trapped to EL2.
- CPTR_EL2.TFP, for accesses to SIMD and floating-point registers trapped to EL3.

ISS encoding for an exception from an access to SVE functionality, resulting from CPACR_EL1.ZEN, CPTR_EL2.ZEN, CPTR_EL2.TZ, or CPTR_EL3.EZ



Bits [24:0]

When SVE is implemented:

Reserved, RES0.

Otherwise:

Reserved, RES0.

The accesses covered by this trap include:

- Execution of SVE instructions.
- Accesses to the SVE system registers, ZCR_ELx and ID_AA64ZFR0_EL1.

For an implementation that does not include SVE, the exception is reported using the EC value `0b000000`.

ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault



Bits [24:0]

Reserved, RES0.

There are no configuration settings for generating Illegal Execution state exceptions and PC alignment fault exceptions. For more information about these exceptions see 'The Illegal Execution state exception' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ and 'PC alignment checking' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

'Stack pointer alignment checking' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ describes the configuration settings for generating SP alignment fault exceptions.

ISS encoding for an exception from HVC or SVC instruction execution



Bits [24:16]

Reserved, RES0.

imm16, bits [15:0]

The value of the immediate field from the HVC or SVC instruction.

For an HVC instruction, and for an A64 SVC instruction, this is the value of the imm16 field of the issued instruction.

For an A32 or T32 SVC instruction:

- If the instruction is unconditional, then:
  - For the T32 instruction, this field is zero-extended from the imm8 field of the instruction.
  - For the A32 instruction, this field is the bottom 16 bits of the imm24 field of the instruction.
- If the instruction is conditional, this field is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

In AArch32 state, the HVC instruction is unconditional, and a conditional SVC instruction generates an exception only if it passes its condition code check. Therefore, the syndrome information for these exceptions does not require conditionality information.

For T32 and A32 instructions, see 'SVC' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ and 'HVC' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

For A64 instructions, see 'SVC' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ and 'HVC' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

If ARMv8.6-FGT is implemented, HFGITR_EL2.{SVC_EL1, SVC_EL0} control fine-grained traps on SVC execution.

ISS encoding for an exception from SMC instruction execution in AArch32 state



For an SMC instruction that completes normally and generates an exception that is taken to EL3, the ISS encoding is RES0.

For an SMC instruction that is trapped to EL2 from EL1 because HCR_EL2.TSC is 1, the ISS encoding is as shown in the diagram.

CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field is only valid if CCKNOWNPASS is 1, otherwise it is RES0.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to `0b1110`.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to `0b1110`.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to `0b1110`, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field is only valid if CCKNOWNPASS is 1, otherwise it is RES0.

This field resets to an architecturally UNKNOWN value.

CCKNOWNPASS, bit [19]

Indicates whether the instruction might have failed its condition code check.

CCKNOWNPASS	Meaning
`0b0`	The instruction was unconditional, or was conditional and passed its condition code check.
`0b1`	The instruction was conditional, and might have failed its condition code check.

Note

In an implementation in which an SMC instruction that fails it code check is not trapped, this field can always return the value 0.

This field resets to an architecturally UNKNOWN value.

Bits [18:0]

Reserved, RES0.

HCR_EL2.TSC describes the configuration settings for trapping SMC instructions to EL2.

See 'System calls' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ describes the case where these exceptions are trapped to EL3.

ISS encoding for an exception from SMC instruction execution in AArch64 state



Bits [24:16]

Reserved, RES0.

imm16, bits [15:0]

The value of the immediate field from the issued SMC instruction.

This field resets to an architecturally UNKNOWN value.

The value of ISS[24:0] described here is used both:

- When an SMC instruction is trapped from EL1 modes.
- When an SMC instruction is not trapped, so completes normally and generates an exception that is taken to EL3.

HCR_EL2.TSC describes the configuration settings for trapping SMC from EL1 modes.

'System calls' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ describes the case where these exceptions are trapped to EL3.

ISS encoding for an exception from MSR, MRS, or System instruction execution in AArch64 state



Bits [24:22]

Reserved, RES0.

Op0, bits [21:20]

The Op0 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Op2, bits [19:17]

The Op2 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Op1, bits [16:14]

The Op1 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

CRn, bits [13:10]

The CRn value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Rt, bits [9:5]

The Rt value from the issued instruction, the general-purpose register used for the transfer.

This field resets to an architecturally UNKNOWN value.

CRm, bits [4:1]

The CRm value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
0b0	Write access, including MSR instructions.
0b1	Read access, including MRS instructions.

This field resets to an architecturally UNKNOWN value.

For exceptions caused by System instructions, see 'System' subsection of 'Branches, exception generating and System instructions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ for the encoding values returned by an instruction.

The following fields describe configuration settings for generating the exception that is reported using EC value 0b011000:

- SCTLR_EL1.UCI, for execution of cache maintenance instructions using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- SCTLR_EL1.UCT, for accesses to CTR_EL0 using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- SCTLR_EL1.DZE, for execution of DC ZVA instructions using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- SCTLR_EL1.UMA, for accesses to the PSTATE interrupt masks using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- CPACR_EL1.TTA, for accesses to the trace registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- MDSCR_EL1.TDCC, for accesses to the Debug Communications Channel (DCC) registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- If ARMv8.6-FGT is implemented, MDCR_EL2.TDCC and MDCR_EL3.TDCC, for accesses to the DCC registers at EL0 and EL1, trapped to EL2.
- CNTKCTL_EL1.{EL0PTEN, EL0VTEN, EL0PCTEN, EL0VCTEN} accesses to the Generic Timer registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- PMUSERENR_EL0.{ER, CR, SW, EN}, for accesses to the Performance Monitor registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- AMUSERENR_EL0.EN, for accesses to Activity Monitors registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- HCR_EL2.{TRVM, TVM}, for accesses to virtual memory control registers using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TDZ, for execution of DC ZVA instructions using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TTLB, for execution of TLB maintenance instructions using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.{TSW, TPC, TPU}, for execution of cache maintenance instructions using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TACR, for accesses to the Auxiliary Control Register, ACTLR_EL1, using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TIDCP, for accesses to lockdown, DMA, and TCM operations using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.{TID1, TID2, TID3}, for accesses to ID group 1, ID group 2 or ID group 3 registers, using AArch64 state, MSR or MRS access trapped to EL2.
- CPTR_EL2.TCPAC, for accesses to CPACR_EL1, using AArch64 state, MSR or MRS access trapped to EL2.
- CPTR_EL2.TTA, for accesses to the trace registers, using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.TTRF, for accesses to the trace filter register, TRFCR_EL1, using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.TDRA, for accesses to Debug ROM registers, using AArch64 state, MSR or MRS access trapped to EL2.

- MDCR_EL2.TDOSA, for accesses to powerdown debug registers using AArch64 state, MSR or MRS access trapped to EL2.
- CNTHCTL_EL2.{EL1PCEN, EL1PCTEN}, for accesses to the Generic Timer registers using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.TDA, for accesses to debug registers using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.{TPM, TPMCR}, for accesses to Performance Monitor registers, using AArch64 state, MSR or MRS access trapped to EL2.
- CPTR_EL2.TAM, for accesses to Activity Monitors registers, using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.APK, for accesses to Pointer authentication key registers. using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.{NV, NV1}, for Nested virtualization register access, using AArch64 state, MSR or MRS access, trapped to EL2.
- HCR_EL2.AT, for execution of AT S1E* instructions, using AArch64 state, MSR or MRS access, trapped to EL2.
- HCR_EL2.{TERR, FIEN}, for accesses to RAS registers, using AArch64 state, MSR or MRS access, trapped to EL2.
- SCR_EL3.APK, for accesses to Pointer authentication key registers, using AArch64 state, MSR or MRS access trapped to EL3.
- SCR_EL3.ST, for accesses to the Counter-timer Physical Secure timer registers, using AArch64 state, MSR or MRS access trapped to EL3.
- SCR_EL3.{TERR, FIEN}, for accesses to RAS registers, using AArch64 state, MSR or MRS access trapped to EL3.
- CPTR_EL3.TCPAC, for accesses to CPTR_EL2 and CPACR_EL1 using AArch64 state, MSR or MRS access trapped to EL3.
- CPTR_EL3.TTA, for accesses to the trace registers, using AArch64 state, MSR or MRS access trapped to EL3.
- MDCR_EL3.TTRF, for accesses to the filter trace control registers, TRFCR_EL1 and TRFCR_EL2, using AArch64 state, MSR or MRS access trapped to EL3.
- MDCR_EL3.TDA, for accesses to debug registers, using AArch64 state, MSR or MRS access trapped to EL3.
- MDCR_EL3.TDOSA, for accesses to powerdown debug registers, using AArch64 state, MSR or MRS access trapped to EL3.
- MDCR_EL3.TPM, for accesses to Performance Monitor registers, using AArch64 state, MSR or MRS access trapped to EL3.
- CPTR_EL3.TAM, for accesses to Activity Monitors registers, using AArch64 state, MSR or MRS access, trapped to EL3.
- If ARMv8.2-EVT is implemented the following registers control traps for EL1 and EL0 Cache controls that use this EC value:~~,HCR_EL2.{TTLBOS, TTLBIS, TICAB, TOCU, TID4} and HCR2.{TTLBIS, TICAB, TOCU, TID4} control traps for EL1 and EL0 Cache controls that use this EC value.~~
  - HCR_EL2.{TTLBOS, TTLBIS, TICAB, TOCU, TID4}.
  - HCR2.{TTLBIS, TICAB, TOCU, TID4}.
- If ARMv8.6-FGT is implemented:
  - SCR_EL3.FGTEn, for accesses to the fine-grained trap registers, MSR or MRS access at EL2 trapped to EL3.
  - HFGRTR_EL2 for reads and HFGWTR_EL2 for writes of registers, using AArch64 state, MSR or MRS access at EL0 and EL1 trapped to EL2.
  - HFGITR_EL2 for execution of system instructions, MSR or MRS access trapped to EL2
  - HDFGRTR_EL2 for reads and HDFGWTR_EL2 for writes of registers, using AArch64 state, MSR or MRS access at EL0 and EL1 state trapped to EL2.
  - HAFGRTR_EL2 for reads of Activity Monitor counters, using AArch64 state, MRS access at EL0 and EL1 trapped to EL2.

ISS encoding for an IMPLEMENTATION DEFINED exception to EL3



IMPLEMENTATION DEFINED, bits [24:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

ISS encoding for an exception from an Instruction Abort



Bits [24:13]

Reserved, RES0.

SET, bits [12:11]

Synchronous Error Type. When the RAS Extension is implemented and IFSC is `0b010000`, describes the state of the PE after taking the Instruction Abort exception. The possible values of this field are:

SET	Meaning
`0b00`	Recoverable error (UER).
`0b10`	Uncontainable error (UC).
`0b11`	Restartable error (UEO) or Corrected error (CE).

All other values are reserved.

Note

Software can use this information to determine what recovery might be possible. Taking a synchronous External Abort exception might result in an unrecoverable PE state.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the IFSC field is not `0b010000`.

This field resets to an architecturally UNKNOWN value.

FnV, bit [10]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
`0b0`	FAR is valid.
`0b1`	FAR is not valid, and holds an UNKNOWN value.

This field is only valid if the IFSC code is `0b010000`. It is RES0 for all other aborts.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

External abort type. This bit can provide an IMPLEMENTATION DEFINED classification of External aborts.

For any abort other than an External abort this bit returns a value of 0.

This field resets to an architecturally UNKNOWN value.

Bit [8]

Reserved, RES0.

S1PTW, bit [7]

For a stage 2 fault, indicates whether the fault was a stage 2 fault on an access made for a stage 1 translation table walk:

S1PTW	Meaning
0b0	Fault not on a stage 2 translation for a stage 1 translation table walk.
0b1	Fault on the stage 2 translation of an access for a stage 1 translation table walk.

For any abort other than a stage 2 fault this bit is RES0.

This field resets to an architecturally UNKNOWN value.

Bit [6]

Reserved, RES0.

IFSC, bits [5:0]

Instruction Fault Status Code. ~~Possible values of this field are:~~

IFSC	Meaning	Applies when
0b000000	Address size fault, level 0 of translation or translation table base register.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000100	Translation fault, level 0.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk or hardware update of translation table.	
0b010100	Synchronous External abort, on translation table walk or hardware update of translation table, level 0.~~0~~	
0b010101	Synchronous External abort, on translation table walk or hardware update of translation table, level 1.~~1~~	
0b010110	Synchronous External abort, on translation table walk or hardware update of translation table, level 2.~~2~~	
0b010111	Synchronous External abort, on translation table walk or hardware update of translation table, level 3.~~3~~	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011100	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 0.~~0~~	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 1.~~1~~	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 2.~~2~~	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 3.~~3~~	When RAS is not implemented
0b110000	TLB conflict abort.	
0b110001	Unsupported atomic hardware update fault. ~~Unsupported atomic hardware update fault, if the implementation includes ARMv8.1-TTHM].~~ ~~Otherwise reserved.~~	When ARMv8.1-TTHM is implemented

All other values are reserved.

~~When the RAS Extension is implemented, 0b011000, 0b011100, 0b011101, 0b011110, and 0b011111, are reserved.~~

Note

Armv8.2 requires the implementation of the RAS Extension.

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

Because Access flag faults and Permission faults can only result from a Block or Page translation table descriptor, they cannot occur at level 0.

If the S1PTW bit is set, then the level refers the level of the stage2 translation that is translating a stage 1 translation walk.

This field resets to an architecturally UNKNOWN value.

ISS encoding for an exception from a Data Abort



ISV, bit [24]

Instruction Syndromesyndrome Valid.valid. Indicates whether the syndrome information in ISS[23:14] is valid.

ISV	Meaning
0b0	No valid instruction syndrome. ISS[23:14] are RES0.
0b1	ISS[23:14] hold a valid instruction syndrome.

This bit is 0 for all faults reported in ESR_EL2 except the following stage 2 aborts:

- AArch64 loads and stores of a single general-purpose register (including the register specified with 0b11111, including those with Acquire/Release semantics, but excluding Load Exclusive or Store Exclusive and excluding those with writeback.
- AArch32 instructions where the instruction:
  - Is an LDR, LDA, LDRT, LDRSH, LDRSHT, LDRH, LDAH, LDRHT, LDRSB, LDRSBT, LDRB, LDAB, LDRBT, STR, STL, STRT, STRH, STLH, STRHT, STRB, STLB, or STRBT instruction.
  - Is not performing register writeback.
  - Is not using R15 as a source or destination register.

For these cases, ISV is UNKNOWN if the exception was generated in Debug state in memory access mode, and otherwise indicates whether ISS[23:14] hold a valid syndrome.

ISV is 0 for all faults reported in ESR_EL1 or ESR_EL3.

When the RAS Extension is implemented, ISV is 0 for any synchronous External abort.

For ISS reporting, a stage 2 abort on a stage 1 translation table walk does not return a valid instruction syndrome, and therefore ISV is 0 for these aborts.

When the RAS Extension is not implemented, the value of ISV on a synchronous External abort on a stage 2 translation table walk is IMPLEMENTATION DEFINED.

When ARMv8.5-MemTag is implemented, for a synchronous Tag Check Fault abort taken to ELx, ESR_ELx.FNV is 0 and FAR_ELx is valid.

This field resets to an architecturally UNKNOWN value.

SAS, bits [23:22]

Syndrome Access Size. When ISV is 1, indicates the size of the access attempted by the faulting operation.

SAS	Meaning
0b00	Byte
0b01	Halfword
0b10	Word
0b11	Doubleword

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

SSE, bit [21]

Syndrome Sign Extend. When ISV is 1, for a byte, halfword, or word load operation, indicates whether the data item must be sign extended. For these cases, the possible values of this bit are:

SSE	Meaning
0b0	Sign-extension not required.
0b1	Data item must be sign-extended.

For all other operations this bit is 0.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

SRT, bits [20:16]

Syndrome Register Transfer. When ISV is 1, the register number of the Rt operand of the faulting instruction.

~~Syndrome Register transfer. When ISV is 1, the register number of the Rt operand of the faulting instruction. If the exception was taken from an Exception level that is using AArch32 then this is the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

If the exception was taken from an Exception level that is using AArch32 then this is the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states'.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

SF, bit [15]

Width of the register accessed by the instruction is Sixty-Four. When ISV is 1, the possible values of this bit are:

SF	Meaning
0b0	Instruction loads/stores a 32-bit wide register.
0b1	Instruction loads/stores a 64-bit wide register.

Note

This field specifies the register width identified by the instruction, not the Execution state.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

AR, bit [14]

Acquire/Release. When ISV is 1, the possible values of this bit are:

AR	Meaning
0b0	Instruction did not have acquire/release semantics.
0b1	Instruction did have acquire/release semantics.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

VNCR, bit [13]

When ARMv8.4-NV is implemented:

Indicates that the fault came from use of VNCR_EL2 register by EL1 code.

VNCR	Meaning
0b0	The fault was not generated by the use of VNCR_EL2, by an MRS or MSR instruction executed at EL1.
0b1	The fault was generated by the use of VNCR_EL2, by an MRS or MSR instruction executed at EL1.

This field is 0 in ESR_EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SET, bits [12:11]

Synchronous Error Type. When the RAS Extension is implemented and DFSC is 0b010000, describes the state of the PE after taking the Data Abort exception. The possible values of this field are:

SET	Meaning
0b00	Recoverable error (UER).
0b10	Uncontainable error (UC).
0b11	Restartable error (UEO) or Corrected error (CE).

All other values are reserved.

Note

Software can use this information to determine what recovery might be possible. Taking a synchronous External Abort exception might result in an unrecoverable PE state.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the DFSC field is not 0b010000.

This field resets to an architecturally UNKNOWN value.

FnV, bit [10]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
0b0	FAR is valid.
0b1	FAR is not valid, and holds an UNKNOWN value.

This field is valid only if the DFSC code is 0b010000. It is RES0 for all other aborts.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

External abort type. This bit can provide an IMPLEMENTATION DEFINED classification of External aborts.

For any abort other than an External abort this bit returns a value of 0.

This field resets to an architecturally UNKNOWN value.

CM, bit [8]

Cache maintenance. Indicates whether the Data Abort came from a cache maintenance or address translation instruction:

CM	Meaning
0b0	The Data Abort was not generated by the execution of one of the System instructions identified in the description of value 1.
0b1	The Data Abort was generated by either the execution of a cache maintenance instruction or by a synchronous fault on the execution of an address translation instruction. The DC ZVA instruction is not classified as a cache maintenance instruction, and therefore its execution cannot cause this field to be set to 1.

This field resets to an architecturally UNKNOWN value.

S1PTW, bit [7]

For a stage 2 fault, indicates whether the fault was a stage 2 fault on an access made for a stage 1 translation table walk:

S1PTW	Meaning
0b0	Fault not on a stage 2 translation for a stage 1 translation table walk.
0b1	Fault on the stage 2 translation of an access for a stage 1 translation table walk.

For any abort other than a stage 2 fault this bit is RES0.

This field resets to an architecturally UNKNOWN value.

WnR, bit [6]

Write not Read. Indicates whether a synchronous abort was caused by an instruction writing to a memory location, or by an instruction reading from a memory location. The possible values of this bit are:

WnR	Meaning
0b0	Abort caused by an instruction reading from a memory location.
0b1	Abort caused by an instruction writing to a memory location.

For faults on cache maintenance and address translation instructions, this bit always returns a value of 1.

For faults from an atomic instruction that both reads and writes from a memory location, this bit is set to 0 if a read of the address specified by the instruction would have generated the fault which is being reported, otherwise it is set to 1. The architecture permits, but does not require, a relaxation of this requirement such that for all stage 2 aborts on stage 1 translation table walks for atomic instructions, the WnR bit is always 0.

This field is UNKNOWN for:

- An External abort on an Atomic access.
- A fault reported using a DFSC value of `0b110101` or `0b110001`, indicating an unsupported Exclusive or atomic access.

This field resets to an architecturally UNKNOWN value.

DFSC, bits [5:0]

Data Fault Status Code. ~~Possible values of this field are:~~

DFSC	Meaning	Applies when
0b000000	Address size fault, level 0 of translation or translation table base register.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000100	Translation fault, level 0.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk or hardware update of translation table.~~walk.~~	
0b010001	Synchronous Tag Check Fault.~~fail~~	When ARMv8.5-MemTag is implemented
0b010100	Synchronous External abort, on translation table walk or hardware update of translation table, level 0.	
0b010101	Synchronous External abort, on translation table walk or hardware update of translation table, level 1.	
0b010110	Synchronous External abort, on translation table walk or hardware update of translation table, level 2.	
0b010111	Synchronous External abort, on translation table walk or hardware update of translation table, level 3.	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011100	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 0.	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 1.	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 2.	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 3.	When RAS is not implemented
0b100001	Alignment fault.	
0b110000	TLB conflict abort.	
0b110001	Unsupported atomic hardware update fault. ~~Unsupported atomic hardware update fault, if the implementation includes ARMv8.1-TTHM]. Otherwise reserved.~~	When ARMv8.1-TTHM is implemented
0b110100	IMPLEMENTATION DEFINED fault (Lockdown).	

0b110101	IMPLEMENTATION DEFINED fault (Unsupported Exclusive or Atomic access).
0b111101	Section Domain Fault, used only for faults reported in the PAR_EL1.
0b111110	Page Domain Fault, used only for faults reported in the PAR_EL1.

All other values are reserved.

When the RAS Extension is implemented, 0b011000, 0b011100, 0b011101, 0b011110, and 0b011111, are reserved.

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

Because Access flag faults and Permission faults can only result from a Block or Page translation table descriptor, they cannot occur at level 0.

If the S1PTW bit is set, then the level refers the level of the stage2 translation that is translating a stage 1 translation walk.

This field resets to an architecturally UNKNOWN value.

ISS encoding for an exception from a trapped floating-point exception



Bit [24]

Reserved, RES0.

TFV, bit [23]

Trapped Fault Valid bit. Indicates whether the IDF, IXF, UFF, OFF, DZF, and IOF bits hold valid information about trapped floating-point exceptions. The possible values of this bit are:

TFV	Meaning
0b0	The IDF, IXF, UFF, OFF, DZF, and IOF bits do not hold valid information about trapped floating-point exceptions and are UNKNOWN.
0b1	One or more floating-point exceptions occurred during an operation performed while executing the reported instruction. The IDF, IXF, UFF, OFF, DZF, and IOF bits indicate trapped floating-point exceptions that occurred. For more information see 'Floating-point exception traps' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

It is IMPLEMENTATION DEFINED whether this field is set to 0 on an exception generated by a trapped floating point exception from a vector instruction.

Note

This is not a requirement. Implementations can set this field to 1 on a trapped floating-point exception from a vector instruction and return valid information in the {IDF, IXF, UFF, OFF, DZF, IOF} fields.

This field resets to an architecturally UNKNOWN value.

Bits [22:11]

Reserved, RES0.

VECITR, bits [10:8]

For a trapped floating-point exception from an instruction executed in AArch32 state this field is RES1.

For a trapped floating-point exception from an instruction executed in AArch64 state this field is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

IDF, bit [7]

Input Denormal floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

IDF	Meaning
0b0	Input denormal floating-point exception has not occurred.
0b1	Input denormal floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

Bits [6:5]

Reserved, RES0.

IXF, bit [4]

Inexact floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

IXF	Meaning
0b0	Inexact floating-point exception has not occurred.
0b1	Inexact floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

UFF, bit [3]

Underflow floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

UFF	Meaning
0b0	Underflow floating-point exception has not occurred.
0b1	Underflow floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

OFF, bit [2]

Overflow floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

OFF	Meaning
0b0	Overflow floating-point exception has not occurred.
0b1	Overflow floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

DZF, bit [1]

Divide by Zero floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

DZF	Meaning
0b0	Divide by Zero floating-point exception has not occurred.
0b1	Divide by Zero floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

IOF, bit [0]

Invalid Operation floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

IOF	Meaning
0b0	Invalid Operation floating-point exception has not occurred.
0b1	Invalid Operation floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

In an implementation that supports the trapping of floating-point exceptions:

- From an Exception level using AArch64, the FPCR.{IDE, IXE, UFE, OFE, DZE, IOE} bits enable each of the floating-point exception traps.
- From an Exception level using AArch32, the FPSCR.{IDE, IXE, UFE, OFE, DZE, IOE} bits enable each of the floating-point exception traps.

ISS encoding for an SError interrupt



IDS, bit [24]

IMPLEMENTATION DEFINED syndrome. Possible values of this bit are:

IDS	Meaning
0b0	Bits[23:0] of the ISS field holds the fields described in this encoding. **Note** If the RAS Extension is not implemented, this means that bits[23:0] of the ISS field are RES0.
0b1	Bits[23:0] of the ISS field holds IMPLEMENTATION DEFINED syndrome information that can be used to provide additional information about the SError interrupt.

Note

This field was previously called ISV.

This field resets to an architecturally UNKNOWN value.

Bits [23:14]

Reserved, RES0.

IESB, bit [13]

When ARMv8.2-IESB is implemented:

Implicit error synchronization event.

IESB	Meaning
0b0	The SError interrupt was either not synchronized by the implicit error synchronization event or not taken immediately.
0b1	The SError interrupt was synchronized by the implicit error synchronization event and taken immediately.

This field is RES0 if the value returned in the DFSC field is not 0b010001.

Note

Armv8.2 requires the implementation of the RAS Extension and ARMv8.2-IESB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

AET, bits [12:10]

When RAS is implemented:

Asynchronous Error Type.

When the RAS Extension is implemented and DFSC is 0b010001, describes the state of the PE after taking the SError interrupt exception. The possible values of this field are:

AET	Meaning
0b000	Uncontainable error (UC).
0b001	Unrecoverable error (UEU).
0b010	Restartable error (UEO).
0b011	Recoverable error (UER).
0b110	Corrected error (CE).

All other values are reserved.

If multiple errors are taken as a single SError interrupt exception, the overall state of the PE is reported. For example, if both a Recoverable and Unrecoverable error occurred, the state is Unrecoverable.

Note

Software can use this information to determine what recovery might be possible. The recovery software must also examine any implemented fault records to determine the location and extent of the error.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the DFSC field is not 0b010001.

Note

Armv8.2 requires the implementation of the RAS Extension.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

Otherwise:

Reserved, RES0.

EA, bit [9]

When RAS is implemented:

External abort type. When the RAS Extension is implemented, this bit can provide an IMPLEMENTATION DEFINED classification of External aborts.

For any abort other than an External abort this bit returns a value of 0.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the DFSC field is not `0b010001`.

~~Note~~

~~Armv8.2 requires the implementation of the RAS Extension.~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [8:6]

Reserved, RES0.

DFSC, bits [5:0]

When RAS is implemented:

Data Fault Status Code. ~~When the RAS Extension is implemented, possible values of this field are:~~

DFSC	Meaning
`0b000000`	Uncategorized.
`0b010001`	Asynchronous SError interrupt.

All other values are reserved.

~~If the RAS Extension is not implemented, this field is RES0.~~

~~Note~~

~~Armv8.2 requires the implementation of the RAS Extension.~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ISS encoding for an exception from a Breakpoint or Vector Catch debug exception



Bits [24:6]

Reserved, RES0.

IFSC, bits [5:0]

Instruction Fault Status Code.

~~Instruction Fault Status Code. This field is set to 0b100010, to indicate a Debug exception.~~

IFSC	Meaning
0b100010	Debug exception.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions:

- For exceptions from AArch64, see 'Breakpoint exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.
- For exceptions from AArch32, see 'Breakpoint exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ and 'Vector Catch exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

ISS encoding for an exception from a Software Step exception



ISV, bit [24]

Instruction syndrome valid. Indicates whether the EX bit, ISS[6], is valid, as follows:

ISV	Meaning
0b0	EX bit is RES0.
0b1	EX bit is valid.

See the EX bit description for more information.

This field resets to an architecturally UNKNOWN value.

Bits [23:7]

Reserved, RES0.

EX, bit [6]

Exclusive operation. If the ISV bit is set to 1, this bit indicates whether a Load-Exclusive instruction was stepped.

EX	Meaning
0b0	An instruction other than a Load-Exclusive instruction was stepped.
0b1	A Load-Exclusive instruction was stepped.

If the ISV bit is set to 0, this bit is RES0, indicating no syndrome data is available.

This field resets to an architecturally UNKNOWN value.

IFSC, bits [5:0]

Instruction Fault Status Code.

~~Instruction Fault Status Code. This field is set to 0b100010, to indicate a Debug exception.~~

IFSC	Meaning
0b100010	Debug exception.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see 'Software Step exceptions'~~ in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile,~~.

ISS encoding for an exception from a Watchpoint exception



Bits [24:14]

Reserved, RES0.

VNCR, bit [13]

When ARMv8.4-NV is implemented:

Indicates that the watchpoint came from use of VNCR_EL2 register by EL1 code.

VNCR	Meaning
0b0	The watchpoint was not generated by the use of VNCR_EL2 by EL1 code.
0b1	The watchpoint was generated by the use of VNCR_EL2 by EL1 code.

This field is 0 in ESR_EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [12:9]

Reserved, RES0.

CM, bit [8]

Cache maintenance. Indicates whether the Watchpoint exception came from a cache maintenance or address translation instruction:

CM	Meaning
0b0	The Watchpoint exception was not generated by the execution of one of the System instructions identified in the description of value 1.
0b1	The Watchpoint exception was generated by either the execution of a cache maintenance instruction or by a synchronous Watchpoint exception on the execution of an address translation instruction. The DC ZVA instruction is not classified as a cache maintenance instruction, and therefore its execution cannot cause this field to be set to 1.

This field resets to an architecturally UNKNOWN value.

Bit [7]

Reserved, RES0.

WnR, bit [6]

Write not Read. Indicates whether the Watchpoint exception was caused by an instruction writing to a memory location, or by an instruction reading from a memory location. The possible values of this bit are:

WnR	Meaning
0b0	Watchpoint exception caused by an instruction reading from a memory location.
0b1	Watchpoint exception caused by an instruction writing to a memory location.

For Watchpoint exceptions on cache maintenance and address translation instructions, this bit always returns a value of 1.

For Watchpoint exceptions from an atomic instruction, this field is set to 0 if a read of the location would have generated the Watchpoint exception, otherwise it is set to 1.

If multiple watchpoints match on the same access, it is UNPREDICTABLE which watchpoint generates the Watchpoint exception.

This field resets to an architecturally UNKNOWN value.

DFSC, bits [5:0]

Data Fault Status Code.

~~Data Fault Status Code. This field is set to 0b100010, to indicate a Debug exception.~~

DFSC	Meaning
0b100010	Debug exception.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see 'Watchpoint exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

ISS encoding for an exception from execution of a Breakpoint instruction



Bits [24:16]

Reserved, RES0.

Comment, bits [15:0]

Set to the instruction comment field value, zero extended as necessary. ~~For the AArch32 BKPT instructions, the comment field is described as the immediate field.~~

For the AArch32 BKPT instructions, the comment field is described as the immediate field.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see 'Breakpoint instruction exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

ISS encoding for an exception from ERET, ERETAA or ERETAB instruction



This EC value applies when ARMv8.6-FGT is implemented, or when HCR_EL2.NV is 1.

Bits [24:2]

Reserved, RES0.

ERET, bit [1]

Indicates whether an ERET or ERETA* instruction was trapped to EL2. Possible values are:

ERET	Meaning
0b0	ERET instruction trapped to EL2.
0b1	ERETAA or ERETAB instruction trapped to EL2.

If this bit is 0, the ERETA field is RES0.

This field resets to an architecturally UNKNOWN value.

ERETA, bit [0]

Indicates whether an ERETAA or ERETAB instruction was trapped to EL2. Possible values are:

ERETA	Meaning
0b0	ERETAA instruction trapped to EL2.
0b1	ERETAB instruction trapped to EL2.

When the ERET field is 0, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see HCR_EL2.NV.

If ARMv8.6-FGT is implemented, HFGITR_EL2.ERET controls fine-grained trap exceptions from ERET, ERETAA and ERETAB execution.

ISS encoding for an exception from Branch Target Identification instruction



Bits [24:2]

Reserved, RES0.

BTYPE, bits [1:0]

This field is set to the PSTATE.BTYPE value that generated the Branch Target Exception.

For more information about generating these exceptions, see 'The AArch64 application level programmers model' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section B1.

ISS encoding for an exception from a Pointer Authentication instruction when HCR_EL2.API == 0 || SCR_EL3.API == 0



Bits [24:0]

Reserved, RES0.

For more information about generating these exceptions, see:

- HCR_EL2.API, for exceptions from Pointer authentication instructions, using AArch64 state, trapped to EL2.
- SCR_EL3.API, for exceptions from Pointer authentication instructions, using AArch64 state, trapped to EL3.

ISS encoding for an exception from a Pointer Authentication instruction authentication failure



Bits [24:2]

Reserved, RES0.

Bit [1], bit [1]

This field indicates whether the exception is as a result of an Instruction key or a Data key.

	Meaning
0b0	Instruction Key.
0b1	Data Key.

This field resets to an architecturally UNKNOWN value.

Bit [0], bit [0]

This field indicates whether the exception is as a result of an A key or a B key.

	Meaning
0b0	A key.
0b1	B key.

This field resets to an architecturally UNKNOWN value.

The following instructions generate an exception when the Pointer Authentication Code (PAC) is incorrect:

- AUTIASP, AUTIAZ, AUTIA1716.
- AUTIBSP, AUTIBZ, AUTIB1716.
- AUTIA, AUTDA, AUTIB, AUTDB.
- AUTIZA, AUTIZB, AUTDZA, AUTDZB.

It is IMPLEMENTATION DEFINED whether the following instructions generate an exception directly from the authorization failure, rather than changing the address in a way that will generate a translation fault when the address is accessed:

- RETAA, RETAB.
- BRAA, BRAB, BLRAA, BLRAB.
- BRAAZ, BRABZ, BLRAAZ, BLRABZ.
- ERETAA, ERETAB.
- LDRAA, LDRAB, whether the authenticated address is written back to the base register or not.

Accessing the ESR_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic ESR_EL2 or ESR_EL1 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, ESR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return ESR_EL1;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return ESR_EL2;
elsif PSTATE.EL == EL3 then
    return ESR_EL2;
```

```
MSR ESR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        ESR_EL1 = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    ESR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    ESR_EL2 = X[t];
```

```
MRS <Xt>, ESR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.ESR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x138];
    else
        return ESR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return ESR_EL2;
    else
        return ESR_EL1;
elsif PSTATE.EL == EL3 then
    return ESR_EL1;
```

```
MSR ESR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.ESR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x138] = X[t];
    else
        ESR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        ESR_EL2 = X[t];
    else
        ESR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    ESR_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ESR_EL3, Exception Syndrome Register (EL3)

The ESR_EL3 characteristics are:

Purpose

Holds syndrome information for an exception taken to EL3.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to ESR_EL3 are UNDEFINED.

Attributes

ESR_EL3 is a 64-bit register.

Field descriptions

The ESR_EL3 bit assignments are:



ESR_EL3 is made UNKNOWN as a result of an exception return from EL3.

When an UNPREDICTABLE instruction is treated as UNDEFINED, and the exception is taken to EL3, the value of ESR_EL3 is UNKNOWN. The value written to ESR_EL3 must be consistent with a value that could be created as a result of an exception from the same Exception level that generated the exception as a result of a situation that is not UNPREDICTABLE at that Exception level, in order to avoid the possibility of a privilege violation.

Bits [63:32]

Reserved, RES0.

EC, bits [31:26]

Exception Class. Indicates the reason for the exception that this register holds information about.

For each EC value, the table references a subsection that gives information about:

- The cause of the exception, for example the configuration required to enable the trap.
- The encoding of the associated ISS.

Possible values of the EC field are:

EC	Meaning	ISS	Applies when
0b000000	Unknown reason.	ISS encoding for exceptions with an unknown reason	
0b000001	Trapped WFI or WFE instruction execution. Conditional WFE and WFI instructions that fail their condition code check do not cause an exception.	ISS encoding for an exception from a WFI or WFE instruction	
0b000011	Trapped MCR or MRC access with (coproc==0b1111) that is not reported using EC 0b000000.	ISS encoding for an exception from an MCR or MRC access	When AArch32 is supported at any Exception level
0b000100	Trapped MCRR or MRRC access with (coproc==0b1111) that is not reported using EC 0b000000.	ISS encoding for an exception from an MCRR or MRRC access	When AArch32 is supported at any Exception level
0b000101	Trapped MCR or MRC access with (coproc==0b1110).	ISS encoding for an exception from an MCR or MRC access	When AArch32 is supported at any Exception level
0b000110	Trapped LDC or STC access. The only architected uses of these instruction are: • An STC to write data to memory from DBGDTRRXint. • An LDC to read data from memory to DBGDTRTXint.	ISS encoding for an exception from an LDC or STC instruction	When AArch32 is supported at any Exception level
0b000111	Access to SVE, Advanced SIMD, or floating-point functionality trapped by CPACR_EL1.FPEN, CPTR_EL2.FPEN, CPTR_EL2.TFP, or CPTR_EL3.TFP control. Excludes exceptions resulting from CPACR_EL1 when the value of HCR_EL2.TGE is 1, or because SVE or Advanced SIMD and floating-point are not implemented. These are reported with EC value 0b000000 as described in 'EC encodings when routing exceptions to EL2' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A	ISS encoding for an exception from an access to SVE, Advanced SIMD or floating-point functionality, resulting from CPACR_EL1.FPEN, CPTR_EL2.FPEN or CPTR_ELx.TFP	

	architecture profile, section D1.10.4.		
0b001001	Trapped use of a Pointer authentication instruction because HCR_EL2.API == 0 || SCR_EL3.API == 0.	ISS encoding for an exception from a Pointer Authentication instruction when HCR_EL2.API == 0 || SCR_EL3.API == 0	When ARMv8.3-PAuth is implemented
0b001100	Trapped MRRC access with (coproc==0b1110).	ISS encoding for an exception from an MCRR or MRRC access	When AArch32 is supported at any Exception level
0b001101	Branch Target Exception.	ISS encoding for an exception from Branch Target Identification instruction	When ARMv8.5-BTI is implemented
0b001110	Illegal Execution state.	ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault	
0b010011	SMC instruction execution in AArch32 state, when SMC is not disabled. This is reported in ESR_EL2 only when the exception is generated because the value of HCR_EL2.TSC is 1.	ISS encoding for an exception from SMC instruction execution in AArch32 state	When AArch32 is supported at any Exception level
0b010101	SVC instruction execution in AArch64 state.	ISS encoding for an exception from HVC or SVC instruction execution	When AArch64 is supported at any Exception level
0b010110	HVC instruction execution in AArch64 state, when HVC is not disabled.	ISS encoding for an exception from HVC or SVC instruction execution	When AArch64 is supported at any Exception level
0b010111	SMC instruction execution in AArch64 state, when SMC is not disabled. This is reported in ESR_EL2 only when the exception is generated because the value of HCR_EL2.TSC is 1.	ISS encoding for an exception from SMC instruction execution in AArch64 state	When AArch64 is supported at any Exception level
0b011000	Trapped MSR, MRS or System instruction execution in AArch64 state, that is not reported using EC 0b000000, 0b000001 or 0b000111. ~~If ARMv8.4-IDST is implemented, also exceptions generated by a read access to the feature ID space.~~	ISS encoding for an exception from MSR, MRS, or System instruction execution in AArch64 state	When AArch64 is supported at any Exception level

	If ARMv8.0-CSV2 is implemented, also Cache Speculation Variant exceptions. This includes all instructions that cause exceptions that are part of the encoding space defined in 'System instruction class encoding overview' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section C5.2.2, except for those exceptions reported using EC values `0b000000`, `0b000001`, or `0b000111`.		
`0b011001`	Access to SVE functionality trapped as a result of CPACR_EL1.ZEN, CPTR_EL2.ZEN, CPTR_EL2.TZ, or CPTR_EL3.EZ, that is not reported using EC `0b000000`. This EC is defined only if SVEis implemented.	ISS encoding for an exception from an access to SVE functionality, resulting from CPACR_EL1.ZEN, CPTR_EL2.ZEN, CPTR_EL2.TZ, or CPTR_EL3.EZ	When SVE is implemented
`0b011100`	Exception from a Pointer Authentication instruction authentication failure	ISS encoding for an exception from a Pointer Authentication instruction authentication failure	When ARMv8.3-FPAC is implemented
`0b011111`	IMPLEMENTATION DEFINED exception to EL3.	ISS encoding for an IMPLEMENTATION DEFINED exception to EL3	
`0b100000`	Instruction Abort from a lower Exception level.level, that might be using AArch32 or AArch64. Used for MMU faults generated by instruction accesses and synchronous External aborts, including synchronous parity or ECC errors. Not used for debug related exceptions.	ISS encoding for an exception from an Instruction Abort	
`0b100001`	Instruction Abort taken without a change in Exception level. Used for MMU faults generated by instruction accesses	ISS encoding for an exception from an Instruction Abort	

	and synchronous External aborts, including synchronous parity or ECC errors. Not used for debug related exceptions.		
0b100010	PC alignment fault exception.	ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault	
0b100100	Data Abort from a lower Exception level.~~level, that might be using AArch32 or AArch64.~~ Used for MMU faults generated by data accesses, alignment faults other than those caused by Stack Pointer misalignment, and synchronous External aborts, including synchronous parity or ECC errors. Not used for debug related exceptions.	ISS encoding for an exception from a Data Abort	
0b100101	Data Abort taken without a change in Exception level. Used for MMU faults generated by data accesses, alignment faults other than those caused by Stack Pointer misalignment, and synchronous External aborts, including synchronous parity or ECC errors. Not used for debug related exceptions.	ISS encoding for an exception from a Data Abort	
0b100110	SP alignment fault exception.	ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault	
0b101100	Trapped floating-point exception taken from AArch64 state. This EC value is valid if the implementation supports trapping of floating-point exceptions, otherwise it is reserved. Whether a floating-point implementation	ISS encoding for an exception from a trapped floating-point exception	When AArch64 is supported at any Exception level

	supports trapping of floating-point exceptions is IMPLEMENTATION DEFINED.		
0b101111	SError interrupt.	ISS encoding for an SError interrupt	
0b111100	BRK instruction execution in AArch64 state. This is reported in ESR_EL3 only if a BRK instruction is executed.	ISS encoding for an exception from execution of a Breakpoint instruction	When AArch64 is supported at any Exception level

All other EC values are reserved by Arm, and:

- Unused values in the range 0b000000 - 0b101100 (0x00 - 0x2C) are reserved for future use for synchronous exceptions.
- Unused values in the range 0b101101 - 0b111111 (0x2D - 0x3F) are reserved for future use, and might be used for synchronous or asynchronous exceptions.

The effect of programming this field to a reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Reserved values in System and memory-mapped registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.1.11.

This field resets to an architecturally UNKNOWN value.

IL, bit [25]

Instruction Length for synchronous exceptions. Possible values of this bit are:

IL	Meaning
0b0	16-bit instruction trapped.
0b1	32-bit instruction trapped. This value is also used when the exception is one of the following: • An SError interrupt. • An Instruction Abort exception. • A PC alignment fault exception. • An SP alignment fault exception. • A Data Abort exception for which the value of the ISV bit is 0. • An Illegal Execution state exception. • Any debug exception except for Breakpoint instruction exceptions. For Breakpoint instruction exceptions, this bit has its standard meaning: ◦ 0b0: 16-bit T32 BKPT instruction. ◦ 0b1: 32-bit A32 BKPT instruction or A64 BRK instruction. • An exception reported using EC value 0b000000.

This field resets to an architecturally UNKNOWN value.

ISS, bits [24:0]

Instruction Specific Syndrome. Architecturally, this field can be defined independently for each defined Exception class. However, in practice, some ISS encodings are used for more than one Exception class.

Typically, an ISS encoding has a number of subfields. When an ISS subfield holds a register number, the value returned in that field is the AArch64 view of the register number.

~~Typically, an ISS encoding has a number of subfields. When an ISS subfield holds a register number, the value returned in that field is the AArch64 view of the register number. For an exception taken from AArch32 state, 'Mapping of the general-purpose registers between the Execution states' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

For an exception taken from AArch32 state, 'Mapping of the general-purpose registers between the Execution states'.

If the AArch32 register descriptor is `0b1111`, then:

- If the instruction that generated the exception was not UNPREDICTABLE, the field takes the value `0b11111`.
- If the instruction that generated the exception was UNPREDICTABLE, the field takes an UNKNOWN value that must be either:
  - The AArch64 view of the register number of a register that might have been used at the Exception level from which the exception was taken.
  - The value `0b11111`.

When the EC field is `0b000000`, indicating an exception with an unknown reason, the ISS field is not valid, RES0.

ISS encoding for exceptions with an unknown reason



Bits [24:0]

Reserved, RES0.

When an exception is reported using this EC code the IL field is set to 1.

This EC code is used for all exceptions that are not covered by any other EC value. This includes exceptions that are generated in the following situations:

- The attempted execution of an instruction bit pattern that has no allocated instruction or that is not accessible at the current Exception level and Security state, including:
  - A read access using a System register pattern that is not allocated for reads or that does not permit reads at the current Exception level and Security state.
  - A write access using a System register pattern that is not allocated for writes or that does not permit writes at the current Exception level and Security state.
  - Instruction encodings that are unallocated.
  - Instruction encodings for instructions or System registers that are not implemented in the implementation.
- In Debug state, the attempted execution of an instruction bit pattern that is not accessible in Debug state.
- In Non-debug state, the attempted execution of an instruction bit pattern that is not accessible in Non-debug state.
- In AArch32 state, attempted execution of a short vector floating-point instruction.
- In an implementation that does not include Advanced SIMD and floating-point functionality, an attempted access to Advanced SIMD or floating-point functionality under conditions where that access would be permitted if that functionality was present. This includes the attempted execution of an Advanced SIMD or floating-point instruction, and attempted accesses to Advanced SIMD and floating-point System registers.
- An exception generated because of the value of one of the SCTLR_EL1.{ITD, SED, CP15BEN} control bits.
- Attempted execution of:
  - An HVC instruction when disabled by HCR_EL2.HCD or SCR_EL3.HCE.
  - An SMC instruction when disabled by SCR_EL3.SMD.
  - An HLT instruction when disabled by EDSCR.HDE.
- Attempted execution of an MSR or MRS instruction to access SP_EL0 when the value of SPSel.SP is 0.
- Attempted execution, in Debug state, of:
  - A DCPS1 instruction when the value of HCR_EL2.TGE is 1 and EL2 is disabled or not implemented in the current Security state.
  - A DCPS2 instruction from EL1 or EL0 when EL2 is disabled or not implemented in the current Security state.
  - A DCPS3 instruction when the value of EDSCR.SDD is 1, or when EL3 is not implemented.
- When EL3 is using AArch64, attempted execution from Secure EL1 of an SRS instruction using R13_mon. See 'Traps to EL3 of monitor functionality from Secure EL1 using AArch32' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.
- In Debug state when the value of EDSCR.SDD is 1, the attempted execution at EL2, EL1, or EL0 of an instruction that is configured to trap to EL3.
- In AArch32 state, the attempted execution of an MRS (banked register) or an MSR (banked register) instruction to SPSR_mon, SP_mon, or LR_mon.
- An exception that is taken to EL2 because the value of HCR_EL2.TGE is 1 that, if the value of HCR_EL2.TGE was 0 would have been reported with an ESR_ELx.EC value of `0b000111`.
- ~~When SVE is not implemented, attempted execution of:~~
  - ~~An SVE instruction.~~

- An MSR or MRS instruction to access ZCR_EL1, ZCR_EL2, or ZCR_EL3.

ISS encoding for an exception from a WFI or WFE instruction



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch64, this field is set to 0b1110.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to 0b1110.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to 0b1110, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to 0b1110, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Bits [19:1]

Reserved, RES0.

TI, bit [0]

Trapped instruction. Possible values of this bit are:

TI	Meaning
0b0	WFI trapped.
0b1	WFE trapped.

This field resets to an architecturally UNKNOWN value.

The following fields describe configuration settings for generating this exception:

- SCTLR_EL1.{nTWE, nTWI}.
- HCR_EL2.{TWE, TWI}.
- SCR_EL3.{TWE, TWI}.

ISS encoding for an exception from an MCR or MRC access



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to 0b1110.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to 0b1110.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to 0b1110, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to 0b1110, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Opc2, bits [19:17]

The Opc2 value from the issued instruction.

For a trapped VMRS access, holds the value `0b000`.

This field resets to an architecturally UNKNOWN value.

Opc1, bits [16:14]

The Opc1 value from the issued instruction.

For a trapped VMRS access, holds the value `0b111`.

This field resets to an architecturally UNKNOWN value.

CRn, bits [13:10]

The CRn value from the issued instruction.

For a trapped VMRS access, holds the reg field from the VMRS instruction encoding.

This field resets to an architecturally UNKNOWN value.

Rt, bits [9:5]

The Rt value from the issued instruction, the general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

This field resets to an architecturally UNKNOWN value.

CRm, bits [4:1]

The CRm value from the issued instruction.

For a trapped VMRS access, holds the value `0b0000`.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
`0b0`	Write to System register space. MCR instruction.
`0b1`	Read from System register space. MRC or VMRS instruction.

This field resets to an architecturally UNKNOWN value.

The following fields describe configuration settings for generating exceptions that are reported using EC value `0b000011`:

- CNTKCTL_EL1.{EL0PTEN, EL0VTEN, EL0PCTEN, EL0VCTEN}, for accesses to the Generic Timer Registers from EL0 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL1 or EL2.
- PMUSERENR_EL0.{ER, CR, SW, EN}, for accesses to Performance Monitor registers from EL0 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL1 or EL2.
- AMUSERENR_EL0.EN, for accesses to Activity Monitors registers from EL0 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL1 or EL2.
- HCR_EL2.{TRVM, TVM}, for accesses to virtual memory control registers from EL1 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.
- HCR_EL2.TTLB, for execution of TLB maintenance instructions at EL1 using AArch32 state, MCR or MRC access (coproc == `0b1111`) trapped to EL2.

- HCR_EL2.{TSW, TPC, TPU} for execution of cache maintenance instructions at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- HCR_EL2.TACR, for accesses to the Auxiliary Control Register at EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- HCR_EL2.TIDCP, for accesses to lockdown, DMA, and TCM operations at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- HCR_EL2.{TID1, TID2, TID3}, for accesses to ID registers at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- CPTR_EL2.TCPAC, for accesses to CPACR_EL1 or CPACR using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- HSTR_EL2.T<n>, for accesses to System registers using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- CNTHCTL_EL2.EL1PCEN, for accesses to the Generic Timer registers from EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- MDCR_EL2.{TPM, TPMCR}, for accesses to Performance Monitor registers from EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- CPTR_EL2.TAM, for accesses to Activity Monitors registers from EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL2.
- CPTR_EL3.TCPAC, for accesses to CPACR from EL1 and EL2, and accesses to HCPTR from EL2 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL3.
- MDCR_EL3.TPM, for accesses to Performance Monitor registers from EL0, EL1 and EL2 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL3.
- CPTR_EL3.TAM, for accesses to Activity Monitors registers from EL0, EL1 and EL2 using AArch32 state, MCR or MRC access (coproc == 0b1111) trapped to EL3.
- See 'Traps to EL3 of Secure monitor functionality from Secure EL1 using AArch32' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ for information on other traps using EC value 0b000011.
- If ARMv8.6-FGT is implemented, MCR or MRC access to some registers at EL0, trapped to EL2.

The following fields describe configuration settings for generating exceptions that are reported using EC value 0b000101:

- CPACR_EL1.TTA for accesses to trace registers, MCR or MRC access (coproc == 0b1110) trapped to EL1 or EL2.
- MDSCR_EL1.TDCC, for accesses to the Debug Communications Channel (DCC) registers at EL0 and EL1 using AArch32 state, MCR or MRC access (coproc == 0b1110) trapped to EL1 or EL2.
- If ARMv8.6-FGT is implemented, MDCR_EL2.TDCC and MDCR_EL3.TDCC, for accesses to the DCC registers at EL0 and EL1, trapped to EL2.
- HCR_EL2.TID0, for accesses to the JIDR register in the ID group 0 at EL0 and EL1 using AArch32, MRC access (coproc == 0b1110) trapped to EL2.
- CPTR_EL2.TTA, for accesses to trace registers using AArch32, MCR or MRC access (coproc == 0b1110) trapped to EL2.
- MDCR_EL2.TDRA, for accesses to Debug ROM registers DBGDRAR and AArch-DBGDSAR using AArch32, MCR or MRC access (coproc == 0b1110) trapped to EL2.
- MDCR_EL2.TDOSA, for accesses to powerdown debug registers, using AArch32 state, MCR or MRC access (coproc == 0b1110) trapped to EL2.
- MDCR_EL2.TDA, for accesses to other debug registers, using AArch32 state, MCR or MRC access (coproc == 0b1110) trapped to EL2.
- CPTR_EL3.TTA, for accesses to trace registers using AArch32, MCR or MRC access (coproc == 0b1110) trapped to EL3.
- MDCR_EL3.TDOSA, for accesses to powerdown debug registers using AArch32, MCR or MRC access (coproc == 0b1110) trapped to EL3.
- MDCR_EL3.TDA, for accesses to other debug registers, using AArch32, MCR or MRC access (coproc == 0b1110) trapped to EL3.

The following fields describe configuration settings for generating exceptions that are reported using EC value 0b001000:

- HCR_EL2.TID0, for accesses to the FPSID register in ID group 0 at EL1 using AArch32 state, VMRS access trapped to EL2.
- HCR_EL2.TID3, for accesses to registers in ID group 3 including MVFR0, MVFR1 and MVFR2, VMRS access trapped to EL2.

ISS encoding for an exception from an MCRR or MRRC access



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to 0b1110.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to 0b1110.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to 0b1110, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to 0b1110, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Opc1, bits [19:16]

The Opc1 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Bit [15]

Reserved, RES0.

Rt2, bits [14:10]

The Rt2 value from the issued instruction, the second general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states'~~ in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

This field resets to an architecturally UNKNOWN value.

Rt, bits [9:5]

The Rt value from the issued instruction, the first general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

CRm, bits [4:1]

The CRm value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
0b0	Write to System register space. MCRR instruction.
0b1	Read from System register space. MRRC instruction.

This field resets to an architecturally UNKNOWN value.

The following fields describe configuration settings for generating exceptions that are reported using EC value 0b000100:

- CNTKCTL_EL1.{EL0PTEN, EL0VTEN, EL0PCTEN, EL0VCTEN}, for accesses to the Generic Timer Registers from EL0 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL1 or EL2.
- PMUSERENR_EL0.{CR, EN}, for accesses to Performance Monitor registers from EL0 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL1 or EL2.
- AMUSERENR_EL0.{EN}, for accesses to Activity Monitors registers AMEVCNTR0<n> and AMEVCNTR1<n> from EL0 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL1 or EL2.
- HCR_EL2.{TRVM, TVM}, for accesses to virtual memory control registers from EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- HSTR_EL2.T<n>, for accesses to System registers using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- CNTHCTL_EL2.{EL1PCEN, EL1PCTEN}, for accesses to the Generic Timer registers from EL0 and EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- MDCR_EL2.{TPM, TPMCR}, for accesses to Performance Monitor registers from EL0 and EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- CPTR_EL2.TAM, for accesses to Activity Monitors registers registers AMEVCNTR0<n> and AMEVCNTR1<n> from EL0 and EL1 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL2.
- MDCR_EL3.TPM, for accesses to Performance Monitor registers from EL0, EL1 and EL2 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL3.
- CPTR_EL3.TAM, for accesses to Activity Monitors registers from EL0, EL1 and EL2 using AArch32 state, MCRR or MRRC access (coproc == 0b1111) trapped to EL3.
- If ARMv8.6-FGT is implemented, HDFGRTR_EL2.PMCCNTR_EL0 for MRRC access and HDFGWTR_EL2.PMCCNTR_EL0 for MCRR access to PMCCNTR at EL0, trapped to EL2.

The following sections describe configuration settings for generating exceptions that are reported using EC value 0b001100:

- CPACR_EL1.TTA for accesses to trace registers using MCR or MRC instructions, MCRR or MRRC access (coproc == 0b1110) trapped to EL1 or EL2.
- MDSCR_EL1.TDCC, for accesses to the Debug Communications Channel (DCC) registers DBGDSAR and DBGDRAR at EL0 using AArch32 state, MCRR or MRRC access (coproc == 0b1110) trapped to EL1 or EL2.
- CPTR_EL2.TTA, for accesses to trace registers using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL2.
- MDCR_EL2.TDRA, for accesses to Debug ROM registers DBGDRAR and AArch-DBGDSAR using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL2.
- CPTR_EL3.TTA, for accesses to trace registers using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL3.

- MDCR_EL3.TDOSA, for traps to powerdown debug registers using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL3.
- MDCR_EL3.TDA, for accesses to other debug registers, using AArch32, MCRR or MRRC access (coproc == 0b1110) trapped to EL3.

ISS encoding for an exception from an LDC or STC instruction



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to 0b1110.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to 0b1110.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to 0b1110, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to 0b1110, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

imm8, bits [19:12]

The immediate value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Bits [11:10]

Reserved, RES0.

Rn, bits [9:5]

The Rn value from the issued instruction, the general-purpose register used for the transfer. The reported value gives the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field is valid only when AM[2] is 0, indicating an immediate form of the LDC or STC instruction. When AM[2] is 1, indicating a literal form of the LDC or STC instruction, this field is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

Offset, bit [4]

Indicates whether the offset is added or subtracted:

Offset	Meaning
0b0	Subtract offset.
0b1	Add offset.

This bit corresponds to the U bit in the instruction encoding.

This field resets to an architecturally UNKNOWN value.

AM, bits [3:1]

Addressing mode. The permitted values of this field are:

AM	Meaning
0b000	Immediate unindexed.
0b001	Immediate post-indexed.
0b010	Immediate offset.
0b011	Immediate pre-indexed.
0b100	For a trapped STC instruction or a trapped T32 LDC instruction this encoding is reserved.
0b110	For a trapped STC instruction, this encoding is reserved.

The values 0b101 and 0b111 are reserved. The effect of programming this field to a reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Reserved values in System and memory-mapped registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Bit [2] in this subfield indicates the instruction form, immediate or literal.

Bits [1:0] in this subfield correspond to the bits {P, W} in the instruction encoding.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
0b0	Write to memory. STC instruction.
0b1	Read from memory. LDC instruction.

This field resets to an architecturally UNKNOWN value.

The following fields describe the configuration settings for the traps that are reported using EC value 0b000110:

- MDSCR_EL1.TDCC, for accesses using AArch32 state, LDC access to DBGDTRTXint or STC access to DBGDTRRXint trapped to EL1 or EL2.

- MDCR_EL2.TDA, for accesses using AArch32 state, LDC access to DBGDTRTXint or STC access to DBGDTRRXint MCR or MRC access trapped to EL2.
- MDCR_EL3.TDA, for accesses using AArch32 state, LDC access to DBGDTRTXint or STC access to DBGDTRRXint MCR or MRC access trapped to EL3.
- If ARMv8.6-FGT is implemented, MDCR_EL2.TDCC and MDCR_EL3.TDCC, for accesses to the DCC registers at EL0 and EL1, trapped to EL2.

ISS encoding for an exception from an access to SVE, Advanced SIMD or floating-point functionality, resulting from CPACR_EL1.FPEN, CPTR_EL2.FPEN or CPTR_ELx.TFP



The accesses covered by this trap include:

- Execution of SVE or Advanced SIMD and floating-point instructions.
- Accesses to the Advanced SIMD and floating-point System registers.

For an implementation that does not include either SVE or support for floating-point and Advanced SIMD, the exception is reported using the EC value `0b000000`.

CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
`0b0`	The COND field is not valid.
`0b1`	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to `0b1110`.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to `0b1110`.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to `0b1110`, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean

that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Bits [19:0]

Reserved, RES0.

The following sections describe the configuration settings for the traps that are reported using EC value `0b000111`:

- CPACR_EL1.FPEN, for accesses to SIMD and floating-point registers trapped to EL1.
- CPTR_EL2.TFP, for accesses to SIMD and floating-point registers trapped to EL2.
- CPTR_EL2.TFP, for accesses to SIMD and floating-point registers trapped to EL3.

ISS encoding for an exception from an access to SVE functionality, resulting from CPACR_EL1.ZEN, CPTR_EL2.ZEN, CPTR_EL2.TZ, or CPTR_EL3.EZ



Bits [24:0]

When SVE is implemented:

Reserved, RES0.

Otherwise:

Reserved, RES0.

The accesses covered by this trap include:

- Execution of SVE instructions.
- Accesses to the SVE system registers, ZCR_ELx and ID_AA64ZFR0_EL1.

For an implementation that does not include SVE, the exception is reported using the EC value `0b000000`.

ISS encoding for an exception from an Illegal Execution state, or a PC or SP alignment fault



Bits [24:0]

Reserved, RES0.

There are no configuration settings for generating Illegal Execution state exceptions and PC alignment fault exceptions. For more information about these exceptions see 'The Illegal Execution state exception' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ and 'PC alignment checking' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

'Stack pointer alignment checking' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ describes the configuration settings for generating SP alignment fault exceptions.

ISS encoding for an exception from HVC or SVC instruction execution



Bits [24:16]

Reserved, RES0.

imm16, bits [15:0]

The value of the immediate field from the HVC or SVC instruction.

For an HVC instruction, and for an A64 SVC instruction, this is the value of the imm16 field of the issued instruction.

For an A32 or T32 SVC instruction:

- If the instruction is unconditional, then:
  - For the T32 instruction, this field is zero-extended from the imm8 field of the instruction.
  - For the A32 instruction, this field is the bottom 16 bits of the imm24 field of the instruction.
- If the instruction is conditional, this field is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

In AArch32 state, the HVC instruction is unconditional, and a conditional SVC instruction generates an exception only if it passes its condition code check. Therefore, the syndrome information for these exceptions does not require conditionality information.

For T32 and A32 instructions, see 'SVC' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile and 'HVC' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

For A64 instructions, see 'SVC' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile and 'HVC' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

If ARMv8.6-FGT is implemented, HFGITR_EL2.{SVC_EL1, SVC_EL0} control fine-grained traps on SVC execution.

ISS encoding for an exception from SMC instruction execution in AArch32 state



For an SMC instruction that completes normally and generates an exception that is taken to EL3, the ISS encoding is RES0.

For an SMC instruction that is trapped to EL2 from EL1 because HCR_EL2.TSC is 1, the ISS encoding is as shown in the diagram.

CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

For exceptions taken from AArch64, CV is set to 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field is only valid if CCKNOWNPASS is 1, otherwise it is RES0.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

~~The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.~~

For exceptions taken from AArch64, this field is set to `0b1110`.

The condition code for the trapped instruction. This field is valid only for exceptions taken from AArch32, and only when the value of CV is 1.

For exceptions taken from AArch32:

- When an A32 instruction is trapped, CV is set to 1 and:
  - If the instruction is conditional, COND is set to the condition code field value from the instruction.
  - If the instruction is unconditional, COND is set to `0b1110`.
- A conditional A32 instruction that is known to pass its condition code check can be presented either:
  - With COND set to `0b1110`, the value for unconditional.
  - With the COND value held in the instruction.
- When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:
  - CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
  - CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.
- For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field is only valid if CCKNOWNPASS is 1, otherwise it is RES0.

This field resets to an architecturally UNKNOWN value.

CCKNOWNPASS, bit [19]

Indicates whether the instruction might have failed its condition code check.

CCKNOWNPASS	Meaning
`0b0`	The instruction was unconditional, or was conditional and passed its condition code check.
`0b1`	The instruction was conditional, and might have failed its condition code check.

Note

In an implementation in which an SMC instruction that fails it code check is not trapped, this field can always return the value 0.

This field resets to an architecturally UNKNOWN value.

Bits [18:0]

Reserved, RES0.

HCR_EL2.TSC describes the configuration settings for trapping SMC instructions to EL2.

See 'System calls' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ describes the case where these exceptions are trapped to EL3.

ISS encoding for an exception from SMC instruction execution in AArch64 state



Bits [24:16]

Reserved, RES0.

imm16, bits [15:0]

The value of the immediate field from the issued SMC instruction.

This field resets to an architecturally UNKNOWN value.

The value of ISS[24:0] described here is used both:

- When an SMC instruction is trapped from EL1 modes.
- When an SMC instruction is not trapped, so completes normally and generates an exception that is taken to EL3.

HCR_EL2.TSC describes the configuration settings for trapping SMC from EL1 modes.

'System calls' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ describes the case where these exceptions are trapped to EL3.

ISS encoding for an exception from MSR, MRS, or System instruction execution in AArch64 state



Bits [24:22]

Reserved, RES0.

Op0, bits [21:20]

The Op0 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Op2, bits [19:17]

The Op2 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Op1, bits [16:14]

The Op1 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

CRn, bits [13:10]

The CRn value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Rt, bits [9:5]

The Rt value from the issued instruction, the general-purpose register used for the transfer.

This field resets to an architecturally UNKNOWN value.

CRm, bits [4:1]

The CRm value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
0b0	Write access, including MSR instructions.
0b1	Read access, including MRS instructions.

This field resets to an architecturally UNKNOWN value.

For exceptions caused by System instructions, see 'System' subsection of 'Branches, exception generating and System instructions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile for the encoding values returned by an instruction.

The following fields describe configuration settings for generating the exception that is reported using EC value 0b011000:

- SCTLR_EL1.UCI, for execution of cache maintenance instructions using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- SCTLR_EL1.UCT, for accesses to CTR_EL0 using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- SCTLR_EL1.DZE, for execution of DC ZVA instructions using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- SCTLR_EL1.UMA, for accesses to the PSTATE interrupt masks using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- CPACR_EL1.TTA, for accesses to the trace registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- MDSCR_EL1.TDCC, for accesses to the Debug Communications Channel (DCC) registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- If ARMv8.6-FGT is implemented, MDCR_EL2.TDCC and MDCR_EL3.TDCC, for accesses to the DCC registers at EL0 and EL1, trapped to EL2.
- CNTKCTL_EL1.{EL0PTEN, EL0VTEN, EL0PCTEN, EL0VCTEN} accesses to the Generic Timer registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- PMUSERENR_EL0.{ER, CR, SW, EN}, for accesses to the Performance Monitor registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- AMUSERENR_EL0.EN, for accesses to Activity Monitors registers using AArch64 state, MSR or MRS access trapped to EL1 or EL2.
- HCR_EL2.{TRVM, TVM}, for accesses to virtual memory control registers using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TDZ, for execution of DC ZVA instructions using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TTLB, for execution of TLB maintenance instructions using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.{TSW, TPC, TPU}, for execution of cache maintenance instructions using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TACR, for accesses to the Auxiliary Control Register, ACTLR_EL1, using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.TIDCP, for accesses to lockdown, DMA, and TCM operations using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.{TID1, TID2, TID3}, for accesses to ID group 1, ID group 2 or ID group 3 registers, using AArch64 state, MSR or MRS access trapped to EL2.
- CPTR_EL2.TCPAC, for accesses to CPACR_EL1, using AArch64 state, MSR or MRS access trapped to EL2.
- CPTR_EL2.TTA, for accesses to the trace registers, using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.TTRF, for accesses to the trace filter register, TRFCR_EL1, using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.TDRA, for accesses to Debug ROM registers, using AArch64 state, MSR or MRS access trapped to EL2.

- MDCR_EL2.TDOSA, for accesses to powerdown debug registers using AArch64 state, MSR or MRS access trapped to EL2.
- CNTHCTL_EL2.{EL1PCEN, EL1PCTEN}, for accesses to the Generic Timer registers using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.TDA, for accesses to debug registers using AArch64 state, MSR or MRS access trapped to EL2.
- MDCR_EL2.{TPM, TPMCR}, for accesses to Performance Monitor registers, using AArch64 state, MSR or MRS access trapped to EL2.
- CPTR_EL2.TAM, for accesses to Activity Monitors registers, using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.APK, for accesses to Pointer authentication key registers. using AArch64 state, MSR or MRS access trapped to EL2.
- HCR_EL2.{NV, NV1}, for Nested virtualization register access, using AArch64 state, MSR or MRS access, trapped to EL2.
- HCR_EL2.AT, for execution of AT S1E* instructions, using AArch64 state, MSR or MRS access, trapped to EL2.
- HCR_EL2.{TERR, FIEN}, for accesses to RAS registers, using AArch64 state, MSR or MRS access, trapped to EL2.
- SCR_EL3.APK, for accesses to Pointer authentication key registers, using AArch64 state, MSR or MRS access trapped to EL3.
- SCR_EL3.ST, for accesses to the Counter-timer Physical Secure timer registers, using AArch64 state, MSR or MRS access trapped to EL3.
- SCR_EL3.{TERR, FIEN}, for accesses to RAS registers, using AArch64 state, MSR or MRS access trapped to EL3.
- CPTR_EL3.TCPAC, for accesses to CPTR_EL2 and CPACR_EL1 using AArch64 state, MSR or MRS access trapped to EL3.
- CPTR_EL3.TTA, for accesses to the trace registers, using AArch64 state, MSR or MRS access trapped to EL3.
- MDCR_EL3.TTRF, for accesses to the filter trace control registers, TRFCR_EL1 and TRFCR_EL2, using AArch64 state, MSR or MRS access trapped to EL3.
- MDCR_EL3.TDA, for accesses to debug registers, using AArch64 state, MSR or MRS access trapped to EL3.
- MDCR_EL3.TDOSA, for accesses to powerdown debug registers, using AArch64 state, MSR or MRS access trapped to EL3.
- MDCR_EL3.TPM, for accesses to Performance Monitor registers, using AArch64 state, MSR or MRS access trapped to EL3.
- CPTR_EL3.TAM, for accesses to Activity Monitors registers, using AArch64 state, MSR or MRS access, trapped to EL3.
- If ARMv8.2-EVT is implemented the following registers control traps for EL1 and EL0 Cache controls that use this EC value:~~,HCR_EL2.{TTLBOS, TTLBIS, TICAB, TOCU, TID4} and HCR2.{TTLBIS, TICAB, TOCU, TID4} control traps for EL1 and EL0 Cache controls that use this EC value.~~
  - HCR_EL2.{TTLBOS, TTLBIS, TICAB, TOCU, TID4}.
  - HCR2.{TTLBIS, TICAB, TOCU, TID4}.
- If ARMv8.6-FGT is implemented:
  - SCR_EL3.FGTEn, for accesses to the fine-grained trap registers, MSR or MRS access at EL2 trapped to EL3.
  - HFGRTR_EL2 for reads and HFGWTR_EL2 for writes of registers, using AArch64 state, MSR or MRS access at EL0 and EL1 trapped to EL2.
  - HFGITR_EL2 for execution of system instructions, MSR or MRS access trapped to EL2
  - HDFGRTR_EL2 for reads and HDFGWTR_EL2 for writes of registers, using AArch64 state, MSR or MRS access at EL0 and EL1 state trapped to EL2.
  - HAFGRTR_EL2 for reads of Activity Monitor counters, using AArch64 state, MRS access at EL0 and EL1 trapped to EL2.

ISS encoding for an IMPLEMENTATION DEFINED exception to EL3



IMPLEMENTATION DEFINED, bits [24:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

ISS encoding for an exception from an Instruction Abort



Bits [24:13]

Reserved, RES0.

SET, bits [12:11]

Synchronous Error Type. When the RAS Extension is implemented and IFSC is `0b010000`, describes the state of the PE after taking the Instruction Abort exception. The possible values of this field are:

SET	Meaning
`0b00`	Recoverable error (UER).
`0b10`	Uncontainable error (UC).
`0b11`	Restartable error (UEO) or Corrected error (CE).

All other values are reserved.

Note

Software can use this information to determine what recovery might be possible. Taking a synchronous External Abort exception might result in an unrecoverable PE state.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the IFSC field is not `0b010000`.

This field resets to an architecturally UNKNOWN value.

FnV, bit [10]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
`0b0`	FAR is valid.
`0b1`	FAR is not valid, and holds an UNKNOWN value.

This field is only valid if the IFSC code is `0b010000`. It is RES0 for all other aborts.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

External abort type. This bit can provide an IMPLEMENTATION DEFINED classification of External aborts.

For any abort other than an External abort this bit returns a value of 0.

This field resets to an architecturally UNKNOWN value.

Bit [8]

Reserved, RES0.

S1PTW, bit [7]

For a stage 2 fault, indicates whether the fault was a stage 2 fault on an access made for a stage 1 translation table walk:

S1PTW	Meaning
0b0	Fault not on a stage 2 translation for a stage 1 translation table walk.
0b1	Fault on the stage 2 translation of an access for a stage 1 translation table walk.

For any abort other than a stage 2 fault this bit is RES0.

This field resets to an architecturally UNKNOWN value.

Bit [6]

Reserved, RES0.

IFSC, bits [5:0]

Instruction Fault Status Code. ~~Possible values of this field are:~~

IFSC	Meaning	Applies when
0b000000	Address size fault, level 0 of translation or translation table base register.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000100	Translation fault, level 0.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk or hardware update of translation table.	
0b010100	Synchronous External abort, on translation table walk or hardware update of translation table, level 0.~~0~~	
0b010101	Synchronous External abort, on translation table walk or hardware update of translation table, level 1.~~1~~	
0b010110	Synchronous External abort, on translation table walk or hardware update of translation table, level 2.~~2~~	
0b010111	Synchronous External abort, on translation table walk or hardware update of translation table, level 3.~~3~~	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011100	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 0.~~0~~	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 1.~~1~~	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 2.~~2~~	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 3.~~3~~	When RAS is not implemented
0b110000	TLB conflict abort.	
0b110001	Unsupported atomic hardware update fault. ~~Unsupported atomic hardware update fault, if the implementation includes ARMv8.1-TTHM].~~ ~~Otherwise reserved.~~	When ARMv8.1-TTHM is implemented

All other values are reserved.

~~When the RAS Extension is implemented, 0b011000, 0b011100, 0b011101, 0b011110, and 0b011111, are reserved.~~

Note

Armv8.2 requires the implementation of the RAS Extension.

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

Because Access flag faults and Permission faults can only result from a Block or Page translation table descriptor, they cannot occur at level 0.

If the S1PTW bit is set, then the level refers the level of the stage2 translation that is translating a stage 1 translation walk.

This field resets to an architecturally UNKNOWN value.

ISS encoding for an exception from a Data Abort



ISV, bit [24]

Instruction Syndromesyndrome Valid.valid. Indicates whether the syndrome information in ISS[23:14] is valid.

ISV	Meaning
0b0	No valid instruction syndrome. ISS[23:14] are RES0.
0b1	ISS[23:14] hold a valid instruction syndrome.

This bit is 0 for all faults reported in ESR_EL2 except the following stage 2 aborts:

- AArch64 loads and stores of a single general-purpose register (including the register specified with 0b11111, including those with Acquire/Release semantics, but excluding Load Exclusive or Store Exclusive and excluding those with writeback.
- AArch32 instructions where the instruction:
  - Is an LDR, LDA, LDRT, LDRSH, LDRSHT, LDRH, LDAH, LDRHT, LDRSB, LDRSBT, LDRB, LDAB, LDRBT, STR, STL, STRT, STRH, STLH, STRHT, STRB, STLB, or STRBT instruction.
  - Is not performing register writeback.
  - Is not using R15 as a source or destination register.

For these cases, ISV is UNKNOWN if the exception was generated in Debug state in memory access mode, and otherwise indicates whether ISS[23:14] hold a valid syndrome.

ISV is 0 for all faults reported in ESR_EL1 or ESR_EL3.

When the RAS Extension is implemented, ISV is 0 for any synchronous External abort.

For ISS reporting, a stage 2 abort on a stage 1 translation table walk does not return a valid instruction syndrome, and therefore ISV is 0 for these aborts.

When the RAS Extension is not implemented, the value of ISV on a synchronous External abort on a stage 2 translation table walk is IMPLEMENTATION DEFINED.

When ARMv8.5-MemTag is implemented, for a synchronous Tag Check Fault abort taken to ELx, ESR_ELx.FNV is 0 and FAR_ELx is valid.

This field resets to an architecturally UNKNOWN value.

SAS, bits [23:22]

Syndrome Access Size. When ISV is 1, indicates the size of the access attempted by the faulting operation.

SAS	Meaning
0b00	Byte
0b01	Halfword
0b10	Word
0b11	Doubleword

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

SSE, bit [21]

Syndrome Sign Extend. When ISV is 1, for a byte, halfword, or word load operation, indicates whether the data item must be sign extended. For these cases, the possible values of this bit are:

SSE	Meaning
0b0	Sign-extension not required.
0b1	Data item must be sign-extended.

For all other operations this bit is 0.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

SRT, bits [20:16]

Syndrome Register Transfer. When ISV is 1, the register number of the Rt operand of the faulting instruction.

~~Syndrome Register transfer. When ISV is 1, the register number of the Rt operand of the faulting instruction. If the exception was taken from an Exception level that is using AArch32 then this is the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

If the exception was taken from an Exception level that is using AArch32 then this is the AArch64 view of the register. See 'Mapping of the general-purpose registers between the Execution states'.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

SF, bit [15]

Width of the register accessed by the instruction is Sixty-Four. When ISV is 1, the possible values of this bit are:

SF	Meaning
0b0	Instruction loads/stores a 32-bit wide register.
0b1	Instruction loads/stores a 64-bit wide register.

Note

This field specifies the register width identified by the instruction, not the Execution state.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

AR, bit [14]

Acquire/Release. When ISV is 1, the possible values of this bit are:

AR	Meaning
0b0	Instruction did not have acquire/release semantics.
0b1	Instruction did have acquire/release semantics.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

VNCR, bit [13]

When ARMv8.4-NV is implemented:

Indicates that the fault came from use of VNCR_EL2 register by EL1 code.

VNCR	Meaning
0b0	The fault was not generated by the use of VNCR_EL2, by an MRS or MSR instruction executed at EL1.
0b1	The fault was generated by the use of VNCR_EL2, by an MRS or MSR instruction executed at EL1.

This field is 0 in ESR_EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SET, bits [12:11]

Synchronous Error Type. When the RAS Extension is implemented and DFSC is 0b010000, describes the state of the PE after taking the Data Abort exception. The possible values of this field are:

SET	Meaning
0b00	Recoverable error (UER).
0b10	Uncontainable error (UC).
0b11	Restartable error (UEO) or Corrected error (CE).

All other values are reserved.

Note

Software can use this information to determine what recovery might be possible. Taking a synchronous External Abort exception might result in an unrecoverable PE state.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the DFSC field is not 0b010000.

This field resets to an architecturally UNKNOWN value.

FnV, bit [10]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
0b0	FAR is valid.
0b1	FAR is not valid, and holds an UNKNOWN value.

This field is valid only if the DFSC code is 0b010000. It is RES0 for all other aborts.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

External abort type. This bit can provide an IMPLEMENTATION DEFINED classification of External aborts.

For any abort other than an External abort this bit returns a value of 0.

This field resets to an architecturally UNKNOWN value.

CM, bit [8]

Cache maintenance. Indicates whether the Data Abort came from a cache maintenance or address translation instruction:

CM	Meaning
0b0	The Data Abort was not generated by the execution of one of the System instructions identified in the description of value 1.
0b1	The Data Abort was generated by either the execution of a cache maintenance instruction or by a synchronous fault on the execution of an address translation instruction. The DC ZVA instruction is not classified as a cache maintenance instruction, and therefore its execution cannot cause this field to be set to 1.

This field resets to an architecturally UNKNOWN value.

S1PTW, bit [7]

For a stage 2 fault, indicates whether the fault was a stage 2 fault on an access made for a stage 1 translation table walk:

S1PTW	Meaning
0b0	Fault not on a stage 2 translation for a stage 1 translation table walk.
0b1	Fault on the stage 2 translation of an access for a stage 1 translation table walk.

For any abort other than a stage 2 fault this bit is RES0.

This field resets to an architecturally UNKNOWN value.

WnR, bit [6]

Write not Read. Indicates whether a synchronous abort was caused by an instruction writing to a memory location, or by an instruction reading from a memory location. The possible values of this bit are:

WnR	Meaning
0b0	Abort caused by an instruction reading from a memory location.
0b1	Abort caused by an instruction writing to a memory location.

For faults on cache maintenance and address translation instructions, this bit always returns a value of 1.

For faults from an atomic instruction that both reads and writes from a memory location, this bit is set to 0 if a read of the address specified by the instruction would have generated the fault which is being reported, otherwise it is set to 1. The architecture permits, but does not require, a relaxation of this requirement such that for all stage 2 aborts on stage 1 translation table walks for atomic instructions, the WnR bit is always 0.

This field is UNKNOWN for:

- An External abort on an Atomic access.
- A fault reported using a DFSC value of `0b110101` or `0b110001`, indicating an unsupported Exclusive or atomic access.

This field resets to an architecturally UNKNOWN value.

DFSC, bits [5:0]

Data Fault Status Code. ~~Possible values of this field are:~~

DFSC	Meaning	Applies when
0b000000	Address size fault, level 0 of translation or translation table base register.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000100	Translation fault, level 0.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk or hardware update of translation table.~~walk.~~	
0b010001	Synchronous Tag Check Fault.~~fail~~	When ARMv8.5-MemTag is implemented
0b010100	Synchronous External abort, on translation table walk or hardware update of translation table, level 0.	
0b010101	Synchronous External abort, on translation table walk or hardware update of translation table, level 1.	
0b010110	Synchronous External abort, on translation table walk or hardware update of translation table, level 2.	
0b010111	Synchronous External abort, on translation table walk or hardware update of translation table, level 3.	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011100	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 0.	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 1.	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 2.	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 3.	When RAS is not implemented
0b100001	Alignment fault.	
0b110000	TLB conflict abort.	
0b110001	Unsupported atomic hardware update fault. ~~Unsupported atomic hardware update fault, if the implementation includes ARMv8.1-TTHM]. Otherwise reserved.~~	When ARMv8.1-TTHM is implemented
0b110100	IMPLEMENTATION DEFINED fault (Lockdown).	

0b110101	IMPLEMENTATION DEFINED fault (Unsupported Exclusive or Atomic access).
0b111101	Section Domain Fault, used only for faults reported in the PAR_EL1.
0b111110	Page Domain Fault, used only for faults reported in the PAR_EL1.

All other values are reserved.

When the RAS Extension is implemented, 0b011000, 0b011100, 0b011101, 0b011110, and 0b011111, are reserved.

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

Because Access flag faults and Permission faults can only result from a Block or Page translation table descriptor, they cannot occur at level 0.

If the S1PTW bit is set, then the level refers the level of the stage2 translation that is translating a stage 1 translation walk.

This field resets to an architecturally UNKNOWN value.

ISS encoding for an exception from a trapped floating-point exception



Bit [24]

Reserved, RES0.

TFV, bit [23]

Trapped Fault Valid bit. Indicates whether the IDF, IXF, UFF, OFF, DZF, and IOF bits hold valid information about trapped floating-point exceptions. The possible values of this bit are:

TFV	Meaning
0b0	The IDF, IXF, UFF, OFF, DZF, and IOF bits do not hold valid information about trapped floating-point exceptions and are UNKNOWN.
0b1	One or more floating-point exceptions occurred during an operation performed while executing the reported instruction. The IDF, IXF, UFF, OFF, DZF, and IOF bits indicate trapped floating-point exceptions that occurred. For more information see 'Floating-point exception traps' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

It is IMPLEMENTATION DEFINED whether this field is set to 0 on an exception generated by a trapped floating point exception from a vector instruction.

Note

This is not a requirement. Implementations can set this field to 1 on a trapped floating-point exception from a vector instruction and return valid information in the {IDF, IXF, UFF, OFF, DZF, IOF} fields.

This field resets to an architecturally UNKNOWN value.

Bits [22:11]

Reserved, RES0.

VECITR, bits [10:8]

For a trapped floating-point exception from an instruction executed in AArch32 state this field is RES1.

For a trapped floating-point exception from an instruction executed in AArch64 state this field is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

IDF, bit [7]

Input Denormal floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

IDF	Meaning
0b0	Input denormal floating-point exception has not occurred.
0b1	Input denormal floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

Bits [6:5]

Reserved, RES0.

IXF, bit [4]

Inexact floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

IXF	Meaning
0b0	Inexact floating-point exception has not occurred.
0b1	Inexact floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

UFF, bit [3]

Underflow floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

UFF	Meaning
0b0	Underflow floating-point exception has not occurred.
0b1	Underflow floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

OFF, bit [2]

Overflow floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

OFF	Meaning
0b0	Overflow floating-point exception has not occurred.
0b1	Overflow floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

DZF, bit [1]

Divide by Zero floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

DZF	Meaning
0b0	Divide by Zero floating-point exception has not occurred.
0b1	Divide by Zero floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

IOF, bit [0]

Invalid Operation floating-point exception trapped bit. If the TFV field is 0, this bit is UNKNOWN. Otherwise, the possible values of this bit are:

IOF	Meaning
0b0	Invalid Operation floating-point exception has not occurred.
0b1	Invalid Operation floating-point exception occurred during execution of the reported instruction.

This field resets to an architecturally UNKNOWN value.

In an implementation that supports the trapping of floating-point exceptions:

- From an Exception level using AArch64, the FPCR.{IDE, IXE, UFE, OFE, DZE, IOE} bits enable each of the floating-point exception traps.
- From an Exception level using AArch32, the FPSCR.{IDE, IXE, UFE, OFE, DZE, IOE} bits enable each of the floating-point exception traps.

ISS encoding for an SError interrupt



IDS, bit [24]

IMPLEMENTATION DEFINED syndrome. Possible values of this bit are:

IDS	Meaning
0b0	Bits[23:0] of the ISS field holds the fields described in this encoding. **Note** If the RAS Extension is not implemented, this means that bits[23:0] of the ISS field are RES0.
0b1	Bits[23:0] of the ISS field holds IMPLEMENTATION DEFINED syndrome information that can be used to provide additional information about the SError interrupt.

Note

This field was previously called ISV.

This field resets to an architecturally UNKNOWN value.

Bits [23:14]

Reserved, RES0.

IESB, bit [13]

When ARMv8.2-IESB is implemented:

Implicit error synchronization event.

IESB	Meaning
0b0	The SError interrupt was either not synchronized by the implicit error synchronization event or not taken immediately.
0b1	The SError interrupt was synchronized by the implicit error synchronization event and taken immediately.

This field is RES0 if the value returned in the DFSC field is not 0b010001.

Note

Armv8.2 requires the implementation of the RAS Extension and ARMv8.2-IESB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

AET, bits [12:10]

When RAS is implemented:

Asynchronous Error Type.

When the RAS Extension is implemented and DFSC is 0b010001, describes the state of the PE after taking the SError interrupt exception. The possible values of this field are:

AET	Meaning
0b000	Uncontainable error (UC).
0b001	Unrecoverable error (UEU).
0b010	Restartable error (UEO).
0b011	Recoverable error (UER).
0b110	Corrected error (CE).

All other values are reserved.

If multiple errors are taken as a single SError interrupt exception, the overall state of the PE is reported. For example, if both a Recoverable and Unrecoverable error occurred, the state is Unrecoverable.

Note

Software can use this information to determine what recovery might be possible. The recovery software must also examine any implemented fault records to determine the location and extent of the error.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the DFSC field is not 0b010001.

Note

Armv8.2 requires the implementation of the RAS Extension.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

Otherwise:

Reserved, RES0.

EA, bit [9]

When RAS is implemented:

External abort type. When the RAS Extension is implemented, this bit can provide an IMPLEMENTATION DEFINED classification of External aborts.

For any abort other than an External abort this bit returns a value of 0.

This field is RES0 if either:

- The RAS Extension is not implemented.
- The value returned in the DFSC field is not `0b010001`.

~~Note~~

~~Armv8.2 requires the implementation of the RAS Extension.~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [8:6]

Reserved, RES0.

DFSC, bits [5:0]

When RAS is implemented:

Data Fault Status Code. ~~When the RAS Extension is implemented, possible values of this field are:~~

DFSC	Meaning
`0b000000`	Uncategorized.
`0b010001`	Asynchronous SError interrupt.

All other values are reserved.

~~If the RAS Extension is not implemented, this field is RES0.~~

~~Note~~

~~Armv8.2 requires the implementation of the RAS Extension.~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ISS encoding for an exception from a Breakpoint or Vector Catch debug exception



Bits [24:6]

Reserved, RES0.

IFSC, bits [5:0]

Instruction Fault Status Code.

~~Instruction Fault Status Code. This field is set to 0b100010, to indicate a Debug exception.~~

IFSC	Meaning
0b100010	Debug exception.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions:

- For exceptions from AArch64, see 'Breakpoint exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.
- For exceptions from AArch32, see 'Breakpoint exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~ and 'Vector Catch exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

ISS encoding for an exception from a Software Step exception



ISV, bit [24]

Instruction syndrome valid. Indicates whether the EX bit, ISS[6], is valid, as follows:

ISV	Meaning
0b0	EX bit is RES0.
0b1	EX bit is valid.

See the EX bit description for more information.

This field resets to an architecturally UNKNOWN value.

Bits [23:7]

Reserved, RES0.

EX, bit [6]

Exclusive operation. If the ISV bit is set to 1, this bit indicates whether a Load-Exclusive instruction was stepped.

EX	Meaning
0b0	An instruction other than a Load-Exclusive instruction was stepped.
0b1	A Load-Exclusive instruction was stepped.

If the ISV bit is set to 0, this bit is RES0, indicating no syndrome data is available.

This field resets to an architecturally UNKNOWN value.

IFSC, bits [5:0]

Instruction Fault Status Code.

~~Instruction Fault Status Code. This field is set to 0b100010, to indicate a Debug exception.~~

IFSC	Meaning
0b100010	Debug exception.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see 'Software Step exceptions'~~ in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile,~~.

ISS encoding for an exception from a Watchpoint exception



Bits [24:14]

Reserved, RES0.

VNCR, bit [13]

When ARMv8.4-NV is implemented:

Indicates that the watchpoint came from use of VNCR_EL2 register by EL1 code.

VNCR	Meaning
0b0	The watchpoint was not generated by the use of VNCR_EL2 by EL1 code.
0b1	The watchpoint was generated by the use of VNCR_EL2 by EL1 code.

This field is 0 in ESR_EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [12:9]

Reserved, RES0.

CM, bit [8]

Cache maintenance. Indicates whether the Watchpoint exception came from a cache maintenance or address translation instruction:

CM	Meaning
0b0	The Watchpoint exception was not generated by the execution of one of the System instructions identified in the description of value 1.
0b1	The Watchpoint exception was generated by either the execution of a cache maintenance instruction or by a synchronous Watchpoint exception on the execution of an address translation instruction. The DC ZVA instruction is not classified as a cache maintenance instruction, and therefore its execution cannot cause this field to be set to 1.

This field resets to an architecturally UNKNOWN value.

Bit [7]

Reserved, RES0.

WnR, bit [6]

Write not Read. Indicates whether the Watchpoint exception was caused by an instruction writing to a memory location, or by an instruction reading from a memory location. The possible values of this bit are:

WnR	Meaning
0b0	Watchpoint exception caused by an instruction reading from a memory location.
0b1	Watchpoint exception caused by an instruction writing to a memory location.

For Watchpoint exceptions on cache maintenance and address translation instructions, this bit always returns a value of 1.

For Watchpoint exceptions from an atomic instruction, this field is set to 0 if a read of the location would have generated the Watchpoint exception, otherwise it is set to 1.

If multiple watchpoints match on the same access, it is UNPREDICTABLE which watchpoint generates the Watchpoint exception.

This field resets to an architecturally UNKNOWN value.

DFSC, bits [5:0]

Data Fault Status Code.

~~Data Fault Status Code. This field is set to 0b100010, to indicate a Debug exception.~~

DFSC	Meaning
0b100010	Debug exception.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see 'Watchpoint exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

ISS encoding for an exception from execution of a Breakpoint instruction

24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0									Comment															

Bits [24:16]

Reserved, RES0.

Comment, bits [15:0]

Set to the instruction comment field value, zero extended as necessary. ~~For the AArch32 BKPT instructions, the comment field is described as the immediate field.~~

For the AArch32 BKPT instructions, the comment field is described as the immediate field.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see 'Breakpoint instruction exceptions' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile~~.

ISS encoding for an exception from ERET, ERETAA or ERETAB instruction



This EC value applies when ARMv8.6-FGT is implemented, or when HCR_EL2.NV is 1.

Bits [24:2]

Reserved, RES0.

ERET, bit [1]

Indicates whether an ERET or ERETA* instruction was trapped to EL2. Possible values are:

ERET	Meaning
0b0	ERET instruction trapped to EL2.
0b1	ERETAA or ERETAB instruction trapped to EL2.

If this bit is 0, the ERETA field is RES0.

This field resets to an architecturally UNKNOWN value.

ERETA, bit [0]

Indicates whether an ERETAA or ERETAB instruction was trapped to EL2. Possible values are:

ERETA	Meaning
0b0	ERETAA instruction trapped to EL2.
0b1	ERETAB instruction trapped to EL2.

When the ERET field is 0, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

For more information about generating these exceptions, see HCR_EL2.NV.

If ARMv8.6-FGT is implemented, HFGITR_EL2.ERET controls fine-grained trap exceptions from ERET, ERETAA and ERETAB execution.

ISS encoding for an exception from Branch Target Identification instruction



Bits [24:2]

Reserved, RES0.

BTYPE, bits [1:0]

This field is set to the PSTATE.BTYPE value that generated the Branch Target Exception.

For more information about generating these exceptions, see 'The AArch64 application level programmers model' ~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section B1~~.

ISS encoding for an exception from a Pointer Authentication instruction when HCR_EL2.API == 0 || SCR_EL3.API == 0



Bits [24:0]

Reserved, RES0.

For more information about generating these exceptions, see:

- HCR_EL2.API, for exceptions from Pointer authentication instructions, using AArch64 state, trapped to EL2.
- SCR_EL3.API, for exceptions from Pointer authentication instructions, using AArch64 state, trapped to EL3.

ISS encoding for an exception from a Pointer Authentication instruction authentication failure



Bits [24:2]

Reserved, RES0.

Bit [1], ~~bit [1]~~

This field indicates whether the exception is as a result of an Instruction key or a Data key.

	Meaning
0b0	Instruction Key.
0b1	Data Key.

This field resets to an architecturally UNKNOWN value.

Bit [0], ~~bit [0]~~

This field indicates whether the exception is as a result of an A key or a B key.

	Meaning
0b0	A key.
0b1	B key.

This field resets to an architecturally UNKNOWN value.

The following instructions generate an exception when the Pointer Authentication Code (PAC) is incorrect:

- AUTIASP, AUTIAZ, AUTIA1716.
- AUTIBSP, AUTIBZ, AUTIB1716.
- AUTIA, AUTDA, AUTIB, AUTDB.
- AUTIZA, AUTIZB, AUTDZA, AUTDZB.

It is IMPLEMENTATION DEFINED whether the following instructions generate an exception directly from the authorization failure, rather than changing the address in a way that will generate a translation fault when the address is accessed:

- RETAA, RETAB.
- BRAA, BRAB, BLRAA, BLRAB.
- BRAAZ, BRABZ, BLRAAZ, BLRABZ.
- ERETAA, ERETAB.
- LDRAA, LDRAB, whether the authenticated address is written back to the base register or not.

Accessing the ESR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, ESR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return ESR_EL3;
```

```
MSR ESR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    ESR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

FAR_EL1, Fault Address Register (EL1)

The FAR_EL1 characteristics are:

Purpose

Holds the faulting Virtual Address for all synchronous Instruction or Data Abort, PC alignment fault and Watchpoint exceptions that are taken to EL1.

Configuration

AArch64 System register FAR_EL1 bits [31:0] are architecturally mapped to AArch32 System register DFAR[31:0] (NS) .

AArch64 System register FAR_EL1 bits [63:32] are architecturally mapped to AArch32 System register IFAR[31:0] (NS) .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

FAR_EL1 is a 64-bit register.

Field descriptions

The FAR_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Faulting Virtual Address for synchronous exceptions taken to EL1																															
Faulting Virtual Address for synchronous exceptions taken to EL1																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Faulting Virtual Address for synchronous exceptions taken to EL1. Exceptions that set the FAR_EL1 are Instruction Aborts (EC `0x20` or `0x21`), Data Aborts (EC `0x24` or `0x25`), PC alignment faults (EC `0x22`), and Watchpoints (EC `0x34` or `0x35`). ESR_EL1.EC holds the EC value for the exception.

For a synchronous External abort, if the VA that generated the abort was from an address range for which TCR_ELx.TBI{<0|1>} == 1 for the translation regime in use when the abort was generated, then the top eight bits of FAR_EL1 are UNKNOWN.

For a synchronous External abort other than a synchronous External abort on a translation table walk, this field is valid only if ESR_EL1.FnV is 0, and the FAR_EL1 is UNKNOWN if ESR_EL1.FnV is 1.

For all other exceptions taken to EL1, the FAR_EL1 is UNKNOWN.

If a memory fault that sets FAR_EL1 is generated from a data cache maintenance or other DC instruction, this field holds the address specified in the register argument of the instruction.

If the exception that updates FAR_EL1 is taken from an Exception level that is using AArch32, the top 32 bits are all zero, unless both of the following apply, in which case the top 32 bits of FAR_ELx are `0x00000001`:

- The faulting address was generated by a load or store instruction that sequentially incremented from address `0xFFFFFFFF`. Such a load or store is CONSTRAINED UNPREDICTABLE. See 'Out of range VA' in Appendix K1 Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.
- The implementation treats such incrementing as setting bit[32] of the virtual address to 1.

For a Data Abort or Watchpoint exception, if address tagging is enabled for the address accessed by the data access that caused the exception, then this field includes the tag. For more information about address tagging, see 'Address tagging in AArch64 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

For a synchronous Tag Check Fault abort, bits[63:60] are UNKNOWN.

Execution at EL0 makes FAR_EL1 become UNKNOWN.

Note

The address held in this field is an address accessed by the instruction fetch or data access that caused the exception that gave rise to the instruction or data abort. It is the lower address that gave rise to the fault. Where different faults from different addresses arise from the same instruction, such as for an instruction that loads or stores a mis-aligned address that crosses a page boundary, the architecture does not prioritize between those different faults.

FAR_EL1 is made UNKNOWN on an exception return from EL1.

This field resets to an architecturally UNKNOWN value.

Accessing the FAR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic FAR_EL1 or FAR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, FAR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.FAR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x220];
    else
        return FAR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return FAR_EL2;
    else
        return FAR_EL1;
elsif PSTATE.EL == EL3 then
    return FAR_EL1;
```

```
MSR FAR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.FAR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x220] = X[t];
    else
        FAR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        FAR_EL2 = X[t];
    else
        FAR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    FAR_EL1 = X[t];
```

MRS <Xt>, FAR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x220];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return FAR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return FAR_EL1;
    else
        UNDEFINED;
```

MSR FAR_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x220] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        FAR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        FAR_EL1 = X[t];
    else
        UNDEFINED;
```

MRS <Xt>, FAR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return FAR_EL1;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return FAR_EL2;
elsif PSTATE.EL == EL3 then
    return FAR_EL2;
```

MSR FAR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        FAR_EL1 = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    FAR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    FAR_EL2 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

FAR_EL2, Fault Address Register (EL2)

The FAR_EL2 characteristics are:

Purpose

Holds the faulting Virtual Address for all synchronous Instruction or Data Abort, PC alignment fault and Watchpoint exceptions that are taken to EL2.

Configuration

AArch64 System register FAR_EL2 bits [31:0] are architecturally mapped to AArch32 System register HDFAR[31:0] .

AArch64 System register FAR_EL2 bits [63:32] are architecturally mapped to AArch32 System register HIFAR[31:0] .

AArch64 System register FAR_EL2 bits [31:0] are architecturally mapped to AArch32 System register DFAR[31:0] (S) when ~~HaveEL(~~EL2 is implemented.~~)~~.

AArch64 System register FAR_EL2 bits [63:32] are architecturally mapped to AArch32 System register IFAR[31:0] (S) when ~~HaveEL(~~EL2 is implemented.~~)~~.

If EL2 is not implemented, this register is RES0 from EL3.

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

FAR_EL2 is a 64-bit register.

Field descriptions

The FAR_EL2 bit assignments are:



Bits [63:0]

Faulting Virtual Address for synchronous exceptions taken to EL2. Exceptions that set the FAR_EL2 are Instruction Aborts (EC `0x20` or `0x21`), Data Aborts (EC `0x24` or `0x25`), PC alignment faults (EC `0x22`), and Watchpoints (EC `0x34` or `0x35`). ESR_EL2.EC holds the EC value for the exception.

For a synchronous External abort, if the VA that generated the abort was from an address range for which TCR_ELx.TBI{<0|1>} == 1 for the translation regime in use when the abort was generated, then the top eight bits of FAR_EL2 are UNKNOWN.

For a synchronous External abort other than a synchronous External abort on a translation table walk, this field is valid only if ESR_EL2.FnV is 0, and the FAR_EL2 is UNKNOWN if ESR_EL2.FnV is 1.

For all other exceptions taken to EL2, the FAR_EL2 is UNKNOWN.

If a memory fault that sets FAR_EL2 is generated from a data cache maintenance or other DC instruction, this field holds the address specified in the register argument of the instruction.

If the exception that updates FAR_EL2 is taken from an Exception level that is using AArch32, the top 32 bits are all zero, unless both of the following apply, in which case the top 32 bits of FAR_ELx are `0x00000001`:

- The faulting address was generated by a load or store instruction that sequentially incremented from address `0xFFFFFFFF`. Such a load or store instruction is CONSTRAINED UNPREDICTABLE. See 'Out of range VA' in Appendix K1 Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.
- The implementation treats such incrementing as setting bit[32] of the virtual address to 1.

For a Data Abort or Watchpoint exception, if address tagging is enabled for the address accessed by the data access that caused the exception, then this field includes the tag. For more information about address tagging, see 'Address tagging in AArch64 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

For a synchronous Tag Check Fault abort, bits[63:60] are UNKNOWN.

Execution at EL1 or EL0 makes FAR_EL2 become UNKNOWN.

Note

The address held in this field is an address accessed by the instruction fetch or data access that caused the exception that gave rise to the instruction or data abort. It is the lower address that gave rise to the fault. Where different faults from different addresses arise from the same instruction, such as for an instruction that loads or stores a mis-aligned address that crosses a page boundary, the architecture does not prioritize between those different faults.

FAR_EL2 is made UNKNOWN on an exception return from EL2.

This field resets to an architecturally UNKNOWN value.

Accessing the FAR_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic FAR_EL2 or FAR_EL1 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, FAR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return FAR_EL1;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return FAR_EL2;
elsif PSTATE.EL == EL3 then
    return FAR_EL2;
```

```
MSR FAR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        FAR_EL1 = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    FAR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    FAR_EL2 = X[t];
```

MRS <Xt>, FAR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.FAR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x220];
    else
        return FAR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return FAR_EL2;
    else
        return FAR_EL1;
elsif PSTATE.EL == EL3 then
    return FAR_EL1;
```

MSR FAR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.FAR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x220] = X[t];
    else
        FAR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        FAR_EL2 = X[t];
    else
        FAR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    FAR_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

FAR_EL3, Fault Address Register (EL3)

The FAR_EL3 characteristics are:

Purpose

Holds the faulting Virtual Address for all synchronous Instruction or Data Abort and PC alignment fault exceptions that are taken to EL3.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to FAR_EL3 are UNDEFINED.

Attributes

FAR_EL3 is a 64-bit register.

Field descriptions

The FAR_EL3 bit assignments are:



Bits [63:0]

Faulting Virtual Address for synchronous exceptions taken to EL3. Exceptions that set the FAR_EL3 are Instruction Aborts (EC `0x20` or `0x21`), Data Aborts (EC `0x24` or `0x25`), and PC alignment faults (EC `0x22`). ESR_EL3.EC holds the EC value for the exception.

For a synchronous External abort, if the VA that generated the abort was from an address range for which TCR_ELx.TBI{<0|1>} == 1 for the translation regime in use when the abort was generated, then the top eight bits of FAR_EL3 are UNKNOWN.

For a synchronous External abort other than a synchronous External abort on a translation table walk, this field is valid only if ESR_EL3.FnV is 0, and the FAR_EL3 is UNKNOWN if ESR_EL3.FnV is 1.

For all other exceptions taken to EL3, the FAR_EL3 is UNKNOWN.

If a memory fault that sets FAR_EL3 is generated from a data cache maintenance or other DC instruction, this field holds the address specified in the register argument of the instruction.

If the exception that updates FAR_EL3 is taken from an Exception Level using AArch32, the top 32 bits are all zero, unless both of the following apply, in which case the top 32 bits of FAR_ELx are `0x00000001`:

- The faulting address was generated by a load or store instruction that sequentially incremented from address `0xFFFFFFFF`. Such a load or store instruction is CONSTRAINED UNPREDICTABLE. See 'Out of range VA' in Appendix K1 Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.
- The implementation treats such incrementing as setting bit[32] of the virtual address to 1.

For a Data Abort or Watchpoint exception, if address tagging is enabled for the address accessed by the data access that caused the exception, then this field includes the tag. For more information about address tagging, see 'Address tagging in AArch64 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

For a synchronous Tag Check Fault abort, bits[63:60] are UNKNOWN.

Execution at EL2, EL1 or EL0 makes FAR_EL3 become UNKNOWN.

Note

The address held in this register is an address accessed by the instruction fetch or data access that caused the exception that actually gave rise to the instruction or data abort. It is the lowest address that gave rise to the fault. Where different faults from different addresses arise from the same instruction, such as for an instruction that loads or stores a mis-aligned address that crosses a page boundary, the architecture does not prioritize between those different faults.

FAR_EL3 is made UNKNOWN on an exception return from EL3.

This field resets to an architecturally UNKNOWN value.

Accessing the FAR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, FAR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return FAR_EL3;
```

```
MSR FAR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    FAR_EL3 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

FPCR, Floating-point Control Register

The FPCR characteristics are:

Purpose

Controls floating-point behavior.

Configuration

The named fields in this register map to the equivalent fields in the AArch32 FPSCR.

It is IMPLEMENTATION DEFINED whether the Len and Stride fields can be programmed to non-zero values, which will cause some AArch32 floating-point instruction encodings to be UNDEFINED, or whether these fields are RAZ.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

FPCR is a 64-bit register.

Field descriptions

The FPCR bit assignments are:



Bits [63:27]

Reserved, RES0.

AHP, bit [26]

Alternative half-precision control bit:

AHP	Meaning
0b0	IEEE half-precision format selected.
0b1	Alternative half-precision format selected.

This bit is only used for conversions between half-precision floating-point and other floating-point formats.

The data-processing instructions added as part of the ARMv8.2-FP16 extension always use the IEEE half-precision format, and ignore the value of this bit.

This field resets to an architecturally UNKNOWN value.

DN, bit [25]

Default NaN mode control bit:

DN	Meaning
0b0	NaN operands propagate through to the output of a floating-point operation.
0b1	Any operation involving one or more NaNs returns the Default NaN.

The value of this bit controls both scalar and Advanced SIMD floating-point arithmetic.

This field resets to an architecturally UNKNOWN value.

FZ, bit [24]

Flush-to-zero mode control bit:

FZ	Meaning
0b0	Flush-to-zero mode disabled. Behavior of the floating-point system is fully compliant with the IEEE 754 standard.
0b1	Flush-to-zero mode enabled.

The value of this bit controls both scalar and Advanced SIMD floating-point arithmetic.

This bit has no effect on half-precision calculations.

This field resets to an architecturally UNKNOWN value.

RMode, bits [23:22]

Rounding Mode control field. The encoding of this field is:

RMode	Meaning
0b00	Round to Nearest (RN) mode.
0b01	Round towards Plus Infinity (RP) mode.
0b10	Round towards Minus Infinity (RM) mode.
0b11	Round towards Zero (RZ) mode.

The specified rounding mode is used by both scalar and Advanced SIMD floating-point instructions.

This field resets to an architecturally UNKNOWN value.

Stride, bits [21:20]

This field has no function in AArch64 state, and non-zero values are ignored during execution in AArch64~~ state.~~ state.~~It is included only for context saving and restoration of the AArch32~~FPSCR.Stride field.~~

This field is included only for context saving and restoration of the AArch32 FPSCR.Stride field.

This field resets to an architecturally UNKNOWN value.

FZ16, bit [19]

When ARMv8.2-FP16 is implemented:

Flush-to-zero mode control bit on half-precision data-processing instructions:

FZ16	Meaning
0b0	Flush-to-zero mode disabled. Behavior of the floating-point system is fully compliant with the IEEE 754 standard.
0b1	Flush-to-zero mode enabled.

The value of this bit applies to both scalar and Advanced SIMD floating-point half-precision calculations. A half-precision floating-point number that is flushed to zero as a result of the value of the FZ16 bit does not generate an Input Denormal exception.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Len, bits [18:16]

This field has no function in AArch64 state, and non-zero values are ignored during execution in AArch64 ~~state.~~ state. ~~It is included only for context saving and restoration of the AArch32~~FPSCR.Len field.

This field is included only for context saving and restoration of the AArch32 FPSCR.Len field.

This field resets to an architecturally UNKNOWN value.

IDE, bit [15]

Input Denormal floating-point exception trap enable. Possible values are:

IDE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the FPSR.IDC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the FPSR.IDC bit. The trap handling software can decide whether to set the FPSR.IDC bit to 1.

The value of this bit controls both scalar and Advanced SIMD floating-point arithmetic.

If the implementation does not support this exception, this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

Bits [14:13]

Reserved, RES0.

IXE, bit [12]

Inexact floating-point exception trap enable. Possible values are:

IXE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the FPSR.IXC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the FPSR.IXC bit. The trap handling software can decide whether to set the FPSR.IXC bit to 1.

The value of this bit controls both scalar and Advanced SIMD floating-point arithmetic.

If the implementation does not support this exception, this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

UFE, bit [11]

Underflow floating-point exception trap enable. Possible values are:

UFE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the FPSR.UFC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the FPSR.UFC bit. The trap handling software can decide whether to set the FPSR.UFC bit to 1.

The value of this bit controls both scalar and Advanced SIMD floating-point arithmetic.

If the implementation does not support this exception, this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

OFE, bit [10]

Overflow floating-point exception trap enable. Possible values are:

OFE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the FPSR.OFC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the FPSR.OFC bit. The trap handling software can decide whether to set the FPSR.OFC bit to 1.

The value of this bit controls both scalar and Advanced SIMD floating-point arithmetic.

If the implementation does not support this exception, this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

DZE, bit [9]

Divide by Zero floating-point exception trap enable. Possible values are:

DZE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the FPSR.DZC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the FPSR.DZC bit. The trap handling software can decide whether to set the FPSR.DZC bit to 1.

The value of this bit controls both scalar and Advanced SIMD floating-point arithmetic.

If the implementation does not support this exception, this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

IOE, bit [8]

Invalid Operation floating-point exception trap enable. Possible values are:

IOE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the FPSR.IOC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the FPSR.IOC bit. The trap handling software can decide whether to set the FPSR.IOC bit to 1.

The value of this bit controls both scalar and Advanced SIMD floating-point arithmetic.

If the implementation does not support this exception, this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

Bits [7:0]

Reserved, RES0.

Accessing the FPCR

Accesses to this register use the following encodings:

MRS <Xt>, FPCR

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0100	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CPACR_EL1.FPEN !=
'11' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x00);
        else
            AArch64.SystemAccessTrap(EL1, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CPTR_EL2.FPEN !=
'11' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        return FPCR;
elsif PSTATE.EL == EL1 then
    if CPACR_EL1.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL1, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        return FPCR;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        return FPCR;
elsif PSTATE.EL == EL3 then
    if CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        return FPCR;
```

MSR FPCR, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0100	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CPACR_EL1.FPEN !=
'11' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x00);
        else
            AArch64.SystemAccessTrap(EL1, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CPTR_EL2.FPEN !=
'11' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        FPCR = X[t];
elsif PSTATE.EL == EL1 then
    if CPACR_EL1.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL1, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        FPCR = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        FPCR = X[t];
elsif PSTATE.EL == EL3 then
    if CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        FPCR = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

FPEXC32_EL2, Floating-Point Exception Control register

The FPEXC32_EL2 characteristics are:

Purpose

Allows access to the AArch32 register FPEXC from AArch64 state only. Its value has no effect on execution in AArch64 state.

Configuration

AArch64 System register FPEXC32_EL2 bits [31:0] are architecturally mapped to AArch32 System register FPEXC[31:0] .

ThisIf registerEL1 iscannot presentuse only when AArch32 is supported at any Exception level. Otherwise, directthis accessesregister to FPEXC32_EL2 areis UNDEFINED.

If EL2 is not implemented but EL3 is implemented, and EL1 is capable of using AArch32, then this register is not RES0.

Implemented only if the implementation includes the Advanced SIMD and floating-point functionality.

This register has no effect if EL2 is not enabled in the current Security state.

RW fields in this register reset to architecturally UNKNOWN values.

Attributes

FPEXC32_EL2 is a 64-bit register.

Field descriptions

The FPEXC32_EL2 bit assignments are:



Bits [63:32]

Reserved, RES0.

EX, bit [31]

Exception bit. From Armv8, this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

EN, bit [30]

Enables access to the Advanced SIMD and floating-point functionality from all Exception levels, except that setting this field to 0 does not disable the following:

- VMSR accesses to the FPEXC or FPSID.
- VMRS accesses from the FPEXC, FPSID, MVFR0, MVFR1, or MVFR2.

EN	Meaning
0b0	Accesses to the FPSCR, and any of the SIMD and floating-point registers Q0-Q15, including their views as D0-D31 registers or S0-S31 registers, are UNDEFINED at all Exception levels.
0b1	This control permits access to the Advanced SIMD and floating-point functionality at all Exception levels.

Execution of floating-point and Advanced SIMD instructions in AArch32 state can be disabled or trapped by the following controls:

- CPACR.cp10, or, if executing at EL0, CPACR_EL1.FPEN.
- FPEXC.EN.
- If executing in Non-secure state:
  - HCPTR.TCP10, or if EL2 is using AArch64, CPTR_EL2.TFP.
  - NSACR.cp10, or if EL3 is using AArch64, CPTR_EL3.TFP.
- For Advanced SIMD instructions only:
  - CPACR.ASEDIS.
  - If executing in Non-secure state, HCPTR.TASE and NSACR.NSTRCDIS.

See the descriptions of the controls for more information.

Note

When executing at EL0 using AArch32:

- If EL1 is using AArch64 then behavior is as if the value of FPEXC.EN is 1.
- If EL2 is using AArch64 and enabled in the current Security state, and the value of HCR_EL2.{RW, TGE} is {1, 1} then behavior is as if the value of FPEXC.EN is 1.
- If EL2 is using AArch64 and enabled in the current Security state, and the value of HCR_EL2.{RW, TGE} is {0, 1} then it is IMPLEMENTATION DEFINED whether the behavior is:
  - As if the value of FPEXC.EN is 1.
  - Determined by the value of FPEXC32_EL2.EN, as described in this field description. However, Arm deprecates using the value of FPEXC32_EL2.EN to determine behavior.

This field resets to an architecturally UNKNOWN value.

DEX, bit [29]

Defined synchronous exception on floating-point execution.

This field identifies whether a synchronous exception generated by the attempted execution of an instruction was generated by an unallocated encoding. The instruction must be in the encoding space that is identified by the pseudocode function ExecutingCP10or11Instr() returning TRUE. This field also indicates whether the FPEXC32_EL2.TFV field is valid.

The meaning of this bit is:

DEX	Meaning
0b0	The exception was generated by the attempted execution of an unallocated instruction in the encoding space that is identified by the pseudocode function ExecutingCP10or11Instr(). If FPEXC32_EL2.TFV is RW then it is invalid and UNKNOWN. If FPEXC32_EL2.{IDF, IXF, UFF, OFF, DZF, IOF} are RW then they are invalid and UNKNOWN.
0b1	The exception was generated during the execution of an unallocated encoding. FPEXC32_EL2.TFV is valid and indicates the cause of the exception.

On an exception that sets this bit to 1 the exception-handling routine must clear this bit to 0.

On an implementation that both does not support trapping of floating-point exceptions and implements the AArch32 FPSCR.{Stride, Len} fields as RAZ, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

FP2V, bit [28]

FPINST2 instruction valid bit. From Armv8, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

VV, bit [27]

VECITR valid bit. From Armv8, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

TFV, bit [26]

Trapped Fault Valid bit. Valid only when the value of FPEXC.DEX is 1. When valid, it indicates the cause of the exception and therefore whether the FPEXC.{IDF, IXF, UFF, OFF, DZF, IOF} bits are valid.

TFV	Meaning
0b0	The exception was caused by the execution of a floating-point VABS, VADD, VDIV, VFMA, VFMS, VFNMA, VFNMS, VMLA, VMLS, VMOV, VMUL, VNEG, VNMLA, VNMLS, VNMUL, VSQRT, or VSUB instruction when one or both of FPSCR.{Stride, Len} was non-zero. If the FPEXC.{IDF, IXF, UFF, OFF, DZF, IOF} bits are RW then they are invalid and UNKNOWN.
0b1	FPEXC.{IDF, IXF, UFF, OFF, DZF, IOF} indicate the presence of trapped floating-point exceptions that had occurred at the time of the exception. Bits are set for all trapped exceptions that had occurred at the time of the exception.

This bit returns a status value and ignores writes.

When the value of FPEXC.DEX is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

On an implementation that supports the trapping of floating-point exceptions and implements FPSCR.{Stride, Len} as RAZ, this bit is RAO/WI.

This field resets to an architecturally UNKNOWN value.

Bits [25:11]

Reserved, RES0.

VECITR, bits [10:8]

Vector iteration count. From Armv8, this field is RES1.

This field resets to an architecturally UNKNOWN value.

IDF, bit [7]

Input Denormal trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether an Input Denormal exception occurred while FPSCR.IDE was 1:

IDF	Meaning
0b0	Input Denormal exception has not occurred.
0b1	Input Denormal exception has occurred.

Input Denormal exceptions can occur only when FPSCR.FZ is 1.

Note

A half-precision floating-point value that is flushed to zero because the value of FPSCR.FZ16 is 1 does not generate an Input Denormal exception.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC32_EL2.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

Bits [6:5]

Reserved, RES0.

IXF, bit [4]

Inexact trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether an Inexact exception occurred while FPSCR.IXE was 1:

IXF	Meaning
0b0	Inexact exception has not occurred.
0b1	Inexact exception has occurred.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

UFF, bit [3]

Underflow trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether an Underflow exception occurred while FPSCR.UFE was 1:

UFF	Meaning
0b0	Underflow exception has not occurred.
0b1	Underflow exception has occurred.

Underflow trapped exceptions can occur:

- On half-precision data-processing instructions only when FPSCR.FZ16 is 0.
- Otherwise only when FPSCR.FZ is 0.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC32_EL2.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

OFF, bit [2]

Overflow trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether an Overflow exception occurred while FPSCR.OFE was 1:

OFF	Meaning
0b0	Overflow exception has not occurred.
0b1	Overflow exception has occurred.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

DZF, bit [1]

Divide by Zero trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether a Divide by Zero exception occurred while FPSCR.DZE was 1:

DZF	Meaning
0b0	Divide by Zero exception has not occurred.
0b1	Divide by Zero exception has occurred.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

IOF, bit [0]

Invalid Operation trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether an Invalid Operation exception occurred while FPSCR.IOE was 1:

IOF	Meaning
0b0	Invalid Operation exception has not occurred.
0b1	Invalid Operation exception has occurred.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

Accessing the FPEXC32_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, FPEXC32_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        return FPEXC32_EL2;
elsif PSTATE.EL == EL3 then
    if CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        return FPEXC32_EL2;
```

```
MSR FPEXC32_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        FPEXC32_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    if CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        FPEXC32_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

FPSR, Floating-point Status Register

The FPSR characteristics are:

Purpose

Provides floating-point system status information.

Configuration

The named fields in this register map to the equivalent fields in the AArch32 FPSCR.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

FPSR is a 64-bit register.

Field descriptions

The FPSR bit assignments are:



Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative condition flag for AArch32 floating-point comparison operations. AArch64 floating-point comparisons set the PSTATE.N flag instead.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero condition flag for AArch32 floating-point comparison operations. AArch64 floating-point comparisons set the PSTATE.Z flag instead.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry condition flag for AArch32 floating-point comparison operations. AArch64 floating-point comparisons set the PSTATE.C flag instead.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow condition flag for AArch32 floating-point comparison operations. AArch64 floating-point comparisons set the PSTATE.V flag instead.

This field resets to an architecturally UNKNOWN value.

QC, bit [27]

Cumulative saturation bit, Advanced SIMD only. This bit is set to 1 to indicate that an Advanced SIMD integer operation has saturated since 0 was last written to this bit.

This field resets to an architecturally UNKNOWN value.

Bits [26:8]

Reserved, RES0.

IDC, bit [7]

Input Denormal cumulative floating-point exception bit. This bit is set to 1 to indicate that the Input Denormal floating-point exception has occurred since 0 was last written to this bit.

How scalar and Advanced SIMD floating-point instructions update this bit depends on the value of the FPCR.IDE bit. This bit is only set to 1 to indicate a floating-point exception if FPCR.IDE is 0, or if trapping software sets it.

This field resets to an architecturally UNKNOWN value.

Bits [6:5]

Reserved, RES0.

IXC, bit [4]

Inexact cumulative floating-point exception bit. This bit is set to 1 to indicate that the Inexact exception floating-point has occurred since 0 was last written to this bit.

How scalar and Advanced SIMD floating-point instructions update this bit depends on the value of the FPCR.IXE bit. This bit is only set to 1 to indicate a floating-point exception if FPCR.IXE is 0, or if trapping software sets it.

The criteria for the Inexact floating-point exception to occur are different in Flush-to-zero mode. For details, see 'Flush-to-zero'.

This field resets to an architecturally UNKNOWN value.

UFC, bit [3]

Underflow cumulative floating-point exception bit. This bit is set to 1 to indicate that the Underflow floating-point exception has occurred since 0 was last written to this bit.

How scalar and Advanced SIMD floating-point instructions update this bit depends on the value of the FPCR.UFE bit. This bit is only set to 1 to indicate a floating-point exception if FPCR.UFE is 0, or if trapping software sets it.

The criteria for the Underflow floating-point exception to occur are different in Flush-to-zero mode. For details, see 'Flush-to-zero'.

This field resets to an architecturally UNKNOWN value.

OFC, bit [2]

Overflow cumulative floating-point exception bit. This bit is set to 1 to indicate that the Overflow floating-point exception has occurred since 0 was last written to this bit.

How scalar and Advanced SIMD floating-point instructions update this bit depends on the value of the FPCR.OFE bit. This bit is only set to 1 to indicate a floating-point exception if FPCR.OFE is 0, or if trapping software sets it.

This field resets to an architecturally UNKNOWN value.

DZC, bit [1]

Divide by Zero cumulative floating-point exception bit. This bit is set to 1 to indicate that the Divide by Zero floating-point exception has occurred since 0 was last written to this bit.

How scalar and Advanced SIMD floating-point instructions update this bit depends on the value of the FPCR.DZE bit. This bit is only set to 1 to indicate a floating-point exception if FPCR.DZE is 0, or if trapping software sets it.

This field resets to an architecturally UNKNOWN value.

IOC, bit [0]

Invalid Operation cumulative floating-point exception bit. This bit is set to 1 to indicate that the Invalid Operation floating-point exception has occurred since 0 was last written to this bit.

How scalar and Advanced SIMD floating-point instructions update this bit depends on the value of the FPCR.IOE bit. This bit is only set to 1 to indicate a floating-point exception if FPCR.IOE is 0, or if trapping software sets it.

This field resets to an architecturally UNKNOWN value.

Accessing the FPSR

Accesses to this register use the following encodings:

```
MRS <Xt>, FPSR
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0100	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CPACR_EL1.FPEN !=
'11' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x00);
        else
            AArch64.SystemAccessTrap(EL1, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CPTR_EL2.FPEN !=
'11' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        return FPSR;
elsif PSTATE.EL == EL1 then
    if CPACR_EL1.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL1, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        return FPSR;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        return FPSR;
elsif PSTATE.EL == EL3 then
    if CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        return FPSR;
```

MSR FPSR, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0100	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CPACR_EL1.FPEN !=
'11' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x00);
        else
            AArch64.SystemAccessTrap(EL1, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CPTR_EL2.FPEN !=
'11' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        FPSR = X[t];
elsif PSTATE.EL == EL1 then
    if CPACR_EL1.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL1, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        FPSR = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x07);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        FPSR = X[t];
elsif PSTATE.EL == EL3 then
    if CPTR_EL3.TFP == '1' then
        AArch64.SystemAccessTrap(EL3, 0x07);
    else
        FPSR = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GCR_EL1, Tag Control Register.

The GCR_EL1 characteristics are:

Purpose

Tag Control Register.

Configuration

This register is present only when ARMv8.5-MemTag is implemented and ID_AA64PFR1_EL1.MTE != 0b0001. Otherwise, direct accesses to GCR_EL1 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

GCR_EL1 is a 64-bit register.

Field descriptions

The GCR_EL1 bit assignments are:



Bits [63:17]

Reserved, RES0.

RRND, bit [16]

Controls generation of tag values by the IRG instruction.

~~Controls whether RandomTag() generates a deterministic value solely based on the contents of RGSR_EL1, or a non-deterministic value.~~

RRND	Meaning
0b0	IRG generates a tag value as defined by RandomTag(). ~~Generate a deterministic value based on RGSR_EL1.~~
0b1	IRG generates an implementation-specific tag value with a distribution of tag values no worse than generated with GCR_EL1.RRND == 0. ~~Generate an IMPLEMENTATION DEFINED non-deterministic value.~~

~~**Note**~~

~~When the value of GCR_EL1.RRND is 1, the value generated does not need to be cryptographically random.~~

~~A similar algorithm to that used when RRND=0 but with free running clock is sufficient.~~

This field resets to an architecturally UNKNOWN value.

Exclude, bits [15:0]

Allocation Tag values excluded from selection by ChooseNonExcludedTag().

This field resets to an architecturally UNKNOWN value.

Accessing the GCR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, GCR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0000	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return GCR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return GCR_EL1;
elsif PSTATE.EL == EL3 then
    return GCR_EL1;
```

```
MSR GCR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0000	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        GCR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        GCR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    GCR_EL1 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

HAFGRTR_EL2, Hypervisor Activity Monitors Fine-Grained Read Trap Register

The HAFGRTR_EL2 characteristics are:

Purpose

Provides controls for traps of MRS reads of Activity Monitors System registers.

Configuration

This register is present only when AMUv1 is implemented and ARMv8.6-FGT is implemented. Otherwise, direct accesses to HAFGRTR_EL2 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HAFGRTR_EL2 is a 64-bit register.

Field descriptions

The HAFGRTR_EL2 bit assignments are:

63	62	61	60	59	58
AMEVTYPER16_EL0	AMEVCNTR16_EL0	AMEVTYPER15_EL0	AMEVCNTR15_EL0	AMEVTYPER14_EL0	AMEVCNTR14_EL0
31	30	29	28	27	26

Bits [63:50]

Reserved, RES0.

AMEVTYPER115_EL0, bit [49]

Trap MRS reads of AMEVTYPER115_EL0~~AMEVTYPER1<15>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER115~~AMEVTYPER1<15>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER115_EL0	Meaning
0b0	MRS reads of AMEVTYPER115_EL0~~AMEVTYPER1<15>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER115~~AMEVTYPER1<15>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER115_EL0~~AMEVTYPER1<15>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER115~~AMEVTYPER1<15>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR115_EL0, bit [48]

Trap MRS reads of AMEVCNTR115_EL0~~AMEVCNTR1<15>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR115~~AMEVCNTR1<15>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR115_EL0	Meaning
0b0	MRS reads of AMEVCNTR115_EL0~~AMEVCNTR1<15>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR115~~AMEVCNTR1<15>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR115_EL0~~AMEVCNTR1<15>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR115~~AMEVCNTR1<15>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER114_EL0, bit [47]

Trap MRS reads of AMEVTYPER114_EL0~~AMEVTYPER1<14>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER114~~AMEVTYPER1<14>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER114_EL0	Meaning
0b0	MRS reads of AMEVTYPER114_EL0~~AMEVTYPER1<14>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER114~~AMEVTYPER1<14>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER114_EL0~~AMEVTYPER1<14>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER114~~AMEVTYPER1<14>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR114_EL0, bit [46]

Trap MRS reads of AMEVCNTR114_EL0~~AMEVCNTR1<14>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR114~~AMEVCNTR1<14>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR114_EL0	Meaning
0b0	MRS reads of AMEVCNTR114_EL0~~AMEVCNTR1<14>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR114~~AMEVCNTR1<14>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR114_EL0~~AMEVCNTR1<14>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR114~~AMEVCNTR1<14>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER113_EL0, bit [45]

Trap MRS reads of AMEVTYPER113_EL0~~AMEVTYPER1<13>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER113~~AMEVTYPER1<13>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER113_EL0	Meaning
0b0	MRS reads of AMEVTYPER113_EL0~~AMEVTYPER1<13>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER113~~AMEVTYPER1<13>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER113_EL0~~AMEVTYPER1<13>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER113~~AMEVTYPER1<13>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR113_EL0, bit [44]

Trap MRS reads of AMEVCNTR113_EL0~~AMEVCNTR1<13>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR113~~AMEVCNTR1<13>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR113_EL0	Meaning
0b0	MRS reads of AMEVCNTR113_EL0~~AMEVCNTR1<13>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR113~~AMEVCNTR1<13>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR113_EL0~~AMEVCNTR1<13>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR113~~AMEVCNTR1<13>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER112_EL0, bit [43]

Trap MRS reads of AMEVTYPER112_EL0~~AMEVTYPER1<12>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER112~~AMEVTYPER1<12>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER112_EL0	Meaning
0b0	MRS reads of AMEVTYPER112_EL0AMEVTYPER1<12>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER112AMEVTYPER1<12> at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER112_EL0AMEVTYPER1<12>_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER112AMEVTYPER1<12> at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR112_EL0, bit [42]

Trap MRS reads of AMEVCNTR112_EL0AMEVCNTR1<12>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR112AMEVCNTR1<12> at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR112_EL0	Meaning
0b0	MRS reads of AMEVCNTR112_EL0AMEVCNTR1<12>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR112AMEVCNTR1<12> at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR112_EL0AMEVCNTR1<12>_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR112AMEVCNTR1<12> at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER111_EL0, bit [41]

Trap MRS reads of AMEVTYPER111_EL0AMEVTYPER1<11>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER111AMEVTYPER1<11> at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER111_EL0	Meaning
0b0	MRS reads of AMEVTYPER111_EL0~~AMEVTYPER1<11>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER111~~AMEVTYPER1<11>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER111_EL0~~AMEVTYPER1<11>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER111~~AMEVTYPER1<11>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR111_EL0, bit [40]

Trap MRS reads of AMEVCNTR111_EL0~~AMEVCNTR1<11>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR111~~AMEVCNTR1<11>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR111_EL0	Meaning
0b0	MRS reads of AMEVCNTR111_EL0~~AMEVCNTR1<11>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR111~~AMEVCNTR1<11>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR111_EL0~~AMEVCNTR1<11>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR111~~AMEVCNTR1<11>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER110_EL0, bit [39]

Trap MRS reads of AMEVTYPER110_EL0~~AMEVTYPER1<10>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER110~~AMEVTYPER1<10>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER110_EL0	Meaning
0b0	MRS reads of AMEVTYPER110_EL0~~AMEVTYPER1<10>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER110~~AMEVTYPER1<10>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER110_EL0~~AMEVTYPER1<10>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER110~~AMEVTYPER1<10>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR110_EL0, bit [38]

Trap MRS reads of AMEVCNTR110_EL0~~AMEVCNTR1<10>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR110~~AMEVCNTR1<10>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR110_EL0	Meaning
0b0	MRS reads of AMEVCNTR110_EL0~~AMEVCNTR1<10>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR110~~AMEVCNTR1<10>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR110_EL0~~AMEVCNTR1<10>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR110~~AMEVCNTR1<10>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER19_EL0, bit [37]

Trap MRS reads of AMEVTYPER19_EL0~~AMEVTYPER1<9>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER19~~AMEVTYPER1<9>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER19_EL0	Meaning
0b0	MRS reads of AMEVTYPER19_EL0~~AMEVTYPER1<9>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER19~~AMEVTYPER1<9>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER19_EL0~~AMEVTYPER1<9>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER19~~AMEVTYPER1<9>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR19_EL0, bit [36]

Trap MRS reads of AMEVCNTR19_EL0~~AMEVCNTR1<9>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR19~~AMEVCNTR1<9>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR19_EL0	Meaning
0b0	MRS reads of AMEVCNTR19_EL0~~AMEVCNTR1<9>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR19~~AMEVCNTR1<9>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR19_EL0~~AMEVCNTR1<9>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR19~~AMEVCNTR1<9>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER18_EL0, bit [35]

Trap MRS reads of AMEVTYPER18_EL0~~AMEVTYPER1<8>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER18~~AMEVTYPER1<8>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER18_EL0	Meaning
0b0	MRS reads of AMEVTYPER18_EL0~~AMEVTYPER1<8>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER18~~AMEVTYPER1<8>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER18_EL0~~AMEVTYPER1<8>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER18~~AMEVTYPER1<8>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR18_EL0, bit [34]

Trap MRS reads of AMEVCNTR18_EL0~~AMEVCNTR1<8>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR18~~AMEVCNTR1<8>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR18_EL0	Meaning
0b0	MRS reads of AMEVCNTR18_EL0~~AMEVCNTR1<8>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR18~~AMEVCNTR1<8>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR18_EL0~~AMEVCNTR1<8>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR18~~AMEVCNTR1<8>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER17_EL0, bit [33]

Trap MRS reads of AMEVTYPER17_EL0~~AMEVTYPER1<7>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER17~~AMEVTYPER1<7>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER17_EL0	Meaning
0b0	MRS reads of AMEVTYPER17_EL0AMEVTYPER1<7>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER17AMEVTYPER1<7> at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER17_EL0AMEVTYPER1<7>_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER17AMEVTYPER1<7> at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR17_EL0, bit [32]

Trap MRS reads of AMEVCNTR17_EL0AMEVCNTR1<7>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR17AMEVCNTR1<7> at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR17_EL0	Meaning
0b0	MRS reads of AMEVCNTR17_EL0AMEVCNTR1<7>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR17AMEVCNTR1<7> at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR17_EL0AMEVCNTR1<7>_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR17AMEVCNTR1<7> at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER16_EL0, bit [31]

Trap MRS reads of AMEVTYPER16_EL0AMEVTYPER1<6>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER16AMEVTYPER1<6> at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER16_EL0	Meaning
0b0	MRS reads of AMEVTYPER16_EL0~~AMEVTYPER1<6>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER16~~AMEVTYPER1<6>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER16_EL0~~AMEVTYPER1<6>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER16~~AMEVTYPER1<6>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR16_EL0, bit [30]

Trap MRS reads of AMEVCNTR16_EL0~~AMEVCNTR1<6>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR16~~AMEVCNTR1<6>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR16_EL0	Meaning
0b0	MRS reads of AMEVCNTR16_EL0~~AMEVCNTR1<6>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR16~~AMEVCNTR1<6>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR16_EL0~~AMEVCNTR1<6>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR16~~AMEVCNTR1<6>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER15_EL0, bit [29]

Trap MRS reads of AMEVTYPER15_EL0~~AMEVTYPER1<5>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER15~~AMEVTYPER1<5>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER15_EL0	Meaning
0b0	MRS reads of AMEVTYPER15_EL0~~AMEVTYPER1<5>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER15~~AMEVTYPER1<5>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER15_EL0~~AMEVTYPER1<5>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER15~~AMEVTYPER1<5>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR15_EL0, bit [28]

Trap MRS reads of AMEVCNTR15_EL0~~AMEVCNTR1<5>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR15~~AMEVCNTR1<5>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR15_EL0	Meaning
0b0	MRS reads of AMEVCNTR15_EL0~~AMEVCNTR1<5>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR15~~AMEVCNTR1<5>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR15_EL0~~AMEVCNTR1<5>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR15~~AMEVCNTR1<5>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER14_EL0, bit [27]

Trap MRS reads of AMEVTYPER14_EL0~~AMEVTYPER1<4>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER14~~AMEVTYPER1<4>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER14_EL0	Meaning
0b0	MRS reads of AMEVTYPER14_EL0~~AMEVTYPER1<4>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER14~~AMEVTYPER1<4>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER14_EL0~~AMEVTYPER1<4>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER14~~AMEVTYPER1<4>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR14_EL0, bit [26]

Trap MRS reads of AMEVCNTR14_EL0~~AMEVCNTR1<4>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR14~~AMEVCNTR1<4>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR14_EL0	Meaning
0b0	MRS reads of AMEVCNTR14_EL0~~AMEVCNTR1<4>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR14~~AMEVCNTR1<4>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR14_EL0~~AMEVCNTR1<4>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR14~~AMEVCNTR1<4>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER13_EL0, bit [25]

Trap MRS reads of AMEVTYPER13_EL0~~AMEVTYPER1<3>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER13~~AMEVTYPER1<3>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER13_EL0	Meaning
0b0	MRS reads of AMEVTYPER13_EL0~~AMEVTYPER1<3>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER13~~AMEVTYPER1<3>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER13_EL0~~AMEVTYPER1<3>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER13~~AMEVTYPER1<3>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR13_EL0, bit [24]

Trap MRS reads of AMEVCNTR13_EL0~~AMEVCNTR1<3>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR13~~AMEVCNTR1<3>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR13_EL0	Meaning
0b0	MRS reads of AMEVCNTR13_EL0~~AMEVCNTR1<3>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR13~~AMEVCNTR1<3>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR13_EL0~~AMEVCNTR1<3>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR13~~AMEVCNTR1<3>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER12_EL0, bit [23]

Trap MRS reads of AMEVTYPER12_EL0~~AMEVTYPER1<2>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER12~~AMEVTYPER1<2>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER12_EL0	Meaning
0b0	MRS reads of AMEVTYPER12_EL0~~AMEVTYPER1<2>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER12~~AMEVTYPER1<2>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER12_EL0~~AMEVTYPER1<2>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER12~~AMEVTYPER1<2>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR12_EL0, bit [22]

Trap MRS reads of AMEVCNTR12_EL0~~AMEVCNTR1<2>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR12~~AMEVCNTR1<2>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR12_EL0	Meaning
0b0	MRS reads of AMEVCNTR12_EL0~~AMEVCNTR1<2>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR12~~AMEVCNTR1<2>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR12_EL0~~AMEVCNTR1<2>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR12~~AMEVCNTR1<2>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER11_EL0, bit [21]

Trap MRS reads of AMEVTYPER11_EL0~~AMEVTYPER1<1>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER11~~AMEVTYPER1<1>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER11_EL0	Meaning
0b0	MRS reads of AMEVTYPER11_EL0~~AMEVTYPER1<1>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER11~~AMEVTYPER1<1>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER11_EL0~~AMEVTYPER1<1>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER11~~AMEVTYPER1<1>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR11_EL0, bit [20]

Trap MRS reads of AMEVCNTR11_EL0~~AMEVCNTR1<1>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR11~~AMEVCNTR1<1>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR11_EL0	Meaning
0b0	MRS reads of AMEVCNTR11_EL0~~AMEVCNTR1<1>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR11~~AMEVCNTR1<1>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR11_EL0~~AMEVCNTR1<1>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR11~~AMEVCNTR1<1>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVTYPER10_EL0, bit [19]

Trap MRS reads of AMEVTYPER10_EL0~~AMEVTYPER1<0>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER10~~AMEVTYPER1<0>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVTYPER10_EL0	Meaning
0b0	MRS reads of AMEVTYPER10_EL0~~AMEVTYPER1<0>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVTYPER10~~AMEVTYPER1<0>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVTYPER10_EL0~~AMEVTYPER1<0>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVTYPER10~~AMEVTYPER1<0>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR10_EL0, bit [18]

Trap MRS reads of AMEVCNTR10_EL0~~AMEVCNTR1<0>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR10~~AMEVCNTR1<0>~~ at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR10_EL0	Meaning
0b0	MRS reads of AMEVCNTR10_EL0~~AMEVCNTR1<0>_EL0~~ at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR10~~AMEVCNTR1<0>~~ at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR10_EL0~~AMEVCNTR1<0>_EL0~~ at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR10~~AMEVCNTR1<0>~~ at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMCNTEN1, bit [17]

Trap MRS reads and MRC reads of multiple System registers.

Enables a trap to EL2 the following operations:

- At EL1 and EL0 using AArch64: MRS reads of AMCNTENCLR1_EL0 and AMCNTENSET1_EL0.
- At EL0 using Arch32 when EL1 is using AArch64: MRC reads of AMCNTENCLR1 and AMCNTENSET1.

AMCNTEN1	Meaning
0b0	The operations listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads at EL1 and EL0 using AArch64 of AMCNTENCLR1_EL0 and AMCNTENSET1_EL0 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads at EL0 using AArch32 of AMCNTENCLR1 and AMCNTENSET1 are trapped to EL2 and reported with EC syndrome value 0x03, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Bits [16:5]

Reserved, RES0.

AMEVCNTR0<x>_EL0~~AMEVCNTR03_EL0~~, bit [x+1], for x = 0 to 3~~4~~]

Trap MRS reads of AMEVCNTR0<x~~3~~>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR0<x~~3~~> at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR0<x>_EL0~~AMEVCNTR03_EL0~~	Meaning
0b0	MRS reads of AMEVCNTR0<x~~3~~>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR0<x~~3~~> at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR0<x~~3~~>_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR0<x~~3~~> at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

~~AMEVCNTR02_EL0, bit [3]~~

~~Trap MRS reads of AMEVCNTR0<2>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR0<2> at EL0 using AArch32 when EL1 is using AArch64 to EL2.~~

AMEVCNTR02_EL0	Meaning
0b0	MRS reads of AMEVCNTR0<2>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR0<2> at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR0<2>_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR0<2> at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR01_EL0, bit [2]

Trap MRS reads of AMEVCNTR0<1>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR0<1> at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR01_EL0	Meaning
0b0	MRS reads of AMEVCNTR0<1>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR0<1> at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR0<1>_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR0<1> at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

AMEVCNTR00_EL0, bit [1]

Trap MRS reads of AMEVCNTR0<0>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR0<0> at EL0 using AArch32 when EL1 is using AArch64 to EL2.

AMEVCNTR00_EL0	Meaning
0b0	MRS reads of AMEVCNTR0<0>_EL0 at EL1 and EL0 using AArch64 and MRC reads of AMEVCNTR0<0> at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of AMEVCNTR0<0>_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of AMEVCNTR0<0> at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

~~In a system where the PE resets into EL2, this field resets to 0.~~

AMCNTEN0, bit [0]

Trap MRS reads and MRC reads of multiple System registers.

Enables a trap to EL2 the following operations:

- At EL1 and EL0 using AArch64: MRS reads of AMCNTENCLR0_EL0 and AMCNTENSET0_EL0.
- At EL0 using Arch32 when EL1 is using AArch64: MRC reads of AMCNTENCLR0 and AMCNTENSET0.

AMCNTEN0	Meaning
0b0	The operations listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads at EL1 and EL0 using AArch64 of AMCNTENCLR0_EL0 and AMCNTENSET0_EL0 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads at EL0 using AArch32 of AMCNTENCLR0 and AMCNTENSET0 are trapped to EL2 and reported with EC syndrome value 0x03, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Accessing the HAFGRTR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, HAFGRTR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0011	0b0001	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x1E8];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FGTEn == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return HAFGRTR_EL2;
elsif PSTATE.EL == EL3 then
    return HAFGRTR_EL2;
```

```
MSR HAFGRTR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0011	0b0001	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x1E8] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FGTEn == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        HAFGRTR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    HAFGRTR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HCR_EL2, Hypervisor Configuration Register

The HCR_EL2 characteristics are:

Purpose

Provides configuration controls for virtualization, including defining whether various operations are trapped to EL2.

Configuration

AArch64 System register HCR_EL2 bits [31:0] are architecturally mapped to AArch32 System register HCR[31:0] .

AArch64 System register HCR_EL2 bits [63:32] are architecturally mapped to AArch32 System register HCR2[31:0] .

If EL2 is not implemented, this register is RES0 from EL3.

The bits in this register behave as if they are 0 for all purposes other than direct reads of the register if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HCR_EL2 is a 64-bit register.

Field descriptions

The HCR_EL2 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	
TWEDEL				TWEDEn	TID5	DCT	ATA	TTLBOS	TTLBIS	EnSCXT	TOCU	AMVOFFEN	TICAB	TID4	RES0	FIEN	FWB	NV2	AT	N
RW	TRVM	HCD	TDZ	TGE	TVM	TTLB	TPU	TPCP	TSW	TACR	TIDCP	TSC	TID3	TID2	TID1	TID0	TWE	TWI	DC	
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	

TWEDEL, bits [63:60]

When ARMv8.6-TWED is implemented:

TWE Delay. A 4-bit unsigned number that, when HCR_EL2.TWEDEn is 1, encodes the minimum delay in taking a trap of WFE caused by HCR_EL2.TWE as 2^(TWEDEL + 8) cycles.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TWEDEn, bit [59]

When ARMv8.6-TWED is implemented:

TWE Delay Enable. Enables a configurable delayed trap of the WFE instruction caused by HCR_EL2.TWE.

TWEDEn	Meaning
0b0	The delay for taking a WFE trap is IMPLEMENTATION DEFINED.
0b1	The delay for taking a WFE trap is at least the number of cycles defined in HCR_EL2.TWEDEL.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TID5, bit [58]

When ARMv8.5-MemTag is implemented:

Trap ID group 5. Traps the following register accesses to EL2, when EL2 is enabled in the current Security state:

AArch64:

- GMID_EL1.

TID5	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	The specified EL1 and EL0 accesses to ID group 5 registers are trapped to EL2.

When the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field has an Effective value of 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DCT, bit [57]

When ARMv8.5-MemTag is implemented:

Default Cacheability Tagging. When HCR_EL2.DC is in effect, controls whether stage 1 translations are treated as Tagged or Untagged.

DCT	Meaning
0b0	Stage 1 translations are treated as Untagged.
0b1	Stage 1 translations are treated as Tagged.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ATA, bit [56]

When ARMv8.5-MemTag is implemented:

Allocation Tag Access. When SCR_EL3.ATA=1 and HCR_EL2.{E2H,TGE} != {1,1}, controls EL1 and EL0 access to Allocation Tags.

When access is prevented:

- Instructions which Load or Store data are Unchecked.
- Instructions which Load or Store Allocation Tags treat the Allocation Tag as RAZ/WI.

- Instructions which insert Logical Address Tags into addresses treat the Allocation Tag used to generate the Logical Address Tag as 0.
- Cache maintenance instructions which invalidate Allocation Tags from caches behave as the equivalent Clean and Invalidate operation on Allocation Tags.
- MRS and MSR instructions at EL1 using GCR_EL1, RGSR_EL1, TFSR_EL1, TFSR_EL2, or TFSRE0_EL1 that are not UNDEFINED are trapped to EL2.

ATA	Meaning
0b0	Access is prevented.
0b1	Access is not prevented.

This field is permitted to be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TTLBOS, bit [55]

When ARMv8.2-EVT is implemented:

Trap TLB maintenance instructions that operate on the Outer Shareable domain. Traps execution of those TLB maintenance instructions at EL1 ~~using AArch64~~ to EL2, when EL2 is enabled in the current Security state. This applies to the following instructions:

TLBI VMALLE1OS, TLBI VAE1OS, TLBI ASIDE1OS,TLBI VAAE1OS, TLBI VALE1OS, TLBI VAALE1OS,TLBI RVAE1OS, TLBI RVAAE1OS,TLBI RVALE1OS, and TLBI RVAALE1OS.

TTLBOS	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Execution of the specified instructions are trapped to EL2.

~~If ARMv8.2-EVT is not implemented, this field is RES0.~~

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TTLBIS, bit [54]

When ARMv8.2-EVT is implemented:

Trap TLB maintenance instructions that operate on the Inner Shareable domain. Traps execution of those TLB maintenance instructions at EL1 ~~using AArch64, and at EL1 using AArch32,~~ to EL2, when EL2 is enabled in the current Security state. This applies to the following instructions:

- When EL1 is using AArch64, TLBI VMALLE1IS, TLBI VAE1IS, TLBI ASIDE1IS,TLBI VAAE1IS, TLBI VALE1IS, TLBI VAALE1IS,TLBI RVAE1IS, TLBI RVAAE1IS,TLBI RVALE1IS, and TLBI RVAALE1IS.
- When EL1 is using AArch32, TLBIALLIS, TLBIMVAIS, TLBIASIDIS, TLBIMVAAIS, TLBIMVALIS, and TLBIMVAALIS.

TTLBIS	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Execution of the specified instructions are trapped to EL2.

~~If ARMv8.2-EVT is not implemented, this field is RES0.~~

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EnSCXT, bit [53]

When ARMv8.0-CSV2 is implemented:

Enable Access to the SCXTNUM_EL1 and SCXTNUM_EL0 registers. The defined values are:

EnSCXT	Meaning
0b0	When (HCR_EL2.TGE==0 or HCR_EL2.E2H==0) and EL2 is enabled in the current Security state, EL1 and EL0 access to SCXTNUM_EL0 and EL1 access to SCXTNUM_EL1 is disabled by this mechanism, causing an exception to EL2, and the values of these registers to be treated as 0. When ((HCR_EL2.TGE==1 and HCR_EL2.E2H==1) and EL2 is enabled in the current Security state, EL0 access to SCXTNUM_EL0 is disabled by this mechanism, causing an exception to EL2, and the value of this register to be treated as 0.
0b1	This control does not cause accesses to SCXTNUM_EL0 or SCXTNUM_EL1 to be trapped.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1,1}, this bit has no effect on execution at EL0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TOCU, bit [52]

When ARMv8.2-EVT is implemented:

Trap cache maintenance instructions that operate to the Point of Unification. Traps execution of those cache maintenance instructions ~~at EL1 or EL0 using AArch64, and at EL1 using AArch32,~~ to EL2, when EL2 is enabled in the current Security state. This applies to the following instructions:

- When SCTLR_EL1.UCI is 1, HCR_EL2.{TGE, E2H} is not {1, 1}, and EL0 is using AArch64, IC IVAU, DC CVAU.
- When EL1 is using AArch64, IC IVAU, IC IALLU, DC CVAU.
- When EL1 is using AArch32, ICIMVAU, ICIALLU, DCCMVAU.

Note

An exception generated because an instruction is UNDEFINED at EL0 is higher priority than this trap to EL2. In addition:

- IC IALLUIS and IC IALLU are always UNDEFINED at EL0 using AArch64.
- ICIMVAU, ICIALLU, ICIALLUIS, and DCCMVAU are always UNDEFINED at EL0 using AArch32.

TOCU	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Execution of the specified instructions are trapped to EL2.

If the Point of Unification is before any level of data cache, it is IMPLEMENTATION DEFINED whether the execution of any data or unified cache clean by VA to the Point of Unification instruction can be trapped when the value of this control is 1.

If the Point of Unification is before any level of instruction cache, it is IMPLEMENTATION DEFINED whether the execution of any instruction cache invalidate to the Point of Unification instruction can be trapped when the value of this control is 1.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

AMVOFFEN, bit [51]

When ARMv8.6-AMU is implemented:

Activity Monitors Virtual Offsets Enable.

AMVOFFEN	Meaning
0b0	Virtualization of the Activity Monitors is disabled. Indirect reads of the virtual offset registers are zero.
0b1	Virtualization of the Activity Monitors is enabled.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TICAB, bit [50]

When ARMv8.2-EVT is implemented:

Trap ICIALLUIS/IC IALLUIS cache maintenance instructions. Traps execution of those cache maintenance instructions at EL1 ~~using AArch64, and at EL1 using AArch32,~~ to EL2, when EL2 is enabled in the current Security state. This applies to the following instructions:

- When EL1 is using AArch64, IC IALLUIS.
- When EL1 is using AArch32, ICIALLUIS.

TICAB	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL1 execution of the specified instructions is trapped to EL2.

~~If ARMv8.2-EVT is not implemented, this field is RES0.~~

If the Point of Unification is before any level of instruction cache, it is IMPLEMENTATION DEFINED whether the execution of any instruction cache invalidate to the Point of Unification instruction can be trapped when the value of this control is 1.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TID4, bit [49]

When ARMv8.2-EVT is implemented:

Trap ID group 4. Traps the following register accesses to EL2, when EL2 is enabled in the current Security state:

AArch64:

- EL1 reads of CCSIDR_EL1, CCSIDR2_EL1, CLIDR_EL1, and CSSELR_EL1.
- EL1 writes to CSSELR_EL1.

AArch32:

- EL1 reads of CCSIDR, CCSIDR2, CLIDR, and CSSELR.
- EL1 writes to CSSELR.

TID4	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	The specified EL1 and EL0 accesses to ID group 4 registers are trapped to EL2.

~~If ARMv8.2-EVT is not implemented, this field is RES0.~~

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [48]

Reserved, RES0.

FIEN, bit [47]

When ARMv8.4-RAS is implemented:

Fault Injection Enable. Unless this bit is set to 1, accesses to the ERXPFGCDN_EL1, ERXPFGCTL_EL1, and ERXPFGF_EL1 registers from EL1 generate a Trap exception to EL2, when EL2 is enabled in the current Security state, reported using EC syndrome value 0x18.

FIEN	Meaning
0b0	Accesses to the specified registers from EL1 are trapped to EL2, when EL2 is enabled in the current Security state.
0b1	This control does not cause any instructions to be trapped.

If EL2 is disabled in the current Security state, the Effective value of HCR_EL2.FIEN is 0b1.

If ERRIDR_EL1.NUM is zero, meaning no error records are implemented, or no error record accessible using System registers is owned by a node that implements the RAS Common Fault Injection Model Extension, then this bit might be RES0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

FWB, bit [46]

When ARMv8.4-S2FWB is implemented:

Defines the combined cacheability attributes in a 2 stage translation regime.

FWB	Meaning
0b0	When this bit is 0, then: • The combination of stage 1 and stage 2 translations on memory type and cacheability attributes are as described in the Armv8.0 architecture. For more information see D4.5.4 Combining the stage 1 and stage 2 attributes • The encoding of the stage 2 memory type and cacheability attributes in bits[5:2] of the stage 2 page or block descriptors are as described in the Armv8.0 architecture.
0b1	When this bit is 1, then: • Bit[5] of stage 2 page or block descriptor is RES0. • When bit[4] of stage 2 page or block descriptor is 1 and when: ◦ Bits[3:2] of stage 2 page or block descriptor are 0b11, the resultant memory type and inner or outer cacheability~~cachebility~~ attribute is the same as the stage 1 memory type and inner or outer cacheability attribute. ◦ Bits[3:2] of stage 2 page or block descriptor are 0b10, the resultant memory type and attribute is Normal Write-Back. ◦ Bits[3:2] of stage 2 page or block descriptor are 0b0x, the resultant memory type will be Normal Non-cacheable except where the stage 1 memory type was Device->attr< the resultant memory type will be Device->attr< • When bit[4] of stage 2 page or block descriptor is 0 the memory type is Device, and when: ◦ Bits[3:2] of stage 2 page or block descriptor are 0b00, the stage 2 memory type is Device-nGnRnE. ◦ Bits[3:2] of stage 2 page or block descriptor are 0b01, the stage 2 memory type is Device-nGnRE. ◦ Bits[3:2] of stage 2 page or block descriptor are 0b10, the stage 2 memory type is Device-nGRE. ◦ Bits[3:2] of stage 2 page or block descriptor are 0b11, the stage 2 memory type is Device-GRE. • If the stage 1 translation specifies a cacheable memory type, then the stage 1 cache allocation hint is applied to the final cache allocation hint where the final memory type is cacheable. • If the stage 1 translation does not specify a cacheable memory type, then if the final memory type is cacheable, it is treated as read allocate, write allocate. The stage 1 and stage 2 memory types are combined in the manner described in D4.5.4 Combining the stage 1 and stage 2 attributes

In Secure state, this bit applies to both the Secure stage 2 translation and the Non-secure stage 2 translation.

This bit is permitted to be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NV2, bit [45]

When ARMv8.4-NV is implemented:

Nested Virtualization. Changes the behaviors of HCR_EL2.{NV, NV1} to provide a mechanism for hardware to transform reads and writes from System registers into reads and writes from memory.

NV2	Meaning
0b0	This bit has no effect on the behavior of HCR_EL2.{NV, NV1}. The behavior of HCR_EL2.{NV, NV1} is as defined for ARMv8.3-NV.
0b1	Redefines behavior of HCR_EL2{NV, NV1} to enable: • Transformation of read/writes to registers into read/writes to memory. • Redirection of EL2 registers to EL1 registers. Any exception taken from EL1 and taken to EL1 causes SPSR_EL1.M[3:2] to be set to 0b10 and not 0b01.

~~When this bit is 0, the behavior of HCR_EL2.{NV, NV1} is as defined for ARMv8.3-NV.~~

~~When this is bit is 1, then any exception taken from EL1 and taken to EL1 causes SPSR_EL1.M[3:2] to be set to 0b10 and not 0b01~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

AT, bit [44]

When ARMv8.3-NV is implemented:

Address Translation. EL1 execution of the following address translation instructions is trapped to EL2, when EL2 is enabled in the current Security state, reported using EC syndrome value 0x18:

- AT S1E0R, AT S1E0W, AT S1E1R, AT S1E1W, AT S1E1RP, AT S1E1WP.

AT	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL1 execution of the specified instructions is trapped to EL2.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NV1, bit [43]

When ARMv8.4-NV is implemented:

Nested Virtualization.

NV1	Meaning
0b0	If HCR_EL2.{NV, NV2} are both 1, accesses executed from EL1 to implemented EL12, EL02, or EL2 registers are transformed to loads and stores. If HCR_EL2.NV2 is 0 or HCR_EL2.{NV, NV2} == {0, 1}, this control does not cause any instructions to be trapped.
0b1	If HCR_EL2.NV2 is 1, accesses executed from EL1 to implemented EL2 registers are transformed to loads and stores. If HCR_EL2.NV2 is 0, EL1 accesses to VBAR_EL1, ELR_EL1, and SPSR_EL1, are trapped to EL2, when EL2 is enabled in the current Security state, reported using EC syndrome value 0x18.

If HCR_EL2.NV2 is 1, the value of HCR_EL2.NV1 defines which EL1 register accesses are transformed to loads and stores. These transformed accesses have priority over the trapping of registers.

The trapping of EL1 registers caused by other control bits has priority over the transformation of these accesses.

If a register is specified that is not implemented by an implementation, then access to that register are UNDEFINED.

For the list of registers affected, see Enhanced support for nested virtualization.

If HCR_EL2.{NV, NV1, NV2} are {1, 0, 0},any exception taken from EL1, and taken to EL1, causes the SPSR_EL1.M[3:2] to be set to `0b10`, and not `0b01`.

If HCR_EL2.{NV, NV1, NV2} are {1, 1, 0}, then:

- The EL1 translation table Block and Page descriptors:
  - Bit[54] holds the PXN instead of the UXN.
  - Bit[53] is RES0.
  - Bit[6] is treated as 0 regardless of the actual value.
- If Hierarchical Permissions are enabled, the EL1 translation table Table descriptors are as follows:
  - Bit[61] is treated as 0 regardless of the actual value.
  - Bit[60] holds the PXNTable instead of the UXNTable.
  - Bit[59] is RES0.
- When executing at EL1, the PSTATE.PAN bit is treated as zero for all purposes except reading the value of the bit.
- When executing at EL1, the LDTR* instructions are treated as the equivalent LDR* instructions, and the STTR* instructions are treated as the equivalent STR* instructions.

If HCR_EL2.{NV, NV1, NV2} are {0, 1, 0}, then the behavior is a CONSTRAINED UNPREDICTABLE choice of:

- Behaving as if HCR_EL2.NV is 1 and HCR_EL2.NV1 is 1 for all purposes other than reading than reading back the value of the HCR_EL2.NV bit.
- Behaving as if HCR_EL2.NV is 0 and HCR_EL2.NV1 is 0 for all purposes other than reading than reading back the value of the HCR_EL2.NV1 bit.
- Behaving with regard to the HCR_EL2.NV and HCR_EL2.NV1 bits behavior as defined in the rest of this description.

This bit is permitted to be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

When ARMv8.3-NV is implemented:

Nested Virtualization. EL1 accesses to certain registers are trapped to EL2, when EL2 is enabled in the current Security state.

NV1	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	EL1 accesses to VBAR_EL1, ELR_EL1, SPSR_EL1 are trapped to EL2, when EL2 is enabled in the current Security state, reported using EC syndrome value `0x18`.

If HCR_EL2.NV is 1 and HCR_EL2.NV1 is 0 then the following effects also apply:

- Any exception taken from EL1, and taken to EL1, causes the SPSR_EL1.M[3:2] to be set to `0b10`, and not `0b01`.

If the bits HCR_EL2.NV and HCR_EL2.NV1 are both set to 1 then following effects also apply:

- The EL1 translation table Block and Page descriptors:
  - Bit[54] holds the PXN instead of the UXN.
  - Bit[53] is RES0.
  - Bit[6] is treated as 0 regardless of the actual value.
- If Hierarchical Permissions are enabled, the EL1 translation table Table descriptors are as follows:
  - Bit[61] is treated as 0 regardless of the actual value.
  - Bit[60] holds the PXNTable instead of the UXNTable.
  - Bit[59] is RES0.
- When executing at EL1, the PSTATE.PAN bit is treated as zero for all purposes except reading the value of the bit.
- When executing at EL1, the LDTR* instructions are treated as the equivalent LDR* instructions, and the STTR* instructions are treated as the equivalent STR* instructions.

If HCR_EL2.NV is 0 and HCR_EL2.NV1 is 1 then the behavior is a CONSTRAINED UNPREDICTABLE choice of:

- Behaving as if HCR_EL2.NV is 1 and HCR_EL2.NV1 is 1 for all purposes other than reading than reading back the value of the HCR_EL2.NV bit.
- Behaving as if HCR_EL2.NV is 0 and HCR_EL2.NV1 is 0 for all purposes other than reading than reading back the value of the HCR_EL2.NV1 bit.
- Behaving with regard to the HCR_EL2.NV and HCR_EL2.NV1 bits behavior as defined in the rest of this description.

This bit is permitted to be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NV, bit [42]

When ARMv8.4-NV is implemented:

Nested Virtualization.

When HCR_EL2.NV2 is 1, redefines register accesses so that:

- Instructions accessing the Special purpose registers SPSR_EL2 and ELR_EL2 instead access SPSR_EL1 and ELR_EL1 respectively.
- Instructions accessing the System registers ESR_EL2 and FAR_EL2 instead access ESR_EL1 and FAR_EL1.

When HCR_EL2.NV2 is 0, or if ARMv8.4-NV is not implemented, traps functionality that is permitted at EL2 and would be UNDEFINED at EL1 if this field was 0, when EL2 is enabled in the current Security state. This applies to the following operations:

- EL1 accesses to Special-purpose registers that are not UNDEFINED at EL2.
- EL1 accesses to System registers that are not UNDEFINED at EL2.
- Execution of EL1 or EL2 translation regime address translation and TLB maintenance instructions for EL2 and above.

NV	Meaning
0b0	When this bit is set to 0, HCR_EL2.NV2 == 0 for all purposes other than reading this register. This control does not cause any instructions to be trapped. When HCR_EL2.NV2 is 1, no ARMv8.4-NV functionality is implemented.
0b1	When HCR_EL2.NV2 is 0, or if ARMv8.4-NV is not implemented, EL1 accesses to the specified registers or the execution of the specified instructions are trapped to EL2, when EL2 is enabled in the current Security state. EL1 read accesses to the CurrentEL register return a value of 0x2. When HCR_EL2.NV2 is 1, this control redefines EL1 register accesses so that instructions accessing SPSR_EL2, ELR_EL2, ESR_EL2, and FAR_EL2 instead access SPSR_EL1, ELR_EL1, ESR_EL1, and FAR_EL1 respectively.

When HCR_EL2.NV2 is 0, or if ARMv8.4-NV is not implemented, then:

- The System or Special-purpose registers for which accesses are trapped and reported using EC syndrome value 0x18 are as follows:
  - Registers accessed using MRS or MSR with a name ending in _EL2, except SP_EL2.
  - Registers accessed using MRS or MSR with a name ending in _EL12.
  - Registers accessed using MRS or MSR with a name ending in _EL02.
  - Special-purpose registers SPSR_irq, SPSR_abt, SPSR_und and SPSR_fiq, accessed using MRS or MSR.
  - Special-purpose register SP_EL1 accessed using the dedicated MRS or MSR instruction.
- The instructions for which the execution is trapped and reported using EC syndrome value 0x18 are as follows:
  - EL2 translation regime Address Translation instructions and TLB maintenance instructions.
  - EL1 translation regime Address Translation instructions and TLB maintenance instructions that are only accessible from EL2 and EL3.
- The instructions for which the execution is trapped as follows:

    - SMC in an implementation that does not include EL3 and when HCR_EL2.TSC is 1. HCR_EL2.TSC bit is not RES0 in this case. This is reported using EC syndrome value 0x17.
    - The ERET, ERETAA, and ERETAB instructions, reported using EC syndrome value 0x1A.

Note

The priority of this trap is higher than the priority of the HCR_EL2.API trap. If both of these bits are set so that EL1 execution of an ERETAA or ERETAB instruction is trapped to EL2, then the syndrome reported is 0x1A.

This field resets to an architecturally UNKNOWN value.

When ARMv8.3-NV is implemented:

Nested Virtualization. Traps functionality that is permitted at EL2 and would be UNDEFINED at EL1 if this field was 0, when EL2 is enabled in the current Security state. This applies to the following operations:

- EL1 accesses to Special-purpose registers that are not UNDEFINED at EL2.
- EL1 accesses to System registers that are not UNDEFINED at EL2.
- Execution of EL1 or EL2 translation regime address translation and TLB maintenance instructions for EL2 and above.

The possible values are:

NV	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL1 accesses to the specified registers or the execution of the specified instructions are trapped to EL2, when EL2 is enabled in the current Security state. EL1 read accesses to the CurrentEL register return a value of 0x2.

The System or Special-purpose registers for which accesses are trapped and reported using EC syndrome value 0x18 are as follows:

- Registers accessed using MRS or MSR with a name ending in _EL2, except SP_EL2.
- Registers accessed using MRS or MSR with a name ending in _EL12.
- Registers accessed using MRS or MSR with a name ending in _EL02.
- Special-purpose registers SPSR_irq, SPSR_abt, SPSR_und and SPSR_fiq, accessed using MRS or MSR.
- Special-purpose register SP_EL1 accessed using the dedicated MRS or MSR instruction.

The instructions for which the execution is trapped and reported using EC syndrome value 0x18 are as follows:

- EL2 translation regime Address Translation instructions and TLB maintenance instructions.
- EL1 translation regime Address Translation instructions and TLB maintenance instructions that are only accessible from EL2 and EL3.

The execution of the ERET, ERETAA, and ERETAB instructions are trapped and reported using EC syndrome value 0x1A

Note

The priority of this trap is higher than the priority of the HCR_EL2.API trap. If both of these bits are set so that EL1 execution of an ERETAA or ERETAB instruction is trapped to EL2, then the syndrome reported is 0x1A.

The execution of the SMC instructions in an implementation that does not include EL3 and when HCR_EL2.TSC is 1 are trapped and reported using EC syndrome value 0x17. HCR_EL2.TSC bit is not RES0 in this case.

This bit is permitted to be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

API, bit [41]

When ARMv8.3-PAuth is implemented:

Controls the use of instructions related to Pointer Authentication:

- In EL0, when HCR_EL2.TGE==0 or HCR_EL2.E2H==0, and the associated SCTLR_EL1.En<N><M>==1.
- In EL1, the associated SCTLR_EL1.En<N><M>==1.

Traps are reported using EC syndrome value `0x09`. The Pointer Authentication instructions trapped are:

- AUTDA, AUTDB, AUTDZA, AUTDZB, AUTIA, AUTIA1716, AUTIASP, AUTIAZ, AUTIB, AUTIB1716, AUTIBSP, AUTIBZ, AUTIZA, AUTIZB.
- PACGA, PACDA, PACDB, PACDZA, PACDZB, PACIA, PACIA1716, PACIASP, PACIAZ, PACIB, PACIB1716, PACIBSP, PACIBZ, PACIZA, PACIZB.
- RETAA, RETAB, BRAA, BRAB, BLRAA, BLRAB, BRAAZ, BRABZ, BLRAAZ, BLRABZ.
- ERETAA, ERETAB, LDRAA and LDRAB.

API	Meaning
`0b0`	The instructions related to Pointer Authentication are trapped to EL2, when EL2 is enabled in the current Security state and the instructions are enabled for the EL1&0 translation regime, from: • EL0 when HCR_EL2.TGE==0 or HCR_EL2.E2H==0. • EL1. If HCR_EL2.NV is 1, the HCR_EL2.NV trap takes precedence over the HCR_EL2.API trap for the ERETAA and ERETAB instructions.
`0b1`	This control does not cause any instructions to be trapped.

If ARMv8.3-PAuth is implemented but EL2 is not implemented or disabled in the current Security state, the system behaves as if this bit is 1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

APK, bit [40]

When ARMv8.3-PAuth is implemented:

Trap registers holding "key" values for Pointer Authentication. Traps accesses to the following registers from EL1 to EL2, when EL2 is enabled in the current Security state, reported using EC syndrome value `0x18`:

- APIAKeyLo_EL1, APIAKeyHi_EL1, APIBKeyLo_EL1, APIBKeyHi_EL1, APDAKeyLo_EL1, APDAKeyHi_EL1, APDBKeyLo_EL1, APDBKeyHi_EL1, APGAKeyLo_EL1, and APGAKeyHi_EL1.

APK	Meaning
`0b0`	Access to the registers holding "key" values for pointer authentication from EL1 are trapped to EL2, when EL2 is enabled in the current Security state.
`0b1`	This control does not cause any instructions to be trapped.

Note

If ARMv8.3-PAuth is implemented but EL2 is not implemented or is disabled in the current Security state, the system behaves as if this bit is 1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [39]

Reserved, RES0.

MIOCNCE, bit [38]

Mismatched Inner/Outer Cacheable Non-Coherency Enable, for the EL1&0 translation regimes.

MIOCNCE	Meaning
0b0	For the EL1&0 translation regimes, for permitted accesses to a memory location that use a common definition of the Shareability and Cacheability of the location, there must be no loss of coherency if the Inner Cacheability attribute for those accesses differs from the Outer Cacheability attribute.
0b1	For the EL1&0 translation regimes, for permitted accesses to a memory location that use a common definition of the Shareability and Cacheability of the location, there might be a loss of coherency if the Inner Cacheability attribute for those accesses differs from the Outer Cacheability attribute.

For more information see 'Mismatched memory attributes' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section B2 (The AArch64 Application Level Memory Model).

This field can be implemented as RAZ/WI.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

TEA, bit [37]

Route synchronous External abort exceptions to EL2. If the RAS Extension is implemented, the possible values of this bit are:

TEA	Meaning
0b0	This control does not cause exceptions to be routed from EL0 and EL1 to EL2.
0b1	Route synchronous External abort exceptions from EL0 and EL1 to EL2, when EL2 is enabled in the current Security state, if not routed to EL3.

When the RAS Extension is not implemented, this field is RES0.

This field resets to an architecturally UNKNOWN value.

TERR, bit [36]

When RAS is implemented:

Trap Error record accesses. Trap accesses to the RAS error registers from EL1 to EL2 as follows:

- If EL1 is using AArch64 state, accesses to the following registers are trapped to EL2, reported using EC syndrome value 0x18:
  - ERRIDR_EL1, ERRSELR_EL1, ERXADDR_EL1, ERXCTLR_EL1, ERXFR_EL1, ERXMISC0_EL1, ERXMISC1_EL1, and ERXSTATUS_EL1.
  - When ARMv8.4-RAS is implemented, ERXMISC2_EL1, and ERXMISC3_EL1.
- If EL1 is using AArch32 state, MCR or MRC accesses are trapped to EL2, reported using EC syndrome value 0x03, MCRR or MRRC accesses are trapped to EL2, reported using EC syndrome value 0x04:
  - ERRIDR, ERRSELR, ERXADDR, ERXADDR2, ERXCTLR, ERXCTLR2, ERXFR, ERXFR2, ERXMISC0, ERXMISC1, ERXMISC2, ERXMISC3, and ERXSTATUS.
  - When ARMv8.4-RAS is implemented, ERXMISC4, ERXMISC5, ERXMISC6, and ERXMISC7.

TERR	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Accesses to the specified registers from EL1 generate a Trap exception to EL2, when EL2 is enabled in the current Security state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TLOR, bit [35]

When ARMv8.1-LOR is implemented:

Trap LOR registers. Traps accesses to the LORSA_EL1, LOREA_EL1, LORN_EL1, LORC_EL1, and LORID_EL1 registers from EL1 to EL2, when EL2 is enabled in the current Security state.

TLOR	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL1 accesses to the LOR registers are trapped to EL2, when EL2 is enabled in the current Security state.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

E2H, bit [34]

When ARMv8.1-VHE is implemented:

EL2 Host. Enables a configuration where a Host Operating System is running in EL2, and the Host Operating System's applications are running in EL0.

E2H	Meaning
0b0	The facilities to support a Host Operating System at EL2 are disabled.
0b1	The facilities to support a Host Operating System at EL2 are enabled.

For information on the behavior of this bit see Behavior of HCR_EL2.E2H.

This bit is permitted to be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ID, bit [33]

Stage 2 Instruction access cacheability disable. For the EL1&0 translation regime, when EL2 is enabled in the current Security state and HCR_EL2.VM==1, this control forces all stage 2 translations for instruction accesses to Normal memory to be Non-cacheable.

ID	Meaning
0b0	This control has no effect on stage 2 of the EL1&0 translation regime.
0b1	Forces all stage 2 translations for instruction accesses to Normal memory to be Non-cacheable.

This bit has no effect on the EL2, EL2&0, or EL3 translation regimes.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

CD, bit [32]

Stage 2 Data access cacheability disable. For the EL1&0 translation regime, when EL2 is enabled in the current Security state and HCR_EL2.VM==1, this control forces all stage 2 translations for data accesses and translation table walks to Normal memory to be Non-cacheable.

CD	Meaning
0b0	This control has no effect on stage 2 of the EL1&0 translation regime for data accesses and translation table walks.
0b1	Forces all stage 2 translations for data accesses and translation table walks to Normal memory to be Non-cacheable.

This bit has no effect on the EL2, EL2&0, or EL3 translation regimes.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

RW, bit [31]

When AArch32 is supported at any Exception level:

Execution state control for lower Exception levels:

RW	Meaning
0b0	Lower levels are all AArch32.
0b1	The Execution state for EL1 is AArch64. The Execution state for EL0 is determined by the current value of PSTATE.nRW when executing at EL0.

If AArch32 state is not supported by the implementation at EL1, then this bit is RAO/WI.

In an implementation that includes EL3, when EL2 is not enabled in Secure state, the PE behaves as if this bit has the same value as the SCR_EL3.RW bit for all purposes other than a direct read or write access of HCR_EL2.

The RW bit is permitted to be cached in a TLB.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 1 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RAO/WI.

TRVM, bit [30]

Trap Reads of Virtual Memory controls. Traps EL1 reads of the virtual memory control registers to EL2, when EL2 is enabled in the current Security state, ~~from both Execution states~~ as follows:

- If EL1 is using AArch64 state, the following registers are trapped to EL2 and reported using EC syndrome value `0x18`.
    - SCTLR_EL1, TTBR0_EL1, TTBR1_EL1, TCR_EL1, ESR_EL1, FAR_EL1, AFSR0_EL1, AFSR1_EL1, MAIR_EL1, AMAIR_EL1, CONTEXTIDR_EL1.
- If EL1 is using AArch32 state, accesses using MRC to the following registers are trapped to EL2 and reported using EC syndrome value `0x03`, accesses using MRRC are trapped to EL2 and reported using EC syndrome value `0x04`:
    - SCTLR, TTBR0, TTBR1, TTBCR, TTBCR2, DACR, DFSR, IFSR, DFAR, IFAR, ADFSR, AIFSR, PRRR, NMRR, MAIR0, MAIR1, AMAIR0, AMAIR1, CONTEXTIDR.

TRVM	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	EL1 read accesses to the specified Virtual Memory controls are trapped to EL2, when EL2 is enabled in the current Security state.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

Note

EL2 provides a second stage of address translation, that a hypervisor can use to remap the address map defined by a Guest OS. In addition, a hypervisor can trap attempts by a Guest OS to write to the registers that control the memory system. A hypervisor might use this trap as part of its virtualization of memory management.

This field resets to an architecturally UNKNOWN value.

HCD, bit [29]

When EL3 is not implemented:

HVC instruction disable. Disables EL1 execution of HVC instructions, from both Execution states, when EL2 is enabled in the current Security state, reported using EC syndrome value `0x00`.

HCD	Meaning
`0b0`	HVC instruction execution is enabled at EL2 and EL1.
`0b1`	HVC instructions are UNDEFINED at EL2 and EL1. Any resulting exception is taken to the Exception level at which the HVC instruction is executed.

Note

HVC instructions are always UNDEFINED at EL0.

~~This bit is only implemented if EL3 is not implemented. Otherwise, it is RES0.~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TDZ, bit [28]

Trap DC ZVA instructions. Traps EL0 and EL1 execution of DC ZVA instructions to EL2, when EL2 is enabled in the current Security state, from AArch64 state only, reported using EC syndrome value `0x18`.

If ARMv8.5-MemTag is implemented, this trap also applies to DC GVA and DC GZVA.

TDZ	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	In AArch64 state, any attempt to execute an instruction this trap applies to at EL1, or at EL0 when the instruction is not UNDEFINED at EL0, is trapped to EL2 when EL2 is enabled in the current Security state. Reading the DCZID_EL0 returns a value that indicates that the instructions this trap applies to are not supported.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

TGE, bit [27]

Trap General Exceptions, from EL0.

TGE	Meaning
0b0	This control has no effect on execution at EL0.
0b1	When EL2 is not enabled in the current Security state, this control has no effect on execution at EL0. When EL2 is enabled in the current Security state, in all cases: • All exceptions that would be routed to EL1 are routed to EL2. • If EL1 is using AArch64, the~~The~~ SCTLR_EL1.M field~~,~~ is~~or~~ treated as being 0 for all purposes other than returning the result of a direct read of SCTLR~~.M field if EL1 is using AArch32, is treated as being 0 for all purposes other than returning the result of a direct read of~~ SCTLR_EL1 ~~or~~ SCTLR~~.~~. • If EL1 is using AArch32, the SCTLR.M field is treated as being 0 for all purposes other than returning the result of a direct read of SCTLR. • All virtual interrupts are disabled. • Any IMPLEMENTATION DEFINED mechanisms for signaling virtual interrupts are disabled. • An exception return to EL1 is treated as an illegal exception return. • The MDCR_EL2.{TDRA, TDOSA, TDA, TDE} fields are treated as being 1 for all purposes other than returning the result of a direct read of MDCR_EL2. In addition, when EL2 is enabled in the current Security state, if: • HCR_EL2.E2H is 0, the Effective values of the HCR_EL2.{FMO, IMO, AMO} fields are 1. • HCR_EL2.E2H is 1, the Effective values of the HCR_EL2.{FMO, IMO, AMO} fields are 0. For further information on the behavior of this bit when E2H is 1, see Behavior of HCR_EL2.E2H.

HCR_EL2.TGE must not be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

TVM, bit [26]

Trap Virtual Memory controls. Traps EL1 writes to the virtual memory control registers to EL2, when EL2 is enabled in the current Security state, ~~from both Execution states~~ as follows:

- If EL1 is using AArch64 state, the following registers are trapped to EL2 and reported using EC syndrome value 0x18:
  - SCTLR_EL1, TTBR0_EL1, TTBR1_EL1, TCR_EL1, ESR_EL1, FAR_EL1, AFSR0_EL1, AFSR1_EL1, MAIR_EL1, AMAIR_EL1, CONTEXTIDR_EL1.
- If EL1 is using AArch32 state, accesses using MCR to the following registers are trapped to EL2 and reported using EC syndrome value 0x03, accesses using MCRR are trapped to EL2 and reported using EC syndrome value 0x04:

    - SCTLR, TTBR0, TTBR1, TTBCR, TTBCR2, DACR, DFSR, IFSR, DFAR, IFAR, ADFSR, AIFSR, PRRR, NMRR, MAIR0, MAIR1, AMAIR0, AMAIR1, CONTEXTIDR.

TVM	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL1 write accesses to the specified EL1 virtual memory control registers are trapped to EL2, when EL2 is enabled in the current Security state.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

TTLB, bit [25]

When ARMv8.4-TLBI is implemented:

Trap TLB maintenance instructions. Traps EL1 execution of TLB maintenance instructions to EL2, when EL2 is enabled in the current Security state, ~~from both Execution states~~ as follows:

- When EL1 is using AArch64 state, the following instructions are trapped to EL2 and reported using EC syndrome value 0x18:
    - TLBI VMALLE1, TLBI VAE1, TLBI ASIDE1, TLBI VAAE1, TLBI VALE1, TLBI VAALE1.
    - TLBI VMALLE1IS, TLBI VAE1IS, TLBI ASIDE1IS, TLBI VAAE1IS, TLBI VALE1IS, TLBI VAALE1IS.
    - TLBI VMALLE1OS, TLBI VAE1OS, TLBI ASIDE1OS, TLBI VAAE1OS, TLBI VALE1OS, TLBI VAALE1OS.
    - TLBI RVAE1, TLBI RVAAE1, TLBI RVALE1, TLBI RVAALE1.
    - TLBI RVAE1IS, TLBI RVAAE1IS, TLBI RVALE1IS, TLBI RVAALE1IS.
    - TLBI RVAE1OS, TLBI RVAAE1OS, TLBI RVALE1OS, TLBI RVAALE1OS.
- When EL1 is using AArch32 state, the following instructions are trapped to EL2 and reported using EC syndrome value 0x03:
    - TLBIALLIS, TLBIMVAIS, TLBIASIDIS, TLBIMVAAIS, TLBIMVALIS, TLBIMVAALIS.
    - TLBIALL, TLBIMVA, TLBIASID, TLBIMVAA, TLBIMVAL, TLBIMVAAL
    - ITLBIALL, ITLBIMVA, ITLBIASID.
    - DTLBIALL, DTLBIMVA, DTLBIASID.

TTLB	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL1 execution of the specified TLB maintenance instructions are trapped to EL2, when EL2 is enabled in the current Security state.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

Note

The TLB maintenance instructions are UNDEFINED at EL0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Trap TLB maintenance instructions. Traps EL1 execution of TLB maintenance instructions to EL2, when EL2 is enabled in the current Security state.~~state, from both Execution states.~~ This applies to the following instructions:

- When EL1 is using AArch64, TLBI VMALLE1IS, TLBI VAE1IS, TLBI ASIDE1IS, TLBI VAAE1IS, TLBI VALE1IS, TLBI VAALE1IS, TLBI VMALLE1, TLBI VAE1, TLBI ASIDE1, TLBI VAAE1, TLBI VALE1, TLBI VAALE1.
- When EL1 is using AArch32, TLBIALLIS, TLBIMVAIS, TLBIASIDIS, TLBIMVAAIS, TLBIMVALIS, TLBIMVAALIS, ITLBIALL, ITLBIMVA, ITLBIASID, DTLBIALL, DTLBIMVA, DTLBIASID, TLBIALL, TLBIMVA, TLBIASID, TLBIMVAA, TLBIMVAL, TLBIMVAAL

TTLB	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL1 execution of the specified TLB maintenance instructions are trapped to EL2, when EL2 is enabled in the current Security state.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

TPU, bit [24]

Trap cache maintenance instructions that operate to the Point of Unification. Traps execution of those cache maintenance instructions ~~at EL1 or EL0 using AArch64, and at EL1 using AArch32,~~ to EL2, when EL2 is enabled in the current Security state as follows:

- If EL0 is using AArch64 state and the value of SCTLR_EL1.UCI is not 0, the following instructions are trapped to EL2 and reported with EC syndrome value `0x18`:
  - IC IVAU, DC CVAU. If the value of SCTLR_EL1.UCI is 0 these instructions are UNDEFINED at EL0 and any resulting exception is higher priority than this trap to EL2.
- If EL1 is using AArch64 state, the following instructions are trapped to EL2 and reported with EC syndrome value `0x18`:
  - IC IVAU, IC IALLU, IC IALLUIS, DC CVAU.
- If EL1 is using AArch32 state, the following instructions are trapped to EL2 and reported with EC syndrome value `0x18`:
  - ICIMVAU, ICIALLU, ICIALLUIS, DCCMVAU.

Note

An exception generated because an instruction is UNDEFINED at EL0 is higher priority than this trap to EL2. In addition:

- IC IALLUIS and IC IALLU are always UNDEFINED at EL0 using AArch64.
- ICIMVAU, ICIALLU, ICIALLUIS, and DCCMVAU are always UNDEFINED at EL0 using AArch32.

TPU	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Execution of the specified instructions is trapped to EL2, when EL2 is enabled in the current Security state.

If the Point of Unification is before any level of data cache, it is IMPLEMENTATION DEFINED whether the execution of any data or unified cache clean by VA to the Point of Unification instruction can be trapped when the value of this control is 1.

If the Point of Unification is before any level of instruction cache, it is IMPLEMENTATION DEFINED whether the execution of any instruction cache invalidate to the Point of Unification instruction can be trapped when the value of this control is 1.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

TPCP, bit [23]

When ARMv8.2-DCPoP is implemented:

Trap data or unified cache maintenance instructions that operate to the Point of Coherency or Persistence. Traps execution of those cache maintenance instructions ~~at EL1 or EL0 using AArch64, and at EL1 using AArch32,~~ to EL2, when EL2 is enabled in the current Security state as follows:

- If EL0 is using AArch64 state and the value of SCTLR_EL1.UCI is not 0, the following instructions are trapped to EL2 and reported using EC syndrome value `0x18`:
  - DC CIVAC, DC CVAC, DC CVAP. If the value of SCTLR_EL1.UCI is 0 these instructions are UNDEFINED at EL0 and any resulting exception is higher priority than this trap to EL2.
- If EL1 is using AArch64 state, the following instructions are trapped to EL2 and reported using EC syndrome value `0x18`:
  - DC IVAC, DC CIVAC, DC CVAC, DC CVAP.
- If EL1 is using AArch32 state, the following instructions are trapped to EL2 and reported using EC syndrome value `0x03`:
  - DCIMVAC, DCCIMVAC, DCCMVAC.

If ARMv8.2-DCCVADP is implemented, this trap also applies to DC CVADP.

If ARMv8.5-MemTag is implemented, this trap also applies to DC CIGVAC, DC CIGDVAC, DC IGVAC, DC IGDVAC, DC CGVAC, DC CGDVAC, DC CGVAP and DC CGDVAP.

If ARMv8.2-DCCVADP and ARMv8.5-MemTag are implemented, this trap also applies to DC CGVADP and DC CGDVADP.

Note

- An exception generated because an instruction is UNDEFINED at EL0 is higher priority than this trap to EL2. In addition:
  - AArch64 instructions which invalidate by VA to the Point of Coherency are always UNDEFINED at EL0 using AArch64.
  - DCIMVAC, DCCIMVAC, and DCCMVAC are always UNDEFINED at EL0 using AArch32.
- In Armv8.0 and Armv8.1, this field is named TPC. From Armv8.2 it is named TPCP.

TPCP	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Execution of the specified instructions is trapped to EL2, when EL2 is enabled in the current Security state.

If the Point of Coherency is before any level of data cache, it is IMPLEMENTATION DEFINED whether the execution of any data or unified cache clean, invalidate, or clean and invalidate instruction that operates by VA to the point of coherency can be trapped when the value of this control is 1.

If HCR_EL2.{E2H, TGE} is set to {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Trap data or unified cache maintenance instructions that operate to the Point of Coherency. Traps execution of those cache maintenance instructions ~~at EL1 or EL0 using AArch64, and at EL1 using AArch32,~~ to EL2, when EL2 is enabled in the current Security state as follows:

- If EL0 is using AArch64 state and the value of SCTLR_EL1.UCI is not 0, accesses to the following registers are trapped and reported using EC syndrome value 0x18:
  - DC CIVAC, DC CVAC. However, if the value of SCTLR_EL1.UCI is 0 these instructions are UNDEFINED at EL0 and any resulting exception is higher priority than this trap to EL2.
- If EL1 is using AArch64 state, accesses to DC IVAC, DC CIVAC, DC CVAC are trapped and reported using EC syndrome value 0x18.
- When EL1 is using AArch32, accesses to DCIMVAC, DCCIMVAC, and DCCMVAC are trapped and reported using EC syndrome value 0x03.

Note

- An exception generated because an instruction is UNDEFINED at EL0 is higher priority than this trap to EL2. In addition:
  - AArch64 instructions which invalidate by VA to the Point of Coherency are always UNDEFINED at EL0 using AArch64.
  - DCIMVAC, DCCIMVAC, and DCCMVAC are always UNDEFINED at EL0 using AArch32.
- In Armv8.0 and Armv8.1, this field is named TPC. From Armv8.2 it is named TPCP.

TPC	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Execution of the specified instructions is trapped to EL2, when EL2 is enabled in the current Security state.

If the Point of Coherency is before any level of data cache, it is IMPLEMENTATION DEFINED whether the execution of any data or unified cache clean, invalidate, or clean and invalidate instruction that operates by VA to the point of coherency can be trapped when the value of this control is 1.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

TSW, bit [22]

Trap data or unified cache maintenance instructions that operate by Set/Way. Traps execution of those cache maintenance instructions at EL1 ~~using AArch64, and at EL1 using AArch32,~~ to EL2, when EL2 is enabled in the current Security state as follows:

- If EL1 is using AArch64 state, accesses to DC ISW, DC CSW, DC CISW are trapped to EL2, reported using EC syndrome value `0x18`.
- If EL1 is using AArch32 state, accesses to DCISW, DCCSW, DCCISW are trapped to EL2, reported using EC syndrome value `0x03`.

If ARMv8.5-MemTag is implemented, this trap also applies to DC IGSW, DC IGDSW, DC CGSW, DC CGDW, DC CIGSW, and DC CIGDSW.

Note

An exception generated because an instruction is UNDEFINED at EL0 is higher priority than this trap to EL2, and these instructions are always UNDEFINED at EL0.

TSW	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Execution of the specified instructions is trapped to EL2, when EL2 is enabled in the current Security state.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

TACR, bit [21]

Trap Auxiliary Control Registers. Traps EL1 accesses to the Auxiliary Control Registers to EL2, when EL2 is enabled in the current Security state, ~~from both Execution states~~ as follows:

- If EL1 is using AArch64 state, accesses to ACTLR_EL1 to EL2, are trapped to EL2 and reported using EC syndrome value `0x18`.
- If EL1 is using AArch32 state, accesses to ACTLR and, if implemented, ACTLR2 are trapped to EL2 and reported using EC syndrome value `0x03`.

TACR	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	EL1 accesses to the specified registers are trapped to EL2, when EL2 is enabled in the current Security state.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

Note

ACTLR_EL1 is not accessible at EL0,~~ACTLR, and ACTLR2 are not accessible at EL0.~~

ACTLR, and ACTLR2 are not accessible at EL0.

The Auxiliary Control Registers are IMPLEMENTATION DEFINED registers that might implement global control bits for the PE.

This field resets to an architecturally UNKNOWN value.

TIDCP, bit [20]

Trap IMPLEMENTATION DEFINED functionality. Traps EL1 accesses to the encodings reserved for IMPLEMENTATION DEFINED functionality to EL2, when EL2 is enabled in the current Security state as follows:

- In AArch64 state, access to any of the encodings in the following reserved encoding spaces are trapped and reported using EC syndrome `0x18`:

    - IMPLEMENTATION DEFINED System instructions, which are accessed using SYS and SYSL, with CRn == {11, 15}.
    - IMPLEMENTATION DEFINED System registers, which are accessed using MRS and MSR with the S3_<op1>_<Cn>_<Cm>_<op2> register name.
- In AArch32 state, MCR and MRC access to instructions with the following encodings are trapped and reported using EC syndrome 0x03:
    - All coproc==p15, CRn==c9, opc1 == {0-7}, CRm == {c0-c2, c5-c8}, opc2 == {0-7}.
    - All coproc==p15, CRn==c10, opc1 =={0-7}, CRm == {c0, c1, c4, c8}, opc2 == {0-7}.
    - All coproc==p15, CRn==c11, opc1=={0-7}, CRm == {c0-c8, c15}, opc2 == {0-7}.

When the value of HCR_EL2.TIDCP is 1, it is IMPLEMENTATION DEFINED whether any of this functionality accessed from EL0 is trapped to EL2. If it is not, then it is UNDEFINED, and any attempt to access it from EL0 generates an exception that is taken to EL1.

TIDCP	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL1 accesses to or execution of the specified encodings reserved for IMPLEMENTATION DEFINED functionality are trapped to EL2, when EL2 is enabled in the current Security state.

An implementation can also include IMPLEMENTATION DEFINED registers that provide additional controls, to give finer-grained control of the trapping of IMPLEMENTATION DEFINED features.

Note

Arm expects the trapping of EL0 accesses to these functions to EL2 to be unusual, and used only when the hypervisor is virtualizing EL0 operation. Arm strongly recommends that unless the hypervisor must virtualize EL0 operation, an EL0 access to any of these functions is UNDEFINED, as it would be if the implementation did not include EL2. The PE then takes any resulting exception to EL1.

The trapping of accesses to these registers from EL1 is higher priority than an exception resulting from the register access being UNDEFINED.

This field resets to an architecturally UNKNOWN value.

TSC, bit [19]

Trap SMC instructions. Traps EL1 execution of SMC instructions to EL2, when EL2 is enabled in the current Security state.~~state, from both Execution states.~~

If execution is in AArch64 state the trap is reported using EC syndrome value 0x17.

~~If execution is in AArch64 state the trap is reported using EC syndrome value 0x17 and if execution is in AArch32 state, the trap is reported using EC syndrome value 0x13.~~

If execution is in AArch32 state, the trap is reported using EC syndrome value 0x13.

Note

HCR_EL2.TSC traps execution of the SMC instruction. It is not a routing control for the SMC exception. Trap exceptions and SMC exceptions have different preferred return addresses.

TSC	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	If EL3 is implemented, then any attempt to execute an SMC instruction at EL1 ~~using AArch64 or EL1 using AArch32~~ is trapped to EL2, when EL2 is enabled in the current Security state, regardless of the value of SCR_EL3.SMD. If EL3 is not implemented, ARMv8.3-NV is implemented, and HCR_EL2.NV is 1, then any attempt to execute an SMC instruction at EL1 using AArch64 is trapped to EL2, when EL2 is enabled in the current Security state. If EL3 is not implemented, and either ARMv8.3-NV is not implemented or HCR_EL2.NV is 0, then it is IMPLEMENTATION DEFINED whether: • Any attempt to execute an SMC instruction at EL1 is trapped to EL2, when EL2 is enabled in the current Security state. • Any attempt to execute an SMC instruction is UNDEFINED.

In AArch32 state, the Armv8-A architecture permits, but does not require, this trap to apply to conditional SMC instructions that fail their condition code check, in the same way as with traps on other conditional instructions.

SMC instructions are UNDEFINED at EL0.

If EL3 is not implemented and HCR_EL2.NV is 0, it is IMPLEMENTATION DEFINED whether this bit is:

- RES0.
- Implemented with the functionality as described in HCR_EL2.TSC.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

TID3, bit [18]

Trap ID group 3. Traps EL1 reads of group 3 ID registers to EL2, when EL2 is enabled in the current Security state, as follows:

- In AArch64 state, reads of the following registers are trapped to EL2, reported using EC syndrome value 0x18:
  - ID_PFR0_EL1, ID_PFR1_EL1, ID_DFR0_EL1, ID_AFR0_EL1, ID_MMFR0_EL1, ID_MMFR1_EL1, ID_MMFR2_EL1, ID_MMFR3_EL1, ID_ISAR0_EL1, ID_ISAR1_EL1, ID_ISAR2_EL1, ID_ISAR3_EL1, ID_ISAR4_EL1, ID_ISAR5_EL1, ID_ISAR6_EL1, MVFR0_EL1, MVFR1_EL1, MVFR2_EL1.
  - ID_AA64PFR0_EL1, ID_AA64PFR1_EL1, ID_AA64DFR0_EL1, ID_AA64DFR1_EL1, ID_AA64ISAR0_EL1, ID_AA64ISAR1_EL1, ID_AA64MMFR0_EL1, ID_AA64MMFR1_EL1, ID_AA64MMFR2_EL1, ID_AA64AFR0_EL1, ID_AA64AFR1_EL1, ID_AA64ZFR0_EL1 (where SVE is implemented), and ID_MMFR4_EL1
- In AArch64 state, ID_MMFR4_EL1 and ID_MMFR5_EL1 are trapped to EL2, unless implemented as RAZ, when it is IMPLEMENTATION DEFINED whether accesses to ID_MMFR4_EL1 or ID_MMFR5_EL1 are trapped to EL2, reported using EC syndrome value 0x18.
- In AArch64 state, ID_AA64MMFR2_EL1 and ID_ISAR6_EL1 are trapped to EL2, unless implemented as RAZ, when it is IMPLEMENTATION DEFINED whether accesses to ID_AA64MMFR2_EL1 or ID_ISAR6_EL1 are trapped to EL2, reported using EC syndrome value 0x18.
- In AArch64 state, ID_DFR1_EL1 is trapped to EL2, unless implemented as RAZ, when it is IMPLEMENTATION DEFINED whether accesses to ID_DFR1_EL1 are trapped to EL2, reported using EC syndrome value 0x18.
- In AArch64 state, ID_AA64ZFR0_EL1 is trapped to EL2, unless implemented as RAZ then it is IMPLEMENTATION DEFINED whether accesses to ID_AA64ZFR0_EL1 are trapped to EL2, reported using EC syndrome value 0x18.
- In AArch64 state, if~~it is~~ ARMv8.6-FGT~~IMPLEMENTATION DEFINED~~ is~~whether~~ implemented, this field traps all MRS accesses to encodings in the following range that are not already mentioned in this field description, reported using EC syndrome value 0x18:
  - Op0 == 3, op1 == 0, CRn == c0, CRm == {c1-c7~~c2-c7~~}, op2 == {0-7}.

- OtherwiseIn AArch32 state, inMRC AArch64access statето the following registers are trapped to EL2, itreported isusing EC syndrome value IMPLEMENTATION DEFINED0x03 whether this field traps MRS accesses to encodings in the following range that are not already mentioned in this field description, reported using EC syndrome value 0x18:
    - ID_PFR0, ID_PFR1, ID_DFR0, ID_AFR0, ID_MMFR0, ID_MMFR1, ID_MMFR2, ID_MMFR3, ID_ISAR0, ID_ISAR1, ID_ISAR2, ID_ISAR3, ID_ISAR4, ID_ISAR5, MVFR0, MVFR1, MVFR2, and ID_MMFR4Op0 == 3, op1 == 0, CRn == c0, CRm == {c2-c7}, op2 == {0-7}..
- In AArch32 state, MRC access to the following registers are trapped to EL2, reported using EC syndrome value 0x03:

  In AArch32 state, VMRS access to MVFR0, MVFR1, and MVFR2, reported using EC syndrome value 0x08.
    - ID_PFR0, ID_PFR1, ID_DFR0, ID_AFR0, ID_MMFR0, ID_MMFR1, ID_MMFR2, ID_MMFR3, ID_ISAR0, ID_ISAR1, ID_ISAR2, ID_ISAR3, ID_ISAR4, ID_ISAR5, MVFR0, MVFR1, MVFR2, and ID_MMFR4.
- In AArch32 state, VMRS access to MVFR0, MVFR1, and MVFR2, reported using EC syndrome value 0x08.

  In AArch32 state, ID_MMFR4 and ID_MMFR5 are trapped to EL2, unless implemented as RAZ, when it is IMPLEMENTATION DEFINED whether accesses to ID_MMFR4 or ID_MMFR5 are trapped to EL2, reported using EC syndrome value 0x03.
- In AArch32 state, ID_MMFR4ID_ISAR6 andis trapped to EL2, unless implemented as RAZ, when it is ID_MMFR5 are trapped to EL2, unless implemented as RAZ, when it is IMPLEMENTATION DEFINED whether accesses to ID_MMFR4ID_ISAR6 or ID_MMFR5 are trapped to EL2, reported using EC syndrome value 0x03.
- In AArch32 state, ID_ISAR6ID_DFR1 is trapped to EL2, unless implemented as RAZ, when it is IMPLEMENTATION DEFINED whether accesses to ID_ISAR6ID_DFR1 are trapped to EL2, reported using EC syndrome value 0x03.
- In AArch32 state, it is ID_DFR1 is trapped to EL2, unless implemented as RAZ, when it is IMPLEMENTATION DEFINED whether accesses to ID_DFR1 are trapped to EL2, reported using EC syndrome value 0x03.whether this bit traps MRC accesses to encodings that are not already mentioned, with coproc==p15, opc1 == 0, CRn == c0, CRm == {c2-c7}, opc2 == {0-7}.
- In AArch32 state, if ARMv8.6-FGT is implemented, this field traps all MRC accesses to encodings in the following range that are not already mentioned in this field description, reported using EC syndrome value 0x03:
    - coproc==p15, opc1 == 0, CRn == c0, CRm == {c1-c7}, opc2 == {0-7}.
- Otherwise, in AArch32 state, it is IMPLEMENTATION DEFINED whether this bit traps MRC accesses to encodings that are not already mentioned, with coproc==p15, opc1 == 0, CRn == c0, CRm == {c2-c7}, opc2 == {0-7}.

TID3	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	The specified EL1 read accesses to ID group 3 registers are trapped to EL2, when EL2 is enabled in the current Security state.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

TID2, bit [17]

Trap ID group 2. Traps the following register accesses to EL2, when EL2 is enabled in the current Security state, as follows:

- If EL1 is using AArch64, reads of CTR_EL0, CCSIDR_EL1, CCSIDR2_EL1, CLIDR_EL1, and CSSELR_EL1 are trapped to EL2, reported using EC syndrome value 0x18.
- If EL0 is using AArch64 and the value of SCTLR_EL1.UCT is not 0, reads of CTR_EL0 are trapped to EL2, reported using EC syndrome value 0x18. If the value of SCTLR_EL1.UCT is 0 then EL0 reads of CTR_EL0 are UNDEFINED and any resulting exception takes precedence over this trap.
- If EL1 is using AArch64, writes to CSSELR_EL1 are trapped to EL2, reported using EC syndrome value 0x18.
- If EL1 is using AArch32, reads of CTR, CCSIDR, CCSIDR2, CLIDR, and CSSELR are trapped to EL2, reported using EC syndrome value 0x03.

- If EL1 is using AArch32, writes to CSSELR are trapped to EL2, reported using EC syndrome value 0x03.

TID2	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	The specified EL1 and EL0 accesses to ID group 2 registers are trapped to EL2, when EL2 is enabled in the current Security state.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

TID1, bit [16]

Trap ID group 1. Traps EL1 reads of the following registers to EL2, when EL2 is enabled in the current Security state as follows:

- In AArch64 state, accesses of REVIDR_EL1, AIDR_EL1, reported using EC syndrome value 0x18.
- In AArch32 state, accesses of TCMTR, TLBTR, REVIDR, AIDR, reported using EC syndrome value 0x03.

TID1	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	The specified EL1 read accesses to ID group 1 registers are trapped to EL2, when EL2 is enabled in the current Security state.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

TID0, bit [15]

When AArch32 is supported at any Exception level:

Trap ID group 0. Traps the following register accesses to EL2:

- EL1 reads of the JIDR, reported using EC syndrome value 0x05.
- If the JIDR is RAZ from EL0, EL0 reads of the JIDR, reported using EC syndrome value 0x05.
- EL1 accesses using VMRS of the FPSID, reported using EC syndrome value 0x08.

Note

- It is IMPLEMENTATION DEFINED whether the JIDR is RAZ or UNDEFINED at EL0. If it is UNDEFINED at EL0 then any resulting exception takes precedence over this trap.
- The FPSID is not accessible at EL0 using AArch32.
- Writes to the FPSID are ignored, and not trapped by this control.

TID0	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	The specified EL1 read accesses to ID group 0 registers are trapped to EL2, when EL2 is enabled in the current Security state.

~~In an AArch64 only implementation, this bit is RES0.~~

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TWE, bit [14]

Traps EL0 and EL1 execution of WFE instructions to EL2, when EL2 is enabled in the current Security state, from both Execution states, reported using EC syndrome value `0x01`.

TWE	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Any attempt to execute a WFE instruction at EL0 or EL1 is trapped to EL2, when EL2 is enabled in the current Security state, if the instruction would otherwise have caused the PE to enter a low-power state and it is not trapped by SCTLR.nTWE or SCTLR_EL1.nTWE.

In AArch32 state, the attempted execution of a conditional WFE instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE can complete at any time, even without a Wakeup event, the traps on WFE are not guaranteed to be taken, even if the WFE is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

For more information about when WFE instructions can cause the PE to enter a low-power state, see 'Wait for Event mechanism and Send event' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

TWI, bit [13]

Traps EL0 and EL1 execution of WFI instructions to EL2, when EL2 is enabled in the current Security state, from both Execution states, reported using EC syndrome value `0x01`.

TWI	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Any attempt to execute a WFI instruction at EL0 or EL1 is trapped to EL2, when EL2 is enabled in the current Security state, if the instruction would otherwise have caused the PE to enter a low-power state and it is not trapped by SCTLR.nTWI or SCTLR_EL1.nTWI.

In AArch32 state, the attempted execution of a conditional WFI instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFI can complete at any time, even without a Wakeup event, the traps on WFI are not guaranteed to be taken, even if the WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

For more information about when WFI instructions can cause the PE to enter a low-power state, see 'Wait for Interrupt' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

DC, bit [12]

Default Cacheability.

DC	Meaning
0b0	This control has no effect on the EL1&0 translation regime.
0b1	In both Security states: • When EL1 is using AArch64, the PE behaves as if the value of the SCTLR_EL1.M field is 0 for all purposes other than returning the value of a direct read of SCTLR_EL1. • When EL1 is using AArch32, the PE behaves as if the value of the SCTLR.M field is 0 for all purposes other than returning the value of a direct read of SCTLR. • The PE behaves as if the value of the HCR_EL2.VM field is 1 for all purposes other than returning the value of a direct read of HCR_EL2. • The memory type produced by stage 1 of the EL1&0 translation regime is Normal Non-Shareable, Inner Write-Back Read-Allocate Write-Allocate, Outer Write-Back Read-Allocate Write-Allocate.

This field has no effect on the EL2, EL2&0, and EL3 translation regimes.

This field is permitted to be cached in a TLB.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this field.

This field resets to an architecturally UNKNOWN value.

BSU, bits [11:10]

Barrier Shareability upgrade. This field determines the minimum shareability domain that is applied to any barrier instruction executed from EL1 or EL0:

BSU	Meaning
0b00	No effect.
0b01	Inner Shareable.
0b10	Outer Shareable.
0b11	Full system.

This value is combined with the specified level of the barrier held in its instruction, using the same principles as combining the shareability attributes from two stages of address translation.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0b00 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

FB, bit [9]

Force broadcast. Causes the following instructions to be broadcast within the Inner Shareable domain when executed from EL1:

AArch32: BPIALL, TLBIALL, TLBIMVA, TLBIASID, DTLBIALL, DTLBIMVA, DTLBIASID, ITLBIALL, ITLBIMVA, ITLBIASID, TLBIMVAA, ICIALLU, TLBIMVAL, TLBIMVAAL.

AArch64: TLBI VMALLE1, TLBI VAE1, TLBI ASIDE1, TLBI VAAE1, TLBI VALE1, TLBI VAALE1, IC IALLU, TLBI RVAE1, TLBI RVAAE1, TLBI RVALE1, TLBI RVAALE1.

FB	Meaning
0b0	This field has no effect on the operation of the specified instructions.
0b1	When one of the specified instruction is executed at EL1, the instruction is broadcast within the Inner Shareable shareability domain.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

VSE, bit [8]

Virtual SError interrupt.

VSE	Meaning
0b0	This mechanism is not making a virtual SError interrupt pending.
0b1	A virtual SError interrupt is pending because of this mechanism.

The virtual SError interrupt is only enabled when the value of HCR_EL2.{TGE, AMO} is {0, 1}.

This field resets to an architecturally UNKNOWN value.

VI, bit [7]

Virtual IRQ Interrupt.

VI	Meaning
0b0	This mechanism is not making a virtual IRQ pending.
0b1	A virtual IRQ is pending because of this mechanism.

The virtual IRQ is enabled only when the value of HCR_EL2.{TGE, IMO} is {0, 1}.

This field resets to an architecturally UNKNOWN value.

VF, bit [6]

Virtual FIQ Interrupt.

VF	Meaning
0b0	This mechanism is not making a virtual FIQ pending.
0b1	A virtual FIQ is pending because of this mechanism.

The virtual FIQ is enabled only when the value of HCR_EL2.{TGE, FMO} is {0, 1}.

This field resets to an architecturally UNKNOWN value.

AMO, bit [5]

Physical SError interrupt routing.

AMO	Meaning
0b0	When executing at Exception levels below EL2, and EL2 is enabled in the current Security state: • Physical SError interrupts are not taken to EL2. • When the value of HCR_EL2.TGE is 0, if the PE is executing at EL2 using AArch64, physical SError interrupts are not taken unless they are routed to EL3 by the SCR_EL3.EA bit. • Virtual SError interrupts are disabled.
0b1	When executing at any Exception level, and EL2 is enabled in the current Security state: • Physical SError interrupts are taken to EL2, unless they are routed to EL3. • When the value of HCR_EL2.TGE is 0, then virtual SError interrupts are enabled.

If EL2 is enabled in the current Security state and the value of HCR_EL2.TGE is 1:

- Regardless of the value of the AMO bit physical asynchronous External aborts and SError interrupts target EL2 unless they are routed to EL3.
- When ARMv8.1-VHE is not implemented, or if HCR_EL2.E2H is 0, this field behaves as 1 for all purposes other than a direct read of the value of this bit.
- When ARMv8.1-VHE is implemented and HCR_EL2.E2H is 1, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

For more information, see 'Asynchronous exception routing' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1 (The AArch64 System Level Programmers' Model).

This field resets to an architecturally UNKNOWN value.

IMO, bit [4]

Physical IRQ Routing.

IMO	Meaning
0b0	When executing at Exception levels below EL2, and EL2 is enabled in the current Security state: • Physical IRQ interrupts are not taken to EL2. • When the value of HCR_EL2.TGE is 0, if the PE is executing at EL2 using AArch64, physical IRQ interrupts are not taken unless they are routed to EL3 by the SCR_EL3.IRQ bit. • Virtual IRQ interrupts are disabled.
0b1	When executing at any Exception level, and EL2 is enabled in the current Security state: • Physical IRQ interrupts are taken to EL2, unless they are routed to EL3. • When the value of HCR_EL2.TGE is 0, then Virtual IRQ interrupts are enabled.

If EL2 is enabled in the current Security state, and the value of HCR_EL2.TGE is 1:

- Regardless of the value of the IMO bit, physical IRQ Interrupts target EL2 unless they are routed to EL3.
- When ARMv8.1-VHE is not implemented, or if HCR_EL2.E2H is 0, this field behaves as 1 for all purposes other than a direct read of the value of this bit.
- When ARMv8.1-VHE is implemented and HCR_EL2.E2H is 1, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

For more information, see 'Asynchronous exception routing' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1.

This field resets to an architecturally UNKNOWN value.

FMO, bit [3]

Physical FIQ Routing.

FMO	Meaning
0b0	When executing at Exception levels below EL2, and EL2 is enabled in the current Security state: • Physical FIQ interrupts are not taken to EL2. • When the value of HCR_EL2.TGE is 0, if the PE is executing at EL2 using AArch64, physical FIQ interrupts are not taken unless they are routed to EL3 by the SCR_EL3.FIQ bit. • Virtual FIQ interrupts are disabled.
0b1	When executing at any Exception level, and EL2 is enabled in the current Security state: • Physical FIQ interrupts are taken to EL2, unless they are routed to EL3. • When HCR_EL2.TGE is 0, then Virtual FIQ interrupts are enabled.

If EL2 is enabled in the current Security state and the value of HCR_EL2.TGE is 1:

- Regardless of the value of the FMO bit, physical FIQ Interrupts target EL2 unless they are routed to EL3.
- When ARMv8.1-VHE is not implemented, or if HCR_EL2.E2H is 0, this field behaves as 1 for all purposes other than a direct read of the value of this bit.
- When ARMv8.1-VHE is implemented and HCR_EL2.E2H is 1, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

For more information, see 'Asynchronous exception routing' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1.

This field resets to an architecturally UNKNOWN value.

PTW, bit [2]

Protected Table Walk. In the EL1&0 translation regime, a translation table access made as part of a stage 1 translation table walk is subject to a stage 2 translation. The combining of the memory type attributes from the two stages of translation means the access might be made to a type of Device memory. If this occurs, then the value of this bit determines the behavior:

PTW	Meaning
0b0	The translation table walk occurs as if it is to Normal Non-cacheable memory. This means it can be made speculatively.
0b1	The memory access generates a stage 2 Permission fault.

This field is permitted to be cached in a TLB.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

SWIO, bit [1]

Set/Way Invalidation Override. Causes EL1 execution of the data cache invalidate by set/way instructions to perform a data cache clean and invalidate by set/way:

SWIO	Meaning
0b0	This control has no effect on the operation of data cache invalidate by set/way instructions.
0b1	Data cache invalidate by set/way instructions perform a data cache clean and invalidate by set/way.

When the value of this bit is 1:

AArch32: DCISW performs the same invalidation as a DCCISW instruction.

AArch64: DC ISW performs the same invalidation as a DC CISW instruction.

This bit can be implemented as RES1.

When HCR_EL2.TGE is 1, the PE ignores the value of this field for all purposes other than a direct read of this field.

This field resets to an architecturally UNKNOWN value.

VM, bit [0]

Virtualization enable. Enables stage 2 address translation for the EL1&0 translation regime, when EL2 is enabled in the current Security state.

VM	Meaning
0b0	EL1&0 stage 2 address translation disabled.
0b1	EL1&0 stage 2 address translation enabled.

When the value of this bit is 1, data cache invalidate instructions executed at EL1 perform a data cache clean and invalidate. For the invalidate by set/way instruction this behavior applies regardless of the value of the HCR_EL2.SWIO bit.

This bit is permitted to be cached in a TLB.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Accessing the HCR_EL2

Accesses to this register use the following encodings:

MRS <Xt>, HCR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b0001	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x078];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HCR_EL2;
elsif PSTATE.EL == EL3 then
    return HCR_EL2;
```

MSR HCR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0001	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x078] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HCR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    HCR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HDFGRTR_EL2, Hypervisor Debug Fine-Grained Read Trap Register

The HDFGRTR_EL2 characteristics are:

Purpose

Provides controls for traps of MRS and MRC reads of debug, trace, PMU, and Statistical Profiling System registers.

Configuration

This register is present only when ARMv8.6-FGT is implemented. Otherwise, direct accesses to HDFGRTR_EL2 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HDFGRTR_EL2 is a 64-bit register.

Field descriptions

The HDFGRTR_EL2 bit assignments are:

63	62	61	60	59	58	57
RES0					PMCEIDn_EL0~~PMUSERENR_EL0~~	PMUSERENR_EL0~~RE~~
PMSIRR_EL1	PMSIDR_EL1	PMSICR_EL1	PMSFCR_EL1	PMSEVFR_EL1	PMSCR_EL1	PMBSR_EL1
31	30	29	28	27	26	25

Bits [63:59~~58~~]

Reserved, RES0.

PMCEIDn_EL0, bit [58]

When PMUv3 is implemented:

Trap MRS reads of PMCEID<n>_EL0 at EL1 and EL0 using AArch64 and MRC reads of PMCEID<n> at EL0 using AArch32 when EL1 is using AArch64 to EL2.

PMCEIDn_EL0	Meaning
0b0	MRS reads of PMCEID<n>_EL0 at EL1 and EL0 using AArch64 and MRC reads of PMCEID<n> at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of PMCEID<n>_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of PMCEID<n> at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMUSERENR_EL0, bit [57]

When PMUv3 is implemented:

Trap MRS reads of PMUSERENR_EL0 at EL1 and EL0 using AArch64 and MRC reads of PMUSERENR at EL0 using AArch32 when EL1 is using AArch64 to EL2.

PMUSERENR_EL0	Meaning
0b0	MRS reads of PMUSERENR_EL0 at EL1 and EL0 using AArch64 and MRC reads of PMUSERENR at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of PMUSERENR_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of PMUSERENR at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

Bits [56:49]

Reserved, RES0.

TRCVICTLR, bit [48]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of TRCVICTLR at EL1 using AArch64 to EL2.

TRCVICTLR	Meaning
0b0	MRS reads of TRCVICTLR are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of TRCVICTLR at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCSTATR, bit [47]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of TRCSTATR at EL1 using AArch64 to EL2.

TRCSTATR	Meaning
0b0	MRS reads of TRCSTATR are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of TRCSTATR at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCSSCSRn, bit [46]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of TRCSSCSR<n> at EL1 using AArch64 to EL2.

TRCSSCSRn	Meaning
0b0	MRS reads of TRCSSCSR<n> are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of TRCSSCSR<n> at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

If Single-shot Comparator n is not implementented, a read of TRCSSCSR<n> is UNDEFINED.

This bit is RES0 if TRCSSCSR<n> are not implemented.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCSEQSTR, bit [45]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of TRCSEQSTR at EL1 using AArch64 to EL2.

TRCSEQSTR	Meaning
0b0	MRS reads of TRCSEQSTR are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of TRCSEQSTR at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

This bit is RES0 if TRCSEQSTR is not implemented.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCPRGCTLR, bit [44]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of TRCPRGCTLR at EL1 using AArch64 to EL2.

TRCPRGCTLR	Meaning
0b0	MRS reads of TRCPRGCTLR are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of TRCPRGCTLR at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCOSLSR, bit [43]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of TRCOSLSR at EL1 using AArch64 to EL2.

TRCOSLSR	Meaning
0b0	MRS reads of TRCOSLSR are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of TRCOSLSR at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

Bit [42]

Reserved, RES0.

TRCIMSPECn, bit [41]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of TRCIMSPEC<n> at EL1 using AArch64 to EL2.

TRCIMSPECn	Meaning
0b0	MRS reads of TRCIMSPEC<n> are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of TRCIMSPEC<n> at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

TRCIMSPEC<1-7> are optional. If TRCIMSPEC<n> is not implemented, a read of TRCIMSPEC<n> is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCID, bit [40]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of multiple System registers. Enables a trap on MRS reads at EL1 using AArch64 of any of the following AArch64 System registers to EL2:

- TRCDEVARCH.
- TRCDEVID.
- TRCIDR<n>.

TRCID	Meaning
0b0	MRS reads of the System registers listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads at EL1 using AArch64 of any of the System registers listed above are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

Bits [39:38]

Reserved, RES0.

TRCCNTVRn, bit [37]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of TRCCNTVR<n> at EL1 using AArch64 to EL2.

TRCCNTVRn	Meaning
0b0	MRS reads of TRCCNTVR<n> are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of TRCCNTVR<n> at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

If Counter n is not implemented, a read of TRCCNTVR<n> is UNDEFINED.

This bit is RES0 if TRCCNTVR<n> are not implemented.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCCLAIM, bit [36]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of multiple System registers. Enables a trap on MRS reads at EL1 using AArch64 of any of the following AArch64 System registers to EL2:

- TRCCLAIMCLR.
- TRCCLAIMSET.

TRCCLAIM	Meaning
0b0	MRS reads of the System registers listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads at EL1 using AArch64 of any of the System registers listed above are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCAUXCTLR, bit [35]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of TRCAUXCTLR at EL1 using AArch64 to EL2.

TRCAUXCTLR	Meaning
0b0	MRS reads of TRCAUXCTLR are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of TRCAUXCTLR at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCAUTHSTATUS, bit [34]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of TRCAUTHSTATUS at EL1 using AArch64 to EL2.

TRCAUTHSTATUS	Meaning
0b0	MRS reads of TRCAUTHSTATUS are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of TRCAUTHSTATUS at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRC, bit [33]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MRS reads of multiple System registers. Enables a trap on MRS reads at EL1 using AArch64 of any of the following AArch64 System registers to EL2:

- TRCACATR<n>.
- TRCACVR<n>.
- TRCBBCTLR.
- TRCCCCTLR.
- TRCCIDCCTLR<n>.
- TRCCIDCVR<n>.
- TRCCNTCTLR<n>.
- TRCCNTRLDVR<n>.
- TRCCONFIGR.
- TRCEVENTCTL0R.
- TRCEVENTCTL1R.
- TRCEXTINSELR.
- TRCQCTLR.
- TRCRSCTLR<n>.
- TRCSEQEVR<n>.
- TRCSEQRSTEVR.
- TRCSSCCR<n>.
- TRCSSPCICR<n>.
- TRCSTALLCTLR.
- TRCSYNCPR.
- TRCTRACEIDR.
- TRCTSCTLR.
- TRCVIIECTLR.
- TRCVIPCSSCTLR.
- TRCVISSCTLR.
- TRCVMIDCCTLR<n>.
- TRCVMIDCVR<n>.

TRC	Meaning
0b0	MRS reads of the System registers listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads at EL1 using AArch64 of any of the System registers listed above are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

A read of an unimplemented register is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSLATFR_EL1, bit [32]

When SPE is implemented:

Trap MRS reads of PMSLATFR_EL1 at EL1 using AArch64 to EL2.

PMSLATFR_EL1	Meaning
0b0	MRS reads of PMSLATFR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of PMSLATFR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSIRR_EL1, bit [31]

When SPE is implemented:

Trap MRS reads of PMSIRR_EL1 at EL1 using AArch64 to EL2.

PMSIRR_EL1	Meaning
0b0	MRS reads of PMSIRR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of PMSIRR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSIDR_EL1, bit [30]

When SPE is implemented:

Trap MRS reads of PMSIDR_EL1 at EL1 using AArch64 to EL2.

PMSIDR_EL1	Meaning
0b0	MRS reads of PMSIDR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of PMSIDR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSICR_EL1, bit [29]

When SPE is implemented:

Trap MRS reads of PMSICR_EL1 at EL1 using AArch64 to EL2.

PMSICR_EL1	Meaning
0b0	MRS reads of PMSICR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of PMSICR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSFCR_EL1, bit [28]

When SPE is implemented:

Trap MRS reads of PMSFCR_EL1 at EL1 using AArch64 to EL2.

PMSFCR_EL1	Meaning
0b0	MRS reads of PMSFCR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of PMSFCR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSEVFR_EL1, bit [27]

When SPE is implemented:

Trap MRS reads of PMSEVFR_EL1 at EL1 using AArch64 to EL2.

PMSEVFR_EL1	Meaning
0b0	MRS reads of PMSEVFR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of PMSEVFR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSCR_EL1, bit [26]

When SPE is implemented:

Trap MRS reads of PMSCR_EL1 at EL1 using AArch64 to EL2.

PMSCR_EL1	Meaning
0b0	MRS reads of PMSCR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of PMSCR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMBSR_EL1, bit [25]

When SPE is implemented:

Trap MRS reads of PMBSR_EL1 at EL1 using AArch64 to EL2.

PMBSR_EL1	Meaning
0b0	MRS reads of PMBSR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of PMBSR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMBPTR_EL1, bit [24]

When SPE is implemented:

Trap MRS reads of PMBPTR_EL1 at EL1 using AArch64 to EL2.

PMBPTR_EL1	Meaning
0b0	MRS reads of PMBPTR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of PMBPTR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMBLIMITR_EL1, bit [23]

When SPE is implemented:

Trap MRS reads of PMBLIMITR_EL1 at EL1 using AArch64 to EL2.

PMBLIMITR_EL1	Meaning
0b0	MRS reads of PMBLIMITR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of PMBLIMITR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMMIR_EL1, bit [22]

When PMUv3 is implemented:

Trap MRS reads of PMMIR_EL1 at EL1 using AArch64 to EL2.

PMMIR_EL1	Meaning
0b0	MRS reads of PMMIR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of PMMIR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

Bits [21:20]

Reserved, RES0.

PMSELR_EL0, bit [19]

When PMUv3 is implemented:

Trap MRS reads of PMSELR_EL0 at EL1 and EL0 using AArch64 and MRC reads of PMSELR at EL0 using AArch32 when EL1 is using AArch64 to EL2.

PMSELR_EL0	Meaning
0b0	MRS reads of PMSELR_EL0 at EL1 and EL0 using AArch64 and MRC reads of PMSELR at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of PMSELR_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of PMSELR at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMOVS, bit [18]

When PMUv3 is implemented:

Trap MRS reads and MRC reads of multiple System registers.

Enables a trap to EL2 the following operations:

- At EL1 and EL0 using AArch64: MRS reads of PMOVSCLR_EL0 and PMOVSSET_EL0.
- At EL0 using Arch32 when EL1 is using AArch64: MRC reads of PMOVSR and PMOVSSET.

PMOVS	Meaning
0b0	The operations listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads at EL1 and EL0 using AArch64 of PMOVSCLR_EL0 and PMOVSSET_EL0 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads at EL0 using AArch32 of PMOVSR and PMOVSSET are trapped to EL2 and reported with EC syndrome value 0x03, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMINTEN, bit [17]

When PMUv3 is implemented:

Trap MRS reads of multiple System registers. Enables a trap on MRS reads at EL1 using AArch64 of any of the following AArch64 System registers to EL2:

- PMINTENCLR_EL1.
- PMINTENSET_EL1.

PMINTEN	Meaning
0b0	MRS reads of the System registers listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads at EL1 using AArch64 of any of the System registers listed above are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMCNTEN, bit [16]

When PMUv3 is implemented:

Trap MRS reads and MRC reads of multiple System registers.

Enables a trap to EL2 the following operations:

- At EL1 and EL0 using AArch64: MRS reads of PMCNTENCLR_EL0 and PMCNTENSET_EL0.
- At EL0 using Arch32 when EL1 is using AArch64: MRC reads of PMCNTENCLR and PMCNTENSET.

PMCNTEN	Meaning
0b0	The operations listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads at EL1 and EL0 using AArch64 of PMCNTENCLR_EL0 and PMCNTENSET_EL0 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads at EL0 using AArch32 of PMCNTENCLR and PMCNTENSET are trapped to EL2 and reported with EC syndrome value 0x03, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMCCNTR_EL0, bit [15]

When PMUv3 is implemented:

Trap MRS reads of PMCCNTR_EL0 at EL1 and EL0 using AArch64 and MRC and MRRC reads of PMCCNTR at EL0 using AArch32 when EL1 is using AArch64 to EL2.

PMCCNTR_EL0	Meaning
0b0	MRS reads of PMCCNTR_EL0 at EL1 and EL0 using AArch64 and MRC and MRRC reads of PMCCNTR at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of PMCCNTR_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC and MRRC reads of PMCCNTR at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03 (for MRC) or 0x04 (for MRRC).

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMCCFILTR_EL0, bit [14]

When PMUv3 is implemented:

Trap MRS reads of PMCCFILTR_EL0 at EL1 and EL0 using AArch64 and MRC reads of PMCCFILTR at EL0 using AArch32 when EL1 is using AArch64 to EL2.

PMCCFILTR_EL0	Meaning
0b0	MRS reads of PMCCFILTR_EL0 at EL1 and EL0 using AArch64 and MRC reads of PMCCFILTR at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads of PMCCFILTR_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads of PMCCFILTR at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

PMCCFILTR_EL0 can also be accessed in AArch64 state using PMXEVTYPER_EL0 when PMSELR_EL0.SEL == 31, and PMCCFILTR can also be accessed in AArch32 state using PMXEVTYPER when PMSELR.SEL == 31.

Setting this bit to 1 has no effect on accesses to PMXEVTYPER_EL0 and PMXEVTYPER, regardless of the value of PMSELR_EL0.SEL or PMSELR.SEL.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMEVTYPERn_EL0, bit [13]

When PMUv3 is implemented:

Trap MRS reads and MRC reads of multiple System registers.

Enables a trap to EL2 the following operations:

- At EL1 and EL0 using AArch64: MRS reads of PMEVTYPER<n>_EL0 and PMXEVTYPER_EL0.
- At EL0 using Arch32 when EL1 is using AArch64: MRC reads of PMEVTYPER<n> and PMXEVTYPER.

PMEVTYPERn_EL0	Meaning
0b0	The operations listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads at EL1 and EL0 using AArch64 of PMEVTYPER<n>_EL0 and PMXEVTYPER_EL0 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads at EL0 using AArch32 of PMEVTYPER<n> and PMXEVTYPER are trapped to EL2 and reported with EC syndrome value 0x03, unless the read generates a higher priority exception.

WhenIf ARMv8.6-FGT is implemented, ~~EL2 is implemented and enabled in the current Security state,~~ then, regardless of the value of this bit, for each value n ~~in the range UInt(MDCR_EL2.HPMN) to 30~~:

- If event counter n is not implemented, the following accesses are UNDEFINED:
  - In AArch64 state, a read of PMEVTYPER<n>_EL0, or, if n is not 31, a read of PMXEVTYPER_EL0 when PMSELR_EL0.SEL == n.
  - In AArch32 state, a read of PMEVTYPER<n>, or, if n is not 31, a read of PMXEVTYPER when PMSELR.SEL == n.
- If event counter n is implemented and EL2 is implemented and enabled in the current Security state, the following generate a Trap exception to EL2 from EL0 or EL1:
  - InAt ~~EL0 or EL1 using~~ AArch64 state, a read of PMEVTYPER<n>_EL0, or a read of PMXEVTYPER_EL0 when PMSELR_EL0.SEL == n, reported with EC syndrome value 0x18.
  - InAt ~~EL0 using~~ AArch32 state, a read of PMEVTYPER<n>, or a read of PMXEVTYPER when PMSELR.SEL == n, reported with EC syndrome value 0x03.

See also HDFGRTR_EL2.PMCCFILTR_EL0.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMEVCNTRn_EL0, bit [12]

When PMUv3 is implemented:

Trap MRS reads and MRC reads of multiple System registers.

Enables a trap to EL2 the following operations:

- At EL1 and EL0 using AArch64: MRS reads of PMEVCNTR<n>_EL0 and PMXEVCNTR_EL0.
- At EL0 using Arch32 when EL1 is using AArch64: MRC reads of PMEVCNTR<n> and PMXEVCNTR.

PMEVCNTRn_EL0	Meaning
0b0	The operations listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the read generates a higher priority exception: • MRS reads at EL1 and EL0 using AArch64 of PMEVCNTR<n>_EL0 and PMXEVCNTR_EL0 are trapped to EL2 and reported with EC syndrome value 0x18. • MRC reads at EL0 using AArch32 of PMEVCNTR<n> and PMXEVCNTR are trapped to EL2 and reported with EC syndrome value 0x03, unless the read generates a higher priority exception.

WhenIf ARMv8.6-FGT is implemented, ~~EL2 is implemented and enabled in the current Security state,~~ then, regardless of the value of this bit, for each value n ~~in the range UInt(MDCR_EL2.HPMN) to 30~~:

- If event counter n is not implemented, the following accesses are UNDEFINED:
  - In AArch64 state, a read of PMEVCNTR<n>_EL0, or a read of PMXEVCNTR_EL0 when PMSELR_EL0.SEL == n.
  - In AArch32 state, a read of PMEVCNTR<n> , or a read of PMXEVCNTR when PMSELR.SEL == n.
- If event counter n is implemented, and EL2 is implemented and enabled in the current Security state, the following generate a Trap exception to EL2 from EL0 or EL1:
  - InAt ~~EL0 or EL1 using~~ AArch64 state, a read of PMEVCNTR<n>_EL0, or a read of PMXEVCNTR_EL0 when PMSELR_EL0.SEL == n, reported with EC syndrome value 0x18.
  - InAt ~~EL0 using~~ AArch32 state, a read of PMEVCNTR<n>, or a read of PMXEVCNTR when PMSELR.SEL == n, reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

OSDLR_EL1, bit [11]

When ARMv8.0-DoubleLock is implemented:

Trap MRS reads of OSDLR_EL1 at EL1 using AArch64 to EL2.

OSDLR_EL1	Meaning
0b0	MRS reads of OSDLR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of OSDLR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

OSECCR_EL1, bit [10]

Trap MRS reads of OSECCR_EL1 at EL1 using AArch64 to EL2.

OSECCR_EL1	Meaning
0b0	MRS reads of OSECCR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of OSECCR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

OSLSR_EL1, bit [9]

Trap MRS reads of OSLSR_EL1 at EL1 using AArch64 to EL2.

OSLSR_EL1	Meaning
0b0	MRS reads of OSLSR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of OSLSR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Bit [8]

Reserved, RES0.

DBGPRCR_EL1, bit [7]

Trap MRS reads of DBGPRCR_EL1 at EL1 using AArch64 to EL2.

DBGPRCR_EL1	Meaning
0b0	MRS reads of DBGPRCR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of DBGPRCR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

DBGAUTHSTATUS_EL1, bit [6]

Trap MRS reads of DBGAUTHSTATUS_EL1 at EL1 using AArch64 to EL2.

DBGAUTHSTATUS_EL1	Meaning
0b0	MRS reads of DBGAUTHSTATUS_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of DBGAUTHSTATUS_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

DBGCLAIM, bit [5]

Trap MRS reads of multiple System registers. Enables a trap on MRS reads at EL1 using AArch64 of any of the following AArch64 System registers to EL2:

- DBGCLAIMCLR_EL1.
- DBGCLAIMSET_EL1.

DBGCLAIM	Meaning
0b0	MRS reads of the System registers listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads at EL1 using AArch64 of any of the System registers listed above are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

MDSCR_EL1, bit [4]

Trap MRS reads of MDSCR_EL1 at EL1 using AArch64 to EL2.

MDSCR_EL1	Meaning
0b0	MRS reads of MDSCR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of MDSCR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

DBGWVRn_EL1, bit [3]

Trap MRS reads of DBGWVR<n>_EL1 at EL1 using AArch64 to EL2.

DBGWVRn_EL1	Meaning
0b0	MRS reads of DBGWVR<n>_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of DBGWVR<n>_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

If watchpoint n is not implemented, a read of DBGWVR<n>_EL1 is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

DBGWCRn_EL1, bit [2]

Trap MRS reads of DBGWCR<n>_EL1 at EL1 using AArch64 to EL2.

DBGWCRn_EL1	Meaning
0b0	MRS reads of DBGWCR<n>_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of DBGWCR<n>_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

If watchpoint n is not implemented, a read of DBGWCR<n>_EL1 is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

DBGBVRn_EL1, bit [1]

Trap MRS reads of DBGBVR<n>_EL1 at EL1 using AArch64 to EL2.

DBGBVRn_EL1	Meaning
0b0	MRS reads of DBGBVR<n>_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of DBGBVR<n>_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

If breakpoint n is not implemented, a read of DBGBVR<n>_EL1 is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

DBGBCRn_EL1, bit [0]

Trap MRS reads of DBGBCR<n>_EL1 at EL1 using AArch64 to EL2.

DBGBCRn_EL1	Meaning
0b0	MRS reads of DBGBCR<n>_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MRS reads of DBGBCR<n>_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the read generates a higher priority exception.

If breakpoint n is not implemented, a read of DBGBCR<n>_EL1 is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

Accessing the HDFGRTR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, HDFGRTR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0011	0b0001	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x1D0];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FGTEn == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return HDFGRTR_EL2;
elsif PSTATE.EL == EL3 then
    return HDFGRTR_EL2;
```

MSR HDFGRTR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0011	0b0001	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x1D0] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FGTEn == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        HDFGRTR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    HDFGRTR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HDFGWTR_EL2, Hypervisor Debug Fine-Grained Write Trap Register

The HDFGWTR_EL2 characteristics are:

Purpose

Provides controls for traps of MSR and MCR writes of debug, trace, PMU, and Statistical Profiling System registers.

Configuration

This register is present only when ARMv8.6-FGT is implemented. Otherwise, direct accesses to HDFGWTR_EL2 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HDFGWTR_EL2 is a 64-bit register.

Field descriptions

The HDFGWTR_EL2 bit assignments are:



Bits [63:58]

Reserved, RES0.

PMUSERENR_EL0, bit [57]

When PMUv3 is implemented:

Trap MSR writes of PMUSERENR_EL0 at EL1 using AArch64 to EL2.

PMUSERENR_EL0	Meaning
0b0	MSR writes of PMUSERENR_EL0 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of PMUSERENR_EL0 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

Bits [56:50]

Reserved, RES0.

TRFCR_EL1, bit [49]

When ARMv8.4-Trace is implemented:

Trap MSR writes of TRFCR_EL1 at EL1 using AArch64 to EL2.

TRFCR_EL1	Meaning
0b0	MSR writes of TRFCR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of TRFCR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCVICTLR, bit [48]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MSR writes of TRCVICTLR at EL1 using AArch64 to EL2.

TRCVICTLR	Meaning
0b0	MSR writes of TRCVICTLR are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of TRCVICTLR at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

Bit [47]

Reserved, RES0.

TRCSSCSRn, bit [46]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MSR writes of TRCSSCSR<n> at EL1 using AArch64 to EL2.

TRCSSCSRn	Meaning
0b0	MSR writes of TRCSSCSR<n> are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of TRCSSCSR<n> at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

If Single-shot Comparator n is not implementented, a write of TRCSSCSR<n> is UNDEFINED.

This bit is RES0 if TRCSSCSR<n> are not implemented.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCSEQSTR, bit [45]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MSR writes of TRCSEQSTR at EL1 using AArch64 to EL2.

TRCSEQSTR	Meaning
0b0	MSR writes of TRCSEQSTR are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of TRCSEQSTR at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

This bit is RES0 if TRCSEQSTR is not implemented.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCPRGCTLR, bit [44]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MSR writes of TRCPRGCTLR at EL1 using AArch64 to EL2.

TRCPRGCTLR	Meaning
0b0	MSR writes of TRCPRGCTLR are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of TRCPRGCTLR at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

Bit [43]

Reserved, RES0.

TRCOSLAR, bit [42]

When the Trace Extension is implemented, System register access to the PE Trace Unit registers is implemented and ETMv4 is implemented:

Trap MSR writes of TRCOSLAR at EL1 using AArch64 to EL2.

TRCOSLAR	Meaning
0b0	MSR writes of TRCOSLAR are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of TRCOSLAR at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCIMSPECn, bit [41]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MSR writes of TRCIMSPEC<n> at EL1 using AArch64 to EL2.

TRCIMSPECn	Meaning
0b0	MSR writes of TRCIMSPEC<n> are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of TRCIMSPEC<n> at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

TRCIMSPEC<1-7> are optional. If TRCIMSPEC<n> is not implemented, a write of TRCIMSPEC<n> is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

~~Trap MSR writes of multiple System registers. Enables a trap on MSR writes at EL1 using AArch64 of any of the following AArch64 System registers to EL2:~~

- ~~TRCDEVARCH.~~
- ~~TRCDEVID.~~
- ~~TRCIDR<n>.~~

~~TRCID~~	~~Meaning~~
~~0b0~~	~~MSR writes of the System registers listed above are not affected by this bit.~~
~~0b1~~	~~If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes at EL1 using AArch64 of any of the System registers listed above are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.~~

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

BitsTRCID, bit [40:38]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Reserved, RES0.

Bits [39:38]

Reserved, RES0.

TRCCNTVRn, bit [37]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MSR writes of TRCCNTVR<n> at EL1 using AArch64 to EL2.

TRCCNTVRn	Meaning
0b0	MSR writes of TRCCNTVR<n> are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of TRCCNTVR<n> at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

If Counter n is not implemented, a write of TRCCNTVR<n> is UNDEFINED.

This bit is RES0 if TRCCNTVR<n> are not implemented.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCCLAIM, bit [36]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MSR writes of multiple System registers. Enables a trap on MSR writes at EL1 using AArch64 of any of the following AArch64 System registers to EL2:

- TRCCLAIMCLR.
- TRCCLAIMSET.

TRCCLAIM	Meaning
0b0	MSR writes of the System registers listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes at EL1 using AArch64 of any of the System registers listed above are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

TRCAUXCTLR, bit [35]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MSR writes of TRCAUXCTLR at EL1 using AArch64 to EL2.

TRCAUXCTLR	Meaning
0b0	MSR writes of TRCAUXCTLR are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of TRCAUXCTLR at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

Bit [34]

Reserved, RES0.

TRC, bit [33]

When the Trace Extension is implemented and System register access to the PE Trace Unit registers is implemented:

Trap MSR writes of multiple System registers. Enables a trap on MSR writes at EL1 using AArch64 of any of the following AArch64 System registers to EL2:

- TRCACATR<n>.
- TRCACVR<n>.
- TRCBBCTLR.
- TRCCCCTLR.
- TRCCIDCCTLR<n>.
- TRCCIDCVR<n>.
- TRCCNTCTLR<n>.
- TRCCNTRLDVR<n>.
- TRCCONFIGR.
- TRCEVENTCTL0R.
- TRCEVENTCTL1R.
- TRCEXTINSELR, if ETMv4 is implemented.
- TRCRSCTLR<n>.
- TRCSEQEVR<n>.
- TRCSEQRSTEVR.
- TRCSSCCR<n>.
- TRCSSPCICR<n>.
- TRCSTALLCTLR.
- TRCSYNCPR.
- TRCTRACEIDR.
- TRCTSCTLR.
- TRCVIIECTLR.
- TRCVIPCSSCTLR.
- TRCVISSCTLR.
- TRCVMIDCCTLR<n>.
- TRCVMIDCVR<n>.

TRC	Meaning
0b0	MSR writes of the System registers listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes at EL1 using AArch64 of any of the System registers listed above are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

A write of an unimplemented register is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSLATFR_EL1, bit [32]

When SPE is implemented:

Trap MSR writes of PMSLATFR_EL1 at EL1 using AArch64 to EL2.

PMSLATFR_EL1	Meaning
0b0	MSR writes of PMSLATFR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of PMSLATFR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSIRR_EL1, bit [31]

When SPE is implemented:

Trap MSR writes of PMSIRR_EL1 at EL1 using AArch64 to EL2.

PMSIRR_EL1	Meaning
0b0	MSR writes of PMSIRR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of PMSIRR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

Bit [30]

Reserved, RES0.

PMSICR_EL1, bit [29]

When SPE is implemented:

Trap MSR writes of PMSICR_EL1 at EL1 using AArch64 to EL2.

PMSICR_EL1	Meaning
0b0	MSR writes of PMSICR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of PMSICR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSFCR_EL1, bit [28]

When SPE is implemented:

Trap MSR writes of PMSFCR_EL1 at EL1 using AArch64 to EL2.

PMSFCR_EL1	Meaning
0b0	MSR writes of PMSFCR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of PMSFCR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSEVFR_EL1, bit [27]

When SPE is implemented:

Trap MSR writes of PMSEVFR_EL1 at EL1 using AArch64 to EL2.

PMSEVFR_EL1	Meaning
0b0	MSR writes of PMSEVFR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of PMSEVFR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSCR_EL1, bit [26]

When SPE is implemented:

Trap MSR writes of PMSCR_EL1 at EL1 using AArch64 to EL2.

PMSCR_EL1	Meaning
0b0	MSR writes of PMSCR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of PMSCR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMBSR_EL1, bit [25]

When SPE is implemented:

Trap MSR writes of PMBSR_EL1 at EL1 using AArch64 to EL2.

PMBSR_EL1	Meaning
0b0	MSR writes of PMBSR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of PMBSR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMBPTR_EL1, bit [24]

When SPE is implemented:

Trap MSR writes of PMBPTR_EL1 at EL1 using AArch64 to EL2.

PMBPTR_EL1	Meaning
0b0	MSR writes of PMBPTR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of PMBPTR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMBLIMITR_EL1, bit [23]

When SPE is implemented:

Trap MSR writes of PMBLIMITR_EL1 at EL1 using AArch64 to EL2.

PMBLIMITR_EL1	Meaning
0b0	MSR writes of PMBLIMITR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of PMBLIMITR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

Bit [22]

Reserved, RES0.

PMCR_EL0, bit [21]

When PMUv3 is implemented:

Trap MSR writes of PMCR_EL0 at EL1 and EL0 using AArch64 and MCR writes of PMCR at EL0 using AArch32 when EL1 is using AArch64 to EL2.

PMCR_EL0	Meaning
0b0	MSR writes of PMCR_EL0 at EL1 and EL0 using AArch64 and MCR writes of PMCR at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the write generates a higher priority exception: • MSR writes of PMCR_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MCR writes of PMCR at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSWINC_EL0, bit [20]

When PMUv3 is implemented:

Trap MSR writes of PMSWINC_EL0 at EL1 and EL0 using AArch64 and MCR writes of PMSWINC at EL0 using AArch32 when EL1 is using AArch64 to EL2.

PMSWINC_EL0	Meaning
0b0	MSR writes of PMSWINC_EL0 at EL1 and EL0 using AArch64 and MCR writes of PMSWINC at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the write generates a higher priority exception: • MSR writes of PMSWINC_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MCR writes of PMSWINC at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMSELR_EL0, bit [19]

When PMUv3 is implemented:

Trap MSR writes of PMSELR_EL0 at EL1 and EL0 using AArch64 and MCR writes of PMSELR at EL0 using AArch32 when EL1 is using AArch64 to EL2.

PMSELR_EL0	Meaning
0b0	MSR writes of PMSELR_EL0 at EL1 and EL0 using AArch64 and MCR writes of PMSELR at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the write generates a higher priority exception: • MSR writes of PMSELR_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MCR writes of PMSELR at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMOVS, bit [18]

When PMUv3 is implemented:

Trap MSR writes and MCR writes of multiple System registers.

Enables a trap to EL2 the following operations:

- At EL1 and EL0 using AArch64: MSR writes of PMOVSCLR_EL0 and PMOVSSET_EL0.
- At EL0 using Arch32 when EL1 is using AArch64: MCR writes of PMOVSR and PMOVSSET.

PMOVS	Meaning
0b0	The operations listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the write generates a higher priority exception: • MSR writes at EL1 and EL0 using AArch64 of PMOVSCLR_EL0 and PMOVSSET_EL0 are trapped to EL2 and reported with EC syndrome value 0x18. • MCR writes at EL0 using AArch32 of PMOVSR and PMOVSSET are trapped to EL2 and reported with EC syndrome value 0x03, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMINTEN, bit [17]

When PMUv3 is implemented:

Trap MSR writes of multiple System registers. Enables a trap on MSR writes at EL1 using AArch64 of any of the following AArch64 System registers to EL2:

- PMINTENCLR_EL1.
- PMINTENSET_EL1.

PMINTEN	Meaning
0b0	MSR writes of the System registers listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes at EL1 using AArch64 of any of the System registers listed above are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMCNTEN, bit [16]

When PMUv3 is implemented:

Trap MSR writes and MCR writes of multiple System registers.

Enables a trap to EL2 the following operations:

- At EL1 and EL0 using AArch64: MSR writes of PMCNTENCLR_EL0 and PMCNTENSET_EL0.
- At EL0 using Arch32 when EL1 is using AArch64: MCR writes of PMCNTENCLR and PMCNTENSET.

PMCNTEN	Meaning
0b0	The operations listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the write generates a higher priority exception: • MSR writes at EL1 and EL0 using AArch64 of PMCNTENCLR_EL0 and PMCNTENSET_EL0 are trapped to EL2 and reported with EC syndrome value 0x18. • MCR writes at EL0 using AArch32 of PMCNTENCLR and PMCNTENSET are trapped to EL2 and reported with EC syndrome value 0x03, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMCCNTR_EL0, bit [15]

When PMUv3 is implemented:

Trap MSR writes of PMCCNTR_EL0 at EL1 and EL0 using AArch64 and MCR and MCRR writes of PMCCNTR at EL0 using AArch32 when EL1 is using AArch64 to EL2.

PMCCNTR_EL0	Meaning
0b0	MSR writes of PMCCNTR_EL0 at EL1 and EL0 using AArch64 and MCR and MCRR writes of PMCCNTR at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the write generates a higher priority exception: • MSR writes of PMCCNTR_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MCR and MCRR writes of PMCCNTR at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03 (for MCR) or 0x04 (for MCRR).

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMCCFILTR_EL0, bit [14]

When PMUv3 is implemented:

Trap MSR writes of PMCCFILTR_EL0 at EL1 and EL0 using AArch64 and MCR writes of PMCCFILTR at EL0 using AArch32 when EL1 is using AArch64 to EL2.

PMCCFILTR_EL0	Meaning
0b0	MSR writes of PMCCFILTR_EL0 at EL1 and EL0 using AArch64 and MCR writes of PMCCFILTR at EL0 using AArch32 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the write generates a higher priority exception: • MSR writes of PMCCFILTR_EL0 at EL1 and EL0 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18. • MCR writes of PMCCFILTR at EL0 using AArch32 are trapped to EL2 and reported with EC syndrome value 0x03.

PMCCFILTR_EL0 can also be accessed in AArch64 state using PMXEVTYPER_EL0 when PMSELR_EL0.SEL == 31, and PMCCFILTR can also be accessed in AArch32 state using PMXEVTYPER when PMSELR.SEL == 31.

Setting this bit to 1 has no effect on accesses to PMXEVTYPER_EL0 and PMXEVTYPER, regardless of the value of PMSELR_EL0.SEL or PMSELR.SEL.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

PMEVTYPERn_EL0, bit [13]

When PMUv3 is implemented:

Trap MSR writes and MCR writes of multiple System registers.

Enables a trap to EL2 the following operations:

- At EL1 and EL0 using AArch64: MSR writes of PMEVTYPER<n>_EL0 and PMXEVTYPER_EL0.
- At EL0 using Arch32 when EL1 is using AArch64: MCR writes of PMEVTYPER<n> and PMXEVTYPER.

PMEVTYPERn_EL0	Meaning
0b0	The operations listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the write generates a higher priority exception: • MSR writes at EL1 and EL0 using AArch64 of PMEVTYPER<n>_EL0 and PMXEVTYPER_EL0 are trapped to EL2 and reported with EC syndrome value 0x18. • MCR writes at EL0 using AArch32 of PMEVTYPER<n> and PMXEVTYPER are trapped to EL2 and reported with EC syndrome value 0x03, unless the write generates a higher priority exception.

WhenIf ARMv8.6-FGT is implemented, ~~EL2 is implemented and enabled in the current Security state,~~ then, regardless of the value of this bit, for each value n ~~in the range UInt(MDCR_EL2.HPMN) to 30~~:

- If event counter n is not implemented, the following accesses are UNDEFINED:
  - In AArch64 state, a write of PMEVTYPER<n>_EL0, or, if n is not 31, a write of PMXEVTYPER_EL0 when PMSELR_EL0.SEL == n.

    - In AArch32 state, a write of PMEVTYPER<n>, or, if n is not 31, a write of PMXEVTYPER when PMSELR.SEL == n.

- If event counter n is implemented and EL2 is implemented and enabled in the current Security state, the following generate a Trap exception to EL2 from EL0 or EL1:

    - InAt ~~EL0 or EL1 using~~ AArch64 state, a write of PMEVTYPER<n>_EL0, or a write of PMXEVTYPER_EL0 when PMSELR_EL0.SEL == n, reported with EC syndrome value `0x18`.

    - InAt ~~EL0 using~~ AArch32 state, a write of PMEVTYPER<n>, or a write of PMXEVTYPER when PMSELR.SEL == n, reported with EC syndrome value `0x03`.

See also HDFGWTR_EL2.PMCCFILTR_EL0.

In a system where the PE resets into EL2, this field resets to `0`.

Otherwise:

Reserved, RES0.

PMEVCNTRn_EL0, bit [12]

When PMUv3 is implemented:

Trap `MSR` writes and `MCR` writes of multiple System registers.

Enables a trap to EL2 the following operations:

- At EL1 and EL0 using AArch64: `MSR` writes of PMEVCNTR<n>_EL0 and PMXEVCNTR_EL0.
- At EL0 using Arch32 when EL1 is using AArch64: `MCR` writes of PMEVCNTR<n> and PMXEVCNTR.

PMEVCNTRn_EL0	Meaning
`0b0`	The operations listed above are not affected by this bit.
`0b1`	If EL2 is implemented and enabled in the current Security state, HCR_EL2.{E2H,TGE} != {1,1}, EL1 is using AArch64, and either EL3 is not implemented or SCR_EL3.FGTEn == 1, then, unless the write generates a higher priority exception: • `MSR` writes at EL1 and EL0 using AArch64 of PMEVCNTR<n>_EL0 and PMXEVCNTR_EL0 are trapped to EL2 and reported with EC syndrome value `0x18`. • `MCR` writes at EL0 using AArch32 of PMEVCNTR<n> and PMXEVCNTR are trapped to EL2 and reported with EC syndrome value `0x03`, unless the write generates a higher priority exception.

WhenIf ARMv8.6-FGT is implemented, ~~EL2 is implemented and enabled in the current Security state,~~ then, regardless of the value of this bit, for each value n ~~in the range UInt(MDCR_EL2.HPMN) to 30~~:

- If event counter n is not implemented, the following accesses are UNDEFINED:

    - In AArch64 state, a write of PMEVCNTR<n>_EL0, or a write of PMXEVCNTR_EL0 when PMSELR_EL0.SEL == n.

    - In AArch32 state, a write of PMEVCNTR<n> , or a write of PMXEVCNTR when PMSELR.SEL == n.

- If event counter n is implemented, and EL2 is implemented and enabled in the current Security state, the following generate a Trap exception to EL2 from EL0 or EL1:

    - InAt ~~EL0 or EL1 using~~ AArch64 state, a write of PMEVCNTR<n>_EL0, or a write of PMXEVCNTR_EL0 when PMSELR_EL0.SEL == n, reported with EC syndrome value `0x18`.

- InAt EL0 using AArch32 state, a write of PMEVCNTR<n>, or a write of PMXEVCNTR when PMSELR.SEL == n, reported with EC syndrome value 0x03.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

OSDLR_EL1, bit [11]

When ARMv8.0-DoubleLock is implemented:

Trap MSR writes of OSDLR_EL1 at EL1 using AArch64 to EL2.

OSDLR_EL1	Meaning
0b0	MSR writes of OSDLR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of OSDLR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Otherwise:

Reserved, RES0.

OSECCR_EL1, bit [10]

Trap MSR writes of OSECCR_EL1 at EL1 using AArch64 to EL2.

OSECCR_EL1	Meaning
0b0	MSR writes of OSECCR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of OSECCR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Bit [9]

Reserved, RES0.

OSLAR_EL1, bit [8]

Trap MSR writes of OSLAR_EL1 at EL1 using AArch64 to EL2.

OSLAR_EL1	Meaning
0b0	MSR writes of OSLAR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of OSLAR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

DBGPRCR_EL1, bit [7]

Trap MSR writes of DBGPRCR_EL1 at EL1 using AArch64 to EL2.

DBGPRCR_EL1	Meaning
0b0	MSR writes of DBGPRCR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of DBGPRCR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

Bit [6]

Reserved, RES0.

DBGCLAIM, bit [5]

Trap MSR writes of multiple System registers. Enables a trap on MSR writes at EL1 using AArch64 of any of the following AArch64 System registers to EL2:

- DBGCLAIMCLR_EL1.
- DBGCLAIMSET_EL1.

DBGCLAIM	Meaning
0b0	MSR writes of the System registers listed above are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes at EL1 using AArch64 of any of the System registers listed above are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

MDSCR_EL1, bit [4]

Trap MSR writes of MDSCR_EL1 at EL1 using AArch64 to EL2.

MDSCR_EL1	Meaning
0b0	MSR writes of MDSCR_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of MDSCR_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

In a system where the PE resets into EL2, this field resets to 0.

DBGWVRn_EL1, bit [3]

Trap MSR writes of DBGWVR<n>_EL1 at EL1 using AArch64 to EL2.

DBGWVRn_EL1	Meaning
0b0	MSR writes of DBGWVR<n>_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of DBGWVR<n>_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

If watchpoint n is not implemented, a write of DBGWVR<n>_EL1 is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

DBGWCRn_EL1, bit [2]

Trap MSR writes of DBGWCR<n>_EL1 at EL1 using AArch64 to EL2.

DBGWCRn_EL1	Meaning
0b0	MSR writes of DBGWCR<n>_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of DBGWCR<n>_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

If watchpoint n is not implemented, a write of DBGWCR<n>_EL1 is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

DBGBVRn_EL1, bit [1]

Trap MSR writes of DBGBVR<n>_EL1 at EL1 using AArch64 to EL2.

DBGBVRn_EL1	Meaning
0b0	MSR writes of DBGBVR<n>_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of DBGBVR<n>_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

If breakpoint n is not implemented, a write of DBGBVR<n>_EL1 is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

DBGBCRn_EL1, bit [0]

Trap MSR writes of DBGBCR<n>_EL1 at EL1 using AArch64 to EL2.

DBGBCRn_EL1	Meaning
0b0	MSR writes of DBGBCR<n>_EL1 are not affected by this bit.
0b1	If EL2 is implemented and enabled in the current Security state and either EL3 is not implemented or SCR_EL3.FGTEn == 1, MSR writes of DBGBCR<n>_EL1 at EL1 using AArch64 are trapped to EL2 and reported with EC syndrome value 0x18, unless the write generates a higher priority exception.

If breakpoint n is not implemented, a write of DBGBCR<n>_EL1 is UNDEFINED.

In a system where the PE resets into EL2, this field resets to 0.

Accessing the HDFGWTR_EL2

Accesses to this register use the following encodings:

MRS <Xt>, HDFGWTR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b0011	0b0001	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x1D8];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FGTEn == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return HDFGWTR_EL2;
elsif PSTATE.EL == EL3 then
    return HDFGWTR_EL2;
```

MSR HDFGWTR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0011	0b0001	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x1D8] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FGTEn == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        HDFGWTR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    HDFGWTR_EL2 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HSTR_EL2, Hypervisor System Trap Register

The HSTR_EL2 characteristics are:

Purpose

Controls trapping to EL2 of EL1 or lower AArch32 accesses to the System register in the coproc == 0b1111 encoding space, by the CRn value used to access the register using MCR or MRC instruction. When the register is accessible using an MCRR or MRRC instruction, this is the CRm value used to access the register.

Configuration

AArch64 System register HSTR_EL2 bits [31:0] are architecturally mapped to AArch32 System register HSTR[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HSTR_EL2 are RES0.

If EL2 is not implemented, this register is RES0 from EL3.

~~If no Exception level can use AArch32, then this register is RES0.~~

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HSTR_EL2 is a 64-bit register.

Field descriptions

The HSTR_EL2 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																T15	T14	T13	T12	T11	T10	T9	T8	T7	T6	T5	T4	T3	T2	T1	T0
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:16]

Reserved, RES0.

T<n>, bit [n], for n = 0 to 15

Fields T14 and T4 are RES0.

The remaining fields control whether EL0 and EL1 accesses, using MCR, MRC, MCRR, and MRRC instructions, to the System registers in the coproc == 0b1111 encoding space are trapped to EL2 as follows:

- MCR or MRC accesses to these registers that are trapped to EL2 are reported using EC syndrome value 0x03, unless the access is UNDEFINED.
- MCRR or MRRC accesses to these registers that are trapped to EL2 are reported using EC syndrome value 0x04, unless the access is UNDEFINED.

T<n>	Meaning
0b0	This control has no effect on EL0 or EL1 accesses to System registers.
0b1	Any EL1 MCR or MRC access with coproc == 0b1111 and CRn == <n> is trapped to EL2. An EL0 MCR or MRC access with these values is trapped to EL2 only if the access is not UNDEFINED when the value of this field is 0. Any EL1 MCRR or MRRC access with coproc == 0b1111 and CRm == <n> is trapped to EL2. An EL0 MCRR or MRRC access with these values is trapped to EL2 only if the access is not UNDEFINED when the value of this field is 0. It is IMPLEMENTATION DEFINED whether a Non-secure EL0 access using AArch32 to these registers is trapped to EL2, or is UNDEFINED and generates an exception that is taken to Non-secure EL1. If the access is UNDEFINED, and generates an exception that is taken to Non-secure EL1 using AArch64, this is reported with EC syndrome value 0x00. **Note** Arm expects that trapping to EL2 of Non-secure EL0 accesses to these registers is unusual and used only when the hypervisor must virtualize EL0 operation. Arm recommends that, whenever possible, Non-secure EL0 accesses to these registers behave as they would if the implementation did not include EL2. This means that, if the architecture does not support the Non-secure EL0 access, then the register access instruction is treated as UNDEFINED and generates an exception that is taken to Non-secure EL1.

For example, when HSTR_EL2.T7 is 1, for instructions executed at EL1:

- An MCR or MRC instruction with coproc set to 0b1111 and <CRn> set to c7 is trapped to EL2.
- An MCRR or MRRC instruction with coproc set to 0b1111 and <CRm> set to c7 is trapped to EL2.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Accessing the HSTR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, HSTR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0001	0b0001	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x080];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HSTR_EL2;
elsif PSTATE.EL == EL3 then
    return HSTR_EL2;
```

```
MSR HSTR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0001	0b0001	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x080] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HSTR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    HSTR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_CTLR_EL1, Interrupt Controller Control Register (EL1)

The ICC_CTLR_EL1 characteristics are:

Purpose

Controls aspects of the behavior of the GIC CPU interface and provides information about the features implemented.

Configuration

AArch64 System register ICC_CTLR_EL1 bits [31:0] (S) are architecturally mapped to AArch32 System register ICC_CTLR[31:0] (S) .

AArch64 System register ICC_CTLR_EL1 bits [31:0] (NS) are architecturally mapped to AArch32 System register ICC_CTLR[31:0] (NS) .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICC_CTLR_EL1 is a 64-bit register.

Field descriptions

The ICC_CTLR_EL1 bit assignments are:



Bits [63:20]

Reserved, RES0.

ExtRange, bit [19]

Extended INTID range (read-only).

ExtRange	Meaning
0b0	CPU interface does not support INTIDs in the range 1024..8191. • Behaviour is UNPREDICTABLE if the IRI delivers an interrupt in the range 1024 to 8191 to the CPU interface. **Note** Arm strongly recommends that the IRI is not configured to deliver interrupts in this range to a PE that does not support them.
0b1	CPU interface supports INTIDs in the range 1024..8191 • All INTIDs in the range 1024..8191 are treated as requiring deactivation.

If EL3 is implemented, ICC_CTLR_EL1.ExtRange is an alias of ICC_CTLR_EL3.ExtRange.

RSS, bit [18]

Range Selector Support. Possible values are:

RSS	Meaning
0b0	Targeted SGIs with affinity level 0 values of 0 - 15 are supported.
0b1	Targeted SGIs with affinity level 0 values of 0 - 255 are supported.

This bit is read-only.

Bits [17:16]

Reserved, RES0.

A3V, bit [15]

Affinity 3 Valid. Read-only and writes are ignored. Possible values are:

A3V	Meaning
0b0	The CPU interface logic only supports zero values of Affinity 3 in SGI generation System registers.
0b1	The CPU interface logic supports non-zero values of Affinity 3 in SGI generation System registers.

If EL3 is implemented, this bit is an alias of ICC_CTLR_EL3.A3V.

SEIS, bit [14]

SEI Support. Read-only and writes are ignored. Indicates whether the CPU interface supports local generation of SEIs:

SEIS	Meaning
0b0	The CPU interface logic does not support local generation of SEIs.
0b1	The CPU interface logic supports local generation of SEIs.

If EL3 is implemented, this bit is an alias of ICC_CTLR_EL3.SEIS.

IDbits, bits [13:11]

Identifier bits. Read-only and writes are ignored. The number of physical interrupt identifier bits supported:

IDbits	Meaning
0b000	16 bits.
0b001	24 bits.

All other values are reserved.

If EL3 is implemented, this field is an alias of ICC_CTLR_EL3.IDbits.

PRIbits, bits [10:8]

Priority bits. Read-only and writes are ignored. The number of priority bits implemented, minus one.

An implementation that supports two Security states must implement at least 32 levels of physical priority (5 priority bits).

An implementation that supports only a single Security state must implement at least 16 levels of physical priority (4 priority bits).

Note

This field always returns the number of priority bits implemented, regardless of the Security state of the access or the value of GICD_CTLR.DS.

For physical accesses, this field determines the minimum value of ICC_BPR0_EL1.

If EL3 is implemented, physical accesses return the value from ICC_CTLR_EL3.PRIbits.

If EL3 is not implemented, physical accesses return the value from this field.

Bit [7]

Reserved, RES0.

PMHE, bit [6]

Priority Mask Hint Enable. Controls whether the priority mask register is used as a hint for interrupt distribution:

PMHE	Meaning
0b0	Disables use of ICC_PMR_EL1 as a hint for interrupt distribution.
0b1	Enables use of ICC_PMR_EL1 as a hint for interrupt distribution.

If EL3 is implemented, this bit is an alias of ICC_CTLR_EL3.PMHE. Whether this bit can be written as part of an access to this register depends on the value of GICD_CTLR.DS:

- If GICD_CTLR.DS == 0, this bit is read-only.
- If GICD_CTLR.DS == 1, this bit is read/write.

If EL3 is not implemented, it is IMPLEMENTATION DEFINED whether this bit is read-only or read-write:

- If this bit is read-only, an implementation can choose to make this field RAZ/WI or RAO/WI.
- If this bit is read/write, it resets to zero.

Bits [5:2]

Reserved, RES0.

EOImode, bit [1]

EOI mode for the current Security state. Controls whether a write to an End of Interrupt register also deactivates the interrupt:

EOImode	Meaning
0b0	ICC_EOIR0_EL1 and ICC_EOIR1_EL1 provide both priority drop and interrupt deactivation functionality. Accesses to ICC_DIR_EL1 are UNPREDICTABLE.
0b1	ICC_EOIR0_EL1 and ICC_EOIR1_EL1 provide priority drop functionality only. ICC_DIR_EL1 provides interrupt deactivation functionality.

The Secure ICC_CTLR_EL1.EOImode~~EOIMode~~ is an alias of ICC_CTLR_EL3.EOImode_EL1S.

The Non-secure ICC_CTLR_EL1.EOImode~~EOIMode~~ is an alias of ICC_CTLR_EL3.EOImode_EL1NS

CBPR, bit [0]

Common Binary Point Register. Controls whether the same register is used for interrupt preemption of both Group 0 and Group 1 interrupts:

CBPR	Meaning
0b0	ICC_BPR0_EL1 determines the preemption group for Group 0 interrupts only. ICC_BPR1_EL1 determines the preemption group for Group 1 interrupts.
0b1	ICC_BPR0_EL1 determines the preemption group for both Group 0 and Group 1 interrupts.

If EL3 is implemented:

- This bit is an alias of ICC_CTLR_EL3.CBPR_EL1{S,NS} where S or NS corresponds to the current Security state.
- If GICD_CTLR.DS == 0, this bit is read-only.
- If GICD_CTLR.DS == 1, this bit is read/write.

If EL3 is not implemented, this bit is read/write.

This field resets to an architecturally UNKNOWN value.

Accessing the ICC_CTLR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ICC_CTLR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b1100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if ICC_SRE_EL1.SRE == '0' then
        AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_CTLR_EL1;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_CTLR_EL1;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) then
        if SCR_EL3.NS == '0' then
            return ICC_CTLR_EL1_S;
        else
            return ICC_CTLR_EL1_NS;
    else
        return ICC_CTLR_EL1;
elsif PSTATE.EL == EL2 then
    if ICC_SRE_EL2.SRE == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) then
        if SCR_EL3.NS == '0' then
            return ICC_CTLR_EL1_S;
        else
            return ICC_CTLR_EL1_NS;
    else
        return ICC_CTLR_EL1;
elsif PSTATE.EL == EL3 then
    if ICC_SRE_EL3.SRE == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        if SCR_EL3.NS == '0' then
            return ICC_CTLR_EL1_S;
        else
            return ICC_CTLR_EL1_NS;
```

MSR ICC_CTLR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b1100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if ICC_SRE_EL1.SRE == '0' then
        AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_CTLR_EL1 = X[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_CTLR_EL1 = X[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) then
        if SCR_EL3.NS == '0' then
            ICC_CTLR_EL1_S = X[t];
        else
            ICC_CTLR_EL1_NS = X[t];
    else
        ICC_CTLR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if ICC_SRE_EL2.SRE == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) then
        if SCR_EL3.NS == '0' then
            ICC_CTLR_EL1_S = X[t];
        else
            ICC_CTLR_EL1_NS = X[t];
    else
        ICC_CTLR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    if ICC_SRE_EL3.SRE == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        if SCR_EL3.NS == '0' then
            ICC_CTLR_EL1_S = X[t];
        else
            ICC_CTLR_EL1_NS = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_CTLR_EL3, Interrupt Controller Control Register (EL3)

The ICC_CTLR_EL3 characteristics are:

Purpose

Controls aspects of the behavior of the GIC CPU interface and provides information about the features implemented.

Configuration

AArch64 System register ICC_CTLR_EL3 bits [31:0] can be mapped to AArch32 System register ICC_MCTLR[31:0] , but this is not architecturally mandated.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to ICC_CTLR_EL3 are UNDEFINED.

Attributes

ICC_CTLR_EL3 is a 64-bit register.

Field descriptions

The ICC_CTLR_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35
RES0																												
RES0												ExtRange	RSS	nDS	RES0	A3V	SEIS	IDbits			PRIbits			RES0		PMHE	RM	EOImode_EL1NS	EOImode_EL
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3

Bits [63:20]

Reserved, RES0.

ExtRange, bit [19]

Extended INTID range (read-only).

ExtRange	Meaning
0b0	CPU interface does not support INTIDs in the range 1024..8191. • Behaviour is UNPREDICTABLE if the IRI delivers an interrupt in the range 1024 to 8191 to the CPU interface. **Note** Arm strongly recommends that the IRI is not configured to deliver interrupts in this range to a PE that does not support them.
0b1	CPU interface supports INTIDs in the range 1024..8191 • All INTIDs in the range 1024..8191 are treated as requiring deactivation.

RSS, bit [18]

Range Selector Support. ~~Possible values are:~~

RSS	Meaning
0b0	Targeted SGIs with affinity level 0 values of 0-150~~ - 15~~ are supported.
0b1	Targeted SGIs with affinity level 0 values of 0-2550~~ - 255~~ are supported.

This bit is read-only.

nDS, bit [17]

Disable Security not supported. Read-only and writes are ignored. ~~Possible values are:~~

nDS	Meaning
0b0	The CPU interface logic supports disabling of security.
0b1	The CPU interface logic does not support disabling of security, and requires that security is not disabled.

Bit [16]

Reserved, RES0.

A3V, bit [15]

Affinity 3 Valid. Read-only and writes are ignored. ~~Possible values are:~~

A3V	Meaning
0b0	The CPU interface logic does not support non-zero values of the Aff3 field in SGI generation System registers.
0b1	The CPU interface logic supports non-zero values of the Aff3 field in SGI generation System registers.

If EL3 is present, ICC_CTLR_EL1.A3V~~AV3~~ is an alias of ICC_CTLR_EL3.A3V

SEIS, bit [14]

SEI Support. Read-only and writes are ignored. Indicates whether the CPU interface supports generation of SEIs:

SEIS	Meaning
0b0	The CPU interface logic does not support generation of SEIs.
0b1	The CPU interface logic supports generation of SEIs.

If EL3 is present, ICC_CTLR_EL1.SEIS is an alias of ICC_CTLR_EL3.SEIS

IDbits, bits [13:11]

Identifier bits. Read-only and writes are ignored. Indicates~~The~~ the number of physical interrupt identifier bits supported.~~supported:~~

IDbits	Meaning
0b000	16 bits.
0b001	24 bits.

All other values are reserved.

If EL3 is present, ICC_CTLR_EL1.IDbits is an alias of ICC_CTLR_EL3.IDbits

PRIbits, bits [10:8]

Priority bits. Read-only and writes are ignored. The number of priority bits implemented, minus one.

An implementation that supports two Security states must implement at least 32 levels of physical priority (5 priority bits).

An implementation that supports only a single Security state must implement at least 16 levels of physical priority (4 priority bits).

Note

This field always returns the number of priority bits implemented, regardless of the value of SCR_EL3.NS or the value of GICD_CTLR.DS.

The division between group priority and subpriority is defined in the binary point registers ICC_BPR0_EL1 and ICC_BPR1_EL1.

This field determines the minimum value of ICC_BPR0_EL1.

Bit [7]

Reserved, RES0.

PMHE, bit [6]

Priority Mask Hint Enable.

PMHE	Meaning
0b0	Disables use of the priority mask register as a hint for interrupt distribution.
0b1	Enables use of the priority mask register as a hint for interrupt distribution.

Software must write ICC_PMR_EL1 to 0xFF before clearing this field to 0.

- An implementation might choose to make this field RAO/WI if priority-based routing is always used
- An implementation might choose to make this field RAZ/WI if priority-based routing is never used

If EL3 is present, ICC_CTLR_EL1.PMHE is an alias of ICC_CTLR_EL3.PMHE.

This field resets to 0.

RM, bit [5]

Routing Modifier. For legacy operation of EL1 software with GICC_CTLR.FIQEn~~FIQen~~ set to 1, this bit indicates whether interrupts can be acknowledged or observed as the Highest Priority Pending Interrupt, or whether a special INTID value is returned.

Possible values of this bit are:

RM	Meaning
0b0	Secure Group 0 and Non-secure Group 1 interrupts can be acknowledged and observed as the highest priority interrupt at the Secure Exception level where the interrupt is taken.
0b1	When accessed at EL3 in AArch64 state: • Secure Group 0 interrupts return a special INTID value of 1020. This affects accesses to ICC_IAR0_EL1 and ICC_HPPIR0_EL1. • Non-secure Group 1 interrupts return a special INTID value of 1021. This affects accesses to ICC_IAR1_EL1 and ICC_HPPIR1_EL1.

Note

The Routing Modifier bit is supported in AArch64 only. In systems without EL3 the behavior is as if the value is 0. Software must ensure this bit is 0 when the Secure copy of ICC_SRE_EL1.SRE is 1, otherwise system behavior is

UNPREDICTABLE. In systems without EL3 or where the Secure copy of ICC_SRE_EL1.SRE is RAO/WI, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

EOImode_EL1NS, bit [4]

EOI mode for interrupts handled at Non-secure EL1 and EL2. Controls whether a write to an End of Interrupt register also deactivates the interrupt.~~interrupt.~~

EOImode_EL1NS	Meaning
0b0	ICC_EOIR0_EL1 and ICC_EOIR1_EL1 provide both priority drop and interrupt deactivation functionality. Accesses to ICC_DIR_EL1 are UNPREDICTABLE.
0b1	ICC_EOIR0_EL1 and ICC_EOIR1_EL1 provide priority drop functionality only. ICC_DIR_EL1 provides interrupt deactivation functionality.

If EL3 is present, ICC_CTLR_EL1(NS).EOImode is an alias of ICC_CTLR_EL3.EOImode_EL1NS.

This field resets to an architecturally UNKNOWN value.

EOImode_EL1S, bit [3]

EOI mode for interrupts handled at Secure EL1. Controls whether a write to an End of Interrupt register also deactivates the interrupt.~~interrupt.~~

EOImode_EL1S	Meaning
0b0	ICC_EOIR0_EL1 and ICC_EOIR1_EL1 provide both priority drop and interrupt deactivation functionality. Accesses to ICC_DIR_EL1 are UNPREDICTABLE.
0b1	ICC_EOIR0_EL1 and ICC_EOIR1_EL1 provide priority drop functionality only. ICC_DIR_EL1 provides interrupt deactivation functionality.

If EL3 is present, ICC_CTLR_EL1(S).EOImode is an alias of ICC_CTLR_EL3.EOImode_EL1S.

This field resets to an architecturally UNKNOWN value.

EOImode_EL3, bit [2]

EOI mode for interrupts handled at EL3. Controls whether a write to an End of Interrupt register also deactivates the interrupt.~~interrupt.~~

EOImode_EL3	Meaning
0b0	ICC_EOIR0_EL1 and ICC_EOIR1_EL1 provide both priority drop and interrupt deactivation functionality. Accesses to ICC_DIR_EL1 are UNPREDICTABLE.
0b1	ICC_EOIR0_EL1 and ICC_EOIR1_EL1 provide priority drop functionality only. ICC_DIR_EL1 provides interrupt deactivation functionality.

This field resets to an architecturally UNKNOWN value.

CBPR_EL1NS, bit [1]

Common Binary Point Register, EL1 Non-secure. Controls whether the same register is used for interrupt preemption of both Group 0 and Group 1 Non-secure interrupts at EL1 and EL2.~~EL2.~~

CBPR_EL1NS	Meaning
0b0	ICC_BPR0_EL1 determines the preemption group for Group 0 interrupts only. ICC_BPR1_EL1 determines the preemption group for Non-secure Group 1 interrupts.
0b1	ICC_BPR0_EL1 determines the preemption group for Group 0 interrupts and Non-secure Group 1 interrupts. Non-secure accesses to GICC_BPR and ICC_BPR1_EL1 access the state of ICC_BPR0_EL1.

If EL3 is present, ICC_CTLR_EL1(NS).CBPR is an alias of ICC_CTLR_EL3.CBPR_EL1NS.

This field resets to an architecturally UNKNOWN value.

CBPR_EL1S, bit [0]

Common Binary Point Register, EL1 Secure. Controls whether the same register is used for interrupt preemption of both Group 0 and Group 1 Secure interrupts at EL1.~~EL1.~~

CBPR_EL1S	Meaning
0b0	ICC_BPR0_EL1 determines the preemption group for Group 0 interrupts only. ICC_BPR1_EL1 determines the preemption group for Secure Group 1 interrupts.
0b1	ICC_BPR0_EL1 determines the preemption group for Group 0 interrupts and Secure Group 1 interrupts. Secure EL1 accesses to ICC_BPR1_EL1 access the state of ICC_BPR0_EL1.

If EL3 is present, ICC_CTLR_EL1(S).CBPR is an alias of ICC_CTLR_EL3.CBPR_EL1S.

This field resets to an architecturally UNKNOWN value.

Accessing the ICC_CTLR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, ICC_CTLR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1100	0b1100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if ICC_SRE_EL3.SRE == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ICC_CTLR_EL3;
```

```
MSR ICC_CTLR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1100	0b1100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if ICC_SRE_EL3.SRE == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ICC_CTLR_EL3 = X[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_EOIR0_EL1, Interrupt Controller End Of Interrupt Register 0

The ICC_EOIR0_EL1 characteristics are:

Purpose

A PE writes to this register to inform the CPU interface that it has completed the processing of the specified Group 0 interrupt.

Configuration

AArch64 System register ICC_EOIR0_EL1 performs the same function as AArch32 System register ICC_EOIR0.

Attributes

ICC_EOIR0_EL1 is a 64-bit register.

Field descriptions

The ICC_EOIR0_EL1 bit assignments are:



Bits [63:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID from the corresponding ICC_IAR0_EL1 access.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICC_CTLR_EL1.IDbits and ICC_CTLR_EL3.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

If the EOImode bit for the current Exception level and Security state is 0, a write to this register drops the priority for the interrupt, and also deactivates the interrupt.

If the EOImode bit for the current Exception level and Security state is 1, a write to this register only drops the priority for the interrupt. Software must write to ICC_DIR_EL1 to deactivate the interrupt.

The EOImode bit for the current Exception level and Security state is determined as follows:

- If EL3 is not implemented, the appropriate bit is ICC_CTLR_EL1.EOIMode.~~EOImode.~~
- If EL3 is implemented and the software is executing at EL3, the appropriate bit is ICC_CTLR_EL3.EOImode_EL3.
- If EL3 is implemented and the software is not executing at EL3, the bit depends on the current Security state:
    - If the software is executing in Secure state, the bit is ICC_CTLR_EL3.EOImode_EL1S.
    - If the software is executing in Non-secure state, the bit is ICC_CTLR_EL3.EOImode_EL1NS.

Accessing the ICC_EOIR0_EL1

A write to this register must correspond to the most recent valid read by this PE from an Interrupt Acknowledge Register, and must correspond to the INTID that was read from ICC_IAR0_EL1, otherwise the system behavior is UNPREDICTABLE. A valid read is a read that returns a valid INTID that is not a special INTID.

A write of a Special INTID is ignored. See Special INTIDs, for more information.

Accesses to this register use the following encodings:

```
MSR ICC_EOIR0_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b1000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if ICC_SRE_EL1.SRE == '0' then
        AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_EOIR0_EL1 = X[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ICC_EOIR0_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if ICC_SRE_EL2.SRE == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ICC_EOIR0_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    if ICC_SRE_EL3.SRE == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ICC_EOIR0_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_EOIR1_EL1, Interrupt Controller End Of Interrupt Register 1

The ICC_EOIR1_EL1 characteristics are:

Purpose

A PE writes to this register to inform the CPU interface that it has completed the processing of the specified Group 1 interrupt.

Configuration

AArch64 System register ICC_EOIR1_EL1 performs the same function as AArch32 System register ICC_EOIR1.

Attributes

ICC_EOIR1_EL1 is a 64-bit register.

Field descriptions

The ICC_EOIR1_EL1 bit assignments are:



Bits [63:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID from the corresponding ICC_IAR1_EL1 access.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICC_CTLR_EL1.IDbits and ICC_CTLR_EL3.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

If the EOImode bit for the current Exception level and Security state is 0, a write to this register drops the priority for the interrupt, and also deactivates the interrupt.

If the EOImode bit for the current Exception level and Security state is 1, a write to this register only drops the priority for the interrupt. Software must write to ICC_DIR_EL1 to deactivate the interrupt.

The EOImode bit for the current Exception level and Security state is determined as follows:

- If EL3 is not implemented, the appropriate bit is ICC_CTLR_EL1.EOIMode.~~EOImode.~~
- If EL3 is implemented and the software is executing at EL3, the appropriate bit is ICC_CTLR_EL3.EOImode_EL3.
- If EL3 is implemented and the software is not executing at EL3, the bit depends on the current Security state:
  - If the software is executing in Secure state, the bit is ICC_CTLR_EL3.EOImode_EL1S.
  - If the software is executing in Non-secure state, the bit is ICC_CTLR_EL3.EOImode_EL1NS.

Accessing the ICC_EOIR1_EL1

A write to this register must correspond to the most recent valid read by this PE from an Interrupt Acknowledge Register, and must correspond to the INTID that was read from ICC_IAR1_EL1, otherwise the system behavior is UNPREDICTABLE. A valid read is a read that returns a valid INTID that is not a special INTID.

A write of a Special INTID is ignored. See Special INTIDs, for more information.

Accesses to this register use the following encodings:

```
MSR ICC_EOIR1_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b1100	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if ICC_SRE_EL1.SRE == '0' then
        AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_EOIR1_EL1 = X[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ICC_EOIR1_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if ICC_SRE_EL2.SRE == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ICC_EOIR1_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    if ICC_SRE_EL3.SRE == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ICC_EOIR1_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_IGRPEN1_EL3, Interrupt Controller Interrupt Group 1 Enable register (EL3)

The ICC_IGRPEN1_EL3 characteristics are:

Purpose

Controls whether Group 1 interrupts are enabled or not.

Configuration

AArch64 System register ICC_IGRPEN1_EL3 bits [31:0] can be mapped to AArch32 System register ICC_MGRPEN1[31:0] , but this is not architecturally mandated.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to ICC_IGRPEN1_EL3 are UNDEFINED.

Attributes

ICC_IGRPEN1_EL3 is a 64-bit register.

Field descriptions

The ICC_IGRPEN1_EL3 bit assignments are:

63 62 61 60 59 58 57 56 55 54 53 52 51 50 49 48 47 46 45 44 43 42 41 40 39 38 37 36 35 34	33	32
RES0		
RES0	EnableGrp1S	EnableGrp1NS
31 30 29 28 27 26 25 24 23 22 21 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2	1	0

Bits [63:2]

Reserved, RES0.

EnableGrp1S, bit [1]

Enables Group 1 interrupts for the Secure state.

EnableGrp1S	Meaning
0b0	Secure Group 1 interrupts are disabled.
0b1	Secure Group 1 interrupts are enabled.

The Secure ICC_IGRPEN1_EL1.Enable bit is a read/write alias of the ICC_IGRPEN1_EL3.EnableGrp1S bit.

If the highest priority pending interrupt for that PE is a Group 1 interrupt using 1 of N model, then the interrupt will target another PE as a result of the Enable bit changing from 1 to 0.

This field resets to 0.

EnableGrp1NS, bit [0]

Enables Group 1 interrupts for the Non-secure state.

EnableGrp1NS	Meaning
0b0	Non-secure Group 1 interrupts are disabled.
0b1	Non-secure Group 1 interrupts are enabled.

The Non-secure ICC_IGRPEN1_EL1.Enable bit is a read/write alias of the ICC_IGRPEN1_EL3.EnableGrp1NS bit.

If the highest priority pending interrupt for that PE is a Group 1 interrupt using 1 of N model, then the interrupt will target another PE as a result of the Enable bit changing from 1 to 0.

This field resets to 0.

Accessing the ICC_IGRPEN1_EL3

Accesses to this register use the following encodings:

MRS <Xt>, ICC_IGRPEN1_EL3

op0	op1	CRn	CRm	op2
0b11	0b110	0b1100	0b1100	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if ICC_SRE_EL3.SRE == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ICC_IGRPEN1_EL3;
```

MSR ICC_IGRPEN1_EL3, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b110	0b1100	0b1100	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if ICC_SRE_EL3.SRE == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ICC_IGRPEN1_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_SRE_EL1, Interrupt Controller System Register Enable register (EL1)

The ICC_SRE_EL1 characteristics are:

Purpose

Controls whether the System register interface or the memory-mapped interface to the GIC CPU interface is used for EL1.

Configuration

AArch64 System register ICC_SRE_EL1 bits [31:0] (S) are architecturally mapped to AArch32 System register ICC_SRE[31:0] (S) .

AArch64 System register ICC_SRE_EL1 bits [31:0] (NS) are architecturally mapped to AArch32 System register ICC_SRE[31:0] (NS) .

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICC_SRE_EL1 is a 64-bit register.

Field descriptions

The ICC_SRE_EL1 bit assignments are:



Bits [63:3]

Reserved, RES0.

DIB, bit [2]

Disable IRQ bypass.

DIB	Meaning
0b0	IRQ bypass enabled.
0b1	IRQ bypass disabled.

If EL3 is implemented and GICD_CTLR.DS == 0, this field is a read-only alias of ICC_SRE_EL3.DIB.

If EL3 is implemented and GICD_CTLR.DS == 1, and EL2 is not implemented, this field is a read-write alias of ICC_SRE_EL3.DIB.

If EL3 is not implemented and EL2 is implemented, this field is a read-only alias of ~~or~~ ~~GICD_CTLR.DS == 1, and EL2 is implemented, this field is a read-only alias of~~ ICC_SRE_EL2.DIB.

If GICD_CTLR.DS == 1 and EL2 is implemented, this field is a read-only alias of ICC_SRE_EL2.DIB.

In systems that do not support IRQ bypass, this field is RAO/WI.

This field resets to 0.

DFB, bit [1]

Disable FIQ bypass.

DFB	Meaning
0b0	FIQ bypass enabled.
0b1	FIQ bypass disabled.

If EL3 is implemented and GICD_CTLR.DS == 0, this field is a read-only alias of ICC_SRE_EL3.DFB.

If EL3 is implemented and GICD_CTLR.DS == 1, and EL2 is not implemented, this field is a read-write alias of ICC_SRE_EL3.DFB.

If EL3 is not implemented and EL2 is implemented, this field is a read-only alias of~~or GICD_CTLR.DS == 1, and EL2 is implemented, this field is a read-only alias of~~ ICC_SRE_EL2.DFB.

If GICD_CTLR.DS == 1 and EL2 is implemented, this field is a read-only alias of ICC_SRE_EL2.DFB.

In systems that do not support FIQ bypass, this field is RAO/WI.

This field resets to 0.

SRE, bit [0]

System Register Enable.

SRE	Meaning
0b0	The memory-mapped interface must be used. Access at EL1 to any ICC_* System register other than ICC_SRE_EL1 is trapped to EL1.
0b1	The System register interface for the current Security state is enabled.

If software changes this bit from 1 to 0 in the Secure instance of this register, the results are UNPREDICTABLE.

If an implementation supports only a System register interface to the GIC CPU interface, this bit is RAO/WI.

If EL3 is implemented and ICC_SRE_EL3.SRE==0 the Secure copy of this bit is RAZ/WI. If ICC_SRE_EL3.SRE is changed from zero to one, the Secure copy of this bit becomes UNKNOWN.

If EL2 is implemented and ICC_SRE_EL2.SRE==0 the Non-secure copy of this bit is RAZ/WI. If ICC_SRE_EL2.SRE is changed from zero to one, the Non-secure copy of this bit becomes UNKNOWN.

If EL3 is implemented and ICC_SRE_EL3.SRE==0 the Non-secure copy of this bit is RAZ/WI. If ICC_SRE_EL3.SRE is changed from zero to one, the Non-secure copy of this bit becomes UNKNOWN.

GICv3 implementations that do not require GICv2 compatibility might choose to make this bit RAO/WI. The following options are supported:

- The Non-secure copy of ICC_SRE_EL1.SRE can be RAO/WI if ICC_SRE_EL2.SRE is also RAO/WI. This means all Non-secure software, including VMs using only virtual interrupts, must access the GIC using System registers.
- The Secure copy of ICC_SRE_EL1.SRE can be RAO/WI if ICC_SRE_EL3.SRE and ICC_SRE_EL2.SRE are also RAO/WI. This means that all Secure software must access the GIC using System registers and all Non-secure accesses to registers for physical interrupts must use System registers.

Note

A VM using only virtual interrupts might still use memory-mapped access if the Non-secure copy of ICC_SRE_EL1.SRE is not RAO/WI.

This field resets to 0.

Accessing the ICC_SRE_EL1

Execution with ICC_SRE_EL1.SRE set to 0 might make some System registers UNKNOWN.

Accesses to this register use the following encodings:

```
MRS <Xt>, ICC_SRE_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b1100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && ICC_SRE_EL2.Enable == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && ICC_SRE_EL3.Enable == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) then
        if SCR_EL3.NS == '0' then
            return ICC_SRE_EL1_S;
        else
            return ICC_SRE_EL1_NS;
    else
        return ICC_SRE_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && ICC_SRE_EL3.Enable == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) then
        if SCR_EL3.NS == '0' then
            return ICC_SRE_EL1_S;
        else
            return ICC_SRE_EL1_NS;
    else
        return ICC_SRE_EL1;
elsif PSTATE.EL == EL3 then
    if SCR_EL3.NS == '0' then
        return ICC_SRE_EL1_S;
    else
        return ICC_SRE_EL1_NS;
```

```
MSR ICC_SRE_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b1100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && ICC_SRE_EL2.Enable == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && ICC_SRE_EL3.Enable == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) then
        if SCR_EL3.NS == '0' then
            ICC_SRE_EL1_S = X[t];
        else
            ICC_SRE_EL1_NS = X[t];
    else
        ICC_SRE_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && ICC_SRE_EL3.Enable == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) then
        if SCR_EL3.NS == '0' then
            ICC_SRE_EL1_S = X[t];
        else
            ICC_SRE_EL1_NS = X[t];
    else
        ICC_SRE_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    if SCR_EL3.NS == '0' then
        ICC_SRE_EL1_S = X[t];
    else
        ICC_SRE_EL1_NS = X[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_SRE_EL3, Interrupt Controller System Register Enable register (EL3)

The ICC_SRE_EL3 characteristics are:

Purpose

Controls whether the System register interface or the memory-mapped interface to the GIC CPU interface is used for EL3.

Configuration

AArch64 System register ICC_SRE_EL3 bits [31:0] can be mapped to AArch32 System register ICC_MSRE[31:0] , but this is not architecturally mandated.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to ICC_SRE_EL3 are UNDEFINED.

Attributes

ICC_SRE_EL3 is a 64-bit register.

Field descriptions

The ICC_SRE_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																												Enable	DIB	DFB	SRE
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:4]

Reserved, RES0.

Enable, bit [3]

Enable. Enables lower Exception level access to ICC_SRE_EL1 and ICC_SRE_EL2.

Enable	Meaning
0b0	EL1 accesses to ICC_SRE_EL1 trap to EL3, unless these accesses are trapped to EL2 as a result of ICC_SRE_EL2.Enable == 0. EL2 accesses to ICC_SRE_EL1 and ICC_SRE_EL2 trap to EL3.
0b1	EL1 accesses to ICC_SRE_EL1 do not trap to EL3. EL2 accesses to ICC_SRE_EL1 and ICC_SRE_EL2 do not trap to EL3.

If ICC_SRE_EL3.SRE is RAO/WI, an implementation is permitted to make the Enable bit RAO/WI.

If ICC_SRE_EL3.SRE is 0, the Enable bit behaves as 1 for all purposes other than reading the value of the bit.

This field resets to an architecturally UNKNOWN value.

DIB, bit [2]

Disable IRQ bypass.

DIB	Meaning
0b0	IRQ bypass enabled.
0b1	IRQ bypass disabled.

In systems that do not support IRQ bypass, this bit is RAO/WI.

This field resets to 0.

DFB, bit [1]

Disable FIQ bypass.

DFB	Meaning
0b0	FIQ bypass enabled.
0b1	FIQ bypass disabled.

In systems that do not support FIQ bypass, this bit is RAO/WI.

This field resets to 0.

SRE, bit [0]

System Register Enable.

SRE	Meaning
0b0	The memory-mapped interface must be used. Access at EL3 to any ICH_* or ICC_* register other than ICC_SRE_EL1, ICC_SRE_EL2, or ICC_SRE_EL3 is trapped to EL3
0b1	The System register interface to the ICH_* registers and the EL1, EL2, and EL3 ICC_* registers is enabled for EL3.

If software changes this bit from 1 to 0, the results are UNPREDICTABLE.

GICv3 implementations that do not require GICv2 compatibility might choose to make this bit RAO/WI.

This field resets to 0.

Accessing the ICC_SRE_EL3

This register is always System register accessible.

Accesses to this register use the following encodings:

```
MRS <Xt>, ICC_SRE_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1100	0b1100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return ICC_SRE_EL3;
```

```
MSR ICC_SRE_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1100	0b1100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    ICC_SRE_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICH_HCR_EL2, Interrupt Controller Hyp Control Register

The ICH_HCR_EL2 characteristics are:

Purpose

Controls the environment for VMs.

Configuration

AArch64 System register ICH_HCR_EL2 bits [31:0] are architecturally mapped to AArch32 System register ICH_HCR[31:0] .

If EL2 is not implemented, this register is RES0 from EL3.

This register has no effect if EL2 is not enabled in the current Security state.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICH_HCR_EL2 is a 64-bit register.

Field descriptions

The ICH_HCR_EL2 bit assignments are:



Bits [63:32]

Reserved, RES0.

EOIcount, bits [31:27]

This field is incremented whenever a successful write to a virtual EOIR or DIR register would have resulted in a virtual interrupt deactivation. That is either:

- A virtual write to EOIR with a valid interrupt identifier that is not in the LPI range (that is < 8192) when EOI mode is zero and no List Register was found.
- A virtual write to DIR with a valid interrupt identifier that is not in the LPI range (that is < 8192) when EOI mode is one and no List Register was found.

This allows software to manage more active interrupts than there are implemented List Registers.

It is CONSTRAINED UNPREDICTABLE whether a virtual write to EOIR that does not clear a bit in the Active Priorities registers (ICH_AP0R<n>_EL2/ICH_AP1R<n>_EL2) increments EOIcount. Permitted behaviors are:

- Increment EOIcount.
- Leave EOIcount unchanged.

This field resets to 0.

Bits [26:15]

Reserved, RES0.

TDIR, bit [14]

Trap EL1 writes to ICC_DIR_EL1 and ICV_DIR_EL1.

TDIR	Meaning
0b0	EL1 writes of ICC_DIR_EL1 and ICV_DIR_EL1 are not trapped to EL2, unless trapped by other mechanisms.
0b1	EL1 writes of ICV_DIR_EL1 are trapped to EL2. It is IMPLEMENTATION DEFINED whether writes of ICC_DIR_EL1 are trapped. Not trapping ICC_DIR_EL1 writes is DEPRECATED.

Support for this bit is OPTIONAL, with support indicated by ICH_VTR_EL2.

If the implementation does not support this trap, this bit is RES0.

Arm deprecates not including this trap bit.

This field resets to 0.

TSEI, bit [13]

Trap all locally generated SEIs. This bit allows the hypervisor to intercept locally generated SEIs that would otherwise be taken at EL1.

TSEI	Meaning
0b0	Locally generated SEIs do not cause a trap to EL2.
0b1	Locally generated SEIs trap to EL2.

If ICH_VTR_EL2.SEIS is 0, this bit is RES0.

This field resets to 0.

TALL1, bit [12]

Trap all EL1 accesses to ICC_* and ICV_* System registers for Group 1 interrupts to EL2.

TALL1	Meaning
0b0	EL1 accesses to ICC_* and ICV_* registers for Group 1 interrupts proceed as normal.
0b1	EL1 accesses to ICC_* and ICV_* registers for Group 1 interrupts trap to EL2.

This field resets to 0.

TALL0, bit [11]

Trap all EL1 accesses to ICC_* and ICV_* System registers for Group 0 interrupts to EL2.

TALL0	Meaning
0b0	EL1 accesses to ICC_* and ICV_* registers for Group 0 interrupts proceed as normal.
0b1	EL1 accesses to ICC_* and ICV_* registers for Group 0 interrupts trap to EL2.

This field resets to 0.

TC, bit [10]

Trap all EL1 accesses to System registers that are common to Group 0 and Group 1 to EL2.

TC	Meaning
0b0	EL1 accesses to common registers proceed as normal.
0b1	EL1 accesses to common registers trap to EL2.

This affects accesses to ICC_SGI0R_EL1, ICC_SGI1R_EL1, ICC_ASGI1R_EL1, ICC_CTLR_EL1, ICC_DIR_EL1, ICC_PMR_EL1, ICC_RPR_EL1, ICV_CTLR_EL1, ICV_DIR_EL1, ICV_PMR_EL1, and ICV_RPR_EL1.

This field resets to 0.

BitBits [9:8]

Reserved, RES0.

vSGIEOICount, bit [8]

When GICv4.1 is implemented:

Controls whether deactivation of virtual SGIs can increment ICH_HCR_EL2.EOIcount

vSGIEOICount	Meaning
0b0	Deactivation of virtual SGIs can increment ICH_HCR_EL2.EOIcount.
0b1	Deactivation of virtual SGIs does not increment ICH_HCR_EL2.EOIcount.

This field resets to 0.

Otherwise:

Reserved, RES0.

VGrp1DIE, bit [7]

VM Group 1 Disabled Interrupt Enable. Enables the signaling of a maintenance interrupt while signaling of Group 1 interrupts from the virtual CPU interface to the connected vPE is disabled:

VGrp1DIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when ICH_VMCR_EL2.VENG1 is 0.

This field resets to 0.

VGrp1EIE, bit [6]

VM Group 1 Enabled Interrupt Enable. Enables the signaling of a maintenance interrupt while signaling of Group 1 interrupts from the virtual CPU interface to the connected vPE is enabled:

VGrp1EIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when ICH_VMCR_EL2.VENG1 is 1.

This field resets to 0.

VGrp0DIE, bit [5]

VM Group 0 Disabled Interrupt Enable. Enables the signaling of a maintenance interrupt while signaling of Group 0 interrupts from the virtual CPU interface to the connected vPE is disabled:

VGrp0DIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when ICH_VMCR_EL2.VENG0 is 0.

This field resets to 0.

VGrp0EIE, bit [4]

VM Group 0 Enabled Interrupt Enable. Enables the signaling of a maintenance interrupt while signaling of Group 0 interrupts from the virtual CPU interface to the connected vPE is enabled:

VGrp0EIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when ICH_VMCR_EL2.VENG0 is 1.

This field resets to 0.

NPIE, bit [3]

No Pending Interrupt Enable. Enables the signaling of a maintenance interrupt when there are no List registers with the State field set to 0b01 (pending):

NPIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled while the List registers contain no interrupts in the pending state.

This field resets to 0.

LRENPIE, bit [2]

List Register Entry Not Present Interrupt Enable. Enables the signaling of a maintenance interrupt while the virtual CPU interface does not have a corresponding valid List register entry for an EOI request:

LRENPIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt is asserted while the EOIcount field is not 0.

This field resets to 0.

UIE, bit [1]

Underflow Interrupt Enable. Enables the signaling of a maintenance interrupt when the List registers are empty, or hold only one valid entry:

UIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt is asserted if none, or only one, of the List register entries is marked as a valid interrupt.

This field resets to 0.

En, bit [0]

Enable. Global enable bit for the virtual CPU interface:

En	Meaning
0b0	Virtual CPU interface operation disabled.
0b1	Virtual CPU interface operation enabled.

When this field is set to 0:

- The virtual CPU interface does not signal any maintenance interrupts.
- The virtual CPU interface does not signal any virtual interrupts.
- A read of ICV_IAR0_EL1, ICV_IAR1_EL1, GICV_IAR or GICV_AIAR returns a spurious interrupt ID.

Note

This field is RES0 when SCR_EL3.{NS,EEL2}=={0,0}

This field resets to 0.

Accessing the ICH_HCR_EL2

Accesses to this register use the following encodings:

MRS <Xt>, ICH_HCR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b1100	0b1011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x4C0];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_SRE_EL2.SRE == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ICH_HCR_EL2;
elsif PSTATE.EL == EL3 then
    if ICC_SRE_EL3.SRE == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return ICH_HCR_EL2;
```

MSR ICH_HCR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b1100	0b1011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x4C0] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_SRE_EL2.SRE == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        ICH_HCR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    if ICC_SRE_EL3.SRE == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        ICH_HCR_EL2 = X[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64AFR0_EL1, AArch64 Auxiliary Feature Register 0

The ID_AA64AFR0_EL1 characteristics are:

Purpose

Provides information about the IMPLEMENTATION DEFINED features of the PE in AArch64 state.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

There are no configuration notes.

Attributes

ID_AA64AFR0_EL1 is a 64-bit register.

Field descriptions

The ID_AA64AFR0_EL1 bit assignments are:



Bits [63:32]

Reserved, RES0.

IMPLEMENTATION DEFINED, bits [31:28]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [27:24]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [23:20]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [19:16]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [15:12]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [11:8]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [7:4]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [3:0]

IMPLEMENTATION DEFINED.

Accessing the ID_AA64AFR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AA64AFR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0101	0b100

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64AFR0_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64AFR0_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64AFR0_EL1;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64AFR1_EL1, AArch64 Auxiliary Feature Register 1

The ID_AA64AFR1_EL1 characteristics are:

Purpose

Reserved for future expansion of information about the IMPLEMENTATION DEFINED features of the PE in AArch64 state.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

There are no configuration notes.

Attributes

ID_AA64AFR1_EL1 is a 64-bit register.

Field descriptions

The ID_AA64AFR1_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Reserved, RES0.

Accessing the ID_AA64AFR1_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AA64AFR1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0101	0b101

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64AFR1_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64AFR1_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64AFR1_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64DFR0_EL1, AArch64 Debug Feature Register 0

The ID_AA64DFR0_EL1 characteristics are:

Purpose

Provides top level information about the debug system in AArch64 state.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

The external register EDDFR gives information from this register.

Attributes

ID_AA64DFR0_EL1 is a 64-bit register.

Field descriptions

The ID_AA64DFR0_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0												MTPMU				RES0				TraceFilt				DoubleLock				PMSVer			
CTX_CMPs				RES0				WRPs				RES0				BRPs				PMUVer				TraceVer				DebugVer			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:52]

Reserved, RES0.

MTPMU, bits [51:48]

From Armv8.6:

Multi-threaded PMU extension. Defined values are:

MTPMU	Meaning
0b0000	ARMv8.6-MTPMU not implemented. If PMUv3 is implemented, it is IMPLEMENTATION DEFINED whether PMEVTYPER<n>_EL0.MT are read/write or RES0.
0b0001	ARMv8.6-MTPMU implemented and PMEVTYPER<n>_EL0.MT are read/write. When ARMv8.6-MTPMU is disabled, the Effective values of PMEVTYPER<n>_EL0.MT are 0.
0b1111	ARMv8.6-MTPMU not implemented. If PMUv3 is implemented, PMEVTYPER<n>_EL0.MT are RES0.

All other values are reserved.

ARMv8.6-MTPMU implements the functionality identified by the value 0b0001.

In an Armv8.6-compliant implementation that includes PMUv3, the value 0b0000 is not permitted.

In an implementation that does not include PMUv3, the value 0b0001 is not permitted.

Otherwise:

Reserved, RES0.

Bits [47:44]

Reserved, RES0.

TraceFilt, bits [43:40]

From Armv8.4:

Armv8.4 Self-hosted Trace Extension version. Defined values are:

TraceFilt	Meaning
0b0000	Armv8.4 Self-hosted Trace Extension not implemented.
0b0001	Armv8.4 Self-hosted Trace Extension implemented.

All other values are reserved.

ARMv8.4-Trace implements the functionality identified by the value 0b0001.

Otherwise:

Reserved, RES0.

DoubleLock, bits [39:36]

OS Double Lock implemented. Defined values are:

DoubleLock	Meaning
0b0000	OS Double Lock implemented. OSDLR_EL1 is RW.
0b1111	OS Double Lock not implemented. OSDLR_EL1 is RAZ/WI.

All other values are reserved.

ARMv8.0-DoubleLock implements the functionality identified by the value 0b0000.

PMSVer, bits [35:32]

From Armv8.2:

Statistical Profiling Extension version. Defined values are:

PMSVer	Meaning
0b0000	Statistical Profiling Extension not implemented.
0b0001	Statistical Profiling Extension implemented.
0b0010	As 0b0001 and also includes support for: • The Event packet Alignment flag. • If SVE is implemented, the Scalable Vector extensions to Statistical Profiling.

All other values are reserved.

SPE implements the functionality identified by the value 0b0001.

ARMv8.3-SPE implements the functionality added by the value 0b0010.

ARMv8.3-SPE implements the functionality added by the value 0b0010. If ARMv8.3-SPE is implemented, then ID_AA64DFR0_EL1.PMSVer is not permitted to read as 0b0000 or 0b0001.

~~Otherwise:~~

~~Reserved, RES0.~~

If ARMv8.3-SPE is implemented, the values `0b0000` and `0b0001` are not permitted.

CTX_CMPs, bits [31:28]

Number of breakpoints that are context-aware, minus 1. These are the highest numbered breakpoints.

Bits [27:24]

Reserved, RES0.

WRPs, bits [23:20]

Number of watchpoints, minus 1. The value of `0b0000` is reserved.

Bits [19:16]

Reserved, RES0.

BRPs, bits [15:12]

Number of breakpoints, minus 1. The value of `0b0000` is reserved.

PMUVer, bits [11:8]

Performance Monitors Extension version.

This field does not follow the standard ID scheme, but uses the Alternative ID scheme described in 'Alternative ID scheme used for the Performance Monitors Extension version' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Defined values are:

PMUVer	Meaning
`0b0000`	Performance Monitors Extension not implemented.
`0b0001`	Performance Monitors Extension implemented, PMUv3.
`0b0100`	PMUv3 for Armv8.1. As `0b0001`, and also includes support for: • Extended 16-bit PMEVTYPER<n>_EL0.evtCount field. • If EL2 is implemented, the MDCR_EL2.HPMD control bit.
`0b0101`	PMUv3 for Armv8.4. As `0b0100` and also includes support for the PMMIR_EL1 register.
`0b0110`	PMUv3 for Armv8.5. As `0b0101` and also includes support for: • 64-bit event counters. • If EL2 is implemented, the MDCR_EL2.HCCD control bit. • If EL3 is implemented, the MDCR_EL3.SCCD control bit.
`0b1111`	IMPLEMENTATION DEFINED form of performance monitors supported, PMUv3 not supported. Arm does not recommend this value in new implementations.

All other values are reserved.

ARMv8.1-PMU implements the functionality identified by the value `0b0100`.

ARMv8.4-PMU implements the functionality identified by the value `0b0101`.

ARMv8.5-PMU implements the functionality identified by the value `0b0110`.

In an Armv8.1-compliant implementation that includes PMUv3, the value `0b0001` is not permitted.

In an Armv8.4-compliant implementation that includes PMUv3, the value `0b0100` is not permitted.

In an Armv8.5-compliant implementation that includes PMUv3, the value `0b0101` is not permitted.

TraceVer, bits [7:4]

Trace support. Indicates whether System register interface to a PE trace unit is implemented. Defined values are:

TraceVer	Meaning
`0b0000`	PE trace unit System registers not implemented.
`0b0001`	PE trace unit System registers implemented.

All other values are reserved.

See the ETM Architecture Specification for more information.

A value of `0b0000` only indicates that no System register interface to a PE trace unit is implemented. A PE trace unit might nevertheless be implemented without a System register interface.

DebugVer, bits [3:0]

Debug architecture version. Indicates presence of Armv8 debug architecture. Defined values are:

DebugVer	Meaning
`0b0110`	Armv8 debug architecture.
`0b0111`	Armv8 debug architecture with Virtualization Host Extensions.
`0b1000`	Armv8.2 debug architecture.
`0b1001`	Armv8.4 debug architecture.

All other values are reserved.

ARMv8.2-Debug adds the functionality identified by the value `0b1000`.

- If ARMv8.1-VHE is not implemented the only permitted value is `0b0110`.
- In an Armv8.0 implementation the value `0b1000` is not permitted.

Accessing the ID_AA64DFR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AA64DFR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0101	0b000

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64DFR0_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64DFR0_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64DFR0_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64DFR1_EL1, AArch64 Debug Feature Register 1

The ID_AA64DFR1_EL1 characteristics are:

Purpose

Reserved for future expansion of top level information about the debug system in AArch64 state.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

There are no configuration notes.

Attributes

ID_AA64DFR1_EL1 is a 64-bit register.

Field descriptions

The ID_AA64DFR1_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Reserved, RES0.

Accessing the ID_AA64DFR1_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AA64DFR1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0101	0b001

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64DFR1_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64DFR1_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64DFR1_EL1;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64ISAR0_EL1, AArch64 Instruction Set Attribute Register 0

The ID_AA64ISAR0_EL1 characteristics are:

Purpose

Provides information about the instructions implemented in AArch64 state.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

There are no configuration notes.

Attributes

ID_AA64ISAR0_EL1 is a 64-bit register.

Field descriptions

The ID_AA64ISAR0_EL1 bit assignments are:



RNDR, bits [63:60]

From Armv8.5:

Indicates support for Random Number instructions in AArch64 state. Defined values are:

RNDR	Meaning
0b0000	No Random Number instructions are implemented.
0b0001	RNDR and RNDRRS registers are implemented.

All other values are reserved.

ARMv8.5-RNG implements the functionality identified by the value 0b0001.

From Armv8.5, the permitted values are 0b0000 and 0b0001.

Reserved, RES0.

TLB, bits [59:56]

From Armv8.4:

Otherwise:
TLB, bits [59:56]

Indicates support for Outer shareable and TLB range maintenance instructions. Defined values are:

TLB	Meaning
0b0000	Outer shareable and TLB range maintenance instructions are not implemented.
0b0001	Outer shareable TLB maintenance instructions are implemented.
0b0010	Outer shareable and TLB range maintenance instructions are implemented.

All other values are reserved.

ARMv8.4-TLBI implements the functionality identified by the values 0b0001 and 0b0010.

From Armv8.4, the only permitted value is 0b0010.

~~**Otherwise:**~~

~~Reserved, RES0.~~

TS, bits [55:52]

Indicates support for flag manipulation instructions. Defined values are:

TS	Meaning
0b0000	No flag manipulation instructions are implemented.
0b0001	CFINV, RMIF, SETF16, and SETF8 instructions are implemented.
0b0010	CFINV, RMIF, SETF16, SETF8, AXFLAG, and XAFLAG instructions are implemented.

All other values are reserved.

ARMv8.4-CondM implements the functionality identified by the value 0b0001.

ARMv8.5-CondM implements the functionality identified by the value 0b0010.

From Armv8.4, the only permitted value is 0b0001.

From Armv8.5, the only permitted value is 0b0010.

FHM, bits [51:48]

~~**From Armv8.2:**~~

Indicates support~~whether~~ for FMLAL and FMLSL instructions.~~instructions~~ Defined~~are~~ values are:~~implemented.~~

FHM	Meaning
0b0000	FMLAL and FMLSL instructions are not implemented.
0b0001	FMLAL and FMLSL instructions are implemented.

All other values are reserved.

ARMv8.2-FHM implements the functionality identified by the value 0b0001.

From Armv8.2, the permitted values are 0b0000 and 0b0001.

~~**DP, bits [47:44]**~~

~~**From Armv8.2:**~~

~~Dot Product instructions implemented in AArch64 state. Defined values are:~~

~~**Otherwise:**~~
DP, bits [47:44]

Indicates support for Dot Product instructions in AArch64 state. Defined values are:

Reserved, RES0.

DP	Meaning
0b0000	No Dot Product instructions implemented.
0b0001	UDOT and SDOT instructions implemented.

All other values are reserved.

ARMv8.2-DotProd implements the functionality identified by the value 0b0001.

From Armv8.2, the permitted values are 0b0000 and 0b0001.

SM4, bits [43:40]

From Armv8.2:

SM4 instructions implemented in AArch64 state. Defined values are:

Otherwise:
SM4, bits [43:40]

Indicates support for SM4 instructions in AArch64 state. Defined values are:

Reserved, RES0.

SM4	Meaning
0b0000	No SM4 instructions implemented.
0b0001	SM4E and SM4EKEY instructions implemented.

All other values are reserved.

If ARMv8.2-SM is not implemented, the value 0b0001 is reserved.

From Armv8.2, the permitted values are 0b0000 and 0b0001.

This field must have the same value as ID_AA64ISAR0_EL1.SM3.

SM3, bits [39:36]

From Armv8.2:

SM3 instructions implemented in AArch64 state. Defined values are:

Otherwise:
SM3, bits [39:36]

Indicates support for SM3 instructions in AArch64 state. Defined values are:

Reserved, RES0.

SM3	Meaning
0b0000	No SM3 instructions implemented.
0b0001	SM3SS1, SM3TT1A, SM3TT1B, SM3TT2A, SM3TT2B, SM3PARTW1, and SM3PARTW2 instructions implemented.

All other values are reserved.

If ARMv8.2-SM is not implemented, the value 0b0001 is reserved.

ARMv8.2-SM implements the functionality identified by the value 0b0001.

From Armv8.2, the permitted values are 0b0000 and 0b0001.

This field must have the same value as ID_AA64ISAR0_EL1.SM4.

SHA3, bits [35:32]

From Armv8.2:

SHA3 instructions implemented in AArch64 state. Defined values are:

Otherwise:

SHA3, bits [35:32]

Indicates support for SHA3 instructions in AArch64 state. Defined values are:

Reserved, RES0.

SHA3	Meaning
0b0000	No SHA3 instructions implemented.
0b0001	EOR3, RAX1, XAR, and BCAX instructions implemented.

All other values are reserved.

If ARMv8.2-SHA is not implemented, the value 0b0001 is reserved.

ARMv8.2-SHA implements the functionality identified by the value 0b0001.

From Armv8.2, the permitted values are 0b0000 and 0b0001.

If the value of ID_AA64ISAR0_EL1.SHA1 is 0b0000, then this field must have the value 0b0000.

If the value of this field is 0b0001, then ID_AA64ISAR0_EL1.SHA2 must have the value 0b0010.

RDM, bits [31:28]

From Armv8.1:

SQRDMLAH and SQRDMLSH instructions implemented in AArch64 state. Defined values are:

Otherwise:

RDM, bits [31:28]

Indicates support for SQRDMLAH and SQRDMLSH instructions in AArch64 state. Defined values are:

Reserved, RES0.

RDM	Meaning
0b0000	No RDMASQRDMLAH and SQRDMLSH instructions implemented.
0b0001	SQRDMLAH and SQRDMLSH instructions implemented.

All other values are reserved.

ARMv8.1-RDMA implements the functionality identified by the value 0b0001.

From Armv8.1, the only permitted value is 0b0001.

Otherwise:

Reserved, RES0.

Bits [27:24]

Reserved, RES0.

Atomic, bits [23:20]

~~From Armv8.1:~~

Indicates support for Atomic instructions ~~implemented~~ in AArch64 state. Defined values are:

Atomic	Meaning
0b0000	No Atomic instructions implemented.
0b0010	LDADD, LDCLR, LDEOR, LDSET, LDSMAX, LDSMIN, LDUMAX, LDUMIN, CAS, CASP, and SWP instructions implemented.

All other values are reserved.

ARMv8.1-LSE implements the functionality identified by the value 0b0010.

From Armv8.1, the only permitted value is 0b0010.

~~Otherwise:~~

~~Reserved, RES0.~~

CRC32, bits [19:16]

CRC32 instructions implemented in AArch64 state. Defined values are:

CRC32	Meaning
0b0000	No CRC32 instructions implemented.
0b0001	CRC32B, CRC32H, CRC32W, CRC32X, CRC32CB, CRC32CH, CRC32CW, and CRC32CX instructions implemented.

All other values are reserved.

In Armv8.0, the permitted values are 0b0000 and 0b0001.

From Armv8.1, the only permitted value is 0b0001.

SHA2, bits [15:12]

SHA2 instructions implemented in AArch64 state. Defined values are:

SHA2	Meaning
0b0000	No SHA2 instructions implemented.
0b0001	SHA256H, SHA256H2, SHA256SU0, and SHA256SU1 instructions implemented.
0b0010	As 0b0001, plus SHA512H, SHA512H2, SHA512SU0, and SHA512SU1 instructions implemented.

All other values are reserved.

If ARMv8.2-SHA is not implemented the value 0b0010 is reserved.

From Armv8.2, the permitted values are 0b0000, 0b0001, and 0b0010.

If the value of ID_AA64ISAR0_EL1.SHA1 is 0b0000, then this field must have the value 0b0000.

If the value of this field is 0b0010, then ID_AA64ISAR0_EL1.SHA3 must have the value 0b0001.

SHA1, bits [11:8]

SHA1 instructions implemented in AArch64 state. Defined values are:

SHA1	Meaning
0b0000	No SHA1 instructions implemented.
0b0001	SHA1C, SHA1P, SHA1M, SHA1H, SHA1SU0, and SHA1SU1 instructions implemented.

All other values are reserved.

From Armv8, the permitted values are `0b0000` and `0b0001`.

If the value of ID_AA64ISAR0_EL1.SHA2 is `0b0000`, then this field must have the value `0b0000`.

AES, bits [7:4]

AES instructions implemented in AArch64 state. Defined values are:

AES	Meaning
`0b0000`	No AES instructions implemented.
`0b0001`	AESE, AESD, AESMC, and AESIMC instructions implemented.
`0b0010`	As for `0b0001`, plus PMULL/PMULL2 instructions operating on 64-bit data quantities.

All other values are reserved.

From Armv8, the permitted values are `0b0000`, `0b0001`, and `0b0010`.

Bits [3:0]

Reserved, RES0.

Accessing the ID_AA64ISAR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AA64ISAR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0110	0b000

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64ISAR0_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64ISAR0_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64ISAR0_EL1;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64ISAR1_EL1, AArch64 Instruction Set Attribute Register 1

The ID_AA64ISAR1_EL1 characteristics are:

Purpose

Provides information about the features and instructions implemented in AArch64 state.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

If ID_AA64ISAR1_EL1.{API, APA} == {0000, 0000}, then:

- The TCR_EL1.{TBID,TBID0}, TCR_EL2.{TBID0,TBID1}, TCR_EL2.TBID and TCR_EL3.TBID bits are RES0.
- APIAKeyHi_EL1, APIAKeyLo_EL1, APIBKeyHi_EL1, APIBKeyLo_EL1, APDAKeyHi_EL1, APDAKeyLo_EL1, APDBKeyHi_EL1, APDBKeyLo_EL1 are not allocated.
- SCTLR_ELx.EnIA, SCTLR_ELx.EnIB, SCTLR_ELx.EnDA, SCTLR_ELx.EnDB are all RES0.

If ID_AA64ISAR1_EL1.{GPI, GPA, API, APA} == {0000, 0000, 0000, 0000}, then:

- HCR_EL2.APK and HCR_EL2.API are RES0.
- SCR_EL3.APK and SCR_EL3.API are RES0.

Attributes

ID_AA64ISAR1_EL1 is a 64-bit register.

Field descriptions

The ID_AA64ISAR1_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0								I8MM				DGH				BF16				SPECRES				SB				FRINTTS			
GPI				GPA				LRCPC				FCMA				JSCVT				API				APA				DPB			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:56]

Reserved, RES0.

I8MM, bits [55:52]

~~From Armv8.2:~~

Indicates support for Floating-point~~Advanced~~ ~~SIMD~~ and Advanced SIMD~~floating-point~~ Int8 matrix multiplication instructions in AArch64 state. Defined values of this field are:

I8MM	Meaning
0b0000	Int8 matrix multiplication instructions are not implemented.
0b0001	SMMLA, SUDOT, UMMLA, USMMLA, and USDOT instructions are implemented.

All other values are reserved.

ARMv8.2-I8MM implements the functionality identified by 0b0001.

When Advanced SIMD and SVE are both implemented, this field must return the same value as ID_AA64ZFR0_EL1.I8MM.

From Armv8.6, the only permitted value is 0b0001.

DGH, bits [51:48]

From Armv8.6:

Indicates presence of the Data Gathering Hint instruction. Defined values are:

Otherwise:
DGH, bits [51:48]

Indicates support for the Data Gathering Hint instruction. Defined values are:

Reserved, RES0.

DGH	Meaning
0b0000	Data Gathering Hint is not implemented.
0b0001	Data Gathering Hint is implemented.

All other values are reserved.

ARMv8.0-DGH implements the functionality identified by 0b0001.

From ARMv8.0, the permitted values are 0b0000 and 0b0001.

If the DGH instruction has no effect in preventing the merging of memory accesses, the value of this field is 0.

BF16, bits [47:44]

From Armv8.2:

Indicates support for Advanced SIMD and floating-point BFloat16 instructions in AArch64 state. Defined values are:

Otherwise:
BF16, bits [47:44]

Indicates support for Advanced SIMD and Floating-point BFloat16 instructions in AArch64 state. Defined values are:

Reserved, RES0.

BF16	Meaning
0b0000	BFloat16 instructions are not implemented.
0b0001	BFDOT, BFMLAL, BFMLAL2, BFMMLA, BFCVT, and BFCVT2 instructions are implemented.

All other values are reserved.

ARMv8.2-BF16 implements the functionality identified by 0b0001.

When Advanced SIMD and SVE are both implemented, this field must return the same value as ID_AA64ZFR0_EL1.BF16.

From ARMv8.6, the only permitted value is 0b0001.

Otherwise:

Reserved, RES0.

SPECRES, bits [43:40]

IndicatesSpeculation supportinvalidation forinstruction prediction invalidation instructionssupport in AArch64 state. Defined values are:

SPECRES	Meaning
0b0000	CFP RCTX, DVP RCTX, and CPP RCTX instructions are not implemented.
0b0001	CFP RCTX, DVP RCTX, and CPP RCTX instructions are implemented.

All other values are reserved.

ARMv8.0-PredInv implements the functionality identified by 0b0001.

From Armv8.5, the only permitted value is 0b0001.

SB, bits [39:36]

Indicates support for SB instruction support in AArch64 state. Defined values are:

SB	Meaning
0b0000	SB instruction is not implemented.
0b0001	SB instruction is implemented.

All other values are reserved.

ARMv8.0-SB implements the functionality identified by 0b0001.

From Armv8.5, the only permitted value is 0b0001.

FRINTTS, bits [35:32]

From Armv8.5:

Indicates support for thewhether FRINT32Z, FRINT32X, FRINT64Z, and FRINT64X instructions are implemented. Defined values are:

FRINTTS	Meaning
0b0000	FRINT32Z, FRINT32X, FRINT64Z, and FRINT64X instructions are not implemented.
0b0001	FRINT32Z, FRINT32X, FRINT64Z, and FRINT64X instructions are implemented.

All other values are reserved.

ARMv8.5-FRINT implements the functionality identified by 0b0001.

From Armv8.5, the only permitted value is 0b0001.

GPI, bits [31:28]

From Armv8.3:

Indicates whether an IMPLEMENTATION DEFINED algorithm is implemented in the PE for generic code authentication, in AArch64 state. Defined values are:

Otherwise:

GPI, bits [31:28]

Indicates support for anReserved, IMPLEMENTATION DEFINEDRES0 algorithm is implemented in the PE for generic code authentication in AArch64 state. Defined values are:.

GPI	Meaning
0b0000	Generic Authentication using an IMPLEMENTATION DEFINED algorithm is not implemented.
0b0001	Generic Authentication using an IMPLEMENTATION DEFINED algorithm is implemented. This includesinvolves the PACGA instruction.

All other values are reserved.

From Armv8.3, the permitted values are 0b0000 and 0b0001.

If the value of ID_AA64ISAR1_EL1.GPA is non-zero, this field must have the value 0b0000.

GPA, bits [27:24]

From Armv8.3:

Indicates whether QARMA or Architected algorithm is implemented in the PE for generic code authentication, in AArch64 state. Defined values are:

Otherwise:
GPA, bits [27:24]

Indicates whether QARMA or Architected algorithm is implemented in the PE for generic code authentication in AArch64 state. Defined values are:

Reserved, RES0.

GPA	Meaning
0b0000	Generic Authentication using an Architected algorithm is not implemented.
0b0001	Generic Authentication using the QARMA algorithm is implemented. This includesinvolves the PACGA instruction.

All other values are reserved.

From Armv8.3, the permitted values are 0b0000 and 0b0001.

If the value of ID_AA64ISAR1_EL1.GPI is non-zero, this field must have the value 0b0000.

LRCPC, bits [23:20]

From Armv8.4:

Indicates support for weaker release consistency, RCpc based model. Defined values are:

Otherwise:
LRCPC, bits [23:20]

Indicates support for weaker release consistency, RCpc, based model. Defined values are:

Reserved, RES0.

LRCPC	Meaning
0b0000	The LDAPRLDAPUR*, LDAPURSTLUR*, and STLURLDAPR* instructions are not implemented.
0b0001	The LDAPR* instructions are implemented.
0b0010	The LDAPRLDAPUR*, LDAPURSTLUR*, and STLURLDAPR* instructions are implemented.

In Armv8.0, Armv8.1, and Armv8.2, the only permitted value is 0b0000.

In Armv8.3, the only permitted value is 0b0001. ARMv8.3-RCPC implements the functionality identified by the value 0b0001.

From Armv8.4, the only permitted value is 0b0010. ARMv8.4-RCPC implements the functionality identified by the value 0b0010.

All other values are reserved.

From Armv8.3:

Indicates support for weaker release consistency, RCpc based model. Defined values are:

LRCPC	Meaning
0b0000	The LDAPRB, LDAPRH and LDAPR instructions are not implemented.
0b0001	The LDAPRB, LDAPRH and LDAPR instructions are implemented.

All other values are reserved.

ARMv8.3-RCPC implements the functionality identified by the value 0b0001.

ARMv8.4-RCPCIn implementsArmv8.0, theArmv8.1, functionalityand identifiedArmv8.2, by the only permitted value is 0b00100b0000.

In Armv8.3, the only permitted value is 0b0001.

Otherwise:

Reserved, RES0.

FCMA, bits [19:16]

From Armv8.3:

From Armv8.4, the only permitted value is 0b0010.

All other values are reserved.

FCMA, bits [19:16]

Indicates support for complex number addition and multiplication, where numbers are stored in vectors. Defined values are:

FCMA	Meaning
0b0000	The FCMLA and FCADD instructions are not implemented.
0b0001	The FCMLA and FCADD instructions are implemented.

All other values are reserved.

ARMv8.3-CompNum implements the functionality identified by the value 0b0001.

In Armv8.0, Armv8.1, and Armv8.2, the only permitted value is 0b0000.

From Armv8.3, if Advanced SIMD or Floating-point is implemented, the only permitted value is 0b0001.

Otherwise:

Reserved, RES0.

JSCVT, bits [15:12]

From Armv8.3:

Indicates support for javascript conversion from double precision floating point values to integers in AArch64 state. Defined values are:

From Armv8.3, if Advanced SIMD or Floating-point is not implemented, the only permitted value is 0b0000.

JSCVT, bits [15:12]

Indicates support for JavaScript conversion from double precision floating point values to integers in AArch64 state. Defined values are:

JSCVT	Meaning
0b0000	The FJCVTZS instruction is not implemented.
0b0001	The FJCVTZS instruction is implemented.

All other values are reserved.

ARMv8.3.JSConv implements the functionality identified by 0b0001.

In Armv8.0, Armv8.1, and Armv8.2, the only permitted value is 0b0000.

From Armv8.3, if Advanced SIMD or Floating-point is implemented, the only permitted value is 0b0001.

~~Otherwise:~~

~~Reserved, RES0.~~

~~API, bits [11:8]~~

~~From Armv8.3:~~

From Armv8.3, if Advanced SIMD or Floating-point is not implemented, the only permitted value is 0b0000.

API, bits [11:8]

Indicates whether an IMPLEMENTATION DEFINED algorithm is implemented in the PE for address authentication, in AArch64 state. This applies to all Pointer Authentication instructions other than the PACGA instruction. Defined values are:

API	Meaning
0b0000	Address Authentication using an IMPLEMENTATION DEFINED algorithm is not implemented.
0b0001	Address Authentication using an IMPLEMENTATION DEFINED algorithm is implemented, with the HaveEnhancedPAC() and HaveEnhancedPAC2() functions returning FALSE.
0b0010	Address Authentication using an IMPLEMENTATION DEFINED algorithm is implemented, with the HaveEnhancedPAC() function returning TRUE, and the HaveEnhancedPAC2() function returning FALSE.
0b0011	Address Authentication using an IMPLEMENTATION DEFINED algorithm is implemented, with the HaveEnhancedPAC2() function returning TRUE, and the HaveEnhancedPAC() function returning FALSE.
0b0100	Address Authentication using an IMPLEMENTATION DEFINED algorithm is implemented, with the HaveEnhancedPAC2() function returning TRUE, the HaveFPAC() function returning TRUE, the HaveFPACCombined() function returning FALSE, and the HaveEnhancedPAC() function returning FALSE.
0b0101	Address Authentication using an IMPLEMENTATION DEFINED algorithm is implemented, with the HaveEnhancedPAC2() function returning TRUE, the HaveFPAC() function returning TRUE, the HaveFPACCombined() function returning TRUE, and the HaveEnhancedPAC() function returning FALSE.

All other values are reserved.

ARMv8.3-PAuth implements the functionality added by the values 0b0000, 0b0001, and 0b0010.

ARMv8.3-PAuth2 implements the functionality added by the value 0b0011.

ARMv8.3-FPAC implements the functionality added by the values 0b0100 and 0b0101.

From Armv8.6, the permitted values are 0b0011, 0b0100, and 0b0101.

If the value of ID_AA64ISAR1_EL1.APA is non-zero, this field must have the value 0b0000.

~~Reserved, RES0.~~

~~APA, bits [7:4]~~

~~From Armv8.3:~~

~~Otherwise:~~
APA, bits [7:4]

Indicates whether QARMA or Architected algorithm is implemented in the PE for address authentication, in AArch64 state. This applies to all Pointer Authentication instructions other than the PACGA instruction. Defined values are:

APA	Meaning
0b0000	Address Authentication using an Architected algorithm is not implemented.
0b0001	Address Authentication using the QARMA algorithm is implemented, with the HaveEnhancedPAC() and HaveEnhancedPAC2() functions returning FALSE.
0b0010	Address Authentication using the QARMA algorithm is implemented, with the HaveEnhancedPAC() function returning TRUE and the HaveEnhancedPAC2() function returning FALSE.
0b0011	Address Authentication using the QARMA algorithm is implemented, with the HaveEnhancedPAC2() function returning TRUE, the HaveFPAC() function returning FALSE, the HaveFPACCombined() function returning FALSE, and the HaveEnhancedPAC() function returning FALSE.
0b0100	Address Authentication using the QARMA algorithm is implemented, with the HaveEnhancedPAC2() function returning TRUE, the HaveFPAC() function returning TRUE, the HaveFPACCombined() function returning FALSE, and the HaveEnhancedPAC() function returning FALSE.
0b0101	Address Authentication using the QARMA algorithm is implemented, with the HaveEnhancedPAC2() function returning TRUE, the HaveFPAC() function returning TRUE, the HaveFPACCombined() function returning TRUE, and the HaveEnhancedPAC() function returning FALSE.

All other values are reserved.

ARMv8.3-PAuth implements the functionality added by the values 0b0000, 0b0001, and 0b0010.

ARMv8.3-PAuth2 implements the functionality added by the value 0b0011.

ARMv8.3-FPAC implements the functionality added by the values 0b0100 and 0b0101.

From Armv8.6, the permitted values are 0b0011, 0b0100, and 0b0101.

If the value of the ID_AA64ISAR1_EL1.API is non-zero, this field must have the value 0b0000.

~~Reserved, RES0.~~

~~DPB, bits [3:0]~~

~~From Armv8.2:~~

~~Otherwise:~~
DPB, bits [3:0]

Data Persistence writeback. Indicates support for the DC CVAP and DC CVADP instructions in AArch64 state. Defined values are:

DPB	Meaning
0b0000	DC CVAP not supported.
0b0001	DC CVAP supported.
0b0010	DC CVAP and DC CVADP supported.

All other values are reserved.

ARMv8.2-DCPoP implements the functionality identified by the value 0b0001.

ARMv8.2-DCCVADP implements the functionality identified by the value 0b0010.

From Armv8.2 to Armv8.4, the only permitted value is 0b0001.

From Armv8.5, the only permitted value is 0b0010

Otherwise:

Reserved, RES0.

If ID_AA64ISAR1_EL1.{API, APA} == {0, 0}, then:

- The TCR_EL1.{TBID,TBID0}, TCR_EL2.{TBID0,TBID1}, TCR_EL2.TBID and TCR_EL3.TBID bits are RES0.
- APIAKeyHi_EL1, APIAKeyLo_EL1, APIBKeyHi_EL1, APIBKeyLo_EL1, APDAKeyHi_EL1, APDAKeyLo_EL1, APDBKeyHi_EL1, APDBKeyLo_EL1 are not allocated.
- SCTLR_ELx.EnIA, SCTLR_ELx.EnIB, SCTLR_ELx.EnDA, SCTLR_ELx.EnDB are all RES0.

If ID_AA64ISAR1_EL1.{GPI, GPA, API, APA} == {0, 0, 0, 0}, then:

- HCR_EL2.APK and HCR_EL2.API are RES0.
- SCR_EL3.APK and SCR_EL3.API are RES0.

Accessing the ID_AA64ISAR1_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AA64ISAR1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0110	0b001

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64ISAR1_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64ISAR1_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64ISAR1_EL1;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64MMFR0_EL1, AArch64 Memory Model Feature Register 0

The ID_AA64MMFR0_EL1 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch64 state.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

There are no configuration notes.

Attributes

ID_AA64MMFR0_EL1 is a 64-bit register.

Field descriptions

The ID_AA64MMFR0_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ECV				FGT				RES0								ExS				TGran4_2				TGran64_2				TGran16_2			
TGran4				TGran64				TGran16				BigEndEL0				SNSMem				BigEnd				ASIDBits				PARange			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

ECV, bits [63:60]

From Armv8.6:

Indicates presence Presence of Enhanced Counter Virtualization. Defined values are:

ECV	Meaning
0b0000	Enhanced Counter Virtualization is not implemented.
0b0001	Enhanced Counter Virtualization is implemented. Supports CNTHCTL_EL2.{ECV, EL1TVT, EL1TVCT, EL1NVPCT, EL1NVVCT, EVNTIS}, CNTKCTL_EL1.EVNTIS, CNTPCTSS_EL0 counter views, and CNTVCTSS_EL0 counter views. Extends the PMSCR_EL1.PCT, PMSCR_EL2.PCT, TRFCR_EL1.TS, and TRFCR_EL2.TS fields.
0b0010	As 0b0001, and also includes support for CNTHCTL_EL2.ECV and CNTPOFF_EL2.

All other values are reserved.

ARMv8.6-ECV implements the functionality identified by the values 0b0001 and 0b0010.

From Armv8.6, the only permitted values are 0b0001 and 0b0010.

FGT, bits [59:56]

From Armv8.6:

Presence of the Fine-Grained Trap controls:

Otherwise:
FGT, bits [59:56]

Indicates presence of the Fine-Grained Trap controls:

Reserved, RES0.

- HAFGRTR_EL2, HDFGRTR_EL2, HDFGWTR_EL2, HFGRTR_EL2, HFGITR_EL2 and HFGWTR_EL2 registers, and their associated traps.
- MDCR_EL2.TDCC and MDCR_EL3.TDCC.
- SCR_EL3.FGTEn.

Defined values are:

FGT	Meaning
0b0000	The fine-grained trap controls are not implemented.
0b0001	The fine-grained trap controlscontols are implemented, and can generate fine-grained traps of EL1 and EL0 functionality.

All other values are reserved.

ARMv8.6-FGT implements the functionality identified by the value 0b0001.

Otherwise:

Reserved, RES0.

From Armv8.6, the only permitted value is 0b0001.

Bits [55:48]

Reserved, RES0.

ExS, bits [47:44]

From Armv8.5:

Indicates supportSupport for disabling context synchronizing exception entry and exit. Defined values are:

ExS	Meaning
0b0000	All exception entries and exits are context synchronization events.
0b0001	Non-context synchronizing exception entry and exit are supported.

All other values are reserved.

ARMv8.5-CSEH implements the functionality identified by the value 0b0001.

TGran4_2, bits [43:40]

From Armv8.5:

Support for 4KB memory granule size for stage 2. Defined values are:

Otherwise:
TGran4_2, bits [43:40]

Indicates support for 4KB memory granule size for stage 2. Defined values are:

Reserved, RES0.

TGran4_2	Meaning
0b0000	4KB Stage 2 granule is identified in the ID_AA64MMFR0_EL1.TGran4~~TGran4~~ field.~~field~~
0b0001	4KB granule not supported at stage 2.
0b0010	4KB granule supported at stage 2.

All other values are reserved.

The 0b0000 value is deprecated.

~~TGran64_2, bits [39:36]~~

~~From Armv8.5:~~

~~Support for 64KB memory granule size for stage 2. Defined values are:~~

~~Otherwise:~~

TGran64_2, bits [39:36]

Indicates support for 64KB memory granule size for stage 2. Defined values are:

~~Reserved, RES0.~~

TGran64_2	Meaning
0b0000	64KB Stage 2 granule is identified in the ID_AA64MMFR0_EL1.TGran64~~TGran64~~ field.~~field~~
0b0001	64KB granule not supported at stage 2.
0b0010	64KB granule supported at stage 2.

All other values are reserved.

The 0b0000 value is deprecated.

~~TGran16_2, bits [35:32]~~

~~From Armv8.5:~~

~~Support for 16KB memory granule size for stage 2. Defined values are:~~

~~Otherwise:~~

TGran16_2, bits [35:32]

Indicates support for 16KB memory granule size for stage 2. Defined values are:

~~Reserved, RES0.~~

TGran16_2	Meaning
0b0000	16KB Stage 2 granule is identified in the ID_AA64MMFR0_EL1.TGran16~~TGran16~~ field
0b0001	16KB granule not supported at stage 2
0b0010	16KB granule supported at stage 2

All other values are reserved.

The 0b0000 value is deprecated.

~~Otherwise:~~

~~Reserved, RES0.~~

TGran4, bits [31:28]

Indicates support~~Support~~ for 4KB memory translation granule size. Defined values are:

TGran4	Meaning
0b0000	4KB granule supported.
0b1111	4KB granule not supported.

All other values are reserved.

TGran64, bits [27:24]

Indicates support~~Support~~ for 64KB memory translation granule size. Defined values are:

TGran64	Meaning
0b0000	64KB granule supported.
0b1111	64KB granule not supported.

All other values are reserved.

TGran16, bits [23:20]

Indicates support~~Support~~ for 16KB memory translation granule size. Defined values are:

TGran16	Meaning
0b0000	16KB granule not supported.
0b0001	16KB granule supported.

All other values are reserved.

BigEndEL0, bits [19:16]

Indicates~~Mixed-endian~~ support for mixed-endian at EL0 only. Defined values are:

BigEndEL0	Meaning
0b0000	No mixed-endian support at EL0. The SCTLR_EL1.E0E bit has a fixed value.
0b0001	Mixed-endian support at EL0. The SCTLR_EL1.E0E bit can be configured.

All other values are reserved.

This field is invalid and is RES0 if ID_AA64MMFR0_EL1.BigEnd~~the BigEnd field, bits [11:8],~~ is not 0b0000.

SNSMem, bits [15:12]

Indicates support for a distinction between Secure and~~versus~~ Non-secure Memory.~~Memory distinction.~~ Defined values are:

SNSMem	Meaning
0b0000	Does not support a distinction between Secure and Non-secure Memory.
0b0001	Does support a distinction between Secure and Non-secure Memory.

All other values are reserved.

BigEnd, bits [11:8]

Indicates~~Mixed-endian~~ support~~configuration~~ for mixed-endian configuration.~~support.~~ Defined values are:

BigEnd	Meaning
0b0000	No mixed-endian support. The SCTLR_ELx.EE bits have a fixed value. See the BigEndEL0 field, bits[19:16], for whether EL0 supports mixed-endian.
0b0001	Mixed-endian support. The SCTLR_ELx.EE and SCTLR_EL1.E0E bits can be configured.

All other values are reserved.

ASIDBits, bits [7:4]

Number of ASID bits. Defined values are:

ASIDBits	Meaning
0b0000	8 bits.
0b0010	16 bits.

All other values are reserved.

PARange, bits [3:0]

Physical Address range supported. Defined values are:

PARange	Meaning
0b0000	32 bits, 4GB.
0b0001	36 bits, 64GB.
0b0010	40 bits, 1TB.
0b0011	42 bits, 4TB.
0b0100	44 bits, 16TB.
0b0101	48 bits, 256TB.
0b0110	52 bits, 4PB.

All other values are reserved.

The value 0b0110 is permitted only if the implementation includes ARMv8.2-LPA, otherwise it is reserved.

Accessing the ID_AA64MMFR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AA64MMFR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0111	0b000

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64MMFR0_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64MMFR0_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64MMFR0_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64MMFR1_EL1, AArch64 Memory Model Feature Register 1

The ID_AA64MMFR1_EL1 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch64 state.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

There are no configuration notes.

Attributes

ID_AA64MMFR1_EL1 is a 64-bit register.

Field descriptions

The ID_AA64MMFR1_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																								ETS				TWED			
XNX				SpecSEI				PAN				LO				HPDS				VH				VMIDBits				HAFDBS			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:40]

Reserved, RES0.

ETS, bits [39:36]

From Armv8.0:

Indicates supportSupport for Enhanced Translation Synchronization. Defined values are:

ETS	Meaning
0b0000	Enhanced Translation Synchronization is not supported.
0b0001	Enhanced Translation Synchronization is supported.

All other values are reserved.

ARMv8.0-ETS implements the functionality identified by the value 0b0001.

From Armv8.0, the permitted values are 0b0000 and 0b0001.

TWED, bits [35:32]

From Armv8.6:

Support for the configurable delayed trapping of WFE. Defined values are:

Otherwise:
TWED, bits [35:32]

Indicates support for the configurable delayed trapping of WFE. Defined values are:

Reserved, RES0.

TWED	Meaning
0b0000	Configurable delayed trapping of WFE is not supported.
0b0001	Configurable delayed trapping of WFE is supported.

All other values are reserved.

ARMv8.6-TWED implements the functionality identified by the value 0b0001.

From Armv8.6, the permitted values are 0b0000 and 0b0001.

XNX, bits [31:28]

From Armv8.2:

Support for execute-never control distinction by Exception level at stage 2. Defined values are:

Otherwise:
XNX, bits [31:28]

Indicates support for execute-never control distinction by Exception level at stage 2. Defined values are:

Reserved, RES0.

XNX	Meaning
0b0000	Distinction between EL0 and EL1 execute-never control at stage 2 not supported.
0b0001	Distinction between EL0 and EL1 execute-never control at stage 2 supported.

All other values are reserved.

ARMv8.2-TTS2UXN implements the functionality identified by the value 0b0001.

From Armv8.2, the only permitted value is 0b0001.

Reserved, RES0.

SpecSEI, bits [27:24]

When RAS is implemented:

Otherwise:
SpecSEI, bits [27:24]

Describes whether the PE can generate SError interrupt exceptions from speculative reads of memory, including speculative instruction fetches. The defined values of this field are:

SpecSEI	Meaning
0b0000	The PE never generates an SError interrupt due to an External abort on a speculative read.
0b0001	The PE might generate an SError interrupt due to an External abort on a speculative read.

All other values are reserved.

Reserved, RES0. This provides no information about whether the PE generates a speculative SError interrupt.

PAN, bits [23:20]

From Armv8.1:

Otherwise:

PAN, bits [23:20]

Privileged Access Never. Indicates support for the PAN bit in PSTATE, SPSR_EL1, SPSR_EL2, SPSR_EL3, and DSPSR_EL0. Defined values are:

PAN	Meaning
0b0000	PAN not supported.
0b0001	PAN supported.
0b0010	PAN supported and AT S1E1RP and AT S1E1WP instructions supported.

All other values are reserved.

ARMv8.1-PAN implements the functionality identified by the value 0b0001.

ARMv8.2-ATS1E1 implements the functionality added by the value 0b0010.

In Armv8.1, the only permitted value is 0b0001.

From Armv8.2, the only permitted value is 0b0010.

~~Reserved, RES0.~~

LO, bits [19:16]

From Armv8.1:

Otherwise:

LO, bits [19:16]

LORegions. Indicates support for LORegions. Defined values are:

LO	Meaning
0b0000	LORegions not supported.
0b0001	LORegions supported.

All other values are reserved.

ARMv8.1-LOR implements the functionality identified by the value 0b0001.

From Armv8.1, the only permitted value is 0b0001.

HPDS, bits [15:12]

From Armv8.1:

~~Hierarchical permission disables bits in translation tables. Defined values are:~~

Otherwise:

HPDS, bits [15:12]

Hierarchical Permission Disables. Indicates support for disabling hierarchical controls in translation tables. Defined values are:

~~Reserved, RES0.~~

HPDS	Meaning
0b0000	Disabling of hierarchical controls not supported.
0b0001	Disabling of hierarchical controls supported with the TCR_EL1.{HPD1, HPD0}, TCR_EL2.HPD or TCR_EL2.{HPD1, HPD0}, and TCR_EL3.HPD bits.
0b0010	As for value 0b0001, and adds possible hardware allocation of bits[62:59] of the translation table descriptors from the final lookup level for IMPLEMENTATION DEFINED use.

All other values are reserved.

ARMv8.1-HPD implements the functionality identified by the value 0b0001.

ARMv8.2-TTPBHA implements the functionality identified by the value 0b0010.

From Armv8.1, the value 0b0000 is not permitted.

~~Reserved, RES0.~~

~~VH, bits [11:8]~~

~~From Armv8.1:~~

~~Otherwise:~~
VH, bits [11:8]

Virtualization Host Extensions. Defined values are:

VH	Meaning
0b0000	Virtualization Host Extensions not supported.
0b0001	Virtualization Host Extensions supported.

All other values are reserved.

ARMv8.1-VHE implements the functionality identified by the value 0b0001.

From Armv8.1, the only permitted value is 0b0001.

~~Reserved, RES0.~~

~~VMIDBits, bits [7:4]~~

~~From Armv8.1:~~

~~Otherwise:~~
VMIDBits, bits [7:4]

Number of VMID bits. Defined values are:

VMIDBits	Meaning
0b0000	8 bits
0b0010	16 bits

All other values are reserved.

ARMv8.1-VMID16 implements the functionality identified by the value 0b0010.

From Armv8.1, the permitted values are 0b0000 and 0b0010.

~~Reserved, RES0.~~

~~HAFDBS, bits [3:0]~~

~~From Armv8.1:~~

~~Otherwise:~~

HAFDBS, bits [3:0]

Hardware updates to Access flag and Dirty state in translation tables. Defined values are:

HAFDBS	Meaning
0b0000	Hardware update of the Access flag and dirty state are not supported.
0b0001	Hardware update of the Access flag is supported.
0b0010	Hardware update of both the Access flag and dirty state is supported.

All other values are reserved.

ARMv8.1-TTHM implements the functionality identified by the values 0b0001 and 0b0010.

From Armv8.1, the permitted values are 0b0000, 0b0001, and 0b0010.

Otherwise:

~~Reserved, RES0.~~

Accessing the ID_AA64MMFR1_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AA64MMFR1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0111	0b001

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64MMFR1_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64MMFR1_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64MMFR1_EL1;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64MMFR2_EL1, AArch64 Memory Model Feature Register 2

The ID_AA64MMFR2_EL1 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch64 state.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers'.

Configuration

This register is present only when AArch64from isArmv8.2. supported at any Exception level. Otherwise, direct accesses to ID_AA64MMFR2_EL1 are RES0.from EL1, EL2, and EL3.

RW fields in this register reset to architecturally UNKNOWN values.

Note

Prior to the introduction of the features described by this register, this register was unnamed and reserved, RES0 from EL1, EL2, and EL3.

Attributes

ID_AA64MMFR2_EL1 is a 64-bit register.

Field descriptions

The ID_AA64MMFR2_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
E0PD				EVT				BBM				TTL				RES0				FWB				IDS				AT			
ST				NV				CCIDX				VARange				IESB				LSM				UAO				CnP			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

E0PD, bits [63:60]

From Armv8.5:

Indicates support for the E0PD mechanism. Defined values are:

E0PD	Meaning
0b0000	E0PDx mechanism is not implemented.
0b0001	E0PDx mechanism is implemented.

All other values are reserved.

ARMv8.5-E0PD implements the functionality identified by the value 0b0001.

In Armv8.4, the permitted values are 0b0000 and 0b0001.

From Armv8.5, the only permitted values is 0b0001.

Reserved, RES0.

EVT, bits [59:56]

From Armv8.2:

Otherwise:
EVT, bits [59:56]

Enhanced Virtualization Traps. If EL2 is implemented, indicates support for the HCR_EL2.{TTLBOS, TTLBIS, TOCU, TICAB, TID4} traps. Defined values are:

EVT	Meaning
0b0000	HCR_EL2.{TTLBOS, TTLBIS, TOCU, TICAB, TID4} traps are not supported.
0b0001	HCR_EL2.{TOCU, TICAB, TID4} traps are supported. HCR_EL2.{TTLBOS, TTLBIS} traps are not supported.
0b0010	HCR_EL2.{TTLBOS, TTLBIS, TOCU, TICAB, TID4} traps are supported.

All other values are reserved.

ARMv8.2-EVT implements the functionality identified by the values 0b0001 and 0b0010.

If EL2 is not implemented, the only permitted value is 0b0000.

From Armv8.1, the permitted values are 0b0000 and 0b0001.

From Armv8.5, if EL2 is implemented, the only permitted valuevalues isare: 0b0010.

- 0b0000 when EL2 is not implemented.
- 0b0010 when EL2 is implemented.

Otherwise:

Reserved, RES0.

BBM, bits [55:52]

From Armv8.4:

BBM, bits [55:52]

Allows identification of the requirements of the hardware to have break-before-make sequences when changing block size for a translation.

BBM	Meaning
0b0000	Level 0 support for changing block size is supported.
0b0001	Level 1 support for changing block size is supported.
0b0010	Level 2 support for changing block size is supported.

All other values are reserved.

ARMv8.4-TTRem implements the functionality identified by the values 0b0000, 0b0001, and 0b0010.

From Armv8.4, the permitted values are 0b0000, 0b0001, and 0b0010.

Reserved, RES0.

TTL, bits [51:48]

From Armv8.4:

Otherwise:
TTL, bits [51:48]

Indicates support for TTL field in address operations. Defined values are:

TTL	Meaning
0b0000	TLB maintenance instructions by address have bits[47:44] as RES0.
0b0001	TLB maintenance instructions by address have bits[47:44] holding the TTL field.

All other values are reserved.

ARMv8.4-TTL implements the functionality identified by the value 0b0001.

This field affects TLBI IPAS2E1, TLBI IPAS2E1IS, TLBI IPAS2E1OS, TLBI IPAS2LE1, TLBI IPAS2LE1IS, TLBI IPAS2LE1OS, TLBI VAAE1, TLBI VAAE1IS, TLBI VAAE1OS, TLBI VAALE1, TLBI VAALE1IS, TLBI VAALE1OS, TLBI VAE1, TLBI VAE1IS, TLBI VAE1OS, TLBI VAE2, TLBI VAE2IS, TLBI VAE2OS, TLBI VAE3, TLBI VAE3IS, TLBI VAE3OS,TLBI VALE1, TLBI VALE1IS, TLBI VALE1OS, TLBI VALE2, TLBI VALE2IS, TLBI VALE2OS, TLBI VALE3, TLBI VALE3IS, TLBI VALE3OS.

From Armv8.4, the only permitted value is 0b0001.

Otherwise:

Reserved, RES0.

Bits [47:44]

Reserved, RES0.

FWB, bits [43:40]

From Armv8.4:

Indicates support for HCR_EL2.FWB. Defined values are:FWB

FWB	Meaning
0b0000	HCR_EL2.FWB bit is not supported. HCR_EL2.FWB bit is not supported and the field is RES0
0b0001	HCR_EL2.FWB is supported.

If ARMv8.4-SecEL2 is implemented the only permitted value is 0b0001

All other values reserved.

ARMv8.4-S2FWB implementsThis thefield functionalityresets identifiedto byan the valuearchitecturally 0b0001UNKNOWN.value.

Otherwise:

Reserved, RES0.

IDS, bits [39:36]

From Armv8.4:

From Armv8.4, the only permitted value is 0b0001.

IDS, bits [39:36]

Indicates the value of ESR_ELx.EC that reports an exception generated by a read access to the feature ID space. Defined values are:

IDS	Meaning
0b0000	An exception which is generated by a read access to the feature ID space, other than a trap caused by HCR_EL2.TIDx, SCTLR_EL1.UCT, or SCTLR_EL2.UCT, is reported by ESR_ELx.EC == 0x0.
0b0001	All exceptions generated by an AArch64 read access to the feature ID space are reported by ESR_ELx.EC == 0x18.

All other values are reserved.

The Feature ID space is defined as the System register space in AArch64 with op0==3, op1=={0, 1, 3}, CRn==0, CRm=={0-7}, op2=={0-7}.

ARMv8.4-IDST implements the functionality identified by the value 0b0001.

From Armv8.4, the only permitted value is 0b0001.

~~Reserved, RES0.~~

~~AT, bits [35:32]~~

~~From Armv8.4:~~

~~Otherwise:~~
AT, bits [35:32]

Identifies support for unaligned single-copy atomicity and atomic functions. Defined values are:

AT	Meaning
0b0000	Unaligned single-copy atomicity and atomic functions are not supported.
0b0001	Unaligned single-copy atomicity and atomic functions with a 16-byte address range aligned to 16-bytes are supported.

All other values are reserved.

ARMv8.4-LSE implements the functionality identified by the value 0b0001.

From Armv8.4, the only permitted value is 0b0001.

~~Reserved, RES0.~~

~~ST, bits [31:28]~~

~~From Armv8.4:~~

~~Otherwise:~~
ST, bits [31:28]

Identifies support for small translation tables. Defined values are:

ST	Meaning
0b0000	The maximum value of the TCR_ELx.{T0SZ,T1SZ} and VTCR_EL2.T0SZ fields is 39.
0b0001	The maximum value of the TCR_ELx.{T0SZ,T1SZ} and VTCR_EL2.T0SZ fields is 48 for 4KB and 16KB granules, and 47 for 64KB granules.

All other values are reserved.

ARMv8.4-TTST implements the functionality identified by the value 0b0001.

~~Reserved, RES0.~~

NV, bits [27:24]

From Armv8.3:

If ARMv8.4-SecEL2 is implemented the only permitted value is ARMv8.4-SecEL2 is implemented, the only permitted value is `0b0001`.

In an implementation which does not support Secure EL2, the permitted values are ARMv8.4-SecEL2, the permitted values are `0b0000` and `0b0001`.

Otherwise:

NV, bits [27:24]

Nested Virtualization. If EL2 is implemented, indicates support for the use of nested virtualization. Defined values are:

NV	Meaning
`0b0000`	Nested virtualization is not supported.
`0b0001`	The HCR_EL2.NV, HCR_EL2.NV1, HCR_EL2.AT bits are implemented.
`0b0010`	The VNCR_EL2 register and the HCR_EL2.{AT, NV, NV1, NV2} bits are implemented.

All other values are reserved.

ARMv8.3-NV implementsIn Armv8.2, the functionalityonly identifiedpermitted byvalue the valueis `0b0001`0b0000.

In Armv8.3, the permitted values are:

- When EL2 is not implemented, `0b0000`.
- When EL2 is implemented, `0b0001`.

ARMv8.4-NV implements the functionality identified by the value `0b0010`.

The feature ARMv8.3-NV implements the functionality identified by the value `0b0001`.

In Armv8.4, the permitted values are:

- When EL2 is not implemented, `0b0000`.
- When EL2 is implemented, `0b0010`.

The feature ARMv8.4-NV implements the functionality identified by the value `0b0010`.

Otherwise:

Reserved, RES0.

CCIDX, bits [23:20]

From Armv8.3:

CCIDX, bits [23:20]

Support for the use of revised CCSIDR_EL1 register format. Defined values are:

CCIDX	Meaning
`0b0000`	32-bit format implemented for all levels of the CCSIDR_EL1.
`0b0001`	64-bit format implemented for all levels of the CCSIDR_EL1.

All other values are reserved.

This feature is identified as ARMv8.3-CCIDX implements the functionality identified by the value `0b0001`.

From Armv8.3, the permitted values are `0b0000` and `0b0001`.

Reserved, RES0.

~~VARange, bits [19:16]~~

~~From Armv8.2:~~

~~Otherwise:~~
VARange, bits [19:16]

Indicates support for a larger virtual address. Defined values are:

VARange	Meaning
0b0000	VMSAv8-64 supports 48-bit VAs.
0b0001	VMSAv8-64 supports 52-bit VAs when using the 64KB translation granule. The other translation granules support 48-bit VAs.

All other values are reserved.

ARMv8.2-LVA implements the functionality identified by the value 0b0001.

From Armv8.2, the permitted values are 0b0000 and 0b0001.

~~Reserved, RES0.~~

~~IESB, bits [15:12]~~

~~From Armv8.2:~~

~~Otherwise:~~
IESB, bits [15:12]

Indicates support for the IESB bit in the SCTLR_ELx registers. Defined values are:

IESB	Meaning
0b0000	IESB bit in the SCTLR_ELx registers is not supported.
0b0001	IESB bit in the SCTLR_ELx registers is supported.

All other values are reserved.

ARMv8.2-IESB implements the functionality identified by the value 0b0001.

~~Reserved, RES0.~~

~~LSM, bits [11:8]~~

~~From Armv8.2:~~

~~Otherwise:~~
LSM, bits [11:8]

Indicates support for LSMAOE and nTLSMD bits in SCTLR_EL1 and SCTLR_EL2. Defined values are:

LSM	Meaning
0b0000	LSMAOE and nTLSMD bits not supported.
0b0001	LSMAOE and nTLSMD bits supported.

All other values are reserved.

ARMv8.2-LSMAOC implements the functionality identified by the value 0b0001.

~~Reserved, RES0.~~

UAO, bits [7:4]

From Armv8.2:

Otherwise:
UAO, bits [7:4]

User Access Override. Defined values are:

UAO	Meaning
0b0000	UAO not supported.
0b0001	UAO supported.

All other values are reserved.

ARMv8.2-UAO implements the functionality identified by the value 0b0001.

From Armv8.2, the only permitted value is 0b0001.

CnP, bits [3:0]

From Armv8.2:

Common not Private translations. Defined values are:

Otherwise:
CnP, bits [3:0]

Indicates support for Common not Private translations. Defined values are:

Reserved, RES0.

CnP	Meaning
0b0000	Common not Private translations not supported.
0b0001	Common not Private translations supported.

All other values are reserved.

ARMv8.2-TTCNP implements the functionality identified by the value 0b0001.

From Armv8.2, the only permitted value is 0b0001.

Otherwise:

Reserved, RES0.

Accessing the ID_AA64MMFR2_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AA64MMFR2_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0111	0b010

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!IsZero(ID_AA64MMFR2_EL1) || boolean
IMPLEMENTATION_DEFINED "ID_AA64MMFR2 trapped by HCR_EL2.TID3") && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64MMFR2_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64MMFR2_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64MMFR2_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64PFR0_EL1, AArch64 Processor Feature Register 0

The ID_AA64PFR0_EL1 characteristics are:

Purpose

Provides additional information about implemented PE features in AArch64 state.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

The external register EDPFR gives information from this register.

Attributes

ID_AA64PFR0_EL1 is a 64-bit register.

Field descriptions

The ID_AA64PFR0_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CSV3				CSV2				RES0				DIT				AMU				MPAM				SEL2				SVE			
RAS				GIC				AdvSIMD				FP				EL3				EL2				EL1				EL0			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CSV3, bits [63:60]

From Armv8.5:

Speculative use of faulting data. Defined values are:

CSV3	Meaning
0b0000	This Device does not disclose whether data loaded under speculation with a permission or domain fault can be used to form an address or generate condition codes or SVE predicate values to be used by instructions newer than the load in the speculative sequence
0b0001	Data loaded under speculation with a permission or domain fault cannot be used to form an address or generate condition codes or SVE predicate values to be used by instructions newer than the load in the speculative sequence

From Armv8.5, the only permitted value is 0b0001.

All other values are reserved.

Reserved, RES0.

CSV2, bits [59:56]

From Armv8.5:

Otherwise:
CSV2, bits [59:56]

Speculative use of out of context branch targets. Defined values are:

CSV2	Meaning
0b0000	This Device does not disclose whether branch targets trained in one hardware described context can affect speculative execution in a different hardware described context.
0b0001	Branch targets trained in one hardware described context can only affect speculative execution in a different hardware described context in a hard-to-determine way. Contexts do not include the SCXTNUM_ELx register contexts, and these registers are not supported.
0b0010	Branch targets trained in one hardware described context can only affect speculative execution in a different hardware described context in a hard-to-determine way. Contexts include the SCXTNUM_ELx register contexts, and these registers are supported.

From Armv8.5 the only permitted values are 0b0001 or 0b0010.

All other values are reserved.

Otherwise:

Reserved, RES0.

Bits [55:52]

Reserved, RES0.

DIT, bits [51:48]

From Armv8.4:

Data Independent Timing. Defined values are:

DIT	Meaning
0b0000	AArch64 does not guarantee constant execution time of any instructions.
0b0001	AArch64 provides the PSTATE.DIT mechanism to guarantee constant execution time of certain instructions.

All other values are reserved.

ARMv8.4-DIT implements the functionality identified by the value 0b0001.

From Armv8.4, the only permitted value is 0b0001.

AMU, bits [47:44]

From Armv8.4:

Activity Monitors Extension. Defined values are:

Otherwise:

AMU, bits [47:44]

Indicates support for Activity Monitors Extension. Defined values are:

Reserved, RES0.

AMU	Meaning
0b0000	Activity Monitors Extension is not implemented.
0b0001	AMUv1 for Armv8.4 is implemented.
0b0010	AMUv1 for Armv8.6 is implemented. As 0b0001 and adds support for virtualization of the activity monitor event counters.

All other values are reserved.

AMUv1 implements the functionality identified by the value 0b0001.

ARMv8.6-AMU implements the functionality identified by the value 0b0010.

MPAM, bits [43:40]

From Armv8.2:

MPAM Extension. Defined values are:

Otherwise:

MPAM, bits [43:40]

Indicates support for MPAM Extension. Defined values are:

Reserved, RES0.

MPAM	Meaning
0b0000	MPAM is not implemented.
0b0001	MPAM is implemented.

All other values are reserved.

Otherwise:

Reserved, RES0.

SEL2, bits [39:36]

From Armv8.4:

MPAM implements the functionality identified by the value 0b0001.

SEL2, bits [39:36]

Secure EL2. Defined values are:

SEL2	Meaning
0b0000	Secure EL2 is not implemented.
0b0001	Secure EL2 is implemented.

All other values are reserved.

Otherwise:

Reserved, RES0.

~~SVE, bits [35:32]~~

~~From Armv8.2:~~

ARMv8.4-SecEL2 implements the functionality identified by the value 0b0001.

SVE, bits [35:32]

Scalable Vector Extension. Defined values are:

SVE	Meaning
0b0000	SVE architectural state and programmers' model are not implemented.
0b0001	SVE architectural state and programmers' model are implemented.

All other values are reserved.

If implemented, refer to ID_AA64ZFR0_EL1 for information about which SVE instructions are available.

~~Otherwise:~~

~~Reserved, RES0.~~

RAS, bits [31:28]

RAS Extension version. Defined~~The~~ ~~defined~~ values ~~of this field~~ are:

RAS	Meaning
0b0000	No RAS Extension.
0b0001	RAS Extension present.
0b0010	ARMv8.4-RAS present. As 0b0001, and adds support for: • If EL3 is implemented, ARMv8.4-DFE. • Additional ERXMISC<m>_EL1 System registers. • Additional System registers ERXPFGCDN_EL1, ERXPFGCTL_EL1, and ERXPFGF_EL1, and the SCR_EL3.FIEN and HCR_EL2.FIEN trap controls, to support the optional RAS Common Fault Injection Model Extension. Error records accessed through System registers conform to RAS System Architecture v1.1, which includes simplifications to ERR<n>STATUS and support for the optional RAS Timestamp and RAS Common Fault Injection Model Extensions.

All other values are reserved.

~~From Armv8.4, when ARMv8.4-DFE is not implemented, and ERRIDR_EL1.NUM is zero, the permitted values are IMPLEMENTATION DEFINED 0b0001 or 0b0010. Otherwise from Armv8.4 the only permitted value is 0b0010.~~

ARMv8.4-RAS implements the functionality identified by the value 0b0010.

In Armv8.0 and Armv8.1, the permitted values are 0b0000 and 0b0001.

In Armv8.2, the only permitted value is 0b0001.

From Armv8.4, when ARMv8.4-DFE is not implemented, and ERRIDR_EL1.NUM is zero, the permitted values are IMPLEMENTATION DEFINED 0b0001 or 0b0010. Otherwise from Armv8.4, the only permitted value is 0b0010.

~~In Armv8.1 and Armv8.0, the permitted values are 0b0000 and 0b0001.~~

GIC, bits [27:24]

System register GIC CPU~~interface~~ interface.~~support.~~ Defined values are:

GIC	Meaning
0b0000	GIC CPU interface system registers not implemented.
0b0001	System register interface to versions 3.0 and 4.0 of the GIC CPU interface is supported.
0b0011	System register interface to version 4.1 of the GIC CPU interface is supported.

All other values are reserved.

AdvSIMD, bits [23:20]

Advanced SIMD. Defined values are:

AdvSIMD	Meaning
0b0000	Advanced SIMD is implemented, including support for the following SISD and SIMD operations: • Integer byte, halfword, word and doubleword element operations. • Single-precision and double-precision floating-point arithmetic. • Conversions between single-precision and half-precision data types, and double-precision and half-precision data types.
0b0001	As for 0b0000, and also includes support for half-precision floating-point arithmetic.
0b1111	Advanced SIMD is not implemented.

All other values are reserved.

This field must have the same value as the FP field.

The permitted values are:

- 0b0000 in an implementation with Advanced SIMD support that does not include the ARMv8.2-FP16 extension.
- 0b0001 in an implementation with Advanced SIMD support that includes the ARMv8.2-FP16 extension.
- 0b1111 in an implementation without Advanced SIMD support.

FP, bits [19:16]

Floating-point. Defined values are:

FP	Meaning
0b0000	Floating-point is implemented, and includes support for: • Single-precision and double-precision floating-point types. • Conversions between single-precision and half-precision data types, and double-precision and half-precision data types.
0b0001	As for 0b0000, and also includes support for half-precision floating-point arithmetic.
0b1111	Floating-point is not implemented.

All other values are reserved.

This field must have the same value as the AdvSIMD field.

The permitted values are:

- 0b0000 in an implementation with floating-point support that does not include the ARMv8.2-FP16 extension.
- 0b0001 in an implementation with floating-point support that includes the ARMv8.2-FP16 extension.
- 0b1111 in an implementation without floating-point support.

EL3, bits [15:12]

EL3 Exception level handling. Defined values are:

EL3	Meaning
0b0000	EL3 is not implemented.
0b0001	EL3 can be executed in AArch64 state only.
0b0010	EL3 can be executed in either AArch64 or AArch32 state.

All other values are reserved.

EL2, bits [11:8]

EL2 Exception level handling. Defined values are:

EL2	Meaning
0b0000	EL2 is not implemented.
0b0001	EL2 can be executed in AArch64 state only.
0b0010	EL2 can be executed in either AArch64 or AArch32 state.

All other values are reserved.

EL1, bits [7:4]

EL1 Exception level handling. Defined values are:

EL1	Meaning
0b0001	EL1 can be executed in AArch64 state only.
0b0010	EL1 can be executed in either AArch64 or AArch32 state.

All other values are reserved.

EL0, bits [3:0]

EL0 Exception level handling. Defined values are:

EL0	Meaning
0b0001	EL0 can be executed in AArch64 state only.
0b0010	EL0 can be executed in either AArch64 or AArch32 state.

All other values are reserved.

Accessing the ID_AA64PFR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AA64PFR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0100	0b000

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64PFR0_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64PFR0_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64PFR0_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64PFR1_EL1, AArch64 Processor Feature Register 1

The ID_AA64PFR1_EL1 characteristics are:

Purpose

Reserved for future expansion of information about implemented PE features in AArch64 state.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

There are no configuration notes.

Attributes

ID_AA64PFR1_EL1 is a 64-bit register.

Field descriptions

The ID_AA64PFR1_EL1 bit assignments are:



Bits [63:20]

Reserved, RES0.

MPAM_frac, bits [19:16]

From Armv8.6:

MPAM Extension fractional field. Defined values are:

MPAM_frac	Meaning
0b0000	If ID_AA64PFR0_EL1.MPAM == 0b0000, MPAM Extension not implemented. If ID_AA64PFR0_EL1.MPAM == 0b0001, MPAM Extension version 1.0 is implemented.
0b0001	If ID_AA64PFR0_EL1.MPAM == 0b0000, implements MPAM version 0.1 which is like version 1.1 but reduces support for Secure PARTIDs. If ID_AA64PFR0_EL1.MPAM == 0b0001, implements MPAM extension version 1.1 and adds support for TIDR bit in MPAM2_EL2 to provide trapping of MPAMIDR_EL1 when MPAMHCR_EL2 is not present.

All other values are reserved.

RAS_frac, bits [15:12]

From Armv8.4:

RAS Extension fractional field.

Otherwise:

RAS_frac, bits [15:12]

RAS Extension fractional field. Defined values are:

Reserved, RES0.

RAS_frac	Meaning
0b0000	If ID_AA64PFR0_EL1.RAS == 0b0001, RAS Extension implemented.
0b0001	If ID_AA64PFR0_EL1.RAS == 0b0001, as 0b0000 and adds support for: • Additional ERXMISC<m>_EL1 System registers. • Additional System registers ERXPFGCDN_EL1, ERXPFGCTL_EL1, and ERXPFGF_EL1, and the SCR_EL3.FIEN and HCR_EL2.FIEN trap controls, to support the optional RAS Common Fault Injection Model Extension. Error records accessed through System registers conform to RAS System Architecture v1.1, which includes simplifications to ERR<n>STATUS, and support for the optional RAS Timestamp and RAS Common Fault Injection Model Extensions.

All other values are reserved.

This field is valid only if ID_AA64PFR0_EL1.RAS == 0b0001.

MTE, bits [11:8]

From Armv8.5:

Support for the Memory Tagging Extension.

Otherwise:

MTE, bits [11:8]

Support for the Memory Tagging Extension. Defined values are:

Reserved, RES0.

MTE	Meaning
0b0000	Memory Tagging Extension is not implemented.
0b0001	Memory Tagging Extension instructions accessible at EL0 are implemented. Instructions and System Registers defined by the extension not configurably accessible at EL0 are Unallocated and other System Register fields defined by the extension are RES0.
0b0010	Memory Tagging Extension is implemented.

All other values are reserved.

ARMv8.5-MemTag implements the functionality identified by the value 0b0001.

When ID_AA64PFR1_EL1.MTE != 0b0010:

- All register fields added to existing System registers and Special-purpose registers as part of the extension are RES0, and treated as 0.
- The following System registers are UNDEFINED:

    - GMID_EL1, GCR_EL1, RGSR_EL1, TFSRE0_EL1, and TFSR_ELx.
- The following System instructions are UNDEFINED:
    - DC CGSW, DC CIGSW, DC IGSW, DC CGDSW, DC CIGDSW, DC IGDSW, DC IGVAC, and DC IGDVAC.
- The following instructions are UNDEFINED:
    - LDGM, STGM, and STZGM.
- The Tagged memory type encoding in MAIR_ELx is UNPREDICTABLE.

~~Reserved, RES0.~~

~~SSBS, bits [7:4]~~

~~From Armv8.5:~~

~~Otherwise:~~
SSBS, bits [7:4]

Speculative Store Bypassing controls in AArch64 state. Defined values are:

SSBS	Meaning
0b0000	AArch64 provides no mechanism to control the use of Speculative Store Bypassing.
0b0001	AArch64 provides the PSTATE.SSBS mechanism to mark regions that are Speculative Store Bypass Safe.
0b0010	AArch64 provides the PSTATE.SSBS mechanism to mark regions that are Speculative Store Bypassing Safe, and the MSR and MRS instructions to directly read and write the PSTATE.SSBS field

All other values are reserved.

~~Reserved, RES0.~~

~~BT, bits [3:0]~~

~~From Armv8.5:~~

~~Otherwise:~~
BT, bits [3:0]

Branch Target Identification mechanism support in AArch64 state. Defined values are:

BT	Meaning
0b0000	The Branch Target Identification mechanism is not implemented.
0b0001	The Branch Target Identification mechanism is implemented.

All other values are reserved.

ARMv8.5-BTI implements the functionality identified by the value 0b0001.

From Armv8.5, the only permitted value is 0b0001.

~~Otherwise:~~

~~Reserved, RES0.~~

Accessing the ID_AA64PFR1_EL1

Accesses to this register use the following encodings:

MRS <Xt>, ID_AA64PFR1_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0100	0b001

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64PFR1_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64PFR1_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64PFR1_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AA64ZFR0_EL1, SVE Feature ID register 0

The ID_AA64ZFR0_EL1 characteristics are:

Purpose

Provides additional information about the implemented features of the AArch64 Scalable Vector Extension, when the ID_AA64PFR0_EL1.SVE field is not zero.

For general information about the interpretation of the ID registers see Principles of the ID scheme for fields in ID registers.

Configuration

This register is present only when SVE is implemented. Otherwise, direct accesses to ID_AA64ZFR0_EL1 are RAZ.

Note

Prior to the introduction of the features described by this register, this register was unnamed and reserved, RES0 from EL1, EL2, and EL3.

Attributes

ID_AA64ZFR0_EL1 is a 64-bit register.

Field descriptions

The ID_AA64ZFR0_EL1 bit assignments are:



Bits [63:60]

Reserved, RES0.

F64MM, bits [59:56]

~~**From Armv8.2:**~~

Indicates support for SVE FP64 double-precision floating-point matrix multiplication instructions. Defined values are:

F64MM	Meaning
0b0000	FP64 matrix multiplication and related instructions are not implemented.
0b0001	FMMLA, and LD1RO* instructions are implemented. The 128-bit element variations of TRN1, TRN2, UZP1, UZP2, ZIP1, and ZIP2 are also implemented.

All other values are reserved.

ARMv8.2-F64MM implements the functionality identified by 0b0001.

Otherwise:

Reserved, RES0.

F32MM, bits [55:52]

From Armv8.2:

From Arm v8.2, the permitted values are `0b0000` and `0b0001`.

F32MM, bits [55:52]

Indicates support for the SVE FP32 single-precision floating-point matrix multiplication instruction. Defined values are:

F32MM	Meaning
`0b0000`	FP32 matrix multiplication instruction is not implemented.
`0b0001`	FMMLA instruction is implemented.

All other values are reserved.

ARMv8.2-F32MM implements the functionality identified by `0b0001`.

Otherwise:

Reserved, RES0.

From Arm v8.2, the permitted values are `0b0000` and `0b0001`.

Bits [51:48]

Reserved, RES0.

I8MM, bits [47:44]

From Armv8.2:

Indicates support for SVE Int8 matrix multiplication instructions. Defined values are:

I8MM	Meaning
`0b0000`	Int8 matrix multiplication instructions are not implemented.
`0b0001`	SMMLA, SUDOT, UMMLA, USMMLA, and USDOT instructions are implemented.

All other values are reserved.

ARMv8.2-I8MM implements the functionality identified by `0b0001`.

When Advanced SIMD and SVE are both implemented, this field must return the same value as ID_AA64ISAR1_EL1.I8MM.

From Armv8.6, the only permitted value is `0b0001`.

Otherwise:

Reserved, RES0.

Bits [43:24]

Reserved, RES0.

BF16, bits [23:20]

From Armv8.2:

Indicates support for SVE BFloat16 instructions. Defined values are:

BF16	Meaning
0b0000	BFloat16 instructions are not implemented.
0b0001	BFCVT, BFCVTNT, BFDOT, BFMLALB, BFMLALT, and BFMMLA instructions are implemented.

All other values are reserved.

ARMv8.2-BF16 implements the functionality identified by 0b0001.

When Advanced SIMD and SVE are both implemented, this field must return the same value as ID_AA64ISAR1_EL1.BF16.

From ARMv8.6, the only permitted value is 0b0001.

Otherwise:

Reserved, RES0.

Bits [19:4]

Reserved, RES0.

SVEver, bits [3:0]

Scalable Vector Extension instruction set version. Defined values are:

SVEver	Meaning
0b0000	SVE instructions are implemented.

All other values are reserved. This field is only valid if the ID_AA64PFR0_EL1.SVE field is not zero.

Accessing the ID_AA64ZFR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AA64ZFR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0100	0b100

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!IsZero(ID_AA64ZFR0_EL1) || boolean
IMPLEMENTATION_DEFINED "ID_AA64ZFR0_EL1 trapped by HCR_EL2.TID3") && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AA64ZFR0_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AA64ZFR0_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AA64ZFR0_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AFR0_EL1, AArch32 Auxiliary Feature Register 0

The ID_AFR0_EL1 characteristics are:

Purpose

Provides information about the IMPLEMENTATION DEFINED features of the PE in AArch32 state.

Must be interpreted with the Main ID Register, MIDR_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_AFR0_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_AFR0[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_AFR0_EL1 areis UNKNOWN.

Attributes

ID_AFR0_EL1 is a 64-bit register.

Field descriptions

The ID_AFR0_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																IMPLEMENTATION DEFINED				IMPLEMENTATION DEFINED				IMPLEMENTATION DEFINED				IMPLEMENTATION DEFINED			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:16]

Reserved, RES0.

IMPLEMENTATION DEFINED, bits [15:12]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [11:8]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [7:4]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [3:0]

IMPLEMENTATION DEFINED.

Accessing the ID_AFR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_AFR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0001	0b011

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_AFR0_EL1;
elsif PSTATE.EL == EL2 then
    return ID_AFR0_EL1;
elsif PSTATE.EL == EL3 then
    return ID_AFR0_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_DFR0_EL1, AArch32 Debug Feature Register 0

The ID_DFR0_EL1 characteristics are:

Purpose

Provides top level information about the debug system in AArch32 state.

Must be interpreted with the Main ID Register, MIDR_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_DFR0_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_DFR0[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_DFR0_EL1 areis UNKNOWN.

Attributes

ID_DFR0_EL1 is a 64-bit register.

Field descriptions

The ID_DFR0_EL1 bit assignments are:



Bits [63:32]

Reserved, RES0.

TraceFilt, bits [31:28]

Armv8.4 Self-hosted Trace Extension version. Defined values are:

TraceFilt	Meaning
0b0000	Armv8.4 Self-hosted Trace Extension not implemented.
0b0001	Armv8.4 Self-hosted Trace Extension implemented.

All other values are reserved.

ARMv8.4-Trace implements the functionality added by the value 0b0001.

From Armv8.3, the permitted values are 0b0000 and 0b0001.

PerfMon, bits [27:24]

Performance Monitors Extension version.

This field does not follow the standard ID scheme, but uses the Alternative ID scheme described in 'Alternative ID scheme used for the Performance Monitors Extension version' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.1.4.

Defined values are:

PerfMon	Meaning
0b0000	Performance Monitors Extension not implemented.
0b0001	Performance Monitors Extension version 1 implemented, PMUv1.
0b0010	Performance Monitors Extension version 2 implemented, PMUv2.
0b0011	Performance Monitors Extension version 3 implemented, PMUv3.
0b0100	PMUv3 for Armv8.1. As 0b0011, and also includes support for: • Extended 16-bit PMEVTYPER<n>.evtCount field. • If EL2 is implemented, the HDCR.HPMD control bit.
0b0101	PMUv3 for Armv8.4. As 0b0100 and also includes support for the PMMIR register.
0b0110	PMUv3 for Armv8.5. As 0b0101 and also includes support for: • 64-bit event counters. • If EL2 is implemented, the HDCR.HCCD control bit. • If EL3 is implemented, the SDCR.SCCD control bit.
0b1111	IMPLEMENTATION DEFINED form of performance monitors supported, PMUv3 not supported. Arm does not recommend this value in new implementations.

ARMv8.1-PMU implements the functionality added by the value 0b0100.

ARMv8.4-PMU implements the functionality added by the value 0b0101.

ARMv8.5-PMU implements the functionality added by the value 0b0110.

All other values are reserved.

In any Armv8 implementation, the values 0b0001 and 0b0010 are not permitted.

From Armv8.1, the value 0b0011 is not permitted.

From Armv8.4, the value 0b0100 is not permitted.

From Armv8.5, the value 0b0101 is not permitted.

Note

In Armv7, the value 0b0000 can mean that PMUv1 is implemented. PMUv1 is not permitted in an Armv8 implementation.

MProfDbg, bits [23:20]

M Profile Debug. Support for memory-mapped debug model for M profile processors. Defined values are:

MProfDbg	Meaning
0b0000	Not supported.
0b0001	Support for M profile Debug architecture, with memory-mapped access.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0000.

MMapTrc	Meaning
0b0000	Not supported.
0b0001	Support for Arm trace architecture, with memory-mapped access.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

See the ETM Architecture Specification for more information.

CopTrc, bits [15:12]

Support for System registers-based trace model, using registers in the coproc == 0b1110 encoding space. Defined values are:

CopTrc	Meaning
0b0000	Not supported.
0b0001	Support for Arm trace architecture, with System registers access.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

See the ETM Architecture Specification for more information.

BitsMMapTrc, bits [19:1216]

Reserved,Memory Mapped Trace. Support for memory-mapped trace model. Defined values are: RES0.

MMapDbg, bits [11:8]

Memory Mapped Debug. Support for v7 memory-mapped debug model, for A and R profile processors.

In Armv8-A, this field is RES0.

The optional memory map defined by Armv8 is not compatible with Armv7.

CopSDbg, bits [7:4]

Support for a System registers-based Secure debug model, using registers in the coproc = 0b1110 encoding space, for an A profile processor that includes EL3.

If EL3 is not implemented and the implemented Security state is Non-secure state, this field is RES0. Otherwise, this field reads the same as bits [3:0].

CopDbg, bits [3:0]

Support for System registers-based debug model, using registers in the coproc == 0b1110 encoding space, for A and R profile processors. Defined values are:

CopDbg	Meaning
0b0000	Not supported.
0b0010	Support for Armv6, v6 Debug architecture, with System registers access.
0b0011	Support for Armv6, v6.1 Debug architecture, with System registers access.
0b0100	Support for Armv7, v7 Debug architecture, with System registers access.
0b0101	Support for Armv7, v7.1 Debug architecture, with System registers access.
0b0110	Support for Armv8 debug architecture, with System registers access.
0b0111	Support for Armv8 debug architecture, with System registers access, and Virtualization Host extensions.
0b1000	Support for Armv8.2 debug architecture.
0b1001	Support for Armv8.4 debug architecture.

All other values are reserved.

In any Armv8 implementation, the values `0b0000`, `0b0010`, `0b0011`, `0b0100`, and `0b0101` are not permitted.

If ARMv8.1-VHE is not implemented, the only permitted value is `0b0110`.

In an Armv8.0 implementation, the value `0b1000` is not permitted.

Accessing the ID_DFR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_DFR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0001	0b010

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_DFR0_EL1;
elsif PSTATE.EL == EL2 then
    return ID_DFR0_EL1;
elsif PSTATE.EL == EL3 then
    return ID_DFR0_EL1;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_DFR1_EL1, Debug Feature Register 1

The ID_DFR1_EL1 characteristics are:

Purpose

Provides top level information about the debug system in AArch32.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_DFR1_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_DFR1[31:0] .

This register is present only when from AArch32 is supported at any Exception level. Armv8.6. Otherwise, direct accesses to ID_DFR1_EL1 are RES0.

Note

Prior to the introduction of the features described by this register, this register was unnamed and reserved, RES0 from EL1, EL2, and EL3.

Attributes

ID_DFR1_EL1 is a 64-bit register.

Field descriptions

The ID_DFR1_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																												MTPMU			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:4]

Reserved, RES0.

MTPMU, bits [3:0]

From Armv8.6:

Multi-threaded PMU extension. Defined values are:

MTPMU	Meaning
0b0000	ARMv8.6-MTPMU not implemented. If PMUv3 is implemented, it is IMPLEMENTATION DEFINED whether PMEVTYPER<n>_EL0.MT are read/write or RES0.
0b0001	ARMv8.6-MTPMU implemented and PMEVTYPER<n>_EL0.MT are read/write. When ARMv8.6-MTPMU is disabled, the Effective values of PMEVTYPER<n>.MT are 0.
0b1111	ARMv8.6-MTPMU not implemented. If PMUv3 is implemented, PMEVTYPER<n>_EL0.MT are RES0.

All other values are reserved.

ARMv8.6-MTPMU implements the functionality identified by the value 0b0001.

In an Armv8.6-compliant implementation that includes PMUv3, the value 0b0000 is not permitted.

In an implementation that does not include PMUv3, the value 0b0001 is not permitted.

Otherwise:

~~Reserved, RES0.~~

Accessing the ID_DFR1_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_DFR1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0011	0b101

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!IsZero(ID_DFR1_EL1) || boolean
IMPLEMENTATION_DEFINED "ID_DFR1 trapped by HCR_EL2.TID3") && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_DFR1_EL1;
elsif PSTATE.EL == EL2 then
    return ID_DFR1_EL1;
elsif PSTATE.EL == EL3 then
    return ID_DFR1_EL1;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR0_EL1, AArch32 Instruction Set Attribute Register 0

The ID_ISAR0_EL1 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR1_EL1, ID_ISAR2_EL1, ID_ISAR3_EL1, ID_ISAR4_EL1, and ID_ISAR5_EL1.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D7.1.3.

Configuration

AArch64 System register ID_ISAR0_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_ISAR0[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_ISAR0_EL1 areis UNKNOWN.

Attributes

ID_ISAR0_EL1 is a 64-bit register.

Field descriptions

The ID_ISAR0_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0				Divide				Debug				Coproc				CmpBranch				BitField				BitCount				Swap			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:28]

Reserved, RES0.

Divide, bits [27:24]

Indicates the implemented Divide instructions. Defined values are:

Divide	Meaning
0b0000	None implemented.
0b0001	Adds SDIV and UDIV in the T32 instruction set.
0b0010	As for 0b0001, and adds SDIV and UDIV in the A32 instruction set.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0010.

Debug, bits [23:20]

Indicates the implemented Debug instructions. Defined values are:

Debug	Meaning
0b0000	None implemented.
0b0001	Adds BKPT.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

Coproc, bits [19:16]

Indicates the implemented System register access instructions. Defined values are:

Coproc	Meaning
0b0000	None implemented, except for instructions separately attributed by the architecture to provide access to AArch32 System registers and System instructions.
0b0001	Adds generic CDP, LDC, MCR, MRC, and STC.
0b0010	As for 0b0001, and adds generic CDP2, LDC2, MCR2, MRC2, and STC2.
0b0011	As for 0b0010, and adds generic MCRR and MRRC.
0b0100	As for 0b0011, and adds generic MCRR2 and MRRC2.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0000.

CmpBranch, bits [15:12]

Indicates the implemented combined Compare and Branch instructions in the T32 instruction set. Defined values are:

CmpBranch	Meaning
0b0000	None implemented.
0b0001	Adds CBNZ and CBZ.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

BitField, bits [11:8]

Indicates the implemented BitField instructions. Defined values are:

BitField	Meaning
0b0000	None implemented.
0b0001	Adds BFC, BFI, SBFX, and UBFX.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

BitCount, bits [7:4]

Indicates the implemented Bit Counting instructions. Defined values are:

BitCount	Meaning
0b0000	None implemented.
0b0001	Adds CLZ.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

Swap, bits [3:0]

Indicates the implemented Swap instructions in the A32 instruction set. Defined values are:

Swap	Meaning
0b0000	None implemented.
0b0001	Adds SWP and SWPB.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0000.

Accessing the ID_ISAR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_ISAR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_ISAR0_EL1;
elsif PSTATE.EL == EL2 then
    return ID_ISAR0_EL1;
elsif PSTATE.EL == EL3 then
    return ID_ISAR0_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR1_EL1, AArch32 Instruction Set Attribute Register 1

The ID_ISAR1_EL1 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0_EL1, ID_ISAR2_EL1, ID_ISAR3_EL1, ID_ISAR4_EL1, and ID_ISAR5_EL1.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D7.1.3.

Configuration

AArch64 System register ID_ISAR1_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_ISAR1[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_ISAR1_EL1 areis UNKNOWN.

Attributes

ID_ISAR1_EL1 is a 64-bit register.

Field descriptions

The ID_ISAR1_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
Jazelle				Interwork				Immediate				IfThen				Extend				Except_AR				Except				Endian			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

Jazelle, bits [31:28]

Indicates the implemented Jazelle extension instructions. Defined values are:

Jazelle	Meaning
0b0000	No support for Jazelle.
0b0001	Adds the BXJ instruction and the J bit in the PSR. This setting might indicate a trivial implementation of the Jazelle extension.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

Interwork, bits [27:24]

Indicates the implemented Interworking instructions. Defined values are:

Interwork	Meaning
0b0000	None implemented.
0b0001	Adds the BX instruction, and the T bit in the PSR.
0b0010	As for 0b0001, and adds the BLX instruction. PC loads have BX-like behavior.
0b0011	As for 0b0010, and guarantees that data-processing instructions in the A32 instruction set with the PC as the destination and the S bit clear have BX-like behavior.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0011.

Immediate, bits [23:20]

Indicates the implemented data-processing instructions with long immediates. Defined values are:

Immediate	Meaning
0b0000	None implemented.
0b0001	Adds: • The MOVT instruction. • The MOV instruction encodings with zero-extended 16-bit immediates. • The T32 ADD and SUB instruction encodings with zero-extended 12-bit immediates, and the other ADD, ADR, and SUB encodings cross-referenced by the pseudocode for those encodings.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

IfThen, bits [19:16]

Indicates the implemented If-Then instructions in the T32 instruction set. Defined values are:

IfThen	Meaning
0b0000	None implemented.
0b0001	Adds the IT instructions, and the IT bits in the PSRs.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

Extend, bits [15:12]

Indicates the implemented Extend instructions. Defined values are:

Extend	Meaning
0b0000	No scalar sign-extend or zero-extend instructions are implemented, where scalar instructions means non-Advanced SIMD instructions.
0b0001	Adds the SXTB, SXTH, UXTB, and UXTH instructions.
0b0010	As for 0b0001, and adds the SXTB16, SXTAB, SXTAB16, SXTAH, UXTB16, UXTAB, UXTAB16, and UXTAH instructions.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0010.

Except_AR, bits [11:8]

Indicates the implemented A and R profile exception-handling instructions. Defined values are:

Except_AR	Meaning
0b0000	None implemented.
0b0001	Adds the SRS and RFE instructions, and the A and R profile forms of the CPS instruction.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

Except, bits [7:4]

Indicates the implemented exception-handling instructions in the A32 instruction set. Defined values are:

Except	Meaning
0b0000	Not implemented. This indicates that the User bank and Exception return forms of the LDM and STM instructions are not implemented.
0b0001	Adds the LDM (exception return), LDM (user registers), and STM (user registers) instruction versions.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

Endian, bits [3:0]

Indicates the implemented Endian instructions. Defined values are:

Endian	Meaning
0b0000	None implemented.
0b0001	Adds the SETEND instruction, and the E bit in the PSRs.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

Accessing the ID_ISAR1_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_ISAR1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_ISAR1_EL1;
elsif PSTATE.EL == EL2 then
    return ID_ISAR1_EL1;
elsif PSTATE.EL == EL3 then
    return ID_ISAR1_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR2_EL1, AArch32 Instruction Set Attribute Register 2

The ID_ISAR2_EL1 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0_EL1, ID_ISAR1_EL1, ID_ISAR3_EL1, ID_ISAR4_EL1, and ID_ISAR5_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_ISAR2_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_ISAR2[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_ISAR2_EL1 areis UNKNOWN.

Attributes

ID_ISAR2_EL1 is a 64-bit register.

Field descriptions

The ID_ISAR2_EL1 bit assignments are:



Bits [63:32]

Reserved, RES0.

Reversal, bits [31:28]

Indicates the implemented Reversal instructions. Defined values are:

Reversal	Meaning
0b0000	None implemented.
0b0001	Adds the REV, REV16, and REVSH instructions.
0b0010	As for 0b0001, and adds the RBIT instruction.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

PSR_AR, bits [27:24]

Indicates the implemented A and R profile instructions to manipulate the PSR. Defined values are:

PSR_AR	Meaning
0b0000	None implemented.
0b0001	Adds the MRS and MSR instructions, and the exception return forms of data-processing instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

The exception return forms of the data-processing instructions are:

- In the A32 instruction set, data-processing instructions with the PC as the destination and the S bit set. These instructions might be affected by the WithShifts attribute.
- In the T32 instruction set, the SUBS PC,LR,#N instruction.

MultU, bits [23:20]

Indicates the implemented advanced unsigned Multiply instructions. Defined values are:

MultU	Meaning
0b0000	None implemented.
0b0001	Adds the UMULL and UMLAL instructions.
0b0010	As for 0b0001, and adds the UMAAL instruction.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

MultS, bits [19:16]

Indicates the implemented advanced signed Multiply instructions. Defined values are:

MultS	Meaning
0b0000	None implemented.
0b0001	Adds the SMULL and SMLAL instructions.
0b0010	As for 0b0001, and adds the SMLABB, SMLABT, SMLALBB, SMLALBT, SMLALTB, SMLALTT, SMLATB, SMLATT, SMLAWB, SMLAWT, SMULBB, SMULBT, SMULTB, SMULTT, SMULWB, and SMULWT instructions. Also adds the Q bit in the PSRs.
0b0011	As for 0b0010, and adds the SMLAD, SMLADX, SMLALD, SMLALDX, SMLSD, SMLSDX, SMLSLD, SMLSLDX, SMMLA, SMMLAR, SMMLS, SMMLSR, SMMUL, SMMULR, SMUAD, SMUADX, SMUSD, and SMUSDX instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0011.

Mult, bits [15:12]

Indicates the implemented additional Multiply instructions. Defined values are:

Mult	Meaning
0b0000	No additional instructions implemented. This means only MUL is implemented.
0b0001	Adds the MLA instruction.
0b0010	As for 0b0001, and adds the MLS instruction.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

MultiAccessInt, bits [11:8]

Indicates the support for interruptible multi-access instructions. Defined values are:

MultiAccessInt	Meaning
0b0000	No support. This means the LDM and STM instructions are not interruptible.
0b0001	LDM and STM instructions are restartable.
0b0010	LDM and STM instructions are continuable.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

MemHint, bits [7:4]

Indicates the implemented Memory Hint instructions. Defined values are:

MemHint	Meaning
0b0000	None implemented.
0b0001	Adds the PLD instruction.
0b0010	Adds the PLD instruction. (0b0001 and 0b0010 have identical effects.)
0b0011	As for 0b0001 (or 0b0010), and adds the PLI instruction.
0b0100	As for 0b0011, and adds the PLDW instruction.

All other values are reserved.

In Armv8-A the only permitted value is 0b0100.

LoadStore, bits [3:0]

Indicates the implemented additional load/store instructions. Defined values are:

LoadStore	Meaning
0b0000	No additional load/store instructions implemented.
0b0001	Adds the LDRD and STRD instructions.
0b0010	As for 0b0001, and adds the Load Acquire (LDAB, LDAH, LDA, LDAEXB, LDAEXH, LDAEX, LDAEXD) and Store Release (STLB, STLH, STL, STLEXB, STLEXH, STLEX, STLEXD) instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

Accessing the ID_ISAR2_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_ISAR2_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0010	0b010

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_ISAR2_EL1;
elsif PSTATE.EL == EL2 then
    return ID_ISAR2_EL1;
elsif PSTATE.EL == EL3 then
    return ID_ISAR2_EL1;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR3_EL1, AArch32 Instruction Set Attribute Register 3

The ID_ISAR3_EL1 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0_EL1, ID_ISAR1_EL1, ID_ISAR2_EL1, ID_ISAR4_EL1, and ID_ISAR5_EL1.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D7.1.3.

Configuration

AArch64 System register ID_ISAR3_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_ISAR3[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_ISAR3_EL1 areis UNKNOWN.

Attributes

ID_ISAR3_EL1 is a 64-bit register.

Field descriptions

The ID_ISAR3_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
T32EE				TrueNOP				T32Copy				TabBranch				SynchPrim				SVC				SIMD				Saturate			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

T32EE, bits [31:28]

Indicates the implemented T32EE instructions. Defined values are:

T32EE	Meaning
0b0000	None implemented.
0b0001	Adds the ENTERX and LEAVEX instructions, and modifies the load behavior to include null checking.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0000.

TrueNOP, bits [27:24]

Indicates the implemented true NOP instructions. Defined values are:

TrueNOP	Meaning
0b0000	None implemented. This means there are no NOP instructions that do not have any register dependencies.
0b0001	Adds true NOP instructions in both the T32 and A32 instruction sets. This also permits additional NOP-compatible hints.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

T32Copy, bits [23:20]

Indicates the support for T32 non flag-setting MOV instructions. Defined values are:

T32Copy	Meaning
0b0000	Not supported. This means that in the T32 instruction set, encoding T1 of the MOV (register) instruction does not support a copy from a low register to a low register.
0b0001	Adds support for T32 instruction set encoding T1 of the MOV (register) instruction, copying from a low register to a low register.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

TabBranch, bits [19:16]

Indicates the implemented Table Branch instructions in the T32 instruction set. Defined values are:

TabBranch	Meaning
0b0000	None implemented.
0b0001	Adds the TBB and TBH instructions.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

SynchPrim, bits [15:12]

Used in conjunction with ID_ISAR4.SynchPrim_frac to indicate the implemented Synchronization Primitive instructions. Defined values are:

SynchPrim	Meaning
0b0000	If SynchPrim_frac == 0b0000, no Synchronization Primitives implemented.
0b0001	If SynchPrim_frac == 0b0000, adds the LDREX and STREX instructions. If SynchPrim_frac == 0b0011, also adds the CLREX, LDREXB, STREXB, and STREXH instructions.
0b0010	If SynchPrim_frac == 0b0000, as for [0b0001, 0b0011] and also adds the LDREXD and STREXD instructions.

All other combinations of SynchPrim and SynchPrim_frac are reserved.

In Armv8-A, the only permitted value is 0b0010.

SVC, bits [11:8]

Indicates the implemented SVC instructions. Defined values are:

SVC	Meaning
0b0000	Not implemented.
0b0001	Adds the SVC instruction.

All other values are reserved.

In Armv8-A, the only permitted value is `0b0001`.

SIMD, bits [7:4]

Indicates the implemented SIMD instructions. Defined values are:

SIMD	Meaning
`0b0000`	None implemented.
`0b0001`	Adds the SSAT and USAT instructions, and the Q bit in the PSRs.
`0b0011`	As for `0b0001`, and adds the PKHBT, PKHTB, QADD16, QADD8, QASX, QSUB16, QSUB8, QSAX, SADD16, SADD8, SASX, SEL, SHADD16, SHADD8, SHASX, SHSUB16, SHSUB8, SHSAX, SSAT16, SSUB16, SSUB8, SSAX, SXTAB16, SXTB16, UADD16, UADD8, UASX, UHADD16, UHADD8, UHASX, UHSUB16, UHSUB8, UHSAX, UQADD16, UQADD8, UQASX, UQSUB16, UQSUB8, UQSAX, USAD8, USADA8, USAT16, USUB16, USUB8, USAX, UXTAB16, and UXTB16 instructions. Also adds support for the GE[3:0] bits in the PSRs.

All other values are reserved.

In Armv8-A the only permitted value is `0b0011`.

The SIMD field relates only to implemented instructions that perform SIMD operations on the general-purpose registers. In an implementation that supports floating-point and Advanced SIMD instructions, MVFR0, MVFR1, and MVFR2 give information about the implemented Advanced SIMD instructions.

Saturate, bits [3:0]

Indicates the implemented Saturate instructions. Defined values are:

Saturate	Meaning
`0b0000`	None implemented. This means no non-Advanced SIMD saturate instructions are implemented.
`0b0001`	Adds the QADD, QDADD, QDSUB, and QSUB instructions, and the Q bit in the PSRs.

All other values are reserved.

In Armv8-A, the only permitted value is `0b0001`.

Accessing the ID_ISAR3_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_ISAR3_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0010	0b011

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_ISAR3_EL1;
elsif PSTATE.EL == EL2 then
    return ID_ISAR3_EL1;
elsif PSTATE.EL == EL3 then
    return ID_ISAR3_EL1;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR4_EL1, AArch32 Instruction Set Attribute Register 4

The ID_ISAR4_EL1 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0_EL1, ID_ISAR1_EL1, ID_ISAR2_EL1, ID_ISAR3_EL1, and ID_ISAR5_EL1.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D7.1.3.

Configuration

AArch64 System register ID_ISAR4_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_ISAR4[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_ISAR4_EL1 areis UNKNOWN.

Attributes

ID_ISAR4_EL1 is a 64-bit register.

Field descriptions

The ID_ISAR4_EL1 bit assignments are:



Bits [63:32]

Reserved, RES0.

SWP_frac, bits [31:28]

Indicates support for the memory system locking the bus for SWP or SWPB instructions. Defined values are:

SWP_frac	Meaning
0b0000	SWP or SWPB instructions not implemented.
0b0001	SWP or SWPB implemented but only in a uniprocessor context. SWP and SWPB do not guarantee whether memory accesses from other masters can come between the load memory access and the store memory access of the SWP or SWPB.

All other values are reserved. This field is valid only if the ID_ISAR0.SwapSwap_instrs field is 0b0000.

In Armv8-A, the only permitted value is 0b0000.

PSR_M, bits [27:24]

Indicates the implemented M profile instructions to modify the PSRs. Defined values are:

PSR_M	Meaning
0b0000	None implemented.
0b0001	Adds the M profile forms of the CPS, MRS, and MSR instructions.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0000.

SynchPrim_frac, bits [23:20]

Used in conjunction with ID_ISAR3.SynchPrim to indicate the implemented Synchronization Primitive instructions. Possible values are:

SynchPrim_frac	Meaning
0b0000	If SynchPrim == 0b0000, no Synchronization Primitives implemented. If SynchPrim == 0b0001, adds the LDREX and STREX instructions. If SynchPrim == 0b0010, also adds the CLREX, LDREXB, LDREXH, STREXB, STREXH, LDREXD, and STREXD instructions.
0b0011	If SynchPrim == 0b0001, adds the LDREX, STREX, CLREX, LDREXB, LDREXH, STREXB, and STREXH instructions.

All other combinations of SynchPrim and SynchPrim_frac are reserved.

In Armv8-A, the only permitted value is 0b0000.

Barrier, bits [19:16]

Indicates the implemented Barrier instructions in the A32 and T32 instruction sets. Defined values are:

Barrier	Meaning
0b0000	None implemented. Barrier operations are provided only as System instructions in the (coproc==0b1111) encoding space.
0b0001	Adds the DMB, DSB, and ISB barrier instructions.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

SMC, bits [15:12]

Indicates the implemented SMC instructions. Defined values are:

SMC	Meaning
0b0000	None implemented.
0b0001	Adds the SMC instruction.

All other values are reserved.

In Armv8-A, the permitted values are 0b0001 and 0b0000.

If EL1 cannot use AArch32, then this field has the value 0b0000.

Writeback, bits [11:8]

Indicates the support for Writeback addressing modes. Defined values are:

Writeback	Meaning
0b0000	Basic support. Only the LDM, STM, PUSH, POP, SRS, and RFE instructions support writeback addressing modes. These instructions support all of their writeback addressing modes.
0b0001	Adds support for all of the writeback addressing modes.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

WithShifts, bits [7:4]

Indicates the support for instructions with shifts. Defined values are:

WithShifts	Meaning
0b0000	Nonzero shifts supported only in MOV and shift instructions.
0b0001	Adds support for shifts of loads and stores over the range LSL 0-3.
0b0011	As for 0b0001, and adds support for other constant shift options, both on load/store and other instructions.
0b0100	As for 0b0011, and adds support for register-controlled shift options.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0100.

Unpriv, bits [3:0]

Indicates the implemented unprivileged instructions. Defined values are:

Unpriv	Meaning
0b0000	None implemented. No T variant instructions are implemented.
0b0001	Adds the LDRBT, LDRT, STRBT, and STRT instructions.
0b0010	As for 0b0001, and adds the LDRHT, LDRSBT, LDRSHT, and STRHT instructions.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0010.

Accessing the ID_ISAR4_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_ISAR4_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0010	0b100

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_ISAR4_EL1;
elsif PSTATE.EL == EL2 then
    return ID_ISAR4_EL1;
elsif PSTATE.EL == EL3 then
    return ID_ISAR4_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR5_EL1, AArch32 Instruction Set Attribute Register 5

The ID_ISAR5_EL1 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0_EL1, ID_ISAR1_EL1, ID_ISAR2_EL1, ID_ISAR3_EL1, and ID_ISAR4_EL1.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D7.1.3.

Configuration

AArch64 System register ID_ISAR5_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_ISAR5[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_ISAR5_EL1 areis UNKNOWN.

Attributes

ID_ISAR5_EL1 is a 64-bit register.

Field descriptions

The ID_ISAR5_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
VCMA				RDM				RES0				CRC32				SHA2				SHA1				AES				SEVL			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

VCMA, bits [31:28]

From Armv8.3:

Indicates AArch32 support for complex number addition and multiplication where numbers are stored in vectors. Defined values are:

VCMA	Meaning
0b0000	The VCMLA and VCADD instructions are not implemented in AArch32.
0b0001	The VCMLA and VCADD instructions are implemented in AArch32.

All other values are reserved.

ARMv8.3-CompNum implements the functionality identified by 0b0001.

In Armv8.0, Armv8.1, and Armv8.2, the only permitted value is 0b0000.

From Armv8.3, the only permitted value is 0b0001.

Reserved, RES0.

RDM, bits [27:24]

From Armv8.1:

Otherwise:
RDM, bits [27:24]

Indicates whether the VQRDMLAH and VQRDMLSH instructions are implemented in AArch32 state. Defined values are:

RDM	Meaning
0b0000	No VQRDMLAH and VQRDMLSH instructions implemented.
0b0001	VQRDMLAH and VQRDMLSH instructions implemented.

All other values are reserved.

ARMv8.1-RDMA implements the functionality identified by the value 0b0001.

In Armv8.0, the only permitted value is 0b0000.

From Armv8.1, the only permitted value is 0b0001.

Otherwise:

Reserved, RES0.

Bits [23:20]

Reserved, RES0.

CRC32, bits [19:16]

Indicates whether the CRC32 instructions are implemented in AArch32 state.

CRC32	Meaning
0b0000	No CRC32 instructions implemented.
0b0001	CRC32B, CRC32H, CRC32W, CRC32CB, CRC32CH, and CRC32CW instructions implemented.

All other values are reserved.

In Armv8.0, the permitted values are 0b0000 and 0b0001.

From Armv8.1, the only permitted value is 0b0001.

SHA2, bits [15:12]

Indicates whether the SHA2 instructions are implemented in AArch32 state.

SHA2	Meaning
0b0000	No SHA2 instructions implemented.
0b0001	SHA256H, SHA256H2, SHA256SU0, and SHA256SU1 implemented.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

SHA1, bits [11:8]

Indicates whether the SHA1 instructions are implemented in AArch32 state.

SHA1	Meaning
0b0000	No SHA1 instructions implemented.
0b0001	SHA1C, SHA1P, SHA1M, SHA1H, SHA1SU0, and SHA1SU1 implemented.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

AES, bits [7:4]

Indicates whether the AES instructions are implemented in AArch32 state.

AES	Meaning
0b0000	No AES instructions implemented.
0b0001	AESE, AESD, AESMC, and AESIMC implemented.
0b0010	As for 0b0001, plus VMULL (polynomial) instructions operating on 64-bit data quantities.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0010.

SEVL, bits [3:0]

Indicates whether the SEVL instruction is implemented in AArch32 state.

SEVL	Meaning
0b0000	SEVL is implemented as a NOP.
0b0001	SEVL is implemented as Send Event Local.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

Accessing the ID_ISAR5_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_ISAR5_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0010	0b101

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_ISAR5_EL1;
elsif PSTATE.EL == EL2 then
    return ID_ISAR5_EL1;
elsif PSTATE.EL == EL3 then
    return ID_ISAR5_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR6_EL1, AArch32 Instruction Set Attribute Register 6

The ID_ISAR6_EL1 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0_EL1, ID_ISAR1_EL1, ID_ISAR2_EL1, ID_ISAR3_EL1, ID_ISAR4_EL1 and ID_ISAR5_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_ISAR6_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_ISAR6[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_ISAR6_EL1 are UNKNOWN.

This register is present only from Armv8.2. Otherwise, direct accesses to ID_ISAR6_EL1 are RES0. In an implementation that supports only AArch64 state, this register is UNKNOWN.

Note

Prior to the introduction of the features described by this register, this register was unnamed and reserved, RES0 from EL1, EL2, and EL3.

Attributes

ID_ISAR6_EL1 is a 64-bit register.

Field descriptions

The ID_ISAR6_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0				I8MM				BF16				SPECRES				SB				FHM				DP				JSCVT			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:28]

Reserved, RES0.

I8MM, bits [27:24]

From Armv8.2:

Indicates support for Advanced SIMD and floating-point Int8 matrix multiplication instructions in AArch32 state. Defined values of this field are:

I8MM	Meaning
0b0000	Int8 matrix multiplication instructions are not implemented.
0b0001	VSMMLA, VSUDOT, VUMMLA, VUSMMLA, and VUSDOT instructions are implemented.

All other values are reserved.

ARMv8.2-AA32I8MM implements the functionality identified by 0b0001.

~~Reserved, RES0.~~

~~BF16, bits [23:20]~~

~~From Armv8.2:~~

~~Otherwise:~~

BF16, bits [23:20]

Indicates support for Advanced SIMD and floating-point BFloat16 instructions in AArch32 state. Defined values are:

BF16	Meaning
0b0000	BFloat16 instructions are not implemented.
0b0001	VCVT, VCVTB, VCVTT, VDOT, VFMAL, and VMMLA instructions with BF16 operand or result types are implemented.

All other values are reserved.

ARMv8.2-AA32BF16 implements the functionality identified by 0b0001.

~~Otherwise:~~

~~Reserved, RES0.~~

SPECRES, bits [19:16]

Indicates support~~supporte~~ for Speculation invalidation instructions~~instruction~~ in AArch32 state. Defined values are:

SPECRES	Meaning
0b0000	Prediction~~CFPRCTX,~~ invalidation~~DVPRCTX, and CPPRCTX~~ instructions are not implemented.
0b0001	CFPRCTX, DVPRCTX, and CPPRCTX instructions are implemented.

All other values are reserved.

ARMv8.0-PredInv implements the functionality identified by 0b0001.

From Armv8.5, the only permitted value is 0b0001.

SB, bits [15:12]

Indicates support for the SB instruction in AArch32 state. Defined values are:

SB	Meaning
0b0000	SB instruction is not implemented.
0b0001	SB instruction is implemented.

All other values are reserved.

ARMv8.0-SB implements the functionality identified by 0b0001.

From Armv8.5, the only permitted value is 0b0001.

FHM, bits [11:8]

Indicates support for Advanced SIMD and floating-point VFMAL and VFMSL instructions in AArch32 state. Defined values are:

FHM	Meaning
0b0000	VFMAL and VMFSL instructions are not implemented.
0b0001	VFMAL and VMFSL instructions are implemented.

All other values are reserved.

~~ARMv8.2-FHM implements the functionality identified by the value 0b0001.~~

ARMv8.2-FHM implements~~In Armv8.0 and Armv8.1, the~~ functionality~~only~~ identified~~permitted~~ by~~value is 0b0001~~0b0000~~.

From~~In~~ Armv8.2, the permitted values are 0b0000 and 0b0001.

DP, bits [7:4]

Indicates ~~the~~ support for Advanced~~dot~~ SIMD and floating-point VFMAL and VFMSL~~product~~ instructions in AArch32 state. Defined values are:

DP	Meaning
0b0000	Dot~~No dot~~ product instructions are not implemented.
0b0001	UDOT~~VUDOT~~ and VSDOT instructions are implemented.

All other values are reserved.

~~In Armv8.0 and Armv8.1, the only permitted value is 0b0000.~~

ARMv8.2-DotProd implements the functionality identified by~~ the value~~ 0b0001.

In Armv8.2, the permitted values are 0b0000 and 0b0001.

~~**JSCVT, bits [3:0]**~~

~~**From Armv8.3:**~~

~~Indicates support for the Javascript conversion instruction in AArch32 state. Defined values are:~~

From Armv8.4, the only permitted value is 0b0001.

JSCVT, bits [3:0]

Indicates support for the VJCVT instruction in AArch32 state. Defined values are:

JSCVT	Meaning
0b0000	The VJCVT instruction is not implemented.
0b0001	The VJCVT instruction is implemented.

All other values are reserved.

ARMv8.3-JSConv implements the functionality identified by 0b0001.

In Armv8.0, Armv8.1, and Armv8.2, the only permitted value is 0b0000.

From Armv8.3, if Advanced SIMD or Floating-point is implemented, the only permitted value is 0b0001.

~~**Otherwise:**~~

~~Reserved, RES0.~~

From Armv8.3, if Advanced SIMD or Floating-point is not implemented, the only permitted value is 0b0000.

Accessing the ID_ISAR6_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_ISAR6_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0010	0b111

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!IsZero(ID_ISAR6_EL1) || boolean
IMPLEMENTATION_DEFINED "ID_ISAR6_EL1 trapped by HCR_EL2.TID3") && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_ISAR6_EL1;
elsif PSTATE.EL == EL2 then
    return ID_ISAR6_EL1;
elsif PSTATE.EL == EL3 then
    return ID_ISAR6_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR0_EL1, AArch32 Memory Model Feature Register 0

The ID_MMFR0_EL1 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

Must be interpreted with ID_MMFR1_EL1, ID_MMFR2_EL1, ID_MMFR3_EL1, and ID_MMFR4_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_MMFR0_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_MMFR0[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_MMFR0_EL1 areis UNKNOWN.

Attributes

ID_MMFR0_EL1 is a 64-bit register.

Field descriptions

The ID_MMFR0_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
InnerShr				FCSE				AuxReg				TCM				ShareLvl				OuterShr				PMSA				VMSA			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

InnerShr, bits [31:28]

Innermost Shareability. Indicates the innermost shareability domain implemented. Defined values are:

InnerShr	Meaning
0b0000	Implemented as Non-cacheable.
0b0001	Implemented with hardware coherency support.
0b1111	Shareability ignored.

All other values are reserved.

From Armv8 the permitted values are 0b0000, 0b0001, and 0b1111.

This field is valid only if the implementation supports two levels of shareability, as indicated by ID_MMFR0_EL1.ShareLvl having the value 0b0001.

When ID_MMFR0_EL1.ShareLvl is zero, this field is UNK. UNKNOWN.

FCSE, bits [27:24]

Indicates whether the implementation includes the FCSE. Defined values are:

FCSE	Meaning
0b0000	Not supported.
0b0001	Support for FCSE.

All other values are reserved.

From Armv8 the only permitted value is 0b0000.

AuxReg, bits [23:20]

Auxiliary Registers. Indicates support for Auxiliary registers. Defined values are:

AuxReg	Meaning
0b0000	None supported.
0b0001	Support for Auxiliary Control Register only.
0b0010	Support for Auxiliary Fault Status Registers (AIFSR and ADFSR) and Auxiliary Control Register.

All other values are reserved.

From Armv8 the only permitted value is 0b0010.

Note

Accesses to unimplemented Auxiliary registers are UNDEFINED.

TCM, bits [19:16]

Indicates support for TCMs and associated DMAs. Defined values are:

TCM	Meaning
0b0000	Not supported.
0b0001	Support is IMPLEMENTATION DEFINED. Armv7 requires this setting.
0b0010	Support for TCM only, Armv6 implementation.
0b0011	Support for TCM and DMA, Armv6 implementation.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

ShareLvl, bits [15:12]

Shareability Levels. Indicates the number of shareability levels implemented. Defined values are:

ShareLvl	Meaning
0b0000	One level of shareability implemented.
0b0001	Two levels of shareability implemented.

All other values are reserved.

From Armv8 the only permitted value is 0b0001.

OuterShr, bits [11:8]

Outermost Shareability. Indicates the outermost shareability domain implemented. Defined values are:

OuterShr	Meaning
0b0000	Implemented as Non-cacheable.
0b0001	Implemented with hardware coherency support.
0b1111	Shareability ignored.

All other values are reserved.

From Armv8 the permitted values are 0b0000, 0b0001, and 0b1111.

PMSA, bits [7:4]

Indicates support for a PMSA. Defined values are:

PMSA	Meaning
0b0000	Not supported.
0b0001	Support for IMPLEMENTATION DEFINED PMSA.
0b0010	Support for PMSAv6, with a Cache Type Register implemented.
0b0011	Support for PMSAv7, with support for memory subsections. Armv7-R profile.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

VMSA, bits [3:0]

Indicates support for a VMSA. Defined values are:

VMSA	Meaning
0b0000	Not supported.
0b0001	Support for IMPLEMENTATION DEFINED VMSA.
0b0010	Support for VMSAv6, with Cache and TLB Type Registers implemented.
0b0011	Support for VMSAv7, with support for remapping and the Access flag. Armv7-A profile.
0b0100	As for 0b0011, and adds support for the PXN bit in the Short-descriptor translation table format descriptors.
0b0101	As for 0b0100, and adds support for the Long-descriptor translation table format.

All other values are reserved.

In Armv8-A the only permitted value is 0b0101.

Accessing the ID_MMFR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_MMFR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0001	0b100

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_MMFR0_EL1;
elsif PSTATE.EL == EL2 then
    return ID_MMFR0_EL1;
elsif PSTATE.EL == EL3 then
    return ID_MMFR0_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR1_EL1, AArch32 Memory Model Feature Register 1

The ID_MMFR1_EL1 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

Must be interpreted with ID_MMFR0_EL1, ID_MMFR2_EL1, ID_MMFR3_EL1, and ID_MMFR4_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_MMFR1_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_MMFR1[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_MMFR1_EL1 areis UNKNOWN.

Attributes

ID_MMFR1_EL1 is a 64-bit register.

Field descriptions

The ID_MMFR1_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
BPred				L1TstCln				L1Uni				L1Hvd				L1UniSW				L1HvdSW				L1UniVA				L1HvdVA			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

BPred, bits [31:28]

Branch Predictor. Indicates branch predictor management requirements. Defined values are:

BPred	Meaning
0b0000	No branch predictor, or no MMU present. Implies a fixed MPU configuration.
0b0001	Branch predictor requires flushing on: • Enabling or disabling a stage of address translation. • Writing new data to instruction locations. • Writing new mappings to the translation tables. • Changes to the TTBR0, TTBR1, or TTBCR registers. • Changes to the ContextID or ASID, or to the FCSE ProcessID if this is supported.
0b0010	Branch predictor requires flushing on: • Enabling or disabling a stage of address translation. • Writing new data to instruction locations. • Writing new mappings to the translation tables. • Any change to the TTBR0, TTBR1, or TTBCR registers without a change to the corresponding ContextID or ASID, or FCSE ProcessID if this is supported.
0b0011	Branch predictor requires flushing only on writing new data to instruction locations.
0b0100	For execution correctness, branch predictor requires no flushing at any time.

All other values are reserved.

In Armv8-A the permitted values are 0b0010, 0b0011, or 0b0100. For values other than 0b0000 and 0b0100 the Arm Architecture Reference Manual, or the product documentation, might give more information about the required maintenance.

L1TstCln, bits [27:24]

Level 1 cache Test and Clean. Indicates the supported Level 1 data cache test and clean operations, for Harvard or unified cache implementations. Defined values are:

L1TstCln	Meaning
0b0000	None supported.
0b0001	Supported Level 1 data cache test and clean operations are: • Test and clean data cache.
0b0010	As for 0001, and adds: • Test, clean, and invalidate data cache.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

L1Uni, bits [23:20]

Level 1 Unified cache. Indicates the supported entire Level 1 cache maintenance operations for a unified cache implementation. Defined values are:

L1Uni	Meaning
0b0000	None supported.
0b0001	Supported entire Level 1 cache operations are: • Invalidate cache, including branch predictor if appropriate. • Invalidate branch predictor, if appropriate.
0b0010	As for 0001, and adds: • Clean cache, using a recursive model that uses the cache dirty status bit. • Clean and invalidate cache, using a recursive model that uses the cache dirty status bit.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

L1Hvd, bits [19:16]

Level 1 Harvard cache. Indicates the supported entire Level 1 cache maintenance operations for a Harvard cache implementation. Defined values are:

L1Hvd	Meaning
0b0000	None supported.
0b0001	Supported entire Level 1 cache operations are: • Invalidate instruction cache, including branch predictor if appropriate. • Invalidate branch predictor, if appropriate.
0b0010	As for 0001, and adds: • Invalidate data cache. • Invalidate data cache and instruction cache, including branch predictor if appropriate.
0b0011	As for 0010, and adds: • Clean data cache, using a recursive model that uses the cache dirty status bit. • Clean and invalidate data cache, using a recursive model that uses the cache dirty status bit.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

L1UniSW, bits [15:12]

Level 1 Unified cache by Set/Way. Indicates the supported Level 1 cache line maintenance operations by set/way, for a unified cache implementation. Defined values are:

L1UniSW	Meaning
0b0000	None supported.
0b0001	Supported Level 1 unified cache line maintenance operations by set/way are: • Clean cache line by set/way.
0b0010	As for 0001, and adds: • Clean and invalidate cache line by set/way.
0b0011	As for 0010, and adds: • Invalidate cache line by set/way.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

L1HvdSW, bits [11:8]

Level 1 Harvard cache by Set/Way. Indicates the supported Level 1 cache line maintenance operations by set/way, for a Harvard cache implementation. Defined values are:

L1HvdSW	Meaning
0b0000	None supported.
0b0001	Supported Level 1 Harvard cache line maintenance operations by set/way are: • Clean data cache line by set/way. • Clean and invalidate data cache line by set/way.
0b0010	As for 0001, and adds: • Invalidate data cache line by set/way.
0b0011	As for 0010, and adds: • Invalidate instruction cache line by set/way.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

L1UniVA, bits [7:4]

Level 1 Unified cache by Virtual Address. Indicates the supported Level 1 cache line maintenance operations by VA, for a unified cache implementation. Defined values are:

L1UniVA	Meaning
0b0000	None supported.
0b0001	Supported Level 1 unified cache line maintenance operations by VA are: • Clean cache line by VA. • Invalidate cache line by VA. • Clean and invalidate cache line by VA.
0b0010	As for 0001, and adds: • Invalidate branch predictor by VA, if branch predictor is implemented.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

L1HvdVA, bits [3:0]

Level 1 Harvard cache by Virtual Address. Indicates the supported Level 1 cache line maintenance operations by VA, for a Harvard cache implementation. Defined values are:

L1HvdVA	Meaning
0b0000	None supported.
0b0001	Supported Level 1 Harvard cache line maintenance operations by VA are: • Clean data cache line by VA. • Invalidate data cache line by VA. • Clean and invalidate data cache line by VA. • Clean instruction cache line by VA.
0b0010	As for 0001, and adds: • Invalidate branch predictor by VA, if branch predictor is implemented.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

Accessing the ID_MMFR1_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_MMFR1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0001	0b101

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_MMFR1_EL1;
elsif PSTATE.EL == EL2 then
    return ID_MMFR1_EL1;
elsif PSTATE.EL == EL3 then
    return ID_MMFR1_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR2_EL1, AArch32 Memory Model Feature Register 2

The ID_MMFR2_EL1 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

Must be interpreted with ID_MMFR0_EL1, ID_MMFR1_EL1, ID_MMFR3_EL1, and ID_MMFR4_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_MMFR2_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_MMFR2[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_MMFR2_EL1 areis UNKNOWN.

Attributes

ID_MMFR2_EL1 is a 64-bit register.

Field descriptions

The ID_MMFR2_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
HWAccFlg				WFIStall				MemBarr				UniTLB				HvdTLB				L1HvdRng				L1HvdBG				L1HvdFG			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

HWAccFlg, bits [31:28]

Hardware Access Flag. In earlier versions of the Arm Architecture, this field indicates support for a Hardware Access flag, as part of the VMSAv7 implementation. Defined values are:

HWAccFlg	Meaning
0b0000	Not supported.
0b0001	Support for VMSAv7 Access flag, updated in hardware.

All other values are reserved.

From Armv8 the only permitted value is 0b0000.

WFIStall, bits [27:24]

Wait For Interrupt Stall. Indicates the support for Wait For Interrupt (WFI) stalling. Defined values are:

WFIStall	Meaning
0b0000	Not supported.
0b0001	Support for WFI stalling.

All other values are reserved.

From Armv8 the permitted values are 0b0000 and 0b0001.

MemBarr, bits [23:20]

Memory Barrier. Indicates the supported memory barrier System instructions in the (coproc==0b1111) encoding space:

MemBarr	Meaning
0b0000	None supported.
0b0001	Supported memory barrier System instructions are: • Data Synchronization Barrier (DSB).
0b0010	As for 0001, and adds: • Instruction Synchronization Barrier (ISB). • Data Memory Barrier (DMB).

All other values are reserved.

From Armv8 the only permitted value is 0b0010.

Arm deprecates the use of these operations. ID_ISAR4.Barrier_instrs indicates the level of support for the preferred barrier instructions.

UniTLB, bits [19:16]

Unified TLB. Indicates the supported TLB maintenance operations, for a unified TLB implementation. Defined values are:

UniTLB	Meaning
0b0000	Not supported.
0b0001	Supported unified TLB maintenance operations are: • Invalidate all entries in the TLB. • Invalidate TLB entry by VA.
0b0010	As for 0001, and adds: • Invalidate TLB entries by ASID match.
0b0011	As for 0010, and adds: • Invalidate instruction TLB and data TLB entries by VA All ASID. This is a shared unified TLB operation.
0b0100	As for 0011, and adds: • Invalidate Hyp mode unified TLB entry by VA. • Invalidate entire Non-secure PL1&0 unified TLB. • Invalidate entire Hyp mode unified TLB.
0b0101	As for 0b0100, and adds the following operations: TLBIMVALIS, TLBIMVAALIS, TLBIMVALHIS, TLBIMVAL, TLBIMVAAL, TLBIMVALH.
0b0110	As for 0b0101, and adds the following operations: TLBIIPAS2IS, TLBIIPAS2LIS, TLBIIPAS2, TLBIIPAS2L.

All other values are reserved.

In Armv8-A the only permitted value is 0b0110.

HvdTLB, bits [15:12]

If the Unified TLB field (UniTLB, bits [19:16]) is not 0000, then the meaning of this field is IMPLEMENTATION DEFINED. Arm deprecates the use of this field by software.

L1HvdRng, bits [11:8]

Level 1 Harvard cache Range. Indicates the supported Level 1 cache maintenance range operations, for a Harvard cache implementation. Defined values are:

L1HvdRng	Meaning
0b0000	Not supported.
0b0001	Supported Level 1 Harvard cache maintenance range operations are: • Invalidate data cache range by VA. • Invalidate instruction cache range by VA. • Clean data cache range by VA. • Clean and invalidate data cache range by VA.

All other values are reserved.

From Armv8 the only permitted value is 0b0000.

L1HvdBG, bits [7:4]

Level 1 Harvard cache Background fetch. Indicates the supported Level 1 cache background fetch operations, for a Harvard cache implementation. When supported, background fetch operations are non-blocking operations. Defined values are:

L1HvdBG	Meaning
0b0000	Not supported.
0b0001	Supported Level 1 Harvard cache background fetch operations are: • Fetch instruction cache range by VA. • Fetch data cache range by VA.

All other values are reserved.

From Armv8 the only permitted value is 0b0000.

L1HvdFG, bits [3:0]

Level 1 Harvard cache Foreground fetch. Indicates the supported Level 1 cache foreground fetch operations, for a Harvard cache implementation. When supported, foreground fetch operations are blocking operations. Defined values are:

L1HvdFG	Meaning
0b0000	Not supported.
0b0001	Supported Level 1 Harvard cache foreground fetch operations are: • Fetch instruction cache range by VA. • Fetch data cache range by VA.

All other values are reserved.

From Armv8 the only permitted value is 0b0000.

Accessing the ID_MMFR2_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_MMFR2_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0001	0b110

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_MMFR2_EL1;
elsif PSTATE.EL == EL2 then
    return ID_MMFR2_EL1;
elsif PSTATE.EL == EL3 then
    return ID_MMFR2_EL1;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR3_EL1, AArch32 Memory Model Feature Register 3

The ID_MMFR3_EL1 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

Must be interpreted with ID_MMFR0_EL1, ID_MMFR1_EL1, ID_MMFR2_EL1, and ID_MMFR4_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_MMFR3_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_MMFR3[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_MMFR3_EL1 areis UNKNOWN.

Attributes

ID_MMFR3_EL1 is a 64-bit register.

Field descriptions

The ID_MMFR3_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
Supersec				CMemSz				CohWalk				PAN				MaintBcst				BPMaint				CMaintSW				CMaintVA			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

Supersec, bits [31:28]

Supersections. On a VMSA implementation, indicates whether Supersections are supported. Defined values are:

Supersec	Meaning
0b0000	Supersections supported.
0b1111	Supersections not supported.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b1111.

CMemSz, bits [27:24]

Cached Memory Size. Indicates the physical memory size supported by the caches. Defined values are:

CMemSz	Meaning
0b0000	4GB, corresponding to a 32-bit physical address range.
0b0001	64GB, corresponding to a 36-bit physical address range.
0b0010	1TB or more, corresponding to a 40-bit or larger physical address range.

All other values are reserved.

In Armv8-A the permitted values are 0b0000, 0b0001, and 0b0010.

CohWalk, bits [23:20]

Coherent Walk. Indicates whether Translation table updates require a clean to the Point of Unification. Defined values are:

CohWalk	Meaning
0b0000	Updates to the translation tables require a clean to the Point of Unification to ensure visibility by subsequent translation table walks.
0b0001	Updates to the translation tables do not require a clean to the Point of Unification to ensure visibility by subsequent translation table walks.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

PAN, bits [19:16]

~~From Armv8.1:~~

Privileged Access Never. Indicates support for the PAN bit in CPSR, SPSR, and DSPSR in AArch32 state. Defined values are:

PAN	Meaning
0b0000	PAN not supported.
0b0001	PAN supported.
0b0010	PAN supported and ATS1CPRP and ATS1CPWP instructions supported.

All other values are reserved.

ARMv8.1-PAN implements the functionality identified by the value 0b0001.

ARMv8.2-ATS1E1 implements the functionality added by the value 0b0010.

In Armv8.1 the value 0b0000 is not permitted.

From Armv8.2, the only permitted value is 0b0010.

~~Otherwise:~~

~~Reserved, RES0.~~

MaintBcst, bits [15:12]

Maintenance Broadcast. Indicates whether Cache, TLB, and branch predictor operations are broadcast. Defined values are:

MaintBcst	Meaning
0b0000	Cache, TLB, and branch predictor operations only affect local structures.
0b0001	Cache and branch predictor operations affect structures according to shareability and defined behavior of instructions. TLB operations only affect local structures.
0b0010	Cache, TLB, and branch predictor operations affect structures according to shareability and defined behavior of instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

BPMaint, bits [11:8]

Branch Predictor Maintenance. Indicates the supported branch predictor maintenance operations in an implementation with hierarchical cache maintenance operations. Defined values are:

BPMaint	Meaning
0b0000	None supported.
0b0001	Supported branch predictor maintenance operations are: • Invalidate all branch predictors.
0b0010	As for 0001, and adds: • Invalidate branch predictors by VA.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

CMaintSW, bits [7:4]

Cache Maintenance by Set/Way. Indicates the supported cache maintenance operations by set/way, in an implementation with hierarchical caches. Defined values are:

CMaintSW	Meaning
0b0000	None supported.
0b0001	Supported hierarchical cache maintenance instructions by set/way are: • Invalidate data cache by set/way. • Clean data cache by set/way. • Clean and invalidate data cache by set/way.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

In a unified cache implementation, the data cache maintenance operations apply to the unified caches.

CMaintVA, bits [3:0]

Cache Maintenance by Virtual Address. Indicates the supported cache maintenance operations by VA, in an implementation with hierarchical caches. Defined values are:

CMaintVA	Meaning
0b0000	None supported.
0b0001	Supported hierarchical cache maintenance operations by VA are: • Invalidate data cache by VA. • Clean data cache by VA. • Clean and invalidate data cache by VA. • Invalidate instruction cache by VA. • Invalidate all instruction cache entries.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

In a unified cache implementation, data cache maintenance operations apply to the unified caches, and the instruction cache maintenance instructions are not implemented.

Accessing the ID_MMFR3_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_MMFR3_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0001	0b111

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_MMFR3_EL1;
elsif PSTATE.EL == EL2 then
    return ID_MMFR3_EL1;
elsif PSTATE.EL == EL3 then
    return ID_MMFR3_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR4_EL1, AArch32 Memory Model Feature Register 4

The ID_MMFR4_EL1 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

Must be interpreted with ID_MMFR0_EL1, ID_MMFR1_EL1, ID_MMFR2_EL1, and ID_MMFR3_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_MMFR4_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_MMFR4[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_MMFR4_EL1 areis UNKNOWN.

Attributes

ID_MMFR4_EL1 is a 64-bit register.

Field descriptions

The ID_MMFR4_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
EVT				CCIDX				LSM				HPDS				CnP				XNX				AC2				SpecSEI			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

EVT, bits [31:28]

When ARMv8.2-EVT is implemented:

Enhanced Virtualization Traps. If EL2 is implemented, indicates support for the HCR2.{TTLBIS, TOCU, TICAB, TID4} traps. Defined values are:

EVT	Meaning
0b0000	HCR2.{TTLBIS, TOCU, TICAB, TID4} traps are not supported.
0b0001	HCR2.{TOCU, TICAB, TID4} traps are supported. HCR2.TTLBIS trap is not supported.
0b0010	HCR2.{TTLBIS, TOCU, TICAB, TID4} traps are supported.

All other values are reserved.

ARMv8.2-EVT implementsIn Armv8.0, the functionalityonly identifiedpermitted byvalue the valuesis 0b00010b0000 and 0b0010.

If EL2 is not implemented, the only permitted value is 0b0000.

From Armv8.1, the permitted values are 0b0000, 0b0001, and 0b0010.

From Armv8.1,Armv8.5 the permitted values are: 0b0000 and 0b0001.

- 0b0000 when EL2 is not implemented.
- 0b0001 when EL2 is implemented. This feature is identified as ARMv8.2-EVT.

Otherwise:

Reserved, RES0.

CCIDX, bits [27:24]

From Armv8.3:

From Armv8.5, if EL2 is implemented, the only permitted value is 0b0010.

CCIDX, bits [27:24]

Support for use of the revised CCSIDR format and the presence of the CCSIDR2 is indicated. Defined values are:

CCIDX	Meaning
0b0000	32-bit format implemented for all levels of the CCSIDR, and the CCSIDR2 register is not implemented.
0b0001	64-bit format implemented for all levels of the CCSIDR, and the CCSIDR2 register is implemented.

All other values are reserved.

ARMv8.3-CCIDX implements the functionality identified by 0b0001.

From Armv8.3, the permitted values are 0b0000 and 0b0001. This feature is identified as ARMv8.3-CCIDX.

Otherwise:

Reserved, RAZ.

LSM, bits [23:20]

From Armv8.2:

From Armv8.3, the permitted values are 0b0000 and 0b0001.

LSM, bits [23:20]

Indicates support for LSMAOE and nTLSMD bits in HSCTLR and SCTLR. Defined values are:

LSM	Meaning
0b0000	LSMAOE and nTLSMD bits not supported.
0b0001	LSMAOE and nTLSMD bits supported.

All other values are reserved.

ARMv8.2-LSMAOC implements the functionality identified by the value 0b0001.

Otherwise:

Reserved, RAZ.

HPDS, bits [19:16]

~~From Armv8.2:~~

From Armv8.2, the permitted values are `0b0000` and `0b0001`.

HPDS, bits [19:16]

Hierarchical permission disables bits in translation tables. Defined values are:

HPDS	Meaning
`0b0000`	Disabling of hierarchical controls not supported.
`0b0001`	Supports disabling of hierarchical controls using the TTBCR2.HPD0, TTBCR2.HPD1, and HTCR.HPD bits.
`0b0010`	As for value `0b0001`, and adds possible hardware allocation of bits[62:59] of the translation table descriptors from the final lookup level for IMPLEMENTATION DEFINED use.

All other values are reserved.

ARMv8.2-AA32HPD implements the functionality identified by the value `0b0001`.

ARMv8.2-TTPBHA implements the functionality added by the value `0b0010`.

Note

The value `0b0000` implies that the encoding for TTBCR2 is UNDEFINED.

~~Reserved, RAZ.~~

~~**CnP, bits [15:12]**~~

~~From Armv8.2:~~

~~Otherwise:~~
CnP, bits [15:12]

Common not Private translations. Defined values are:

CnP	Meaning
`0b0000`	Common not Private translations not supported.
`0b0001`	Common not Private translations supported.

All other values are reserved.

ARMv8.2-TTCNP implements the functionality identified by the value `0b0001`.

From Armv8.2 the only permitted value is `0b0001`.

~~Reserved, RAZ.~~

~~**XNX, bits [11:8]**~~

~~From Armv8.2:~~

~~Otherwise:~~
XNX, bits [11:8]

Support for execute-never control distinction by Exception level at stage 2. Defined values are:

XNX	Meaning
`0b0000`	Distinction between EL0 and EL1 execute-never control at stage 2 not supported.
`0b0001`	Distinction between EL0 and EL1 execute-never control at stage 2 supported.

All other values are reserved.

ARMv8.2-TTS2UXN implements the functionality identified by the value 0b0001.

When ARMv8.2-TTS2UXN is implemented:

- If all of the following conditions are true, it is IMPLEMENTATION DEFINED whether the value of ID_MMFR4_EL1.XNX is 0b0000 or 0b0001:
  - ID_AA64MMFR1_EL1.XNX ==1.
  - EL2 cannot use AArch32.
  - EL1 can use AArch32.
- If EL2 can use AArch32 then the only permitted value is 0b0001.

~~**Otherwise:**~~

~~Reserved, RAZ.~~

AC2, bits [7:4]

Indicates the extension of the ACTLR and HACTLR registers using ACTLR2 and HACTLR2. Defined values are:

AC2	Meaning
0b0000	ACTLR2 and HACTLR2 are not implemented.
0b0001	ACTLR2 and HACTLR2 are implemented.

All other values are reserved.

In Armv8.0 and Armv8.1 the permitted values are 0b0000 and 0b0001.

From Armv8.2, the only permitted value is 0b0001.

SpecSEI, bits [3:0]

~~**When RAS is implemented:**~~

Describes whether the PE can generate SError interrupt exceptions from speculative reads of memory, including speculative instruction fetches. The defined values of this field are:

SpecSEI	Meaning
0b0000	The PE never generates an SError interrupt due to an External abort on a speculative read.
0b0001	The PE might generate an SError interrupt due to an External abort on a speculative read.

All other values are reserved.

~~**Otherwise:**~~

~~Reserved, RES0. This provides no information about whether the PE generates a speculative SError interrupt.~~

Accessing the ID_MMFR4_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_MMFR4_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0010	0b110

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!IsZero(ID_MMFR4_EL1) || boolean
IMPLEMENTATION_DEFINED "ID_MMFR4_EL1 trapped by HCR_EL2.TID3") && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_MMFR4_EL1;
elsif PSTATE.EL == EL2 then
    return ID_MMFR4_EL1;
elsif PSTATE.EL == EL3 then
    return ID_MMFR4_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR5_EL1, AArch32 Memory Model Feature Register 5

The ID_MMFR5_EL1 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_MMFR5_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_MMFR5[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_MMFR5_EL1 areis UNKNOWN.

Attributes

ID_MMFR5_EL1 is a 64-bit register.

Field descriptions

The ID_MMFR5_EL1 bit assignments are:



Bits [63:4]

Reserved, RES0.

ETS, bits [3:0]

From Armv8.0:

Support for Enhanced Translation Synchronization. Defined values are:

ETS	Meaning
0b0000	Enhanced Translation Synchronization is not supported.
0b0001	Enhanced Translation Synchronization is supported.

All other values are reserved.

ARMv8.0-ETS implements the functionality identified by the value 0b0001.

From Armv8.0, the permitted values are 0b0000 and 0b0001.

Otherwise:

Reserved, RES0.

Accessing the ID_MMFR5_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_MMFR5_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0011	0b110

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!IsZero(ID_MMFR5_EL1) || boolean
IMPLEMENTATION_DEFINED "ID_MMFR5_EL1 trapped by HCR_EL2.TID3") && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_MMFR5_EL1;
elsif PSTATE.EL == EL2 then
    return ID_MMFR5_EL1;
elsif PSTATE.EL == EL3 then
    return ID_MMFR5_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_PFR0_EL1, AArch32 Processor Feature Register 0

The ID_PFR0_EL1 characteristics are:

Purpose

Gives top-level information about the instruction sets supported by the PE in AArch32 state.

Must be interpreted with ID_PFR1_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_PFR0_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_PFR0[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_PFR0_EL1 areis UNKNOWN.

Attributes

ID_PFR0_EL1 is a 64-bit register.

Field descriptions

The ID_PFR0_EL1 bit assignments are:



Bits [63:32]

Reserved, RES0.

RAS, bits [31:28]

RAS Extension version. Defined values are:

RAS	Meaning
0b0000	No RAS Extension.
0b0001	RAS Extension present.
0b0010	ARMv8.4-RAS present. As 0b0001, and adds support for additional ERXMISC<m> System registers. Error records accessed through System registers conform to RAS System Architecture v1.1, which includes simplifications to ERR<n>STATUS ,and support for the optional RAS Timestamp Extension.

All other values are reserved.

From Armv8.4, when ARMv8.4-DFE is not implemented, and ERRIDR.NUM is zero, the permitted values are IMPLEMENTATION DEFINED 0b0001 or 0b0010. Otherwise from Armv8.4 the only permitted value is 0b0010.

ARMv8.4-RAS implements the functionality identified by the value 0b0010.

In Armv8.0 and Armv8.1, the permitted values are 0b0000 and 0b0001.

In Armv8.2, the only permitted value is 0b0001.

From Armv8.4, when ARMv8.4-DFE is not implemented, and ERRIDR.NUM is zero, the permitted values are IMPLEMENTATION DEFINED 0b0001 or 0b0010. Otherwise from Armv8.4 the only permitted value is 0b0010.

~~In Armv8.1 and Armv8.0, the permitted values are 0b0000 and 0b0001.~~

DIT, bits [27:24]

~~From Armv8.4:~~

Data Independent Timing. Defined values are:

DIT	Meaning
0b0000	AArch32 does not guarantee constant execution time of any instructions.
0b0001	AArch32 provides the CPSR.DIT mechanism to guarantee constant execution time of certain instructions.

All other values are reserved.

ARMv8.4-DIT implements the functionality identified by the value 0b0001.

From Armv8.4, the only permitted value is 0b0001.

~~Reserved, RES0.~~

~~AMU, bits [23:20]~~

~~From Armv8.4:~~

~~Otherwise:~~
AMU, bits [23:20]

Activity Monitors Extension. Defined values are:

AMU	Meaning
0b0000	Activity Monitors Extension is not implemented.
0b0001	AMUv1 for Armv8.4 is implemented.
0b0010	AMUv1 for Armv8.6 is implemented. As 0b0001 and adds support for virtualization of the activity monitor event counters.

All other values are reserved.

AMUv1 implements the functionality identified by the value 0b0001.

ARMv8.6-AMU implements the functionality identified by the value 0b0010.

~~Reserved, RES0.~~

~~CSV2, bits [19:16]~~

~~From Armv8.5:~~

~~Otherwise:~~
CSV2, bits [19:16]

Speculative use of out of context branch targets. Defined values are:

CSV2	Meaning
0b0000	This Device does not disclose whether branch targets trained in one hardware described context can affect speculative execution in a different hardware described context.
0b0001	Branch targets trained in one hardware described context can only affect speculative execution in a different hardware described context in a hard-to-determine way.

~~From Armv8.5 the only permitted value is 0b0001.~~

All other values are reserved.

~~**Otherwise:**~~

~~Reserved, RES0.~~

ARMv8.0-CSV2 implements the functionality identified by 0b0001.

From Armv8.5, the only permitted value is 0b0001.

State3, bits [15:12]

T32EE instruction set support. Defined values are:

State3	Meaning
0b0000	Not implemented.
0b0001	T32EE instruction set implemented.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

State2, bits [11:8]

Jazelle extension support. Defined values are:

State2	Meaning
0b0000	Not implemented.
0b0001	Jazelle extension implemented, without clearing of JOSCR.CV on exception entry.
0b0010	Jazelle extension implemented, with clearing of JOSCR.CV on exception entry.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

State1, bits [7:4]

T32 instruction set support. Defined values are:

State1	Meaning
0b0000	T32 instruction set not implemented.
0b0001	T32 encodings before the introduction of Thumb-2 technology implemented: • All instructions are 16-bit. • A BL or BLX is a pair of 16-bit instructions. • 32-bit instructions other than BL and BLX cannot be encoded.
0b0011	T32 encodings after the introduction of Thumb-2 technology implemented, for all 16-bit and 32-bit T32 basic instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0011.

State0, bits [3:0]

A32 instruction set support. Defined values are:

State0	Meaning
0b0000	A32 instruction set not implemented.
0b0001	A32 instruction set implemented.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

Accessing the ID_PFR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_PFR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0001	0b000

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_PFR0_EL1;
elsif PSTATE.EL == EL2 then
    return ID_PFR0_EL1;
elsif PSTATE.EL == EL3 then
    return ID_PFR0_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_PFR1_EL1, AArch32 Processor Feature Register 1

The ID_PFR1_EL1 characteristics are:

Purpose

Gives information about the AArch32 programmers' model.

Must be interpreted with ID_PFR0_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_PFR1_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_PFR1[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_PFR1_EL1 areis UNKNOWN.

Attributes

ID_PFR1_EL1 is a 64-bit register.

Field descriptions

The ID_PFR1_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
GIC				Virt_frac				Sec_frac				GenTimer				Virtualization				MProgMod				Security				ProgMod			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

GIC, bits [31:28]

System register GIC CPU interface. Defined values are:

GIC	Meaning
0b0000	GIC CPU interface system registers not implemented.
0b0001	System register interface to versions 3.0 and 4.0 of the GIC CPU interface is supported.
0b0011	System register interface to version 4.1 of the GIC CPU interface is supported.

All other values are reserved.

Virt_frac, bits [27:24]

Virtualization fractional field. When the Virtualization field is 0b0000, determines the support for features from the ARMv7 Virtualization Extensions. Defined values are:

Virt_frac	Meaning
0b0000	No features from the ARMv7 Virtualization Extensions are implemented.
0b0001	The following features of the ARMv7 Virtualization Extensions are implemented: • The SCR.SIF bit, if EL3 is implemented. • The modifications to the SCR.AW and SCR.FW bits described in the Virtualization Extensions, if EL3 is implemented. • The MSR (banked register) and MRS (banked register) instructions. • The ERET instruction.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 when EL2 is implemented.
- 0b0001 when EL2 is not implemented.

This field is only valid when the value of ID_PFR1_EL1.Virtualization is 0, otherwise it holds the value 0b0000.

Note

The ID_ISAR registers do not identify whether the instructions added by the ARMv7 Virtualization Extensions are implemented.

Sec_frac, bits [23:20]

Security fractional field. When the Security field is 0b0000, determines the support for features from the ARMv7 Security Extensions. Defined values are:

Sec_frac	Meaning
0b0000	No features from the ARMv7 Security Extensions are implemented.
0b0001	The following features from the ARMv7 Security Extensions are implemented: • The VBAR register. • The TTBCR.PD0 and TTBCR.PD1 bits.
0b0010	As for 0b0001, plus the ability to access Secure or Non-secure physical memory is supported.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 when EL3 is implemented.
- 0b0001 or 0b0010 when EL3 is not implemented.

This field is only valid when the value of ID_PFR1_EL1.Security is 0, otherwise it holds the value 0b0000.

GenTimer, bits [19:16]

Generic Timer support. Defined values are:

GenTimer	Meaning
0b0000	Generic Timer is not implemented.
0b0001	Generic Timer is implemented.
0b0010	Generic Timer is implemented, and also includes support for CNTHCTL.EVNTIS and CNTKCTL.EVNTIS fields, and CNTPCTSS and CNTVCVSS counter views.

All other values are reserved.

ARMv8.6-ECV implements the functionality identified by the value 0b0010.

In Armv8.0, Armv8.1, Armv8.2, Armv8.3, Armv8.4, and Armv8.5, the only permitted value is 0b0001.

From Armv8.6, the only permitted value is 0b0010.

Virtualization, bits [15:12]

Virtualization support. Defined values are:

Virtualization	Meaning
0b0000	EL2, Hyp mode, and the HVC instruction not implemented.
0b0001	EL2, Hyp mode, the HVC instruction, and all the features described by Virt_frac == 0b0001 implemented.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 when EL2 is not implemented.
- 0b0001 when EL2 is implemented.

In an implementation that includes EL2, if EL2 cannot use AArch32 but EL1 can use AArch32 then this field has the value 0b0001.

If EL1 cannot use AArch32 then this field has the value 0b0000.

Note

The ID_ISARs do not identify whether the HVC instruction is implemented.

MProgMod, bits [11:8]

M profile programmers' model support. Defined values are:

MProgMod	Meaning
0b0000	Not supported.
0b0010	Support for two-stack programmers' model.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

Security, bits [7:4]

Security support. Defined values are:

Security	Meaning
0b0000	EL3, Monitor mode, and the SMC instruction not implemented.
0b0001	EL3, Monitor mode, the SMC instruction, and all the features described by Sec_frac == 0b0001 implemented.
0b0010	As for 0b0001, and adds the ability to set the NSACR.RFR bit. Not permitted in Armv8 as the NSACR.RFR bit is RES0.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 when EL3 is not implemented.
- 0b0001 when EL3 is implemented.

In an implementation that includes EL3, if EL3 cannot use AArch32 but EL1 can use AArch32 then this field has the value 0b0001.

If EL1 cannot use AArch32 then this field has the value 0b0000.

ProgMod, bits [3:0]

Support for the standard programmers' model for Armv4 and later. Model must support User, FIQ, IRQ, Supervisor, Abort, Undefined, and System modes. Defined values are:

ProgMod	Meaning
0b0000	Not supported.
0b0001	Supported.

All other values are reserved.

In Armv8-A the permitted values are 0b0001 and 0b0000.

If EL1 cannot use AArch32 then this field has the value 0b0000.

Accessing the ID_PFR1_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_PFR1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0001	0b001

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_PFR1_EL1;
elsif PSTATE.EL == EL2 then
    return ID_PFR1_EL1;
elsif PSTATE.EL == EL3 then
    return ID_PFR1_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_PFR2_EL1, AArch32 Processor Feature Register 2

The ID_PFR2_EL1 characteristics are:

Purpose

Gives information about the AArch32 programmers' model.

Must be interpreted with ID_PFR0_EL1 and ID_PFR1_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register ID_PFR2_EL1 bits [31:0] are architecturally mapped to AArch32 System register ID_PFR2[31:0] .

ThisIn registeran isimplementation presentthat supports only when AArch32AArch64 is supported at any Exception level. Otherwisestate, directthis accessesregister to ID_PFR2_EL1 areis UNKNOWN.

Attributes

ID_PFR2_EL1 is a 64-bit register.

Field descriptions

The ID_PFR2_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																				RAS_frac				SSBS				CSV3			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:12]

Reserved, RES0.

RAS_frac, bits [11:8]

From Armv8.4:

RAS Extension fractional field. Defined values are:

RAS_frac	Meaning
0b0000	If ID_PFR0_EL1.RAS == 0b0001, RAS Extension implemented.
0b0001	If ID_PFR0_EL1.RAS == 0b0001, as 0b0000 and adds support for additional ERXMISC<m> System registers. Error records accessed through System registers conform to RAS System Architecture v1.1, which includes simplifications to ERR<n>STATUS and support for the optional RAS Timestamp Extension.

All other values are reserved.

This field is valid only if ID_PFR0_EL1.RAS == 0b0001.

~~Reserved, RES0.~~

~~SSBS, bits [7:4]~~

~~From Armv8.5:~~

~~Otherwise:~~
SSBS, bits [7:4]

Speculative Store Bypassing controls in AArch64 state. Defined values are:

SSBS	Meaning
0b0000	AArch32 provides no mechanism to control the use of Speculative Store Bypassing.
0b0001	AArch32 provides the PSTATE.SSBS mechanism to mark regions that are Speculative Store Bypass Safe.

From Armv8.0, the permitted values are 0b0000 and 0b0001.

From Armv8.5, the only permitted value is 0b0001.

All other values are reserved.

~~Reserved, RES0.~~

~~CSV3, bits [3:0]~~

~~From Armv8.5:~~

~~Otherwise:~~
CSV3, bits [3:0]

Speculative use of faulting data. Defined values are:

CSV3	Meaning
0b0000	This Device does not disclose whether data loaded under speculation with a permission or domain fault can be used to form an address or generate condition codes or SVE predicate values to be used by instructions newer than the load in the speculative sequence
0b0001	Data loaded under speculation with a permission or domain fault cannot be used to form an address or generate condition codes or SVE predicate values to be used by instructions newer than the load in the speculative sequence

From Armv8.0, the permitted values are 0b0000 and 0b0001.

From Armv8.5, the only permitted value is 0b0001.

All other values are reserved.

~~Otherwise:~~

~~Reserved, RES0.~~

Accessing the ID_PFR2_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, ID_PFR2_EL1
```

op0	op1	CRn	CRm	op2

0b11	0b000	0b0000	0b0011	0b100

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return ID_PFR2_EL1;
elsif PSTATE.EL == EL2 then
    return ID_PFR2_EL1;
elsif PSTATE.EL == EL3 then
    return ID_PFR2_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

IFSR32_EL2, Instruction Fault Status Register (EL2)

The IFSR32_EL2 characteristics are:

Purpose

Allows access to the AArch32 IFSR register from AArch64 state only. Its value has no effect on execution in AArch64 state.

Configuration

AArch64 System register IFSR32_EL2 bits [31:0] are architecturally mapped to AArch32 System register IFSR[31:0] .

ThisIf registerEL1 is presentAArch64 only when AArch32 is supported at any Exception level. Otherwise, directthis accessesregister to IFSR32_EL2 areis UNDEFINED.

If EL2 is not implemented but EL3 is implemented, and EL1 is capable of using AArch32, then this register is not RES0.

This register has no effect if EL2 is not enabled in the current Security state.

RW fields in this register reset to architecturally UNKNOWN values.

Attributes

IFSR32_EL2 is a 64-bit register.

Field descriptions

The IFSR32_EL2 bit assignments are:

When TTBCR.EAE == 0:



Bits [63:17]

Reserved, RES0.

FnV, bit [16]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
0b0	IFAR is valid.
0b1	IFAR is not valid, and holds an UNKNOWN value.

This field is only valid for a synchronous External abort other than a synchronous External abort on a translation table walk. It is RES0 for all other Prefetch Abort exceptions.

This field resets to an architecturally UNKNOWN value.

Bits [15:13]

Reserved, RES0.

ExT, bit [12]

External abort type. This bit can be used to provide an IMPLEMENTATION DEFINED classification of External aborts.

In an implementation that does not provide any classification of External aborts, this bit is RES0.

For aborts other than External aborts this bit always returns 0.

This field resets to an architecturally UNKNOWN value.

Bit [11]

Reserved, RES0.

FS[4], bit [10]

This field is bit[4] of FS[4:0].

Fault Status bits. Bits [10] and [3:0] are interpreted together.

FS	Meaning	Applies when
0b00001	PC alignment fault.	
0b00010	Debug exception.	
0b00011	Access flag fault, level 1.	
0b00101	Translation fault, level 1.	
0b00110	Access flag fault, level 2.	
0b00111	Translation fault, level 2.	
0b01000	Synchronous External abort, not on translation table walk.	
0b01001	Domain fault, level 1.	
0b01011	Domain fault, level 2.	
0b01100	Synchronous External abort, on translation table walk, level 1.	
0b01101	Permission fault, level 1.	
0b01110	Synchronous External abort, on translation table walk, level 2.	
0b01111	Permission fault, level 2.	
0b10000	TLB conflict abort.	
0b10100	IMPLEMENTATION DEFINED fault (Lockdown fault).	
0b11001	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b11100	Synchronous parity or ECC error on translation table walk, level 1.	When RAS is not implemented
0b11110	Synchronous parity or ECC error on translation table walk, level 2.	When RAS is not implemented

All other values are reserved.

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults on a Short-descriptor translation table lookup' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

~~When the RAS Extension is implemented, 0b11001, 0b11100, and 0b11110 are reserved.~~

The FS field is split as follows:

- FS[4] is IFSR32_EL2[10].
- FS[3:0] is IFSR32_EL2[3:0].

This field resets to an architecturally UNKNOWN value.

LPAE, bit [9]

On taking a Data Abort exception, this bit is set as follows:

LPAE	Meaning
0b0	Using the Short-descriptor translation table formats.
0b1	Using the Long-descriptor translation table formats.

Hardware does not interpret this bit to determine the behavior of the memory system, and therefore software can set this bit to 0 or 1 without affecting operation.

This field resets to an architecturally UNKNOWN value.

Bits [8:4]

Reserved, RES0.

FS[3:0], bits [3:0]

This field is bits[3:0] of FS[4:0].

See FS[4] for the field description.

When TTBCR.EAE == 1:



Bits [63:17]

Reserved, RES0.

FnV, bit [16]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
0b0	IFAR is valid.
0b1	IFAR is not valid, and holds an UNKNOWN value.

This field is only valid for a synchronous External abort other than a synchronous External abort on a translation table walk. It is RES0 for all other Prefetch Abort exceptions.

This field resets to an architecturally UNKNOWN value.

Bits [15:13]

Reserved, RES0.

ExT, bit [12]

External abort type. This bit can be used to provide an IMPLEMENTATION DEFINED classification of External aborts.

In an implementation that does not provide any classification of External aborts, this bit is RES0.

For aborts other than External aborts this bit always returns 0.

This field resets to an architecturally UNKNOWN value.

Bits [11:10]

Reserved, RES0.

LPAE, bit [9]

On taking a Data Abort exception, this bit is set as follows:

LPAE	Meaning
0b0	Using the Short-descriptor translation table formats.
0b1	Using the Long-descriptor translation table formats.

Hardware does not interpret this bit to determine the behavior of the memory system, and therefore software can set this bit to 0 or 1 without affecting operation.

This field resets to an architecturally UNKNOWN value.

Bits [8:6]

Reserved, RES0.

STATUS, bits [5:0]

Fault status bits. PossibleAll valuesencodings ofnot thisshown fieldbelow are reserved:

STATUS	Meaning	Applies when
0b000000	Address size fault in translation table base register.TTBR0 or TTBR1.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk.	
0b010101	Synchronous External abort, on translation table walk, level 1.	
0b010110	Synchronous External abort, on translation table walk, level 2.	
0b010111	Synchronous External abort, on translation table walk, level 3.	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk, level 1.	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk, level 2.	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk, level 3.	When RAS is not implemented
0b100001	PC alignment fault.	
0b100010	Debug exception.	
0b110000	TLB conflict abort.	

All other values are reserved.

When the RAS Extension is implemented, `0b011000`, `0b011101`, `0b011110`, and `0b011111`, are reserved.

- ~~For a fault generated on a translation table walk, the lookup level of the walk being performed.~~
- ~~For a Translation fault, the lookup level of the translation table that gave the fault. If a fault occurs because a stage of address translation is disabled, or because the input address is outside the range specified by the appropriate base address register or registers, the fault is reported as a fault at level 1.~~
- ~~For an Access flag fault, the lookup level of the translation table that gave the fault.~~
- ~~For a Permission fault, including a Permission fault caused by hierarchical permissions, the lookup level of the final level of translation table accessed for the translation. That is, the lookup level of the translation table that returned a Block or Page descriptor.~~

For~~The~~ more information about the lookup level associated with a fault, see~~is:~~ 'The level associated with MMU faults on a Long-descriptor translation table lookup' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the IFSR32_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, IFSR32_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return IFSR32_EL2;
elsif PSTATE.EL == EL3 then
    return IFSR32_EL2;
```

```
MSR IFSR32_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    IFSR32_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    IFSR32_EL2 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MAIR_EL1, Memory Attribute Indirection Register (EL1)

The MAIR_EL1 characteristics are:

Purpose

Provides the memory attribute encodings corresponding to the possible AttrIndx values in a Long-descriptor format translation table entry for stage 1 translations at EL1.

Configuration

AArch64 System register MAIR_EL1 bits [31:0] are architecturally mapped to AArch32 System register PRRR[31:0] when TTBCR.EAE == 0.

AArch64 System register MAIR_EL1 bits [31:0] are architecturally mapped to AArch32 System register MAIR0[31:0] when TTBCR.EAE == 1.

AArch64 System register MAIR_EL1 bits [63:32] are architecturally mapped to AArch32 System register NMRR[31:0] when TTBCR.EAE == 0.

AArch64 System register MAIR_EL1 bits [63:32] are architecturally mapped to AArch32 System register MAIR1[31:0] when TTBCR.EAE == 1.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

MAIR_EL1 is a 64-bit register.

Field descriptions

The MAIR_EL1 bit assignments are:



MAIR_EL1 is permitted to be cached in a TLB.

Attr<n>, bits [8n+7:8n], for n = 0 to 7

The memory attribute encoding for an AttrIndx[2:0] entry in a Long descriptor format translation table entry, where AttrIndx[2:0] gives the value of <n> in Attr<n>.

Attr is encoded as follows:

Attr	Meaning
0b0000dd00	Device memory. See encoding of 'dd' for the type of Device memory.
0b0000ddxx, (xx != 00)	UNPREDICTABLE
0booooiiii, (oooo != 0000 and iiii != 0000)	Normal memory. See encoding of 'oooo' and 'iiii' for the type of Normal Memory.
0b11110000	Tagged Normal Memory. Inner+Outer Write-Back Non-transient~~Non-Transient~~ memory, Inner+Outer Read-Allocate, Inner+Outer Write-Allocate.
0bxxxx0000, (xxxx != 0000 and xxxx != 1111)	UNPREDICTABLE

'dd' is encoded as follows:

dd	Meaning
0b00	Device-nGnRnE memory
0b01	Device-nGnRE memory
0b10	Device-nGRE memory
0b11	Device-GRE memory

'oooo' is encoded as follows:

'oooo'	Meaning
0b0000	See encoding of Attr
0b00RW, RW not 0b00	Normal memory, Outer Write-Through Transient
0b0100	Normal memory, Outer Non-cacheable
0b01RW, RW not 0b00	Normal memory, Outer Write-Back Transient
0b10RW	Normal memory, Outer Write-Through Non-transient
0b11RW	Normal memory, Outer Write-Back Non-transient

R = Outer Read-Allocate policy, W = Outer Write-Allocate policy.

'iiii' is encoded as follows:

'iiii'	Meaning
0b0000	See encoding of Attr
0b00RW, RW not 0b00	Normal memory, Inner Write-Through Transient
0b0100	Normal memory, Inner Non-cacheable
0b01RW, RW not 0b00	Normal memory, Inner Write-Back Transient
0b10RW	Normal memory, Inner Write-Through Non-transient
0b11RW	Normal memory, Inner Write-Back Non-transient

R = Inner Read-Allocate policy, W = Inner Write-Allocate policy.

The R and W bits in 'oooo' and 'iiii' fields have the following meanings:

R or W	Meaning
0b0	No Allocate
0b1	Allocate

This field resets to an architecturally UNKNOWN value.

Accessing the MAIR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic MAIR_EL1 or MAIR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

MRS <Xt>, MAIR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.MAIR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x140];
    else
        return MAIR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return MAIR_EL2;
    else
        return MAIR_EL1;
elsif PSTATE.EL == EL3 then
    return MAIR_EL1;
```

MSR MAIR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.MAIR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x140] = X[t];
    else
        MAIR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        MAIR_EL2 = X[t];
    else
        MAIR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    MAIR_EL1 = X[t];
```

MRS <Xt>, MAIR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x140];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return MAIR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return MAIR_EL1;
    else
        UNDEFINED;
```

```
MSR MAIR_EL12, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x140] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        MAIR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        MAIR_EL1 = X[t];
    else
        UNDEFINED;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MAIR_EL2, Memory Attribute Indirection Register (EL2)

The MAIR_EL2 characteristics are:

Purpose

Provides the memory attribute encodings corresponding to the possible AttrIndx values in a Long-descriptor format translation table entry for stage 1 translations at EL2.

Configuration

AArch64 System register MAIR_EL2 bits [31:0] are architecturally mapped to AArch32 System register HMAIR0[31:0] .

AArch64 System register MAIR_EL2 bits [63:32] are architecturally mapped to AArch32 System register HMAIR1[31:0] .

If EL2 is not implemented, this register is RES0 from EL3.

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

MAIR_EL2 is a 64-bit register.

Field descriptions

The MAIR_EL2 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Attr7								Attr6								Attr5								Attr4							
Attr3								Attr2								Attr1								Attr0							
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

MAIR_EL2 is permitted to be cached in a TLB.

Attr<n>, bits [8n+7:8n], for n = 0 to 7

The memory attribute encoding for an AttrIndx[2:0] entry in a Long descriptor format translation table entry, where AttrIndx[2:0] gives the value of <n> in Attr<n>.

Attr is encoded as follows:

Attr	Meaning
0b0000dd00	Device memory. See encoding of 'dd' for the type of Device memory.
0b0000ddxx, (xx != 00)	UNPREDICTABLE
0booooiiii, (oooo != 0000 and iiii != 0000)	Normal memory. See encoding of 'oooo' and 'iiii' for the type of Normal Memory.
0b11110000	Tagged Normal Memory. Inner+Outer Write-Back Non-transient~~Non-Transient~~ memory, Inner+Outer Read-Allocate, Inner+Outer Write-Allocate.
0bxxxx0000, (xxxx != 0000 and xxxx != 1111)	UNPREDICTABLE

'dd' is encoded as follows:

dd	Meaning
0b00	Device-nGnRnE memory
0b01	Device-nGnRE memory
0b10	Device-nGRE memory
0b11	Device-GRE memory

'oooo' is encoded as follows:

'oooo'	Meaning
0b0000	See encoding of Attr
0b00RW, RW not 0b00	Normal memory, Outer Write-Through Transient
0b0100	Normal memory, Outer Non-cacheable
0b01RW, RW not 0b00	Normal memory, Outer Write-Back Transient
0b10RW	Normal memory, Outer Write-Through Non-transient
0b11RW	Normal memory, Outer Write-Back Non-transient

R = Outer Read-Allocate policy, W = Outer Write-Allocate policy.

'iiii' is encoded as follows:

'iiii'	Meaning
0b0000	See encoding of Attr
0b00RW, RW not 0b00	Normal memory, Inner Write-Through Transient
0b0100	Normal memory, Inner Non-cacheable
0b01RW, RW not 0b00	Normal memory, Inner Write-Back Transient
0b10RW	Normal memory, Inner Write-Through Non-transient
0b11RW	Normal memory, Inner Write-Back Non-transient

R = Inner Read-Allocate policy, W = Inner Write-Allocate policy.

The R and W bits in 'oooo' and 'iiii' fields have the following meanings:

R or W	Meaning
0b0	No Allocate
0b1	Allocate

This field resets to an architecturally UNKNOWN value.

Accessing the MAIR_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic MAIR_EL2 or MAIR_EL1 is~~are~~ not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

MRS <Xt>, MAIR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return MAIR_EL2;
elsif PSTATE.EL == EL3 then
    return MAIR_EL2;
```

MSR MAIR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    MAIR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    MAIR_EL2 = X[t];
```

MRS <Xt>, MAIR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.MAIR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x140];
    else
        return MAIR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return MAIR_EL2;
    else
        return MAIR_EL1;
elsif PSTATE.EL == EL3 then
    return MAIR_EL1;
```

```
MSR MAIR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.MAIR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x140] = X[t];
    else
        MAIR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        MAIR_EL2 = X[t];
    else
        MAIR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    MAIR_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MAIR_EL3, Memory Attribute Indirection Register (EL3)

The MAIR_EL3 characteristics are:

Purpose

Provides the memory attribute encodings corresponding to the possible AttrIndx values in a Long-descriptor format translation table entry for stage 1 translations at EL3.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to MAIR_EL3 are UNDEFINED.

Attributes

MAIR_EL3 is a 64-bit register.

Field descriptions

The MAIR_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Attr7								Attr6								Attr5								Attr4							
Attr3								Attr2								Attr1								Attr0							
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

MAIR_EL3 is permitted to be cached in a TLB.

Attr<n>, bits [8n+7:8n], for n = 0 to 7

The memory attribute encoding for an AttrIndx[2:0] entry in a Long descriptor format translation table entry, where AttrIndx[2:0] gives the value of <n> in Attr<n>.

Attr is encoded as follows:

Attr	Meaning
0b0000dd00	Device memory. See encoding of 'dd' for the type of Device memory.
0b0000ddxx, (xx != 00)	UNPREDICTABLE
0booooiiii, (oooo != 0000 and iiii != 0000)	Normal memory. See encoding of 'oooo' and 'iiii' for the type of Normal Memory.
0b11110000	Tagged Normal Memory. Inner+Outer Write-Back Non-transient~~Non-Transient~~ memory, Inner+Outer Read-Allocate, Inner+Outer Write-Allocate.
0bxxxx0000, (xxxx != 0000 and xxxx != 1111)	UNPREDICTABLE

'dd' is encoded as follows:

dd	Meaning
0b00	Device-nGnRnE memory
0b01	Device-nGnRE memory
0b10	Device-nGRE memory
0b11	Device-GRE memory

'oooo' is encoded as follows:

'oooo'	Meaning
0b0000	See encoding of Attr
0b00RW, RW not 0b00	Normal memory, Outer Write-Through Transient
0b0100	Normal memory, Outer Non-cacheable
0b01RW, RW not 0b00	Normal memory, Outer Write-Back Transient
0b10RW	Normal memory, Outer Write-Through Non-transient
0b11RW	Normal memory, Outer Write-Back Non-transient

R = Outer Read-Allocate policy, W = Outer Write-Allocate policy.

'iiii' is encoded as follows:

'iiii'	Meaning
0b0000	See encoding of Attr
0b00RW, RW not 0b00	Normal memory, Inner Write-Through Transient
0b0100	Normal memory, Inner Non-cacheable
0b01RW, RW not 0b00	Normal memory, Inner Write-Back Transient
0b10RW	Normal memory, Inner Write-Through Non-transient
0b11RW	Normal memory, Inner Write-Back Non-transient

R = Inner Read-Allocate policy, W = Inner Write-Allocate policy.

The R and W bits in 'oooo' and 'iiii' fields have the following meanings:

R or W	Meaning
0b0	No Allocate
0b1	Allocate

This field resets to an architecturally UNKNOWN value.

Accessing the MAIR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, MAIR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return MAIR_EL3;
```

```
MSR MAIR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    MAIR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MDCR_EL2, Monitor Debug Configuration Register (EL2)

The MDCR_EL2 characteristics are:

Purpose

Provides EL2 configuration options for self-hosted debug and the Performance Monitors Extension.

Configuration

AArch64 System register MDCR_EL2 bits [31:0] are architecturally mapped to AArch32 System register HDCR[31:0] .

If EL2 is not implemented, this register is RES0 from EL3.

This register has no effect if EL2 is not enabled in the current Security state.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

MDCR_EL2 is a 64-bit register.

Field descriptions

The MDCR_EL2 bit assignments are:



Bits [63:29]

Reserved, RES0.

MTPME, bit [28]

When ARMv8.6-MTPMU is implemented and ~~!HaveEL(~~EL3 is not implemented~~):~~

Multi-threaded PMU Enable. Enables use of the PMEVTYPER<n>_EL0.MT bits.

MTPME	Meaning
0b0	ARMv8.6-MTPMU is disabled. The Effective value of PMEVTYPER<n>_EL0.MT is zero.
0b1	PMEVTYPER<n>_EL0.MT bits not affected by this bit.

If ARMv8.6-MTPMU is disabled for any other PE in the system that has the same level 1 Affinity as the PE, it is IMPLEMENTATION DEFINED whether the PE behaves as if this bit is 0.

On a Cold reset, this field resets to 1.

Otherwise:

Reserved, RES0.

TDCC, bit [27]

When ARMv8.6-FGT is implemented:

Trap DCC. Traps use of the Debug Comms Channel at EL1 and EL0 to EL2.

TDCC	Meaning
0b0	This control does not cause any register accesses to be trapped.
0b1	If EL2 is implemented and enabled in the current Security state, accesses to the DCC registers at EL1 and EL0 generate a Trap exception to EL2, unless the access also generates a higher priority exception. Traps on the DCC data transfer registers are ignored when the PE is in Debug state.

The DCC registers trapped by this control are:

AArch64: OSDTRRX_EL1, OSDTRTX_EL1, MDCCSR_EL0, MDCCINT_EL1, and, when the PE is in Non-debug state, DBGDTR_EL0, DBGDTRRX_EL0, and DBGDTRTX_EL0.

AArch32: DBGDTRRXext, DBGDTRTXext, DBGDSCRint, DBGDCCINT, and, when the PE is in Non-debug state, DBGDTRRXint and DBGDTRTXint.

The traps are reported with EC syndrome value:

- 0x05 for trapped AArch32 MRC and MCR accesses with coproc == 0b1110.
- 0x06 for trapped AArch32 LDC to DBGDTRTXint and STC from DBGDTRRXint.
- 0x18 for trapped AArch64 MRS and MSR accesses.

When the PE is in Debug state, MDCR_EL2.TDCC does not trap any accesses to:

AArch64: DBGDTR_EL0, DBGDTRRX_EL0, and DBGDTRTX_EL0.

AArch32: DBGDTRRXint and DBGDTRTXint.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HLP, bit [26]

When ARMv8.5-PMU is implemented:

Hypervisor Long event counter enable. Determines when unsigned overflow is recorded by a counter overflow bit.

HLP	Meaning
0b0	Event counter overflow on increment that causes unsigned overflow of PMEVCNTR<n>_EL0[31:0].
0b1	Event counter overflow on increment that causes unsigned overflow of PMEVCNTR<n>_EL0[63:0].

If MDCR_EL2.HPMN is less than PMCR_EL0.N or PMCR.N, this bit affects the operation of event counters in the range [MDCR_EL2.HPMN..(PMCR_EL0.N-1)] or [MDCR_EL2.HPMN..(PMCR.N-1)]. Otherwise this bit has no effect on the operation of the event counters.

Note

The effect of MDCR_EL2.HPMN on the operation of this bit always applies if EL2 is implemented, at all Exception levels including EL2 and EL3, and regardless of whether EL2 is enabled in the current Security state.

For more information see the description of the MDCR_EL2.HPMN field.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [25:24]

Reserved, RES0.

HCCD, bit [23]

When ARMv8.5-PMU is implemented:

Hypervisor Cycle Counter Disable. Prohibits PMCCNTR_EL0 from counting at EL2.

HCCD	Meaning
0b0	Cycle counting by PMCCNTR_EL0 is not affected by this bit.
0b1	Cycle counting by PMCCNTR_EL0 is prohibited at EL2.

This bit does not affect the CPU_CYCLES event or any other event that counts cycles.

On a Warm reset, this field resets to 0.

Otherwise:

Reserved, RES0.

Bits [22:20]

Reserved, RES0.

TTRF, bit [19]

When ARMv8.4-Trace is implemented:

Traps use of the Trace Filter Control registers at EL1 to EL2, as follows:

- Access to TRFCR_EL1 is trapped to EL2, reported using EC syndrome value 0x18.
- Access to TRFCR is trapped to EL2, reported using EC syndrome value 0x03.

TTRF	Meaning
0b0	Accesses to TRFCR_EL1 and TRFCR at EL1 are not affected by this control.
0b1	Accesses to TRFCR_EL1 and TRFCR at EL1 generate a trap exception to EL2 when EL2 is enabled in the current Security state.

Otherwise:

Reserved, RES0.

Bit [18]

Reserved, RES0.

HPMD, bit [17]

When ARMv8.1-PMU is implemented:

Guest Performance Monitors Disable. This control prohibits event counting at EL2.

HPMD	Meaning
0b0	Event counting allowed at EL2.
0b1	Event counting prohibited at EL2. If ARMv8.2-Debug is not implemented, event counting is prohibited unless enabled by the IMPLEMENTATION DEFINED authentication interface ExternalSecureNoninvasiveDebugEnabled().

This control applies only to:

- The event counters in the range [0..(MDCR_EL2.HPMN-1)].
- If PMCR_EL0.DP is set to 1, PMCCNTR_EL0.

The other event counters are unaffected, and when PMCR_EL0.DP is set to 0, PMCCNTR_EL0 is unaffected.

On a Warm reset, this field resets to 0.

Otherwise:

Reserved, RES0.

Bits [16:15]

Reserved, RES0.

TPMS, bit [14]

When SPE is implemented:

Trap Performance Monitor Sampling. When EL2 is enabled in the current Security state, this field controls access to Statistical Profiling control registers from EL1.

TPMS	Meaning
0b0	Do not trap Statistical Profiling controls to EL2.
0b1	Accesses to Statistical Profiling controls at EL1 generate a Trap exception to EL2 when EL2 is enabled in the current Security state.

The Statistical Profiling control registers trapped by this control are: PMSCR_EL1, PMSEVFR_EL1, PMSFCR_EL1, PMSICR_EL1, PMSIDR_EL1, PMSIRR_EL1, and PMSLATFR_EL1.

Otherwise:

Reserved, RES0.

E2PB, bits [13:12]

When SPE is implemented:

EL2 Profiling Buffer. If EL2 is implemented and enabled in the Profiling Buffer owning Security state, this field controls the owning translation regime. If EL2 is implemented and enabled in the current Security state, this field controls access to Profiling Buffer control registers from EL1.

E2PB	Meaning
0b00	If EL2 is implemented and enabled in the Profiling Buffer owning Security state, the Profiling Buffer uses the EL2 or EL2&0 stage 1 translation regime. Otherwise the Profiling Buffer uses the EL1&0 stage 1 translation regime. ~~If EL2 is implemented and enabled in the current Security state, accesses to Profiling Buffer control registers at EL1 generate a Trap exception to EL2.~~ If EL2 is implemented and enabled in the current Security state, accesses to Profiling Buffer control registers at EL1 generate a Trap exception to EL2.
0b10	Profiling Buffer uses the EL1&0 stage 1 translation regime. If EL2 is implemented and enabled in the current Security state, accesses to Profiling Buffer control registers at EL1 generate a Trap exception to EL2.
0b11	Profiling Buffer uses the EL1&0 stage 1 translation regime. Accesses to Profiling Buffer control registers at EL1 are not trapped to EL2.

All other values are reserved.

The Profiling Buffer control registers trapped by this control are: PMBLIMITR_EL1, PMBPTR_EL1, and PMBSR_EL1.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TDRA, bit [11]

Trap Debug ROM Address register access. Traps System register accesses to the Debug ROM registers to EL2 when EL2 is enabled in the current Security state as follows:

- If EL1 is using AArch64 state, accesses to MDRAR_EL1 are trapped to EL2, reported using EC syndrome value 0x18.
- If EL0 or EL1 is using AArch32 state, MRC or MCR accesses to the following registers are trapped to EL2, reported using EC syndrome value 0x05 and MRRC or MCRR accesses are trapped to EL2, reported using EC syndrome value 0x0C:
  - DBGDRAR, DBGDSAR.

TDRA	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL0 and EL1 System register accesses to the Debug ROM registers are trapped to EL2 when EL2 is enabled in the current Security state, unless it is trapped by DBGDSCRext.UDCCdis or MDSCR_EL1.TDCC.

This field is treated as being 1 for all purposes other than a direct read when one or more of the following are true:

- MDCR_EL2.TDE == 1.
- HCR_EL2.TGE == 1.

Note

EL2 does not provide traps on debug register accesses through the optional memory-mapped external debug interfaces.

System register accesses to the debug registers might have side-effects. When a System register access is trapped to EL2, no side-effects occur before the exception is taken to EL2.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

TDOSA, bit [10]

When ARMv8.0-DoubleLock is implemented:

Trap debug OS-related register access. Traps EL1 System register accesses to the powerdown debug registers to EL2, from both Execution states as follows:

- In AArch64 state, accesses to the following registers are trapped to EL2, reported using EC syndrome value `0x18`:
  - OSLAR_EL1, OSLSR_EL1, OSDLR_EL1, and DBGPRCR_EL1.
  - Any IMPLEMENTATION DEFINED register with similar functionality that the implementation specifies as trapped by this bit.
- In AArch32 state, accesses to the following registers are trapped to EL2, reported using EC syndrome value `0x05`:
  - DBGOSLSR, DBGOSLAR, DBGOSDLR, and DBGPRCR.
  - Any IMPLEMENTATION DEFINED register with similar functionality that the implementation specifies as trapped by this bit.

TDOSA	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	EL1 System register accesses to the powerdown debug registers are trapped to EL2 when EL2 is enabled in the current Security state.

Note

These registers are not accessible at EL0.

This field is treated as being 1 for all purposes other than a direct read when one or more of the following are true:

- MDCR_EL2.TDE == 1.
- HCR_EL2.TGE == 1.

System register accesses to the debug registers might have side-effects. When a System register access is trapped to EL2, no side-effects occur before the exception is taken to EL2.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Trap debug OS-related register access. Traps EL1 System register accesses to the powerdown debug registers to EL2, from both Execution states as follows:

- In AArch64 state, accesses to the following registers are trapped to EL2, reported using EC syndrome value `0x18`:
  - OSLAR_EL1, OSLSR_EL1, and DBGPRCR_EL1.
  - Any IMPLEMENTATION DEFINED register with similar functionality that the implementation specifies as trapped by this bit.
- In AArch32 state, accesses to the following registers are trapped to EL2, reported using EC syndrome value `0x05`:
  - DBGOSLSR, DBGOSLAR, and DBGPRCR.
  - Any IMPLEMENTATION DEFINED register with similar functionality that the implementation specifies as trapped by this bit.

It is IMPLEMENTATION DEFINED whether accesses to OSDLR_EL1 are trapped.~~trapped and DBGOSDLR are trapped.~~

It is IMPLEMENTATION DEFINED whether accesses to DBGOSDLR are trapped.

TDOSA	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	EL1 System register accesses to the powerdown debug registers are trapped to EL2 when EL2 is enabled in the current Security state.

Note

These registers are not accessible at EL0.

This field is treated as being 1 for all purposes other than a direct read when one or more of the following are true:

- MDCR_EL2.TDE == 1.
- HCR_EL2.TGE == 1.

Note

EL2 does not provide traps on debug register accesses through the optional memory-mapped external debug interfaces.

System register accesses to the debug registers might have side-effects. When a System register access is trapped to EL2, no side-effects occur before the exception is taken to EL2.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

TDA, bit [9]

Trap Debug Access. Traps EL0 and EL1 System register accesses to debug System registers that are not trapped by MDCR_EL2.TDRA or MDCR_EL2.TDOSA, as follows:

- In AArch64 state, accesses to the following registers are trapped to EL2 reported using EC syndrome value `0x18`:
  - MDCCSR_EL0, MDCCINT_EL1, OSDTRRX_EL1, MDSCR_EL1, OSDTRTX_EL1, OSECCR_EL1, DBGBVR<n>_EL1, DBGBCR<n>_EL1, DBGWVR<n>_EL1, DBGWCR<n>_El1, DBGCLAIMSET_EL1, DBGCLAIMCLR_EL1, DBGAUTHSTATUS_EL1.
  - When not in Debug state, DBGDTR_EL0, DBGDTRRX_EL0, DBGDTRTX_EL0.
- In AArch32 state, MRC or MCR accesses to the following registers are trapped to EL2, reported using EC syndrome value `0x05`.
  - DBGDIDR, DBGDSCRint, DBGDCCINT, DBGWFAR, DBGVCR, DBGDSCRext, DBGDTRTXext, DBGDTRRXext, DBGBVR<n>, DBGBCR<n>, DBGBXVR<n>, DBGWCR<n>, DBGWVR<n>, DBGCLAIMSET, DBGCLAIMCLR, DBGAUTHSTATUS, DBGDEVID, DBGDEVID1, DBGDEVID2, DBGOSECCR.
  - When not in Debug state, DBGDTRRXint and DBGDTRTXint.
- In AArch32 state, STC accesses to DBGDTRRXint and LDC accesses to DBGDTRTXint are trapped to EL2, reported using EC syndrome value `0x06`.

TDA	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	EL0 or EL1 System register accesses to the debug registers are trapped from both Execution states to EL2 when EL2 is enabled in the current Security state, unless the access generates a higher priority exception.

Traps of AArch32 accesses to DBGDTRRXint and DBGDTRTXint are ignored in Debug state.

Traps of AArch64 accesses to DBGDTR_EL0, DBGDTRRX_EL0, and DBGDTRTX_EL0 are ignored in Debug state.

This field is treated as being 1 for all purposes other than a direct read when one or more of the following are true:

- MDCR_EL2.TDE == 1
- HCR_EL2.TGE == 1

On a Warm reset, this field resets to an architecturally UNKNOWN value.

TDE, bit [8]

Trap Debug exceptions.

TDE	Meaning
0b0	This control has no effect on the routing of debug exceptions, and has no effect on accesses to debug registers.
0b1	Debug exceptions generated at EL1 or EL0 are routed to EL2 when EL2 is enabled in the current Security state. The MDCR_EL2.{TDRA, TDOSA, TDA} fields are treated as being 1 for all purposes other than returning the result of a direct read of the register.

This field is treated as being 1 for all purposes other than a direct read when HCR_EL2.TGE == 1.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

HPME, bit [7]

When PMUv3 is implemented:

[MDCR_EL2.HPMN..(N-1)] event counters enable.

HPME	Meaning
0b0	Event counters in the range [MDCR_EL2.HPMN..(PMCR_EL0.N-1)] are disabled.
0b1	Event counters in the range [MDCR_EL2.HPMN..(PMCR_EL0.N-1)] are enabled by PMCNTENSET_EL0.

If MDCR_EL2.HPMN is less than PMCR_EL0.N or PMCR.N, the event counters in the range [MDCR_EL2.HPMN..(PMCR_EL0.N-1)] or [HDCR.HPMN..(PMCR.N-1)], are enabled and disabled by this bit. Otherwise this bit has no effect on the operation of the event counters.

Note

The effect of MDCR_EL2.HPMN on the operation of this bit applies regardless of whether EL2 is enabled in the current Security state.

For more information see the description of the HPMN field.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TPM, bit [6]

When PMUv3 is implemented:

Trap Performance Monitors accesses. Traps EL0 and EL1 accesses to all Performance Monitor registers to EL2 when EL2 is enabled in the current Security state, from both Execution states, as follows:

- In AArch64 state, accesses to the following registers are trapped to EL2, reported using EC syndrome value 0x18:
  - ~~PMCR_EL0, PMCNTENSET_EL0, PMCNTENCLR_EL0, PMOVSCLR_EL0, PMSWINC_EL0, PMSELR_EL0, PMCEID0_EL0, PMCEID1_EL0, PMCCNTR_EL0, PMXEVTYPER_EL0, PMXEVCNTR_EL0, PMUSERENR_EL0, PMINTENSET_EL1, PMINTENCLR_EL1, PMOVSSET_EL0, PMEVCNTR<n>_EL0, PMEVTYPER<n>_EL0, PMCCFILTR_EL0.~~

    PMCR_EL0, PMCNTENSET_EL0, PMCNTENCLR_EL0, PMOVSCLR_EL0, PMSWINC_EL0, PMSELR_EL0, PMCEID0_EL0, PMCEID1_EL0, PMCCNTR_EL0, PMXEVTYPER_EL0, PMXEVCNTR_EL0, PMUSERENR_EL0, PMINTENSET_EL1, PMINTENCLR_EL1, PMOVSSET_EL0, PMEVCNTR<n>_EL0, PMEVTYPER<n>_EL0, PMCCFILTR_EL0.

  - If ARMv8.4-PMU is implemented, PMMIR_EL1

- In AArch32 state, MRC or MCR accesses to the following registers are trapped to EL2 and reported using EC syndrome value `0x03`, MRRC or MCRR accesses are trapped to EL2 and reported using EC syndrome value `0x04`:
    - ~~PMCR, PMCNTENSET, PMCNTENCLR, PMOVSR, PMSWINC, PMSELR, PMCEID0, PMCEID1, PMCCNTR, PMXEVTYPER, PMXEVNTR, PMUSERENR, PMINTENSET, PMINTENCLR, PMOVSSET, PMEVCNTR<n>, PMEVTYPER<n>, PMCCFILTR.~~

      PMCR, PMCNTENSET, PMCNTENCLR, PMOVSR, PMSWINC, PMSELR, PMCEID0, PMCEID1, PMCCNTR, PMXEVTYPER, PMXEVNTR, PMUSERENR, PMINTENSET, PMINTENCLR, PMOVSSET, PMEVCNTR<n>, PMEVTYPER<n>, PMCCFILTR.

    - If ARMv8.4-PMU is implemented, PMMIR.
    - If ARMv8.1-PMU is implemented, PMCEID2, and PMCEID3.
- ~~If ARMv8.4-PMU is implemented, in AArch64 state, PMMIR_EL1 and in AArch32 state, PMMIR.~~
- ~~If ARMv8.1-PMU is implemented, in AArch32 state, PMCEID2, and PMCEID3.~~

TPM	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	EL0 and EL1 accesses to all Performance Monitor registers are trapped to EL2 when EL2 is enabled in the current Security state.

Note

EL2 does not provide traps on Performance Monitor register accesses through the optional memory-mapped external debug interface.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TPMCR, bit [5]

When PMUv3 is implemented:

Trap PMCR_EL0 or PMCR accesses. Traps EL0 and EL1 accesses to EL2, when EL2 is enabled in the current Security state, as follows:

- In AArch64 state, accesses to PMCR_EL0 are trapped to EL2, reported using EC syndrome value `0x18`.
- In AArch32 state, accesses to PMCR are trapped to EL2, reported using EC syndrome value `0x03`.

TPMCR	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	EL0 and EL1 accesses to the PMCR_EL0 or PMCR are trapped to EL2 when EL2 is enabled in the current Security state, unless it is trapped by PMUSERENR.EN or PMUSERENR_EL0.EN.

Note

EL2 does not provide traps on Performance Monitor register accesses through the optional memory-mapped external debug interface.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HPMN, bits [4:0]

When PMUv3 is implemented:

Defines the number of event counters that are accessible from EL3, EL2, EL1, and from EL0 if permitted.

If HPMN is less than PMCR_EL0.N, HPMN divides the Performance Monitors into two ranges: [0..(HPMN-1)] and [HPMN..(PMCR_EL0.N-1)].

For an event counter in the range [0..(HPMN-1)]:

- The counter is accessible from EL3, EL2, and EL1, and from EL0 if permitted by PMUSERENR_EL0 or PMUSERENR.
- If ARMv8.5-PMU is implemented, PMCR_EL0.LP or PMCR.LP determines whether the counter overflow flag is set on unsigned overflow of PMEVCNTR<n>_EL0[31:0] or PMEVCNTR<n>_EL0[63:0].
- The counter is enabled by PMCR_EL0.E or PMCR.E and bit <n> of PMCNTENSET_EL0.

Note

If HPMN is equal to PMCR_EL0.N, this applies to all event counters.

If HPMN is less than PMCR_EL0.N, for an event counter in the range [HPMN..(PMCR_EL0.N-1)]:

- The counter is accessible from EL2 and EL3.
- If ARMv8.4-SecEL2 is disabled or is not implemented, the counter is also accessible from Secure EL1, and from Secure EL0 if permitted by PMUSERENR_EL0.
- If ARMv8.5-PMU is implemented, MDCR_EL2.HLP or HDCR.HLP determines whether the counter overflow flag is set on unsigned overflow of PMEVCNTR<n>_EL0[31:0] or PMEVCNTR<n>_EL0[63:0].
- The counter is enabled by MDCR_EL2.HPME or HDCR.HPME and bit <n> of PMCNTENSET_EL0.

If this field is set to 0, or to a value larger than PMCR_EL0.N, then the following CONSTRAINED UNPREDICTABLE behaviors apply:

- The value returned by a direct read of MDCR_EL2.HPMN is UNKNOWN.
- Either:
  - An UNKNOWN number of counters are reserved for EL2 and EL3 use. That is, the PE behaves as if MDCR_EL2.HPMN is set to an UNKNOWN non-zero value less than or equal to PMCR_EL0.N.
  - All counters are reserved for EL2 and EL3 use, meaning no counters are accessible from EL1 and EL0.

On a Warm reset, this field resets to the value in PMCR_EL0.N.

Otherwise:

Reserved, RES0.

Accessing the MDCR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, MDCR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0001	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return MDCR_EL2;
elsif PSTATE.EL == EL3 then
    return MDCR_EL2;
```

MSR MDCR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0001	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        MDCR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    MDCR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MDCR_EL3, Monitor Debug Configuration Register (EL3)

The MDCR_EL3 characteristics are:

Purpose

Provides EL3 configuration options for self-hosted debug and the Performance Monitors Extension.

Configuration

AArch64 System register MDCR_EL3 bits [31:0] can be mapped to AArch32 System register SDCR[31:0] , but this is not architecturally mandated.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to MDCR_EL3 are UNDEFINED.

Attributes

MDCR_EL3 is a 64-bit register.

Field descriptions

The MDCR_EL3 bit assignments are:



Bits [63:29]

Reserved, RES0.

MTPME, bit [28]

When ARMv8.6-MTPMU is implemented:

Multi-threaded PMU Enable. Enables use of the PMEVTYPER<n>_EL0.MT bits.

MTPME	Meaning
0b0	ARMv8.6-MTPMU is disabled. The Effective value of PMEVTYPER<n>_EL0.MT is zero.
0b1	PMEVTYPER<n>_EL0.MT bits not affected by this bit.

If ARMv8.6-MTPMU is disabled for any other PE in the system that has the same level 1 Affinity as the PE, it is IMPLEMENTATION DEFINED whether the PE behaves as if this bit is 0.

On a Cold reset, this field resets to 1.

Otherwise:

Reserved, RES0.

TDCC, bit [27]

When ARMv8.6-FGT is implemented:

Trap DCC. Traps use of the Debug Comms Channel at EL2, EL1, and EL0 to EL3.

TDCC	Meaning
0b0	This control does not cause any register accesses to be trapped.
0b1	Accesses to the DCC registers at EL2, EL1, and EL0 generate a Trap exception to EL3, unless the access also generates a higher priority exception. Traps on the DCC data transfer registers are ignored when the PE is in Debug state.

The DCC registers trapped by this control are:

AArch64: OSDTRRX_EL1, OSDTRTX_EL1, MDCCSR_EL0, MDCCINT_EL1, and, when the PE is in Non-debug state, DBGDTR_EL0, DBGDTRRX_EL0, and DBGDTRTX_EL0.

AArch32: DBGDTRRXext, DBGDTRTXext, DBGDSCRint, DBGDCCINT, and, when the PE is in Non-debug state, DBGDTRRXint and DBGDTRTXint.

The traps are reported with EC syndrome value:

- 0x05 for trapped AArch32 MRC and MCR accesses with coproc == 0b1110.
- 0x06 for trapped AArch32 LDC to DBGDTRTXint and STC from DBGDTRRXint.
- 0x18 for trapped AArch64 MRS and MSR accesses.

When the PE is in Debug state, MDCR_EL3.TDCC does not trap any accesses to:

AArch64: DBGDTR_EL0, DBGDTRRX_EL0, and DBGDTRTX_EL0.

AArch32: DBGDTRRXint and DBGDTRTXint.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [26:24]

Reserved, RES0.

SCCD, bit [23]

When ARMv8.5-PMU is implemented:

Secure Cycle Counter Disable. Prohibits PMCCNTR_EL0 from counting in Secure state.

SCCD	Meaning
0b0	Cycle counting by PMCCNTR_EL0 is not affected by this bit.
0b1	Cycle counting by PMCCNTR_EL0 is prohibited in Secure state.

This bit does not affect the CPU_CYCLES event or any other event that counts cycles.

On a Warm reset, this field resets to 0.

Otherwise:

Reserved, RES0.

Bit [22]

Reserved, RES0.

EPMAD, bit [21]

When ARMv8.4-Debug is implemented and PMUv3 is implemented:

External Performance Monitors Non-secure Access Disable. Controls Non-secure access to Performance Monitor registers by an external debugger.

EPMAD	Meaning
0b0	Non-secure access to Performance Monitor registers from external debugger is permitted.
0b1	Non-secure access to Performance Monitor registers from external debugger is not permitted.

If the Performance Monitors Extension does not support external debug interface accesses this bit is RES0.

Otherwise, if EL3 is not implemented and the Effective value of SCR_EL3.NS is 0b0, then the Effective value of this bit is 0b1.

On a Warm reset, this field resets to 0.

When PMUv3 is implemented:

External Performance Monitors Access Disable. Controls access to Performance Monitor registers by an external debugger.

EPMAD	Meaning
0b0	Access to Performance Monitor registers from external debugger is permitted.
0b1	Access to Performance Monitor registers from external debugger is not permitted, unless overridden by the IMPLEMENTATION DEFINED authentication interface.

If the Performance Monitors Extension does not support external debug interface accesses this bit is RES0.

Otherwise, if EL3 is not implemented and the Effective value of SCR_EL3.NS is 0b0, then the Effective value of this bit is 0b1.

On a Warm reset, this field resets to 0.

Otherwise:

Reserved, RES0.

EDAD, bit [20]

When ARMv8.4-Debug is implemented:

External Debug Non-secure Access Disable. Controls Non-secure access to breakpoint, watchpoint, and OSLAR_EL1 registers by an external debugger.

EDAD	Meaning
0b0	Non-secure access to debug registers from external debugger is permitted.
0b1	Non-secure access to breakpoint and watchpoint registers, and OSLAR_EL1 from external debugger is not permitted.

If EL3 is not implemented and the Effective value of SCR_EL3.NS is `0b0`, then the Effective value of this field is `0b1`.

On a Warm reset, this field resets to `0`.

When ARMv8.2-Debug is implemented:

External Debug Access Disable. Controls access to breakpoint, watchpoint, and OSLAR_EL1 registers by an external debugger.

EDAD	Meaning
`0b0`	Access to debug registers, and to OSLAR_EL1 from external debugger is permitted.
`0b1`	Access to breakpoint and watchpoint registers, and to OSLAR_EL1 from external debugger is not permitted, unless overridden by the IMPLEMENTATION DEFINED authentication interface.

If EL3 is not implemented and the Effective value of SCR_EL3.NS is `0b0`, then the Effective value of this field is `0b1`.

On a Warm reset, this field resets to `0`.

Otherwise:

External Debug Access disable. Controls access to breakpoint, watchpoint, and optionally OSLAR_EL1 registers by an external debugger.

EDAD	Meaning
`0b0`	Access to debug registers from external debugger is permitted.
`0b1`	Access to breakpoint and watchpoint registers from an external debugger is not permitted, unless overridden by the IMPLEMENTATION DEFINED authentication interface. It is IMPLEMENTATION DEFINED whether access to the OSLAR_EL1 register from an external debugger is permitted or not permitted.

If EL3 is not implemented and the Effective value of SCR_EL3.NS is `0b0`, then the Effective value of this field is `0b1`.

On a Warm reset, this field resets to `0`.

TTRF, bit [19]

When ARMv8.4-Trace is implemented:

Trap Trace Filter controls. Traps use of the Trace Filter control registers at EL2 and EL1 to EL3.

The Trace Filter registers trapped by this control are:

- TRFCR_EL2, TRFCR_EL12, TRFCR_EL1, reported using EC syndrome value `0x18`.
- HTRFCR and TRFCR, reported using EC syndrome value `0x03`.

TTRF	Meaning
`0b0`	Accesses to Trace Filter registers at EL2 and EL1 are not affected by this bit.
`0b1`	Accesses to Trace Filter registers at EL2 and EL1 generate a Trap exception to EL3, unless the access generates a higher priority exception.

Otherwise:

Reserved, RES0.

STE, bit [18]

When ARMv8.4-Trace is implemented:

Secure Trace enable. Enables tracing in Secure state.

STE	Meaning
0b0	Trace prohibited in Secure state unless overridden by the IMPLEMENTATION DEFINED authentication interface.
0b1	Trace in Secure state is not affected by this bit.

This bit also controls the level of authentication required by an external debugger to enable external tracing. See 'Register controls to enable self-hosted trace' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

If EL3 is not implemented the Effective value of SCR_EL3.NS is 0b0, the Effective value of this bit is 0b1.

On a Warm reset, this field resets to 0.

Otherwise:

Reserved, RES0.

SPME, bit [17]

When ARMv8.2-Debug is implemented and PMUv3 is implemented:

Secure Performance Monitors enable. This allows event counting in Secure state.

SPME	Meaning
0b0	Event counting prohibited in Secure state.
0b1	Event counting in Secure state not affected by this bit.

If EL3 is not implemented the Effective value of SCR_EL3.NS is 0b0, then the Effective value of this bit is 0b1.

On a Warm reset, this field resets to 0.

When PMUv3 is implemented:

Secure Performance Monitors enable. This allows event counting in Secure state.

SPME	Meaning
0b0	Event counting prohibited in Secure state, unless ExternalSecureNoninvasiveDebugEnabled() is TRUE.
0b1	Event counting in Secure state not affected by this bit.

If EL3 is not implemented the Effective value of SCR_EL3.NS is 0b0, then the Effective value of this bit is 0b1.

On a Warm reset, this field resets to 0.

Otherwise:

Reserved, RES0.

SDD, bit [16]

AArch64 Secure Self-hosted invasive debug disable. Disables Software debug exceptions in Secure state, other than Breakpoint Instruction exceptions.

SDD	Meaning
0b0	Debug exceptions in Secure state are not affected by this bit.
0b1	Debug exceptions, other than Breakpoint Instruction exceptions, are disabled from all Exception levels in Secure state.

The SDD bit is ignored unless both of the following are true:

- The PE is in Secure state.
- The Effective value of SCR_EL3.RW is `0b1`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SPD32, bits [15:14]

When EL1 is capable of using AArch32:

AArch32 Secure self-hosted privileged debug. Enables or disables debug exceptions from Secure EL1 using AArch32, other than Breakpoint Instruction exceptions.

SPD32	Meaning
`0b00`	Legacy mode. Debug exceptions from Secure EL1 are enabled by the IMPLEMENTATION DEFINED authentication interface.
`0b10`	Secure privileged debug disabled. Debug exceptions from Secure EL1 are disabled.
`0b11`	Secure privileged debug enabled. Debug exceptions from Secure EL1 are enabled.

Other values are reserved, and have the CONSTRAINED UNPREDICTABLE behavior that they must have the same behavior as `0b00`. Software must not rely on this property as the behavior of reserved values might change in a future revision of the architecture.

This field has no effect on Breakpoint Instruction exceptions. These are always enabled.

This field is ignored if the PE is either:

- In~~Ignored~~ Non-secure~~if~~ state.~~the PE is either:~~
  - ~~In Non-secure state.~~
  - ~~In Secure state and Secure EL1 is using AArch64.~~
- In Secure state and Secure EL1 is using AArch64.
- ~~RES0 if the implementation does not support EL1 using AArch32.~~

If Secure EL1 is using AArch32 then:

- If debug exceptions from Secure EL1 are enabled, then debug exceptions from Secure EL0 are also enabled.
- Otherwise, debug exceptions from Secure EL0 are enabled only if the value of SDER32_EL3.SUIDEN is `0b1`.

If EL3 is not implemented and the Effective value of SCR_EL3.NS is `0b0`, then the Effective value of this field is `0b11`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NSPB, bits [13:12]

When SPE is implemented:

Non-secure Profiling Buffer. This field controls the owning translation regime and accesses to Statistical Profiling and Profiling Buffer control registers.

NSPB	Meaning
0b00	Profiling Buffer uses Secure Virtual Addresses. Statistical Profiling enabled in Secure state and disabled in Non-secure state. Accesses to Statistical Profiling and Profiling Buffer control registers at EL2 and EL1 in both security states generate Trap exceptions to EL3.
0b01	Profiling Buffer uses Secure Virtual Addresses. Statistical Profiling enabled in Secure state and disabled in Non-secure state. Accesses to Statistical Profiling and Profiling Buffer control registers at EL2 and EL1 in Non-secure state generate Trap exceptions to EL3.
0b10	Profiling Buffer uses Non-secure Virtual Addresses. Statistical Profiling enabled in Non-secure state and disabled in Secure state. Accesses to Statistical Profiling and Profiling Buffer control registers at EL2 and EL1 in both security states generate Trap exceptions to EL3.
0b11	Profiling Buffer uses Non-secure Virtual Addresses. Statistical Profiling enabled in Non-secure state and disabled in Secure state. Accesses to Statistical Profiling and Profiling Buffer control registers at EL2 and EL1 in Secure state generate Trap exceptions to EL3.

The Statistical Profiling and Profiling Buffer control registers trapped by this control are: PMBLIMITR_EL1, PMBPTR_EL1, PMBSR_EL1, PMSCR_EL1, PMSCR_EL2, PMSEVFR_EL1, PMSFCR_EL1, PMSICR_EL1, PMSIDR_EL1, PMSIRR_EL1, and PMSLATFR_EL1.

If EL3 is not implemented and the Effective value of SCR_EL3.NS is 0b1, the Effective value of this field is 0b11.

~~If EL3 is not implemented and the Effective value of SCR_EL3.NS is 0b1, the Effective value of this field is 0b11. If EL3 is not implemented and the Effective value of SCR_EL3.NS is 0b0, the Effective value of this field is 0b01.~~

If EL3 is not implemented and the Effective value of SCR_EL3.NS is 0b0, the Effective value of this field is 0b01.

On a Warm reset, this field resets to an UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [11]

Reserved, RES0.

TDOSA, bit [10]

When ARMv8.0-DoubleLock is implemented:

Trap debug OS-related register access. Traps EL2 and EL1 System register accesses to the powerdown debug registers to EL3.

Accesses to the registers are trapped as follows:

- Accesses from AArch64 state, OSLAR_EL1, OSLSR_EL1, OSDLR_EL1, DBGPRCR_EL1 and any IMPLEMENTATION DEFINED register with similar functionality that the implementation specifies as trapped by this bit, are trapped to EL3 and reported using EC syndrome value 0x18.
- Accesses using MCR or MRC to DBGOSLAR, DBGOSLSR, DBGOSDLR, and DBGPRCR, are trapped to EL3 and reported using EC syndrome value 0x05.
- Accesses to any IMPLEMENTATION DEFINED register with similar functionality that the implementation specifies as trapped by this bit.

TDOSA	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL2 and EL1 System register accesses to the powerdown debug registers are trapped to EL3, unless it is trapped by HDCR.TDOSA or MDCR_EL2.TDOSA.

Note

The powerdown debug registers are not accessible at EL0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Trap debug OS-related register access. Traps EL2 and EL1 System register accesses to the powerdown debug registers to EL3.

The following registers are affected by this trap:

- AArch64: OSLAR_EL1, OSLSR_EL1, and DBGPRCR_EL1.
- AArch32: DBGOSLAR, DBGOSLSR, and DBGPRCR.
- AArch64 and AArch32: Any IMPLEMENTATION DEFINED register with similar functionality that the implementation specifies as trapped by this bit.
- It is IMPLEMENTATION DEFINED whether accesses to OSDLR_EL1 and DBGOSDLR are trapped.

TDOSA	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL2 and EL1 System register accesses to the powerdown debug registers are trapped to EL3, unless it is trapped by HDCR.TDOSA or MDCR_EL2.TDOSA.

Note

The powerdown debug registers are not accessible at EL0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

TDA, bit [9]

Trap Debug Access. Traps EL2, EL1, and EL0 System register accesses to those debug System registers that cannot be trapped using the MDCR_EL3.TDOSA field.

Accesses to the debug registers are trapped as follows:

- In AArch64 state, the following registers are trapped to EL3 and reported using EC syndrome value 0x18:
  - DBGBVR<n>_EL1, DBGBCR<n>_EL1, DBGWVR<n>_EL1, DBGWCR<n>_EL1, DBGCLAIMSET_EL1, DBGCLAIMCLR_EL1, DBGAUTHSTATUS_EL1, DBGVCR32_EL2.
  - AArch64: MDCR_EL2, MDRAR_EL1, MDCCSR_EL0, MDCCINT_EL1, MDSCR_EL1, OSDTRRX_EL1, OSDTRTX_EL1, OSECCR_EL1.
- In AArch32 state, SDER is trapped to EL3 and reported using EC syndrome value 0x03.
- In AArch32 state, accesses using MCR or MRC to the following registers are reported using EC syndrome value 0x05, accesses using MCRR or MRRC are reported using EC syndrome value 0x0C:
  - HDCR, DBGDRAR, DBGDSAR, DBGDIDR, DBGDCCINT, DBGWFAR, DBGVCR, DBGBVR<n>, DBGBCR<n>, DBGBXVR<n>, DBGWCR<n>, DBGWVR<n>.
  - DBGCLAIMSET, DBGCLAIMCLR, DBGAUTHSTATUS, DBGDEVID, DBGDEVID1, DBGDEVID2, DBGOSECCR.
- In AArch32 state, STC accesses to DBGDTRRXint and LDC accesses to DBGDTRTXint are reported using EC syndrome value 0x06.
- When not in Debug state, the following registers are also trapped to EL3:
  - AArch64 accesses to DBGDTR_EL0, DBGDTRRX_EL0, and DBGDTRTX_EL0, reported using EC syndrome value 0x18.
  - AArch32 accesses using MCR or MRC to DBGDTRRXint and DBGDTRTXint, reported using EC syndrome value 0x05.

TDA	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL0, EL1, and EL2 accesses to the debug registers, other than the registers that can be trapped by MDCR_EL3.TDOSA, are trapped to EL3, from both Security states and both Execution states, unless it is trapped by DBGDSCRext.UDCCdis, MDSCR_EL1.TDCC, HDCR.TDA or MDCR_EL2.TDA.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bits [8:7]

Reserved, RES0.

TPM, bit [6]

When PMUv3 is implemented:

Trap Performance Monitor register accesses. Accesses to all Performance Monitor registers from EL0, EL1 and EL2 to EL3, from both Security states and both Execution states are trapped as follows:

- In AArch64 state, accesses to the following registers are trapped to EL3 and are reported using EC syndrome value 0x18:
  - PMCR_EL0, PMCNTENSET_EL0, PMCNTENCLR_EL0, PMOVSCLR_EL0, PMSWINC_EL0, PMSELR_EL0, PMCEID0_EL0, PMCEID1_EL0, PMCCNTR_EL0, PMXEVTYPER_EL0, PMXEVCNTR_EL0, PMUSERENR_EL0, PMINTENSET_EL1, PMINTENCLR_EL1, PMOVSSET_EL0, PMEVCNTR<n>_EL0, PMEVTYPER<n>_EL0, PMCCFILTR_EL0...
  - If ARMv8.4-PMU is implemented, PMMIR_EL1
- In AArch32 state, accesses using MCR or MRC to the following registers are reported using EC syndrome value 0x03, accesses using MCRR or MRRC are reported using EC syndrome value 0x04:
  - PMCR, PMCNTENSET, PMCNTENCLR, PMOVSR, PMSWINC, PMSELR, PMCEID0, PMCEID1, PMCCNTR, PMXEVTYPER, PMXEVCNTR, PMUSERENR, PMINTENSET, PMINTENCLR, PMOVSSET, PMEVCNTR<n>, PMEVTPER<n>, PMCFILTR.
  - If ARMv8.1-PMU is implemented, PMCEID2, and PMCEID3.
  - If ARMv8.4-PMU is implemented, PMMIR.
- ~~If ARMv8.4-PMU is implemented, in AArch64 state, PMMIR_EL1, and in AArch32 state, PMMIR.~~
- ~~If ARMv8.1-PMU is implemented, in AArch32 state, PMCEID2, and PMCEID3.~~

TPM	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL2, EL1, and EL0 System register accesses to all Performance Monitor registers are trapped to EL3, unless it is trapped by HDCR.TPM or MDCR_EL2.TPM.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [5:0]

Reserved, RES0.

Accessing the MDCR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, MDCR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return MDCR_EL3;
```

```
MSR MDCR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    MDCR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAM1_EL1, MPAM1 Register (EL1)

The MPAM1_EL1 characteristics are:

Purpose

Holds information to generate MPAM labels for memory requests when executing at EL1.

When EL2 is present and enabled, the MPAM virtualization option is present, MPAMHCR_EL2.GSTAPP_PLK == 1 and HCR_EL2.TGE == 0, MPAM1_EL1 is used instead of MPAM0_EL1 to generate MPAM labels for memory requests when executing at EL0.

MPAM1_EL1 is an alias for MPAM2_EL2 when executing at EL2 with HCR_EL2.E2H == 1.

MPAM1_EL12 is an alias for MPAM1_EL1 when executing at EL2 or EL3 with HCR_EL2.E2H == 1.

If EL2 is is present and enabled, the MPAM virtualization option is present and MPAMHCR_EL2.EL1_VPMEN == 1, MPAM PARTIDs in MPAM1_EL1 are virtual and mapped into physical PARTIDs for the current Security state. This mapping of MPAM1_EL1 virtual PARTIDs to physical PARTIDs when EL1_VPMEN is 1 also applies when MPAM1_EL1 is used at EL0 due to MPAMHCR_EL2.GSTAPP_PLK.

Configuration

AArch64 System register MPAM1_EL1 bit [63] is architecturally mapped to AArch64 System register MPAM3_EL3[63] when ~~HaveEL(~~EL3 is implemented.~~)~~.

AArch64 System register MPAM1_EL1 bit [63] is architecturally mapped to AArch64 System register MPAM2_EL2[63] when ~~!HaveEL(~~EL3~~)~~ is not implemented and ~~HaveEL(~~EL2 is implemented.~~)~~.

This register is present only when MPAM is implemented. Otherwise, direct accesses to MPAM1_EL1 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

MPAM1_EL1 is a 64-bit register.

Field descriptions

The MPAM1_EL1 bit assignments are:

63	62 61	60	59 58 57 56 55 54 53 52 51 50 49 48	47 46 45 44 43 42 41 40	39 38 37 36 35 34 33 32
MPAMEN	RES0	FORCED_NS	RES0	PMG_D	PMG_I
PARTID_D				PARTID_I	
31	30 29	28	27 26 25 24 23 22 21 20 19 18 17 16	15 14 13 12 11 10 9 8	7 6 5 4 3 2 1 0

MPAMEN, bit [63]

MPAM Enable. MPAM is enabled when MPAMEN == 1. When disabled, all PARTIDs and PMGs are output as their default value in the corresponding ID space.

~~Values of this field are:~~

MPAMEN	Meaning
0b0	The default PARTID and default PMG are output in MPAM information.
0b1	MPAM information is output based on the MPAMn_ELx register for ELn according the MPAM configuration.

If neither EL3 nor EL2 is implemented, this field is read/write.

If EL3 is implemented, this field is read-only and reads the current value of the read/write bit MPAM3_EL3.MPAMEN.

If EL3 is not implemented and EL2 is implemented, this field is read-only and reads the current value of the read/write bit MPAM2_EL2.MPAMEN.

This field resets to 0.

Accessing this field has the following behavior:

- When ~~!HaveEL(~~EL3~~)~~ is not implemented and ~~!HaveEL(~~EL2 is not implemented,~~),~~ access to this field is **RW**.
- Otherwise, access to this field is **RO**.

Bits [62:61]

Reserved, RES0.

FORCED_NS, bit [60]

When ARMv8.6-MPAM is implemented:

In the Secure state, FORCED_NS ~~Secure state~~ indicates the state of MPAM3_EL3.FORCE_NS.

FORCED_NS	Meaning
0b0	In the Non-secure state, always reads as 0. In the Secure state, indicates that MPAM3_EL3.FORCE_NS == 0.
0b1	In the Secure state, indicates~~Indicate~~ that MPAM3_EL3.FORCE_NS == 1.

Always reads~~Reads~~ as 0 in the Non-secure state.

Writes are ignored.

Access to this field is **RO**.

Otherwise:

Reserved, RES0.

Bits [59:48]

Reserved, RES0.

PMG_D, bits [47:40]

Performance monitoring group property for PARTID_D.

This field resets to an architecturally UNKNOWN value.

PMG_I, bits [39:32]

Performance monitoring group property for PARTID_I.

This field resets to an architecturally UNKNOWN value.

PARTID_D, bits [31:16]

Partition ID for data accesses, including load and store accesses, made from EL1.

This field resets to an architecturally UNKNOWN value.

PARTID_I, bits [15:0]

Partition ID for instruction accesses made from EL1.

This field resets to an architecturally UNKNOWN value.

Accessing the MPAM1_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, accesses from EL3 using the mnemonic MPAM1_EL1 or MPAM1_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

None of the fields in this register are permitted to be cached in a TLB.

Accesses to this register use the following encodings:

```
MRS <Xt>, MPAM1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1010	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MPAM2_EL2.TRAPMPAM1EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x900];
    else
        return MPAM1_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        return MPAM2_EL2;
    else
        return MPAM1_EL1;
elsif PSTATE.EL == EL3 then
    return MPAM1_EL1;
```

```
MSR MPAM1_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1010	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MPAM2_EL2.TRAPMPAM1EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x900] = X[t];
    else
        MPAM1_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        MPAM2_EL2 = X[t];
    else
        MPAM1_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    MPAM1_EL1 = X[t];
```

MRS <Xt>, MPAM1_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b1010	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x900];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            return MPAM1_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return MPAM1_EL1;
    else
        UNDEFINED;
```

MSR MPAM1_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b1010	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x900] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            MPAM1_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        MPAM1_EL1 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAM2_EL2, MPAM2 Register (EL2)

The MPAM2_EL2 characteristics are:

Purpose

Holds information to generate MPAM labels for memory requests when executing at EL2.

Configuration

AArch64 System register MPAM2_EL2 bit [63] is architecturally mapped to AArch64 System register MPAM3_EL3[63] when ~~HaveEL(~~EL3 is implemented.~~)~~.

AArch64 System register MPAM2_EL2 bit [63] is architecturally mapped to AArch64 System register MPAM1_EL1[63] .

This register is present only when MPAM is implemented. Otherwise, direct accesses to MPAM2_EL2 are UNDEFINED.

This register has no effect if EL2 is not enabled in the current Security state.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

MPAM2_EL2 is a 64-bit register.

Field descriptions

The MPAM2_EL2 bit assignments are:

63	62616059	58	5756555453525150	49	48	4746454443424140393837363534333 2
MPAMEN	RES0	TIDR	RES0	TRAPMPAM0EL1	TRAPMPAM1EL1	PMG_D	PMG_I
PARTID_D						PARTID_I
31	30292827	26	2524232221201918	17	16	1514131211109 8 7 6 5 4 3 2 1 0

MPAMEN, bit [63]

MPAM Enable. MPAM is enabled when MPAMEN == 1. When disabled, all PARTIDs and PMGs are output as their default value in the corresponding ID space.

~~Values of this field are:~~

MPAMEN	Meaning
0b0	The default PARTID and default PMG are output in MPAM information from all Exception levels.
0b1	MPAM information is output based on the MPAMn_ELx register for ELn according the MPAM configuration.

If EL3 is not implemented, this field is read/write.

If EL3 is implemented, this field is read-only and reads the current value of the read/write MPAM3_EL3.MPAMEN bit.

This field resets to 0.

Accessing this field has the following behavior:

- When ~~!HaveEL(~~EL3 is not implemented,~~),~~ access to this field is **RW**.
- Otherwise, access to this field is **RO**.

Bits [62:59]

Reserved, RES0.

TIDR, bit [58]

When ARMv8.6-MPAM is implemented and MPAMIDR_EL1.HAS_TIDR == 1:

TIDR traps accesses to MPAMIDR_EL1 from EL1 to EL2.

TIDR	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Trap accesses to MPAMIDR_EL1 from EL1 to EL2.

MPAMHCR_EL2.TRAP_MPAMIDR_EL1 == 1 also traps MPAMIDR_EL1 accesses from EL1 to EL2. If either TIDR or TRAP_MPAMIDR_EL1 are 1, accesses are trapped.

Otherwise:

Reserved, RES0.

Bits [57:50]

Reserved, RES0.

TRAPMPAM0EL1, bit [49]

TRAPMPAM0EL1: Trap accesses from EL1 to the MPAM0_EL1 register trap to EL2.

TRAPMPAM0EL1	Meaning
0b0	Accesses to MPAM0_EL1 from EL1 are not trapped.
0b1	Accesses to MPAM0_EL1 from EL1 are trapped to EL2.

This field resets to:

- If EL3 is not implemented, 1.
- If EL3 is implemented, an architecturally UNKNOWN value.

~~When EL3 is not implemented, this field resets to 1. When EL3 is implemented, this field resets to UNKNOWN.~~

TRAPMPAM1EL1, bit [48]

TRAPMPAM1EL1: Trap accesses from EL1 to the MPAM1_EL1 register trap to EL2.

TRAPMPAM1EL1	Meaning
0b0	Accesses to MPAM1_EL1 from EL1 are not trapped.
0b1	Accesses to MPAM1_EL1 from EL1 are trapped to EL2.

This field resets to:

- If EL3 is not implemented, 1.
- If EL3 is implemented, an architecturally UNKNOWN value.

~~When EL3 is not implemented, this field resets to 1. When EL3 is implemented, this field resets to UNKNOWN.~~

PMG_D, bits [47:40]

Performance monitoring group for data accesses.

This field resets to an architecturally UNKNOWN value.

PMG_I, bits [39:32]

Performance monitoring group for instruction accesses.

This field resets to an architecturally UNKNOWN value.

PARTID_D, bits [31:16]

Partition ID for data accesses, including load and store accesses, made from EL2.

This field resets to an architecturally UNKNOWN value.

PARTID_I, bits [15:0]

Partition ID for instruction accesses made from EL2.

This field resets to an architecturally UNKNOWN value.

Accessing the MPAM2_EL2

None of the fields in this register are permitted to be cached in a TLB.

Accesses to this register use the following encodings:

```
MRS <Xt>, MPAM2_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1010	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return MPAM2_EL2;
elsif PSTATE.EL == EL3 then
    return MPAM2_EL2;
```

```
MSR MPAM2_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1010	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        MPAM2_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    MPAM2_EL2 = X[t];
```

MRS <Xt>, MPAM1_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b1010	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MPAM2_EL2.TRAPMPAM1EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x900];
    else
        return MPAM1_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        return MPAM2_EL2;
    else
        return MPAM1_EL1;
elsif PSTATE.EL == EL3 then
    return MPAM1_EL1;
```

MSR MPAM1_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b1010	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MPAM2_EL2.TRAPMPAM1EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x900] = X[t];
    else
        MPAM1_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        MPAM2_EL2 = X[t];
    else
        MPAM1_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    MPAM1_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAM3_EL3, MPAM3 Register (EL3)

The MPAM3_EL3 characteristics are:

Purpose

Holds information to generate MPAM labels for memory requests when executing at EL3.

Configuration

AArch64 System register MPAM3_EL3 bit [63] is architecturally mapped to AArch64 System register MPAM2_EL2[63] when ~~HaveEL(~~EL2 is implemented.~~).~~

AArch64 System register MPAM3_EL3 bit [63] is architecturally mapped to AArch64 System register MPAM1_EL1[63] .

This register is present only when MPAM is implemented. Otherwise, direct accesses to MPAM3_EL3 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

MPAM3_EL3 is a 64-bit register.

Field descriptions

The MPAM3_EL3 bit assignments are:

63	62	61	60	59 58 57 56 55 54 53 52 51 50 49 48 47 46 45 44 43 42 41 40 39 38 37 36 35 34 33 32	
MPAMEN	TRAPLOWER	SDEFLT	FORCE_NS	RES0	PMG_D / PMG_I
PARTID_D					PARTID_I
31	30	29	28	27 26 25 24 23 22 21 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 0	

MPAMEN, bit [63]

MPAM Enable. MPAM is enabled when MPAMEN == 1. When disabled, all PARTIDs and PMGs are output as their default value in the corresponding ID space.

Values of this field are:

MPAMEN	Meaning
0b0	The default PARTID and default PMG are output in MPAM information when executing at any ELn.
0b1	MPAM information is output based on the MPAMn_ELx register for ELn according the MPAM configuration.

This field is always read/write in MPAM3_EL3.

This field resets to 0.

TRAPLOWER, bit [62]

Trap direct accesses to any MPAM system registers that are not UNDEFINED from all ELn lower than EL3.

TRAPLOWER	Meaning
0b0	Do not force trapping of direct accesses of MPAM system registers to EL3.
0b1	Force all direct accesses of MPAM system registers to trap to EL3.

On a Cold reset, this field resets to 1.

SDEFLT, bit [61]

When ARMv8.6-MPAM is implemented and MPAMIDR_EL1.HAS_SDEFLT == 1:

SDEFLT overrides the PARTID with the default PARTID when executing in the Secure state.

SDEFLT	Meaning
0b0	The PARTID is determined normally in the Secure state.
0b1	The PARTID is always PARTID 0 when executing in the Secure state.

This field resets to an UNKNOWN value.

Otherwise:

Reserved, RES0.

FORCE_NS, bit [60]

When ARMv8.6-MPAM is implemented and MPAMIDR_EL1.HAS_FORCE_NS == 1:

FORCE_NS forces MPAM_NS to always be 1 in the Secure state.

FORCE_NS	Meaning
0b0	MPAM_NS is 0 when executing in the Secure state.
0b1	MPAM_NS is 1 when executing in the Secure state.

An implementation is permitted to have this field as RAO if the implementation does not support generating MPAM_NS as 0.

This field resets to an UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [59:48]

Reserved, RES0.

PMG_D, bits [47:40]

Performance monitoring group for data accesses.

This field resets to an architecturally UNKNOWN value.

PMG_I, bits [39:32]

Performance monitoring group for instruction accesses.

PARTID_D, bits [31:16]

Partition ID for data accesses, including load and store accesses, made from EL3.

This field resets to an architecturally UNKNOWN value.

PARTID_I, bits [15:0]

Partition ID for instruction accesses made from EL3.

This field resets to an architecturally UNKNOWN value.

Accessing the MPAM3_EL3

None of the fields in this register are permitted to be cached in a TLB.

Accesses to this register use the following encodings:

```
MRS <Xt>, MPAM3_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1010	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return MPAM3_EL3;
```

```
MSR MPAM3_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1010	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    MPAM3_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMHCR_EL2, MPAM Hypervisor Control Register (EL2)

The MPAMHCR_EL2 characteristics are:

Purpose

Controls the PARTID virtualization features of MPAM. It controls the mapping of virtual PARTIDs into physical PARTIDs in MPAM0_EL1 when EL0_VPMEN == 1 and in MPAM1_EL1 when EL1_VPMEN == 1.

Configuration

This register is present only when MPAM is implemented and MPAMIDR_EL1.HAS_HCR == 1. Otherwise, direct accesses to MPAMHCR_EL2 are UNDEFINED.

This register has no effect if EL2 is not enabled in the current Security state.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

MPAMHCR_EL2 is a 64-bit register.

Field descriptions

The MPAMHCR_EL2 bit assignments are:

63	62 61 60 59 58 57 56 55 54 53 52 51 50 49 48 47 46 45 44 43 42 41	40	39 38 37 36 35	34	33	32
RES0						
TRAP_MPAMIDR_EL1	RES0	GSTAPP_PLK	RES0		EL1_VPMEN	EL0_VPMEN
31	30 29 28 27 26 25 24 23 22 21 20 19 18 17 16 15 14 13 12 11 10 9	8	7 6 5 4 3 2		1	0

Bits [63:32]

Reserved, RES0.

TRAP_MPAMIDR_EL1, bit [31]

Trap accesses from EL1 to MPAMIDR_EL1 to EL2.

TRAP_MPAMIDR_EL1	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Direct accesses to MPAMIDR_EL1 from EL1 are trapped to EL2.

This field resets to:

- If EL3 is not implemented, 1.
- If EL3 is implemented, an architecturally UNKNOWN value.

~~When EL3 is not implemented, this field is reset to 1. When EL3 is implemented, this field resets to UNKNOWN.~~

Bits [30:9]

Reserved, RES0.

GSTAPP_PLK, bit [8]

Make the PARTIDs at EL0 the same as the PARTIDs at EL1. When executing at EL0, EL2 is enabled, HCR_EL2.TGE == 0 and GSTAPP_PLK = 1, MPAM1_EL1 is used instead of MPAM0_EL1 to generate MPAM labels for memory requests.

GSTAPP_PLK	Meaning
0b0	MPAM0_EL1 is used to generate MPAM labels when executing at EL0.
0b1	MPAM1_EL1 is used to generate MPAM labels when executing at EL0 with EL2 enabled and HCR_EL2.TGE == 0. Otherwise MPAM0_EL1 is used.

This field resets to an architecturally UNKNOWN value.

Bits [7:2]

Reserved, RES0.

EL1_VPMEN, bit [1]

Enable the virtual PARTID mapping of the PARTID fields in MPAM1_EL1 when executing at EL1. This bit also enables virtual PARTID mapping when MPAM1_EL1 is used to generate MPAM labels for memory requests at EL0 due to GSTAPP_PLK == 1.

EL1_VPMEN	Meaning
0b0	MPAM1_EL1.PARTID_I and MPAM1_EL1.PARTID_D are physical PARTIDs that are used to label memory system requests.
0b1	MPAM1_EL1.PARTID_I and MPAM1_EL1.PARTID_D are virtual PARTIDs that are used to index the PhyPARTID fields of MPAMVPM0_EL2 to MPAMVPM7_EL2 registers to map the virtual PARTID into a physical PARTID to label memory system requests.

This field resets to an architecturally UNKNOWN value.

EL0_VPMEN, bit [0]

Enable the virtual PARTID mapping of the PARTID fields of MPAM0_EL1 unless HCR_EL2.E2H == 1 and HCR_EL2.TGE == 1.

When HCR_EL2.E2H == 1 and HCR_EL2.TGE == 1, EL0_VPMEN is ignored and MPAM0_EL1 PARTID fields are not mapped.

When MPAMHCR_EL2.GSTAPP_PLK == 1 and HCR_EL2.TGE == 0, MPAM1_EL1 is used as the source of PARTIDs and the virtual PARTID mapping of MPAM1_EL1 PARTIDs is controlled by MPAMHCR_EL2.EL1_VPMEN.

EL0_VPMEN	Meaning
0b0	MPAM0_EL1.PARTID_I and MPAM0_EL1.PARTID_D are physical PARTIDs that are used to label memory system requests.
0b1	MPAM0_EL1.PARTID_I and MPAM0_EL1.PARTID_D are virtual PARTIDs that are used to index the PhyPARTID fields of MPAMVPM0_EL2 to MPAMVPM7_EL2 registers to map the virtual PARTID into a physical PARTID to label memory system requests.

This field resets to an architecturally UNKNOWN value.

Accessing the MPAMHCR_EL2

Accesses to this register use the following encodings:

MRS <Xt>, MPAMHCR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b1010	0b0100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x930];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return MPAMHCR_EL2;
elsif PSTATE.EL == EL3 then
    return MPAMHCR_EL2;
```

MSR MPAMHCR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b1010	0b0100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x930] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        MPAMHCR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    MPAMHCR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMIDR_EL1, MPAM ID Register (EL1)

The MPAMIDR_EL1 characteristics are:

Purpose

Indicates the presence and maximum PARTID and PMG values supported in the implementation. It also indicates whether the implementation supports MPAM virtualization.

Configuration

This register is present only when MPAM is implemented. Otherwise, direct accesses to MPAMIDR_EL1 are UNDEFINED.

Attributes

MPAMIDR_EL1 is a 64-bit register.

Field descriptions

The MPAMIDR_EL1 bit assignments are:



MPAMIDR_EL1 indicates the MPAM implementation parameters of the PE.

Bits [63:62]

Reserved, RES0.

HAS_SDEFLT, bit [61]

~~**From Armv8.6:**~~

HAS_SDEFLT indicates support for MPAM3_EL3.SDEFLT bit. Defined values are:

HAS_SDEFLT	Meaning
0b0	The SDEFLT bit is not implemented in MPAM3_EL3.
0b1	The SDEFLT bit is implemented in MPAM3_EL3.

When MPAM3_EL3.SDEFLT == 1, accesses from the Secure execution state use the default PARTID, PARTID == 0.

~~**HAS_FORCE_NS, bit [60]**~~

~~**From Armv8.6:**~~

~~HAS_FORCE_NS indicates support for MPAM3_EL3.FORCE_NS bit.~~

~~**Otherwise:**~~
HAS_FORCE_NS, bit [60]

HAS_FORCE_NS indicates support for MPAM3_EL3.FORCE_NS bit. Defined values are:

~~Reserved, RES0.~~

HAS_FORCE_NS	Meaning
0b0	The FORCE_NS bit is not implemented in MPAM3_EL3.
0b1	The FORCE_NS bit is implemented in MPAM3_EL3.

When MPAM3_EL3.FORCE_NS == 1, accesses from the Secure execution state have MPAM_NS == 1.

~~Otherwise:~~

~~Reserved, RES0.~~

Bit [59]

Reserved, RES0.

HAS_TIDR, bit [58]

~~From Armv8.6:~~

HAS_TIDR indicates support for MPAM2_EL2.TIDR bit. Defined values are:

HAS_TIDR	Meaning
0b0	The TIDR bit is not implemented in MPAM2_EL2.
0b1	The TIDR bit is implemented in MPAM2_EL2.

~~Otherwise:~~

~~Reserved, RES0.~~

Bits [57:40]

Reserved, RES0.

PMG_MAX, bits [39:32]

The largest value of PMG that the implementation can generate. The PMG_I and PMG_D fields of every MPAMn_ELx must implement at least enough bits to represent PMG_MAX.

Bits [31:21]

Reserved, RES0.

VPMR_MAX, bits [20:18]

If HAS_HCR == 0, VPMR_MAX must be 0b000. Otherwise, it indicates the maximum register index n for the MPAMVPM<n>_EL2 registers.

HAS_HCR, bit [17]

HAS_HCR indicates that the PE implementation supports MPAM virtualization, including MPAMHCR_EL2, MPAMVPMV_EL2 and MPAMVPM<n>_EL2 with n in the range 0 to VPMR_MAX. Must be 0 if EL2 is not implemented in either security state.

HAS_HCR	Meaning
0b0	MPAM virtualization is not supported.
0b1	MPAM virtualization is supported.

Bit [16]

Reserved, RES0.

PARTID_MAX, bits [15:0]

The largest value of PARTID that the implementation can generate. The PARTID_I and PARTID_D fields of every MPAMn_ELx must implement at least enough bits to represent PARTID_MAX.

Accessing the MPAMIDR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, MPAMIDR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1010	0b0100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MPAMIDR_EL1.HAS_HCR == '1' &&
MPAMHCR_EL2.TRAP_MPAMIDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MPAMIDR_EL1.HAS_TIDR == '1' && MPAM2_EL2.TIDR ==
'1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return MPAMIDR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && MPAM3_EL3.TRAPLOWER == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return MPAMIDR_EL1;
elsif PSTATE.EL == EL3 then
    return MPAMIDR_EL1;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MVFR0_EL1, AArch32 Media and VFP Feature Register 0

The MVFR0_EL1 characteristics are:

Purpose

Describes the features provided by the AArch32 Advanced SIMD and Floating-point implementation.

Must be interpreted with MVFR1_EL1 and MVFR2_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register MVFR0_EL1 bits [31:0] are architecturally mapped to AArch32 System register MVFR0[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to MVFR0_EL1 are UNKNOWN.

In an implementation where at least one Exception level supports execution in AArch32 state, but there is no support for Advanced SIMD and floating-point operation, this register is RAZ.

~~In an AArch64 only implementation, this register is UNKNOWN.~~

Attributes

MVFR0_EL1 is a 64-bit register.

Field descriptions

The MVFR0_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
FPRound				FPShVec				FPSqrt				FPDivide				FPTrap				FPDP				FPSP				SIMDReg			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

FPRound, bits [31:28]

Floating-Point Rounding modes. Indicates whether the floating-point implementation provides support for rounding modes. Defined values are:

FPRound	Meaning
0b0000	Not implemented, or only Round to Nearest mode supported, except that Round towards Zero mode is supported for VCVT instructions that always use that rounding mode regardless of the FPSCR setting.
0b0001	All rounding modes supported.

All other values are reserved.

In Armv8-A the permitted values are `0b0000` and `0b0001`.

FPShVec, bits [27:24]

Short Vectors. Indicates whether the floating-point implementation provides support for the use of short vectors. Defined values are:

FPShVec	Meaning
`0b0000`	Short vectors not supported.
`0b0001`	Short vector operation supported.

All other values are reserved.

In Armv8-A the only permitted value is `0b0000`.

FPSqrt, bits [23:20]

Square Root. Indicates whether the floating-point implementation provides support for the ARMv6 VFP square root operations. Defined values are:

FPSqrt	Meaning
`0b0000`	Not supported in hardware.
`0b0001`	Supported.

All other values are reserved.

In Armv8-A the permitted values are `0b0000` and `0b0001`.

The VSQRT.F32 instruction also requires the single-precision floating-point attribute, bits [7:4], and the VSQRT.F64 instruction also requires the double-precision floating-point attribute, bits [11:8].

FPDivide, bits [19:16]

Indicates whether the floating-point implementation provides support for VFP divide operations. Defined values are:

FPDivide	Meaning
`0b0000`	Not supported in hardware.
`0b0001`	Supported.

All other values are reserved.

In Armv8-A the permitted values are `0b0000` and `0b0001`.

The VDIV.F32 instruction also requires the single-precision floating-point attribute, bits [7:4], and the VDIV.F64 instruction also requires the double-precision floating-point attribute, bits [11:8].

FPTrap, bits [15:12]

Floating Point Exception Trapping. Indicates whether the floating-point implementation provides support for exception trapping. Defined values are:

FPTrap	Meaning
`0b0000`	Not supported.
`0b0001`	Supported.

All other values are reserved.

A value of `0b0001` indicates that, when the corresponding trap is enabled, a floating-point exception generates an exception.

FPDP, bits [11:8]

Double Precision. Indicates whether the floating-point implementation provides support for double-precision operations. Defined values are:

FPDP	Meaning
0b0000	Not supported in hardware.
0b0001	Supported, VFPv2.
0b0010	Supported, VFPv3, VFPv4, or Armv8. VFPv3 and Armv8 add an instruction to load a double-precision floating-point constant, and conversions between double-precision and fixed-point values.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0010.

A value of 0b0001 or 0b0010 indicates support for all VFP double-precision instructions in the supported version of VFP, except that, in addition to this field being nonzero:

- VSQRT.F64 is only available if the Square root field is 0b0001.
- VDIV.F64 is only available if the Divide field is 0b0001.
- Conversion between double-precision and single-precision is only available if the single-precision field is nonzero.

FPSP, bits [7:4]

Single Precision. Indicates whether the floating-point implementation provides support for single-precision operations. Defined values are:

FPSP	Meaning
0b0000	Not supported in hardware.
0b0001	Supported, VFPv2.
0b0010	Supported, VFPv3 or VFPv4. VFPv3 adds an instruction to load a single-precision floating-point constant, and conversions between single-precision and fixed-point values.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0010.

A value of 0b0001 or 0b0010 indicates support for all VFP single-precision instructions in the supported version of VFP, except that, in addition to this field being nonzero:

- VSQRT.F32 is only available if the Square root field is 0b0001.
- VDIV.F32 is only available if the Divide field is 0b0001.
- Conversion between double-precision and single-precision is only available if the double-precision field is nonzero.

SIMDReg, bits [3:0]

Advanced SIMD registers. Indicates whether the Advanced SIMD and floating-point implementation provides support for the Advanced SIMD and floating-point register bank. Defined values are:

SIMDReg	Meaning
0b0000	The implementation has no Advanced SIMD and floating-point support.
0b0001	The implementation includes floating-point support with 16 x 64-bit registers.
0b0010	The implementation includes Advanced SIMD and floating-point support with 32 x 64-bit registers.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0010.

Accessing the MVFR0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, MVFR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return MVFR0_EL1;
elsif PSTATE.EL == EL2 then
    return MVFR0_EL1;
elsif PSTATE.EL == EL3 then
    return MVFR0_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MVFR1_EL1, AArch32 Media and VFP Feature Register 1

The MVFR1_EL1 characteristics are:

Purpose

Describes the features provided by the AArch32 Advanced SIMD and Floating-point implementation.

Must be interpreted with MVFR0_EL1 and MVFR2_EL1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

AArch64 System register MVFR1_EL1 bits [31:0] are architecturally mapped to AArch32 System register MVFR1[31:0].

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to MVFR1_EL1 are UNKNOWN.

In an implementation where at least one Exception level supports execution in AArch32 state, but there is no support for Advanced SIMD and floating-point operation, this register is RAZ.

~~In an AArch64 only implementation, this register is UNKNOWN.~~

Attributes

MVFR1_EL1 is a 64-bit register.

Field descriptions

The MVFR1_EL1 bit assignments are:



Bits [63:32]

Reserved, RES0.

SIMDFMAC, bits [31:28]

Advanced SIMD Fused Multiply-Accumulate. Indicates whether the Advanced SIMD implementation provides fused multiply accumulate instructions. Defined values are:

SIMDFMAC	Meaning
0b0000	Not implemented.
0b0001	Implemented.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

The Advanced SIMD and floating-point implementations must provide the same level of support for these instructions.

FPHP, bits [27:24]

Floating Point Half Precision. Indicates the level of half-precision floating-point support. Defined values are:

FPHP	Meaning
0b0000	Not supported.
0b0001	Floating-point half-precision conversion instructions are supported for conversion between single-precision and half-precision.
0b0010	As for 0b0001, and adds instructions for conversion between double-precision and half-precision.
0b0011	As for 0b0010, and adds support for half-precision floating-point arithmetic.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 in an implementation without floating-point support.
- 0b0010 in an implementation with floating-point support that does not include the ARMv8.2-FP16 extension.
- 0b0011 in an implementation with floating-point support that includes the ARMv8.2-FP16 extension.

The level of support indicated by this field must be equivalent to the level of support indicated by the SIMDHP field, meaning the permitted values are:

Half Precision instructions supported	FPHP	SIMDHP
No support	0b0000	0b0000
Conversions only	0b0010	0b0001
Conversions and arithmetic	0b0011	0b0010

SIMDHP, bits [23:20]

Advanced SIMD Half Precision. Indicates the level of half-precision floating-point support. Defined values are:

SIMDHP	Meaning
0b0000	Not supported.
0b0001	SIMD half-precision conversion instructions are supported for conversion between single-precision and half-precision.
0b0010	As for 0b0001, and adds support for half-precision floating-point arithmetic.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 in an implementation without SIMD floating-point support.
- 0b0010 in an implementation with SIMD floating-point support that does not include the ARMv8.2-FP16 extension.
- 0b0011 in an implementation with SIMD floating-point support that includes the ARMv8.2-FP16 extension.

The level of support indicated by this field must be equivalent to the level of support indicated by the FPHP field, meaning the permitted values are:

Half Precision instructions supported	FPHP	SIMDHP
No support	0b0000	0b0000
Conversions only	0b0010	0b0001
Conversions and arithmetic	0b0011	0b0010

SIMDSP, bits [19:16]

Advanced SIMD Single Precision. Indicates whether the Advanced SIMD and floating-point implementation provides single-precision floating-point instructions. Defined values are:

SIMDSP	Meaning
0b0000	Not implemented.
0b0001	Implemented. This value is permitted only if the SIMDInt field is 0b0001.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

SIMDInt, bits [15:12]

Advanced SIMD Integer. Indicates whether the Advanced SIMD and floating-point implementation provides integer instructions. Defined values are:

SIMDInt	Meaning
0b0000	Not implemented.
0b0001	Implemented.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

SIMDLS, bits [11:8]

Advanced SIMD Load/Store. Indicates whether the Advanced SIMD and floating-point implementation provides load/store instructions. Defined values are:

SIMDLS	Meaning
0b0000	Not implemented.
0b0001	Implemented.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

FPDNaN, bits [7:4]

Default NaN mode. Indicates whether the floating-point implementation provides support only for the Default NaN mode. Defined values are:

FPDNaN	Meaning
0b0000	Not implemented, or hardware supports only the Default NaN mode.
0b0001	Hardware supports propagation of NaN values.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

FPFtZ, bits [3:0]

Flush to Zero mode. Indicates whether the floating-point implementation provides support only for the Flush-to-Zero mode of operation. Defined values are:

FPFtZ	Meaning
0b0000	Not implemented, or hardware supports only the Flush-to-Zero mode of operation.
0b0001	Hardware supports full denormalized number arithmetic.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

Accessing the MVFR1_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, MVFR1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return MVFR1_EL1;
elsif PSTATE.EL == EL2 then
    return MVFR1_EL1;
elsif PSTATE.EL == EL3 then
    return MVFR1_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MVFR2_EL1, AArch32 Media and VFP Feature Register 2

The MVFR2_EL1 characteristics are:

Purpose

Describes the features provided by the AArch32 Advanced SIMD and Floating-point implementation.

Must be interpreted with MVFR0_EL1 and MVFR1_EL1.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D7.1.3.

Configuration

AArch64 System register MVFR2_EL1 bits [31:0] are architecturally mapped to AArch32 System register MVFR2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to MVFR2_EL1 are UNKNOWN.

In an implementation where at least one Exception level supports execution in AArch32 state, but there is no support for Advanced SIMD and floating-point operation, this register is RAZ.

~~In an AArch64 only implementation, this register is UNKNOWN.~~

Attributes

MVFR2_EL1 is a 64-bit register.

Field descriptions

The MVFR2_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																												FPMisc			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:8]

Reserved, RES0.

FPMisc, bits [7:4]

Indicates whether the floating-point implementation provides support for miscellaneous VFP features.

FPMisc	Meaning
0b0000	Not implemented, or no support for miscellaneous features.
0b0001	Support for Floating-point selection.
0b0010	As 0b0001, and Floating-point Conversion to Integer with Directed Rounding modes.
0b0011	As 0b0010, and Floating-point Round to Integer Floating-point.
0b0100	As 0b0011, and Floating-point MaxNum and MinNum.

All other values are reserved.

In Armv8-A, the permitted values are `0b0000` and `0b0100`.

SIMDMisc, bits [3:0]

Indicates whether the Advanced SIMD implementation provides support for miscellaneous Advanced SIMD features.

SIMDMisc	Meaning
`0b0000`	Not implemented, or no support for miscellaneous features.
`0b0001`	Floating-point Conversion to Integer with Directed Rounding modes.
`0b0010`	As `0b0001`, and Floating-point Round to Integer Floating-point.
`0b0011`	As `0b0010`, and Floating-point MaxNum and MinNum.

All other values are reserved.

In Armv8-A, the permitted values are `0b0000` and `0b0011`.

Accessing the MVFR2_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, MVFR2_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0011	0b010

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return MVFR2_EL1;
elsif PSTATE.EL == EL2 then
    return MVFR2_EL1;
elsif PSTATE.EL == EL3 then
    return MVFR2_EL1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

NZCV, Condition Flags

The NZCV characteristics are:

Purpose

Allows access to the condition flags.

Configuration

There are no configuration notes.

Attributes

NZCV is a 64-bit register.

Field descriptions

The NZCV bit assignments are:



Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative condition flag. Set to 1 if the result of the last flag-setting instruction was negative.

Z, bit [30]

Zero condition flag. Set to 1 if the result of the last flag-setting instruction was zero, and to 0 otherwise. A result of zero often indicates an equal result from a comparison.

C, bit [29]

Carry condition flag. Set to 1 if the last flag-setting instruction resulted in a carry condition, for example an unsigned overflow on an addition.

V, bit [28]

Overflow condition flag. Set to 1 if the last flag-setting instruction resulted in an overflow condition, for example a signed overflow on an addition.

Bits [27:0]

Reserved, RES0.

Accessing the NZCV

Accesses to this register use the following encodings:

MRS <Xt>, NZCV

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0010	0b000

```
if PSTATE.EL == EL0 then
    return Zeros(32):PSTATE.<N,Z,C,V>:Zeros(28);
elsif PSTATE.EL == EL1 then
    return Zeros(32):PSTATE.<N,Z,C,V>:Zeros(28);
elsif PSTATE.EL == EL2 then
    return Zeros(32):PSTATE.<N,Z,C,V>:Zeros(28);
elsif PSTATE.EL == EL3 then
    return Zeros(32):PSTATE.<N,Z,C,V>:Zeros(28);
```

MSR NZCV, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0010	0b000

```
if PSTATE.EL == EL0 then
    PSTATE.<N,Z,C,V> = X[t]<31:28>;
elsif PSTATE.EL == EL1 then
    PSTATE.<N,Z,C,V> = X[t]<31:28>;
elsif PSTATE.EL == EL2 then
    PSTATE.<N,Z,C,V> = X[t]<31:28>;
elsif PSTATE.EL == EL3 then
    PSTATE.<N,Z,C,V> = X[t]<31:28>;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

OSECCR_EL1, OS Lock Exception Catch Control Register

The OSECCR_EL1 characteristics are:

Purpose

Provides a mechanism for an operating system to access the contents of EDECCR that are otherwise invisible to software, so it can save/restore the contents of EDECCR over powerdown on behalf of the external debugger.

Configuration

AArch64 System register OSECCR_EL1 bits [31:0] are architecturally mapped to AArch32 System register DBGOSECCR[31:0] .

AArch64 System register OSECCR_EL1 bits [31:0] are architecturally mapped to External register EDECCR[31:0] .

If OSLSR_EL1.OSLK == 0, then OSECCR_EL1 returns an UNKNOWN value on reads and ignores writes.

Attributes

OSECCR_EL1 is a 64-bit register.

Field descriptions

The OSECCR_EL1 bit assignments are:

When OSLSR_EL1.OSLK~~DBGOSLSR.OSLK~~ == 1:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
EDECCR																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

EDECCR, bits [31:0]

Used for save/restore to EDECCR over powerdown.

Reads or writes to this field are indirect accesses to EDECCR.

Accessing the OSECCR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, OSECCR_EL1
```

op0	op1	CRn	CRm	op2
0b10	0b000	0b0000	0b0110	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.OSECCR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return OSECCR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return OSECCR_EL1;
elsif PSTATE.EL == EL3 then
    return OSECCR_EL1;
```

```
MSR OSECCR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b10	0b000	0b0000	0b0110	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.OSECCR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        OSECCR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        OSECCR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    OSECCR_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PAN, Privileged Access Never

The PAN characteristics are:

Purpose

Allows access to the Privileged Access Never bit.

Configuration

This register is present only when ARMv8.1-PAN is implemented. Otherwise, direct accesses to PAN are UNDEFINED.

Attributes

PAN is a 64-bit register.

Field descriptions

The PAN bit assignments are:



Bits [63:23]

Reserved, RES0.

PAN, bit [22]

Privileged Access Never.

PAN	Meaning
0b0	Privileged reads and write are not disabled by this mechanism.
0b1	Disables privileged read and write accesses to addresses accessible at EL0 for an enabled stage 1 translation regime that defines the EL0 permissions.

The value of this bit is usually preserved on taking an exception, except in the following situations:

- When the target of the exception is EL1, and the value of the SCTLR_EL1.SPAN bit is 0, this bit is set to 1.
- When the target of the exception is EL2, HCR_EL2.{E2H, TGE} is {1, 1}, and the value of the SCTLR_EL2.SPAN bit is 0, this bit is set to 1.

Bits [21:0]

Reserved, RES0.

Accessing the PAN

~~For details on the operation of the MSR (immediate) accessor, see MSR (immediate) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

MRS <Xt>, PAN

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0010	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    return Zeros(41):PSTATE.PAN:Zeros(22);
elsif PSTATE.EL == EL2 then
    return Zeros(41):PSTATE.PAN:Zeros(22);
elsif PSTATE.EL == EL3 then
    return Zeros(41):PSTATE.PAN:Zeros(22);
```

MSR PAN, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0010	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    PSTATE.PAN = X[t]<22>;
elsif PSTATE.EL == EL2 then
    PSTATE.PAN = X[t]<22>;
elsif PSTATE.EL == EL3 then
    PSTATE.PAN = X[t]<22>;
```

MSR PAN, #<imm>

op0	op1	CRn	op2
0b00	0b000	0b0100	0b100

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PAR_EL1, Physical Address Register

The PAR_EL1 characteristics are:

Purpose

Returns the output address (OA) from an Address translation instruction that executed successfully, or fault information if the instruction did not execute successfully.

Configuration

AArch64 System register PAR_EL1 bits [63:0] are architecturally mapped to AArch32 System register PAR[63:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PAR_EL1 is a 64-bit register.

Field descriptions

The PAR_EL1 bit assignments are:

When PAR_EL1.F == 0b0:



This section describes the register value returned by the successful execution of an Address translation instruction. Software might subsequently write a different value to the register, and that write does not affect the operation of the PE.

On a successful conversion, the PAR_EL1 can return a value that indicates the resulting attributes, rather than the values that appear in the translation table descriptors. More precisely:

- The PAR_EL1.{ATTR, SH} fields are permitted to report the resulting attributes, as determined by any permitted implementation choices and any applicable configuration bits, instead of reporting the values that appear in the translation table descriptors.
- See the PAR_EL1.NS bit description for constraints on the value it returns.

ATTR, bits [63:56]

Memory attributes for the returned output address. This field uses the same encoding as the Attr<n> fields in MAIR_EL1, MAIR_EL2, and MAIR_EL3.

The value returned in this field can be the resulting attribute, as determined by any permitted implementation choices and any applicable configuration bits, instead of the value that appears in the translation table descriptor.

This field resets to an architecturally UNKNOWN value.

Bits [55:52]

Reserved, RES0.

PA[51:48], bits [51:48]

When ARMv8.2-LPA is implemented:

Extension to PA[47:12]. See PA[47:12] for more details.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PA[47:12], bits [47:12]

Output address. The output address (OA) corresponding to the supplied input address. This field returns address bits[47:12].

When ARMv8.2-LPA is implemented, and 52-bit addresses and a 64KB translation granule are in use, the PA[51:48] bits form the upper part of the address value. Otherwise the PA[51:48] bits are RES0.

For implementations with fewer than 48 physical address bits, the corresponding upper bits in this field are RES0.

This field resets to an architecturally UNKNOWN value.

Bit [11]

Reserved, RES1.

IMPLEMENTATION DEFINED, bit [10]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

NS, bit [9]

Non-secure. The NS attribute for a translation table entry from a Secure translation regime.

For a result from a Secure translation regime, when SCR_EL3.EEL2 is 1, this bit reflects the Security state of the intermediate physical address space of the translation for the instructions:

- In AArch64 state: AT S1E1R, AT S1E1W, AT S1E1RP, AT S1E1WP, AT S1E0R, and AT S1E0W.
- In AArch32 state: ATS1CPR, ATS1CPW, ATS1CPRP, ATS1CPWP, ATS1CUR, and ATS1CUW.

Otherwise, this bit reflects the Security state of the physical address space of the translation. This means it reflects the effect of the NSTable bits of earlier levels of the translation table walk if those NSTable bits have an effect on the translation.

For a result from a Non-secure translation regime, this bit is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

SH, bits [8:7]

Shareability attribute, for the returned output address. Permitted values are:

SH	Meaning
0b00	Non-shareable.
0b10	Outer Shareable.
0b11	Inner Shareable.

The value 0b01 is reserved.

Note

This field returns the value `0b10` for:

- Any type of Device memory.
- Normal memory with both Inner Non-cacheable and Outer Non-cacheable attributes.

The value returned in this field can be the resulting attribute, as determined by any permitted implementation choices and any applicable configuration bits, instead of the value that appears in the translation table descriptor.

This field resets to an architecturally UNKNOWN value.

Bits [6:1]

Reserved, RES0.

F, bit [0]

Indicates whether the instruction performed a successful address translation.

F	Meaning
`0b0`	Address translation completed successfully.

This field resets to an architecturally UNKNOWN value.

When PAR_EL1.F == 0b1:



This section describes the register value returned by a fault on the execution of an Address translation instruction. Software might subsequently write a different value to the register, and that write does not affect the operation of the PE.

IMPLEMENTATION DEFINED, bits [63:56]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

IMPLEMENTATION DEFINED, bits [55:52]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

IMPLEMENTATION DEFINED, bits [51:48]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Bits [47:12]

Reserved, RES0.

Bit [11]

Reserved, RES1.

Bit [10]

Reserved, RES0.

S, bit [9]

Indicates the translation stage at which the translation aborted:

S	Meaning
0b0	Translation aborted because of a fault in the stage 1 translation.
0b1	Translation aborted because of a fault in the stage 2 translation.

This field resets to an architecturally UNKNOWN value.

PTW, bit [8]

If this bit is set to 1, it indicates the translation aborted because of a stage 2 fault during a stage 1 translation table walk.

This field resets to an architecturally UNKNOWN value.

Bit [7]

Reserved, RES0.

FST, bits [6:1]

Fault status code, as shown in the Data Abort ESR encoding.

FST	Meaning	Applies when
0b000000	Address size fault, level 0 of translation or translation table base register.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000100	Translation fault, level 0.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk or hardware update of translation table.	
0b010001	Synchronous Tag Check Fault.	When ARMv8.5-MemTag is implemented
0b010100	Synchronous External abort, on translation table walk or hardware update of translation table, level 0.	
0b010101	Synchronous External abort, on translation table walk or hardware update of translation table, level 1.	
0b010110	Synchronous External abort, on translation table walk or hardware update of translation table, level 2.	
0b010111	Synchronous External abort, on translation table walk or hardware update of translation table, level 3.	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011100	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 0.	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 1.	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 2.	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk or hardware update of translation table, level 3.	When RAS is not implemented
0b100001	Alignment fault.	
0b110000	TLB conflict abort.	
0b110001	Unsupported atomic hardware update fault.	When ARMv8.1-TTHM is implemented
0b111101	Section Domain fault, from an AArch32 stage 1 EL1&0 translation regime using Short-descriptor translation table format.	When AArch32 is supported at any Exception level and EL1 is capable of using AArch32
0b111110	Page Domain fault, from an AArch32 stage 1 EL1&0	When AArch32 is supported at any

translation regime using Short-descriptor translation table format.	Exception level and EL1 is capable of using AArch32

This field resets to an architecturally UNKNOWN value.

F, bit [0]

Indicates whether the instruction performed a successful address translation.

F	Meaning
0b1	Address translation aborted.

This field resets to an architecturally UNKNOWN value.

Accessing the PAR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, PAR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0111	0b0100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.PAR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        return PAR_EL1;
elsif PSTATE.EL == EL2 then
    return PAR_EL1;
elsif PSTATE.EL == EL3 then
    return PAR_EL1;
```

```
MSR PAR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0111	0b0100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.PAR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        PAR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    PAR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    PAR_EL1 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMBSR_EL1, Profiling Buffer Status/syndrome Register

The PMBSR_EL1 characteristics are:

Purpose

Provides syndrome information to software when the buffer is disabled because the management interrupt has been raised.

Configuration

This register is present only when SPE is implemented. Otherwise, direct accesses to PMBSR_EL1 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PMBSR_EL1 is a 64-bit register.

Field descriptions

The PMBSR_EL1 bit assignments are:



Bits [63:32]

Reserved, RES0.

EC, bits [31:26]

Exception class

Top-level description of the cause of the buffer management event

EC	Meaning	MSS
0b000000	Other buffer management event. All buffer management events other than those described by other defined Exception class codes.	MSS encoding for other buffer management events
0b100100	Stage 1 Data Abort on write to Profiling Buffer.	MSS encoding for stage 1 or stage 2 Data Aborts on write to buffer
0b100101	Stage 2 Data Abort on write to Profiling Buffer.	MSS encoding for stage 1 or stage 2 Data Aborts on write to buffer

All other values are reserved. Reserved values might be defined in a future version of the architecture.

Writing a reserved value to this field will make the value of this field UNKNOWN. Values that are not supported act as reserved values when writing to this register.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bits [25:20]

Reserved, RES0.

DL, bit [19]

Partial record lost.

Following a buffer management event other than an asynchronous External abort, indicates whether the last record written to the Profiling Buffer is complete.

DL	Meaning
0b0	PMBPTR_EL1 points to the first byte after the last complete record written to the Profiling Buffer.
0b1	Part of a record was lost because of a buffer management event or synchronous External abort. PMBPTR_EL1 might not point to the first byte after the last complete record written to the buffer, and so restarting collection might result in a data record stream that software cannot parse. All records prior to the last record have been written to the buffer.

When the buffer management event was because of an asynchronous external abort, this bit is set to 1 and software must not assume that any valid data has been written to the Profiling Buffer.

This bit is RES0 if the PE never sets this bit as a result of a buffer management event caused by an asynchronous External abort.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

EA, bit [18]

External abort.

EA	Meaning
0b0	An external abort has not been asserted.
0b1	An external abort has been asserted and detected by the Statistical Profiling Extension.

This bit is RES0 if the PE never sets this bit as the result of an External abort.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

S, bit [17]

Service

S	Meaning
0b0	PMBIRQ is not asserted.
0b1	PMBIRQ is asserted. All profiling data has either been written to the buffer or discarded.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

COLL, bit [16]

Collision detected.

COLL	Meaning
0b0	No collision events detected.
0b1	At least one collision event was recorded.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

MSS, bits [15:0]

Management Event Specific Syndrome.

Contains syndrome specific to the management event.

The syndrome contents for each management event are described in the following sections.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

MSS encoding for stage 1 or stage 2 Data Aborts on write to buffer



Bits [15:6]

Reserved, RES0.

FSC, bits [5:0]

Fault status code

FSC	Meaning	Applies when
0b0000000b0000xx	Address sizeSize fault,fault. levelBits [1:0] ofencode translationthe or translation table base register.level.	
0b0000010b0001xx	AddressTranslation sizefault. fault,Bits level[1:0] 1.encode the level.	
0b0000100b0010xx	AddressAccess sizeFlag fault,fault. levelBits 2.[1:0] encode the level.	
0b0000110b0011xx	AddressPermission sizefault. fault,Bits level[1:0] 3.encode the level.	
0b0001000b010000	TranslationSynchronous fault,External levelabort 0.on write.	
0b0001010b0101xx	TranslationSynchronous fault,External levelabort 1.on translation table walk or hardware update of translation table. Bits [1:0] encode the level.	
0b0001100b010001	TranslationAsynchronous fault,External levelabort 2.on write.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk or hardware update of translation table.	
0b010001	Asynchronous External abort.	
0b010100	Synchronous External abort, on translation table walk or hardware update of translation table, level 0.	
0b010101	Synchronous External abort, on translation table walk or hardware update of translation table, level 1.	
0b010110	Synchronous External abort, on translation table walk or hardware update of translation table, level 2.	
0b010111	Synchronous External abort, on translation table walk or hardware update of translation table, level 3.	
0b100001	Alignment fault.	
0b110000	TLB conflictConflict abort.fault.	
0b110001	Unsupported atomic hardware update fault.	When ARMv8.1-TTHM is implemented

Writing a reserved value to this field will make the value of this field UNKNOWN. Values that are not supported act as reserved values when writing to this register.

All other values are reserved. Reserved values might be defined in a future version of the architecture.

It is IMPLEMENTATION DEFINED whether each of the Access Flag fault, asynchronous External abort and synchronous External abort, Alignment fault, and TLB Conflict abort values can be generated by the PE. For more information see Faults and Watchpoints.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

MSS encoding for other buffer management events



Bits [15:6]

Reserved, RES0.

BSC, bits [5:0]

Buffer status code

BSC	Meaning
0b000000	Buffer not filled
0b000001	Buffer filled

All other values are reserved. Reserved values might be defined in a future version of the architecture.

Writing a reserved value to this field will make the value of this field UNKNOWN. Values that are not supported act as reserved values when writing to this register.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMBSR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, PMBSR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1001	0b1010	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.PMBSR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.E2PB == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '1x1' then
        return NVMem[0x820];
    else
        return PMBSR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMBSR_EL1;
elsif PSTATE.EL == EL3 then
    return PMBSR_EL1;
```

```
MSR PMBSR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1001	0b1010	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.PMBSR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.E2PB == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '1x1' then
        NVMem[0x820] = X[t];
    else
        PMBSR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMBSR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    PMBSR_EL1 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCCFILTR_EL0, Performance Monitors Cycle Count Filter Register

The PMCCFILTR_EL0 characteristics are:

Purpose

Determines the modes in which the Cycle Counter, PMCCNTR_EL0, increments.

Configuration

AArch64 System register PMCCFILTR_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMCCFILTR[31:0] .

AArch64 System register PMCCFILTR_EL0 bits [31:0] are architecturally mapped to External register PMCCFILTR_EL0[31:0] .

This register is present only when PMUv3 is implemented. Otherwise, direct accesses to PMCCFILTR_EL0 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PMCCFILTR_EL0 is a 64-bit register.

Field descriptions

The PMCCFILTR_EL0 bit assignments are:



Bits [63:32]

Reserved, RES0.

P, bit [31]

Privileged filtering bit. Controls counting in EL1.

If EL3 is implemented, then counting in Non-secure EL1 is further controlled by the PMCCFILTR_EL0.NSK bit.

P	Meaning
0b0	Count cycles in EL1.
0b1	Do not count cycles in EL1.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

U, bit [30]

User filtering bit. Controls counting in EL0.

If EL3 is implemented, then counting in Non-secure EL0 is further controlled by the PMCCFILTR_EL0.NSU bit.

U	Meaning
0b0	Count cycles in EL0.
0b1	Do not count cycles in EL0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSK, bit [29]

When ~~HaveEL(~~EL3 is implemented~~):~~

Non-secure EL1 (kernel) modes filtering bit. Controls counting in Non-secure EL1.

If the value of this bit is equal to the value of the PMCCFILTR_EL0.P bit, cycles in Non-secure EL1 are counted.

Otherwise, cycles in Non-secure EL1 are not counted.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NSU, bit [28]

When ~~HaveEL(~~EL3 is implemented~~):~~

Non-secure EL0 (Unprivileged) filtering bit. Controls counting in Non-secure EL0.

If the value of this bit is equal to the value of the PMCCFILTR_EL0.U bit, cycles in Non-secure EL0 are counted.

Otherwise, cycles in Non-secure EL0 are not counted.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NSH, bit [27]

When ~~HaveEL(~~EL2 is implemented~~):~~

EL2 (Hypervisor) filtering bit. Controls counting in EL2.

If Secure EL2 is implemented, counting in Secure EL2 is further controlled by the PMCCFILTR_EL0.SH bit.

NSH	Meaning
0b0	Do not count cycles in EL2.
0b1	Count cycles in EL2.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

M, bit [26]

When ~~HaveEL(~~EL3 is implemented~~):~~

Secure EL3 filtering bit.

If the value of this bit is equal to the value of the PMCCFILTR_EL0.P bit, cycles in Secure EL3 are counted.

Otherwise, cycles in Secure EL3 are not counted.

Most applications can ignore this field and set its value to 0.

Note

This field is not visible in the AArch32 PMCCFILTR System register.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [25]

Reserved, RES0.

SH, bit [24]

When ARMv8.4-SecEL2 is implemented:

Secure EL2 filtering.

If the value of this bit is not equal to the value of the PMCCFILTR_EL0.NSH bit, cycles in Secure EL2 are counted.

Otherwise, cycles in Secure EL2 are not counted.

If Secure EL2 is not implemented or is disabled, this field is RES0.

Note

This field is not visible in the AArch32 PMCCFILTR System register.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [23:0]

Reserved, RES0.

Accessing the PMCCFILTR_EL0

PMCCFILTR_EL0 can also be accessed by using PMXEVTYPER_EL0 with PMSELR_EL0.SEL set to `0b11111`.

Accesses to this register use the following encodings:

```
MRS <Xt>, PMCCFILTR_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b1111	0b111

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMCCFILTR_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMCCFILTR_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.PMCCFILTR_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMCCFILTR_EL0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMCCFILTR_EL0;
elsif PSTATE.EL == EL3 then
    return PMCCFILTR_EL0;
```

MSR PMCCFILTR_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b1111	0b111

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMCCFILTR_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMCCFILTR_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.PMCCFILTR_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMCCFILTR_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMCCFILTR_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    PMCCFILTR_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCR_EL0, Performance Monitors Control Register

The PMCR_EL0 characteristics are:

Purpose

Provides details of the Performance Monitors implementation, including the number of counters implemented, and configures and controls the counters.

Configuration

AArch64 System register PMCR_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMCR[31:0] .

AArch64 System register PMCR_EL0 bits [7:0] are architecturally mapped to External register PMCR_EL0[7:0] .

This register is present only when PMUv3 is implemented. Otherwise, direct accesses to PMCR_EL0 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PMCR_EL0 is a 64-bit register.

Field descriptions

The PMCR_EL0 bit assignments are:



Bits [63:32]

Reserved, RES0.

IMP, bits [31:24]

Implementer code. This field has an IMPLEMENTATION DEFINED value.

If this field is zero, then PMCR_EL0.IDCODE is RES0 and software must use the MIDR_EL1 to identify the PE.

Otherwise, this field and PMCR_EL0.IDCODE identifies the PMU implementation to software. The implementer codes are allocated by Arm. A non-zero value has the same interpretation as MIDR_EL1.Implementer.

Access to this field is **RO**.

IDCODE, bits [23:16]

When PMCR_EL0.IMP != 0x00:

Identification code. This field has an IMPLEMENTATION DEFINED value.

Each implementer must maintain a list of identification codes that are specific to the implementer. A specific implementation is identified by the combination of the implementer code and the identification code.

Access to this field is **RO**.

Otherwise:

Reserved, RES0.

N, bits [15:11]

Indicates the number of event counters implemented. This value is in the range of `0b00000`-`0b11111`. If the value is `0b00000` then only PMCCNTR_EL0 is implemented. If the value is `0b11111` PMCCNTR_EL0 and 31 event counters are implemented.

When EL2 is implemented and enabled for the current Security state, reads of this field from EL1 and EL0 return the value of MDCR_EL2.HPMN.

Access to this field is **RO**.

Bits [10:8]

Reserved, RES0.

LP, bit [7]

When ARMv8.5-PMU is implemented:

Long event counter enable. Determines when unsigned overflow is recorded by a counter overflow bit.

LP	Meaning
`0b0`	Event counter overflow on increment that causes unsigned overflow of PMEVCNTR<n>_EL0[31:0].
`0b1`	Event counter overflow on increment that causes unsigned overflow of PMEVCNTR<n>_EL0[63:0].

If EL2 is implemented and MDCR_EL2.HPMN or HDCR.HPMN is less than PMCR_EL0.N, this bit does not affect the operation of event counters in the range [HDCR.HPMN..(PMCR_EL0.N-1)] or [MDCR_EL2.HPMN..(PMCR_EL0.N-1)].

Note

The effect of MDCR_EL2.HPMN or HDCR.HPMN on the operation of this bit always applies if EL2 is implemented, at all Exception levels including EL2 and EL3, and regardless of whether EL2 is enabled in the current Security state. For more information, see the description of MDCR_EL2.HPMN or HDCR.HPMN.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

LC, bit [6]

When AArch32 is supported at any Exception level:

Long cycle counter enable. Determines when unsigned overflow is recorded by the cycle counter overflow bit.

LC	Meaning
`0b0`	Cycle counter overflow on increment that causes unsigned overflow of PMCCNTR_EL0[31:0].
`0b1`	Cycle counter overflow on increment that causes unsigned overflow of PMCCNTR_EL0[63:0].

Arm deprecates use of PMCR_EL0.LC = 0.

~~In an AArch64 only implementation, this field is RES1.~~

On a Warm reset, this field resets to an architecturally UNKNOWN value.

~~DP, bit [5]~~

~~When HaveEL(EL3) or (ARMv8.1-PMU is implemented and HaveEL(EL2)):~~

Otherwise:

Reserved, RES1.

DP, bit [5]

When EL3 is implemented or (ARMv8.1-PMU is implemented and EL2 is implemented):

Disable cycle counter when event counting is prohibited.

DP	Meaning
0b0	Cycle counting by PMCCNTR_EL0 is not affected by this bit.
0b1	When event counting for counters in the range [0..(MDCR_EL2.HPMN-1)] is prohibited, cycle counting by PMCCNTR_EL0 is disabled.

For more information about the interaction between the Performance Monitors and EL3, see 'Effect of EL3 and EL2' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

X, bit [4]

When the implementation includes a~~a~~n PMU event export bus:

Enable export of events in an IMPLEMENTATION DEFINED PMU event export bus.

X	Meaning
0b0	Do not export events.
0b1	Export events where not prohibited.

This field enables the exporting of events over an IMPLEMENTATION DEFINED PMU event export bus to another device, for example to an OPTIONAL PE trace unit.

No events are exported when counting is prohibited.

This field does not affect the generation of Performance Monitors overflow interrupt requests or signaling to a cross-trigger interface (CTI) that can be implemented as signals exported from the PE.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RAZ/WI.

D, bit [3]

When AArch32 is supported at any Exception level:

Clock divider.

D	Meaning
0b0	When enabled, PMCCNTR_EL0 counts every clock cycle.
0b1	When enabled, PMCCNTR_EL0 counts once every 64 clock cycles.

If PMCR_EL0.LC == 1, this bit is ignored and the cycle counter counts every clock cycle.

Arm deprecates use of PMCR_EL0.D = 1.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

C, bit [2]

Cycle counter reset. The effects of writing to this bit are:

C	Meaning
0b0	No action.
0b1	Reset PMCCNTR_EL0 to zero.

This bit is always RAZ.

Note

Resetting PMCCNTR_EL0 does not change the cycle counter overflow bit.

The value of PMCR_EL0.LC is ignored, and bits [63:0] of all affected event counters are reset.

Access to this field is **WO**.

P, bit [1]

Event counter reset. The effects of writing to this bit are:

P	Meaning
0b0	No action.
0b1	Reset all event counters accessible in the current Exception level, not including PMCCNTR_EL0, to zero.

This bit is always RAZ.

In EL0 and EL1:

- If EL2 is implemented and enabled in the current Security state, and MDCR_EL2.HPMN is less than PMCR_EL0.N, a write of 1 to this bit does not reset event counters in the range [MDCR_EL2.HPMN..(PMCR_EL0.N-1)].
- If EL2 is not implemented, EL2 is disabled in the current Security state, or MDCR_EL2.HPMN equals PMCR_EL0.N, a write of 1 to this bit resets all the event counters.

In EL2 and EL3, a write of 1 to this bit resets all the event counters.

Note

Resetting the event counters does not change the event counter overflow bits.

If ARMv8.5-PMU is implemented, the values of MDCR_EL2.HLP and PMCR_EL0.LP are ignored, and bits [63:0] of all affected event counters are reset.

Access to this field is **WO**.

E, bit [0]

Enable.

E	Meaning
0b0	All event counters in the range [0..(PMN-1)] and PMCCNTR_EL0, are disabled.
0b1	All event counters in the range [0..(PMN-1)] and PMCCNTR_EL0, are enabled by PMCNTENSET_EL0.

If EL2 is implemented, then:

- If EL2 is using AArch32, PMN is HDCR.HPMN.
- If EL2 is using AArch64, PMN is MDCR_EL2.HPMN.
- If PMN is less than PMCR_EL0.N, this bit does not affect the operation of event counters in the range [PMN..(PMCR_EL0.N-1)].

If EL2 is not implemented, PMN is PMCR_EL0.N.

Note

The effect of MDCR_EL2.HPMN or HDCR.HPMN on the operation of this bit always applies if EL2 is implemented, at all Exception levels including EL2 and EL3, and regardless of whether EL2 is enabled in the current Security state. For more information, see the description of MDCR_EL2.HPMN or HDCR.HPMN.

On a Warm reset, this field resets to 0.

Accessing the PMCR_EL0

Accesses to this register use the following encodings:

```
MRS <Xt>, PMCR_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1001	0b1100	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMCR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMCR_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMCR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMCR_EL0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMCR_EL0;
elsif PSTATE.EL == EL3 then
    return PMCR_EL0;
```

```
MSR PMCR_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1001	0b1100	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMCR_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMCR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMCR_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.PMCR_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMCR == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMCR_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMCR_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    PMCR_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMEVCNTR<n>_EL0, Performance Monitors Event Count Registers, n = 0 - 30

The PMEVCNTR<n>_EL0 characteristics are:

Purpose

Holds event counter n, which counts events, where n is 0 to 30.

Configuration

AArch64 System register PMEVCNTR<n>_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMEVCNTR<n>[31:0] .

AArch64 System register PMEVCNTR<n>_EL0 bits [31:0] are architecturally mapped to External register PMEVCNTR<n>_EL0[31:0] .

This register is present only when PMUv3 is implemented. Otherwise, direct accesses to PMEVCNTR<n>_EL0 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PMEVCNTR<n>_EL0 is a 64-bit register.

Field descriptions

The PMEVCNTR<n>_EL0 bit assignments are:

When ARMv8.5-PMU is implemented:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Event counter n																															
Event counter n																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Event counter n. Value of event counter n, where n is the number of this register and is a number from 0 to 30.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
Event counter n																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

Bits [31:0]

Event counter n. Value of event counter n, where n is the number of this register and is a number from 0 to 30.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMEVCNTR<n>_EL0

PMEVCNTR<n>_EL0 can also be accessed by using PMXEVCNTR_EL0 with PMSELR_EL0.SEL set to the value of <n>.

If ARMv8.6-FGT is implemented, and <n>EL2 is greaterimplemented thanand orenabled equalin to the numbercurrent ofSecurity accessible countersstate, thenfor thereads behaviorand ofwrites at EL1 and permitted reads and writes ofat EL0. PMEVCNTR<n>_EL0 is as follows:

- If <n> is an unimplemented event counter, the access is UNDEFINED.
- Otherwise, theif access<n> is trappedgreater than or equal to EL2. MDCR_EL2.HPMN, the access is trapped to EL2.

If <n> is greater than or equal to the number of accessible counters, reads and writes of PMEVCNTR<n>_EL0 are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

If ARMv8.6-FGT is not implemented, and <n> is greater than or equal to the numberabove ofbehaviors accessibledo counters,not then reads and writes ofapply: PMEVCNTR<n>_EL0 are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

- Accesses to the register are UNDEFINED.
- Accesses to the register behave as RAZ/WI.
- Accesses to the register execute as a NOP.
- If EL2 is implemented and enabled in the current Security state, and <n> is less than the number of implemented counters, accesses from EL1 or permitted accesses from EL0 are trapped to EL2.

Note

In EL0, an access is permitted if it is enabled by PMUSERENR_EL0.{ER,EN}.

If EL2 is implemented and enabled in the current Security state, in EL1 and EL0, MDCR_EL2.HPMN identifies the number of accessible counters. Otherwise, the number of accessible counters is the number of implemented counters. See MDCR_EL2.HPMN for more details.

Accesses to this register use the following encodings:

```
MRS <Xt>, PMEVCNTR<n>_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b10:n[4:3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.<ER,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMEVCNTR_EL0[UInt(CRm<1:0>:op2<2:0>)];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMEVCNTR_EL0[UInt(CRm<1:0>:op2<2:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMEVCNTR_EL0[UInt(CRm<1:0>:op2<2:0>)];
elsif PSTATE.EL == EL3 then
    return PMEVCNTR_EL0[UInt(CRm<1:0>:op2<2:0>)];
```

MSR PMEVCNTR<n>_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b10:n[4:3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMEVCNTR_EL0[UInt(CRm<1:0>:op2<2:0>)] = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMEVCNTR_EL0[UInt(CRm<1:0>:op2<2:0>)] = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMEVCNTR_EL0[UInt(CRm<1:0>:op2<2:0>)] = X[t];
elsif PSTATE.EL == EL3 then
    PMEVCNTR_EL0[UInt(CRm<1:0>:op2<2:0>)] = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMEVTYPER<n>_EL0, Performance Monitors Event Type Registers, n = 0 - 30

The PMEVTYPER<n>_EL0 characteristics are:

Purpose

Configures event counter n, where n is 0 to 30.

Configuration

AArch64 System register PMEVTYPER<n>_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMEVTYPER<n>[31:0] .

AArch64 System register PMEVTYPER<n>_EL0 bits [31:0] are architecturally mapped to External register PMEVTYPER<n>_EL0[31:0] .

This register is present only when PMUv3 is implemented. Otherwise, direct accesses to PMEVTYPER<n>_EL0 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PMEVTYPER<n>_EL0 is a 64-bit register.

Field descriptions

The PMEVTYPER<n>_EL0 bit assignments are:



Bits [63:32]

Reserved, RES0.

P, bit [31]

Privileged filtering bit. Controls counting in EL1.

If EL3 is implemented, then counting in Non-secure EL1 is further controlled by the PMEVTYPER<n>_EL0.NSK bit.

P	Meaning
0b0	Count events in EL1.
0b1	Do not count events in EL1.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

U, bit [30]

User filtering bit. Controls counting in EL0.

If EL3 is implemented, then counting in Non-secure EL0 is further controlled by the PMEVTYPER<n>_EL0.NSU bit.

U	Meaning
0b0	Count events in EL0.
0b1	Do not count events in EL0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSK, bit [29]

When HaveEL(EL3 is implemented):

Non-secure EL1 (kernel) modes filtering bit. Controls counting in Non-secure EL1.

If the value of this bit is equal to the value of the PMEVTYPER<n>_EL0.P bit, events in Non-secure EL1 are counted.

Otherwise, events in Non-secure EL1 are not counted.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NSU, bit [28]

When HaveEL(EL3 is implemented):

Non-secure EL0 (Unprivileged) filtering bit. Controls counting in Non-secure EL0.

If the value of this bit is equal to the value of the PMEVTYPER<n>_EL0.U bit, events in Non-secure EL0 are counted.

Otherwise, events in Non-secure EL0 are not counted.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NSH, bit [27]

When HaveEL(EL2 is implemented):

EL2 (Hypervisor) filtering bit. Controls counting in EL2.

If Secure EL2 is implemented, and EL3 is implemented, counting in Secure EL2 is further controlled by the PMEVTYPER<n>_EL0.SH bit.

NSH	Meaning
0b0	Do not count events in EL2.
0b1	Count events in EL2.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

M, bit [26]

When HaveEL(EL3 is implemented):

Secure EL3 filtering bit.

If the value of this bit is equal to the value of the PMEVTYPER<n>_EL0.P bit, events in Secure EL3 are counted.

Otherwise, events in Secure EL3 are not counted.

Most applications can ignore this field and set its value to `0b0`.

Note

This field is not visible in the AArch32 PMEVTYPER<n> System register.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

MT, bit [25]

When (ARMv8.6-MTPMU is implemented and enabled) or an IMPLEMENTATION DEFINED multi-threaded PMU Extension is implemented:

Multithreading.

MT	Meaning
`0b0`	Count events only on controlling PE.
`0b1`	Count events from any PE with the same affinity at level 1 and above as this PE.

Note

- When the lowest level of affinity consists of logical PEs that are implemented using a multi-threading type approach, an implementation is described as multi-threaded. That is, the performance of PEs at the lowest affinity level is highly interdependent.
- Events from a different thread of a multithreaded implementation are not Attributable to the thread counting the event.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SH, bit [24]

When ARMv8.4-SecEL2 is implemented and EL3 is implemented:

Secure EL2 filtering.

If the value of this bit is not equal to the value of the PMEVTYPER<n>_EL0.NSH bit, events in Secure EL2 are counted.

Otherwise, events in Secure EL2 are not counted.

Note

This field is not visible in the AArch32 PMEVTYPER<n> System register.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [23:16]

Reserved, RES0.

evtCount[15:10], bits [15:10]

When ARMv8.1-PMU is implemented:

Extension to evtCount[9:0]. See evtCount[9:0] for more details.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

evtCount[9:0], bits [9:0]

Event to count. The event number of the event that is counted by event counter PMEVCNTR<n>_EL0.

Software must program this field with an event that is supported by the PE being programmed.

The ranges of event numbers allocated to each type of event are shown in Allocation of the PMU event number space.

If evtCount is programmed to an event that is reserved or not supported by the PE, the behavior depends on the value written:

- For the range `0x0000` to `0x003F`, no events are counted, and the value returned by a direct or external read of the evtCount field is the value written to the field.
- If 16-bit evtCount is implemented, for the range `0x4000` to `0x403F`, no events are counted, and the value returned by a direct or external read of the evtCount field is the value written to the field.
- For IMPLEMENTATION DEFINED events, it is UNPREDICTABLE what event, if any, is counted, and the value returned by a direct or external read of the evtCount field is UNKNOWN.

Note

UNPREDICTABLE means the event must not expose privileged information.

Arm recommends that the behavior across a family of implementations is defined such that if a given implementation does not include an event from a set of common IMPLEMENTATION DEFINED events, then no event is counted and the value read back on evtCount is the value written.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMEVTYPER<n>_EL0

PMEVTYPER<n>_EL0 can also be accessed by using PMXEVTYPER_EL0 with PMSELR_EL0.SEL set to n.

If ARMv8.6-FGT is implemented, and <n>EL2 is greaterimplemented thanand orenabled equalin to the numbercurrent ofSecurity accessible counterstate, thenfor thereads behaviorand ofwrites at EL1 and permitted reads and writes ofat EL0: PMEVTYPER<n>_EL0 is as follows:

- If <n> is an unimplemented event counter, the access is UNDEFINED.
- Otherwise, theif access<n> is trappedgreater than or equal to EL2. MDCR_EL2.HPMN, the access is trapped to EL2.

~~If <n> is greater than or equal to the number of accessible counters, reads and writes of PMEVTYPER<n>_EL0 are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:~~

If ARMv8.6-FGT is not implemented~~,~~ and <n> is greater than or equal to the number~~above~~ of~~behaviors~~ accessible~~do~~ counters,~~not~~ then reads and writes of~~apply:~~ PMEVTYPER<n>_EL0 are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

- Accesses to the register are UNDEFINED.
- Accesses to the register behave as RAZ/WI.
- Accesses to the register execute as a NOP.
- If EL2 is implemented and enabled in the current Security state, and <n> is less than the number of implemented counters, accesses from EL1 or permitted accesses from EL0 are trapped to EL2.

Note

In EL0, an access is permitted if it is enabled by PMUSERENR_EL0.EN.

If EL2 is implemented and enabled in the current Security state, in EL1 and EL0, MDCR_EL2.HPMN identifies the number of accessible counters. Otherwise, the number of accessible counters is the number of implemented counters. See MDCR_EL2.HPMN for more details.

Accesses to this register use the following encodings:

```
MRS <Xt>, PMEVTYPER<n>_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1110	0b11:n[4:3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMEVTYPER_EL0[UInt(CRm<1:0>:op2<2:0>)];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMEVTYPER_EL0[UInt(CRm<1:0>:op2<2:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMEVTYPER_EL0[UInt(CRm<1:0>:op2<2:0>)];
elsif PSTATE.EL == EL3 then
    return PMEVTYPER_EL0[UInt(CRm<1:0>:op2<2:0>)];
```

```
MSR PMEVTYPER<n>_EL0, <Xt>
```

op0	op1	CRn	CRm	op2

0b11	0b011	0b1110	0b11:n[4:3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMEVTYPER_EL0[UInt(CRm<1:0>:op2<2:0>)] = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMEVTYPER_EL0[UInt(CRm<1:0>:op2<2:0>)] = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMEVTYPER_EL0[UInt(CRm<1:0>:op2<2:0>)] = X[t];
elsif PSTATE.EL == EL3 then
    PMEVTYPER_EL0[UInt(CRm<1:0>:op2<2:0>)] = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMSCR_EL1, Statistical Profiling Control Register (EL1)

The PMSCR_EL1 characteristics are:

Purpose

Provides EL1 controls for Statistical Profiling

Configuration

This register is present only when SPE is implemented. Otherwise, direct accesses to PMSCR_EL1 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PMSCR_EL1 is a 64-bit register.

Field descriptions

The PMSCR_EL1 bit assignments are:



Bits [63:8]

Reserved, RES0.

PCT, bits [7:6]

When ~~HaveEL(~~EL2 is implemented~~:):~~

Physical Timestamp. If timestamp sampling is enabled and the Profiling Buffer is owned by EL1, requests which timestamp counter value is collected.

If ARMv8.6-ECV is implemented, this is a two bit field as shown. Otherwise, bit[7] is RES0.

PCT	Meaning	Applies when
0b00	Virtual counter, CNTVCT_EL0, is collected.	
0b01	Physical counter, CNTPCT_EL0, is collected.	
0b11	Physical counter, CNTPCT_EL0, minus CNTPOFF_EL2 is collected.	When ARMv8.6-ECV is implemented

If the Profiling Buffer owning Exception level is EL2, this field is ignored.

If the Profiling Buffer owning Exception level is EL1, this field is combined with PMSCR_EL2.PCT to determine which timestamp counter value is collected. For more information, see 'Controlling the data that is collected' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

When EL2 is implemented and enabled in the current Security state, the physical counter uses a fixed physical offset of zero if either of the following are true:

- CNTHCTL_EL2.ECV is 0.
- SCR_EL3.ECVEn is 0.
- HCR_EL2.{E2H, TGE} is {1, 1}.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Physical Timestamp. Reserved. This field reads as `0b01` and ignores writes. Software should treat this field as UNK/SBZP.

When EL2 is not implemented, the Effective values of CNTVOFF_EL2 and CNTPOFF_EL2 are zero, meaning the virtual counter and physical counter have the same value.

TS, bit [5]

Timestamp enable.

TS	Meaning
`0b0`	Timestamp sampling disabled.
`0b1`	Timestamp sampling enabled.

This bit is ignored by the PE if EL2 is implemented and the Profiling Buffer is owned by EL2. For more information, see 'Controlling the data that is collected' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

PA, bit [4]

Physical Address sample enable.

PA	Meaning
`0b0`	Physical addresses are not collected.
`0b1`	Physical addresses are collected.

If EL2 is implemented:

- If the Profiling Buffer is owned by EL1, this bit is combined with PMSCR_EL2.PA to determine which address is collected. For more information, see 'Controlling the data that is collected' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.
- If the Profiling Buffer is owned by EL2, this bit is ignored by the PE.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

CX, bit [3]

CONTEXTIDR_EL1 sample enable.

CX	Meaning
`0b0`	CONTEXTIDR_EL1 is not collected.
`0b1`	CONTEXTIDR_EL1 is collected.

If EL2 is implemented and enabled in the current Security state when an operation is sampled:

- If the PE is at EL2, this bit is ignored by the PE.
- If HCR_EL2.TGE == 1, this bit is ignored by the PE.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [2]

Reserved, RES0.

E1SPE, bit [1]

EL1 Statistical Profiling Enable.

E1SPE	Meaning
0b0	Sampling disabled at EL1.
0b1	Sampling enabled at EL1.

If EL2 is implemented and enabled in the current Security state, this bit is ignored by the PE when HCR_EL2.TGE == 1.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E0SPE, bit [0]

EL0 Statistical Profiling Enable. Controls sampling at EL0 when HCR_EL2.TGE == 0 or if EL2 is disabled or not implemented.

E0SPE	Meaning
0b0	Sampling disabled at EL0.
0b1	Sampling enabled at EL0.

If EL2 is implemented and enabled in the current Security state, this bit is ignored by the PE when HCR_EL2.TGE == 1.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMSCR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, PMSCR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1001	0b1001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.PMSCR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x828];
    else
        return PMSCR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        return PMSCR_EL2;
    else
        return PMSCR_EL1;
elsif PSTATE.EL == EL3 then
    return PMSCR_EL1;
```

MSR PMSCR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b1001	0b1001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.PMSCR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x828] = X[t];
    else
        PMSCR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        PMSCR_EL2 = X[t];
    else
        PMSCR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    PMSCR_EL1 = X[t];
```

MRS <Xt>, PMSCR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b1001	0b1001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x828];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11'
then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            return PMSCR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return PMSCR_EL1;
    else
        UNDEFINED;
```

```
MSR PMSCR_EL12, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b1001	0b1001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x828] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11'
then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            PMSCR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        PMSCR_EL1 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMSEVFR_EL1, Sampling Event Filter Register

The PMSEVFR_EL1 characteristics are:

Purpose

Controls sample filtering by events. The overall filter is the logical AND of these filters. For example, if E[3] and E[5] are both set to 1, only samples that have both event 3 (Level 1 unified or data cache refill) and event 5 set (TLB walk) are recorded

Configuration

This register is present only when SPE is implemented. Otherwise, direct accesses to PMSEVFR_EL1 are UNDEFINED.

RW fields in this register reset to architecturally UNKNOWN values.

Attributes

PMSEVFR_EL1 is a 64-bit register.

Field descriptions

The PMSEVFR_EL1 bit assignments are:



E[<z>], bit [63z], bitfor [z = 48 to 63]

E[63][<z>] is the event filter for event 63.<z>. If event 63<z> is not implemented, or filtering on event 63<z> is not supported, the corresponding bit is RAZ/WI.

E[63][<z>]	Meaning
0b0	Event 63<z> is ignored.
0b1	Do not record samples that have event 63<z> == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[62], bit [62]

E[62] is the event filter for event 62. If event 62 is not implemented, or filtering on event 62 is not supported, the corresponding bit is RAZ/WI.

E[62]	Meaning
0b0	Event 62 is ignored.
0b1	Do not record samples that have event 62 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[61], bit [61]

E[61] is the event filter for event 61. If event 61 is not implemented, or filtering on event 61 is not supported, the corresponding bit is RAZ/WI.

E[61]	Meaning
0b0	Event 61 is ignored.
0b1	Do not record samples that have event 61 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[60], bit [60]

E[60] is the event filter for event 60. If event 60 is not implemented, or filtering on event 60 is not supported, the corresponding bit is RAZ/WI.

E[60]	Meaning
0b0	Event 60 is ignored.
0b1	Do not record samples that have event 60 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[59], bit [59]

E[59] is the event filter for event 59. If event 59 is not implemented, or filtering on event 59 is not supported, the corresponding bit is RAZ/WI.

E[59]	Meaning
0b0	Event 59 is ignored.
0b1	Do not record samples that have event 59 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[58], bit [58]

E[58] is the event filter for event 58. If event 58 is not implemented, or filtering on event 58 is not supported, the corresponding bit is RAZ/WI.

E[58]	Meaning
0b0	Event 58 is ignored.
0b1	Do not record samples that have event 58 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[57], bit [57]

E[57] is the event filter for event 57. If event 57 is not implemented, or filtering on event 57 is not supported, the corresponding bit is RAZ/WI.

E[57]	Meaning
0b0	Event 57 is ignored.
0b1	Do not record samples that have event 57 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[56], bit [56]

E[56] is the event filter for event 56. If event 56 is not implemented, or filtering on event 56 is not supported, the corresponding bit is RAZ/WI.

E[56]	Meaning
0b0	Event 56 is ignored.
0b1	Do not record samples that have event 56 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[55], bit [55]

E[55] is the event filter for event 55. If event 55 is not implemented, or filtering on event 55 is not supported, the corresponding bit is RAZ/WI.

E[55]	Meaning
0b0	Event 55 is ignored.
0b1	Do not record samples that have event 55 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[54], bit [54]

E[54] is the event filter for event 54. If event 54 is not implemented, or filtering on event 54 is not supported, the corresponding bit is RAZ/WI.

E[54]	Meaning
0b0	Event 54 is ignored.
0b1	Do not record samples that have event 54 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[53], bit [53]

E[53] is the event filter for event 53. If event 53 is not implemented, or filtering on event 53 is not supported, the corresponding bit is RAZ/WI.

E[53]	Meaning
0b0	Event 53 is ignored.
0b1	Do not record samples that have event 53 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[52], bit [52]

E[52] is the event filter for event 52. If event 52 is not implemented, or filtering on event 52 is not supported, the corresponding bit is RAZ/WI.

E[52]	Meaning
0b0	Event 52 is ignored.
0b1	Do not record samples that have event 52 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[51], bit [51]

E[51] is the event filter for event 51. If event 51 is not implemented, or filtering on event 51 is not supported, the corresponding bit is RAZ/WI.

E[51]	Meaning
0b0	Event 51 is ignored.
0b1	Do not record samples that have event 51 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[50], bit [50]

E[50] is the event filter for event 50. If event 50 is not implemented, or filtering on event 50 is not supported, the corresponding bit is RAZ/WI.

E[50]	Meaning
0b0	Event 50 is ignored.
0b1	Do not record samples that have event 50 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[49], bit [49]

E[49] is the event filter for event 49. If event 49 is not implemented, or filtering on event 49 is not supported, the corresponding bit is RAZ/WI.

E[49]	Meaning
0b0	Event 49 is ignored.
0b1	Do not record samples that have event 49 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[48], bit [48]

E[48] is the event filter for event 48. If event 48 is not implemented, or filtering on event 48 is not supported, the corresponding bit is RAZ/WI.

E[48]	Meaning
0b0	Event 48 is ignored.
0b1	Do not record samples that have event 48 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bits [47:32]

Reserved, RAZ/WI.

E[<y>], bit [31y], bitfor [y = 24 to 31]

E[31][<y>] is the event filter for event 31.<y>. If event 31<y> is not implemented, or filtering on event 31<y> is not supported, the corresponding bit is RAZ/WI.

E[31][<y>]	Meaning
0b0	Event 31<y> is ignored.
0b1	Do not record samples that have event 31<y> == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[30], bit [30]

E[30] is the event filter for event 30. If event 30 is not implemented, or filtering on event 30 is not supported, the corresponding bit is RAZ/WI.

E[30]	Meaning
0b0	Event 30 is ignored.
0b1	Do not record samples that have event 30 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[29], bit [29]

E[29] is the event filter for event 29. If event 29 is not implemented, or filtering on event 29 is not supported, the corresponding bit is RAZ/WI.

E[29]	Meaning
0b0	Event 29 is ignored.
0b1	Do not record samples that have event 29 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[28], bit [28]

E[28] is the event filter for event 28. If event 28 is not implemented, or filtering on event 28 is not supported, the corresponding bit is RAZ/WI.

E[28]	Meaning
0b0	Event 28 is ignored.
0b1	Do not record samples that have event 28 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[27], bit [27]

E[27] is the event filter for event 27. If event 27 is not implemented, or filtering on event 27 is not supported, the corresponding bit is RAZ/WI.

E[27]	Meaning
0b0	Event 27 is ignored.
0b1	Do not record samples that have event 27 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[26], bit [26]

E[26] is the event filter for event 26. If event 26 is not implemented, or filtering on event 26 is not supported, the corresponding bit is RAZ/WI.

E[26]	Meaning
0b0	Event 26 is ignored.
0b1	Do not record samples that have event 26 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[25], bit [25]

E[25] is the event filter for event 25. If event 25 is not implemented, or filtering on event 25 is not supported, the corresponding bit is RAZ/WI.

E[25]	Meaning
0b0	Event 25 is ignored.
0b1	Do not record samples that have event 25 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[24], bit [24]

E[24] is the event filter for event 24. If event 24 is not implemented, or filtering on event 24 is not supported, the corresponding bit is RAZ/WI.

E[24]	Meaning
0b0	Event 24 is ignored.
0b1	Do not record samples that have event 24 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bits [23:19]

Reserved, RAZ/WI.

E[18], bit [18]

When ARMv8.3-SPE is implemented and SVE is implemented:

Empty predicate.

E[18]	Meaning
0b0	Empty predicate event is ignored.
0b1	Do not record samples that have the Empty predicate event == 0.

This bit is ignored by the PE when PMSFCR_EL1.FE == 0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RAZ/WI.

E[17], bit [17]

When ARMv8.3-SPE is implemented and SVE is implemented:

Partial predicate.

E[17]	Meaning
0b0	Partial predicate event is ignored.
0b1	Do not record samples that have the Partial predicate event == 0.

This bit is ignored by the PE when PMSFCR_EL1.FE == 0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RAZ/WI.

Bit [16]

Reserved, RAZ/WI.

E[~~<x>~~], bit [15~~x~~], bit~~for~~ [~~x = 12 to~~ 15]

E[15][~~<x>~~] is the event filter for event 15.~~<x>~~. If event 15~~<x>~~ is not implemented, or filtering on event 15~~<x>~~ is not supported, the corresponding bit is RAZ/WI.

E[15][~~<x>~~]	Meaning
0b0	Event 15~~<x>~~ is ignored.
0b1	Do not record samples that have event 15~~<x>~~ == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[14], bit [14]

E[14] is the event filter for event 14. If event 14 is not implemented, or filtering on event 14 is not supported, the corresponding bit is RAZ/WI.

E[14]	Meaning
0b0	Event 14 is ignored.
0b1	Do not record samples that have event 14 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[13], bit [13]

E[13] is the event filter for event 13. If event 13 is not implemented, or filtering on event 13 is not supported, the corresponding bit is RAZ/WI.

E[13]	Meaning
0b0	Event 13 is ignored.
0b1	Do not record samples that have event 13 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[12], bit [12]

E[12] is the event filter for event 12. If event 12 is not implemented, or filtering on event 12 is not supported, the corresponding bit is RAZ/WI.

E[12]	Meaning
0b0	Event 12 is ignored.
0b1	Do not record samples that have event 12 == 0.

An IMPLEMENTATION DEFINED event might be recorded as a multi-bit field. In this case, if the corresponding bits of PMSEVFR_EL1 define an IMPLEMENTATION DEFINED filter for the event.

This field is ignored by the PE when PMSFCR_EL1.FE == 0

On a Warm reset, this field resets to an architecturally UNKNOWN value.

E[11], bit [11]

When ARMv8.3-SPE is implemented:

Alignment.

E[11]	Meaning
0b0	Alignment event is ignored.
0b1	Do not record samples that have the Alignment event == 0.

This bit is ignored by the PE when PMSFCR_EL1.FE == 0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RAZ/WI.

Bits [10:8]

Reserved, RAZ/WI.

E[7], bit [7]

Mispredicted.

E[7]	Meaning
0b0	Mispredicted event is ignored.
0b1	Do not record samples that have the Mispredicted event == 0.

This bit is ignored by the PE when PMSFCR_EL1.FE == 0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [6]

Reserved, RAZ/WI.

E[5], bit [5]

TLB walk.

E[5]	Meaning
0b0	TLB walk event is ignored.
0b1	Do not record samples that have the TLB walk event == 0.

This bit is ignored by the PE when PMSFCR_EL1.FE == 0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [4]

Reserved, RAZ/WI.

E[3], bit [3]

Level 1 data or unified cache refill.

E[3]	Meaning
0b0	Level 1 data or unified cache refill event is ignored.
0b1	Do not record samples that have the Level 1 data or unified cache refill event == 0.

This bit is ignored by the PE when PMSFCR_EL1.FE == 0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [2]

Reserved, RAZ/WI.

E[1], bit [1]

When the PE supports sampling of speculative instructions:

Architecturally retired.

When the PE supports sampling of speculative instructions:

E[1]	Meaning
0b0	Architecturally retired event is ignored.
0b1	Do not record samples that have the Architecturally retired event == 0.

This bit is ignored by the PE when PMSFCR_EL1.FE == 0.

If the PE does not support the sampling of speculative instructions, or always discards the sample record for speculative instructions, this bit reads as an UNKNOWN value and the PE ignores its value.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, UNKNOWN.

Bit [0]

Reserved, RAZ/WI.

Accessing the PMSEVFR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, PMSEVFR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1001	0b1001	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.PMSEVFR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '1x1' then
        return NVMem[0x830];
    else
        return PMSEVFR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMSEVFR_EL1;
elsif PSTATE.EL == EL3 then
    return PMSEVFR_EL1;
```

MSR PMSEVFR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b1001	0b1001	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.PMSEVFR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '1x1' then
        NVMem[0x830] = X[t];
    else
        PMSEVFR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' && MDCR_EL3.NSPB != '01' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.NS == '1' && MDCR_EL3.NSPB != '11' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMSEVFR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    PMSEVFR_EL1 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMUSERENR_EL0, Performance Monitors User Enable Register

The PMUSERENR_EL0 characteristics are:

Purpose

Enables or disables EL0 access to the Performance Monitors.

Configuration

AArch64 System register PMUSERENR_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMUSERENR[31:0] .

This register is present only when PMUv3 is implemented. Otherwise, direct accesses to PMUSERENR_EL0 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PMUSERENR_EL0 is a 64-bit register.

Field descriptions

The PMUSERENR_EL0 bit assignments are:



Bits [63:4]

Reserved, RES0.

ER, bit [3]

Event counter Read. Traps EL0 access to event counters to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1.

In AArch64 state, trapped accesses are reported using EC syndrome value `0x18`.

In AArch32~~AArch64~~ state, trapped accesses are reported using EC syndrome value `0x03`.

ER	Meaning
`0b0`	EL0 using AArch64: EL0 reads of the PMXEVCNTR_EL0 and PMEVCNTR<n>_EL0, and EL0 read/write accesses to the PMSELR_EL0, are trapped if PMUSERENR_EL0.EN is also 0. EL0 using AArch32: EL0 reads of the PMXEVCNTR and PMEVCNTR<n>, and EL0 read/write accesses to the PMSELR, are trapped if PMUSERENR_EL0.EN is also 0.
`0b1`	Overrides PMUSERENR_EL0.EN and enables RO access to PMXEVCNTR_EL0 and PMEVCNTR<n>_EL0, and RW access to PMSELR_EL0 and PMSELR at EL0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

CR, bit [2]

Cycle counter Read. Traps EL0 access to cycle counter reads to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1.

In AArch64 state, trapped accesses are reported using EC syndrome value `0x18`.

In AArch32 state, trapped MRC accesses are reported using EC syndrome value `0x03`, trapped MRRC accesses are reported using EC syndrome value `0x04`.

CR	Meaning
`0b0`	EL0 using AArch64: EL0 read accesses to the PMCCNTR_EL0 are trapped if PMUSERENR_EL0.EN is also 0. EL0 using AArch32: EL0 read accesses to the PMCCNTR are trapped if PMUSERENR_EL0.EN is also 0.
`0b1`	Overrides PMUSERENR_EL0.EN and enables access to PMCCNTR_EL0 and PMCCNTR at EL0.

SW, bit [1]

Traps Software Increment writes to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1.

In AArch64 state, trapped accesses are reported using EC syndrome value `0x18`.

In AArch32 state, trapped accesses are reported using EC syndrome value `0x03`.

SW	Meaning
`0b0`	EL0 using AArch64: EL0 writes to the PMSWINC_EL0 are trapped if PMUSERENR_EL0.EN is also 0. EL0 using AArch32: EL0 writes to the PMSWINC are trapped if PMUSERENR_EL0.EN is also 0.
`0b1`	Overrides PMUSERENR_EL0.EN and enables access to:~~PMSWINC_EL0 and PMSWINC at EL0.~~ • PMSWINC_EL0 at EL0. • PMSWINC at EL0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

EN, bit [0]

Traps EL0 accesses to the Performance Monitor registers to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, from both Execution states as follows:

- In AArch64 state, MRS or MSR accesses to the following registers are reported using EC syndrome value `0x18`:
  - PMCR_EL0, PMOVSCLR_EL0, PMSELR_EL0, PMCEID0_EL0, PMCEID1_EL0, PMCCNTR_EL0, PMXEVTYPER_EL0, PMXEVCNTR_EL0, ~~PMUSERENR_EL0,~~ PMCNTENSET_EL0, PMCNTENSET_EL0, PMOVSSET_EL0, PMEVCNTR<n>_EL0, PMEVTYPER<n>_EL0, PMCCFILTR_EL0.
  - PMSWINC_EL0, MSR accesses only.
  - If ARMv8.4-PMU is implemented, PMMIR_EL1
- In AArch32 state, MRC or MCR accesses to the following registers are reported using EC syndrome value `0x03`, MRRC or MCRR accesses are trapped to EL2 and reported using EC syndrome value `0x04`:
  - PMCR, PMOVSR, PMSELR, PMCEID0, PMCEID1, PMCCNTR, PMXEVTYPER, PMXEVNTR, ~~PMUSERENR,~~ PMCNTENSET, PMCNTENCLR, PMOVSSET, PMEVCNTR<n>, PMEVTYPER<n>, PMCCFILTR.
  - PMSWINC, MCR accesses only.
  - If ARMv8.4-PMU is implemented, PMMIR.

    - If ARMv8.1-PMU is implemented, in AArch32 state, PMCEID2, and PMCEID3.

- In AArch32 state, MRRC or MCRR accesses to PMCCNTR are reported using EC syndrome value 0x04.
- ~~If ARMv8.4-PMU is implemented, in AArch64 state, PMMIR_EL1 and in AArch32 state, PMMIR.~~
- ~~If ARMv8.1-PMU is implemented, in AArch32 state, PMCEID2, and PMCEID3.~~

EN	Meaning
0b0	While at EL0, accesses~~Accesses~~ to the specified registers at EL0 are trapped, unless overridden by one of PMUSERENR_EL0.{ER, CR, SW}.
0b1	While at EL0, software can access all of the specified registers.

Note

The EL0 access is trapped only if the corresponding EL1 access is permitted. If PMUSERENR_EL0.EN is 0, write access to PMSWINC_EL0 and PMSWINC from EL0 are trapped, but read access is UNDEFINED.

The affected registers do not include PMINTENSET_EL1, PMINTENCLR_EL1, PMINTENSET and PMINTENCLR.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMUSERENR_EL0

Accesses to this register use the following encodings:

```
MRS <Xt>, PMUSERENR_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1001	0b1110	0b000

```
if PSTATE.EL == EL0 then
    if EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMUSERENR_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMUSERENR_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.PMUSERENR_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMUSERENR_EL0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMUSERENR_EL0;
elsif PSTATE.EL == EL3 then
    return PMUSERENR_EL0;
```

```
MSR PMUSERENR_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1001	0b1110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.PMUSERENR_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMUSERENR_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMUSERENR_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    PMUSERENR_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMXEVCNTR_EL0, Performance Monitors Selected Event Count Register

The PMXEVCNTR_EL0 characteristics are:

Purpose

Reads or writes the value of the selected event counter, PMEVCNTR<n>_EL0. PMSELR_EL0.SEL determines which event counter is selected.

Configuration

AArch64 System register PMXEVCNTR_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMXEVCNTR[31:0] .

This register is present only when PMUv3 is implemented. Otherwise, direct accesses to PMXEVCNTR_EL0 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PMXEVCNTR_EL0 is a 64-bit register.

Field descriptions

The PMXEVCNTR_EL0 bit assignments are:

When ARMv8.5-PMU is implemented:



PMEVCNTR<n>, bits [63:0]

Value of the selected event counter, PMEVCNTR<n>_EL0, where n is the value stored in PMSELR_EL0.SEL.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:



Bits [63:32]

Reserved, RES0.

PMEVCNTR<n>, bits [31:0]

Value of the selected event counter, PMEVCNTR<n>_EL0, where n is the value stored in PMSELR_EL0.SEL.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMXEVCNTR_EL0

If ARMv8.6-FGT is implemented, and EL2 is implemented and enabled in the current Security state, for reads and writes at EL1 and permitted reads and writes at EL0: PMSELR_EL0.SEL is greater than or equal to the number of accessible counters, then the behavior of permitted reads and writes of PMXEVCNTR_EL0 is as follows:

- If PMSELR_EL0.SEL selectsis an unimplemented event counter, the access is UNDEFINED.
- Otherwise, the access is trapped to EL2.if PMSELR_EL0.SEL is greater than or equal to MDCR_EL2.HPMN, the access is trapped to EL2.

If PMSELR_EL0.SEL is greater than or equal to the number of accessible counters then reads and writes of PMXEVCNTR_EL0 are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

If ARMv8.6-FGT is not implemented, andor the above behaviors do not apply: PMSELR_EL0.SEL is greater than or equal to the number of accessible counters, then reads and writes of PMXEVCNTR_EL0 are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

- Accesses to the register are UNDEFINED.
- Accesses to the register behave as RAZ/WI.
- Accesses to the register execute as a `NOP`
- Accesses to the register behave as if PMSELR_EL0.SEL has an UNKNOWN value less than the number of counters accessible at the current Exception level and Security state.
- If EL2 is implemented and enabled in the current Security state, and PMSELR_EL0.SEL is less than the number of implemented counters, accesses from EL1 or permitted accesses from EL0 are trapped to EL2.

Note

In EL0, an access is permitted if it is enabled by PMUSERENR_EL0.{ER,EN}.

If EL2 is implemented and enabled in the current Security state, in EL1 and EL0, MDCR_EL2.HPMN identifies the number of accessible counters. Otherwise, the number of accessible counters is the number of implemented counters. See MDCR_EL2.HPMN for more details.

Accesses to this register use the following encodings:

```
MRS <Xt>, PMXEVCNTR_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1001	0b1101	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.<ER,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMXEVCNTR_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMXEVCNTR_EL0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMXEVCNTR_EL0;
elsif PSTATE.EL == EL3 then
    return PMXEVCNTR_EL0;
```

MSR PMXEVCNTR_EL0, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b011	0b1001	0b1101	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMXEVCNTR_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMXEVCNTR_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMXEVCNTR_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    PMXEVCNTR_EL0 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMXEVTYPER_EL0, Performance Monitors Selected Event Type Register

The PMXEVTYPER_EL0 characteristics are:

Purpose

When PMSELR_EL0.SEL selects an event counter, this accesses a PMEVTYPER<n>_EL0 register. When PMSELR_EL0.SEL selects the cycle counter, this accesses PMCCFILTR_EL0.

Configuration

AArch64 System register PMXEVTYPER_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMXEVTYPER[31:0] .

This register is present only when PMUv3 is implemented. Otherwise, direct accesses to PMXEVTYPER_EL0 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PMXEVTYPER_EL0 is a 64-bit register.

Field descriptions

The PMXEVTYPER_EL0 bit assignments are:



Bits [63:32]

Reserved, RES0.

Bits~~Event type register or PMCCFILTR_EL0, bits~~ [31:0]

When PMSELR_EL0.SEL == 31, this register accesses PMCCFILTR_EL0.

Otherwise, this register accesses PMEVTYPER<n>_EL0 where n is the value in PMSELR_EL0.SEL.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMXEVTYPER_EL0

If ARMv8.6-FGT is implemented, and ~~EL2 is implemented and enabled in the current Security state, for reads and writes at EL1 and permitted reads and writes at EL0:~~ PMSELR_EL0.SEL is not 31 and is greater than or equal to the number of accessible counters, then the behavior of permitted reads and writes of PMXEVTYPER_EL0 is as follows:

- If PMSELR_EL0.SEL selects~~is~~ an unimplemented event counter, the access is UNDEFINED.
- Otherwise, the access is trapped to EL2.~~if PMSELR_EL0.SEL is not 31 and greater than or equal to MDCR_EL2.HPMN, the access is trapped to EL2.~~

~~If PMSELR_EL0.SEL is not 31 and greater than or equal to the number of accessible counters then reads and writes of PMXEVTYPER_EL0 are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:~~

If ARMv8.6-FGT is not implemented, and~~or the above behaviors do not apply:~~ PMSELR_EL0.SEL is not 31 and is greater than or equal to the number of accessible counters, then reads and writes of PMXEVTYPER_EL0 are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

- Accesses to the register are UNDEFINED.
- Accesses to the register behave as RAZ/WI.
- Accesses to the register execute as a `NOP`
- Accesses to the register behave as if PMSELR_EL0.SEL has an UNKNOWN value less than the number of counters accessible at the current Exception level and Security state.
- Accesses to the register behave as if PMSELR_EL0.SEL is 31.
- If EL2 is implemented and enabled in the current Security state, PMSELR_EL0 is less than the number of implemented counters, accesses from EL1 or permitted accesses from EL0 are trapped to EL2.

Note

In EL0, an access is permitted if it is enabled by PMUSERENR_EL0.EN.

If EL2 is implemented and enabled in the current Security state, in EL1 and EL0, MDCR_EL2.HPMN identifies the number of accessible counters. Otherwise, the number of accessible counters is the number of implemented counters. See MDCR_EL2.HPMN for more details.

Accesses to this register use the following encodings:

```
MRS <Xt>, PMXEVTYPER_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1001	0b1101	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMXEVTYPER_EL0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGRTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMXEVTYPER_EL0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return PMXEVTYPER_EL0;
elsif PSTATE.EL == EL3 then
    return PMXEVTYPER_EL0;
```

```
MSR PMXEVTYPER_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b1001	0b1101	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMXEVTYPER_EL0 = X[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMXEVTYPER_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        PMXEVTYPER_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    PMXEVTYPER_EL0 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

RGSR_EL1, Random Allocation Tag Seed Register.

The RGSR_EL1 characteristics are:

Purpose

Random Allocation Tag Seed Register.

Configuration

This register is present only when ARMv8.5-MemTag is implemented and ID_AA64PFR1_EL1.MTE != 0b0001. Otherwise, direct accesses to RGSR_EL1 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

When GCR_EL1.RRND==0b1, updates to RGSR_EL1 are implementation-specific.

~~When GCR_EL1.RRND==0b1, the value of RGSR_EL1 is UNKNOWN.~~

Attributes

RGSR_EL1 is a 64-bit register.

Field descriptions

The RGSR_EL1 bit assignments are:



Bits [63:24]

Reserved, RES0.

SEED, bits [23:8]

Seed register used for generating values returned by RandomAllocationTag().

This field resets to an architecturally UNKNOWN value.

Bits [7:4]

Reserved, RES0.

TAG, bits [3:0]

Tag generated by the most recent IRG instruction.

This field resets to an architecturally UNKNOWN value.

Accessing the RGSR_EL1

Accesses to this register use the following encodings:

MRS <Xt>, RGSR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return RGSR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return RGSR_EL1;
elsif PSTATE.EL == EL3 then
    return RGSR_EL1;
```

MSR RGSR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        RGSR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        RGSR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    RGSR_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

RMR_EL1, Reset Management Register (EL1)

The RMR_EL1 characteristics are:

Purpose

WhenIf EL1 is the highest implemented Exception level and this register is implemented:

- A write to the register at EL1 can request a Warm reset.
- If EL1 can use allAArch32 Executionand statesAArch64, this register specifies the Execution state that the PE boots into on a Warm reset.

Configuration

AArch64 System register RMR_EL1 bits [31:0] are architecturally mapped to AArch32 System register RMR[31:0] when the highest implemented Exception level is EL1.IsHighestEL(EL1).

ThisOnly registerimplemented isif presentEL1 only whenis the highest implemented Exception levellevel. isIn EL1. Otherwise,this direct accesses to RMR_EL1 arecase: UNDEFINED.

When EL1 is the highest implemented Exception level:

- If EL1 can use allAArch32 Executionand statesAArch64 then this register must be implemented.
- If EL1 cannot use AArch32 then it is IMPLEMENTATION DEFINED whether the register is implemented.

Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.

Attributes

RMR_EL1 is a 64-bit register.

Field descriptions

The RMR_EL1 bit assignments are:



Bits [63:2]

Reserved, RES0.

RR, bit [1]

Reset Request. Setting this bit to 1 requests a Warm reset.

This field resets to 0.

AA64, bit [0]

When AArch32 is supported at any Exception level:

When EL1 can use AArch32, determines which Execution state the PE boots into after a Warm reset:

AA64	Meaning
0b0	AArch32.
0b1	AArch64.

On coming out of the Warm reset, execution starts at the IMPLEMENTATION DEFINED reset vector address of the specified Execution state.

If EL1 can~~cannot~~ only use AArch64 state,~~AArch32~~ this bit is RAO/WI.

When implemented as a RW field, this field resets to 1 on a Cold reset.

Otherwise:

Reserved, RAO/WI.

Accessing the RMR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, RMR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b0000	0b010

```
if PSTATE.EL == EL1 && IsHighestEL(EL1) then
    return RMR_EL1;
else
    UNDEFINED;
```

```
MSR RMR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b0000	0b010

```
if PSTATE.EL == EL1 && IsHighestEL(EL1) then
    RMR_EL1 = X[t];
else
    UNDEFINED;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

RMR_EL2, Reset Management Register (EL2)

The RMR_EL2 characteristics are:

Purpose

WhenIf EL2 is the highest implemented Exception level and this register is implemented:

- A write to the register at EL2 can request a Warm reset.
- If EL2 can use allAArch32 Executionand statesAArch64, this register specifies the Execution state that the PE boots into on a Warm reset.

Configuration

AArch64 System register RMR_EL2 bits [31:0] are architecturally mapped to AArch32 System register HRMR[31:0] when the highest implemented Exception level is EL2.IsHighestEL(EL2).

ThisOnly registerimplemented isif presentEL2 only whenis the highest implemented Exception levellevel. isIn EL2. Otherwise,this direct accesses to RMR_EL2 arecase: UNDEFINED.

When EL2 is the highest implemented Exception level:

- If EL2 can use allAArch32 Executionand statesAArch64 then this register must be implemented.
- If EL2 cannot use AArch32 then it is IMPLEMENTATION DEFINED whether the register is implemented.

This register has no effect if EL2 is not enabled in the current Security state.

Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.

Attributes

RMR_EL2 is a 64-bit register.

Field descriptions

The RMR_EL2 bit assignments are:



Bits [63:2]

Reserved, RES0.

RR, bit [1]

Reset Request. Setting this bit to 1 requests a Warm reset.

This field resets to 0.

AA64, bit [0]

When AArch32 is supported at any Exception level:

When EL2 can use AArch32, determines which Execution state the PE boots into after a Warm reset:

AA64	Meaning
0b0	AArch32.
0b1	AArch64.

On coming out of the Warm reset, execution starts at the IMPLEMENTATION DEFINED reset vector address of the specified Execution state.

If EL2 can~~cannot~~ only use AArch64 state,~~AArch32~~ this bit is RAO/WI.

When implemented as a RW field, this field resets to 1 on a Cold reset.

Otherwise:

Reserved, RAO/WI.

Accessing the RMR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, RMR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1100	0b0000	0b010

```
if PSTATE.EL == EL1 && EL2Enabled() && IsHighestEL(EL2) && HCR_EL2.NV == '1' then
    AArch64.SystemAccessTrap(EL2, 0x18);
elsif PSTATE.EL == EL2 && IsHighestEL(EL2) then
    return RMR_EL2;
else
    UNDEFINED;
```

```
MSR RMR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1100	0b0000	0b010

```
if PSTATE.EL == EL1 && EL2Enabled() && IsHighestEL(EL2) && HCR_EL2.NV == '1' then
    AArch64.SystemAccessTrap(EL2, 0x18);
elsif PSTATE.EL == EL2 && IsHighestEL(EL2) then
    RMR_EL2 = X[t];
else
    UNDEFINED;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

RMR_EL3, Reset Management Register (EL3)

The RMR_EL3 characteristics are:

Purpose

If EL3 is the implemented and this register is implemented:

- A write to the register at EL3 can request a Warm reset.
- If EL3 can use allAArch32 Executionand statesAArch64, this register specifies the Execution state that the PE boots into on a Warm reset.

Configuration

AArch64 System register RMR_EL3 bits [31:0] are architecturally mapped to AArch32 System register RMR[31:0] when HaveEL(EL3 is implemented.).

This register is present only when EL3 is implemented. Otherwise, direct accesses to RMR_EL3 are UNDEFINED.

When EL3 is implemented:

- If EL3 can use allAArch32 Executionand statesAArch64, then this register must be implemented.
- If EL3 cannot use AArch32 ,then it is IMPLEMENTATION DEFINED whether the register is implemented.

Otherwise, direct accesses to RMR_EL3 are UNDEFINED.

Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.

Attributes

RMR_EL3 is a 64-bit register.

Field descriptions

The RMR_EL3 bit assignments are:



Bits [63:2]

Reserved, RES0.

RR, bit [1]

Reset Request. Setting this bit to 1 requests a Warm reset.

This field resets to 0.

AA64, bit [0]

When AArch32 is supported at any Exception level:

When EL3 can use AArch32, determines which Execution state the PE boots into after a Warm reset:

AA64	Meaning
0b0	AArch32.
0b1	AArch64.

On coming out of the Warm reset, execution starts at the IMPLEMENTATION DEFINED reset vector address of the specified Execution state.

If EL3 can~~cannot~~ only use AArch64 state,~~AArch32~~ this bit is RAO/WI.

When implemented as a RW field, this field resets to 1 on a Cold reset.

Otherwise:

Reserved, RAO/WI.

Accessing the RMR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, RMR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1100	0b0000	0b010

```
if PSTATE.EL == EL3 && IsHighestEL(EL3) then
    return RMR_EL3;
else
    UNDEFINED;
```

```
MSR RMR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1100	0b0000	0b010

```
if PSTATE.EL == EL3 && IsHighestEL(EL3) then
    RMR_EL3 = X[t];
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

RNDR, Random Number

The RNDR characteristics are:

Purpose

Random Number. Returns a 64-bit random number which is reseeded from the True Random Number source at an IMPLEMENTATION DEFINED rate.

If the hardware returns a genuine random number, PSTATE.NZCV is set to `0b0000`.

If the instruction cannot return a genuine random number in a reasonable period of time, PSTATE.NZCV is set to `0b0100` and the data value returned is 0.

~~If the instruction cannot return a genuine random number in a reasonable period of time, PSTATE.NZCV is set to `0b0100` and the data value returned in UNKNOWN.~~

RNDR is a read-only register.

Configuration

This register is present only when ARMv8.5-RNG is implemented. Otherwise, direct accesses to RNDR are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

RNDR is a 64-bit register.

Field descriptions

The RNDR bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RNDR																															
RNDR																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

RNDR, bits [63:0]

Random Number. Returns a 64-bit Random Number which is reseeded from the True Random Number source at an IMPLEMENTATION DEFINED rate.

This field resets to an architecturally UNKNOWN value.

Accessing the RNDR

Accesses to this register use the following encodings:

```
MRS <Xt>, RNDR
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b0010	0b0100	0b000

```
if PSTATE.EL == EL0 then
    return RNDR;
elsif PSTATE.EL == EL1 then
    return RNDR;
elsif PSTATE.EL == EL2 then
    return RNDR;
elsif PSTATE.EL == EL3 then
    return RNDR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

RNDRRS, Reseeded Random Number

The RNDRRS characteristics are:

Purpose

Reseeded Random Number. Returns a 64-bit random number which is reseeded from the True Random Number source at an IMPLEMENTATION DEFINED rate.

If the hardware returns a genuine random number, PSTATE.NZCV is set to `0b0000`.

If the instruction cannot return a genuine random number in a reasonable period of time, PSTATE.NZCV is set to `0b0100` and the data value returned is 0.

~~If the instruction cannot return a genuine random number in a reasonable period of time, PSTATE.NZCV is set to `0b0100` and the data value returned in UNKNOWN.~~

RNDRRS is a read-only register.

Configuration

This register is present only when ARMv8.5-RNG is implemented. Otherwise, direct accesses to RNDRRS are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

RNDRRS is a 64-bit register.

Field descriptions

The RNDRRS bit assignments are:



RNDRRS, bits [63:0]

Reseeded Random Number. Returns a 64-bit Random Number which is reseeded from the True Random Number source immediately before this read.

This field resets to an architecturally UNKNOWN value.

Accessing the RNDRRS

Accesses to this register use the following encodings:

```
MRS <Xt>, RNDRRS
```

op0	op1	CRn	CRm	op2
0b11	0b011	0b0010	0b0100	0b001

```
if PSTATE.EL == EL0 then
    return RNDRRS;
elsif PSTATE.EL == EL1 then
    return RNDRRS;
elsif PSTATE.EL == EL2 then
    return RNDRRS;
elsif PSTATE.EL == EL3 then
    return RNDRRS;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

RVBAR_EL1, Reset Vector Base Address Register (if EL2 and EL3 not implemented)

The RVBAR_EL1 characteristics are:

Purpose

If EL1 is the highest Exception level implemented, contains the IMPLEMENTATION DEFINED address that execution starts from after reset when executing in AArch64 state.

Configuration

ThisOnly registerimplemented isif present only when the highest implemented Exception level implemented is EL1. Otherwise, direct accesses to RVBAR_EL1 are UNDEFINED.

Attributes

RVBAR_EL1 is a 64-bit register.

Field descriptions

The RVBAR_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Reset Address																															
Reset Address																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Reset Address. The IMPLEMENTATION DEFINED address that execution starts from after reset when executing in 64-bit state. Bits[1:0] of this register are 00, as this address must be aligned, and the address must be within the physical address size supported by the PE.

Accessing the RVBAR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, RVBAR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b0000	0b001

```
if PSTATE.EL == EL1 && IsHighestEL(EL1) then
    return RVBAR_EL1;
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

RVBAR_EL2, Reset Vector Base Address Register (if EL3 not implemented)

The RVBAR_EL2 characteristics are:

Purpose

If EL2 is the highest Exception level implemented, contains the IMPLEMENTATION DEFINED address that execution starts from after reset when executing in AArch64 state.

Configuration

~~This register has no effect if EL2 is not enabled in the current Security state.~~

This~~Only~~ register~~implemented~~ is~~if~~ present only when the highest implemented Exception level ~~implemented~~ is EL2. Otherwise, direct accesses to RVBAR_EL2 are UNDEFINED.

Attributes

RVBAR_EL2 is a 64-bit register.

Field descriptions

The RVBAR_EL2 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Reset Address																															
Reset Address																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Reset Address. The IMPLEMENTATION DEFINED address that execution starts from after reset when executing in 64-bit state. Bits[1:0] of this register are 00, as this address must be aligned, and the address must be within the physical address size supported by the PE.

Accessing the RVBAR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, RVBAR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1100	0b0000	0b001

```
if PSTATE.EL == EL1 && EL2Enabled() && IsHighestEL(EL2) && HCR_EL2.NV == '1' then
    AArch64.SystemAccessTrap(EL2, 0x18);
elsif PSTATE.EL == EL2 && IsHighestEL(EL2) then
    return RVBAR_EL2;
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

RVBAR_EL3, Reset Vector Base Address Register (if EL3 implemented)

The RVBAR_EL3 characteristics are:

Purpose

If EL3 is the highest Exception level implemented, contains the IMPLEMENTATION DEFINED address that execution starts from after reset when executing in AArch64 state.

Configuration

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to RVBAR_EL3 are UNDEFINED.

Only implemented if the highest Exception level implemented is EL3.

Attributes

RVBAR_EL3 is a 64-bit register.

Field descriptions

The RVBAR_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Reset Address																															
Reset Address																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Reset Address. The IMPLEMENTATION DEFINED address that execution starts from after reset when executing in 64-bit state. Bits[1:0] of this register are 00, as this address must be aligned, and the address must be within the physical address size supported by the PE.

Accessing the RVBAR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, RVBAR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1100	0b0000	0b001

```
if PSTATE.EL == EL3 && IsHighestEL(EL3) then
    return RVBAR_EL3;
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

S1_<op1>_<Cn>_<Cm>_<op2>, IMPLEMENTATION DEFINED maintenance instructions

The S1_<op1>_<Cn>_<Cm>_<op2> characteristics are:

Purpose

This area of the System instruction encoding space is reserved for IMPLEMENTATION DEFINED System instructions.

Configuration

There are no configuration notes.

Attributes

S1_<op1>_<Cn>_<Cm>_<op2> is a 64-bit System instruction.

Field descriptions

The S1_<op1>_<Cn>_<Cm>_<op2> input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
IMPLEMENTATION DEFINED																															
IMPLEMENTATION DEFINED																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

Executing the S1_<op1>_<Cn>_<Cm>_<op2> instruction

Accesses to this instruction use the following encodings:

```
SYS #<op1>, <Cn>, <Cm>, #<op2>{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	op1[2:0]	0b1x11	Cm[3:0]	op2[2:0]

```
if PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.TIDCP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        IMPLEMENTATION_DEFINED "";
else
    IMPLEMENTATION_DEFINED "";
```

```
SYSL <Xt>, #<op1>, <Cn>, <Cm>, #<op2>
```

op0	op1	CRn	CRm	op2
0b01	op1[2:0]	0b1x11	Cm[3:0]	op2[2:0]

```
if PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.TIDCP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        IMPLEMENTATION_DEFINED "";
else
    IMPLEMENTATION_DEFINED "";
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

S3_<op1>_<Cn>_<Cm>_<op2>, IMPLEMENTATION DEFINED registers

The S3_<op1>_<Cn>_<Cm>_<op2> characteristics are:

Purpose

This area of the instruction set space is reserved for IMPLEMENTATION DEFINED registers.

Configuration

There are no configuration notes.

Attributes

S3_<op1>_<Cn>_<Cm>_<op2> is a 64-bit register.

Field descriptions

The S3_<op1>_<Cn>_<Cm>_<op2> bit assignments are:



IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

Accessing the S3_<op1>_<Cn>_<Cm>_<op2>

Accesses to this register use the following encodings:

MRS <Xt>, S3_<op1>_C<Cn>_C<Cm>_<op2>

op0	op1	CRn	CRm	op2
0b11	op1[2:0]	0b1x11	Cm[3:0]	op2[2:0]

```
if PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.TIDCP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        IMPLEMENTATION_DEFINED "";
else
    IMPLEMENTATION_DEFINED "";
```

MSR S3_<op1>_C<Cn>_C<Cm>_<op2>, <Xt>

op0	op1	CRn	CRm	op2
0b11	op1[2:0]	0b1x11	Cm[3:0]	op2[2:0]

```
if PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.TIDCP == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        IMPLEMENTATION_DEFINED "";
else
    IMPLEMENTATION_DEFINED "";
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SCR_EL3, Secure Configuration Register

The SCR_EL3 characteristics are:

Purpose

Defines the configuration of the current Security state. It specifies:

- The Security state of EL0, EL1, and EL2. The Security state is either Secure or Non-secure.
- The Execution state at lower Exception levels.
- Whether IRQ, FIQ, SError interrupts, and External abort exceptions are taken to EL3.
- Whether various operations are trapped to EL3.

Configuration

AArch64 System register SCR_EL3 bits [31:0] can be mapped to AArch32 System register SCR[31:0] , but this is not architecturally mandated.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to SCR_EL3 are UNDEFINED.

Attributes

SCR_EL3 is a 64-bit register.

Field descriptions

The SCR_EL3 bit assignments are:



Bits [63:36]

Reserved, RES0.

AMVOFFEN, bit [35]

When ARMv8.6-AMU is implemented:

Activity Monitors Virtual Offsets Enable.

AMVOFFEN	Meaning
0b0	Accesses to AMEVCNTVOFF0<n>_EL2 and AMEVCNTVOFF1<n>_EL2 at EL2 are trapped to EL3. Indirect reads of the virtual offset registers are zero.
0b1	Accesses to AMEVCNTVOFF0<n>_EL2 and AMEVCNTVOFF1<n>_EL2 are not affected by this field.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [34]

Reserved, RES0.

TWEDEL, bits [33:30]

When ARMv8.6-TWED is implemented:

TWE Delay. A 4-bit unsigned number that, when SCR_EL3.TWEDEn is 1, encodes the minimum delay in taking a trap of WFE caused by SCR_EL3.TWE as 2^(TWEDEL + 8) cycles.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TWEDEn, bit [29]

When ARMv8.6-TWED is implemented:

TWE Delay Enable. Enables a configurable delayed trap of the WFE instruction caused by SCR_EL3.TWE.

TWEDEn	Meaning
0b0	The delay for taking a WFE trap is IMPLEMENTATION DEFINED.
0b1	The delay for taking a WFE trap is at least the number of cycles defined in SCR_EL3.TWEDEL.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ECVEn, bit [28]

When ARMv8.6-ECV is implemented:

ECV Enable. Enables access to the CNTPOFF_EL2 register.

ECVEn	Meaning
0b0	EL2 accesses to CNTPOFF_EL2 are trapped to EL3, and the value of CNTPOFF_EL2 is treated as 0 for all purposes other than direct reads or writes to the register from EL3.
0b1	EL2 accesses to CNTPOFF_EL2 are not trapped to EL3 by this mechanism.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

FGTEn, bit [27]

When ARMv8.6-FGT is implemented:

Enables access to the Fine-Grained Traps registers: HAFGRTR_EL2, HDFGRTR_EL2, HDFGWTR_EL2, HFGRTR_EL2, HFGITR_EL2 and HFGWTR_EL2.

FGTEn	Meaning
0b0	EL2 Accesses to HAFGRTR_EL2, HDFGRTR_EL2, HDFGWTR_EL2, HFGRTR_EL2, HFGITR_EL2 and HFGWTR_EL2 registers are trapped to EL3, and those registers behave as if all bits are set to 0.
0b1	EL2 Accesses to HAFGRTR_EL2, HDFGRTR_EL2, HDFGWTR_EL2, HFGRTR_EL2, HFGITR_EL2 and HFGWTR_EL2 registers are not trapped to EL3 by this mechanism.

Traps caused by accesses to the fine-grained trap registers are reported using the EC code of 0x18 and its associated ISS.

Otherwise:

Reserved, RES0.

ATA, bit [26]

When ARMv8.5-MemTag is implemented:

Allocation Tag Access. Controls access at EL2, EL1 and EL0 to Allocation Tags.

When access is prevented:

- Instructions which Load or Store data are Unchecked.
- Instructions which Load or Store Allocation Tags treat the Allocation Tag as RAZ/WI.
- Instructions which insert Logical Address Tags into addresses treat the Allocation Tag used to generate the Logical Address Tag as 0.
- Cache maintenance instructions which invalidate Allocation Tags from caches behave as the equivalent Clean and Invalidate operation on Allocation Tags.
- MRS and MSR instructions at EL1 and EL2 using GCR_EL1, RGSR_EL1, TFSR_EL1, TFSR_EL2 or TFSRE0_EL1 that are not UNDEFINED or trapped to a lower Exception level are trapped to EL3.
- MRS and MSR instructions at EL2 using TFSR_EL12 that are not UNDEFINED are trapped to EL3.

ATA	Meaning
0b0	Access is prevented.
0b1	Access is not prevented.

This field is permitted to be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EnSCXT, bit [25]

When ARMv8.0-CSV2 is implemented:

Enable access to the SCXTNUM_EL2, SCXTNUM_EL1, and SCXTNUM_EL0 registers. The defined values are:

EnSCXT	Meaning
0b0	EL2, EL1 and EL0 access to SCXTNUM_EL0, EL2 and EL1 access to SCXTNUM_EL1, EL2 access to SCXTNUM_EL2 registers are disabled by this mechanism, causing an exception to EL3, and the values of these registers to be treated as 0.
0b1	This control does not cause accesses to SCXTNUM_EL0, SCXTNUM_EL1, SCXTNUM_EL2 to be trapped.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [24:22]

Reserved, RES0.

FIEN, bit [21]

When ARMv8.4-RAS is implemented:

Fault Injection enable. Trap accesses to the RAS ERX* registers ERXPFGCDN_EL1, ERXPFGCTL_EL1, and ERXPFGF_EL1 from EL1 and EL2 to EL3, reported using EC syndrome value 0x18.

FIEN	Meaning
0b0	Accesses to the specified registers from EL1 and EL2 generate a Trap exception to EL3.
0b1	This control does not cause any instructions to be trapped.

If EL3 is not implemented, the Effective value of SCR_EL3.FIEN is 0b1.

If ERRIDR_EL1.NUM is zero, meaning no error records are implemented, or no error record accessible using System registers is owned by a node that implements the RAS Common Fault Injection Model Extension, then this bit might be RES0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NMEA, bit [20]

When ARMv8.4-DFE is implemented:

Non-maskable External Aborts. When SCR_EL3.EA == 1, controls whether PSTATE.A masks SError interrupts at EL3.

NMEA	Meaning
0b0	If SCR_EL3.EA == 1, asserted SError interrupts are not taken at EL3 if PSTATE.A == 1.
0b1	If SCR_EL3.EA == 1, asserted SError interrupts are taken at EL3 regardless of the value of PSTATE.A.

When SCR_EL3.EA == 0:

- Asserted SError interrupts are not taken at EL3 regardless of the value of PSTATE.A and this field.
- This field is ignored and its Effective value is 0.

This field resets to 0.

Otherwise:

Reserved, RES0.

EASE, bit [19]

When ARMv8.4-DFE is implemented:

External aborts to SError interrupt vector.

EASE	Meaning
0b0	Synchronous External abort exceptions taken to EL3 are taken to the appropriate synchronous exception vector offset from VBAR_EL3.
0b1	Synchronous External abort exceptions taken to EL3 are taken to the appropriate SError interrupt vector offset from VBAR_EL3.

This field resets to 0.

Otherwise:

Reserved, RES0.

EEL2, bit [18]

When ARMv8.4-SecEL2 is implemented:

Secure EL2 Enable.

EEL2	Meaning
0b0	All behaviors associated with Secure EL2 are disabled. All registers, including timer registers, defined by ARMv8.4-SecEL2 are UNDEFINED, and those timers are disabled.
0b1	All behaviors associated with Secure EL2 are enabled.

When the value of this bit is 1, then:

- When SCR_EL3.NS == 0, the SCR_EL3.RW bit is treated as 1 for all purposes other than reading or writing the register.
- If Secure EL1 is using AArch32, then any of the following operations, executed in Secure EL1, is trapped to Secure EL2, using the EC value of ESR_EL2.EC== 0x3 :
  - A read or write of the SCR.
  - A read or write of the NSACR.
  - A read or write of the MVBAR.
  - A read or write of the SDCR.
  - Execution of an ATS12NSO** instruction.
- If Secure EL1 is using AArch32, then any of the following operations, executed in Secure EL1, is trapped to Secure EL2 using the EC value of ESR_EL2.EC== 0x0 :
  - Execution of an SRS instruction that uses R13_mon.
  - Execution of an MRS (Banked register) or MSR (Banked register) instruction that would access SPSR_mon, R13_mon, or R14_mon.

Note

If the Effective value of SCR_EL3.EEL2 is 0, then these operations executed in Secure EL1 using AArch32 are trapped to EL3.

In a Secure only implementation that does not implement EL3 but implements EL2, behaves as if SCR_EL3.EEL2 == 1.

This bit is permitted to be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

API, bit [17]

When ARMv8.4-SecEL2 is implemented and ARMv8.3-PAuth is implemented:

Controls the use of the following instructions related to Pointer Authentication. Traps are reported using EC syndrome value `0x09`:

- PACGA, which is always enabled.
- AUTDA, AUTDB, AUTDZA, AUTDZB, AUTIA, AUTIA1716, AUTIASP, AUTIAZ, AUTIB, AUTIB1716, AUTIBSP, AUTIBZ, AUTIZA, AUTIZB, PACDA, PACDB, PACDZA, PACDZB, PACIA, PACIA1716, PACIASP, PACIAZ, PACIB, PACIB1716, PACIBSP, PACIBZ, PACIZA, PACIZB, RETAA, RETAB, BRAA, BRAB, BLRAA, BLRAB, BRAAZ, BRABZ, BLRAAZ, BLRABZ, ERETAA, ERETAB, LDRAA and LDRAB when:
  - In EL0, when HCR_EL2.TGE==0 or HCR_EL2.E2H==0, and the associated SCTLR_EL1.En<N><M> == 1.
  - In EL0, when HCR_EL2.TGE==1 and HCR_EL2.E2H==1, and the associated SCTLR_EL2.En<N><M> == 1.
  - In EL1, when the associated SCTLR_EL1.En<N><M> == 1.
  - In EL2, when the associated SCTLR_EL2.En<N><M> == 1.

API	Meaning
`0b0`	The use of any instruction related to pointer authentication in any Exception level except EL3 when the instructions are enabled are trapped to EL3 unless they are trapped to EL2 as a result of the HCR_EL2.API bit.
`0b1`	This control does not cause any instructions to be trapped.

An instruction is trapped only if Pointer Authentication is enabled for that instruction, for more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

If ARMv8.3-PAuth is implemented but EL3 is not implemented, the system behaves as if this bit is 1.

This field resets to an architecturally UNKNOWN value.

When ARMv8.4-SecEL2 is not implemented and ARMv8.3-PAuth is implemented:

Controls the use of instructions related to Pointer Authentication:

- PACGA.
- AUTDA, AUTDB, AUTDZA, AUTDZB, AUTIA, AUTIA1716, AUTIASP, AUTIAZ, AUTIB, AUTIB1716, AUTIBSP, AUTIBZ, AUTIZA, AUTIZB, PACDA, PACDB, PACDZA, PACDZB, PACIA, PACIA1716, PACIASP, PACIAZ, PACIB, PACIB1716, PACIBSP, PACIBZ, PACIZA, PACIZ, RETAA, RETAB, BRAA, BRAB, BLRAA, BLRAB, BRAAZ, BRABZ, BLRAAZ, BLRABZ, ERETAA, ERETAB, LDRAA and LDRAB when:
  - In Non-secure EL0, when HCR_EL2.TGE==0 or HCR_EL2.E2H==0, and the associated SCTLR_EL1.En<N><M>== 1.
  - In Non-secure EL0, when HCR_EL2.TGE==1 and HCR_EL2.E2H==1, and the associated SCTLR_EL2.En<N><M> == 1.
  - In Secure EL0, when the associated SCTLR_EL2.En<N><M> == 1.
  - In Secure or Non-secure EL1, when the associated SCTLR_EL1.En<N><M> == 1.
  - In EL2, when the associated SCTLR_EL2.En<N><M> == 1.

API	Meaning
0b0	The use of any instruction related to pointer authentication in any Exception level except EL3 when the instructions are enabled are trapped to EL3 unless they are trapped to EL2 as a result of the HCR_EL2.API bit.
0b1	This control does not cause any instructions to be trapped.

Note

If ARMv8.3-PAuth is implemented but EL3 is not implemented, the system behaves as if this bit is 1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

APK, bit [16]

When ARMv8.3-PAuth is implemented:

Trap registers holding "key" values for Pointer Authentication. Traps accesses to the following registers, using EC syndrome value 0x18, from EL1 or EL2 to EL3 unless they are trapped to EL2 as a result of the HCR_EL2.APK bit or other traps:

- APIAKeyLo_EL1, APIAKeyHi_EL1, APIBKeyLo_EL1, APIBKeyHi_EL1.
- APDAKeyLo_EL1, APDAKeyHi_EL1, APDBKeyLo_EL1, APDBKeyHi_EL1.
- APGAKeyLo_EL1, and APGAKeyHi_EL1.

APK	Meaning
0b0	Access to the registers holding "key" values for pointer authentication from EL1 or EL2 are trapped to EL3 unless they are trapped to EL2 as a result of the HCR_EL2.APK bit or other traps.
0b1	This control does not cause any instructions to be trapped.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

If ARMv8.3-PAuth is implemented but EL3 is not implemented, the system behaves as if this bit is 1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TERR, bit [15]

When RAS is implemented:

Trap Error record accesses. Accesses to the RAS ERR and RAS ERX registers from EL1 and EL2 to EL3 are trapped as follows:

- If EL1 is using AArch64, ERRIDR_EL1, ERRSELR_EL1, ERXADDR_EL1, ERXCTLR_EL1, ERXFR_EL1, ERXMISC0_EL1, ERXMISC1_EL1, and ERXSTATUS_EL1, are trapped and reported using EC syndrome value 0x18.

- If ARMv8.4-RAS is implemented, ERXMISC2_EL1, and ERXMISC3_EL1, are trapped and reported using EC syndrome value 0x18.
- If EL1 is using AArch32, accesses by MCR or MRC to the following registers are reported using EC syndrome value 0x03, accesses by MCRR or MRRC are reported using EC syndrome value 0x04:
  - ERRIDR, ERRSELR, ERXADDR, ERXADDR2, ERXCTLR, ERXCTLR2, ERXFR, ERXFR2, ERXMISC0, ERXMISC1, ERXMISC2, ERXMISC3, and ERXSTATUS.
- If ARMv8.4-RAS is implemented, accesses by MCR or MRC to the following registers are reported using EC syndrome value 0x03, accesses by MCRR or MRRC are reported using EC syndrome value 0x04:
  - ERXMISC4, ERXMISC5, ERXMISC6, and ERXMISC7.

TERR	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Accesses to the specified registers from EL1 and EL2 generate a Trap exception to EL3.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TLOR, bit [14]

When ARMv8.1-LOR is implemented:

Trap LOR registers. Traps accesses to the LORSA_EL1, LOREA_EL1, LORN_EL1, LORC_EL1, and LORID_EL1 registers from EL1 and EL2 to EL3, unless the access has been trapped to EL2.

TLOR	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL1 and EL2 accesses to the LOR registers that are not UNDEFINED are trapped to EL3, unless it is trapped HCR_EL2.TLOR.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TWE, bit [13]

Traps EL2, EL1, and EL0 execution of WFE instructions to EL3, from both Security states and both Execution states, reported using EC syndrome value 0x01.

TWE	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Any attempt to execute a WFE instruction at any Exception level lower than EL3 is trapped to EL3, if the instruction would otherwise have caused the PE to enter a low-power state and it is not trapped by SCTLR.nTWE, HCR.TWE, SCTLR_EL1.nTWE, SCTLR_EL2.nTWE, or HCR_EL2.TWE.

In AArch32 state, the attempted execution of a conditional WFE instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE or WFI can complete at any time, even without a Wakeup event, the traps on WFE of WFI are not guaranteed to be taken, even if the WFE or

WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

For more information about when WFE instructions can cause the PE to enter a low-power state, see 'Wait for Event mechanism and Send event' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

TWI, bit [12]

Traps EL2, EL1, and EL0 execution of WFI instructions to EL3, from both Security states and both Execution states, reported using EC syndrome value `0x01`.

TWI	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Any attempt to execute a WFI instruction at any Exception level lower than EL3 is trapped to EL3, if the instruction would otherwise have caused the PE to enter a low-power state and it is not trapped by SCTLR.nTWI, HCR.TWI, SCTLR_EL1.nTWI, SCTLR_EL2.nTWI, or HCR_EL2.TWI.

In AArch32 state, the attempted execution of a conditional WFI instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE or WFI can complete at any time, even without a Wakeup event, the traps on WFE of WFI are not guaranteed to be taken, even if the WFE or WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

For more information about when WFI instructions can cause the PE to enter a low-power state, see 'Wait for Interrupt' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

ST, bit [11]

Traps Secure EL1 accesses to the Counter-timer Physical Secure timer registers to EL3, from AArch64 state only, reported using EC syndrome value `0x18`.

ST	Meaning
`0b0`	Secure EL1 using AArch64 accesses to the CNTPS_TVAL_EL1, CNTPS_CTL_EL1, and CNTPS_CVAL_EL1 are trapped to EL3 when Secure EL2 is disabled. If Secure EL2 is enabled, the behavior is as if the value of this field was `0b1`.
`0b1`	This control does not cause any instructions to be trapped.

Note

Accesses to the Counter-timer Physical Secure timer registers are always enabled at EL3. These registers are not accessible at EL0.

This field resets to an architecturally UNKNOWN value.

RW, bit [10]

When AArch32 is supported at any Exception level:

Execution state control for lower Exception levels.

RW	Meaning
0b0	Lower levels are all AArch32.
0b1	The next lower level is AArch64. If EL2 is present: • EL2 is AArch64. • EL2 controls EL1 and EL0 behaviors. If EL2 is not present: • EL1 is AArch64. • EL0 is determined by the Execution state described in the current process state when executing at EL0.

If AArch32 state is not supported by the implementation at EL2 and AArch32 state is not supported by the implementation at EL1, then this bit is RAO/WI.

If AArch32 state is supported by the implementation at EL1, SCR_EL3.NS == 1 and AArch32 state is not supported by the implementation at EL2, the Effective value of this bit is 1.

If AArch32 state is supported by the implementation at EL1, ARMv8.4-SecEL2 is implemented and SCR_EL3.{EEL2, NS} == {1, 0}, the Effective value of this bit is 1.

This bit is permitted to be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RAO/WI.

SIF, bit [9]

When ARMv8.4-SecEL2 is implemented:

Secure instruction fetch. When the PE is in Secure state, this bit disables instruction fetch from memory marked in the first stage of translation as being Non-secure. The possible values for this bit are:

SIF	Meaning
0b0	Secure state instruction fetches from memory marked in the first stage of translation as being Non-secure are permitted.
0b1	Secure state instruction fetches from memory marked in the first stage of translation as being Non-secure are not permitted.

This bit is permitted to be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Secure instruction fetch. When the PE is in Secure state, this bit disables instruction fetch from Non-secure memory.

SIF	Meaning
0b0	Secure state instruction fetches from Non-secure memory are permitted.
0b1	Secure state instruction fetches from Non-secure memory are not permitted.

This bit is permitted to be cached in a TLB.

This field resets to an architecturally UNKNOWN value.

HCE, bit [8]

Hypervisor Call instruction enable. Enables HVC instructions at EL3 and, if EL2 is enabled in the current Security state, at EL2 and EL1, in both Execution states, reported using EC syndrome value 0x00.

HCE	Meaning
0b0	HVC instructions are UNDEFINED.
0b1	HVC instructions are enabled at EL3, EL2, and EL1.

Note

HVC instructions are always UNDEFINED at EL0 and, if Secure EL2 is disabled, at Secure EL1. Any resulting exception is taken from the current Exception level to the current Exception level.

If EL2 is not implemented, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

SMD, bit [7]

Secure Monitor Call disable. Disables SMC instructions at EL1 and above, from both Security states and both Execution states, reported using EC syndrome value 0x00.

SMD	Meaning
0b0	SMC instructions are enabled at EL3, EL2 and EL1.
0b1	SMC instructions are UNDEFINED.

Note

SMC instructions are always UNDEFINED at EL0. Any resulting exception is taken from the current Exception level to the current Exception level.

If HCR_EL2.TSC or HCR.TSC traps attempted EL1 execution of SMC instructions to EL2, that trap has priority over this disable.

This field resets to an architecturally UNKNOWN value.

Bit [6]

Reserved, RES0.

Bits [5:4]

Reserved, RES1.

EA, bit [3]

External Abort and SError interrupt routing.

EA	Meaning
0b0	When executing at Exception levels below EL3, External aborts and SError interrupts are not taken to EL3. In addition, when executing at EL3: • SError interrupts are not taken. • External aborts are taken to EL3.
0b1	When executing at any Exception level, External aborts and SError interrupts are taken to EL3.

For more information, see 'Asynchronous exception routing' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1 (The AArch64 System Level Programmers' Model).

This field resets to an architecturally UNKNOWN value.

FIQ, bit [2]

Physical FIQ Routing.

FIQ	Meaning
0b0	When executing at Exception levels below EL3, physical FIQ interrupts are not taken to EL3. When executing at EL3, physical FIQ interrupts are not taken.
0b1	When executing at any Exception level, physical FIQ interrupts are taken to EL3.

For more information, see 'Asynchronous exception routing' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1.

This field resets to an architecturally UNKNOWN value.

IRQ, bit [1]

Physical IRQ Routing.

IRQ	Meaning
0b0	When executing at Exception levels below EL3, physical IRQ interrupts are not taken to EL3. When executing at EL3, physical IRQ interrupts are not taken.
0b1	When executing at any Exception level, physical IRQ interrupts are taken to EL3.

For more information, see 'Asynchronous exception routing' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1.

This field resets to an architecturally UNKNOWN value.

NS, bit [0]

Non-secure bit.

NS	Meaning
0b0	Indicates that EL0 and EL1 are in Secure state.
0b1	Indicates that Exception levels lower than EL3 are in Non-secure state, and so memory accesses from those Exception levels cannot access Secure memory.

When SCR_EL3.{EEL2, NS} == {1, 0}, then EL2 is using AArch64 and in Secure state.

This field resets to an architecturally UNKNOWN value.

Accessing the SCR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, SCR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return SCR_EL3;
```

```
MSR SCR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    SCR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SCTLR_EL1, System Control Register (EL1)

The SCTLR_EL1 characteristics are:

Purpose

Provides top level control of the system, including its memory system, at EL1 and EL0.

Configuration

AArch64 System register SCTLR_EL1 bits [31:0] are architecturally mapped to AArch32 System register SCTLR[31:0] .

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL1 using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SCTLR_EL1 is a 64-bit register.

Field descriptions

The SCTLR_EL1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	4
RES0														TWEDEL				TWEDEn	DSSBS	ATA	AT
EnIA	EnIB	LSMAOE	nTLSMD	EnDA	UCI	EE	E0E	SPAN	EIS	IESB	TSCXT	WXN	nTWE	RES0	nTWI	UCT	DZE	EnDB	I	EOS	EnR
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	1

Bits [63:50]

Reserved, RES0.

TWEDEL, bits [49:46]

When ARMv8.6-TWED is implemented:

TWE Delay. A 4-bit unsigned number that, when SCTLR_EL1.TWEDEn is 1, encodes the minimum delay in taking a trap of WFE caused by SCTLR_EL1.nTWE as 2~~^(TWEDEL + 8) cycles.~~ (TWEDEL + 8) cycles.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TWEDEn, bit [45]

When ARMv8.6-TWED is implemented:

TWE Delay Enable. Enables a configurable delayed trap of the WFE instruction caused by SCTLR_EL1.nTWE.

TWEDEn	Meaning
0b0	The delay for taking a WFE trap is IMPLEMENTATION DEFINED.
0b1	The delay for taking a WFE trap is at least the number of cycles defined in SCTLR_EL1.TWEDEL.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DSSBS, bit [44]

When ARMv8.0-SSBS is implemented:

Default PSTATE.SSBS value on Exception Entry. The defined values are:

DSSBS	Meaning
0b0	PSTATE.SSBS is set to 0 on an exception to EL1.
0b1	PSTATE.SSBS is set to 1 on an exception to EL1.

In a system where the PE resets into EL1, this field resets to an IMPLEMENTATION DEFINED value.

Otherwise:

Reserved, RES0.

ATA, bit [43]

When ARMv8.5-MemTag is implemented:

Allocation Tag Access in EL1. When SCR_EL3.ATA=1 and HCR_EL2.ATA=1, controls EL1 access to Allocation Tags.

When access to Allocation Tags is prevented:

- Instructions which Load or Store data are Unchecked.
- Instructions which Load or Store Allocation Tags treat the Allocation Tag as RAZ/WI.
- Instructions which insert Logical Address Tags into addresses treat the Allocation Tag used to generate the Logical Address Tag as 0.
- Cache maintenance instructions which invalidate Allocation Tags from caches behave as the equivalent Clean and Invalidate operation on Allocation Tags.

ATA	Meaning
0b0	Access to Allocation Tags is prevented.
0b1	Access to Allocation Tags is not prevented.

This bit is permitted to be cached in a TLB.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ATA0, bit [42]

When ARMv8.5-MemTag is implemented:

Allocation Tag Access in EL0. When SCR_EL3.ATA=1, HCR_EL2.ATA=1, and HCR_EL2.{E2H,TGE} != {1,1}, controls EL0 access to Allocation Tags.

When access to Allocation Tags is prevented:

- Instructions which Load or Store data are Unchecked.
- Instructions which Load or Store Allocation Tags treat the Allocation Tag as RAZ/WI.
- Instructions which insert Logical Address Tags into addresses treat the Allocation Tag used to generate the Logical Address Tag as 0.
- Cache maintenance instructions which invalidate Allocation Tags from caches behave as the equivalent Clean and Invalidate operation on Allocation Tags.

ATA0	Meaning
0b0	Access to Allocation Tags is prevented.
0b1	Access to Allocation Tags is not prevented.

This field is permitted to be cached in a TLB.

Note

Software may change this control bit on a context switch.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TCF, bits [41:40]

When ARMv8.5-MemTag is implemented:

Tag Check Fault~~Fail~~ in EL1. Controls the effect of Tag~~tag~~ Check~~check~~ Faults~~fails~~ due to Loads and Stores in EL1.

TCF	Meaning
0b00	Tag Check~~check~~ Faults~~fails~~ have no effect on the PE.
0b01	Tag Check~~check~~ Faults~~fails~~ causes a synchronous exception.
0b10	Tag Check~~check~~ Faults~~fails~~ are asynchronously accumulated.

The value 0b11 is reserved.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TCF0, bits [39:38]

When ARMv8.5-MemTag is implemented:

Tag Check Fault~~Fail~~ in EL0. When HCR_EL2.{E2H,TGE} != {1,1}, controls the effect of Tag~~tag~~ Check~~check~~ Faults~~fails~~ due to Loads and Stores in EL0.

TCF0	Meaning
0b00	Tag Check~~check~~ Faults~~fails~~ have no effect on the PE.
0b01	Tag Check~~check~~ Faults~~fails~~ causes a synchronous exception.
0b10	Tag Check~~check~~ Faults~~fails~~ are asynchronously accumulated.

The value 0b11 is reserved.

Note

Software may change this control bit on a context switch.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ITFSB, bit [37]

When ARMv8.5-MemTag is implemented:

When synchronous exceptions are not being generated by Tag Check Faultsfails which are generated for Loads and Stores in EL0 or EL1, controls the auto-synchronization of Tag Check Faultsfails into TFSRE0_EL1 and TFSR_EL1.

ITFSB	Meaning
0b0	Tag Checkcheck Faultsfails are not synchronized on entry to EL1.
0b1	Tag Checkcheck Faultsfails are synchronized on entry to EL1.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

BT1, bit [36]

When ARMv8.5-BTI is implemented:

PAC Branch Type compatibility at EL1.

BT1	Meaning
0b0	When the PE is executing at EL1, PACIASP and PACIBSP are compatible with PSTATE.BTYPE == 0b11.
0b1	When the PE is executing at EL1, PACIASP and PACIBSP are not compatible with PSTATE.BTYPE == 0b11.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

BT0, bit [35]

When ARMv8.5-BTI is implemented:

PAC Branch Type compatibility at EL0.

BT0	Meaning
0b0	When the PE is executing at EL0, PACIASP and PACIBSP are compatible with PSTATE.BTYPE == 0b11.
0b1	When the PE is executing at EL0, PACIASP and PACIBSP are not compatible with PSTATE.BTYPE == 0b11.

When HCR_EL2.E2H == 1 && HCR_EL2.TGE == 1, the value of the SCTLR_EL1.BT0 has no effect on execution at EL0

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [34:32]

Reserved, RES0.

EnIA, bit [31]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APIAKey_EL1 key) of instruction addresses in the EL1&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnIA	Meaning
0b0	Pointer authentication (using the APIAKey_EL1 key) of instruction addresses is not enabled.
0b1	Pointer authentication (using the APIAKey_EL1 key) of instruction addresses is enabled.

Note

This field controls the behavior of the AddPACIA and AuthIA pseudocode functions. Specifically, when the field is 1, AddPACIA returns a copy of a pointer to which a pointer authentication code has been added, and AuthIA returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EnIB, bit [30]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APIBKey_EL1 key) of instruction addresses in the EL1&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnIB	Meaning
0b0	Pointer authentication (using the APIBKey_EL1 key) of instruction addresses is not enabled.
0b1	Pointer authentication (using the APIBKey_EL1 key) of instruction addresses is enabled.

Note

This field controls the behavior of the AddPACIB and AuthIB pseudocode functions. Specifically, when the field is 1, AddPACIB returns a copy of a pointer to which a pointer authentication code has been added, and AuthIB returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

LSMAOE, bit [29]

When ARMv8.2-LSMAOC is implemented:

Load Multiple and Store Multiple Atomicity and Ordering Enable.

LSMAOE	Meaning
0b0	For all memory accesses at EL0, A32 and T32 Load Multiple and Store Multiple can have an interrupt taken during the sequence memory accesses, and the memory accesses are not required to be ordered.
0b1	The ordering and interrupt behavior of A32 and T32 Load Multiple and Store Multiple at EL0 is as defined for Armv8.0.

This bit is permitted to be cached in a TLB.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1,1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

nTLSMD, bit [28]

When ARMv8.2-LSMAOC is implemented:

No Trap Load Multiple and Store Multiple to Device-nGRE/Device-nGnRE/Device-nGnRnE memory.

nTLSMD	Meaning
0b0	All memory accesses by A32 and T32 Load Multiple and Store Multiple at EL0 that are marked at stage 1 as Device-nGRE/Device-nGnRE/Device-nGnRnE memory are trapped and generate a stage 1 Alignment fault.
0b1	All memory accesses by A32 and T32 Load Multiple and Store Multiple at EL0 that are marked at stage 1 as Device-nGRE/Device-nGnRE/Device-nGnRnE memory are not trapped.

This bit is permitted to be cached in a TLB.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1,1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

EnDA, bit [27]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APDAKey_EL1 key) of instruction addresses in the EL1&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnDA	Meaning
0b0	Pointer authentication (using the APDAKey_EL1 key) of data addresses is not enabled.
0b1	Pointer authentication (using the APDAKey_EL1 key) of data addresses is enabled.

Note

This field controls the behavior of the AddPACDA and AuthDA pseudocode functions. Specifically, when the field is 1, AddPACDA returns a copy of a pointer to which a pointer authentication code has been added, and AuthDA returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

UCI, bit [26]

Traps EL0 execution of cache maintenance instructions, to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, from AArch64 state only, reported using EC syndrome value 0x18.

This applies to DC CVAU, DC CIVAC, DC CVAC, DC CVAP, and IC IVAU.

If ARMv8.2-DCCVADP is implemented, this trap also applies to DC CVADP.

If ARMv8.5-MemTag is implemented, this trap also applies to DC CIGVAC, DC CIGDVAC, DC CGVAC, DC CGDVAC, DC CGVAP, and DC CGDVAP.

If ARMv8.2-DCCVADP and ARMv8.5-MemTag are implemented, this trap also applies to DC CGVADP and DC CGDVADP.

UCI	Meaning
0b0	Execution of the specified instructions at EL0 using AArch64 is trapped.
0b1	This control does not cause any instructions to be trapped.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

If the Point of Coherency is before any level of data cache, it is IMPLEMENTATION DEFINED whether the execution of any data or unified cache clean, or clean and invalidate instruction that operates by VA to the point of coherency can be trapped when the value of this control is 1.

If the Point of Unification is before any level of data cache, it is IMPLEMENTATION DEFINED whether the execution of any data or unified cache clean by VA to the Point of Unification instruction can be trapped when the value of this control is 1.

If the Point of Unification is before any level of instruction cache, it is IMPLEMENTATION DEFINED whether the execution of any instruction cache invalidate by VA to the Point of Unification instruction can be trapped when the value of this control is 1.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

EE, bit [25]

Endianness of data accesses at EL1, and stage 1 translation table walks in the EL1&0 translation regime.

The possible values of this bit are:

EE	Meaning
0b0	Explicit data accesses at EL1, and stage 1 translation table walks in the EL1&0 translation regime are little-endian.
0b1	Explicit data accesses at EL1, and stage 1 translation table walks in the EL1&0 translation regime are big-endian.

If an implementation does not provide Big-endian support at Exception Levels higher than EL0, this bit is RES0.

If an implementation does not provide Little-endian support at Exception Levels higher than EL0, this bit is RES1.

The EE bit is permitted to be cached in a TLB.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on the PE.

In a system where the PE resets into EL1, this field resets to an IMPLEMENTATION DEFINED value.

E0E, bit [24]

Endianness of data accesses at EL0.

The possible values of this bit are:

E0E	Meaning
0b0	Explicit data accesses at EL0 are little-endian.
0b1	Explicit data accesses at EL0 are big-endian.

If an implementation only supports Little-endian accesses at EL0 then this bit is RES0. This option is not permitted when SCTLR_EL1.EE is RES1.

If an implementation only supports Big-endian accesses at EL0 then this bit is RES1. This option is not permitted when SCTLR_EL1.EE is RES0.

This bit has no effect on the endianness of LDTR, LDTRH, LDTRSH, LDTRSW, STTR, and STTRH instructions executed at EL1.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

SPAN, bit [23]

When ARMv8.1-PAN is implemented:

Set Privileged Access Never, on taking an exception to EL1.

SPAN	Meaning
0b0	PSTATE.PAN is set to 1 on taking an exception to EL1.
0b1	The value of PSTATE.PAN is left unchanged on taking an exception to EL1.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

EIS, bit [22]

When ARMv8.5-CSEH is implemented:

Exception Entry is Context Synchronizing. The defined values are:

EIS	Meaning
0b0	The taking of an exception to EL1 is not a context synchronizing event.
0b1	The taking of an exception to EL1 is a context synchronizing event.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1,1}, this bit has no effect on execution at EL0.

If SCTLR_EL1.EIS is set to 0b0:

- Indirect writes to ESR_EL1, FAR_EL1, SPSR_EL1, ELR_EL1 are synchronized on exception entry to EL1, so that a direct read of the register after exception entry sees the indirectly written value caused by the exception entry.
- Memory transactions, including instruction fetches, from an Exception level always use the translation resources associated with that translation regime.
- Exception Catch debug events are synchronous debug events.
- DCPS* and DRPS instructions are context synchronization events.

The following are not affected by the value of SCTLR_EL1.EIS:

- Changes to the PSTATE information on entry to EL1.
- Behavior of accessing the banked copies of the stack pointer using the SP register name for loads, stores and data processing instructions.
- Exit from Debug state.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

IESB, bit [21]

When ARMv8.2-IESB is implemented:

Implicit Error Synchronization event enable. Possible values are:

IESB	Meaning
0b0	Disabled.
0b1	An implicit error synchronization event is added: • At each exception taken to EL1. • Before the operational pseudocode of each ERET instruction executed at EL1.

When the PE is in Debug state, the effect of this field is CONSTRAINED UNPREDICTABLE, and its Effective value might be 0 or 1 regardless of the value of the field. If the Effective value of the field is 1, then an implicit error synchronization event is added after each DCPSX instruction taken to EL1 and before each DRPS instruction executed at EL1, in addition to the other cases where it is added.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TSCXT, bit [20]

When ARMv8.0-CSV2 is implemented:

Trap EL0 Access to the SCXTNUM_EL0 register, when EL0 is using AArch64. The defined values are:

TSCXT	Meaning
0b0	EL0 access to SCXTNUM_EL0 is not disabled by this mechanism.
0b1	EL0 access to SCXTNUM_EL0 is disabled, causing an exception to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1. The value of SCXTNUM_EL0 is treated as 0.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1,1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

WXN, bit [19]

Write permission implies XN (Execute-never). For the EL1&0 translation regime, this bit can force all memory regions that are writable to be treated as XN. The possible values of this bit are:

WXN	Meaning
0b0	This control has no effect on memory access permissions.
0b1	Any region that is writable in the EL1&0 translation regime is forced to XN for accesses from software executing at EL1 or EL0.

This bit applies only when SCTLR_EL1.M bit is set.

The WXN bit is permitted to be cached in a TLB.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on the PE.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

nTWE, bit [18]

Traps EL0 execution of WFE instructions to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, from both Execution states, reported using EC syndrome value 0x01.

nTWE	Meaning
0b0	Any attempt to execute a WFE instruction at EL0 is trapped, if the instruction would otherwise have caused the PE to enter a low-power state.
0b1	This control does not cause any instructions to be trapped.

In AArch32 state, the attempted execution of a conditional WFE instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE or WFI can complete at any time, even without a Wakeup event, the traps on WFE of WFI are not guaranteed to be taken, even if the WFE or WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Bit [17]

Reserved, RES0.

nTWI, bit [16]

Traps EL0 execution of WFI instructions to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, from both Execution states, reported using EC syndrome value 0x01.

nTWI	Meaning
0b0	Any attempt to execute a WFI instruction at EL0 is trapped, if the instruction would otherwise have caused the PE to enter a low-power state.
0b1	This control does not cause any instructions to be trapped.

In AArch32 state, the attempted execution of a conditional WFI instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE or WFI can complete at any time, even without a Wakeup event, the traps on WFE of WFI are not guaranteed to be taken, even if the WFE or WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

UCT, bit [15]

Traps EL0 accesses to the CTR_EL0 to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, from AArch64 state only, reported using EC value 0x18.

UCT	Meaning
0b0	Accesses to the CTR_EL0 from EL0 using AArch64 are trapped.
0b1	This control does not cause any instructions to be trapped.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

DZE, bit [14]

Traps EL0 execution of DC ZVA instructions to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, from AArch64 state only, reported using EC syndrome value 0x18.

If ARMv8.5-MemTag is implemented, this trap also applies to DC GVA and DC GZVA.

DZE	Meaning
0b0	Any attempt to execute an instruction that this trap applies to at EL0 using AArch64 is trapped. Reading DCZID_EL0.DZP from EL0 returns 1, indicating that the instructions this trap applies to are not supported.
0b1	This control does not cause any instructions to be trapped.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

EnDB, bit [13]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APDBKey_EL1 key) of instruction addresses in the EL1&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnDB	Meaning
0b0	Pointer authentication (using the APDBKey_EL1 key) of data addresses is not enabled.
0b1	Pointer authentication (using the APDBKey_EL1 key) of data addresses is enabled.

Note

This field controls the behavior of the AddPACDB and AuthDB pseudocode functions. Specifically, when the field is 1, AddPACDB returns a copy of a pointer to which a pointer authentication code has been added, and AuthDB returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

I, bit [12]

Instruction access Cacheability control, for accesses at EL0 and EL1:

I	Meaning
0b0	All instruction access to Normal memory from EL0 and EL1 are Non-cacheable for all levels of instruction and unified cache. If the value of SCTLR_EL1.M is 0, instruction accesses from stage 1 of the EL1&0 translation regime are to Normal, Outer Shareable, Inner Non-cacheable, Outer Non-cacheable memory.
0b1	This control has no effect on the Cacheability of instruction access to Normal memory from EL0 and EL1. If the value of SCTLR_EL1.M is 0, instruction accesses from stage 1 of the EL1&0 translation regime are to Normal, Outer Shareable, Inner Write-Through, Outer Write-Through memory.

When the value of the HCR_EL2.DC bit is 1, then instruction access to Normal memory from EL0 and EL1 are Cacheable regardless of the value of the SCTLR_EL1.I bit.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on the PE.

In a system where the PE resets into EL1, this field resets to 0.

EOS, bit [11]

When ARMv8.5-CSEH is implemented:

Exception Exit is Context Synchronizing. The defined values are:

EOS	Meaning
0b0	An exception return from EL1 is not a context synchronizing event
0b1	An exception return from EL1 is a context synchronizing event

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1,1}, this bit has no effect on execution at EL0.

If SCTLR_EL1.EOS is set to 0b0:

- Memory transactions, including instruction fetches, from an Exception level always use the translation resources associated with that translation regime.
- Exception Catch debug events are synchronous debug events.
- DCPS* and DRPS instructions are context synchronization events.

The following are not affected by the value of SCTLR_EL1.EOS:

- The indirect write of the PSTATE and PC values from SPSR_EL1 and ELR_EL1 on exception return is synchronized.
- Behavior of accessing the banked copies of the stack pointer using the SP register name for loads, stores and data processing instructions.
- Exit from Debug state.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

EnRCTX, bit [10]

When ARMv8.0-PredInv is implemented:

Enable EL0 Access to the following~~AArch32 CFPRCTX, DVPRCTX and CPPRCTX~~ instructions~~, and the AArch64 CFP RCTX, DVP RCT and CPP RCTX instructions. The defined values are~~:

- AArch32 CFPRCTX, DVPRCTX and CPPRCTX instructions.
- AArch64 CFP RCTX, DVP RCT and CPP RCTX instructions.

The defined values are:

EnRCTX	Meaning
0b0	EL0 access to these instructions is disabled, and these instructions are trapped to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1.
0b1	EL0 access to these instructions is enabled.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1,1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

UMA, bit [9]

User Mask Access. Traps EL0 execution of MSR and MRS instructions that access the PSTATE.{D, A, I, F} masks to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, from AArch64 state only, reported using EC syndrome value 0x18.

UMA	Meaning
0b0	Any attempt at EL0 using AArch64 to execute an MRS, MSR(REGISTER), or MSR(IMMEDIATE) instruction that accesses the DAIF is trapped.
0b1	This control does not cause any instructions to be trapped.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

SED, bit [8]

When AArch32 is supported at any Exception level and EL0 is capable of using AArch32:

SETEND instruction disable. Disables SETEND instructions at EL0 using AArch32.

SED	Meaning
0b0	SETEND instruction execution is enabled at EL0 using AArch32.
0b1	SETEND instructions are UNDEFINED at EL0 using AArch32 and any attempt at EL0 to access a SETEND instruction generates an exception to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1, reported using EC syndrome value 0x00.

If the implementation does not support mixed-endian operation at any Exception level, this bit is RES1.

~~If EL0 cannot use AArch32, this bit is RES1.~~

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

~~**ITD, bit [7]**~~

Otherwise:

Reserved, RES1.

ITD, bit [7]

When AArch32 is supported at any Exception level and EL0 is capable of using AArch32:

IT Disable. Disables some uses of IT instructions at EL0 using AArch32.

ITD	Meaning
0b0	All IT instruction functionality is enabled at EL0 using AArch32.
0b1	Any attempt at EL0 using AArch32 to execute any of the following is UNDEFINED and generates an exception, reported using EC syndrome value 0x00, to EL1 or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1: • All encodings of the IT instruction with hw1[3:0]!=1000. • All encodings of the subsequent instruction with the following values for hw1: ◦ 0b11xxxxxxxxxxxxxx: All 32-bit instructions, and the 16-bit instructions B, UDF, SVC, LDM, and STM. ◦ 0b1011xxxxxxxxxxxx: All instructions in 'Miscellaneous 16-bit instructions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section F3.2.5. ◦ 0b10100xxxxxxxxxxx: ADD Rd, PC, #imm ◦ 0b01001xxxxxxxxxxx: LDR Rd, [PC, #imm] ◦ 0b0100x1xxx1111xxx: ADD Rdn, PC; CMP Rn, PC; MOV Rd, PC; BX PC; BLX PC. ◦ 0b010001xx1xxxx111: ADD PC, Rm; CMP PC, Rm; MOV PC, Rm. This pattern also covers unpredictable cases with BLX Rn. These instructions are always UNDEFINED, regardless of whether they would pass or fail the condition code check that applies to them as a result of being in an IT block. It is IMPLEMENTATION DEFINED whether the IT instruction is treated as: • A 16-bit instruction, that can only be followed by another 16-bit instruction. • The first half of a 32-bit instruction. This means that, for the situations that are UNDEFINED, either the second 16-bit instruction or the 32-bit instruction is UNDEFINED. An implementation might vary dynamically as to whether IT is treated as a 16-bit instruction or the first half of a 32-bit instruction.

If an instruction in an active IT block that would be disabled by this field sets this field to 1 then behavior is CONSTRAINED UNPREDICTABLE. For more information see 'Changes to an ITD control by an instruction in an IT block' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section E1.2.4

~~If EL0 cannot use AArch32, this bit is RES1.~~

ITD is optional, but if it is implemented in the SCTLR then it must also be implemented in the SCTLR_EL1. If it is not implemented then this bit is RAZ/WI.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

nAA, bit [6]

When ARMv8.4-LSE is implemented:

Non-aligned access. This bit controls generation of Alignment faults at EL1 and EL0 under certain conditions.

nAA	Meaning
0b0	LDAPR, LDAPRH, LDAPUR, LDAPURH, LDAPURSH, LDAPURSW, LDAR, LDARH, LDLAR, LDLARH, STLLR, STLLRH, STLR, STLRH, STLUR, and STLURH generate an Alignment fault if all bytes being accessed are not within a single 16-byte quantity, aligned to 16 bytes for accesses.
0b1	This control bit does not cause LDAPR, LDAPRH, LDAPUR, LDAPURH, LDAPURSH, LDAPURSW, LDAR, LDARH, LDLAR, LDLARH, STLLR, STLLRH, STLR, STLRH, STLUR, or STLURH to generate an Alignment fault if all bytes being accessed are not within a single 16-byte quantity, aligned to 16 bytes.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

CP15BEN, bit [5]

When AArch32 is supported at any Exception level and EL0 is capable of using AArch32:

System instruction memory barrier enable. Enables accesses to the DMB, DSB, and ISB System instructions in the (coproc==0b1111) encoding space from EL0:

CP15BEN	Meaning
0b0	EL0 using AArch32: EL0 execution of the CP15DMB, CP15DSB, and CP15ISB instructions is UNDEFINED and generates an exception to EL1, or to EL2 when it is implemented and enabled for the current Security state and HCR_EL2.TGE is 1. The exception is reported using EC syndrome value 0x00.
0b1	EL0 using AArch32: EL0 execution of the CP15DMB, CP15DSB, and CP15ISB instructions is enabled.

~~If EL0 cannot use AArch32, this bit is RES0.~~

CP15BEN is optional, but if it is implemented in the SCTLR then it must also be implemented in the SCTLR_EL1. If it is not implemented then this bit is RAO/WI.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SA0, bit [4]

SP Alignment check enable for EL0. When set to 1, if a load or store instruction executed at EL0 uses the SP as the base address and the SP is not aligned to a 16-byte boundary, then a SP alignment fault exception is generated. For more information, see 'SP alignment checking' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1 (The AArch64 System Level Programmers' Model).

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

SA, bit [3]

SP Alignment check enable. When set to 1, if a load or store instruction executed at EL1 uses the SP as the base address and the SP is not aligned to a 16-byte boundary, then a SP alignment fault exception is generated. For more information, see 'SP alignment checking' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1 (The AArch64 System Level Programmers' Model).

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on the PE.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

C, bit [2]

Cacheability control, for data accesses.

C	Meaning
0b0	All data access to Normal memory from EL0 and EL1, and all Normal memory accesses to the EL1&0 stage 1 translation tables, are Non-cacheable for all levels of data and unified cache.
0b1	This control has no effect on the Cacheability of: • Data access to Normal memory from EL0 and EL1. • Normal memory accesses to the EL1&0 stage 1 translation tables.

When the value of the HCR_EL2.DC bit is 1, the PE ignores SCLTR.C. This means that Non-secure EL0 and Non-secure EL1 data accesses to Normal memory are Cacheable.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on the PE.

In a system where the PE resets into EL1, this field resets to 0.

A, bit [1]

Alignment check enable. This is the enable bit for Alignment fault checking at EL1 and EL0 ~~.EL0.~~

A	Meaning
0b0	Alignment fault checking disabled when executing at EL1 or EL0. Instructions that load or store one or more registers, other than load/store exclusive and load-acquire/store-release, do not check that the address being accessed is aligned to the size of the data element(s) being accessed.
0b1	Alignment fault checking enabled when executing at EL1 or EL0. All instructions that load or store one or more registers have an alignment check that the address being accessed is aligned to the size of the data element(s) being accessed. If this check fails it causes an Alignment fault, which is taken as a Data Abort exception.

Load/store exclusive and load-acquire/store-release instructions have an alignment check regardless of the value of the A bit.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on execution at EL0.

In a system where the PE resets into EL1, this field resets to an architecturally UNKNOWN value.

M, bit [0]

MMU enable for EL1&0 ~~and EL0~~ stage 1 address translation. ~~Possible values of this bit are:~~

M	Meaning
0b0	EL1&0 ~~and EL0~~ stage 1 address translation disabled. See the SCTLR_EL1.I field for the behavior of instruction accesses to Normal memory.
0b1	EL1&0 ~~and EL0~~ stage 1 address translation enabled.

If the value of HCR_EL2.{DC, TGE} is not {0, 0} then in Non-secure state the PE behaves as if the value of the SCTLR_EL1.M field is 0 for all purposes other than returning the value of a direct read of the field.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this bit has no effect on the PE.

In a system where the PE resets into EL1, this field resets to `0`.

Accessing the SCTLR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic SCTLR_EL1 or SCTLR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, SCTLR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.SCTLR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x110];
    else
        return SCTLR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return SCTLR_EL2;
    else
        return SCTLR_EL1;
elsif PSTATE.EL == EL3 then
    return SCTLR_EL1;
```

```
MSR SCTLR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.SCTLR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x110] = X[t];
    else
        SCTLR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        SCTLR_EL2 = X[t];
    else
        SCTLR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    SCTLR_EL1 = X[t];
```

MRS <Xt>, SCTLR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x110];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return SCTLR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return SCTLR_EL1;
    else
        UNDEFINED;
```

MSR SCTLR_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x110] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        SCTLR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        SCTLR_EL1 = X[t];
    else
        UNDEFINED;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SCTLR_EL2, System Control Register (EL2)

The SCTLR_EL2 characteristics are:

Purpose

Provides top level control of the system, including its memory system, at EL2.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, these controls apply also to execution at EL0.

Configuration

AArch64 System register SCTLR_EL2 bits [31:0] are architecturally mapped to AArch32 System register HSCTLR[31:0] .

If EL2 is not implemented, this register is RES0 from EL3.

This register has no effect if EL2 is not enabled in the current Security state.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SCTLR_EL2 is a 64-bit register.

Field descriptions

The SCTLR_EL2 bit assignments are:

When HCR_EL2.E2H != 0b1 or HCR_EL2.TGE != 0b1:



This format applies in all Armv8.0 implementations, and from Armv8.1 when the Effective value of HCR_EL2.{E2H, TGE} != {1, 1}.

Bits [63:45]

Reserved, RES0.

DSSBS, bit [44]

When ARMv8.0-SSBS is implemented:

Default PSTATE.SSBS value on Exception Entry.

DSSBS	Meaning
0b0	PSTATE.SSBS is set to 0 on an exception to EL2.
0b1	PSTATE.SSBS is set to 1 on an exception to EL2.

In a system where the PE resets into EL2, this field resets to an IMPLEMENTATION DEFINED value.

Otherwise:

Reserved, RES0.

ATA, bit [43]

When ARMv8.5-MemTag is implemented:

Allocation Tag Access. When SCR_EL3.ATA=1, controls EL2 access to Allocation Tags.

When access to Allocation Tags is prevented:

- Instructions thatwhich Load or Store data are Unchecked.
- Instructions thatwhich Load or Store Allocation Tags treat the Allocation Tag as RAZ/WI.
- Instructions thatwhich insert Logical Address Tags into addresses treat the Allocation Tag used to generate the Logical Address Tag as 0.
- Cache maintenance instructions thatwhich invalidate Allocation Tags from caches behave as the equivalent Clean and Invalidate operation on Allocation Tags.

ATA	Meaning
0b0	Access to Allocation Tags is prevented.
0b1	Access to Allocation Tags is not prevented.

This bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [42]

Reserved, RES0.

TCF, bits [41:40]

When ARMv8.5-MemTag is implemented:

TagTack Check Fault.Fail in EL2. Controls the effect of Tagtag Checkcheck Faultsfails due to Loads and Stores in EL2.

TCF	Meaning
0b00	Tag Checkcheck Faultsfails have no effect on the PE.
0b01	Tag Checkcheck Faultsfails causecauses a synchronous exception.
0b10	Tag Checkcheck Faultsfails are asynchronously accumulated.

The value 0b11 is reserved.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [39:38]

Reserved, RES0.

ITFSB, bit [37]

When ARMv8.5-MemTag is implemented:

When synchronous exceptions are not being generated by Tag Check Faults,~~fails~~ which are generated for Loads and Stores in EL0, EL1 or EL2, controls the auto-synchronizaton~~auto-synchronisaton~~ of Tag Check Faults~~fails~~ into TFSRE0_EL1, TFSR_EL1, and TFSR_EL2.

ITFSB	Meaning
0b0	Tag Check~~check~~ Faults~~fails~~ are not synchronized on entry to EL2.
0b1	Tag Check~~check~~ Faults~~fails~~ are synchronized on entry to EL2.

Otherwise:

Reserved, RES0.

BT, bit [36]

When ARMv8.5-BTI is implemented:

PAC Branch Type compatibility at EL2.

BT	Meaning
0b0	When the PE is executing at EL2, PACIASP and PACIBSP are compatible with PSTATE.BTYPE == 0b11.
0b1	When the PE is executing at EL2, PACIASP and PACIBSP are not compatible with PSTATE.BTYPE == 0b11.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [35:32]

Reserved, RES0.

EnIA, bit [31]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APIAKey_EL1 key) of instruction addresses in the EL2&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnIA	Meaning
0b0	Pointer authentication (using the APIAKey_EL1 key) of instruction addresses is not enabled.
0b1	Pointer authentication (using the APIAKey_EL1 key) of instruction addresses is enabled.

Note

This field controls the behavior of the AddPACIA and AuthIA pseudocode functions. Specifically, when the field is 1, AddPACIA returns a copy of a pointer to which a pointer authentication code has been added, and AuthIA returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EnIB, bit [30]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APIBKey_EL1 key) of instruction addresses in the EL2&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnIB	Meaning
0b0	Pointer authentication (using the APIBKey_EL1 key) of instruction addresses is not enabled.
0b1	Pointer authentication (using the APIBKey_EL1 key) of instruction addresses is enabled.

Note

This field controls the behavior of the AddPACIB and AuthIB pseudocode functions. Specifically, when the field is 1, AddPACIB returns a copy of a pointer to which a pointer authentication code has been added, and AuthIB returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [29:28]

Reserved, RES1.

EnDA, bit [27]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APDAKey_EL1 key) of instruction addresses in the EL2&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnDA	Meaning
0b0	Pointer authentication (using the APDAKey_EL1 key) of data addresses is not enabled.
0b1	Pointer authentication (using the APDAKey_EL1 key) of data addresses is enabled.

Note

This field controls the behavior of the AddPACDA and AuthDA pseudocode functions. Specifically, when the field is 1, AddPACDA returns a copy of a pointer to which a pointer authentication code has been added, and AuthDA returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [26]

Reserved, RES0.

EE, bit [25]

Endianness of data accesses at EL2, stage 1 translation table walks in the EL2 or EL2&0 translation regime, and stage 2 translation table walks in the EL1&0 translation regime.

~~The possible values of this bit are:~~

EE	Meaning
0b0	Explicit data accesses at EL2, stage 1 translation table walks in the EL2 or EL2&0 translation regime, and stage 2 translation table walks in the EL1&0 translation regime are little-endian.
0b1	Explicit data accesses at EL2, stage 1 translation table walks in the EL2 or EL2&0 translation regime, and stage 2 translation table walks in the EL1&0 translation regime are big-endian.

If an implementation does not provide Big-endian support at Exception Levels higher than EL0, this bit is RES0.

If an implementation does not provide Little-endian support at Exception Levels higher than EL0, this bit is RES1.

The EE bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2, this field resets to an IMPLEMENTATION DEFINED value.

Bit [24]

Reserved, RES0.

Bit [23]

Reserved, RES1.

EIS, bit [22]

When ARMv8.5-CSEH is implemented:

Exception entry is a context synchronization event. The defined values are:

EIS	Meaning
0b0	The taking of an exception to EL2 is not a context synchronization event.
0b1	The taking of an exception to EL2 is a context synchronization event.

If SCTLR_EL2.EIS is set to 0b0:

- Indirect writes to ESR_EL2, FAR_EL2, SPSR_EL2, ELR_EL2, and HPFAR_EL2 are synchronized on exception entry to EL2, so that a direct read of the register after exception entry sees the indirectly written value caused by the exception entry.
- Memory transactions, including instruction fetches, from an Exception level always use the translation resources associated with that translation regime.
- Exception Catch debug events are synchronous debug events.
- DCPS* and DRPS instructions are context synchronization events.

The following are not affected by the value of SCTLR_EL2.EIS:

- Changes to the PSTATE information on entry to EL2.

- Behavior of accessing the banked copies of the stack pointer using the SP register name for loads, stores, and data processing instructions.
- Exit from Debug state.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

IESB, bit [21]

When ARMv8.2-IESB is implemented:

Implicit Error Synchronization event enable.

IESB	Meaning
0b0	Disabled.
0b1	An implicit error synchronization event is added: • At each exception taken to EL2. • Before the operational pseudocode of each ERET instruction executed at EL2.

When the PE is in Debug state, the effect of this field is CONSTRAINED UNPREDICTABLE, and its Effective value might be 0 or 1 regardless of the value of the field. If the Effective value of the field is 1, then an implicit error synchronization event is added after each DCPSX instruction taken to EL2 and before each DRPS instruction executed at EL2, in addition to the other cases where it is added.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [20]

Reserved, RES0.

WXN, bit [19]

Write permission implies XN (Execute-never). For the EL2 or EL2&0 translation regime, this bit can force all memory regions that are writable to be treated as XN:

WXN	Meaning
0b0	This control has no effect on memory access permissions.
0b1	Any region that is writable in the EL2 or EL2&0 translation regime is forced to XN for accesses from software executing at EL2.

This bit applies only when SCTLR_EL2.M bit is set.

The WXN bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Bit [18]

Reserved, RES1.

Bit [17]

Reserved, RES0.

Bit [16]

Reserved, RES1.

Bits [15:14]

Reserved, RES0.

EnDB, bit [13]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APDBKey_EL1 key) of instruction addresses in the EL2&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnDB	Meaning
0b0	Pointer authentication (using the APDBKey_EL1 key) of data addresses is not enabled.
0b1	Pointer authentication (using the APDBKey_EL1 key) of data addresses is enabled.

Note

This field controls the behavior of the AddPACDB and AuthDB pseudocode functions. Specifically, when the field is 1, AddPACDB returns a copy of a pointer to which a pointer authentication code has been added, and AuthDB returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

I, bit [12]

Instruction access Cacheability control, for accesses at EL2:

I	Meaning
0b0	All instruction accessesaccess to Normal memory from EL2 are Non-cacheable for all levels of instruction and unified cache. If the value of SCTLR_EL2.M is 0, instruction accesses from stage 1 of the EL2 or EL2&0 translation regime are to Normal, Outer Shareable, Inner Non-cacheable, Outer Non-cacheable memory.
0b1	This control has no effect on the Cacheability of instruction access to Normal memory from EL2. If the value of SCTLR_EL2.M is 0, instruction accesses from stage 1 of the EL2 or EL2&0 translation regime are to Normal, Outer Shareable, Inner Write-Through, Outer Write-Through memory.

This bit has no effect on the EL1&0 or EL3 translation regimes.

In a system where the PE resets into EL2, this field resets to 0.

EOS, bit [11]

When ARMv8.5-CSEH is implemented:

Exception exit is a context synchronization Event.

EOS	Meaning
0b0	An exception return from EL2 is not a context synchronization event.
0b1	An exception return from EL2 is a context synchronization event.

If SCTLR_EL2.EOS is set to 0b0:

- Memory transactions, including instruction fetches, from an Exception level always use the translation resources associated with that translation regime.
- Exception Catch debug events are synchronous debug events.
- DCPS* and DRPS instructions are context synchronization events.

The following are not affected by the value of SCTLR_EL2.EOS:

- The indirect write of the PSTATE and PC values from SPSR_EL2 and ELR_EL2 on exception return is synchronized.
- Behavior of accessing the banked copies of the stack pointer using the SP register name for loads, stores, and data processing instructions.
- Exit from Debug state.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

Bits [10:7]

Reserved, RES0.

nAA, bit [6]

When ARMv8.4-LSE is implemented:

Non-aligned access. This bit controls generation of Alignment faults at EL2 under certain conditions.

nAA	Meaning
0b0	LDAPR, LDAPRH, LDAPUR, LDAPURH, LDAPURSH, LDAPURSW, LDAR, LDARH, LDLAR, LDLARH, STLLR, STLLRH, STLR, STLRH, STLUR, and STLURH generate an Alignment fault if all bytes being accessed are not within a single 16-byte quantity, aligned to 16 bytes for accesses.
0b1	This control bit does not cause LDAPR, LDAPRH, LDAPUR, LDAPURH, LDAPURSH, LDAPURSW, LDAR, LDARH, LDLAR, LDLARH, STLLR, STLLRH, STLR, STLRH, STLUR, or STLURH to generate an Alignment fault if all bytes being accessed are not within a single 16-byte quantity, aligned to 16 bytes.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [5:4]

Reserved, RES1.

SA, bit [3]

SP Alignment check enable. When set to 1, if a load or store instruction executed at EL2 uses the SP as the base address and the SP is not aligned to a 16-byte boundary, then ana SP alignment fault exception is generated. For more

information, see 'SP alignment checking' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1 (The AArch64 System Level Programmers' Model).

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

C, bit [2]

Cacheability control, for data accesses.

C	Meaning
0b0	All data accessesaccess to Normal memory from EL2, and all Normal memory accesses to the EL2 translation tables, are Non-cacheable for all levels of data and unified cache.
0b1	This control has no effect on the Cacheability of: • Data access to Normal memory from EL2. • Normal memory accesses to the EL2 translation tables.

This bit has no effect on the EL1&0 or EL3 translation regimes.

In a system where the PE resets into EL2, this field resets to 0.

A, bit [1]

Alignment check enable. This is the enable bit for Alignment fault checking at EL2:

A	Meaning
0b0	Alignment fault checking disabled when executing at EL2. Instructions that load or store one or more registers, other than load/store exclusive and load-acquire/store-release, do not check that the address being accessed is aligned to the size of the data element(s) being accessed.
0b1	Alignment fault checking enabled when executing at EL2. All instructions that load or store one or more registers have an alignment check that the address being accessed is aligned to the size of the data element(s) being accessed. If this check fails it causes an Alignment fault, which is taken as a Data Abort exception.

Load/store exclusive and load-acquire/store-release instructions have an alignment check regardless of the value of the A bit.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

M, bit [0]

MMU enable for EL2 stage 1 address translation. ~~Possible values of this bit are:~~

M	Meaning
0b0	EL2 stage 1 address translation disabled. See the SCTLR_EL2.I field for the behavior of instruction accesses to Normal memory.
0b1	EL2 stage 1 address translation enabled.

In a system where the PE resets into EL2, this field resets to 0.

When HCR_EL2.E2H == 0b1 and HCR_EL2.TGE == 0b1:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	4
RES0														TWEDEL				TWEDEn	DSSBS	ATA	AT
EnIA	EnIB	LSMAOE	nTLSMD	EnDA	UCI	EE	E0E	SPAN	EIS	IESB	TSCXT	WXN	nTWE	RES0	nTWI	UCT	DZE	EnDB	I	EOS	EnR
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	1

This format applies only from Armv8.1 when EL2 is enabled in the current Security state and HCR_EL2.{E2H, TGE} == {1, 1}.

Bits [63:50]

Reserved, RES0.

TWEDEL, bits [49:46]

When ARMv8.6-TWED is implemented:

TWE Delay. A 4-bit unsigned number that, when SCTLR_EL2.TWEDEn is 1, encodes the minimum delay in taking a trap of WFE caused by SCTLR_EL2.nTWE as 2^(TWEDEL + 8) cycles.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TWEDEn, bit [45]

When ARMv8.6-TWED is implemented:

TWE Delay Enable. Enables a configurable delayed trap of the WFE instruction caused by SCTLR_EL2.nTWE.

TWEDEn	Meaning
0b0	The delay for taking a WFE trap is IMPLEMENTATION DEFINED.
0b1	The delay for taking a WFE trap is at least the number of cycles defined in SCTLR_EL2.TWEDEL.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DSSBS, bit [44]

When ARMv8.0-SSBS is implemented:

Default PSTATE.SSBS value on Exception Entry.

DSSBS	Meaning
0b0	PSTATE.SSBS is set to 0 on an exception to EL2.
0b1	PSTATE.SSBS is set to 1 on an exception to EL2.

In a system where the PE resets into EL2, this field resets to an IMPLEMENTATION DEFINED value.

Otherwise:

Reserved, RES0.

ATA, bit [43]

When ARMv8.5-MemTag is implemented:

Allocation Tag Access in EL2. When SCR_EL3.ATA=1, controls EL2 access to Allocation Tags.

When access to Allocation Tags is prevented:

- Instructions which Load or Store data are Unchecked.
- Instructions which Load or Store Allocation Tags treat the Allocation Tag as RAZ/WI.

- Instructions which insert Logical Address Tags into addresses treat the Allocation Tag used to generate the Logical Address Tag as 0.
- Cache maintenance instructions which invalidate Allocation Tags from caches behave as the equivalent Clean and Invalidate operation on Allocation Tags.

ATA	Meaning
0b0	Access to Allocation Tags is prevented.
0b1	Access to Allocation Tags is not prevented.

This bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ATA0, bit [42]

When ARMv8.5-MemTag is implemented:

Allocation Tag Access in EL0. When SCR_EL3.ATA=1, controls EL0 access to Allocation Tags.

When access to Allocation Tags is prevented:

- Instructions which Load or Store data are Unchecked.
- Instructions which Load or Store Allocation Tags treat the Allocation Tag as RAZ/WI.
- Instructions which insert Logical Address Tags into addresses treat the Allocation Tag used to generate the Logical Address Tag as 0.
- Cache maintenance instructions which invalidate Allocation Tags from caches behave as the equivalent Clean and Invalidate operation on Allocation Tags.

ATA0	Meaning
0b0	Access to Allocation Tags is prevented.
0b1	Access to Allocation Tags is not prevented.

This field is permitted to be cached in a TLB.

Note

Software may change this control bit on a context switch.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TCF, bits [41:40]

When ARMv8.5-MemTag is implemented:

Tag Check Fault~~Fail~~ in EL2. Controls the effect of Tag~~tag~~ Check~~check~~ Faults~~fails~~ due to Loads and Stores in EL2.

TCF	Meaning
0b00	Tag Check~~check~~ Faults~~fails~~ have no effect on the PE.
0b01	Tag Check~~check~~ Faults~~fails~~ causes a synchronous exception.
0b10	Tag Check~~check~~ Faults~~fails~~ are asynchronously accumulated.

The value 0b11 is reserved.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TCF0, bits [39:38]

When ARMv8.5-MemTag is implemented:

Tag Check FaultFail in EL0. Controls the effect of Tagtag Checkcheck Faultsfails due to Loads and Stores in EL0.

TCF0	Meaning
0b00	Tag Checkcheck Faultsfails have no effect on the PE.
0b01	Tag Checkcheck Faultsfails causes a synchronous exception.
0b10	Tag Checkcheck Faultsfails are asynchronously accumulated.

The value 0b11 is reserved.

Note

Software may change this control bit on a context switch.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

ITFSB, bit [37]

When ARMv8.5-MemTag is implemented:

When synchronous exceptions are not being generated by Tag Check Faultsfails which are generated for Loads and Stores in EL0, EL1 or EL2, controls the auto-synchronizaton of Tag Check Faultsfails into TFSRE0_EL1, TFSR_EL1 and TFSR_EL2.

ITFSB	Meaning
0b0	Tag Checkcheck Faultsfails are not synchronized on entry to EL2.
0b1	Tag Checkcheck Faultsfails are synchronized on entry to EL2.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

BT1, bit [36]

When ARMv8.5-BTI is implemented:

PAC Branch Type compatibility at EL2.

BT1	Meaning
0b0	When the PE is executing at EL2, PACIASP and PACIBSP are compatible with PSTATE.BTYPE == 0b11.
0b1	When the PE is executing at EL2, PACIASP and PACIBSP are not compatible with PSTATE.BTYPE == 0b11.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

BT0, bit [35]

When ARMv8.5-BTI is implemented:

PAC Branch Type compatibility at EL0.

BT0	Meaning
0b0	When the PE is executing at EL0, PACIASP and PACIBSP are compatible with PSTATE.BTYPE == 0b11.
0b1	When the PE is executing at EL0, PACIASP and PACIBSP are not compatible with PSTATE.BTYPE == 0b11.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [34:32]

Reserved, RES0.

EnIA, bit [31]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APIAKey_EL1 key) of instruction addresses in the EL2&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnIA	Meaning
0b0	Pointer authentication (using the APIAKey_EL1 key) of instruction addresses is not enabled.
0b1	Pointer authentication (using the APIAKey_EL1 key) of instruction addresses is enabled.

Note

This field controls the behavior of the AddPACIA and AuthIA pseudocode functions. Specifically, when the field is 1, AddPACIA returns a copy of a pointer to which a pointer authentication code has been added, and AuthIA returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EnIB, bit [30]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APIBKey_EL1 key) of instruction addresses in the EL2&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnIB	Meaning
0b0	Pointer authentication (using the APIBKey_EL1 key) of instruction addresses is not enabled.
0b1	Pointer authentication (using the APIBKey_EL1 key) of instruction addresses is enabled.

Note

This field controls the behavior of the AddPACIB and AuthIB pseudocode functions. Specifically, when the field is 1, AddPACIB returns a copy of a pointer to which a pointer authentication code has been added, and AuthIB returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

LSMAOE, bit [29]

When ARMv8.2-LSMAOC is implemented:

Load Multiple and Store Multiple Atomicity and Ordering Enable.

LSMAOE	Meaning
0b0	For all memory accesses at EL0, A32 and T32 Load Multiple and Store Multiple can have an interrupt taken during the sequence memory accesses, and the memory accesses are not required to be ordered.
0b1	The ordering and interrupt behavior of A32 and T32 Load Multiple and Store Multiple at EL0 is as defined for Armv8.0.

This bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

nTLSMD, bit [28]

When ARMv8.2-LSMAOC is implemented:

No Trap Load Multiple and Store Multiple to Device-nGRE/Device-nGnRE/Device-nGnRnE memory.

nTLSMD	Meaning
0b0	All memory accesses by A32 and T32 Load Multiple and Store Multiple at EL0 that are marked at stage 1 as Device-nGRE/Device-nGnRE/Device-nGnRnE memory are trapped and generate a stage 1 Alignment fault.
0b1	All memory accesses by A32 and T32 Load Multiple and Store Multiple at EL0 that are marked at stage 1 as Device-nGRE/Device-nGnRE/Device-nGnRnE memory are not trapped.

This bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

EnDA, bit [27]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APDAKey_EL1 key) of instruction addresses in the EL2&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnDA	Meaning
0b0	Pointer authentication (using the APDAKey_EL1 key) of data addresses is not enabled.
0b1	Pointer authentication (using the APDAKey_EL1 key) of data addresses is enabled.

Note

This field controls the behavior of the AddPACDA and AuthDA pseudocode functions. Specifically, when the field is 1, AddPACDA returns a copy of a pointer to which a pointer authentication code has been added, and AuthDA returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

UCI, bit [26]

Traps EL0 execution of cache maintenance instructions to EL2, from AArch64 state only. This applies to DC CVAU, DC CIVAC, DC CVAC, DC CVAP, and IC IVAU.

If ARMv8.2-DCCVADP is implemented, this trap also applies to DC CVADP.

If ARMv8.5-MemTag is implemented, this trap also applies to DC CIGVAC, DC CIGDVAC, DC CGVAC, DC CGDVAC, DC CGVAP, and DC CGDVAP.

If ARMv8.2-DCCVADP and ARMv8.5-MemTag are implemented, this trap also applies to DC CGVADP and DC CGDVADP.

UCI	Meaning
0b0	Any attempt to execute an instruction that this trap applies to at EL0 using AArch64 is trapped to EL2.
0b1	This control does not cause any instructions to be trapped.

If the Point of Coherency is before any level of data cache, it is IMPLEMENTATION DEFINED whether the execution of any data or unified cache clean, or clean and invalidate instruction that operates by VA to the point of coherency can be trapped when the value of this control is 1.

If the Point of Unification is before any level of data cache, it is IMPLEMENTATION DEFINED whether the execution of any data or unified cache clean by VA to the Point of Unification instruction can be trapped when the value of this control is 1.

If the Point of Unification is before any level of instruction cache, it is IMPLEMENTATION DEFINED whether the execution of any instruction cache invalidate by VA to the Point of Unification instruction can be trapped when the value of this control is 1.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

EE, bit [25]

Endianness of data accesses at EL2, stage 1 translation table walks in the EL2 or EL2&0 translation regime, and stage 2 translation table walks in the EL2&0 translation regime.

The possible values of this bit are:

EE	Meaning
0b0	Explicit data accesses at EL2, stage 1 translation table walks in the EL2 or EL2&0 translation regime, and stage 2 translation table walks in the EL2&0 translation regime are little-endian.
0b1	Explicit data accesses at EL2, stage 1 translation table walks in the EL2 or EL2&0 translation regime, and stage 2 translation table walks in the EL2&0 translation regime are big-endian.

If an implementation does not provide Big-endian support at Exception Levels higher than EL0, this bit is RES0.

If an implementation does not provide Little-endian support at Exception Levels higher than EL0, this bit is RES1.

The EE bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2, this field resets to an IMPLEMENTATION DEFINED value.

E0E, bit [24]

Endianness of data accesses at EL0.

E0E	Meaning
0b0	Explicit data accesses at EL0 are little-endian.
0b1	Explicit data accesses at EL0 are big-endian.

If an implementation only supports Little-endian accesses at EL0 then this bit is RES0. This option is not permitted when SCTLR_EL1.EE is RES1.

If an implementation only supports Big-endian accesses at EL0 then this bit is RES1. This option is not permitted when SCTLR_EL1.EE is RES0.

This bit has no effect on the endianness of LDTR, LDTRH, LDTRSH, LDTRSW, STTR, and STTRH instructions executed at EL1.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

SPAN, bit [23]

Set Privileged Access Never, on taking an exception to EL2.

SPAN	Meaning
0b0	PSTATE.PAN is set to 1 on taking an exception to EL2.
0b1	The value of PSTATE.PAN is left unchanged on taking an exception to EL2.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

EIS, bit [22]

When ARMv8.5-CSEH is implemented:

Exception Entry is a context synchronization event.

EIS	Meaning
0b0	The taking of an exception to EL2 is not a context synchronization event.
0b1	The taking of an exception to EL2 is a context synchronization event.

If SCTLR_EL2.EIS is set to 0b0:

- Indirect writes to ESR_EL2, FAR_EL2, SPSR_EL2, ELR_EL2, HPFAR_EL2 are synchronized on exception entry to EL2, so that a direct read of the register after exception entry sees the indirectly written value caused by the exception entry.
- Memory transactions, including instruction fetches, from an Exception level always use the translation resources associated with that translation regime.
- Exception Catch debug events are synchronous debug events.
- DCPS* and DRPS instructions are context synchronization events.

The following are not affected by the value of SCTLR_EL2.EIS:

- Changes to the PSTATE information on entry to EL2.
- Behavior of accessing the banked copies of the stack pointer using the SP register name for loads, stores and data processing instructions.
- Exit from Debug state.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

IESB, bit [21]

When ARMv8.2-IESB is implemented:

Implicit Error Synchronization event Enable.

IESB	Meaning
0b0	Disabled.
0b1	An implicit error synchronization event is added: • After each exception taken to EL2. • Before the operational pseudocode of each ERET instruction executed at EL2.

When the PE is in Debug state, the effect of this field is CONSTRAINED UNPREDICTABLE, and its Effective value might be 0 or 1 regardless of the value of the field. If the Effective value of the field is 1, then an implicit error synchronization event is added after each DCPSx instruction taken to EL2 and before each DRPS instruction executed at EL2, in addition to the other cases where it is added.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TSCXT, bit [20]

When ARMv8.0-CSV2 is implemented:

Trap EL0 Access to the SCXTNUM_EL0 register, when EL0 is using AArch64.

TSCXT	Meaning
0b0	EL0 access to SCXTNUM_EL0 is not disabled by this mechanism.
0b1	EL0 access to SCXTNUM_EL0 is disabled, causing an exception to EL2, and the SCXTNUM_EL0 value is treated at 0.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

WXN, bit [19]

Write permission implies XN (Execute-never). For the EL2 or EL2&0 translation regime, this bit can force all memory regions that are writable to be treated as XN. The possible values of this bit are:

WXN	Meaning
0b0	This control has no effect on memory access permissions.
0b1	Any region that is writable in the EL2 or EL2&0 translation regime is forced to XN for accesses from software executing at EL2.

This bit applies only when SCTLR_EL2.M bit is set.

The WXN bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

nTWE, bit [18]

Traps EL0 execution of WFE instructions to EL2, from both Execution states.

nTWE	Meaning
0b0	Any attempt to execute a WFE instruction at EL0 is trapped to EL2, if the instruction would otherwise have caused the PE to enter a low-power state.
0b1	This control does not cause any instructions to be trapped.

In AArch32 state, the attempted execution of a conditional WFE instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE or WFI can complete at any time, even without a Wakeup event, the traps on WFE of WFI are not guaranteed to be taken, even if the WFE or WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Bit [17]

Reserved, RES0.

nTWI, bit [16]

Traps EL0 execution of WFI instructions to EL2, from both Execution states.

nTWI	Meaning
0b0	Any attempt to execute a WFI instruction at EL0 is trapped EL2, if the instruction would otherwise have caused the PE to enter a low-power state.
0b1	This control does not cause any instructions to be trapped.

In AArch32 state, the attempted execution of a conditional WFI instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE or WFI can complete at any time, even without a Wakeup event, the traps on WFE of WFI are not guaranteed to be taken, even if the WFE or WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

UCT, bit [15]

Traps EL0 accesses to the CTR_EL0 to EL2, from AArch64 state only.

UCT	Meaning
0b0	Accesses to the CTR_EL0 from EL0 using AArch64 are trapped to EL2.
0b1	This control does not cause any instructions to be trapped.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

DZE, bit [14]

Traps EL0 execution of DC ZVA instructions to EL2, from AArch64 state only.

If ARMv8.5-MemTag is implemented, this trap also applies to DC GVA and DC GZVA.

DZE	Meaning
0b0	Any attempt to execute an instruction that this trap applies to at EL0 using AArch64 is trapped to EL2. Reading DCZID_EL0.DZP from EL0 returns 1, indicating that the instructions that this trap applies to are not supported.
0b1	This control does not cause any instructions to be trapped.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

EnDB, bit [13]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APDBKey_EL1 key) of instruction addresses in the EL2&0 translation regime.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

EnDB	Meaning
0b0	Pointer authentication (using the APDBKey_EL1 key) of data addresses is not enabled.
0b1	Pointer authentication (using the APDBKey_EL1 key) of data addresses is enabled.

Note

This field controls the behavior of the AddPACDB and AuthDB pseudocode functions. Specifically, when the field is 1, AddPACDB returns a copy of a pointer to which a pointer authentication code has been added, and AuthDB returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

I, bit [12]

Instruction access Cacheability control, for accesses at EL2 and EL0:

I	Meaning
0b0	All instruction access to Normal memory from EL2 and EL0 are Non-cacheable for all levels of instruction and unified cache. If the value of SCTLR_EL2.M is 0, instruction accesses from stage 1 of the EL2&0 translation regime are to Normal, Outer Shareable, Inner Non-cacheable, Outer Non-cacheable memory.
0b1	This control has no effect on the Cacheability of instruction access to Normal memory from EL2 and EL0. If the value of SCTLR_EL2.M is 0, instruction accesses from stage 1 of the EL2&0 translation regime are to Normal, Outer Shareable, Inner Write-Through, Outer Write-Through memory.

This bit has no effect on the EL3 translation regimes.

In a system where the PE resets into EL2, this field resets to 0.

EOS, bit [11]

When ARMv8.5-CSEH is implemented:

Exception exit is a context synchronization event.

EOS	Meaning
0b0	An exception return from EL2 is not a context synchronization event.
0b1	An exception return from EL2 is a context synchronization event.

If SCTLR_EL2.EOS is set to 0b0:

- Memory transactions, including instruction fetches, from an Exception level always use the translation resources associated with that translation regime.
- Exception Catch debug events are synchronous debug events.
- DCPS* and DRPS instructions are context synchronization events.

The following are not affected by the value of SCTLR_EL2.EOS:

- The indirect write of the PSTATE and PC values from SPSR_EL2 and ELR_EL2 on exception return is synchronized.
- Behavior of accessing the banked copies of the stack pointer using the SP register name for loads, stores and data processing instructions.
- Exit from Debug state.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

EnRCTX, bit [10]

When ARMv8.0-PredInv is implemented:

Enable EL0 Access to the followingAArch32 ~~CFPRCTX, DVPRCTX and CPPRCTX~~ instructions~~:, and the AArch64 CFP RCTX, DVP RCT and CPP RCTX System instructions.~~

- AArch32 CFPRCTX, DVPRCTX and CPPRCTX instructions.
- AArch64 CFP RCTX, DVP RCT and CPP RCTX instructions.

The defined values are:

EnRCTX	Meaning
0b0	EL0 access to these instructions is disabled, and these instructions are trapped to EL1.
0b1	EL0 access to these instructions is enabled.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [9]

Reserved, RES0.

SED, bit [8]

When AArch32 is supported at any Exception level and EL0 is capable of using AArch32:

SETEND instruction disable. Disables SETEND instructions at EL0 using AArch32.

SED	Meaning
0b0	SETEND instruction execution is enabled at EL0 using AArch32.
0b1	SETEND instructions are UNDEFINED at EL0 using AArch32.

If the implementation does not support mixed-endian operation at any Exception level, this bit is RES1.

~~If EL0 cannot use AArch32, this bit is RES1.~~

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

~~**ITD, bit [7]**~~

Otherwise:

Reserved, RES1.

ITD, bit [7]

When AArch32 is supported at any Exception level and EL0 is capable of using AArch32:

IT Disable. Disables some uses of IT instructions at EL0 using AArch32.

ITD	Meaning
0b0	All IT instruction functionality is enabled at EL0 using AArch32.
0b1	Any attempt at EL0 using AArch32 to execute any of the following is UNDEFINED: • All encodings of the IT instruction with hw1[3:0]!=1000. • All encodings of the subsequent instruction with the following values for hw1: ◦ 0b11xxxxxxxxxxxxxx: All 32-bit instructions, and the 16-bit instructions B, UDF, SVC, LDM, and STM. ◦ 0b1011xxxxxxxxxxxx: All instructions in 'Miscellaneous 16-bit instructions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section F3.2.5. ◦ 0b10100xxxxxxxxxxx: ADD Rd, PC, #imm ◦ 0b01001xxxxxxxxxxx: LDR Rd, [PC, #imm] ◦ 0b0100x1xxx1111xxx: ADD Rdn, PC; CMP Rn, PC; MOV Rd, PC; BX PC; BLX PC. ◦ 0b010001xx1xxxx111: ADD PC, Rm; CMP PC, Rm; MOV PC, Rm. This pattern also covers UNPREDICTABLE cases with BLX Rn. These instructions are always UNDEFINED, regardless of whether they would pass or fail the condition code check that applies to them as a result of being in an IT block. It is IMPLEMENTATION DEFINED whether the IT instruction is treated as: • A 16-bit instruction, that can only be followed by another 16-bit instruction. • The first half of a 32-bit instruction. This means that, for the situations that are UNDEFINED, either the second 16-bit instruction or the 32-bit instruction is UNDEFINED. An implementation might vary dynamically as to whether IT is treated as a 16-bit instruction or the first half of a 32-bit instruction.

If an instruction in an active IT block that would be disabled by this field sets this field to 1 then behavior is CONSTRAINED UNPREDICTABLE. For more information see 'Changes to an ITD control by an instruction in an IT block' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section E1.2.4

~~If EL0 cannot use AArch32, this bit is RES1.~~

ITD is optional, but if it is implemented in the SCTLR then it must also be implemented in the SCTLR_EL1. If it is not implemented then this bit is RAZ/WI.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

nAA, bit [6]

When ARMv8.4-LSE is implemented:

Non-aligned access. This bit controls generation of Alignment faults at EL2 and EL0 under certain conditions.

nAA	Meaning
0b0	LDAPR, LDAPRH, LDAPUR, LDAPURH, LDAPURSH, LDAPURSW, LDAR, LDARH, LDLAR, LDLARH, STLLR, STLLRH, STLR, STLRH, STLUR, and STLURH generate an Alignment fault if all bytes being accessed are not within a single 16-byte quantity, aligned to 16 bytes for accesses.
0b1	This control bit does not cause LDAPR, LDAPRH, LDAPUR, LDAPURH, LDAPURSH, LDAPURSW, LDAR, LDARH, LDLAR, LDLARH, STLLR, STLLRH, STLR, STLRH, STLUR, or STLURH to generate an Alignment fault if all bytes being accessed are not within a single 16-byte quantity, aligned to 16 bytes.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

CP15BEN, bit [5]

When AArch32 is supported at any Exception level and EL0 is capable of using AArch32:

System instruction memory barrier enable. Enables accesses to the DMB, DSB, and ISB System instructions in the (coproc==0b1111) encoding space from EL0:

CP15BEN	Meaning
0b0	EL0 using AArch32: EL0 execution of the CP15DMB, CP15DSB, and CP15ISB instructions is UNDEFINED.
0b1	EL0 using AArch32: EL0 execution of the CP15DMB, CP15DSB, and CP15ISB instructions is enabled.

~~If EL0 cannot use AArch32, this bit is RES0.~~

CP15BEN is optional, but if it is implemented in the SCTLR then it must also be implemented in the SCTLR_EL1. If it is not implemented then this bit is RAO/WI.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SA0, bit [4]

SP Alignment check enable for EL0. When set to 1, if a load or store instruction executed at EL0 uses the SP as the base address and the SP is not aligned to a 16-byte boundary, then a SP alignment fault exception is generated. For more information, see 'SP alignment checking' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1 (The AArch64 System Level Programmers' Model).

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

SA, bit [3]

SP Alignment check enable. When set to 1, if a load or store instruction executed at EL2 uses the SP as the base address and the SP is not aligned to a 16-byte boundary, then a SP alignment fault exception is generated. For more information, see 'SP alignment checking' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1 (The AArch64 System Level Programmers' Model).

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

C, bit [2]

Cacheability control, for data accesses.

C	Meaning
0b0	All data access to Normal memory from EL2 and EL0, and all Normal memory accesses to the EL2&0 translation tables, are Non-cacheable for all levels of data and unified cache.
0b1	This control has no effect on the Cacheability of: • Data access to Normal memory from EL2 and EL0. • Normal memory accesses to the EL2&0 translation tables.

This bit has no effect on the EL3 translation regimes.

In a system where the PE resets into EL2, this field resets to 0.

A, bit [1]

Alignment check enable. This is the enable bit for Alignment fault checking at EL2 and EL0.

A	Meaning
0b0	Alignment fault checking disabled when executing at EL2 and EL0. Instructions that load or store one or more registers, other than load/store exclusive and load-acquire/store-release, do not check that the address being accessed is aligned to the size of the data element(s) being accessed.
0b1	Alignment fault checking enabled when executing at EL2 and EL0. All instructions that load or store one or more registers have an alignment check that the address being accessed is aligned to the size of the data element(s) being accessed. If this check fails it causes an Alignment fault, which is taken as a Data Abort exception.

Load/store exclusive and load-acquire/store-release instructions have an alignment check regardless of the value of the A bit.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

M, bit [0]

MMU enable for EL2&0 stage 1 address translation. Possible values of this bit are:

M	Meaning
0b0	EL2&0 stage 1 address translation disabled. See the SCTLR_EL2.I field for the behavior of instruction accesses to Normal memory.
0b1	EL2&0 stage 1 address translation enabled.

In a system where the PE resets into EL2, this field resets to 0.

Accessing the SCTLR_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic SCTLR_EL2 or SCTLR_EL1 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, SCTLR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return SCTLR_EL2;
elsif PSTATE.EL == EL3 then
    return SCTLR_EL2;
```

```
MSR SCTLR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    SCTLR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    SCTLR_EL2 = X[t];
```

MRS <Xt>, SCTLR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.SCTLR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x110];
    else
        return SCTLR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return SCTLR_EL2;
    else
        return SCTLR_EL1;
elsif PSTATE.EL == EL3 then
    return SCTLR_EL1;
```

MSR SCTLR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.SCTLR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x110] = X[t];
    else
        SCTLR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        SCTLR_EL2 = X[t];
    else
        SCTLR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    SCTLR_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SCTLR_EL3, System Control Register (EL3)

The SCTLR_EL3 characteristics are:

Purpose

Provides top level control of the system, including its memory system, at EL3.

Configuration

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL3 using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to SCTLR_EL3 are UNDEFINED.

Attributes

SCTLR_EL3 is a 64-bit register.

Field descriptions

The SCTLR_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37
RES0																			DSSBS	ATA	RES0	TCF		RES0		ITFS
EnIA	EnIB	RES1		EnDA	RES0	EE	RES0	RES1	EIS	IESB	RES0	WXN	RES1	RES0	RES1	RES0		EnDB	I	EOS	RES0				nAA	R
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5

Bits [63:45]

Reserved, RES0.

DSSBS, bit [44]

When ARMv8.0-SSBS is implemented:

Default PSTATE.SSBS value on Exception Entry.

DSSBS	Meaning
0b0	PSTATE.SSBS is set to 0 on an exception to EL3.
0b1	PSTATE.SSBS is set to 1 on an exception to EL3.

In a system where the PE resets into EL3, this field resets to an IMPLEMENTATION DEFINED value.

Otherwise:

Reserved, RES0.

ATA, bit [43]

When ARMv8.5-MemTag is implemented:

Allocation Tag Access in EL3. Controls EL3 access to Allocation Tags.

When access to Allocation Tags is prevented:

- Instructions which Load or Store data are Unchecked.
- Instructions which Load or Store Allocation Tags treat the Allocation Tag as RAZ/WI.
- Instructions which insert Logical Address Tags into addresses treat the Allocation Tag used to generate the Logical Address Tag as 0.
- Cache maintenance instructions which invalidate Allocation Tags from caches behave as the equivalent Clean and Invalidate operation on Allocation Tags.

ATA	Meaning
0b0	Access to Allocation Tags is prevented.
0b1	Access to Allocation Tags is not prevented.

This bit is permitted to be cached in a TLB.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [42]

Reserved, RES0.

TCF, bits [41:40]

When ARMv8.5-MemTag is implemented:

Tag Check Fault~~Fail~~ in EL3. Controls the effect of Tag~~tag~~ Check~~check~~ Faults~~fails~~ due to Loads and Stores in EL3.

TCF	Meaning
0b00	Tag Check~~check~~ Faults~~fails~~ have no effect on the PE.
0b01	Tag Check~~check~~ Faults~~fails~~ causes a synchronous exception.
0b10	Tag Check~~check~~ Faults~~fails~~ are asynchronously accumulated.

The value 0b11 is reserved.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [39:38]

Reserved, RES0.

ITFSB, bit [37]

When ARMv8.5-MemTag is implemented:

When asynchronous exceptions are being generated by Tag Check Faults~~fails~~ which are generated for Loads and Stores at any exception level, controls the auto-synchronisaton of Tag Check Faults~~fails~~ into TFSRE0_EL1 and TFSR_ELx.

ITFSB	Meaning
0b0	Tag Check~~check~~ Faults~~fails~~ are not synchronized on entry to EL3.
0b1	Tag Check~~check~~ Faults~~fails~~ are synchronized on entry to EL3.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

BT, bit [36]

When ARMv8.5-BTI is implemented:

PAC Branch Type compatibility at EL3.

BT	Meaning
0b0	When the PE is executing at EL3, PACIASP and PACIBSP are compatible with PSTATE.BTYPE == 0b11.
0b1	When the PE is executing at EL3, PACIASP and PACIBSP are not compatible with PSTATE.BTYPE == 0b11.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [35:32]

Reserved, RES0.

EnIA, bit [31]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APIAKey_EL1 key) of instruction addresses in the EL3 translation regime.

Possible values of this bit are:

EnIA	Meaning
0b0	Pointer authentication (using the APIAKey_EL1 key) of instruction addresses is not enabled.
0b1	Pointer authentication (using the APIAKey_EL1 key) of instruction addresses is enabled.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

This field controls the behavior of the AddPACIA and AuthIA pseudocode functions. Specifically, when the field is 1, AddPACIA returns a copy of a pointer to which a pointer authentication code has been added, and AuthIA returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

EnIB, bit [30]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APIBKey_EL1 key) of instruction addresses in the EL3 translation regime.

Possible values of this bit are:

EnIB	Meaning
0b0	Pointer authentication (using the APIBKey_EL1 key) of instruction addresses is not enabled.
0b1	Pointer authentication (using the APIBKey_EL1 key) of instruction addresses is enabled.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

This field controls the behavior of the AddPACIB and AuthIB pseudocode functions. Specifically, when the field is 1, AddPACIB returns a copy of a pointer to which a pointer authentication code has been added, and AuthIB returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [29:28]

Reserved, RES1.

EnDA, bit [27]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APDAKey_EL1 key) of instruction addresses in the EL3 translation regime.

EnDA	Meaning
0b0	Pointer authentication (using the APDAKey_EL1 key) of data addresses is not enabled.
0b1	Pointer authentication (using the APDAKey_EL1 key) of data addresses is enabled.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

This field controls the behavior of the AddPACDA and AuthDA pseudocode functions. Specifically, when the field is 1, AddPACDA returns a copy of a pointer to which a pointer authentication code has been added, and AuthDA returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [26]

Reserved, RES0.

EE, bit [25]

Endianness of data accesses at EL3, and stage 1 translation table walks in the EL3 translation regime.

EE	Meaning
0b0	Explicit data accesses at EL3, and stage 1 translation table walks in the EL3 translation regime are little-endian.
0b1	Explicit data accesses at EL3, and stage 1 translation table walks in the EL3 translation regime are big-endian.

If an implementation does not provide Big-endian support at Exception Levels higher than EL0, this bit is RES0.

If an implementation does not provide Little-endian support at Exception Levels higher than EL0, this bit is RES1.

The EE bit is permitted to be cached in a TLB.

In a system where the PE resets into EL3, this field resets to an IMPLEMENTATION DEFINED value.

Bit [24]

Reserved, RES0.

Bit [23]

Reserved, RES1.

EIS, bit [22]

When ARMv8.5-CSEH is implemented:

Exception Entry is Context Synchronizing.

EIS	Meaning
0b0	The taking of an exception to EL3 is not a context synchronizing event.
0b1	The taking of an exception to EL3 is a context synchronizing event.

If SCTLR_EL3.EIS is set to 0b0:

- Indirect writes to ESR_EL3, FAR_EL3, SPSR_EL3, ELR_EL3 are synchronized on exception entry to EL3, so that a direct read of the register after exception entry sees the indirectly written value caused by the exception entry.
- Memory transactions, including instruction fetches, from an Exception level always use the translation resources associated with that translation regime.
- Exception Catch debug events are synchronous debug events.
- DCPS* and DRPS instructions are context synchronization events.

The following are not affected by the value of SCTLR_EL3.EIS:

- Changes to the PSTATE information on entry to EL3.
- Behavior of accessing the banked copies of the stack pointer using the SP register name for loads, stores and data processing instructions.
- Debug state exit.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

IESB, bit [21]

When ARMv8.2-IESB is implemented:

Implicit Error Synchronization event enable.

IESB	Meaning
0b0	Disabled.
0b1	An implicit error synchronization event is added: • At each exception taken to EL3. • Before the operational pseudocode of each ERET instruction executed at EL3.

When the PE is in Debug state, the effect of this field is CONSTRAINED UNPREDICTABLE, and its Effective value might be 0 or 1 regardless of the value of the field. If the Effective value of the field is 1, then an implicit error synchronization event is added after each DCPSX instruction taken to EL3 and before each DRPS instruction executed at EL3, in addition to the other cases where it is added.

When ARMv8.4-DFE is implemented, and the Effective value of SCR_EL3.NMEA is 1, this field is ignored and its Effective value is 1.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [20]

Reserved, RES0.

WXN, bit [19]

Write permission implies XN (Execute-never). For the EL3 translation regime, this bit can force all memory regions that are writable to be treated as XN. The possible values of this bit are:

WXN	Meaning
0b0	This control has no effect on memory access permissions.
0b1	Any region that is writable in the EL3 translation regime is forced to XN for accesses from software executing at EL3.

This bit applies only when SCTLR_EL3.M bit is set.

The WXN bit is permitted to be cached in a TLB.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Bit [18]

Reserved, RES1.

Bit [17]

Reserved, RES0.

Bit [16]

Reserved, RES1.

Bits [15:14]

Reserved, RES0.

EnDB, bit [13]

When ARMv8.3-PAuth is implemented:

Controls enabling of pointer authentication (using the APDBKey_EL1 key) of instruction addresses in the EL3 translation regime.

EnDB	Meaning
0b0	Pointer authentication (using the APDBKey_EL1 key) of data addresses is not enabled.
0b1	Pointer authentication (using the APDBKey_EL1 key) of data addresses is enabled.

For more information, see 'System register control of pointer authentication' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

This field controls the behavior of the AddPACDB and AuthDB pseudocode functions. Specifically, when the field is 1, AddPACDB returns a copy of a pointer to which a pointer authentication code has been added, and AuthDB returns an authenticated copy of a pointer. When the field is 0, both of these functions are NOP.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

I, bit [12]

Instruction access Cacheability control, for accesses at EL3:

I	Meaning
0b0	All instruction access to Normal memory from EL3 are Non-cacheable for all levels of instruction and unified cache. If the value of SCTLR_EL3.M is 0, instruction accesses from stage 1 of the EL3 translation regime are to Normal, Outer Shareable, Inner Non-cacheable, Outer Non-cacheable memory.
0b1	This control has no effect on the Cacheability of instruction access to Normal memory from EL3. If the value of SCTLR_EL3.M is 0, instruction accesses from stage 1 of the EL3 translation regime are to Normal, Outer Shareable, Inner Write-Through, Outer Write-Through memory.

This bit has no effect on the EL1&0, EL2, or EL2&0 translation regimes.

In a system where the PE resets into EL3, this field resets to 0.

EOS, bit [11]

When ARMv8.5-CSEH is implemented:

Exception Exit is Context Synchronizing.

EOS	Meaning
0b0	An exception return from EL3 is not a context synchronizing event
0b1	An exception return from EL3 is a context synchronizing event

If SCTLR_EL3.EOS is set to 0b0:

- Memory transactions, including instruction fetches, from an Exception level always use the translation resources associated with that translation regime.
- Exception Catch debug events are synchronous debug events.
- DCPS* and DRPS instructions are context synchronization events.

The following are not affected by the value of SCTLR_EL3.EOS:

- The indirect write of the PSTATE and PC values from SPSR_EL3 and ELR_EL3 on exception return is synchronized.
- If the PE enters Debug state before the first instruction after an Exception return from EL3 to Non-secure state, any pending Halting debug event completes execution.
- The GIC behavior that allocates interrupts to FIQ or IRQ changes simultaneously with leaving the EL3 Exception level.
- Behavior of accessing the banked copies of the stack pointer using the SP register name for loads, stores and data processing instructions.
- Exit from Debug state.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

Bits [10:7]

Reserved, RES0.

nAA, bit [6]

When ARMv8.4-LSE is implemented:

Non-aligned access. This bit controls generation of Alignment faults at EL3 under certain conditions.

nAA	Meaning
0b0	LDAPR, LDAPRH, LDAPUR, LDAPURH, LDAPURSH, LDAPURSW, LDAR, LDARH, LDLAR, LDLARH, STLLR, STLLRH, STLR, STLRH, STLUR, and STLURH generate an Alignment fault if all bytes being accessed are not within a single 16-byte quantity, aligned to 16 bytes for accesses.
0b1	This control bit does not cause LDAPR, LDAPRH, LDAPUR, LDAPURH, LDAPURSH, LDAPURSW, LDAR, LDARH, LDLAR, LDLARH, STLLR, STLLRH, STLR, STLRH, STLUR, or STLURH to generate an Alignment fault if all bytes being accessed are not within a single 16-byte quantity, aligned to 16 bytes.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [5:4]

Reserved, RES1.

SA, bit [3]

SP Alignment check enable. When set to 1, if a load or store instruction executed at EL3 uses the SP as the base address and the SP is not aligned to a 16-byte boundary, then a SP alignment fault exception is generated. For more information, see 'SP alignment checking' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D1 (The AArch64 System Level Programmers' Model).

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

C, bit [2]

Cacheability control, for data accesses.

C	Meaning
0b0	All data access to Normal memory from EL3, and all Normal memory accesses to the EL3 translation tables, are Non-cacheable for all levels of data and unified cache.
0b1	This control has no effect on the Cacheability of: • Data access to Normal memory from EL3. • Normal memory accesses to the EL3 translation tables.

This bit has no effect on the EL1&0, EL2, or EL2&0 translation regimes.

In a system where the PE resets into EL3, this field resets to 0.

A, bit [1]

Alignment check enable. This is the enable bit for Alignment fault checking at EL3.

A	Meaning
0b0	Alignment fault checking disabled when executing at EL3. Instructions that load or store one or more registers, other than load/store exclusive and load-acquire/store-release, do not check that the address being accessed is aligned to the size of the data element(s) being accessed.
0b1	Alignment fault checking enabled when executing at EL3. All instructions that load or store one or more registers have an alignment check that the address being accessed is aligned to the size of the data element(s) being accessed. If this check fails it causes an Alignment fault, which is taken as a Data Abort exception.

Load/store exclusive and load-acquire/store-release instructions have an alignment check regardless of the value of the A bit.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

M, bit [0]

MMU enable for EL3 stage 1 address translation. Possible values of this bit are:

M	Meaning
0b0	EL3 stage 1 address translation disabled. See the SCTLR_EL3.I field for the behavior of instruction accesses to Normal memory.
0b1	EL3 stage 1 address translation enabled.

In a system where the PE resets into EL3, this field resets to 0.

Accessing the SCTLR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, SCTLR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return SCTLR_EL3;
```

MSR SCTLR_EL3, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    SCTLR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SCXTNUM_EL1, EL1 Read/Write Software Context Number

The SCXTNUM_EL1 characteristics are:

Purpose

Provides a number that can be used to separate out different context numbers with the EL1 exception level, for the purpose of protecting against side-channels using branch prediction and similar resources.

Configuration

This register is present only when ARMv8.0-CSV2 is implemented. Otherwise, direct accesses to SCXTNUM_EL1 are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SCXTNUM_EL1 is a 64-bit register.

Field descriptions

The SCXTNUM_EL1 bit assignments are:



Bits [63:0]

Software Context Number. A number to identify the context within the EL1 exception level.

This field resets to an architecturally UNKNOWN value.

Accessing the SCXTNUM_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, SCXTNUM_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b1101	0b0000	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.EnSCXT == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.SCXTNUM_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.EnSCXT == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x188];
    else
        return SCXTNUM_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.EnSCXT == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        return SCXTNUM_EL2;
    else
        return SCXTNUM_EL1;
elsif PSTATE.EL == EL3 then
    return SCXTNUM_EL1;
```

MSR SCXTNUM_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b1101	0b0000	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.EnSCXT == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.SCXTNUM_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.EnSCXT == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x188] = X[t];
    else
        SCXTNUM_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.EnSCXT == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        SCXTNUM_EL2 = X[t];
    else
        SCXTNUM_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    SCXTNUM_EL1 = X[t];
```

MRS <Xt>, SCXTNUM_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b1101	0b0000	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x188];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.EnSCXT == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            return SCXTNUM_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return SCXTNUM_EL1;
    else
        UNDEFINED;
```

MSR SCXTNUM_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b1101	0b0000	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x188] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.EnSCXT == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            SCXTNUM_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        SCXTNUM_EL1 = X[t];
    else
        UNDEFINED;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SCXTNUM_EL3, EL3 Read/Write Software Context Number

The SCXTNUM_EL3 characteristics are:

Purpose

Provides a number that can be used to separate out different context numbers with the EL3 exception level, for the purpose of protecting against side-channels using branch prediction and similar resources.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented~~)~~ and ARMv8.0-CSV2 is implemented. Otherwise, direct accesses to SCXTNUM_EL3 are UNDEFINED.

Attributes

SCXTNUM_EL3 is a 64-bit register.

Field descriptions

The SCXTNUM_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Software Context Number																															
Software Context Number																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Software Context Number. A number to identify the context within the EL3 exception level.

This field resets to an architecturally UNKNOWN value.

Accessing the SCXTNUM_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, SCXTNUM_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1101	0b0000	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return SCXTNUM_EL3;
```

```
MSR SCXTNUM_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1101	0b0000	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    SCXTNUM_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SDER32_EL3, AArch32 Secure Debug Enable Register

The SDER32_EL3 characteristics are:

Purpose

Allows access to the AArch32 register SDER from AArch64 state only. Its value has no effect on execution in AArch64 state.

Configuration

AArch64 System register SDER32_EL3 bits [31:0] are architecturally mapped to AArch32 System register SDER[31:0] .

This register is present only when ~~HaveEL(~~EL3 is implemented~~)~~ and EL1 supports AArch32. Otherwise, direct accesses to SDER32_EL3 are UNDEFINED.

This register is ignored by the PE when when one or more of the following are true:

- The PE is in Non-secure state.
- EL1 is using AArch64.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SDER32_EL3 is a 64-bit register.

Field descriptions

The SDER32_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																														SUNIDEN	SUIDEN
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:2]

Reserved, RES0.

SUNIDEN, bit [1]

Secure User Non-Invasive Debug Enable.

SUNIDEN	Meaning
0b0	This bit does not affect Performance Monitors event counting at Secure EL0.
0b1	If EL1 is using AArch32, Performance Monitors event counting is allowed in Secure EL0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SUIDEN, bit [0]

Secure User Invasive Debug Enable.

SUIDEN	Meaning
0b0	This bit does not affect the generation of debug exceptions at Secure EL0.
0b1	If EL1 is using AArch32, debug exceptions from Secure EL0 are enabled.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the SDER32_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, SDER32_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return SDER32_EL3;
```

```
MSR SDER32_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0001	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    SDER32_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SP_EL0, Stack Pointer (EL0)

The SP_EL0 characteristics are:

Purpose

Holds the stack pointer associated with EL0. At higher Exception levels, this is used as the current stack pointer when the value of SPSel.SP is 0.

Configuration

There are no configuration notes.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SP_EL0 is a 64-bit register.

Field descriptions

The SP_EL0 bit assignments are:



Bits [63:0]

Stack pointer.

This field resets to an architecturally UNKNOWN value.

Accessing the SP_EL0

When the value of PSTATE.SP is 0, this register is accessible at all Exception levels as the current stack pointer.

Accesses to this register use the following encodings:

```
MRS <Xt>, SP_EL0
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if PSTATE.SP == '0' then
        UNDEFINED;
    else
        return SP_EL0;
elsif PSTATE.EL == EL2 then
    if PSTATE.SP == '0' then
        UNDEFINED;
    else
        return SP_EL0;
elsif PSTATE.EL == EL3 then
    if PSTATE.SP == '0' then
        UNDEFINED;
    else
        return SP_EL0;
```

```
MSR SP_EL0, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if PSTATE.SP == '0' then
        UNDEFINED;
    else
        SP_EL0 = X[t];
elsif PSTATE.EL == EL2 then
    if PSTATE.SP == '0' then
        UNDEFINED;
    else
        SP_EL0 = X[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.SP == '0' then
        UNDEFINED;
    else
        SP_EL0 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SP_EL1, Stack Pointer (EL1)

The SP_EL1 characteristics are:

Purpose

Holds the stack pointer associated with EL1. When executing at EL1, the value of SPSel.SP determines the current stack pointer:

SPSel.SP	Current stack pointer
0b0	SP_EL0
0b1	SP_EL1

Configuration

There are no configuration notes.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SP_EL1 is a 64-bit register.

Field descriptions

The SP_EL1 bit assignments are:



Bits [63:0]

Stack pointer.

This field resets to an architecturally UNKNOWN value.

Accessing the SP_EL1

This accessibility information only applies to accesses using the MRS or MSR instructions.

When the value of SPSel.SP is 1, this register is also accessible at EL1 as the current stack pointer.

Note

When the value of SPSel.SP is 0, SP_EL0 is used as the current stack pointer at all Exception levels.

Accesses to this register use the following encodings:

```
MRS <Xt>, SP_EL1
```

op0	op1	CRn	CRm	op2

0b11	0b100	0b0100	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x240];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return SP_EL1;
elsif PSTATE.EL == EL3 then
    return SP_EL1;
```

MSR SP_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x240] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    SP_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    SP_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SP_EL3, Stack Pointer (EL3)

The SP_EL3 characteristics are:

Purpose

Holds the stack pointer associated with EL3. When executing at EL3, the value of SPSel.SP determines the current stack pointer:

SPSel.SP	Current stack pointer
0b0	SP_EL0
0b1	SP_EL3

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to SP_EL3 are UNDEFINED.

Attributes

SP_EL3 is a 64-bit register.

Field descriptions

The SP_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Stack pointer																															
Stack pointer																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Stack pointer.

This field resets to an architecturally UNKNOWN value.

Accessing the SP_EL3

This register is not accessible using MRS and MSR instructions.

When the value of SPSel.SP is 1, this register is accessible at EL3 as the current stack pointer.

Note

When the value of SPSel.SP is 0, SP_EL0 is used as the current stack pointer at all Exception levels.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSel, Stack Pointer Select

The SPSel characteristics are:

Purpose

Allows the Stack Pointer to be selected between SP_EL0 and SP_ELx.

Configuration

There are no configuration notes.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SPSel is a 64-bit register.

Field descriptions

The SPSel bit assignments are:



Bits [63:1]

Reserved, RES0.

SP, bit [0]

Stack pointer to use. Possible values of this bit are:

SP	Meaning
0b0	Use SP_EL0 at all Exception levels.
0b1	Use SP_ELx for Exception level ELx.

This field resets to 1.

Accessing the SPSel

~~For details on the operation of the MSR (immediate) accessor, see MSR (immediate) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

```
MRS <Xt>, SPSel
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    return Zeros(63):PSTATE.SP;
elsif PSTATE.EL == EL2 then
    return Zeros(63):PSTATE.SP;
elsif PSTATE.EL == EL3 then
    return Zeros(63):PSTATE.SP;
```

MSR SPSel, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    PSTATE.SP = X[t]<0>;
elsif PSTATE.EL == EL2 then
    PSTATE.SP = X[t]<0>;
elsif PSTATE.EL == EL3 then
    PSTATE.SP = X[t]<0>;
```

MSR SPSel, #<imm>

op0	op1	CRn	op2
0b00	0b000	0b0100	0b101

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_abt, Saved Program Status Register (Abort mode)

The SPSR_abt characteristics are:

Purpose

Holds the saved process state when an exception is taken to Abort mode.

Configuration

AArch64 System register SPSR_abt bits [31:0] are architecturally mapped to AArch32 System register SPSR_abt[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

If EL1 only~~does~~ supports~~not~~ ~~support~~ execution in AArch64~~AArch32~~ state, this register is RES0 from EL2 and EL3.

Attributes

SPSR_abt is a 64-bit register.

Field descriptions

The SPSR_abt bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
N	Z	C	V	Q	IT[1:0]		J	SSBS	PAN	DIT	IL	GE				IT[7:2]						E	A	I	F	T	M[4:0]				
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to Abort mode, and copied to PSTATE.N on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to Abort mode, and copied to PSTATE.Z on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to Abort mode, and copied to PSTATE.C on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to Abort mode, and copied to PSTATE.V on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to Abort mode, and copied to PSTATE.Q on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to Abort mode, and copied to PSTATE.IT[1:0] on executing an exception return operation in Abort mode.

On executing an exception return operation in Abort mode SPSR_abt.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. ~~Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.~~

Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to Abort mode, and copied to PSTATE.SSBS on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to Abort mode, and copied to PSTATE.PAN on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to Abort mode, and copied to PSTATE.DIT on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to Abort mode, and copied to PSTATE.IL on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to Abort mode, and copied to PSTATE.GE on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to Abort mode, and copied to PSTATE.IT[7:2] on executing an exception return operation in Abort mode.

SPSR_abt.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to Abort mode, and copied to PSTATE.E on executing an exception return operation in Abort mode.

If the implementation does not support big-endian operation, SPSR_abt.E is RES0. If the implementation does not support little-endian operation, SPSR_abt.E is RES1. On executing an exception return operation in Abort mode, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_abt.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_abt.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to Abort mode, and copied to PSTATE.A on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to Abort mode, and copied to PSTATE.I on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to Abort mode, and copied to PSTATE.F on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to Abort mode, and copied to PSTATE.T on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on taking an exception to Abort mode, and copied to PSTATE.M[4:0] on executing an exception return operation in Abort mode.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10111	Abort.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If SPSR_abt.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in Abort mode is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_abt

Accesses to this register use the following encodings:

```
MRS <Xt>, SPSR_abt
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return SPSR_abt;
elsif PSTATE.EL == EL3 then
    return SPSR_abt;
```

```
MSR SPSR_abt, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    SPSR_abt = X[t];
elsif PSTATE.EL == EL3 then
    SPSR_abt = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_EL1, Saved Program Status Register (EL1)

The SPSR_EL1 characteristics are:

Purpose

Holds the saved process state when an exception is taken to EL1.

Configuration

AArch64 System register SPSR_EL1 bits [31:0] are architecturally mapped to AArch32 System register SPSR_svc[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SPSR_EL1 is a 64-bit register.

Field descriptions

The SPSR_EL1 bit assignments are:

When AArch32 is supported at any Exception level and exception taken from AArch32 state:



An exception return from EL1 using AArch64 makes SPSR_EL1 become UNKNOWN.

Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to EL1, and copied to PSTATE.N on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to EL1, and copied to PSTATE.Z on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to EL1, and copied to PSTATE.C on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to EL1, and copied to PSTATE.V on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to EL1, and copied to PSTATE.Q on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to EL1, and copied to PSTATE.IT[1:0] on executing an exception return operation in EL1.

On executing an exception return operation in EL1 SPSR_EL1.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

DIT, bit [24]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to EL1, and copied to PSTATE.DIT on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to EL1, and copied to PSTATE.SSBS on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to EL1, and copied to PSTATE.PAN on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SS, bit [21]

Software Step. Set to the value of PSTATE.SS on taking an exception to EL1, and conditionally copied to PSTATE.SS on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to EL1, and copied to PSTATE.IL on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to EL1, and copied to PSTATE.GE on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to EL1, and copied to PSTATE.IT[7:2] on executing an exception return operation in EL1.

SPSR_EL1.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to EL1, and copied to PSTATE.E on executing an exception return operation in EL1.

If the implementation does not support big-endian operation, SPSR_EL1.E is RES0. If the implementation does not support little-endian operation, SPSR_EL1.E is RES1. On executing an exception return operation in EL1, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_EL1.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_EL1.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to EL1, and copied to PSTATE.A on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to EL1, and copied to PSTATE.I on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to EL1, and copied to PSTATE.F on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to EL1, and copied to PSTATE.T on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

M[4], bit [4]

Execution state. Set to `0b1`, the value of PSTATE.nRW, on taking an exception to EL1 from AArch32 state, and copied to PSTATE.nRW on executing an exception return operation in EL1.

M[4]	Meaning
`0b1`	AArch32 execution state.

This field resets to an architecturally UNKNOWN value.

M[3:0], bits [3:0]

AArch32 Mode. Set to the value of PSTATE.M[3:0] on taking an exception to EL1, and copied to PSTATE.M[3:0] on executing an exception return operation in EL1.

M[3:0]	Meaning
`0b0000`	User.
`0b0001`	FIQ.
`0b0010`	IRQ.
`0b0011`	Supervisor.
`0b0111`	Abort.
`0b1011`	Undefined.
`0b1111`	System.

Other values are reserved. If SPSR_EL1.M[3:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in EL1 is an illegal return event, as described in 'Illegal return events from AArch64 state' in the Arm®Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

When exception taken from AArch64 state:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
N	Z	C	V	RES0							TCO	DIT	UAO	PAN	SS	IL	RES0				SSBS	BTYPE		D	A	I	F	RES0		M[4]	M[3:0]	
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

An exception return from EL1 using AArch64 makes SPSR_EL1 become UNKNOWN.

Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to EL1, and copied to PSTATE.N on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to EL1, and copied to PSTATE.Z on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to EL1, and copied to PSTATE.C on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to EL1, and copied to PSTATE.V on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Bits [27:26]

Reserved, RES0.

TCO, bit [25]

When ARMv8.5-MemTag is implemented:

Tag Check Override. Set to the value of PSTATE.TCO on taking an exception to EL1, and copied to PSTATE.TCO on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [24]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to EL1, and copied to PSTATE.DIT on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

UAO, bit [23]

When ARMv8.2-UAO is implemented:

User Access Override. Set to the value of PSTATE.UAO on taking an exception to EL1, and copied to PSTATE.UAO on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to EL1, and copied to PSTATE.PAN on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SS, bit [21]

Software Step. Set to the value of PSTATE.SS on taking an exception to EL1, and conditionally copied to PSTATE.SS on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to EL1, and copied to PSTATE.IL on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Bits [19:13]

Reserved, RES0.

SSBS, bit [12]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to EL1, and copied to PSTATE.SSBS on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

BTYPE, bits [11:10]

When ARMv8.5-BTI is implemented:

Branch Type Indicator. Set to the value of PSTATE.BTYPE on taking an exception to EL1, and copied to PSTATE.BTYPE on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

D, bit [9]

Debug exception mask. Set to the value of PSTATE.D on taking an exception to EL1, and copied to PSTATE.D on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to EL1, and copied to PSTATE.A on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to EL1, and copied to PSTATE.I on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to EL1, and copied to PSTATE.F on executing an exception return operation in EL1.

This field resets to an architecturally UNKNOWN value.

Bit [5]

Reserved, RES0.

M[4], bit [4]

When AArch32 is supported at any Exception level:

Execution state. Set to `0b0`, the value of PSTATE.nRW, on taking an exception to EL1 from AArch64 state, and copied to PSTATE.nRW on executing an exception return operation in EL1.

M[4]	Meaning
`0b0`	AArch64 execution state.

~~If AArch32 is not supported at any Exception level, this bit is RES0.~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

M[3:0], bits [3:0]

AArch64 Exception level and selected Stack Pointer.

M[3:0]	Meaning
0b0000	EL0t.
0b0100	EL1t.
0b0101	EL1h.

Other values are reserved. If SPSR_EL1.M[3:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in EL1 is an illegal return event, as described in 'Illegal return events from AArch64 state' in the Arm®Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The bits in this field are interpreted as follows:

- M[3:2] is set to the value of PSTATE.EL on taking an exception to EL1 and copied to PSTATE.EL on executing an exception return operation in EL1.
- M[1] is unused and is 0 for all non-reserved values.
- M[0] is set to the value of PSTATE.SP on taking an exception to EL1 and copied to PSTATE.SP on executing an exception return operation in EL1

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic SPSR_EL1 or SPSR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, SPSR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x160];
    else
        return SPSR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return SPSR_EL2;
    else
        return SPSR_EL1;
elsif PSTATE.EL == EL3 then
    return SPSR_EL1;
```

```
MSR SPSR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x160] = X[t];
    else
        SPSR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        SPSR_EL2 = X[t];
    else
        SPSR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    SPSR_EL1 = X[t];
```

MRS <Xt>, SPSR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x160];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return SPSR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return SPSR_EL1;
    else
        UNDEFINED;
```

MSR SPSR_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x160] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        SPSR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        SPSR_EL1 = X[t];
    else
        UNDEFINED;
```

MRS <Xt>, SPSR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return SPSR_EL1;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return SPSR_EL2;
elsif PSTATE.EL == EL3 then
    return SPSR_EL2;
```

MSR SPSR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        SPSR_EL1 = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    SPSR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    SPSR_EL2 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_EL2, Saved Program Status Register (EL2)

The SPSR_EL2 characteristics are:

Purpose

Holds the saved process state when an exception is taken to EL2.

Configuration

AArch64 System register SPSR_EL2 bits [31:0] are architecturally mapped to AArch32 System register SPSR_hyp[31:0] .

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SPSR_EL2 is a 64-bit register.

Field descriptions

The SPSR_EL2 bit assignments are:

When AArch32 is supported at any Exception level and exception taken from AArch32 state:



An exception return from EL2 using AArch64 makes SPSR_EL2 become UNKNOWN.

Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to EL2, and copied to PSTATE.N on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to EL2, and copied to PSTATE.Z on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to EL2, and copied to PSTATE.C on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to EL2, and copied to PSTATE.V on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to EL2, and copied to PSTATE.Q on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to EL2, and copied to PSTATE.IT[1:0] on executing an exception return operation in EL2.

On executing an exception return operation in EL2 SPSR_EL2.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

DIT, bit [24]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to EL2, and copied to PSTATE.DIT on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to EL2, and copied to PSTATE.SSBS on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to EL2, and copied to PSTATE.PAN on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SS, bit [21]

Software Step. Set to the value of PSTATE.SS on taking an exception to EL2, and conditionally copied to PSTATE.SS on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to EL2, and copied to PSTATE.IL on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to EL2, and copied to PSTATE.GE on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to EL2, and copied to PSTATE.IT[7:2] on executing an exception return operation in EL2.

SPSR_EL2.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to EL2, and copied to PSTATE.E on executing an exception return operation in EL2.

If the implementation does not support big-endian operation, SPSR_EL2.E is RES0. If the implementation does not support little-endian operation, SPSR_EL2.E is RES1. On executing an exception return operation in EL2, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_EL2.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_EL2.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to EL2, and copied to PSTATE.A on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to EL2, and copied to PSTATE.I on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to EL2, and copied to PSTATE.F on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to EL2, and copied to PSTATE.T on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

M[4], bit [4]

Execution state. Set to `0b1`, the value of PSTATE.nRW, on taking an exception to EL2 from AArch32 state, and copied to PSTATE.nRW on executing an exception return operation in EL2.

M[4]	Meaning
0b1	AArch32 execution state.

This field resets to an architecturally UNKNOWN value.

M[3:0], bits [3:0]

AArch32 Mode. Set to the value of PSTATE.M[3:0] on taking an exception to EL2, and copied to PSTATE.M[3:0] on executing an exception return operation in EL2.

M[3:0]	Meaning
0b0000	User.
0b0001	FIQ.
0b0010	IRQ.
0b0011	Supervisor.
0b0111	Abort.
0b1010	Hyp.
0b1011	Undefined.
0b1111	System.

Other values are reserved. If SPSR_EL2.M[3:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in EL2 is an illegal return event, as described in 'Illegal return events from AArch64 state' in the Arm®Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

When exception taken from AArch64 state:



An exception return from EL2 using AArch64 makes SPSR_EL2 become UNKNOWN.

Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to EL2, and copied to PSTATE.N on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to EL2, and copied to PSTATE.Z on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to EL2, and copied to PSTATE.C on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to EL2, and copied to PSTATE.V on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Bits [27:26]

Reserved, RES0.

TCO, bit [25]

When ARMv8.5-MemTag is implemented:

Tag Check Override. Set to the value of PSTATE.TCO on taking an exception to EL2, and copied to PSTATE.TCO on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [24]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to EL2, and copied to PSTATE.DIT on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

UAO, bit [23]

When ARMv8.2-UAO is implemented:

User Access Override. Set to the value of PSTATE.UAO on taking an exception to EL2, and copied to PSTATE.UAO on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to EL2, and copied to PSTATE.PAN on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SS, bit [21]

Software Step. Set to the value of PSTATE.SS on taking an exception to EL2, and conditionally copied to PSTATE.SS on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to EL2, and copied to PSTATE.IL on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Bits [19:13]

Reserved, RES0.

SSBS, bit [12]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to EL2, and copied to PSTATE.SSBS on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

BTYPE, bits [11:10]

When ARMv8.5-BTI is implemented:

Branch Type Indicator. Set to the value of PSTATE.BTYPE on taking an exception to EL2, and copied to PSTATE.BTYPE on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

D, bit [9]

Debug exception mask. Set to the value of PSTATE.D on taking an exception to EL2, and copied to PSTATE.D on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to EL2, and copied to PSTATE.A on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to EL2, and copied to PSTATE.I on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to EL2, and copied to PSTATE.F on executing an exception return operation in EL2.

This field resets to an architecturally UNKNOWN value.

Bit [5]

Reserved, RES0.

M[4], bit [4]

When AArch32 is supported at any Exception level:

Execution state. Set to `0b0`, the value of PSTATE.nRW, on taking an exception to EL2 from AArch64 state, and copied to PSTATE.nRW on executing an exception return operation in EL2.

M[4]	Meaning
`0b0`	AArch64 execution state.

~~If AArch32 is not supported at any Exception level, this bit is RES0.~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

M[3:0], bits [3:0]

AArch64 Exception level and selected Stack Pointer.

M[3:0]	Meaning
0b0000	EL0t.
0b0100	EL1t.
0b0101	EL1h.
0b1000	EL2t.
0b1001	EL2h.

Other values are reserved. If SPSR_EL2.M[3:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in EL2 is an illegal return event, as described in 'Illegal return events from AArch64 state' in the Arm®Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The bits in this field are interpreted as follows:

- M[3:2] is set to the value of PSTATE.EL on taking an exception to EL2 and copied to PSTATE.EL on executing an exception return operation in EL2.
- M[1] is unused and is 0 for all non-reserved values.
- M[0] is set to the value of PSTATE.SP on taking an exception to EL2 and copied to PSTATE.SP on executing an exception return operation in EL2

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic SPSR_EL2 or SPSR_EL1 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, SPSR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return SPSR_EL1;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return SPSR_EL2;
elsif PSTATE.EL == EL3 then
    return SPSR_EL2;
```

```
MSR SPSR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        SPSR_EL1 = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    SPSR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    SPSR_EL2 = X[t];
```

MRS <Xt>, SPSR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x160];
    else
        return SPSR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return SPSR_EL2;
    else
        return SPSR_EL1;
elsif PSTATE.EL == EL3 then
    return SPSR_EL1;
```

MSR SPSR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x160] = X[t];
    else
        SPSR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        SPSR_EL2 = X[t];
    else
        SPSR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    SPSR_EL1 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_EL3, Saved Program Status Register (EL3)

The SPSR_EL3 characteristics are:

Purpose

Holds the saved process state when an exception is taken to EL3.

Configuration

AArch64 System register SPSR_EL3 bits [31:0] can be mapped to AArch32 System register SPSR_mon[31:0] , but this is not architecturally mandated.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to SPSR_EL3 are UNDEFINED.

Attributes

SPSR_EL3 is a 64-bit register.

Field descriptions

The SPSR_EL3 bit assignments are:

When AArch32 is supported at any Exception level and exception taken from AArch32 state:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
N	Z	C	V	Q	IT[1:0]		DIT	SSBS	PAN	SS	IL	GE				IT[7:2]						E	A	I	F	T	M[4]	M[3:0]			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

An exception return from EL3 using AArch64 makes SPSR_EL1 become UNKNOWN.

Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to EL3, and copied to PSTATE.N on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to EL3, and copied to PSTATE.Z on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to EL3, and copied to PSTATE.C on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to EL3, and copied to PSTATE.V on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to EL3, and copied to PSTATE.Q on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to EL3, and copied to PSTATE.IT[1:0] on executing an exception return operation in EL3.

On executing an exception return operation in EL3 SPSR_EL1.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

DIT, bit [24]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to EL3, and copied to PSTATE.DIT on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to EL3, and copied to PSTATE.SSBS on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to EL3, and copied to PSTATE.PAN on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SS, bit [21]

Software Step. Set to the value of PSTATE.SS on taking an exception to EL3, and conditionally copied to PSTATE.SS on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to EL3, and copied to PSTATE.IL on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to EL3, and copied to PSTATE.GE on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to EL3, and copied to PSTATE.IT[7:2] on executing an exception return operation in EL3.

SPSR_EL1.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to EL3, and copied to PSTATE.E on executing an exception return operation in EL3.

If the implementation does not support big-endian operation, SPSR_EL1.E is RES0. If the implementation does not support little-endian operation, SPSR_EL1.E is RES1. On executing an exception return operation in EL3, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_EL1.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_EL1.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to EL3, and copied to PSTATE.A on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to EL3, and copied to PSTATE.I on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to EL3, and copied to PSTATE.F on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to EL3, and copied to PSTATE.T on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

M[4], bit [4]

Execution state. Set to `0b1`, the value of PSTATE.nRW, on taking an exception to EL3 from AArch32 state, and copied to PSTATE.nRW on executing an exception return operation in EL3.

M[4]	Meaning
`0b1`	AArch32 execution state.

This field resets to an architecturally UNKNOWN value.

M[3:0], bits [3:0]

AArch32 Mode. Set to the value of PSTATE.M[3:0] on taking an exception to EL3, and copied to PSTATE.M[3:0] on executing an exception return operation in EL3.

M[3:0]	Meaning
`0b0000`	User.
`0b0001`	FIQ.
`0b0010`	IRQ.
`0b0011`	Supervisor.
`0b0110`	Monitor.
`0b0111`	Abort.
`0b1010`	Hyp.
`0b1011`	Undefined.
`0b1111`	System.

Other values are reserved. If SPSR_EL1.M[3:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in EL3 is an illegal return event, as described in 'Illegal return events from AArch64 state' in the Arm®Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

When exception taken from AArch64 state:



An exception return from EL3 using AArch64 makes SPSR_EL1 become UNKNOWN.

Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to EL3, and copied to PSTATE.N on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to EL3, and copied to PSTATE.Z on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to EL3, and copied to PSTATE.C on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to EL3, and copied to PSTATE.V on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Bits [27:26]

Reserved, RES0.

TCO, bit [25]

When ARMv8.5-MemTag is implemented:

Tag Check Override. Set to the value of PSTATE.TCO on taking an exception to EL3, and copied to PSTATE.TCO on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [24]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to EL3, and copied to PSTATE.DIT on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

UAO, bit [23]

When ARMv8.2-UAO is implemented:

User Access Override. Set to the value of PSTATE.UAO on taking an exception to EL3, and copied to PSTATE.UAO on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to EL3, and copied to PSTATE.PAN on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SS, bit [21]

Software Step. Set to the value of PSTATE.SS on taking an exception to EL3, and conditionally copied to PSTATE.SS on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to EL3, and copied to PSTATE.IL on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Bits [19:13]

Reserved, RES0.

SSBS, bit [12]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to EL3, and copied to PSTATE.SSBS on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

BTYPE, bits [11:10]

When ARMv8.5-BTI is implemented:

Branch Type Indicator. Set to the value of PSTATE.BTYPE on taking an exception to EL3, and copied to PSTATE.BTYPE on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

D, bit [9]

Debug exception mask. Set to the value of PSTATE.D on taking an exception to EL3, and copied to PSTATE.D on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to EL3, and copied to PSTATE.A on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to EL3, and copied to PSTATE.I on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to EL3, and copied to PSTATE.F on executing an exception return operation in EL3.

This field resets to an architecturally UNKNOWN value.

Bit [5]

Reserved, RES0.

M[4], bit [4]

When AArch32 is supported at any Exception level:

Execution state. Set to `0b0`, the value of PSTATE.nRW, on taking an exception to EL3 from AArch64 state, and copied to PSTATE.nRW on executing an exception return operation in EL3.

M[4]	Meaning
`0b0`	AArch64 execution state.

~~If AArch32 is not supported at any Exception level, this bit is RES0.~~

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

M[3:0], bits [3:0]

AArch64 Exception level and selected Stack Pointer.

M[3:0]	Meaning
0b0000	EL0t.
0b0100	EL1t.
0b0101	EL1h.
0b1000	EL2t.
0b1001	EL2h.
0b1100	EL3t.
0b1101	EL3h.

Other values are reserved. If SPSR_EL1.M[3:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in EL3 is an illegal return event, as described in 'Illegal return events from AArch64 state' in the Arm®Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The bits in this field are interpreted as follows:

- M[3:2] is set to the value of PSTATE.EL on taking an exception to EL3 and copied to PSTATE.EL on executing an exception return operation in EL3.
- M[1] is unused and is 0 for all non-reserved values.
- M[0] is set to the value of PSTATE.SP on taking an exception to EL3 and copied to PSTATE.SP on executing an exception return operation in EL3

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, SPSR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return SPSR_EL3;
```

```
MSR SPSR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    SPSR_EL3 = X[t];
```

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_fiq, Saved Program Status Register (FIQ mode)

The SPSR_fiq characteristics are:

Purpose

Holds the saved process state when an exception is taken to FIQ mode.

Configuration

AArch64 System register SPSR_fiq bits [31:0] are architecturally mapped to AArch32 System register SPSR_fiq[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

If EL1 only~~does~~ supports~~not~~ ~~support~~ execution in AArch64~~AArch32~~ state, this register is RES0 from EL2 and EL3.

Attributes

SPSR_fiq is a 64-bit register.

Field descriptions

The SPSR_fiq bit assignments are:



Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to FIQ mode, and copied to PSTATE.N on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to FIQ mode, and copied to PSTATE.Z on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to FIQ mode, and copied to PSTATE.C on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to FIQ mode, and copied to PSTATE.V on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to FIQ mode, and copied to PSTATE.Q on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to FIQ mode, and copied to PSTATE.IT[1:0] on executing an exception return operation in FIQ mode.

On executing an exception return operation in FIQ mode SPSR_fiq.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. ~~Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.~~

Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to FIQ mode, and copied to PSTATE.SSBS on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to FIQ mode, and copied to PSTATE.PAN on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to FIQ mode, and copied to PSTATE.DIT on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to FIQ mode, and copied to PSTATE.IL on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to FIQ mode, and copied to PSTATE.GE on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to FIQ mode, and copied to PSTATE.IT[7:2] on executing an exception return operation in FIQ mode.

SPSR_fiq.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to FIQ mode, and copied to PSTATE.E on executing an exception return operation in FIQ mode.

If the implementation does not support big-endian operation, SPSR_fiq.E is RES0. If the implementation does not support little-endian operation, SPSR_fiq.E is RES1. On executing an exception return operation in FIQ mode, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_fiq.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_fiq.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to FIQ mode, and copied to PSTATE.A on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to FIQ mode, and copied to PSTATE.I on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to FIQ mode, and copied to PSTATE.F on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to FIQ mode, and copied to PSTATE.T on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on taking an exception to FIQ mode, and copied to PSTATE.M[4:0] on executing an exception return operation in FIQ mode.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10111	Abort.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If SPSR_fiq.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in FIQ mode is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_fiq

Accesses to this register use the following encodings:

```
MRS <Xt>, SPSR_fiq
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0011	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return SPSR_fiq;
elsif PSTATE.EL == EL3 then
    return SPSR_fiq;
```

```
MSR SPSR_fiq, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0011	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    SPSR_fiq = X[t];
elsif PSTATE.EL == EL3 then
    SPSR_fiq = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_irq, Saved Program Status Register (IRQ mode)

The SPSR_irq characteristics are:

Purpose

Holds the saved process state when an exception is taken to IRQ mode.

Configuration

AArch64 System register SPSR_irq bits [31:0] are architecturally mapped to AArch32 System register SPSR_irq[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

If EL1 only~~does~~ supports~~not~~ ~~support~~ execution in AArch64~~AArch32~~ state, this register is RES0 from EL2 and EL3.

Attributes

SPSR_irq is a 64-bit register.

Field descriptions

The SPSR_irq bit assignments are:



Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to IRQ mode, and copied to PSTATE.N on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to IRQ mode, and copied to PSTATE.Z on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to IRQ mode, and copied to PSTATE.C on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to IRQ mode, and copied to PSTATE.V on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to IRQ mode, and copied to PSTATE.Q on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to IRQ mode, and copied to PSTATE.IT[1:0] on executing an exception return operation in IRQ mode.

On executing an exception return operation in IRQ mode SPSR_irq.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. ~~Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.~~

Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to IRQ mode, and copied to PSTATE.SSBS on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to IRQ mode, and copied to PSTATE.PAN on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to IRQ mode, and copied to PSTATE.DIT on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to IRQ mode, and copied to PSTATE.IL on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to IRQ mode, and copied to PSTATE.GE on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to IRQ mode, and copied to PSTATE.IT[7:2] on executing an exception return operation in IRQ mode.

SPSR_irq.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to IRQ mode, and copied to PSTATE.E on executing an exception return operation in IRQ mode.

If the implementation does not support big-endian operation, SPSR_irq.E is RES0. If the implementation does not support little-endian operation, SPSR_irq.E is RES1. On executing an exception return operation in IRQ mode, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_irq.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_irq.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to IRQ mode, and copied to PSTATE.A on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to IRQ mode, and copied to PSTATE.I on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to IRQ mode, and copied to PSTATE.F on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to IRQ mode, and copied to PSTATE.T on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on taking an exception to IRQ mode, and copied to PSTATE.M[4:0] on executing an exception return operation in IRQ mode.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10111	Abort.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If SPSR_irq.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in IRQ mode is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_irq

Accesses to this register use the following encodings:

```
MRS <Xt>, SPSR_irq
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return SPSR_irq;
elsif PSTATE.EL == EL3 then
    return SPSR_irq;
```

```
MSR SPSR_irq, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    SPSR_irq = X[t];
elsif PSTATE.EL == EL3 then
    SPSR_irq = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_und, Saved Program Status Register (Undefined mode)

The SPSR_und characteristics are:

Purpose

Holds the saved process state when an exception is taken to Undefined mode.

Configuration

AArch64 System register SPSR_und bits [31:0] are architecturally mapped to AArch32 System register SPSR_und[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

If EL1 only~~does~~ supports~~not~~ ~~support~~ execution in AArch64~~AArch32~~ state, this register is RES0 from EL2 and EL3.

Attributes

SPSR_und is a 64-bit register.

Field descriptions

The SPSR_und bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
N	Z	C	V	Q	IT[1:0]		J	SSBS	PAN	DIT	IL	GE				IT[7:2]						E	A	I	F	T	M[4:0]				
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to Undefined mode, and copied to PSTATE.N on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to Undefined mode, and copied to PSTATE.Z on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to Undefined mode, and copied to PSTATE.C on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to Undefined mode, and copied to PSTATE.V on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to Undefined mode, and copied to PSTATE.Q on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to Undefined mode, and copied to PSTATE.IT[1:0] on executing an exception return operation in Undefined mode.

On executing an exception return operation in Undefined mode SPSR_und.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. ~~Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.~~

Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to Undefined mode, and copied to PSTATE.SSBS on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to Undefined mode, and copied to PSTATE.PAN on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to Undefined mode, and copied to PSTATE.DIT on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to Undefined mode, and copied to PSTATE.IL on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to Undefined mode, and copied to PSTATE.GE on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to Undefined mode, and copied to PSTATE.IT[7:2] on executing an exception return operation in Undefined mode.

SPSR_und.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to Undefined mode, and copied to PSTATE.E on executing an exception return operation in Undefined mode.

If the implementation does not support big-endian operation, SPSR_und.E is RES0. If the implementation does not support little-endian operation, SPSR_und.E is RES1. On executing an exception return operation in Undefined mode, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_und.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_und.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to Undefined mode, and copied to PSTATE.A on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to Undefined mode, and copied to PSTATE.I on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to Undefined mode, and copied to PSTATE.F on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to Undefined mode, and copied to PSTATE.T on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on taking an exception to Undefined mode, and copied to PSTATE.M[4:0] on executing an exception return operation in Undefined mode.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10111	Abort.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If SPSR_und.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in Undefined mode is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_und

Accesses to this register use the following encodings:

```
MRS <Xt>, SPSR_und
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0011	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return SPSR_und;
elsif PSTATE.EL == EL3 then
    return SPSR_und;
```

```
MSR SPSR_und, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0100	0b0011	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    SPSR_und = X[t];
elsif PSTATE.EL == EL3 then
    SPSR_und = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SSBS, Speculative Store Bypass Safe

The SSBS characteristics are:

Purpose

Allows access to the Speculative Store Bypass Safe bit.

Configuration

This register is present only when ARMv8.0-SSBS is implemented. Otherwise, direct accesses to SSBS are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SSBS is a 64-bit register.

Field descriptions

The SSBS bit assignments are:



Bits [63:13]

Reserved, RES0.

SSBS, bit [12]

Speculative Store Bypass Safe.

Prohibits speculative loads or stores which might practically allow a cache timing side channel.

A cache timing side channel might be exploited where a load or store uses an address that is derived from a register that is being loaded from memory using a load instruction speculatively read from a memory location. If PSTATE.SSBS is enabled, the address derived from the load instruction might be from earlier in the coherence order than the latest store to that memory location with the same virtual address.

SSBS	Meaning
0b0	Hardware is not permitted to load or store speculatively, in a manner that could practically give rise to a cache timing side channel, using an address derived from a register value that has been loaded from memory using a load instruction (L) that speculatively reads an entry from earlier in the coherence order from that location being loaded from than the entry generated by the latest store (S) to that location using the same virtual address as L.
0b1	Hardware is permitted to load or store speculatively, in a manner that could practically give rise to a cache timing side channel, using an address derived from a register value that has been loaded from memory using a load instruction (L) that speculatively reads an entry from earlier in the coherence order fro that location being loaded from than the entry generated by the latest store (S) to that location using the same virtual address as L.

The value of this bit is set to the value in the SCTLR_ELx.DSSBS field on taking an exception to ELx.

This field resets to an IMPLEMENTATION DEFINED value.

Bits [11:0]

Reserved, RES0.

Accessing the SSBS

~~For details on the operation of the MSR (immediate) accessor, see MSR (immediate) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

`MRS <Xt>, SSBS`

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0010	0b110

```
if PSTATE.EL == EL0 then
    return Zeros(51):PSTATE.SSBS:Zeros(12);
elsif PSTATE.EL == EL1 then
    return Zeros(51):PSTATE.SSBS:Zeros(12);
elsif PSTATE.EL == EL2 then
    return Zeros(51):PSTATE.SSBS:Zeros(12);
elsif PSTATE.EL == EL3 then
    return Zeros(51):PSTATE.SSBS:Zeros(12);
```

`MSR SSBS, <Xt>`

op0	op1	CRn	CRm	op2
0b11	0b011	0b0100	0b0010	0b110

```
if PSTATE.EL == EL0 then
    PSTATE.SSBS = X[t]<12>;
elsif PSTATE.EL == EL1 then
    PSTATE.SSBS = X[t]<12>;
elsif PSTATE.EL == EL2 then
    PSTATE.SSBS = X[t]<12>;
elsif PSTATE.EL == EL3 then
    PSTATE.SSBS = X[t]<12>;
```

MSR SSBS, #<imm>

op0	op1	CRn	op2
0b00	0b011	0b0100	0b001

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TCR_EL1, Translation Control Register (EL1)

The TCR_EL1 characteristics are:

Purpose

The control register for stage 1 of the EL1&0 translation regime.

Configuration

AArch64 System register TCR_EL1 bits [31:0] are architecturally mapped to AArch32 System register TTBCR[31:0] .

AArch64 System register TCR_EL1 bits [63:32] are architecturally mapped to AArch32 System register TTBCR2[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

TCR_EL1 is a 64-bit register.

Field descriptions

The TCR_EL1 bit assignments are:



Any of the bits in TCR_EL1, other than the A1 bit and the EPDx bits when they have the value 1, are permitted to be cached in a TLB.

Bits [63:59]

Reserved, RES0.

TCMA1, bit [58]

When ARMv8.5-MemTag is implemented:

Controls the generation of Unchecked accesses at EL1, and at EL0 if HCR_EL2.{E2H,TGE}!={1,1}, when address[59:55] = 0b11111.

TCMA1	Meaning
0b0	This control has no effect on the generation of Unchecked accesses at EL1 or EL0.
0b1	All accesses at EL1 and EL0 are Unchecked.

Note

Software may change this control bit on a context switch.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TCMA0, bit [57]

When ARMv8.5-MemTag is implemented:

Controls the generation of Unchecked accesses at EL1, and at EL0 if HCR_EL2.{E2H,TGE}!={1,1}, when address[59:55] = 0b00000.

TCMA0	Meaning
0b0	This control has no effect on the generation of Unchecked accesses at EL1 or EL0.
0b1	All accesses at EL1 and EL0 are Unchecked.

Note

Software may change this control bit on a context switch.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

E0PD1, bit [56]

When ARMv8.5-E0PD is implemented:

Faulting control for EL0 access to any address translated by TTBR1_EL1.

E0PD1	Meaning
0b0	Unprivileged access to any address translated by TTBR1_EL1 will not generate a fault by this mechanism.
0b1	Unprivileged access to any address translated by TTBR1_EL1 will generate a level 0 translation fault

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

E0PD0, bit [55]

When ARMv8.5-E0PD is implemented:

Faulting control for EL0 access to any address translated by TTBR0_EL1.

E0PD0	Meaning
0b0	Unprivileged access to any address translated by TTBR0_EL1 will not generate a fault by this mechanism.
0b1	Unprivileged access to any address translated by TTBR0_EL1 will generate a level 0 translation fault

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NFD1, bit [54]

When SVE is implemented:

Non-fault translation table walk disable for stage 1 translations using TTBR1_EL1.

This bit controls whether to perform a stage 1 translation table walk in response to a non-fault access from EL0 for a virtual address that is translated using TTBR1_EL1.

If SVE is implemented, the affected access types include:

- All accesses due to an SVE non-fault contiguous load instruction.
- Accesses due to an SVE first-fault gather load instruction that are not for the First active element. Accesses due to an SVE first-fault contiguous load instruction are not affected.
- Accesses due to prefetch instructions might be affected, but the effect is not architecturally visible.

See 'The Scalable Vector Extension (SVE)', in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile for more information.

Defined values are:

NFD1	Meaning
0b0	Does not disable stage 1 translation table walks using TTBR1_EL1.
0b1	A TLB miss on a virtual address that is translated using TTBR1_EL1 due to the specified access types causes the access to fail without taking an exception. No stage 1 translation table walk is performed.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NFD0, bit [53]

When SVE is implemented:

Non-fault translation table walk disable for stage 1 translations using TTBR0_EL1.

This bit controls whether to perform a stage 1 translation table walk in response to a non-fault access from EL0 for a virtual address that is translated using TTBR0_EL1.

If SVE is implemented, the affected access types include:

- All accesses due to an SVE non-fault contiguous load instruction.
- Accesses due to an SVE first-fault gather load instruction that are not for the First active element. Accesses due to an SVE first-fault contiguous load instruction are not affected.
- Accesses due to prefetch instructions might be affected, but the effect is not architecturally visible.

See 'The Scalable Vector Extension (SVE)', in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile for more information.

Defined values are:

NFD0	Meaning
0b0	Does not disable stage 1 translation table walks using TTBR0_EL1.
0b1	A TLB miss on a virtual address that is translated using TTBR0_EL1 due to the specified access types causes the access to fail without taking an exception. No stage 1 translation table walk is performed.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TBID1, bit [52]

When ARMv8.3-PAuth is implemented:

Controls the use of the top byte of instruction addresses for address matching.

For the purpose of this field, all cache maintenance and address translation instructions that perform address translation are treated as data accesses.

For more information, see 'Address tagging in AArch64 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

TBID1	Meaning
0b0	TCR_EL1.TBI1 applies to Instruction and Data accesses.
0b1	TCR_EL1.TBI1 applies to Data accesses only.

This affects addresses where the address would be translated by tables pointed to by TTBR1_EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TBID0, bit [51]

When ARMv8.3-PAuth is implemented:

Controls the use of the top byte of instruction addresses for address matching.

For the purpose of this field, all cache maintenance and address translation instructions that perform address translation are treated as data accesses.

For more information, see 'Address tagging in AArch64 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

TBID0	Meaning
0b0	TCR_EL1.TBI0 applies to Instruction and Data accesses.
0b1	TCR_EL1.TBI0 applies to Data accesses only.

This affects addresses where the address would be translated by tables pointed to by TTBR0_EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU162, bit [50]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[62] of the stage 1 translation table Block or Page entry for translations using TTBR1_EL1.

HWU162	Meaning
0b0	For translations using TTBR1_EL1, bit[62] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR1_EL1, bit[62] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL1.HPD1 is 1.

The Effective value of this field is 0 if the value of TCR_EL1.HPD1 is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU161, bit [49]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[61] of the stage 1 translation table Block or Page entry for translations using TTBR1_EL1.

HWU161	Meaning
0b0	For translations using TTBR1_EL1, bit[61] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR1_EL1, bit[61] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL1.HPD1 is 1.

The Effective value of this field is 0 if the value of TCR_EL1.HPD1 is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU160, bit [48]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[60] of the stage 1 translation table Block or Page entry for translations using TTBR1_EL1.

HWU160	Meaning
0b0	For translations using TTBR1_EL1, bit[60] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR1_EL1, bit[60] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL1.HPD1 is 1.

The Effective value of this field is 0 if the value of TCR_EL1.HPD1 is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU159, bit [47]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[59] of the stage 1 translation table Block or Page entry for translations using TTBR1_EL1.

HWU159	Meaning
0b0	For translations using TTBR1_EL1, bit[59] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR1_EL1, bit[59] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL1.HPD1 is 1.

The Effective value of this field is 0 if the value of TCR_EL1.HPD1 is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU062, bit [46]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[62] of the stage 1 translation table Block or Page entry for translations using TTBR0_EL1.

HWU062	Meaning
0b0	For translations using TTBR0_EL1, bit[62] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR0_EL1, bit[62] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL1.HPD0 is 1.

The Effective value of this field is 0 if the value of TCR_EL1.HPD0 is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU061, bit [45]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[61] of the stage 1 translation table Block or Page entry for translations using TTBR0_EL1.

HWU061	Meaning
0b0	For translations using TTBR0_EL1, bit[61] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR0_EL1, bit[61] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL1.HPD0 is 1.

The Effective value of this field is 0 if the value of TCR_EL1.HPD0 is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU060, bit [44]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[60] of the stage 1 translation table Block or Page entry for translations using TTBR0_EL1.

HWU060	Meaning
0b0	For translations using TTBR0_EL1, bit[60] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR0_EL1, bit[60] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL1.HPD0 is 1.

The Effective value of this field is 0 if the value of TCR_EL1.HPD0 is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU059, bit [43]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[59] of the stage 1 translation table Block or Page entry for translations using TTBR0_EL1.

HWU059	Meaning
0b0	For translations using TTBR0_EL1, bit[59] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR0_EL1, bit[59] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL1.HPD0 is 1.

The Effective value of this field is 0 if the value of TCR_EL1.HPD0 is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HPD1, bit [42]

When ARMv8.1-HPD is implemented:

Hierarchical Permission Disables. This affects the hierarchical control bits, APTable, PXNTable, and UXNTable, except NSTable, in the translation tables pointed to by TTBR1_EL1.

HPD1	Meaning
0b0	Hierarchical permissions are enabled.
0b1	Hierarchical permissions are disabled.

When disabled, the permissions are treated as if the bits are zero.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HPD0, bit [41]

When ARMv8.1-HPD is implemented:

Hierarchical Permission Disables. This affects the hierarchical control bits, APTable, PXNTable, and UXNTable, except NSTable, in the translation tables pointed to by TTBR0_EL1.

HPD0	Meaning
0b0	Hierarchical permissions are enabled.
0b1	Hierarchical permissions are disabled.

When disabled, the permissions are treated as if the bits are zero.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HD, bit [40]

When ARMv8.1-TTHM is implemented:

Hardware management of dirty state in stage 1 translations from EL0 and EL1.

HD	Meaning
0b0	Stage 1 hardware management of dirty state disabled.
0b1	Stage 1 hardware management of dirty state enabled, only if the HA bit is also set to 1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HA, bit [39]

When ARMv8.1-TTHM is implemented:

Hardware Access flag update in stage 1 translations from EL0 and EL1.

HA	Meaning
0b0	Stage 1 Access flag update disabled.
0b1	Stage 1 Access flag update enabled.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TBI1, bit [38]

Top Byte ignored - indicates whether the top byte of an address is used for address match for the TTBR1_EL1 region, or ignored and used for tagged addresses. Defined values are:

TBI1	Meaning
0b0	Top Byte used in the address calculation.
0b1	Top Byte ignored in the address calculation.

This affects addresses generated in EL0 and EL1 using AArch64 where the address would be translated by tables pointed to by TTBR1_EL1. It has an effect whether the EL1&0 translation regime is enabled or not.

If ARMv8.3-PAuth is implemented and TCR_EL1.TBID1 is 1, then this field only applies to Data accesses.

Otherwise, if the value of TBI1 is 1 and bit [55] of the target address to be stored to the PC is 1, then bits[63:56] of that target address are also set to 1 before the address is stored in the PC, in the following cases:

- A branch or procedure return within EL0 or EL1.
- An exception taken to EL1.
- An exception return to EL0 or EL1.

This field resets to an architecturally UNKNOWN value.

TBI0, bit [37]

Top Byte ignored - indicates whether the top byte of an address is used for address match for the TTBR0_EL1 region, or ignored and used for tagged addresses. Defined values are:

TBI0	Meaning
0b0	Top Byte used in the address calculation.
0b1	Top Byte ignored in the address calculation.

This affects addresses generated in EL0 and EL1 using AArch64 where the address would be translated by tables pointed to by TTBR0_EL1. It has an effect whether the EL1&0 translation regime is enabled or not.

If ARMv8.3-PAuth is implemented and TCR_EL1.TBID0 is 1, then this field only applies to Data accesses.

Otherwise, if the value of TBI0 is 1 and bit [55] of the target address to be stored to the PC is 0, then bits[63:56] of that target address are also set to 0 before the address is stored in the PC, in the following cases:

- A branch or procedure return within EL0 or EL1.
- An exception taken to EL1.
- An exception return to EL0 or EL1.

This field resets to an architecturally UNKNOWN value.

AS, bit [36]

ASID Size. Defined values are:

AS	Meaning
0b0	8 bit - the upper 8 bits of TTBR0_EL1 and TTBR1_EL1 are ignored by hardware for every purpose except reading back the register, and are treated as if they are all zeros for when used for allocation and matching entries in the TLB.
0b1	16 bit - the upper 16 bits of TTBR0_EL1 and TTBR1_EL1 are used for allocation and matching in the TLB.

If the implementation has only 8 bits of ASID, this field is RES0.

This field resets to an architecturally UNKNOWN value.

Bit [35]

Reserved, RES0.

IPS, bits [34:32]

Intermediate Physical Address Size.

IPS	Meaning
0b000	32 bits, 4GB.
0b001	36 bits, 64GB.
0b010	40 bits, 1TB.
0b011	42 bits, 4TB.
0b100	44 bits, 16TB.
0b101	48 bits, 256TB.
0b110	52 bits, 4PB.

Other values are reserved.

The reserved values behave in the same way as the 0b101 or 0b110 encoding, but software must not rely on this property as the behavior of the reserved values might change in a future revision of the architecture.

The value 0b110 is permitted only if ARMv8.2-LPA is implemented and the translation granule size is 64KB.

In an implementation that supports 52-bit PAs, if the value of this field is not 0b110 or a value treated as 0b110, then bits[51:48] of every translation table base address for the stage of translation controlled by TCR_EL1 are 0b0000.

This field resets to an architecturally UNKNOWN value.

TG1, bits [31:30]

Granule size for the TTBR1_EL1.

TG1	Meaning
0b01	16KB.
0b10	4KB.
0b11	64KB.

Other values are reserved.

If the value is programmed to either a reserved value, or a size that has not been implemented, then the hardware will treat the field as if it has been programmed to an IMPLEMENTATION DEFINED choice of the sizes that has been implemented for all purposes other than the value read back from this register.

It is IMPLEMENTATION DEFINED whether the value read back is the value programmed or the value that corresponds to the size chosen.

This field resets to an architecturally UNKNOWN value.

SH1, bits [29:28]

Shareability attribute for memory associated with translation table walks using TTBR1_EL1.

SH1	Meaning
0b00	Non-shareable.
0b10	Outer Shareable.
0b11	Inner Shareable.

Other values are reserved. The effect of programming this field to a Reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Reserved values in AArch64 System registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

ORGN1, bits [27:26]

Outer cacheability attribute for memory associated with translation table walks using TTBR1_EL1.

ORGN1	Meaning
0b00	Normal memory, Outer Non-cacheable.
0b01	Normal memory, Outer Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Outer Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Outer Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

IRGN1, bits [25:24]

Inner cacheability attribute for memory associated with translation table walks using TTBR1_EL1.

IRGN1	Meaning
0b00	Normal memory, Inner Non-cacheable.
0b01	Normal memory, Inner Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Inner Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Inner Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

EPD1, bit [23]

Translation table walk disable for translations using TTBR1_EL1. This bit controls whether a translation table walk is performed on a TLB miss, for an address that is translated using TTBR1_EL1. The encoding of this bit is:

EPD1	Meaning
0b0	Perform translation table walks using TTBR1_EL1.
0b1	A TLB miss on an address that is translated using TTBR1_EL1 generates a Translation fault. No translation table walk is performed.

This field resets to an architecturally UNKNOWN value.

A1, bit [22]

Selects whether TTBR0_EL1 or TTBR1_EL1 defines the ASID. The encoding of this bit is:

A1	Meaning
0b0	TTBR0_EL1.ASID defines the ASID.
0b1	TTBR1_EL1.ASID defines the ASID.

This field resets to an architecturally UNKNOWN value.

T1SZ, bits [21:16]

The size offset of the memory region addressed by TTBR1_EL1. The region size is $2^{(64-T1SZ)}$ bytes.

The maximum and minimum possible values for T1SZ depend on the level of translation table and the memory translation granule size, as described in the AArch64 Virtual Memory System Architecture chapter.

This field resets to an architecturally UNKNOWN value.

TG0, bits [15:14]

Granule size for the TTBR0_EL1.

TG0	Meaning
0b00	4KB
0b01	64KB
0b10	16KB

Other values are reserved.

If the value is programmed to either a reserved value, or a size that has not been implemented, then the hardware will treat the field as if it has been programmed to an IMPLEMENTATION DEFINED choice of the sizes that has been implemented for all purposes other than the value read back from this register.

It is IMPLEMENTATION DEFINED whether the value read back is the value programmed or the value that corresponds to the size chosen.

This field resets to an architecturally UNKNOWN value.

SH0, bits [13:12]

Shareability attribute for memory associated with translation table walks using TTBR0_EL1.

SH0	Meaning
0b00	Non-shareable
0b10	Outer Shareable
0b11	Inner Shareable

Other values are reserved. The effect of programming this field to a Reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Reserved values in AArch64 System registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

ORGN0, bits [11:10]

Outer cacheability attribute for memory associated with translation table walks using TTBR0_EL1.

ORGN0	Meaning
0b00	Normal memory, Outer Non-cacheable.
0b01	Normal memory, Outer Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Outer Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Outer Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

IRGN0, bits [9:8]

Inner cacheability attribute for memory associated with translation table walks using TTBR0_EL1.

IRGN0	Meaning
0b00	Normal memory, Inner Non-cacheable.
0b01	Normal memory, Inner Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Inner Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Inner Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

EPD0, bit [7]

Translation table walk disable for translations using TTBR0_EL1. This bit controls whether a translation table walk is performed on a TLB miss, for an address that is translated using TTBR0_EL1. The encoding of this bit is:

EPD0	Meaning
0b0	Perform translation table walks using TTBR0_EL1.
0b1	A TLB miss on an address that is translated using TTBR0_EL1 generates a Translation fault. No translation table walk is performed.

This field resets to an architecturally UNKNOWN value.

Bit [6]

Reserved, RES0.

T0SZ, bits [5:0]

The size offset of the memory region addressed by TTBR0_EL1. The region size is $2^{(64-T0SZ)}$ bytes.

The maximum and minimum possible values for T0SZ depend on the level of translation table and the memory translation granule size, as described in the AArch64 Virtual Memory System Architecture chapter.

This field resets to an architecturally UNKNOWN value.

Accessing the TCR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic TCR_EL1 or TCR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, TCR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0010	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.TCR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x120];
    else
        return TCR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return TCR_EL2;
    else
        return TCR_EL1;
elsif PSTATE.EL == EL3 then
    return TCR_EL1;
```

```
MSR TCR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2

0b11	0b000	0b0010	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.TCR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x120] = X[t];
    else
        TCR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        TCR_EL2 = X[t];
    else
        TCR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    TCR_EL1 = X[t];
```

MRS <Xt>, TCR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0010	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x120];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return TCR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return TCR_EL1;
    else
        UNDEFINED;
```

MSR TCR_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b0010	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x120] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        TCR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        TCR_EL1 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TCR_EL3, Translation Control Register (EL3)

The TCR_EL3 characteristics are:

Purpose

The control register for stage 1 of the EL3 translation regime.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to TCR_EL3 are UNDEFINED.

Attributes

TCR_EL3 is a 64-bit register.

Field descriptions

The TCR_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES1	TCMA	TBID	HWU62	HWU61	HWU60	HWU59	HPD	RES1	HD	HA	TBI	RES0	PS			TG0	SH0	ORGN0		IRGN0		RES0						T0SZ			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Any of the bits in TCR_EL3 are permitted to be cached in a TLB.

Bits [63:32]

Reserved, RES0.

Bit [31]

Reserved, RES1.

TCMA, bit [30]

When ARMv8.5-MemTag is implemented:

Controls the generation of Unchecked accesses at EL3 when address [59:56] = `0b0000`.

TCMA	Meaning
`0b0`	This control has no effect on the generation of Unchecked accesses.
`0b1`	All accesses are Unchecked.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TBID, bit [29]

When ARMv8.3-PAuth is implemented:

Controls the use of the top byte of instruction addresses for address matching.

TBID	Meaning
0b0	TCR_EL3.TBI applies to Instruction and Data accesses.
0b1	TCR_EL3.TBI applies to Data accesses only.

This affects addresses where the address would be translated by tables pointed to by TTBR0_EL3.

For the purpose of this field, all cache maintenance and address translation instructions that perform address translation are treated as data accesses.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU62, bit [28]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[62] of the stage 1 translation table Block or Page entry.

HWU62	Meaning
0b0	Bit[62] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[62] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL3.HPD is 1.

The Effective value of this field is 0 if the value of TCR_EL3.HPD is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU61, bit [27]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[61] of the stage 1 translation table Block or Page entry.

HWU61	Meaning
0b0	Bit[61] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[61] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL3.HPD is 1.

The Effective value of this field is 0 if the value of TCR_EL3.HPD is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU60, bit [26]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[60] of the stage 1 translation table Block or Page entry.

HWU60	Meaning
0b0	Bit[60] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[60] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL3.HPD is 1.

The Effective value of this field is 0 if the value of TCR_EL3.HPD is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU59, bit [25]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[59] of the stage 1 translation table Block or Page entry.

HWU59	Meaning
0b0	Bit[59] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[59] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TCR_EL3.HPD is 1.

The Effective value of this field is 0 if the value of TCR_EL3.HPD is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HPD, bit [24]

When ARMv8.1-HPD is implemented:

Hierarchical Permission Disables. This affects the hierarchical control bits, APTable, PXNTable, and UXNTable, except NSTable, in the translation tables pointed to by TTBR0_EL3.

HPD	Meaning
0b0	Hierarchical permissions are enabled.
0b1	Hierarchical permissions are disabled.

Note
In this case bit[61] (APTable[0]) and bit[59] (PXNTable) of the next level descriptor attributes are required to be ignored by the PE, and are no longer reserved, allowing them to be used by software.

When disabled, the permissions are treated as if the bits are zero.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [23]

Reserved, RES1.

HD, bit [22]

When ARMv8.1-TTHM is implemented:

Hardware management of dirty state in stage 1 translations from EL3.

HD	Meaning
0b0	Stage 1 hardware management of dirty state disabled.
0b1	Stage 1 hardware management of dirty state enabled, only if the HA bit is also set to 1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HA, bit [21]

When ARMv8.1-TTHM is implemented:

Hardware Access flag update in stage 1 translations from EL3.

HA	Meaning
0b0	Stage 1 Access flag update disabled.
0b1	Stage 1 Access flag update enabled.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TBI, bit [20]

Top Byte Ignored. Indicates whether the top byte of an address is used for address match for the TTBR0_EL3 region, or ignored and used for tagged addresses.

TBI	Meaning
0b0	Top Byte used in the address calculation.
0b1	Top Byte ignored in the address calculation.

This affects addresses generated in EL3 using AArch64 where the address would be translated by tables pointed to by TTBR0_EL3. It has an effect whether the EL3 translation regime is enabled or not.

If ARMv8.3-PAuth is implemented and TCR_EL3.TBID is 1, then this field only applies to Data accesses.

Otherwise, if the value of TBI is 1, then bits[63:56] of that target address are also set to 0 before the address is stored in the PC, in the following cases:

- A branch or procedure return within EL3.
- A exception taken to EL3.
- An exception return to EL3.

For more information, see 'Address tagging in AArch64 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Note

This control detrmines the scope of address tagging. It never causes an exception to be generated.

This field resets to an architecturally UNKNOWN value.

Bit [19]

Reserved, RES0.

PS, bits [18:16]

Physical Address Size.

PS	Meaning
0b000	32 bits, 4GB.
0b001	36 bits, 64GB.
0b010	40 bits, 1TB.
0b011	42 bits, 4TB.
0b100	44 bits, 16TB.
0b101	48 bits, 256TB.
0b110	52 bits, 4PB.

Other values are reserved.

The reserved values behave in the same way as the 0b101 or 0b110 encoding, but software must not rely on this property as the behavior of the reserved values might change in a future revision of the architecture.

The value 0b110 is permitted only if ARMv8.2-LPA is implemented and the translation granule size is 64KB.

In an implementation that supports 52-bit PAs, if the value of this field is not 0b110 or a value treated as 0b110, then bits[51:48] of every translation table base address for the stage of translation controlled by TCR_EL3 are 0b0000.

This field resets to an architecturally UNKNOWN value.

TG0, bits [15:14]

Granule size for the TTBR0_EL3.

TG0	Meaning
0b00	4KB.
0b01	64KB.
0b10	16KB.

Other values are reserved.

If the value is programmed to either a reserved value, or a size that has not been implemented, then the hardware will treat the field as if it has been programmed to an IMPLEMENTATION DEFINED choice of the sizes that has been implemented for all purposes other than the value read back from this register.

It is IMPLEMENTATION DEFINED whether the value read back is the value programmed or the value that corresponds to the size chosen.

This field resets to an architecturally UNKNOWN value.

SH0, bits [13:12]

Shareability attribute for memory associated with translation table walks using TTBR0_EL3.

SH0	Meaning
0b00	Non-shareable.
0b10	Outer Shareable.
0b11	Inner Shareable.

Other values are reserved. The effect of programming this field to a Reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Reserved values in AArch64 System registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.2.2.

This field resets to an architecturally UNKNOWN value.

ORGN0, bits [11:10]

Outer cacheability attribute for memory associated with translation table walks using TTBR0_EL3.

ORGN0	Meaning
0b00	Normal memory, Outer Non-cacheable.
0b01	Normal memory, Outer Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Outer Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Outer Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

IRGN0, bits [9:8]

Inner cacheability attribute for memory associated with translation table walks using TTBR0_EL3.

IRGN0	Meaning
0b00	Normal memory, Inner Non-cacheable.
0b01	Normal memory, Inner Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Inner Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Inner Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

Bits [7:6]

Reserved, RES0.

T0SZ, bits [5:0]

The size offset of the memory region addressed by TTBR0_EL3. The region size is $2^{(64-T0SZ)}$ bytes.

The maximum and minimum possible values for T0SZ depend on the level of translation table and the memory translation granule size, as described in the AArch64 Virtual Memory System Architecture chapter.

This field resets to an architecturally UNKNOWN value.

Accessing the TCR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, TCR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0010	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return TCR_EL3;
```

```
MSR TCR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0010	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    TCR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TFSR_EL1, Tag FaultFail Status Register (EL1)

The TFSR_EL1 characteristics are:

Purpose

Holds accumulated Tag Check FaultsFails occurring in EL1 thatwhich are not taken precisely.

Configuration

This register is present only when ARMv8.5-MemTag is implemented and ID_AA64PFR1_EL1.MTE != 0b0001. Otherwise, direct accesses to TFSR_EL1 are UNDEFINED.

RW fields in this register reset to architecturally UNKNOWN values.

Attributes

TFSR_EL1 is a 64-bit register.

Field descriptions

The TFSR_EL1 bit assignments are:



Bits [63:2]

Reserved, RES0.

TF1, bit [1]

Tag Check Fault.Fail. Asynchronously set to 1 when a Tag Check Faultfail using a virtual address with bit[<55] ==>== 0b1 occurs.

This field resets to an architecturally UNKNOWN value.

TF0, bit [0]

Tag Check Fault.Fail. Asynchronously set to 1 when a Tag Check Faultfail using a virtual address with bit[<55] ==>== 0b0 occurs.

This field resets to an architecturally UNKNOWN value.

Accessing the TFSR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, TFSR_EL1
```

op0	op1	CRn	CRm	op2

0b11	0b000	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x190];
    else
        return TFSR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        return TFSR_EL2;
    else
        return TFSR_EL1;
elsif PSTATE.EL == EL3 then
    return TFSR_EL1;
```

MSR TFSR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x190] = X[t];
    else
        TFSR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        TFSR_EL2 = X[t];
    else
        TFSR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    TFSR_EL1 = X[t];
```

MRS <Xt>, TFSR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x190];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            return TFSR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return TFSR_EL1;
    else
        UNDEFINED;
```

MSR TFSR_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x190] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            TFSR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        TFSR_EL1 = X[t];
    else
        UNDEFINED;
```

MRS <Xt>, TFSR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            return TFSR_EL1;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return TFSR_EL2;
elsif PSTATE.EL == EL3 then
    return TFSR_EL2;
```

MSR TFSR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            TFSR_EL1 = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        TFSR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    TFSR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TFSR_EL2, Tag FaultFail Status Register (EL2)

The TFSR_EL2 characteristics are:

Purpose

Holds accumulated Tag Check FaultsFails occurring in EL2 thatwhich are not taken precisely.

Configuration

This register is present only when ARMv8.5-MemTag is implemented and ID_AA64PFR1_EL1.MTE != 0b0001. Otherwise, direct accesses to TFSR_EL2 are UNDEFINED.

RW fields in this register reset to architecturally UNKNOWN values.

Attributes

TFSR_EL2 is a 64-bit register.

Field descriptions

The TFSR_EL2 bit assignments are:



Bits [63:2]

Reserved, RES0.

TF1, bit [1]

Tag Check Fault.Fail. Asynchronously set to 1 when a Tag Check Faultfail using a virtual address with bit[<55] ==>== `0b1` occurs.

When HCR_EL2.E2H==`0b0`, this field is RES0.

This field resets to an architecturally UNKNOWN value.

TF0, bit [0]

Tag Check Fault.Fail. Asynchronously set to 1 when a Tag Check Faultfail using a virtual address with bit[<55] ==>== `0b0` occurs.

This field resets to an architecturally UNKNOWN value.

Accessing the TFSR_EL2

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL2 using the mnemonic TFSR_EL2 or TFSR_EL1 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

MRS <Xt>, TFSR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            return TFSR_EL1;
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return TFSR_EL2;
elsif PSTATE.EL == EL3 then
    return TFSR_EL2;
```

MSR TFSR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            TFSR_EL1 = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        TFSR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    TFSR_EL2 = X[t];
```

MRS <Xt>, TFSR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x190];
    else
        return TFSR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        return TFSR_EL2;
    else
        return TFSR_EL1;
elsif PSTATE.EL == EL3 then
    return TFSR_EL1;
```

```
MSR TFSR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x190] = X[t];
    else
        TFSR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        TFSR_EL2 = X[t];
    else
        TFSR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    TFSR_EL1 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TFSR_EL3, Tag FaultFail Status Register (EL3)

The TFSR_EL3 characteristics are:

Purpose

Holds accumulated Tag Check FaultsFails occurring in EL3 thatwhich are not taken precisely.

Configuration

This register is present only when ARMv8.5-MemTag is implemented and ID_AA64PFR1_EL1.MTE != 0b0001. Otherwise, direct accesses to TFSR_EL3 are UNDEFINED.

RW fields in this register reset to architecturally UNKNOWN values.

Attributes

TFSR_EL3 is a 64-bit register.

Field descriptions

The TFSR_EL3 bit assignments are:



Bits [63:1]

Reserved, RES0.

TF0, bit [0]

Tag Check Fault.Fail. Asynchronously set to 1 when a Tag Check Faultfail using a virtual address with bit[<55] ==>== 0b0 occurs.

This field resets to an architecturally UNKNOWN value.

Accessing the TFSR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, TFSR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return TFSR_EL3;
```

```
MSR TFSR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0101	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    TFSR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TFSRE0_EL1, Tag FaultFail Status Register (EL0).

The TFSRE0_EL1 characteristics are:

Purpose

Holds accumulated Tag Check FaultsFails occurring in EL0 thatwhich are not taken precisely.

Configuration

This register is present only when ARMv8.5-MemTag is implemented and ID_AA64PFR1_EL1.MTE != 0b0001. Otherwise, direct accesses to TFSRE0_EL1 are UNDEFINED.

RW fields in this register reset to architecturally UNKNOWN values.

Attributes

TFSRE0_EL1 is a 64-bit register.

Field descriptions

The TFSRE0_EL1 bit assignments are:



Bits [63:2]

Reserved, RES0.

TF1, bit [1]

Tag Check Fault.Fail. Asynchronously set to 1 when a Tag Check Faultfail using a virtual address with bit[<55] ==>== 0b1 occurs.

This field resets to an architecturally UNKNOWN value.

TF0, bit [0]

Tag Check Fault.Fail. Asynchronously set to 1 when a Tag Check Faultfail using a virtual address with bit[<55] ==>== 0b0 occurs.

This field resets to an architecturally UNKNOWN value.

Accessing the TFSRE0_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, TFSRE0_EL1
```

op0	op1	CRn	CRm	op2

0b11	0b000	0b0101	0b0110	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return TFSRE0_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return TFSRE0_EL1;
elsif PSTATE.EL == EL3 then
    return TFSRE0_EL1;
```

MSR TFSRE0_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0101	0b0110	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.ATA == '0' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        TFSRE0_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.ATA == '0' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        TFSRE0_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    TFSRE0_EL1 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI ALLE1, TLB Invalidate All, EL1

The TLBI ALLE1 characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 or stage 2 translation table entry, from any level of the translation table walk.
- If SCR_EL3.NS is 0 and the entry would be required to translate an address using the Secure EL1&0 translation regime.
- If SCR_EL3.NS is 1 and the entry would be required to translate an address using the Non-secure EL1&0 translation regime.

The invalidation applies to entries with any VMID.

The invalidation only applies to the PE that executes this System instruction.

Note

For the EL1&0 translation regimes, the invalidation applies to both global entries, and non-global entries with any ASID.

Configuration

There are no configuration notes.

Attributes

TLBI ALLE1 is a 64-bit System instruction.

Field descriptions

TLBI ALLE1 ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBI ALLE1 instruction

Accesses to this instruction use the following encodings:

```
TLBI ALLE1{, <Xt>}
```

op0	op1	CRn	CRm	op2	Rt
0b01	0b100	0b1000	0b0111	0b100	0b11111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_ALLE1();
elsif PSTATE.EL == EL3 then
    TLBI_ALLE1();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI ALLE1IS, TLB Invalidate All, EL1, Inner Shareable

The TLBI ALLE1IS characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 or stage 2 translation table entry, from any level of the translation table walk.
- If SCR_EL3.NS is 0 and the entry would be required to translate an address using the Secure EL1&0 translation regime.
- If SCR_EL3.NS is 1 and the entry would be required to translate an address using the Non-secure EL1&0 translation regime.

The invalidation applies to entries with any VMID.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Note

For the EL1&0 translation regimes, the invalidation applies to both global entries, and non-global entries with any ASID.

Configuration

There are no configuration notes.

Attributes

TLBI ALLE1IS is a 64-bit System instruction.

Field descriptions

TLBI ALLE1IS ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBI ALLE1IS instruction

Accesses to this instruction use the following encodings:

```
TLBI ALLE1IS{, <Xt>}
```

op0	op1	CRn	CRm	op2	Rt
0b01	0b100	0b1000	0b0011	0b100	0b11111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_ALLE1IS();
elsif PSTATE.EL == EL3 then
    TLBI_ALLE1IS();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI ALLE2, TLB Invalidate All, EL2

The TLBI ALLE2 characteristics are:

Purpose

If EL2 is implemented and enabled in the current Security state, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- If SCR_EL3.NS is 1 and the entry would be required to translate an address using the Non-secure EL2 or Non-secure EL2&0 translation regime.
- If SCR_EL3.NS is 0 and the entry would be required to translate an address using the Secure EL2 or Secure EL2&0 translation regime.

The invalidation only applies to the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI ALLE2 is a 64-bit System instruction.

Field descriptions

TLBI ALLE2 ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBI ALLE2 instruction

Accesses to this instruction use the following encodings:

```
TLBI ALLE2{, <Xt>}
```

op0	op1	CRn	CRm	op2	Rt
0b01	0b100	0b1000	0b0111	0b000	0b11111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_ALLE2();
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        UNDEFINED;
    else
        TLBI_ALLE2();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI ALLE2IS, TLB Invalidate All, EL2, Inner Shareable

The TLBI ALLE2IS characteristics are:

Purpose

If EL2 is implemented and enabled in the current Security state, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- If SCR_EL3.NS is 1 and the entry would be required to translate an address using the Non-secure EL2 or Non-secure EL2&0 translation regime.
- If SCR_EL3.NS is 0 and the entry would be required to translate an address using the Secure EL2 or Secure EL2&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI ALLE2IS is a 64-bit System instruction.

Field descriptions

TLBI ALLE2IS ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBI ALLE2IS instruction

Accesses to this instruction use the following encodings:

```
TLBI ALLE2IS{, <Xt>}
```

op0	op1	CRn	CRm	op2	Rt
0b01	0b100	0b1000	0b0011	0b000	0b11111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_ALLE2IS();
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        UNDEFINED;
    else
        TLBI_ALLE2IS();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI ALLE3, TLB Invalidate All, EL3

The TLBI ALLE3 characteristics are:

Purpose

If EL3 is implemented, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- The entry would be required to translate an address using the EL3 translation regime.

The invalidation applies to the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI ALLE3 is a 64-bit System instruction.

Field descriptions

TLBI ALLE3 ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBI ALLE3 instruction

Accesses to this instruction use the following encodings:

```
TLBI ALLE3{, <Xt>}
```

op0	op1	CRn	CRm	op2	Rt
0b01	0b110	0b1000	0b0111	0b000	0b11111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    TLBI_ALLE3();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI ALLE3IS, TLB Invalidate All, EL3, Inner Shareable

The TLBI ALLE3IS characteristics are:

Purpose

If EL3 is implemented, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- The entry would be required to translate an address using the EL3 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI ALLE3IS is a 64-bit System instruction.

Field descriptions

TLBI ALLE3IS ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBI ALLE3IS instruction

Accesses to this instruction use the following encodings:

```
TLBI ALLE3IS{, <Xt>}
```

op0	op1	CRn	CRm	op2	Rt
0b01	0b110	0b1000	0b0011	0b000	0b11111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    TLBI_ALLE3IS();
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI ASIDE1, TLB Invalidate by ASID, EL1

The TLBI ASIDE1 characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used for the specified ASID, and either:
  - Is from a level of lookup above the final level.
  - Is a non-global entry from the final level of lookup.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID, and would be required to translate an address using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate an address using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate an address using the EL1&0 translation regime.

The invalidation applies to the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI ASIDE1 is a 64-bit System instruction.

Field descriptions

The TLBI ASIDE1 input value bit assignments are:



ASID, bits [63:48]

ASID value to match. Any appropriate TLB entries that match the ASID values will be affected by this System instruction.

If the implementation supports 16 bits of ASID, but only 8 bits are being used in the context being invalidated, the upper bits are RES0.

Bits [47:0]

Reserved, RES0.

Executing the TLBI ASIDE1 instruction

Accesses to this instruction use the following encodings:

```
TLBI ASIDE1{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b1000	0b0111	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIASIDE1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FB == '1' then
        TLBI_ASIDE1IS(X[t]);
    else
        TLBI_ASIDE1(X[t]);
elsif PSTATE.EL == EL2 then
    TLBI_ASIDE1(X[t]);
elsif PSTATE.EL == EL3 then
    TLBI_ASIDE1(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI ASIDE1IS, TLB Invalidate by ASID, EL1, Inner Shareable

The TLBI ASIDE1IS characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used for the specified ASID, and either:
  - Is from a level of lookup above the final level.
  - Is a non-global entry from the final level of lookup.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID, and would be required to translate an address using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate an address using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate an address using the EL1&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI ASIDE1IS is a 64-bit System instruction.

Field descriptions

The TLBI ASIDE1IS input value bit assignments are:



ASID, bits [63:48]

ASID value to match. Any appropriate TLB entries that match the ASID values will be affected by this System instruction.

If the implementation supports 16 bits of ASID, but only 8 bits are being used in the context being invalidated, the upper bits are RES0.

Bits [47:0]

Reserved, RES0.

Executing the TLBI ASIDE1IS instruction

Accesses to this instruction use the following encodings:

```
TLBI ASIDE1IS{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b1000	0b0011	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIASIDE1IS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        TLBI_ASIDE1IS(X[t]);
elsif PSTATE.EL == EL2 then
    TLBI_ASIDE1IS(X[t]);
elsif PSTATE.EL == EL3 then
    TLBI_ASIDE1IS(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI IPAS2E1, TLB Invalidate by Intermediate Physical Address, Stage 2, EL1

The TLBI IPAS2E1 characteristics are:

Purpose

If EL2 is implemented and enabled in the current Security state, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 2 only translation table entry, from any level of the translation table walk.
- One of the following applies:
  - SCR_EL3.NS==1 and the entry would be required to translate the specified IPA using the Non-secure EL1&0 translation regime.
  - SCR_EL3.NS==0 and the entry would be required to translate the specified IPA using the Secure EL1&0 translation regime.
- The entry would be used with the current VMID.

The invalidation is not required to apply to caching structures that combine stage 1 and stage 2 translation table entries.

The invalidation applies to the PE that executes this System instruction.

For more information about the architectural requirements for this System instruction see 'Invalidation of TLB entries from stage 2 translations' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Configuration

There are no configuration notes.

Attributes

TLBI IPAS2E1 is a 64-bit System instruction.

Field descriptions

The TLBI IPAS2E1 input value bit assignments are:



NS, bit [63]

When ARMv8.4-SecEL2 is implemented:

Not Secure. Specifies the IPA space.

NS	Meaning
0b0	IPA is in the Secure IPA space.
0b1	IPA is in the Non-secure IPA space.

When the instruction is executed in Non-secure state, this field is RES0, and the instruction applies only to the Non-secure IPA space.

When ARMv8.4-SecEL2 is not implemented or is disabled in the current Security state, this field is RES0.

Otherwise:

Reserved, RES0.

Bits [62:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

Bits [43:40]

Reserved, RES0.

IPA[51:48], bits [39:36]

When ARMv8.2-LPA is implemented:

Extension to IPA[47:12]. See IPA[47:12] for more details.

Otherwise:

Reserved, RES0.

IPA[47:12], bits [35:0]

Bits[47:12] of the intermediate physical address to match. For implementations with fewer than 48 bits, the upper bits of this field are RES0.

When ARMv8.2-LPA is implemented, and 52-bit addresses and a 64KB translation granule are in use, IPA[51:48] form the upper part of the address value. Otherwise, IPA[51:48] are RES0.

Executing the TLBI IPAS2E1 instruction

Accesses to this instruction use the following encodings:

```
TLBI IPAS2E1{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b1000	0b0100	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_IPAS2E1(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        //no operation
    else
        TLBI_IPAS2E1(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI IPAS2E1IS, TLB Invalidate by Intermediate Physical Address, Stage 2, EL1, Inner Shareable

The TLBI IPAS2E1IS characteristics are:

Purpose

If EL2 is implemented and enabled in the current Security state, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 2 only translation table entry, from any level of the translation table walk.
- One of the following applies:
  - SCR_EL3.NS==1 and the entry would be required to translate the specified IPA using the Non-secure EL1&0 translation regime.
  - SCR_EL3.NS==0 and the entry would be required to translate the specified IPA using the Secure EL1&0 translation regime.
- The entry would be used with the current VMID.

The invalidation is not required to apply to caching structures that combine stage 1 and stage 2 translation table entries.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

For more information about the architectural requirements for this System instruction see 'Invalidation of TLB entries from stage 2 translations' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Configuration

There are no configuration notes.

Attributes

TLBI IPAS2E1IS is a 64-bit System instruction.

Field descriptions

The TLBI IPAS2E1IS input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
NS	RES0															TTL				RES0				IPA[51:48]				IPA[47:12]			
IPA[47:12]																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

NS, bit [63]

When ARMv8.4-SecEL2 is implemented:

Not Secure. Specifies the IPA space.

NS	Meaning
0b0	IPA is in the Secure IPA space.
0b1	IPA is in the Non-secure IPA space.

When the instruction is executed in Non-secure state, this field is RES0, and the instruction applies only to the Non-secure IPA space.

When ARMv8.4-SecEL2 is not implemented or is disabled in the current Security state, this field is RES0.

Otherwise:

Reserved, RES0.

Bits [62:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

Bits [43:40]

Reserved, RES0.

IPA[51:48], bits [39:36]

When ARMv8.2-LPA is implemented:

Extension to IPA[47:12]. See IPA[47:12] for more details.

Otherwise:

Reserved, RES0.

IPA[47:12], bits [35:0]

Bits[47:12] of the intermediate physical address to match. For implementations with fewer than 48 bits, the upper bits of this field are RES0.

When ARMv8.2-LPA is implemented, and 52-bit addresses and a 64KB translation granule are in use, IPA[51:48] form the upper part of the address value. Otherwise, IPA[51:48] are RES0.

Executing the TLBI IPAS2E1IS instruction

Accesses to this instruction use the following encodings:

```
TLBI IPAS2E1IS{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b1000	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_IPAS2E1IS(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        //no operation
    else
        TLBI_IPAS2E1IS(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI IPAS2LE1, TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1

The TLBI IPAS2LE1 characteristics are:

Purpose

If EL2 is implemented and enabled in the current Security state, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 2 only translation table entry, from the final level of the translation table walk.
- One of the following applies:
  - SCR_EL3.NS==1 and the entry would be required to translate the specified IPA using the Non-secure EL1&0 translation regime.
  - SCR_EL3.NS==0 and the entry would be required to translate the specified IPA using the Secure EL1&0 translation regime.
- The entry would be used with the current VMID.

The invalidation is not required to apply to caching structures that combine stage 1 and stage 2 translation table entries.

The invalidation applies to the PE that executes this System instruction.

For more information about the architectural requirements for this System instruction see 'Invalidation of TLB entries from stage 2 translations' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Configuration

There are no configuration notes.

Attributes

TLBI IPAS2LE1 is a 64-bit System instruction.

Field descriptions

The TLBI IPAS2LE1 input value bit assignments are:



NS, bit [63]

When ARMv8.4-SecEL2 is implemented:

Not Secure. Specifies the IPA space.

NS	Meaning
0b0	IPA is in the Secure IPA space.
0b1	IPA is in the Non-secure IPA space.

When the instruction is executed in Non-secure state, this field is RES0, and the instruction applies only to the Non-secure IPA space.

When ARMv8.4-SecEL2 is not implemented or is disabled in the current Security state, this field is RES0.

Otherwise:

Reserved, RES0.

Bits [62:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

Bits [43:40]

Reserved, RES0.

IPA[51:48], bits [39:36]

When ARMv8.2-LPA is implemented:

Extension to IPA[47:12]. See IPA[47:12] for more details.

Otherwise:

Reserved, RES0.

IPA[47:12], bits [35:0]

Bits[47:12] of the intermediate physical address to match. For implementations with fewer than 48 bits, the upper bits of this field are RES0.

When ARMv8.2-LPA is implemented, and 52-bit addresses and a 64KB translation granule are in use, IPA[51:48] form the upper part of the address value. Otherwise, IPA[51:48] are RES0.

Executing the TLBI IPAS2LE1 instruction

Accesses to this instruction use the following encodings:

```
TLBI IPAS2LE1{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b1000	0b0100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_IPAS2LE1(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        //no operation
    else
        TLBI_IPAS2LE1(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI IPAS2LE1IS, TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Inner Shareable

The TLBI IPAS2LE1IS characteristics are:

Purpose

If EL2 is implemented and enabled in the current Security state, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 2 only translation table entry, from the final level of the translation table walk.
- One of the following applies:
  - SCR_EL3.NS==1 and the entry would be required to translate the specified IPA using the Non-secure EL1&0 translation regime.
  - SCR_EL3.NS==0 and the entry would be required to translate the specified IPA using the Secure EL1&0 translation regime.
- The entry would be used with the current VMID.

The invalidation is not required to apply to caching structures that combine stage 1 and stage 2 translation table entries.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

For more information about the architectural requirements for this System instruction see 'Invalidation of TLB entries from stage 2 translations' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Configuration

There are no configuration notes.

Attributes

TLBI IPAS2LE1IS is a 64-bit System instruction.

Field descriptions

The TLBI IPAS2LE1IS input value bit assignments are:



NS, bit [63]

When ARMv8.4-SecEL2 is implemented:

Not Secure. Specifies the IPA space.

NS	Meaning
0b0	IPA is in the Secure IPA space.
0b1	IPA is in the Non-secure IPA space.

When the instruction is executed in Non-secure state, this field is RES0, and the instruction applies only to the Non-secure IPA space.

When ARMv8.4-SecEL2 is not implemented or is disabled in the current Security state, this field is RES0.

Otherwise:

Reserved, RES0.

Bits [62:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

Bits [43:40]

Reserved, RES0.

IPA[51:48], bits [39:36]

When ARMv8.2-LPA is implemented:

Extension to IPA[47:12]. See IPA[47:12] for more details.

Otherwise:

Reserved, RES0.

IPA[47:12], bits [35:0]

Bits[47:12] of the intermediate physical address to match. For implementations with fewer than 48 bits, the upper bits of this field are RES0.

When ARMv8.2-LPA is implemented, and 52-bit addresses and a 64KB translation granule are in use, IPA[51:48] form the upper part of the address value. Otherwise, IPA[51:48] are RES0.

Executing the TLBI IPAS2LE1IS instruction

Accesses to this instruction use the following encodings:

```
TLBI IPAS2LE1IS{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b1000	0b0000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_IPAS2LE1IS(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        //no operation
    else
        TLBI_IPAS2LE1IS(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VAAE1, TLB Invalidate by VA, All ASID, EL1

The TLBI VAAE1 characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID and would be required to translate the specified VA using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate the specified VA using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate the specified VA using the EL1&0 translation regime.

The invalidation applies to the PE that executes this System instruction.

Note

For the EL1&0 and EL2&0 translation regimes, the invalidation applies to both global entries, and non-global entries with any ASID.

Configuration

There are no configuration notes.

Attributes

TLBI VAAE1 is a 64-bit System instruction.

Field descriptions

The TLBI VAAE1 input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																TTL				VA[55:12]											
VA[55:12]																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the VA will be affected by this System instruction, regardless of the ASID.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VAAE1 instruction

Accesses to this instruction use the following encodings:

```
TLBI VAAE1{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b1000	0b0111	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIVAAE1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FB == '1' then
        TLBI_VAAE1IS(X[t]);
    else
        TLBI_VAAE1(X[t]);
elsif PSTATE.EL == EL2 then
    TLBI_VAAE1(X[t]);
elsif PSTATE.EL == EL3 then
    TLBI_VAAE1(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VAAE1IS, TLB Invalidate by VA, All ASID, EL1, Inner Shareable

The TLBI VAAE1IS characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID and would be required to translate the specified VA using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate the specified VA using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate the specified VA using the EL1&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Note

From Armv8.4, when a TLB maintenance instruction is generated to the Secure EL1&0 translation regime and is defined to pass a VMID argument, or would be defined to pass a VMID argument if SCR_EL3.EEL2==1, then:

- A PE with SCR_EL3.EEL2==1 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==0.
- A PE with SCR_EL3.EEL2==0 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==1.
- A PE is architecturally required to invalidate all relevant entries in the Secure EL1&0 translation of a System MMU in the same required shareability domain with a VMID of 0.

For the EL1&0 and EL2&0 translation regimes, the invalidation applies to both global entries, and non-global entries with any ASID.

Configuration

There are no configuration notes.

Attributes

TLBI VAAE1IS is a 64-bit System instruction.

Field descriptions

The TLBI VAAE1IS input value bit assignments are:



Bits [63:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the VA will be affected by this System instruction, regardless of the ASID.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VAAE1IS instruction

Accesses to this instruction use the following encodings:

```
TLBI VAAE1IS{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b1000	0b0011	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIVAAE1IS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        TLBI_VAAE1IS(X[t]);
elsif PSTATE.EL == EL2 then
    TLBI_VAAE1IS(X[t]);
elsif PSTATE.EL == EL3 then
    TLBI_VAAE1IS(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VAALE1, TLB Invalidate by VA, All ASID, Last level, EL1

The TLBI VAALE1 characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from the final level of the translation table walk.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID and would be required to translate the specified VA using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate the specified VA using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate the specified VA using the EL1&0 translation regime.

The invalidation applies to the PE that executes this System instruction.

Note

For the EL1&0 and EL2&0 translation regimes, the invalidation applies to both global entries, and non-global entries with any ASID.

Configuration

There are no configuration notes.

Attributes

TLBI VAALE1 is a 64-bit System instruction.

Field descriptions

The TLBI VAALE1 input value bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																TTL				VA[55:12]											
VA[55:12]																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the VA will be affected by this System instruction, regardless of the ASID.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VAALE1 instruction

Accesses to this instruction use the following encodings:

```
TLBI VAALE1{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b1000	0b0111	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIVAALE1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FB == '1' then
        TLBI_VAALE1IS(X[t]);
    else
        TLBI_VAALE1(X[t]);
elsif PSTATE.EL == EL2 then
    TLBI_VAALE1(X[t]);
elsif PSTATE.EL == EL3 then
    TLBI_VAALE1(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VAALE1IS, TLB Invalidate by VA, All ASID, Last Level, EL1, Inner Shareable

The TLBI VAALE1IS characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from the final level of the translation table walk.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID and would be required to translate the specified VA using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate the specified VA using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate the specified VA using the EL1&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Note

From Armv8.4, when a TLB maintenance instruction is generated to the Secure EL1&0 translation regime and is defined to pass a VMID argument, or would be defined to pass a VMID argument if SCR_EL3.EEL2==1, then:

- A PE with SCR_EL3.EEL2==1 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==0.
- A PE with SCR_EL3.EEL2==0 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==1.
- A PE is architecturally required to invalidate all relevant entries in the Secure EL1&0 translation of a System MMU in the same required shareability domain with a VMID of 0.

For the EL1&0 and EL2&0 translation regimes, the invalidation applies to both global entries, and non-global entries with any ASID.

Configuration

There are no configuration notes.

Attributes

TLBI VAALE1IS is a 64-bit System instruction.

Field descriptions

The TLBI VAALE1IS input value bit assignments are:



Bits [63:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the VA will be affected by this System instruction, regardless of the ASID.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VAALE1IS instruction

Accesses to this instruction use the following encodings:

```
TLBI VAALE1IS{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b1000	0b0011	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIVAALE1IS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        TLBI_VAALE1IS(X[t]);
elsif PSTATE.EL == EL2 then
    TLBI_VAALE1IS(X[t]);
elsif PSTATE.EL == EL3 then
    TLBI_VAALE1IS(X[t]);
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VAE1, TLB Invalidate by VA, EL1

The TLBI VAE1 characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified VA, and one of the following applies:
  - The entry is from a level of lookup above the final level and matches the specified ASID.
  - The entry is a global entry from the final level of lookup.
  - The entry is a non-global entry from the final level of lookup that matches the specified ASID.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID and would be required to translate the specified VA using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate the specified VA using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate the specified VA using the EL1&0 translation regime.

The invalidation applies to the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI VAE1 is a 64-bit System instruction.

Field descriptions

The TLBI VAE1 input value bit assignments are:



ASID, bits [63:48]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

If the implementation supports 16 bits of ASID, but only 8 bits are being used in the context being invalidated, the upper bits are RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VAE1 instruction

Accesses to this instruction use the following encodings:

```
TLBI VAE1{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b1000	0b0111	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIVAE1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FB == '1' then
        TLBI_VAE1IS(X[t]);
    else
        TLBI_VAE1(X[t]);
elsif PSTATE.EL == EL2 then
    TLBI_VAE1(X[t]);
elsif PSTATE.EL == EL3 then
    TLBI_VAE1(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VAE1IS, TLB Invalidate by VA, EL1, Inner Shareable

The TLBI VAE1IS characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified VA, and one of the following applies:
  - The entry is from a level of lookup above the final level and matches the specified ASID.
  - The entry is a global entry from the final level of lookup.
  - The entry is a non-global entry from the final level of lookup that matches the specified ASID.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID and would be required to translate the specified VA using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate the specified VA using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate the specified VA using the EL1&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Note

From Armv8.4, when a TLB maintenance instruction is generated to the Secure EL1&0 translation regime and is defined to pass a VMID argument, or would be defined to pass a VMID argument if SCR_EL3.EEL2==1, then:

- A PE with SCR_EL3.EEL2==1 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==0.
- A PE with SCR_EL3.EEL2==0 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==1.
- A PE is architecturally required to invalidate all relevant entries in the Secure EL1&0 translation of a System MMU in the same required shareability domain with a VMID of 0.

Configuration

There are no configuration notes.

Attributes

TLBI VAE1IS is a 64-bit System instruction.

Field descriptions

The TLBI VAE1IS input value bit assignments are:



ASID, bits [63:48]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

If the implementation supports 16 bits of ASID, but only 8 bits are being used in the context being invalidated, the upper bits are RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VAE1IS instruction

Accesses to this instruction use the following encodings:

```
TLBI VAE1IS{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b1000	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIVAE1IS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        TLBI_VAE1IS(X[t]);
elsif PSTATE.EL == EL2 then
    TLBI_VAE1IS(X[t]);
elsif PSTATE.EL == EL3 then
    TLBI_VAE1IS(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VAE2, TLB Invalidate by VA, EL2

The TLBI VAE2 characteristics are:

Purpose

When EL2 is implemented and enabled in the current Security state, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be required to translate the specified VA using the EL2 or the EL2&0 translation regime.
- If HCR_EL2.E2H == 0, the entry is from any level of the translation table walk.
- If HCR_EL2.E2H == 1 one of the following applies:
  - The entry is from a level of the translation table walk above the final level and matches the specified ASID.
  - The entry is a global entry from the final level of the translation table walk.
  - The entry is a non-global entry from the final level of the translation table walk and matches the specified ASID.

The invalidation applies to the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI VAE2 is a 64-bit System instruction.

Field descriptions

The TLBI VAE2 input value bit assignments are:



ASID, bits [63:48]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

If the implementation supports 16 bits of ASID, but only 8 bits are being used in the context being invalidated, the upper bits are RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VAE2 instruction

Accesses to this instruction use the following encodings:

```
TLBI VAE2{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b1000	0b0111	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_VAE2(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        UNDEFINED;
    else
        TLBI_VAE2(X[t]);
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VAE2IS, TLB Invalidate by VA, EL2, Inner Shareable

The TLBI VAE2IS characteristics are:

Purpose

When EL2 is implemented and enabled in the current Security state, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be required to translate the specified VA using the EL2 or the EL2&0 translation regime.
- If HCR_EL2.E2H == 0, the entry is from any level of the translation table walk.
- If HCR_EL2.E2H == 1 one of the following applies:
  - The entry is from a level of the translation table walk above the final level and matches the specified ASID.
  - The entry is a global entry from the final level of the translation table walk.
  - The entry is a non-global entry from the final level of the translation table walk and matches the specified ASID.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI VAE2IS is a 64-bit System instruction.

Field descriptions

The TLBI VAE2IS input value bit assignments are:



ASID, bits [63:48]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

If the implementation supports 16 bits of ASID, but only 8 bits are being used in the context being invalidated, the upper bits are RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VAE2IS instruction

Accesses to this instruction use the following encodings:

```
TLBI VAE2IS{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b1000	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_VAE2IS(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        UNDEFINED;
    else
        TLBI_VAE2IS(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VAE3, TLB Invalidate by VA, EL3

The TLBI VAE3 characteristics are:

Purpose

If EL3 is implemented, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- The entry would be used to translate the specified VA using the EL3 translation regime.

The invalidation applies to the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI VAE3 is a 64-bit System instruction.

Field descriptions

The TLBI VAE3 input value bit assignments are:



Bits [63:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VAE3 instruction

Accesses to this instruction use the following encodings:

```
TLBI VAE3{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b110	0b1000	0b0111	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    TLBI_VAE3(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VAE3IS, TLB Invalidate by VA, EL3, Inner Shareable

The TLBI VAE3IS characteristics are:

Purpose

If EL3 is implemented, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- The entry would be used to translate the specified VA using the EL3 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI VAE3IS is a 64-bit System instruction.

Field descriptions

The TLBI VAE3IS input value bit assignments are:



Bits [63:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VAE3IS instruction

Accesses to this instruction use the following encodings:

```
TLBI VAE3IS{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b110	0b1000	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    TLBI_VAE3IS(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VALE1, TLB Invalidate by VA, Last level, EL1

The TLBI VALE1 characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified VA, and one of the following applies:
  - The entry is a global entry from the final level of lookup.
  - The entry is a non-global entry from the final level of lookup that matches the specified ASID.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID and would be required to translate the specified VA using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate the specified VA using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate the specified VA using the EL1&0 translation regime.

The invalidation applies to the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI VALE1 is a 64-bit System instruction.

Field descriptions

The TLBI VALE1 input value bit assignments are:



ASID, bits [63:48]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

If the implementation supports 16 bits of ASID, but only 8 bits are being used in the context being invalidated, the upper bits are RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VALE1 instruction

Accesses to this instruction use the following encodings:

```
TLBI VALE1{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b1000	0b0111	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIVALE1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FB == '1' then
        TLBI_VALE1IS(X[t]);
    else
        TLBI_VAAE1(X[t]);
elsif PSTATE.EL == EL2 then
    TLBI_VAAE1(X[t]);
elsif PSTATE.EL == EL3 then
    TLBI_VAAE1(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VALE1IS, TLB Invalidate by VA, Last level, EL1, Inner Shareable

The TLBI VALE1IS characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified VA, and one of the following applies:
  - The entry is a global entry from the final level of lookup.
  - The entry is a non-global entry from the final level of lookup that matches the specified ASID.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID and would be required to translate the specified VA using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate the specified VA using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate the specified VA using the EL1&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Note

From Armv8.4, when a TLB maintenance instruction is generated to the Secure EL1&0 translation regime and is defined to pass a VMID argument, or would be defined to pass a VMID argument if SCR_EL3.EEL2==1, then:

- A PE with SCR_EL3.EEL2==1 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==0.
- A PE with SCR_EL3.EEL2==0 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==1.
- A PE is architecturally required to invalidate all relevant entries in the Secure EL1&0 translation of a System MMU in the same required shareability domain with a VMID of 0.

Configuration

There are no configuration notes.

Attributes

TLBI VALE1IS is a 64-bit System instruction.

Field descriptions

The TLBI VALE1IS input value bit assignments are:



ASID, bits [63:48]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

If the implementation supports 16 bits of ASID, but only 8 bits are being used in the context being invalidated, the upper bits are RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.

- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VALE1IS instruction

Accesses to this instruction use the following encodings:

```
TLBI VALE1IS{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b000	0b1000	0b0011	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIVALE1IS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        TLBI_VALE1IS(X[t]);
elsif PSTATE.EL == EL2 then
    TLBI_VALE1IS(X[t]);
elsif PSTATE.EL == EL3 then
    TLBI_VALE1IS(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VALE2, TLB Invalidate by VA, Last level, EL2

The TLBI VALE2 characteristics are:

Purpose

When EL2 is implemented and enabled in the current Security state, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified VA using the EL2 or EL2&0 translation regime.
- If HCR_EL2.E2H == 0, the entry is from the final level of the translation table walk.
- If HCR_EL2.E2H == 1, one of the following applies:
  - The entry is a global entry from the final level of the translation table walk.
  - The entry is a non-global entry from the final level of translation table walk that matches the specified ASID.

The invalidation applies to the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI VALE2 is a 64-bit System instruction.

Field descriptions

The TLBI VALE2 input value bit assignments are:



ASID, bits [63:48]

When HCR_EL2.E2H == 1:

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

If the implementation supports 16 bits of ASID, but only 8 bits are being used in the context being invalidated, the upper bits are RES0.

Otherwise:

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VALE2 instruction

Accesses to this instruction use the following encodings:

```
TLBI VALE2{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b1000	0b0111	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_VALE2(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        UNDEFINED;
    else
        TLBI_VALE2(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VALE2IS, TLB Invalidate by VA, Last level, EL2, Inner Shareable

The TLBI VALE2IS characteristics are:

Purpose

When EL2 is implemented and enabled in the current Security state, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified VA using the EL2 or EL2&0 translation regime.
- If HCR_EL2.E2H == 0, the entry is from the final level of the translation table walk.
- If HCR_EL2.E2H == 1, one of the following applies:
  - The entry is a global entry from the final level of the translation table walk.
  - The entry is a non-global entry from the final level of translation table walk that matches the specified ASID.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI VALE2IS is a 64-bit System instruction.

Field descriptions

The TLBI VALE2IS input value bit assignments are:



ASID, bits [63:48]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

If the implementation supports 16 bits of ASID, but only 8 bits are being used in the context being invalidated, the upper bits are RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VALE2IS instruction

Accesses to this instruction use the following encodings:

```
TLBI VALE2IS{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b100	0b1000	0b0011	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_VALE2IS(X[t]);
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        UNDEFINED;
    else
        TLBI_VALE2IS(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VALE3, TLB Invalidate by VA, Last level, EL3

The TLBI VALE3 characteristics are:

Purpose

If EL3 is implemented, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from the final level of the translation table walk.
- The entry would be used to translate the specified VA using the EL3 translation regime.

The invalidation applies to the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI VALE3 is a 64-bit System instruction.

Field descriptions

The TLBI VALE3 input value bit assignments are:



Bits [63:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VALE3 instruction

Accesses to this instruction use the following encodings:

```
TLBI VALE3{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b110	0b1000	0b0111	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    TLBI_VALE3(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VALE3IS, TLB Invalidate by VA, Last level, EL3, Inner Shareable

The TLBI VALE3IS characteristics are:

Purpose

If EL3 is implemented, invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from the final level of the translation table walk.
- The entry would be used to translate the specified VA using the EL3 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

There are no configuration notes.

Attributes

TLBI VALE3IS is a 64-bit System instruction.

Field descriptions

The TLBI VALE3IS input value bit assignments are:



Bits [63:48]

Reserved, RES0.

TTL, bits [47:44]

When ARMv8.4-TTL is implemented:

Translation Table Level. Indicates the level of the page table walk that holds the leaf entry for the address being invalidated.

TTL	Meaning
0b00xx	No information supplied as to the translation table level. Hardware must assume that the entry can be from any level. In this case, TTL<1:0> is RES0.
0b01xx	The entry comes from a 4KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.
0b10xx	The entry comes from a 16KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Reserved. Treat as if TTL<3:2> is 0b00. 0b10 : Level 2. 0b11 : Level 3.
0b11xx	The entry comes from a 64KB translation granule. The level of walk for the leaf level 0bxx is encoded as: 0b00 : Reserved. Treat as if TTL<3:2> is 0b00. 0b01 : Level 1. 0b10 : Level 2. 0b11 : Level 3.

If an incorrect value of the TTL field is specified for the entry being invalidated by the instruction, then no entries are required by the architecture to be invalidated from the TLB.

Otherwise:

Reserved, RES0.

VA[55:12], bits [43:0]

Bits[55:12] of the virtual address to match. Any appropriate TLB entries that match the ASID value (if appropriate) and VA will be affected by this System instruction.

If the TLB maintenance instructions are targeting a translation regime that is using AArch32, and so has a VA of only 32 bits, then the software must treat bits[55:32] as RES0.

The treatment of the low-order bits of this field depends on the translation granule size, as follows:

- Where a 4KB translation granule is being used, all bits are valid and used for the invalidation.
- Where a 16KB translation granule is being used, bits [1:0] of this field are RES0 and ignored when the instruction is executed, because VA[13:12] have no effect on the operation of the instruction.
- Where a 64KB translation granule is being used, bits [3:0] of this field are RES0 and ignored when the instruction is executed, because VA[15:12] have no effect on the operation of the instruction.

Executing the TLBI VALE3IS instruction

Accesses to this instruction use the following encodings:

```
TLBI VALE3IS{, <Xt>}
```

op0	op1	CRn	CRm	op2
0b01	0b110	0b1000	0b0011	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    TLBI_VALE3IS(X[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VMALLE1, TLB Invalidate by VMID, All at stage 1, EL1

The TLBI VMALLE1 characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID and would be required to translate the specified VA using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate the specified VA using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate the specified VA using the EL1&0 translation regime.

The invalidation applies to the PE that executes this System instruction.

Note

For the EL1&0 translation regimes, the invalidation applies to both global entries, and non-global entries with any ASID.

Configuration

There are no configuration notes.

Attributes

TLBI VMALLE1 is a 64-bit System instruction.

Field descriptions

TLBI VMALLE1 ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBI VMALLE1 instruction

Accesses to this instruction use the following encodings:

```
TLBI VMALLE1{, <Xt>}
```

op0	op1	CRn	CRm	op2	Rt
0b01	0b000	0b1000	0b0111	0b000	0b11111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIVMALLE1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FB == '1' then
        TLBI_VMALLE1IS();
    else
        TLBI_VMALLE1();
elsif PSTATE.EL == EL2 then
    TLBI_VMALLE1();
elsif PSTATE.EL == EL3 then
    TLBI_VMALLE1();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VMALLE1IS, TLB Invalidate by VMID, All at stage 1, EL1, Inner Shareable

The TLBI VMALLE1IS characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- When EL2 is implemented and enabled in the Security state described by the current value of SCR_EL3.NS:
  - If HCR_EL2.{E2H, TGE} is not {1, 1}, the entry would be used with the current VMID and would be required to translate the specified VA using the EL1&0 translation regime.
  - If HCR_EL2.{E2H, TGE} is {1, 1}, the entry would be required to translate the specified VA using the EL2&0 translation regime.
- When EL2 is not implemented or is disabled in the current Security state, the entry would be required to translate the specified VA using the EL1&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Note

From Armv8.4, when a TLB maintenance instruction is generated to the Secure EL1&0 translation regime and is defined to pass a VMID argument, or would be defined to pass a VMID argument if SCR_EL3.EEL2==1, then:

- A PE with SCR_EL3.EEL2==1 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==0.
- A PE with SCR_EL3.EEL2==0 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==1.
- A PE is architecturally required to invalidate all relevant entries in the Secure EL1&0 translation of a System MMU in the same required shareability domain with a VMID of 0.

For the EL1&0 translation regimes, the invalidation applies to both global entries, and non-global entries with any ASID.

Configuration

There are no configuration notes.

Attributes

TLBI VMALLE1IS is a 64-bit System instruction.

Field descriptions

TLBI VMALLE1IS ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBI VMALLE1IS instruction

Accesses to this instruction use the following encodings:

```
TLBI VMALLE1IS{, <Xt>}
```

op0	op1	CRn	CRm	op2	Rt
0b01	0b000	0b1000	0b0011	0b000	0b11111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGITR_EL2.TLBIVMALLE1IS == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        TLBI_VMALLE1IS();
elsif PSTATE.EL == EL2 then
    TLBI_VMALLE1IS();
elsif PSTATE.EL == EL3 then
    TLBI_VMALLE1IS();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VMALLS12E1, TLB Invalidate by VMID, All at Stage 1 and 2, EL1

The TLBI VMALLS12E1 characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 or stage 2 translation table entry, from any level of the translation table walk.
- If SCR_EL3.NS is 0, then
  - The entry would be required to translate an address using the Secure EL1&0 translation regime.
  - If ARMv8.4-SecEL2 is implemented and enabled, the entry would be used with the current VMID.
- If SCR_EL3.NS is 1, then:
  - The entry would be required to translate an address using the Non-secure EL1&0 translation regime.
  - If Non-secure EL2 is implemented, the entry would be used with the current VMID.

The invalidation applies to the PE that executes this System instruction.

Note

For the EL1&0 translation regimes, the invalidation applies to both global entries, and non-global entries with any ASID.

Configuration

There are no configuration notes.

Attributes

TLBI VMALLS12E1 is a 64-bit System instruction.

Field descriptions

TLBI VMALLS12E1 ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBI VMALLS12E1 instruction

Accesses to this instruction use the following encodings:

```
TLBI VMALLS12E1{, <Xt>}
```

op0	op1	CRn	CRm	op2	Rt
0b01	0b100	0b1000	0b0111	0b110	0b11111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_VMALLS12E1();
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        TLBI_VMALLE1();
    else
        TLBI_VMALLS12E1();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBI VMALLS12E1IS, TLB Invalidate by VMID, All at Stage 1 and 2, EL1, Inner Shareable

The TLBI VMALLS12E1IS characteristics are:

Purpose

Invalidates cached copies of translation table entries from TLBs that meet all the following requirements:

- The entry is a stage 1 or stage 2 translation table entry, from any level of the translation table walk.
- If SCR_EL3.NS is 0, then
  - The entry would be required to translate an address using the Secure EL1&0 translation regime.
  - If ARMv8.4-SecEL2 is implemented and enabled, the entry would be used with the current VMID.
- If SCR_EL3.NS is 1, then:
  - The entry would be required to translate an address using the Non-secure EL1&0 translation regime.
  - If Non-secure EL2 is implemented, the entry would be used with the current VMID.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Note

From Armv8.4, when a TLB maintenance instruction is generated to the Secure EL1&0 translation regime and is defined to pass a VMID argument, or would be defined to pass a VMID argument if SCR_EL3.EEL2==1, then:

- A PE with SCR_EL3.EEL2==1 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==0.
- A PE with SCR_EL3.EEL2==0 is not architecturally required to invalidate any entries in the Secure EL1&0 translation of a PE in the same required shareability domain with SCR_EL3.EEL2==1.
- A PE is architecturally required to invalidate all relevant entries in the Secure EL1&0 translation of a System MMU in the same required shareability domain with a VMID of 0.

For the EL1&0 translation regimes, the invalidation applies to both global entries, and non-global entries with any ASID.

Configuration

There are no configuration notes.

Attributes

TLBI VMALLS12E1IS is a 64-bit System instruction.

Field descriptions

TLBI VMALLS12E1IS ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBI VMALLS12E1IS instruction

Accesses to this instruction use the following encodings:

```
TLBI VMALLS12E1IS{, <Xt>}
```

op0	op1	CRn	CRm	op2	Rt
0b01	0b100	0b1000	0b0011	0b110	0b11111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBI_VMALLS12E1IS();
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        TLBI_VMALLE1IS();
    else
        TLBI_VMALLS12E1IS();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TPIDR_EL3, EL3 Software Thread ID Register

The TPIDR_EL3 characteristics are:

Purpose

Provides a location where software executing at EL3 can store thread identifying information, for OS management purposes.

The PE makes no use of this register.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to TPIDR_EL3 are UNDEFINED.

Attributes

TPIDR_EL3 is a 64-bit register.

Field descriptions

The TPIDR_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Thread ID																															
Thread ID																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Thread ID. Thread identifying information stored by software running at this Exception level.

This field resets to an architecturally UNKNOWN value.

Accessing the TPIDR_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, TPIDR_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1101	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return TPIDR_EL3;
```

```
MSR TPIDR_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b1101	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    TPIDR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TRFCR_EL1, Trace Filter Control Register (EL1)

The TRFCR_EL1 characteristics are:

Purpose

Provides EL1 controls for Trace.

Configuration

AArch64 System register TRFCR_EL1 bits [31:0] are architecturally mapped to AArch32 System register TRFCR[31:0] .

This register is present only when ARMv8.4-Trace is implemented. Otherwise, direct accesses to TRFCR_EL1 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

TRFCR_EL1 is a 64-bit register.

Field descriptions

The TRFCR_EL1 bit assignments are:



Bits [63:7]

Reserved, RES0.

TS, bits [6:5]

Timestamp Control

TS	Meaning	Applies when
0b01	Virtual timestamp. The traced timestamp is the physical counter value, minus the value of CNTVOFF_EL2.	
0b10	Guest Physical timestamp. The traced timestamp is the physical counter value, minus the value of CNTPOFF_EL2.	When ARMv8.6-ECV is implemented
0b11	Physical timestamp. The traced timestamp is the physical counter value.	

All other values are reserved

This field is ignored if any of the following are true:

- SelfHostedTraceEnabled() == FALSE.

- EL2 is implemented and TRFCR_EL2.TS != 0b00.

IfWhen EL2 is implemented and enabled in the current Security state, the physical counter uses a fixed physical offset of zero if either of the following are true: ARMv8.6-ECV is implemented, and EL2 is implemented and enabled in the current Security state, the physical counter uses a fixed physical offset of zero if any of the following are true:

- CNTHCTL_EL2.ECV is 0.
- SCR_EL3.ECVEn is 0.
- HCR_EL2.{E2H, TGE} is {1, 1}.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bits [4:2]

Reserved, RES0.

E1TRE, bit [1]

EL1 Trace Enable.

E1TRE	Meaning
0b0	Trace is prohibited at EL1.
0b1	Trace is allowed at EL1.

This field is ignored if SelfHostedTraceEnabled() == FALSE.

On a Warm reset, this field resets to 0.

E0TRE, bit [0]

EL0 Trace Enable.

E0TRE	Meaning
0b0	Trace is prohibited at EL0.
0b1	Trace is allowed at EL0.

This field is ignored if any of the following are true:

- SelfHostedTraceEnabled() == FALSE.
- EL2 is implemented and enabled in the current Security state and HCR_EL2.TGE == 1.

On a Warm reset, this field resets to 0.

Accessing the TRFCR_EL1

Accesses to this register use the following encodings:

```
MRS <Xt>, TRFCR_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TTRF == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x880];
    else
        return TRFCR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        return TRFCR_EL2;
    else
        return TRFCR_EL1;
elsif PSTATE.EL == EL3 then
    return TRFCR_EL1;
```

MSR TRFCR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.TRFCR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TTRF == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x880] = X[t];
    else
        TRFCR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        TRFCR_EL2 = X[t];
    else
        TRFCR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    TRFCR_EL1 = X[t];
```

MRS <Xt>, TRFCR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x880];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            return TRFCR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return TRFCR_EL1;
    else
        UNDEFINED;
```

MSR TRFCR_EL12, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b101	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x880] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
            AArch64.SystemAccessTrap(EL3, 0x18);
        else
            TRFCR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        TRFCR_EL1 = X[t];
    else
        UNDEFINED;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TRFCR_EL2, Trace Filter Control Register (EL2)

The TRFCR_EL2 characteristics are:

Purpose

Provides EL2 controls for Trace.

Configuration

AArch64 System register TRFCR_EL2 bits [31:0] are architecturally mapped to AArch32 System register HTRFCR[31:0] .

This register is present only when ARMv8.4-Trace is implemented. Otherwise, direct accesses to TRFCR_EL2 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch64. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

TRFCR_EL2 is a 64-bit register.

Field descriptions

The TRFCR_EL2 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																									TS		RES0	CX	RES0	E2TRE	E0HTRE

Bits [63:7]

Reserved, RES0.

TS, bits [6:5]

Timestamp Control. Controls which timebase is used for trace timestamps.

TS	Meaning	Applies when
0b00	Timestamp controlled by TRFCR_EL1.TS or TRFCR.TS.	
0b01	Virtual timestamp. The traced timestamp is the physical counter value, minus the value of CNTVOFF_EL2.	
0b10	Guest Physical timestamp. The traced timestamp is the physical counter value, minus the value of CNTPOFF_EL2.	When ARMv8.6-ECV is implemented
0b11	Physical timestamp. The traced timestamp is the physical counter value.	

All other values are reserved.

This field is ignored if SelfHostedTraceEnabled() == FALSE.

IfWhen EL2 is implemented and enabled in the current Security state, the physical counter uses a fixed physical offset of zero if either of the following are true: ARMv8.6-ECV is implemented, and EL2 is implemented and enabled in the current Security state, the physical counter uses a fixed physical offset of zero if any of the following are true:

- CNTHCTL_EL2.ECV is 0.
- SCR_EL3.ECVEn is 0.
- HCR_EL2.{E2H, TGE} is {1, 1}.

On a Warm reset, this field resets to `0`.

Bit [4]

Reserved, RES0.

CX, bit [3]

CONTEXTIDR_EL2 and VMID trace enable.

CX	Meaning
`0b0`	CONTEXTIDR_EL2 and VMID trace prohibited.
`0b1`	CONTEXTIDR_EL2 and VMID trace allowed.

This field is ignored if SelfHostedTraceEnabled() == FALSE.

On a Warm reset, this field resets to `0`.

Bit [2]

Reserved, RES0.

E2TRE, bit [1]

EL2 Trace Enable.

E2TRE	Meaning
`0b0`	Trace is prohibited at EL2.
`0b1`	Trace is allowed at EL2.

This field is ignored if SelfHostedTraceEnabled() == FALSE.

On a Warm reset, this field resets to `0`.

E0HTRE, bit [0]

EL0 Trace Enable.

E0HTRE	Meaning
`0b0`	Trace is prohibited at EL0 when HCR_EL2.TGE == 1.
`0b1`	Trace is allowed at EL0 when HCR_EL2.TGE == 1.

This field is ignored if any of the following are true:

- SelfHostedTraceEnabled() == FALSE.
- EL2 is disabled in the current security state.
- HCR_EL2.TGE == 0.

On a Warm reset, this field resets to `0`.

Accessing the TRFCR_EL2

Accesses to this register use the following encodings:

MRS <Xt>, TRFCR_EL2

op0	op1	CRn	CRm	op2
0b11	0b100	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        return TRFCR_EL2;
elsif PSTATE.EL == EL3 then
    return TRFCR_EL2;
```

MSR TRFCR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    else
        TRFCR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    TRFCR_EL2 = X[t];
```

MRS <Xt>, TRFCR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TTRF == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x880];
    else
        return TRFCR_EL1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        return TRFCR_EL2;
    else
        return TRFCR_EL1;
elsif PSTATE.EL == EL3 then
    return TRFCR_EL1;
```

```
MSR TRFCR_EL1, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HDFGWTR_EL2.TRFCR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TTRF == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x880] = X[t];
    else
        TRFCR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.SystemAccessTrap(EL3, 0x18);
    elsif HCR_EL2.E2H == '1' then
        TRFCR_EL2 = X[t];
    else
        TRFCR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    TRFCR_EL1 = X[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TTBR0_EL1, Translation Table Base Register 0 (EL1)

The TTBR0_EL1 characteristics are:

Purpose

Holds the base address of the translation table for the initial lookup for stage 1 of the translation of an address from the lower VA range in the EL1&0 translation regime, and other information for this translation regime.

Configuration

AArch64 System register TTBR0_EL1 bits [63:0] are architecturally mapped to AArch32 System register TTBR0[63:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

TTBR0_EL1 is a 64-bit register.

Field descriptions

The TTBR0_EL1 bit assignments are:



ASID, bits [63:48]

An ASID for the translation table base address. The TCR_EL1.A1 field selects either TTBR0_EL1.ASID or TTBR1_EL1.ASID.

If the implementation has only 8 bits of ASID, then the upper 8 bits of this field are RES0.

This field resets to an architecturally UNKNOWN value.

BADDR, bits [47:1]

Translation table base address, A[47:x] or A[51:x], bits[47:1].

Note

- Translation table base addresses of 52 bits, A[51:x], are supported only in an implementation that includes ARMv8.2-LPA and is using the 64KB translation granule.
- A translation table must be aligned to the size of the table, except that when using a translation table base address larger than 48 bits the minimum alignment of a table containing fewer than eight entries is 64 bytes.

In an implementation that includes ARMv8.2-LPA, if the value of TCR_EL1.IPS is `0b110`, then:

- Register bits[47:z] hold bits[47:z] of the stage 1 translation table base address, where z is determined as follows:
  - If x >= 6 then z=x.
  - Otherwise, z=6.
- Register bits[5:2] hold bits[51:48] of the stage 1 translation table base address.

- When z>x register bits[(z-1):x] are RES0, and bits[(z-1):x] of the translation table base address are zero.
- When x>6 register bits[(x-1):6] are RES0.
- Register bit[1] is RES0.
- Bits[5:2] of the stage 1 translation table base address are zero.
- In an implementation that includes ARMv8.2-TTCNP bit[0] of the stage 1 translation table base address is zero.

Note

- In an implementation that includes ARMv8.2-LPA a TCR_EL1.IPS value of `0b110`, that selects an IPA size of 52 bits, is permitted only when using the 64KB translation granule.
- When the value of ID_AA64MMFR0_EL1.PARange indicates that the implementation does not support a 52 bit PA size, if a translation table lookup uses this register with the 64KB translation granule when the value of TCR_EL1.IPS is `0b110` and the value of register bits[5:2] is nonzero, an Address size fault is generated.

If the Effective value of TCR_EL1.IPS is not `0b110` then:

- Register bits[47:x] hold bits[47:x] of the stage 1 translation table base address.
- Register bits[(x-1):1] are RES0.
- If the implementation supports 52-bit PAs and IPAs, then bits[51:48] of the translation table base addresses used in this stage of translation are `0b0000`.

Note

This definition applies:

- To an implementation that includes ARMv8.2-LPA and is using a translation granule smaller than 64KB.
- To any implementation that does not include ARMv8.2-LPA.

If any TTBR0_EL1[47:0] bit that is defined as RES0 has the value 1 when a translation table walk is performed using TTBR0_EL1, then the translation table base address might be misaligned, with effects that are CONSTRAINED UNPREDICTABLE, and must be one of the following:

- Bits[x-1:0] of the translation table base address are treated as if all the bits are zero. The value read back from the corresponding register bits is either the value written to the register or zero.
- The result of the calculation of an address for a translation table walk using this register can be corrupted in those bits that are nonzero.

The AArch64 Virtual Memory System Architecture chapter describes how x is calculated based on the value of TCR_EL1.T0SZ, the stage of translation, and the translation granule size.

This field resets to an architecturally UNKNOWN value.

CnP, bit [0]

When ARMv8.2-TTCNP is implemented:

Common not Private. This bit indicates whether each entry that is pointed to by TTBR0_EL1 is a member of a common set that can be used by every PE in the Inner Shareable domain for which the value of TTBR0_EL1.CnP is 1.

CnP	Meaning
0b0	The translation table entries pointed to by TTBR0_EL1, for the current translation regime and ASID, are permitted to differ from corresponding entries for TTBR0_EL1 for other PEs in the Inner Shareable domain. This is not affected by: • The value of TTBR0_EL1.CnP on those other PEs. • The value of the current ASID. • If EL2 is implemented and enabled in the current Security state, the value of the current VMID.
0b1	The translation table entries pointed to by TTBR0_EL1 are the same as the translation table entries for every other PE in the Inner Shareable domain for which the value of TTBR0_EL1.CnP is 1 and all of the following apply: • The translation table entries are pointed to by TTBR0_EL1. • The translation tables relate to the same translation regime. • The ASID is the same as the current ASID. • If EL2 is implemented and enabled in the current Security state, the value of the current VMID.

This field is permitted to be cached in a TLB.

When a TLB combines entries from stage 1 translation and stage 2 translation into a single entry, that entry can only be shared between different PEs if the value of the CnP bit is 1 for both stage 1 and stage 2.

Note

If the value of the TTBR0_EL1.CnP bit is 1 on multiple PEs in the same Inner Shareable domain and those TTBR0_EL1s do not point to the same translation table entries when the other conditions specified for the case when the value of CnP is 1 apply, then the results of translations are CONSTRAINED UNPREDICTABLE, see 'CONSTRAINED UNPREDICTABLE behaviors due to caching of control or data values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Accessing the TTBR0_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic TTBR0_EL1 or TTBR0_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, TTBR0_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0010	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.TTBR0_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x200];
    else
        return TTBR0_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return TTBR0_EL2;
    else
        return TTBR0_EL1;
elsif PSTATE.EL == EL3 then
    return TTBR0_EL1;
```

MSR TTBR0_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0010	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.TTBR0_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x200] = X[t];
    else
        TTBR0_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        TTBR0_EL2 = X[t];
    else
        TTBR0_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    TTBR0_EL1 = X[t];
```

MRS <Xt>, TTBR0_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0010	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x200];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return TTBR0_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return TTBR0_EL1;
    else
        UNDEFINED;
```

```
MSR TTBR0_EL12, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b0010	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x200] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        TTBR0_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        TTBR0_EL1 = X[t];
    else
        UNDEFINED;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TTBR0_EL3, Translation Table Base Register 0 (EL3)

The TTBR0_EL3 characteristics are:

Purpose

Holds the base address of the translation table for the initial lookup for stage 1 of an address translation in the EL3 translation regime, and other information for this translation regime.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to TTBR0_EL3 are UNDEFINED.

Attributes

TTBR0_EL3 is a 64-bit register.

Field descriptions

The TTBR0_EL3 bit assignments are:



Bits [63:48]

Reserved, RES0.

BADDR, bits [47:1]

Translation table base address, A[47:x] or A[51:x].

Note

- Translation table base addresses of 52 bits, A[51:x], are supported only in an implementation that includes ARMv8.2-LPA and is using the 64KB translation granule.
- A translation table must be aligned to the size of the table, except that when using translation table base address larger than 48 bits the minimum alignment of a table containing fewer than eight entries is 64 bytes.

In an implementation that includes ARMv8.2-LPA, if the value of TCR_EL3.PS is `0b110` then:

- Register bits[47:z] hold bits[47:z] of the stage 1 translation table base address, where z is determined as follows:
  - If x >= 6 then z=x.
  - Otherwise, z=6.
- Register bits[5:2] hold bits[51:48] of the stage 1 translation table base address.
- When z>x register bits[(z-1):x] are RES0, and bits[(z-1):x] of the translation table base address are zero.
- When x>6 register bits[(x-1):6] are RES0.
- Register bit[1] is RES0.
- Bits[5:2] of the stage 1 translation table base address are zero.

- In an implementation that includes ARMv8.2-TTCNP bit[0] of the stage 1 translation table base address is zero.

Note

- In an implementation that includes ARMv8.2-LPA a TCR_EL3.PS value of `0b110`, that selects a PA size of 52 bits, is permitted only when using the 64KB translation granule.
- When the value of ID_AA64MMFR0_EL1.PARange indicates that the implementation does not support a 52 bit PA size, if a translation table lookup uses this register with the 64KB translation granule when the value of TCR_EL3.PS is `0b110` and the value of register bits[5:2] is nonzero, an Address size fault is generated.

If the Effective value of TCR_EL3.PS is not `0b110` then:

- Register bits[47:x] hold bits[47:x] of the stage 1 translation table base address.
- Register bits[(x-1):1] are RES0.
- If the implementation supports 52-bit PAs and IPAs, then bits[51:48] of the translation table base addresses used in this stage of translation are `0b0000`.

Note

This definition applies:

- To an implementation that includes ARMv8.2-LPA and is using a translation granule smaller than 64KB.
- To any implementation that does not include ARMv8.2-LPA.

If any TTBR0_EL3[47:0] bit that is defined as RES0 has the value 1 when a translation table walk is performed using TTBR0_EL3, then the translation table base address might be misaligned, with effects that are CONSTRAINED UNPREDICTABLE, and must be one of the following:

- Bits[x-1:0] of the translation table base address are treated as if all the bits are zero. The value read back from the corresponding register bits is either the value written to the register or zero.
- The result of the calculation of an address for a translation table walk using this register can be corrupted in those bits that are nonzero.

The AArch64 Virtual Memory System Architecture chapter describes how x is calculated based on the value of TCR_EL3.T0SZ, the stage of translation, and the translation granule size.

This field resets to an architecturally UNKNOWN value.

CnP, bit [0]

When ARMv8.2-TTCNP is implemented:

Common not Private. This bit indicates whether each entry that is pointed to by TTBR0_EL3 is a member of a common set that can be used by every PE in the Inner Shareable domain for which the value of TTBR0_EL3.CnP is 1.

CnP	Meaning
`0b0`	The translation table entries pointed to by TTBR0_EL3, for the current translation regime, are permitted to differ from corresponding entries for TTBR0_EL3 for other PEs in the Inner Shareable domain. This is not affected by the value of TTBR0_EL3.CnP on those other PEs.
`0b1`	The translation table entries pointed to by TTBR0_EL3 are the same as the translation table entries for every other PE in the Inner Shareable domain for which the value of TTBR0_EL3.CnP is 1 and the translation table entries are pointed to by TTBR0_EL3.

This field is permitted to be cached in a TLB.

Note

If the value of the TTBR0_EL3.CnP bit is 1 on multiple PEs in the same Inner Shareable domain and those TTBR0_EL3s do not point to the same translation table entries the results of translations using TTBR0_EL3 are CONSTRAINED UNPREDICTABLE, see 'CONSTRAINED UNPREDICTABLE behaviors due to

caching of control or data values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Accessing the TTBR0_EL3

Accesses to this register use the following encodings:

```
MRS <Xt>, TTBR0_EL3
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0010	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return TTBR0_EL3;
```

```
MSR TTBR0_EL3, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b110	0b0010	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    TTBR0_EL3 = X[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TTBR1_EL1, Translation Table Base Register 1 (EL1)

The TTBR1_EL1 characteristics are:

Purpose

Holds the base address of the translation table for the initial lookup for stage 1 of the translation of an address from the higher VA range in the EL1&0 stage 1 translation regime, and other information for this translation regime.

Configuration

AArch64 System register TTBR1_EL1 bits [63:0] are architecturally mapped to AArch32 System register TTBR1[63:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

TTBR1_EL1 is a 64-bit register.

Field descriptions

The TTBR1_EL1 bit assignments are:



ASID, bits [63:48]

An ASID for the translation table base address. The TCR_EL1.A1 field selects either TTBR0_EL1.ASID or TTBR1_EL1.ASID.

If the implementation has only 8 bits of ASID, then the upper 8 bits of this field are RES0.

This field resets to an architecturally UNKNOWN value.

BADDR, bits [47:1]

Translation table base address, A[47:x] or A[51:x], bits[47:1].

Note

- Translation table base addresses of 52 bits, A[51:x], are supported only in an implementation that includes ARMv8.2-LPA and is using the 64KB translation granule.
- A translation table must be aligned to the size of the table, except that when using a translation table base address larger than 48 bits the minimum alignment of a table containing fewer than eight entries is 64 bytes.

In an implementation that includes ARMv8.2-LPA, if the value of TCR_EL1.IPS is `0b110`, then:

- Register bits[47:z] hold bits[47:z] of the stage 1 translation table base address, where z is determined as follows:
  - If x >= 6 then z=x.
  - Otherwise, z=6.
- Register bits[5:2] hold bits[51:48] of the stage 1 translation table base address.

- When z>x register bits[(z-1):x] are RES0, and bits[(z-1):x] of the translation table base address are zero.
- When x>6 register bits[(x-1):6] are RES0.
- Register bit[1] is RES0.
- Bits[5:2] of the stage 1 translation table base address are zero.
- In an implementation that includes ARMv8.2-TTCNP bit[0] of the stage 1 translation table base address is zero.

Note

- In an implementation that includes ARMv8.2-LPA a TCR_EL1.IPS value of `0b110`, that selects an IPA size of 52 bits, is permitted only when using the 64KB translation granule.
- When the value of ID_AA64MMFR0_EL1.PARange indicates that the implementation does not support a 52 bit PA size, if a translation table lookup uses this register with the 64KB translation granule when the value of TCR_EL1.IPS is `0b110` and the value of register bits[5:2] is nonzero, an Address size fault is generated.

If the Effective value of TCR_EL1.IPS is not `0b110` then:

- Register bits[47:x] hold bits[47:x] of the stage 1 translation table base address.
- Register bits[(x-1):1] are RES0.
- If the implementation supports 52-bit PAs and IPAs, then bits[51:48] of the translation table base addresses used in this stage of translation are `0b0000`.

Note

This definition applies:

- To an implementation that includes ARMv8.2-LPA and is using a translation granule smaller than 64KB.
- To any implementation that does not include ARMv8.2-LPA.

If any TTBR1_EL1[47:0] bit that is defined as RES0 has the value 1 when a translation table walk is performed using TTBR1_EL1, then the translation table base address might be misaligned, with effects that are CONSTRAINED UNPREDICTABLE, and must be one of the following:

- Bits[x-1:0] of the translation table base address are treated as if all the bits are zero. The value read back from the corresponding register bits is either the value written to the register or zero.
- The result of the calculation of an address for a translation table walk using this register can be corrupted in those bits that are nonzero.

The AArch64 Virtual Memory System Architecture chapter describes how x is calculated based on the value of TCR_EL1.T1SZ, the stage of translation, and the translation granule size.

This field resets to an architecturally UNKNOWN value.

CnP, bit [0]

When ARMv8.2-TTCNP is implemented:

Common not Private. This bit indicates whether each entry that is pointed to by TBR1_EL1 is a member of a common set that can be used by every PE in the Inner Shareable domain for which the value of TTBR1_EL1.CnP is 1.

CnP	Meaning
0b0	The translation table entries pointed to by TTBR1_EL1, for the current translation regime and ASID, are permitted to differ from corresponding entries for TTBR1_EL1 for other PEs in the Inner Shareable domain. This is not affected by: • The value of TTBR1_EL1.CnP on those other PEs. • The value of the current ASID. • If EL2 is implemented and enabled in the current Security state, the value of the current VMID.
0b1	The translation table entries pointed to by TTBR1_EL1 are the same as the translation table entries for every other PE in the Inner Shareable domain for which the value of TTBR1_EL1.CnP is 1 and all of the following apply: • The translation table entries are pointed to by TTBR1_EL1. • The translation tables relate to the same translation regime. • The ASID is the same as the current ASID. • If EL2 is implemented and enabled in the current Security state, the value of the current VMID.

This field is permitted to be cached in a TLB.

When a TLB combines entries from stage 1 translation and stage 2 translation into a single entry, that entry can only be shared between different PEs if the value of the CnP bit is 1 for both stage 1 and stage 2.

Note

If the value of the TTBR1_EL1.CnP bit is 1 on multiple PEs in the same Inner Shareable domain and those TTBR1_EL1s do not point to the same translation table entries when the other conditions specified for the case when the value of CnP is 1 apply, then the results of translations are CONSTRAINED UNPREDICTABLE, see 'CONSTRAINED UNPREDICTABLE behaviors due to caching of control or data values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Accessing the TTBR1_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic TTBR1_EL1 or TTBR1_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

```
MRS <Xt>, TTBR1_EL1
```

op0	op1	CRn	CRm	op2
0b11	0b000	0b0010	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.TTBR1_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x210];
    else
        return TTBR1_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return TTBR1_EL2;
    else
        return TTBR1_EL1;
elsif PSTATE.EL == EL3 then
    return TTBR1_EL1;
```

MSR TTBR1_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0010	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.TTBR1_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x210] = X[t];
    else
        TTBR1_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        TTBR1_EL2 = X[t];
    else
        TTBR1_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    TTBR1_EL1 = X[t];
```

MRS <Xt>, TTBR1_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0010	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x210];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return TTBR1_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return TTBR1_EL1;
    else
        UNDEFINED;
```

```
MSR TTBR1_EL12, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b0010	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x210] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        TTBR1_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        TTBR1_EL1 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VBAR_EL1, Vector Base Address Register (EL1)

The VBAR_EL1 characteristics are:

Purpose

Holds the vector base address for any exception that is taken to EL1.

Configuration

AArch64 System register VBAR_EL1 bits [31:0] are architecturally mapped to AArch32 System register VBAR[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VBAR_EL1 is a 64-bit register.

Field descriptions

The VBAR_EL1 bit assignments are:



Bits [63:11]

Vector Base Address. Base address of the exception vectors for exceptions taken to EL1.

If the implementation does not support ARMv8.2-LVA, then:

- If tagged addresses are being used, bits [55:48] of VBAR_EL1 must be the same or else the use of the vector address will result in a recursive exception.
- If tagged addresses are not being used, bits [63:48] of VBAR_EL1 must be the same or else the use of the vector address will result in a recursive exception.

If the implementation supports ARMv8.2-LVA, then:

- If tagged addresses are being used, bits [55:52] of VBAR_EL1 must be the same or else the use of the vector address will result in a recursive exception.
- If tagged addresses are not being used, bits [63:52] of VBAR_EL1 must be the same or else the use of the vector address will result in a recursive exception.

This field resets to an architecturally UNKNOWN value.

Bits [10:0]

Reserved, RES0.

Accessing the VBAR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic VBAR_EL1 or VBAR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

MRS <Xt>, VBAR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.VBAR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x250];
    else
        return VBAR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        return VBAR_EL2;
    else
        return VBAR_EL1;
elsif PSTATE.EL == EL3 then
    return VBAR_EL1;
```

MSR VBAR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1> == '01' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGWTR_EL2.VBAR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x250] = X[t];
    else
        VBAR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '1' then
        VBAR_EL2 = X[t];
    else
        VBAR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    VBAR_EL1 = X[t];
```

MRS <Xt>, VBAR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b1100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x250];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        return VBAR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        return VBAR_EL1;
    else
        UNDEFINED;
```

```
MSR VBAR_EL12, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b1100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x250] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        VBAR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        VBAR_EL1 = X[t];
    else
        UNDEFINED;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VBAR_EL3, Vector Base Address Register (EL3)

The VBAR_EL3 characteristics are:

Purpose

Holds the vector base address for any exception that is taken to EL3.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ~~HaveEL(~~EL3 is implemented.~~).~~ Otherwise, direct accesses to VBAR_EL3 are UNDEFINED.

Attributes

VBAR_EL3 is a 64-bit register.

Field descriptions

The VBAR_EL3 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Vector Base Address																															
Vector Base Address																					RES0									

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Vector Base Address																					RES0										

Bits [63:11]

Vector Base Address. Base address of the exception vectors for exceptions taken to EL3.

If the implementation does not support ARMv8.2-LVA, then:

- If tagged addresses are being used, bits [55:48] of VBAR_EL3 must be 0 or else the use of the vector address will result in a recursive exception.
- If tagged addresses are not being used, bits [63:48] of VBAR_EL3 must be 0 or else the use of the vector address will result in a recursive exception.

If the implementation supports ARMv8.2-LVA, then:

- If tagged addresses are being used, bits [55:52] of VBAR_EL3 must be the same or else the use of the vector address will result in a recursive exception.
- If tagged addresses are not being used, bits [63:52] of VBAR_EL3 must be the same or else the use of the vector address will result in a recursive exception.

This field resets to an architecturally UNKNOWN value.

Bits [10:0]

Reserved, RES0.

Accessing the VBAR_EL3

Accesses to this register use the following encodings:

MRS <Xt>, VBAR_EL3

op0	op1	CRn	CRm	op2
0b11	0b110	0b1100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return VBAR_EL3;
```

MSR VBAR_EL3, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b110	0b1100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    VBAR_EL3 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VDISR_EL2, Virtual Deferred Interrupt Status Register

The VDISR_EL2 characteristics are:

Purpose

Records that a virtual SError interrupt has been consumed by an ESB instruction executed at EL1.

An indirect write to VDISR_EL2 made by an ESB instruction does not require an explicit synchronization operation for the value written to be observed by a direct read of DISR_EL1 or DISR occurring in program order after the ESB instruction.

Configuration

AArch64 System register VDISR_EL2 bits [31:0] are architecturally mapped to AArch32 System register VDISR[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to VDISR_EL2 are UNDEFINED.

If EL2 is not implemented, this register is RES0 from EL3.

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VDISR_EL2 is a 64-bit register.

Field descriptions

The VDISR_EL2 bit assignments are:

When ~~!ELUsingAArch32(~~EL1 is using AArch64:~~):~~



Bits [63:32]

Reserved, RES0.

A, bit [31]

Set to 1 when an ESB instruction defers a virtual SError interrupt.

This field resets to an architecturally UNKNOWN value.

Bits [30:25]

Reserved, RES0.

IDS, bit [24]

The value copied from VSESR_EL2.IDS.

This field resets to an architecturally UNKNOWN value.

ISS, bits [23:0]

The value copied from VSESR_EL2.ISS.

This field resets to an architecturally UNKNOWN value.

When ~~ELUsingAArch32(~~EL1 is using AArch32~~)~~ and VDISR_EL2.LPAE == 0:



Bits [63:32]

Reserved, RES0.

A, bit [31]

Set to 1 when an ESB instruction defers a virtual SError interrupt.

This field resets to an architecturally UNKNOWN value.

Bits [30:16]

Reserved, RES0.

AET, bits [15:14]

The value copied from VSESR_EL2.AET.

This field resets to an architecturally UNKNOWN value.

Bit [13]

Reserved, RES0.

ExT, bit [12]

The value copied from VSESR_EL2.ExT.

This field resets to an architecturally UNKNOWN value.

Bit [11]

Reserved, RES0.

FS[4], bit [10]

This field is bit[4] of FS[4:0].

Fault status code. Set to `0b10110` when an ESB instruction defers a virtual SError interrupt.

FS	Meaning
0b10110	Asynchronous SError interrupt.

All other values are reserved.

The FS field is split as follows:

- FS[4] is VDISR_EL2[10].
- FS[3:0] is VDISR_EL2[3:0].

This field resets to an architecturally UNKNOWN value.

LPAE, bit [9]

Format.

Set to TTBCR.EAE when an ESB instruction defers a virtual SError interrupt.

LPAE	Meaning
0b0	Using the Short-descriptor translation table format.

This field resets to an architecturally UNKNOWN value.

Bits [8:4]

Reserved, RES0.

FS[3:0], bits [3:0]

This field is bits[3:0] of FS[4:0].

See FS[4] for the field description.

When ~~ELUsingAArch32(~~EL1 is using AArch32~~)~~ and VDISR_EL2.LPAE == 1:



Bits [63:32]

Reserved, RES0.

A, bit [31]

Set to 1 when an ESB instruction defers a virtual SError interrupt.

This field resets to an architecturally UNKNOWN value.

Bits [30:16]

Reserved, RES0.

AET, bits [15:14]

The value copied from VSESR_EL2.AET.

This field resets to an architecturally UNKNOWN value.

Bit [13]

Reserved, RES0.

ExT, bit [12]

The value copied from VSESR_EL2.ExT.

This field resets to an architecturally UNKNOWN value.

Bits [11:10]

Reserved, RES0.

LPAE, bit [9]

Format.

Set to TTBCR.EAE when an ESB instruction defers a virtual SError interrupt.

LPAE	Meaning
0b1	Using the Long-descriptor translation table format.

This field resets to an architecturally UNKNOWN value.

Bits [8:6]

Reserved, RES0.

STATUS, bits [5:0]

Fault status code. Set to 0b010001 when an ESB instruction defers a virtual SError interrupt.

STATUS	Meaning
0b010001	Asynchronous SError interrupt.

All other values are reserved.

This field resets to an architecturally UNKNOWN value.

Accessing the VDISR_EL2

An indirect write to VDISR_EL2 made by an ESB instruction does not require an explicit synchronization operation for the value that is written to be observed by a direct read of DISR_EL1 or DISR occurring in program order after the ESB instruction.

Accesses to this register use the following encodings:

```
MRS <Xt>, VDISR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b1100	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x500];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return VDISR_EL2;
elsif PSTATE.EL == EL3 then
    return VDISR_EL2;
```

MSR VDISR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b1100	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x500] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    VDISR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    VDISR_EL2 = X[t];
```

MRS <Xt>, DISR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.AMO == '1' then
        return VDISR_EL2;
    else
        return DISR_EL1;
elsif PSTATE.EL == EL2 then
    return DISR_EL1;
elsif PSTATE.EL == EL3 then
    return DISR_EL1;
```

MSR DISR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b1100	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.AMO == '1' then
        VDISR_EL2 = X[t];
    else
        DISR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    DISR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    DISR_EL1 = X[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VMPIDR_EL2, Virtualization Multiprocessor ID Register

The VMPIDR_EL2 characteristics are:

Purpose

Holds the value of the Virtualization Multiprocessor ID. This is the value returned by EL1 reads of MPIDR_EL1.

Configuration

AArch64 System register VMPIDR_EL2 bits [31:0] are architecturally mapped to AArch32 System register VMPIDR[31:0] .

If EL2 is not implemented, reads of this register return the value of the MPIDR_EL1 ,~~-~~and writes to the register are ignored.

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VMPIDR_EL2 is a 64-bit register.

Field descriptions

The VMPIDR_EL2 bit assignments are:



Bits [63:40]

Reserved, RES0.

Aff3, bits [39:32]

Affinity level 3. See the description of VMPIDR_EL2.Aff0~~Aff0~~ for more information.

Aff3 is not supported in AArch32 state.

This field resets to an architecturally UNKNOWN value.

Bit [31]

Reserved, RES1.

U, bit [30]

Indicates a Uniprocessor system, as distinct from PE 0 in a multiprocessor system. ~~The possible values of this bit are:~~

U	Meaning
0b0	Processor is part of a multiprocessor system.
0b1	Processor is part of a uniprocessor system.

This field resets to an architecturally UNKNOWN value.

Bits [29:25]

Reserved, RES0.

MT, bit [24]

Indicates whether the lowest level of affinity consists of logical PEs that are implemented using a multithreading type approach. See the description of VMPIDR_EL2.Aff0~~Aff0~~ for more information about affinity levels. ~~The possible values of this bit are:~~

MT	Meaning
0b0	Performance of PEs at the lowest affinity level is largely independent.
0b1	Performance of PEs at the lowest affinity level is very interdependent.

This field resets to an architecturally UNKNOWN value.

Aff2, bits [23:16]

Affinity level 2. See the description of VMPIDR_EL2.Aff0~~Aff0~~ for more information.

This field resets to an architecturally UNKNOWN value.

Aff1, bits [15:8]

Affinity level 1. See the description of VMPIDR_EL2.Aff0~~Aff0~~ for more information.

This field resets to an architecturally UNKNOWN value.

Aff0, bits [7:0]

Affinity level 0. This is the affinity level that is most significant for determining PE behavior. Higher affinity levels are increasingly less significant in determining PE behavior. The assigned value of the MPIDR.{Aff2, Aff1, Aff0} or MPIDR_EL1.{Aff3, Aff2, Aff1, Aff0} set of fields of each PE must be unique within the system as a whole.

This field resets to an architecturally UNKNOWN value.

Accessing the VMPIDR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, VMPIDR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0000	0b0000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x050];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return VMPIDR_EL2;
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        return MPIDR_EL1;
    else
        return VMPIDR_EL2;
```

MSR VMPIDR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0000	0b0000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x050] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    VMPIDR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        //no operation
    else
        VMPIDR_EL2 = X[t];
```

MRS <Xt>, MPIDR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0000	0b101

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.MPIDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) then
        return VMPIDR_EL2;
    else
        return MPIDR_EL1;
elsif PSTATE.EL == EL2 then
    return MPIDR_EL1;
elsif PSTATE.EL == EL3 then
    return MPIDR_EL1;
```

MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) then
        return VMPIDR_EL2<31:0>;
    elsif EL2Enabled() && ELUsingAArch32(EL2) then
        return VMPIDR<31:0>;
    else
        return MPIDR<31:0>;
elsif PSTATE.EL == EL2 then
    return MPIDR<31:0>;
elsif PSTATE.EL == EL3 then
    return MPIDR<31:0>;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VNCR_EL2, Virtual Nested Control Register

The VNCR_EL2 characteristics are:

Purpose

When ARMv8.4-NV is implemented, holds the base address that is used to define the memory location that is accessed by transformed reads and writes of System registers.

Configuration

This register is present only when ARMv8.4-NV is implemented. Otherwise, direct accesses to VNCR_EL2 are UNDEFINED.

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VNCR_EL2 is a 64-bit register.

Field descriptions

The VNCR_EL2 bit assignments are:



RESS, bits [63:53]

Reserved, Sign extended. If the bits marked as RESS do not all have the same value, then there is a CONSTRAINED UNPREDICTABLE choice between:

- Generating an EL2 translation regime Translation abort on use of the VNCR_EL2 register.
- Bits[63:49] of VNCR_EL2 are treated as the same value as bit[48] for all purposes other than reading back the register.
- Bits[63:49] of VNCR_EL2 are treated as the same value as bit[48] for all purposes.
- If the virtual address space for EL2 supports more than 48 bits, bits[63:53] of VNCR_EL2 are treated as the same value as bit[52] for all purposes other than reading back the register.
- If the virtual address space for EL2 supports more than 48 bits, bits[63:53] of VNCR_EL2 are treated as the same value as bit[52].

Where the EL2 translation regime has upper and lower address ranges, bit[52] is used to select between those address ranges to determine if the address space supports more than 48 bits.

BADDR, bits [52:12]

Base Address. If the virtual address space for EL2 does not support more than 48 bits, then bits [52:49] are RESS.

When a register read/write is transformed to be a Load or Store, the address of the load/store is to SignOffset(VNCR_EL2.BADDR~~VNCR.BADDR~~:Offset<11:0>, 64).

This field resets to an architecturally UNKNOWN value.

Bits [11:0]

Reserved, RES0.

Accessing the VNCR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, VNCR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x0B0];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return VNCR_EL2;
elsif PSTATE.EL == EL3 then
    return VNCR_EL2;
```

```
MSR VNCR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x0B0] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    VNCR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    VNCR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VPIDR_EL2, Virtualization Processor ID Register

The VPIDR_EL2 characteristics are:

Purpose

Holds the value of the Virtualization Processor ID. This is the value returned by EL1 reads of MIDR_EL1.

Configuration

AArch64 System register VPIDR_EL2 bits [31:0] are architecturally mapped to AArch32 System register VPIDR[31:0] .

If EL2 is not implemented, reads of this register return the value of the MIDR_EL1 ,and writes to the register are ignored.

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VPIDR_EL2 is a 64-bit register.

Field descriptions

The VPIDR_EL2 bit assignments are:



Bits [63:32]

Reserved, RES0.

Implementer, bits [31:24]

The Implementer code. This field must hold an implementer code that has been assigned by Arm. Assigned codes include the following:

Hex representation	ASCII representation	Implementer
0x41	A	Arm Limited
0x42	B	Broadcom Corporation
0x43	C	Cavium Inc.
0x44	D	Digital Equipment Corporation
0x49	I	Infineon Technologies AG
0x4D	M	Motorola or Freescale Semiconductor Inc.
0x4E	N	NVIDIA Corporation
0x50	P	Applied Micro Circuits Corporation
0x51	Q	Qualcomm Inc.
0x56	V	Marvell International Ltd.
0x69	i	Intel Corporation

Arm can assign codes that are not published in this manual. All values not assigned by Arm are reserved and must not be used.

This field resets to an architecturally UNKNOWN value.

Variant, bits [23:20]

An IMPLEMENTATION DEFINED variant number. Typically, this field is used to distinguish between different product variants, or major revisions of a product.

This field resets to an architecturally UNKNOWN value.

Architecture, bits [19:16]

The permitted values of this field are:

Architecture	Meaning
0b0001	Armv4.
0b0010	Armv4T.
0b0011	Armv5 (obsolete).
0b0100	Armv5T.
0b0101	Armv5TE.
0b0110	Armv5TEJ.
0b0111	Armv6.
0b1111	Architectural features are individually identified in the ID_* registers, see 'ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K12.3.3.

All other values are reserved.

This field resets to an architecturally UNKNOWN value.

PartNum, bits [15:4]

An IMPLEMENTATION DEFINED primary part number for the device.

On processors implemented by Arm, if the top four bits of the primary part number are 0x0 or 0x7, the variant and architecture are encoded differently.

This field resets to an architecturally UNKNOWN value.

Revision, bits [3:0]

An IMPLEMENTATION DEFINED revision number for the device.

This field resets to an architecturally UNKNOWN value.

Accessing the VPIDR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, VPIDR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x088];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return VPIDR_EL2;
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        return MIDR_EL1;
    else
        return VPIDR_EL2;
```

MSR VPIDR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x088] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    VPIDR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        //no operation
    else
        VPIDR_EL2 = X[t];
```

MRS <Xt>, MIDR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    if IsFeatureImplemented("ARMv8.4-IDST") then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.SystemAccessTrap(EL2, 0x18);
        else
            AArch64.SystemAccessTrap(EL1, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && (!HaveEL(EL3) || SCR_EL3.FGTEn == '1') &&
HFGRTR_EL2.MIDR_EL1 == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) then
        return VPIDR_EL2;
    else
        return MIDR_EL1;
elsif PSTATE.EL == EL2 then
    return MIDR_EL1;
elsif PSTATE.EL == EL3 then
    return MIDR_EL1;
```

MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) then
        return VPIDR_EL2<31:0>;
    elsif EL2Enabled() && ELUsingAArch32(EL2) then
        return VPIDR<31:0>;
    else
        return MIDR<31:0>;
elsif PSTATE.EL == EL2 then
    return MIDR<31:0>;
elsif PSTATE.EL == EL3 then
    return MIDR<31:0>;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VSESR_EL2, Virtual SError Exception Syndrome Register

The VSESR_EL2 characteristics are:

Purpose

Provides the syndrome value reported to software on taking a virtual SError interrupt exception to EL1, or on executing an ESB instruction at EL1.

When the virtual SError interrupt is taken to EL1 using AArch64, then the syndrome value is reported in ESR_EL1.

When the virtual SError interrupt is taken to EL1 using AArch32, then the syndrome value is reported in DFSR.{AET, ExT} and the remainder of DFSR is set as defined by VMSAv8-32. For more information, see The AArch32 Virtual Memory System Architecture.

When the virtual SError interrupt is deferred by an ESB instruction, then the syndrome value is written to VDISR_EL2.

Configuration

AArch64 System register VSESR_EL2 bits [31:0] are architecturally mapped to AArch32 System register VDFSR[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to VSESR_EL2 are UNDEFINED.

If EL2 is not implemented, this register is RES0 from EL3.

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VSESR_EL2 is a 64-bit register.

Field descriptions

The VSESR_EL2 bit assignments are:

When ~~ELUsingAArch32(~~EL1 is using AArch32:~~):~~



Bits [63:16]

Reserved, RES0.

AET, bits [15:14]

When a virtual SError interrupt is taken to EL1 using AArch32, DFSR[15:4] is set to VSESR_EL2.AET.

When a virtual SError interrupt is deferred by an ESB instruction, VDISR_EL2[15:4] is set to VSESR_EL2.AET.

This field resets to an architecturally UNKNOWN value.

Bit [13]

Reserved, RES0.

ExT, bit [12]

When a virtual SError interrupt is taken to EL1 using AArch32, DFSR[12] is set to VSESR_EL2.ExT.

When a virtual SError interrupt is deferred by an ESB instruction, VDISR_EL2[12] is set to VSESR_EL2.ExT.

This field resets to an architecturally UNKNOWN value.

Bits [11:0]

Reserved, RES0.

When ~~!ELUsingAArch32(~~EL1 is using AArch64:~~):~~



Bits [63:25]

Reserved, RES0.

IDS, bit [24]

When a virtual SError interrupt is taken to EL1 using AArch64, ESR_EL1[24] is set to VSESR_EL2.IDS.

When a virtual SError interrupt is deferred by an ESB instruction, VDISR_EL2[24] is set to VSESR_EL2.IDS.

This field resets to an architecturally UNKNOWN value.

ISS, bits [23:0]

When a virtual SError interrupt is taken to EL1 using AArch64, ESR_EL1[23:0] is set to VSESR_EL2.ISS.

When a virtual SError interrupt is deferred by an ESB instruction, VDISR_EL2[23:0] is set to VSESR_EL2.ISS.

This field resets to an architecturally UNKNOWN value.

Accessing the VSESR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, VSESR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0010	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x508];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return VSESR_EL2;
elsif PSTATE.EL == EL3 then
    return VSESR_EL2;
```

```
MSR VSESR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0101	0b0010	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x508] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    VSESR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    VSESR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VSTCR_EL2, Virtualization Secure Translation Control Register

The VSTCR_EL2 characteristics are:

Purpose

The control register for stage 2 of the Secure EL1&0 translation regime.

Configuration

This register is present only when ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to VSTCR_EL2 are UNDEFINED.

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VSTCR_EL2 is a 64-bit register.

Field descriptions

The VSTCR_EL2 bit assignments are:



Any of the bits in VSTCR_EL2 are permitted to be cached in a TLB.

Bits [63:32]

Reserved, RES0.

Bit [31]

Reserved, RES1.

SA, bit [30]

Secure stage 2 translation output address space.

SA	Meaning
0b0	All stage 2 translations for the Secure IPA space access the Secure PA space.
0b1	All stage 2 translations for the Secure IPA space access the Non-secure PA space.

When the value of VSTCR_EL2.SW is 1, this bit behaves as 1 for all purposes other than reading back the value of the bit.

This field resets to an architecturally UNKNOWN value.

SW, bit [29]

Secure stage 2 translation address space.

SW	Meaning
0b0	All stage 2 translation table walks for the Secure IPA space are to the Secure PA space.
0b1	All stage 2 translation table walks for the Secure IPA space are to the Non-secure PA space.

This field resets to an architecturally UNKNOWN value.

Bits [28:16]

Reserved, RES0.

TG0, bits [15:14]

Secure stage 2 granule size for VSTTBR_EL2.

TG0	Meaning
0b00	4KB.
0b01	64KB.
0b10	16KB.

Other values are reserved.

If ARMv8.5-GTG is implemented, ID_AA64MMFR0_EL1.{TGran4_2, TGran16_2, TGran64_2} indicate which granule sizes are supported for Level 2 translation.

If ARMv8.5-GTG is not implemented, ID_AA64MMFR0_EL1.{TGran4, TGran16, TGran64} indicate which granule sizes are supported.

If the value is programmed to either a reserved value, or a size that has not been implemented, then for all purposes other than read back from this register, the hardware will treat the field as if it has been programmed to an IMPLEMENTATION DEFINED choice of the sizes that has been implemented.

It is IMPLEMENTATION DEFINED whether the value read back is the value programmed or the value that corresponds to the size chosen.

This field resets to an architecturally UNKNOWN value.

Bits [13:8]

Reserved, RES0.

SL0, bits [7:6]

When ARMv8.4-TTST is implemented:

Starting level of the Secure stage 2 translation lookup, controlled by VSTCR_EL2. The meaning of this field depends on the value of VSTCR_EL2.TG0.

SL0	Meaning
0b00	If VSTCR_EL2.TG0 is 0b00 (4KB granule), start at level 2. If VSTCR_EL2.TG0 is 0b10 (16KB granule) or 0b01 (64KB granule), start at level 3.
0b01	If VSTCR_EL2.TG0 is 0b00 (4KB granule), start at level 1. If VSTCR_EL2.TG0 is 0b10 (16KB granule) or 0b01 (64KB granule), start at level 2.
0b10	If VSTCR_EL2.TG0 is 0b00 (4KB granule), start at level 0. If VSTCR_EL2.TG0 is 0b10 (16KB granule) or 0b01 (64KB granule), start at level 1.
0b11	If VSTCR_EL2.TG0 is 0b00 (4KB granule), start at level 3.

All other values are reserved. If this field is programmed to a reserved value, or to a value that is not consistent with the programming of VSTCR_EL2.T0SZ, then a stage 2 level 0 Translation fault is generated.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Starting level of the Secure stage 2 translation lookup, controlled by VSTCR_EL2. The meaning of this field depends on the value of VSTCR_EL2.TG0.

SL0	Meaning
0b00	If VSTCR_EL2.TG0 is 0b00 (4KB granule), start at level 2. If VSTCR_EL2.TG0 is 0b10 (16KB granule) or 0b01 (64KB granule), start at level 3.
0b01	If VSTCR_EL2.TG0 is 0b00 (4KB granule), start at level 1. If VSTCR_EL2.TG0 is 0b10 (16KB granule) or 0b01 (64KB granule), start at level 2.
0b10	If VSTCR_EL2.TG0 is 0b00 (4KB granule), start at level 0. If VSTCR_EL2.TG0 is 0b10 (16KB granule) or 0b01 (64KB granule), start at level 1.

All other values are reserved. If this field is programmed to a reserved value, or to a value that is not consistent with the programming of VSTCR_EL2.T0SZ, then a stage 2 level 0 Translation fault is generated.

This field resets to an architecturally UNKNOWN value.

T0SZ, bits [5:0]

The size offset of the memory region addressed by VSTTBR_EL2. The region size is $2^{(64\text{-}T0SZ\ 64\text{-}VSTCR_EL2.T0SZ)}$ bytes.

The maximum and minimum possible values for this field depend on the level of translation table and the memory translation granule size, as described in the AArch64 Virtual Memory System Architecture chapter.

If this field is programmed to a value that is not consistent with the programming of SL0, then a stage 2 level 0 Translation fault is generated.

This field resets to an architecturally UNKNOWN value.

Accessing the VSTCR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, VSTCR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0010	0b0110	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x048];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        return VSTCR_EL2;
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        return VSTCR_EL2;
```

```
MSR VSTCR_EL2, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0010	0b0110	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    elsif EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x048] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && SCR_EL3.NS == '1' then
        UNDEFINED;
    else
        VSTCR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    if SCR_EL3.EEL2 == '0' then
        UNDEFINED;
    else
        VSTCR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VTTBR_EL2, Virtualization Translation Table Base Register

The VTTBR_EL2 characteristics are:

Purpose

Holds the base address of the translation table for the initial lookup for stage 2 of an address translation in the EL1&0 translation regime, and other information for this translation regime.

Configuration

AArch64 System register VTTBR_EL2 bits [63:0] are architecturally mapped to AArch32 System register VTTBR[63:0] .

If EL2 is not implemented, this register is RES0 from EL3.

This register has no effect if EL2 is not enabled in the current Security state.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VTTBR_EL2 is a 64-bit register.

Field descriptions

The VTTBR_EL2 bit assignments are:



VMID[15:8], bits [63:56]

When ARMv8.1-VMID16 is implemented and VTCR_EL2.VS == 1:

Extension to VMID[7:0]. See VTTBR_EL2.VMID~~VMID~~[7:0] for more details.

If EL2 is using AArch32, or if the implementation has an 8-bit VMID, this field is RES0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

VMID[7:0], bits [55:48]

The VMID for the translation table.

~~If the implementation has an 8-bit VMID, then VMID[15:8] are RES0.~~

~~If the implementation has a 16-bit VMID, then:~~

The VMID is 8 bits when any of the following are true:

~~It is IMPLEMENTATION DEFINED whether the VMID is 8 bits or 16 bits.~~

- EL2 is using AArch32.~~The VTCR_EL2.VS bit selects whether VMID[15:8] are ignored by the hardware for every purpose except reading back the register, or whether these bits are used for allocation and matching in the TLB.~~
- The~~ 16-bit VMID is only supported when EL2 is using AArch64. This means the hardware must ignore VMID[15:8] when EL2 is using AArch32.~~ VTCR_EL2.VS is 0.
- ARMv8.1-VMID16 is not implemented.

This field resets to an architecturally UNKNOWN value.

BADDR, bits [47:1]

Translation table base address, A[47:x] or A[51:x], bits[47:1].

Note

- Translation table base addresses of 52 bits, A[51:x], are supported only in an implementation that includes ARMv8.2-LPA and is using the 64KB translation granule.
- A translation table must be aligned to the size of the table, except that when using a translation table base address larger than 48 bits the minimum alignment of a table containing fewer than eight entries is 64 bytes.

In an implementation that includes ARMv8.2-LPA, if the value of VTCR_EL2.PS is `0b110`, then:

- Register bits[47:z] hold bits[47:z] of the stage 1 translation table base address, where z is determined as follows:
  - If x >= 6 then z=x.
  - Otherwise, z=6.
- Register bits[5:2] hold bits[51:48] of the stage 1 translation table base address.
- When z>x register bits[(z-1):x] are RES0, and bits[(z-1):x] of the translation table base address are zero.
- When x>6 register bits[(x-1):6] are RES0.
- Register bit[1] is RES0.
- Bits[5:2] of the stage 1 translation table base address are zero.
- In an implementation that includes ARMv8.2-TTCNP, bit[0] of the stage 1 translation table base address is zero.

Note

- In an implementation that includes ARMv8.2-LPA a VTCR_EL2.PS value of `0b110`, that selects a PA size of 52 bits, is permitted only when using the 64KB translation granule.
- When the value of ID_AA64MMFR0_EL1.PARange indicates that the implementation does not support a 52 bit PA size, if a translation table lookup uses this register with the 64KB translation granule when the value of VTCR_EL2.PS is `0b110` and the value of register bits[5:2] is nonzero, an Address size fault is generated.

If the Effective value of VTCR_EL2.PS is not `0b110` then:

- Register bits[47:x] hold bits[47:x] of the stage 1 translation table base address.
- Register bits[(x-1):1] are RES0.
- If the implementation supports 52-bit PAs and IPAs then bits[51:48] of the translation table base addresses used in this stage of translation are `0b0000`.

Note

This definition applies:

- To an implementation that includes ARMv8.2-LPA and is using a translation granule smaller than 64KB.
- To any implementation that does not include ARMv8.2-LPA.

If any VTTBR_EL2[47:0] bit that is defined as RES0 has the value 1 when a translation table walk is performed using VTTBR_EL2, then the translation table base address might be misaligned, with effects that are CONSTRAINED UNPREDICTABLE, and must be one of the following:

- Bits[x-1:0] of the translation table base address are treated as if all the bits are zero. The value read back from the corresponding register bits is either the value written to the register or zero.
- The result of the calculation of an address for a translation table walk using this register can be corrupted in those bits that are nonzero.

The AArch64 Virtual Memory System Architecture chapter describes how x is calculated based on the value of VTCR_EL2.T0SZ, the stage of translation, and the translation granule size.

This field resets to an architecturally UNKNOWN value.

CnP, bit [0]

When ARMv8.2-TTCNP is implemented:

Common not Private. This bit indicates whether each entry that is pointed to by VTTBR_EL2 is a member of a common set that can be used by every PE in the Inner Shareable domain for which the value of VTTBR_EL2.CnP is 1.

CnP	Meaning
0b0	The translation table entries pointed to by VTTBR_EL2 are permitted to differ from the entries for VTTBR_EL2 for other PEs in the Inner Shareable domain. This is not affected by the value of the current VMID.
0b1	The translation table entries pointed to by VTTBR_EL2 are the same as the translation table entries for every other PE in the Inner Shareable domain for which the value of VTTBR_EL2.CnP is 1 and the VMID is the same as the current VMID.

This field is permitted to be cached in a TLB.

Note

If the value of VTTBR_EL2.CnP bit is 1 on multiple PEs in the same Inner Shareable domain and those VTTBR_EL2s do not point to the same translation table entries when using the current VMID then the results of translations using VTTBR_EL2 are CONSTRAINED UNPREDICTABLE, see 'CONSTRAINED UNPREDICTABLE behaviors due to caching of control or data values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Accessing the VTTBR_EL2

Accesses to this register use the following encodings:

```
MRS <Xt>, VTTBR_EL2
```

op0	op1	CRn	CRm	op2
0b11	0b100	0b0010	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        return NVMem[0x020];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return VTTBR_EL2;
elsif PSTATE.EL == EL3 then
    return VTTBR_EL2;
```

MSR VTTBR_EL2, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b100	0b0010	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV> == '11' then
        NVMem[0x020] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    VTTBR_EL2 = X[t];
elsif PSTATE.EL == EL3 then
    VTTBR_EL2 = X[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ZCR_EL1, SVE Control Register for EL1

The ZCR_EL1 characteristics are:

Purpose

The SVE Control Register for EL1 is used to control aspects of SVE visible at Exception levels EL1 and EL0.

Configuration

This register is present only when SVE is implemented. Otherwise, direct accesses to ZCR_EL1 are UNDEFINED.

When HCR_EL2.{E2H, TGE} == {1, 1} and EL2 is enabled in the current Security state, the fields in this register have no effect on execution at EL0

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ZCR_EL1 is a 64-bit register.

Field descriptions

The ZCR_EL1 bit assignments are:



Bits [63:9]

Reserved, RES0.

Bits [8:4]

Reserved, RAZ/WI.

LEN, bits [3:0]

Constrains the scalable vector register length for EL1 and EL0 to (LEN+1)x128 bits. For all purposes other than returning the result of a direct read of ZCR_EL1 then this field behaves as if it is set to the minimum of the stored value and the constrained length inherited from more privileged Exception levels in the current Security state, rounded down to the nearest implemented vector length.

An indirect read of ZCR_EL1.LEN appears to occur in program order relative to a direct write of the same register, without the need for explicit synchronization.

This field resets to an architecturally UNKNOWN value.

Accessing the ZCR_EL1

When HCR_EL2.E2H is 1, without explicit synchronization, access from EL3 using the mnemonic ZCR_EL1 or ZCR_EL12 are not guaranteed to be ordered with respect to accesses using the other mnemonic.

Accesses to this register use the following encodings:

MRS <Xt>, ZCR_EL1

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if CPACR_EL1.ZEN == 'x0' then
        AArch64.SystemAccessTrap(EL1, 0x19);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TZ == '1' then
        AArch64.SystemAccessTrap(EL2, 0x19);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.ZEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x19);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.EZ == '0' then
        AArch64.SystemAccessTrap(EL3, 0x19);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        return NVMem[0x1E0];
    else
        return ZCR_EL1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TZ == '1' then
        AArch64.SystemAccessTrap(EL2, 0x19);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.ZEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x19);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.EZ == '0' then
        AArch64.SystemAccessTrap(EL3, 0x19);
    elsif HCR_EL2.E2H == '1' then
        return ZCR_EL2;
    else
        return ZCR_EL1;
elsif PSTATE.EL == EL3 then
    if CPTR_EL3.EZ == '0' then
        AArch64.SystemAccessTrap(EL3, 0x19);
    else
        return ZCR_EL1;
```

MSR ZCR_EL1, <Xt>

op0	op1	CRn	CRm	op2
0b11	0b000	0b0001	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if CPACR_EL1.ZEN == 'x0' then
        AArch64.SystemAccessTrap(EL1, 0x19);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TZ == '1' then
        AArch64.SystemAccessTrap(EL2, 0x19);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.ZEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x19);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.EZ == '0' then
        AArch64.SystemAccessTrap(EL3, 0x19);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<NV2,NV1,NV> == '111' then
        NVMem[0x1E0] = X[t];
    else
        ZCR_EL1 = X[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TZ == '1' then
        AArch64.SystemAccessTrap(EL2, 0x19);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.ZEN == 'x0' then
        AArch64.SystemAccessTrap(EL2, 0x19);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.EZ == '0' then
        AArch64.SystemAccessTrap(EL3, 0x19);
    elsif HCR_EL2.E2H == '1' then
        ZCR_EL2 = X[t];
    else
        ZCR_EL1 = X[t];
elsif PSTATE.EL == EL3 then
    if CPTR_EL3.EZ == '0' then
        AArch64.SystemAccessTrap(EL3, 0x19);
    else
        ZCR_EL1 = X[t];
```

MRS <Xt>, ZCR_EL12

op0	op1	CRn	CRm	op2
0b11	0b101	0b0001	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        return NVMem[0x1E0];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HCR_EL2.E2H == '0' && CPTR_EL2.TZ == '1' then
            AArch64.SystemAccessTrap(EL2, 0x19);
        elsif HCR_EL2.E2H == '1' && CPTR_EL2.ZEN == 'x0' then
            AArch64.SystemAccessTrap(EL2, 0x19);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.EZ == '0' then
            AArch64.SystemAccessTrap(EL3, 0x19);
        else
            return ZCR_EL1;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        if CPTR_EL3.EZ == '0' then
            AArch64.SystemAccessTrap(EL3, 0x19);
        else
            return ZCR_EL1;
    else
        UNDEFINED;
```

```
MSR ZCR_EL12, <Xt>
```

op0	op1	CRn	CRm	op2
0b11	0b101	0b0001	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && HCR_EL2.<NV2,NV1,NV> == '101' then
        NVMem[0x1E0] = X[t];
    elsif EL2Enabled() && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x18);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if EL2Enabled() && HCR_EL2.E2H == '1' then
        if HCR_EL2.E2H == '0' && CPTR_EL2.TZ == '1' then
            AArch64.SystemAccessTrap(EL2, 0x19);
        elsif HCR_EL2.E2H == '1' && CPTR_EL2.ZEN == 'x0' then
            AArch64.SystemAccessTrap(EL2, 0x19);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.EZ == '0' then
            AArch64.SystemAccessTrap(EL3, 0x19);
        else
            ZCR_EL1 = X[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' then
        if CPTR_EL3.EZ == '0' then
            AArch64.SystemAccessTrap(EL3, 0x19);
        else
            ZCR_EL1 = X[t];
    else
        UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AArch32 System Registers

ACTLR: Auxiliary Control Register

ACTLR2: Auxiliary Control Register 2

ADFSR: Auxiliary Data Fault Status Register

AIDR: Auxiliary ID Register

AIFSR: Auxiliary Instruction Fault Status Register

AMAIR0: Auxiliary Memory Attribute Indirection Register 0

AMAIR1: Auxiliary Memory Attribute Indirection Register 1

AMCFGR: Activity Monitors Configuration Register

AMCGCR: Activity Monitors Counter Group Configuration Register

AMCNTENCLR0: Activity Monitors Count Enable Clear Register 0

AMCNTENCLR1: Activity Monitors Count Enable Clear Register 1

AMCNTENSET0: Activity Monitors Count Enable Set Register 0

AMCNTENSET1: Activity Monitors Count Enable Set Register 1

AMCR: Activity Monitors Control Register

AMEVCNTR0<n>: Activity Monitors Event Counter Registers 0

AMEVCNTR1<n>: Activity Monitors Event Counter Registers 1

AMEVTYPER0<n>: Activity Monitors Event Type Registers 0

AMEVTYPER1<n>: Activity Monitors Event Type Registers 1

AMUSERENR: Activity Monitors User Enable Register

APSR: Application Program Status Register

CCSIDR: Current Cache Size ID Register

CCSIDR2: Current Cache Size ID Register 2

CLIDR: Cache Level ID Register

CNTFRQ: Counter-timer Frequency register

CNTHCTL: Counter-timer Hyp Control register

CNTHPS_CTL: Counter-timer Secure Physical Timer Control Register (EL2)

CNTHPS_CVAL: Counter-timer Secure Physical Timer CompareValue Register (EL2)

CNTHPS_TVAL: Counter-timer Secure Physical Timer TimerValue Register (EL2)

CNTHP_CTL: Counter-timer Hyp Physical Timer Control register

CNTHP_CVAL: Counter-timer Hyp Physical CompareValue register

CNTHP_TVAL: Counter-timer Hyp Physical Timer TimerValue register

CNTHVS_CTL: Counter-timer Secure Virtual Timer Control Register (EL2)

CNTHVS_CVAL: Counter-timer Secure Virtual Timer CompareValue Register (EL2)

CNTHVS_TVAL: Counter-timer Secure Virtual Timer TimerValue Register (EL2)

CNTHV_CTL: Counter-timer Virtual Timer Control register (EL2)

CNTHV_CVAL: Counter-timer Virtual Timer CompareValue register (EL2)

CNTHV_TVAL: Counter-timer Virtual Timer TimerValue register (EL2)

CNTKCTL: Counter-timer Kernel Control register

CNTPCT: Counter-timer Physical Count register

CNTPCTSS: Counter-timer Self-Synchronized Physical Count register

CNTP_CTL: Counter-timer Physical Timer Control register

CNTP_CVAL: Counter-timer Physical Timer CompareValue register

CNTP_TVAL: Counter-timer Physical Timer TimerValue register

CNTVCT: Counter-timer Virtual Count register

CNTVCTSS: Counter-timer Self-Synchronized Virtual Count register

CNTVOFF: Counter-timer Virtual Offset register

CNTV_CTL: Counter-timer Virtual Timer Control register

CNTV_CVAL: Counter-timer Virtual Timer CompareValue register

CNTV_TVAL: Counter-timer Virtual Timer TimerValue register

CONTEXTIDR: Context ID Register

CPACR: Architectural Feature Access Control Register

CPSR: Current Program Status Register

CSSELR: Cache Size Selection Register

CTR: Cache Type Register

DACR: Domain Access Control Register

DBGAUTHSTATUS: Debug Authentication Status register

DBGBCR<n>: Debug Breakpoint Control Registers

DBGBVR<n>: Debug Breakpoint Value Registers

DBGBXVR<n>: Debug Breakpoint Extended Value Registers

DBGCLAIMCLR: Debug CLAIM Tag Clear register

DBGCLAIMSET: Debug CLAIM Tag Set register

DBGDCCINT: DCC Interrupt Enable Register

DBGDEVID: Debug Device ID register 0

DBGDEVID1: Debug Device ID register 1

DBGDEVID2: Debug Device ID register 2

DBGDIDR: Debug ID Register

DBGDRAR: Debug ROM Address Register

DBGDSAR: Debug Self Address Register

DBGDSCRext: Debug Status and Control Register, External View

DBGDSCRint: Debug Status and Control Register, Internal View

DBGDTRRXext: Debug OS Lock Data Transfer Register, Receive, External View

DBGDTRRXint: Debug Data Transfer Register, Receive

DBGDTRTXext: Debug OS Lock Data Transfer Register, Transmit

DBGDTRTXint: Debug Data Transfer Register, Transmit

DBGOSDLR: Debug OS Double Lock Register

DBGOSECCR: Debug OS Lock Exception Catch Control Register

DBGOSLAR: Debug OS Lock Access Register

DBGOSLSR: Debug OS Lock Status Register

DBGPRCR: Debug Power Control Register

DBGVCR: Debug Vector Catch Register

DBGWCR<n>: Debug Watchpoint Control Registers

DBGWFAR: Debug Watchpoint Fault Address Register

DBGWVR<n>: Debug Watchpoint Value Registers

DFAR: Data Fault Address Register

DFSR: Data Fault Status Register

DISR: Deferred Interrupt Status Register

DLR: Debug Link Register

DSPSR: Debug Saved Program Status Register

ELR_hyp: Exception Link Register (Hyp mode)

ERRIDR: Error Record ID Register

ERRSELR: Error Record Select Register

ERXADDR: Selected Error Record Address Register

ERXADDR2: Selected Error Record Address Register 2

ERXCTLR: Selected Error Record Control Register

ERXCTLR2: Selected Error Record Control Register 2

ERXFR: Selected Error Record Feature Register

ERXFR2: Selected Error Record Feature Register 2

ERXMISC0: Selected Error Record Miscellaneous Register 0

ERXMISC1: Selected Error Record Miscellaneous Register 1

ERXMISC2: Selected Error Record Miscellaneous Register 2

ERXMISC3: Selected Error Record Miscellaneous Register 3

ERXMISC4: Selected Error Record Miscellaneous Register 4

ERXMISC5: Selected Error Record Miscellaneous Register 5

ERXMISC6: Selected Error Record Miscellaneous Register 6

ERXMISC7: Selected Error Record Miscellaneous Register 7

ERXSTATUS: Selected Error Record Primary Status Register

FCSEIDR: FCSE Process ID register

FPEXC: Floating-Point Exception Control register

FPSCR: Floating-Point Status and Control Register

FPSID: Floating-Point System ID register

HACR: Hyp Auxiliary Configuration Register

HACTLR: Hyp Auxiliary Control Register

HACTLR2: Hyp Auxiliary Control Register 2

HADFSR: Hyp Auxiliary Data Fault Status Register

HAIFSR: Hyp Auxiliary Instruction Fault Status Register

HAMAIR0: Hyp Auxiliary Memory Attribute Indirection Register 0

HAMAIR1: Hyp Auxiliary Memory Attribute Indirection Register 1

HCPTR: Hyp Architectural Feature Trap Register

HCR: Hyp Configuration Register

HCR2: Hyp Configuration Register 2

HDCR: Hyp Debug Control Register

HDFAR: Hyp Data Fault Address Register

HIFAR: Hyp Instruction Fault Address Register

HMAIR0: Hyp Memory Attribute Indirection Register 0

HMAIR1: Hyp Memory Attribute Indirection Register 1

HPFAR: Hyp IPA Fault Address Register

HRMR: Hyp Reset Management Register

HSCTLR: Hyp System Control Register

HSR: Hyp Syndrome Register

HSTR: Hyp System Trap Register

HTCR: Hyp Translation Control Register

HTPIDR: Hyp Software Thread ID Register

HTRFCR: Hyp Trace Filter Control Register

HTTBR: Hyp Translation Table Base Register

HVBAR: Hyp Vector Base Address Register

ICC_AP0R<n>: Interrupt Controller Active Priorities Group 0 Registers

ICC_AP1R<n>: Interrupt Controller Active Priorities Group 1 Registers

ICC_ASGI1R: Interrupt Controller Alias Software Generated Interrupt Group 1 Register

ICC_BPR0: Interrupt Controller Binary Point Register 0

ICC_BPR1: Interrupt Controller Binary Point Register 1

ICC_CTLR: Interrupt Controller Control Register

ICC_DIR: Interrupt Controller Deactivate Interrupt Register

ICC_EOIR0: Interrupt Controller End Of Interrupt Register 0

ICC_EOIR1: Interrupt Controller End Of Interrupt Register 1

ICC_HPPIR0: Interrupt Controller Highest Priority Pending Interrupt Register 0

ICC_HPPIR1: Interrupt Controller Highest Priority Pending Interrupt Register 1

ICC_HSRE: Interrupt Controller Hyp System Register Enable register

ICC_IAR0: Interrupt Controller Interrupt Acknowledge Register 0

ICC_IAR1: Interrupt Controller Interrupt Acknowledge Register 1

ICC_IGRPEN0: Interrupt Controller Interrupt Group 0 Enable register

ICC_IGRPEN1: Interrupt Controller Interrupt Group 1 Enable register

ICC_MCTLR: Interrupt Controller Monitor Control Register

ICC_MGRPEN1: Interrupt Controller Monitor Interrupt Group 1 Enable register

ICC_MSRE: Interrupt Controller Monitor System Register Enable register

ICC_PMR: Interrupt Controller Interrupt Priority Mask Register

ICC_RPR: Interrupt Controller Running Priority Register

ICC_SGI0R: Interrupt Controller Software Generated Interrupt Group 0 Register

ICC_SGI1R: Interrupt Controller Software Generated Interrupt Group 1 Register

ICC_SRE: Interrupt Controller System Register Enable register

ICH_AP0R<n>: Interrupt Controller Hyp Active Priorities Group 0 Registers

ICH_AP1R<n>: Interrupt Controller Hyp Active Priorities Group 1 Registers

ICH_EISR: Interrupt Controller End of Interrupt Status Register

ICH_ELRSR: Interrupt Controller Empty List Register Status Register

ICH_HCR: Interrupt Controller Hyp Control Register

ICH_LR<n>: Interrupt Controller List Registers

ICH_LRC<n>: Interrupt Controller List Registers

ICH_MISR: Interrupt Controller Maintenance Interrupt State Register

ICH_VMCR: Interrupt Controller Virtual Machine Control Register

ICH_VTR: Interrupt Controller VGIC Type Register

ICV_AP0R<n>: Interrupt Controller Virtual Active Priorities Group 0 Registers

ICV_AP1R<n>: Interrupt Controller Virtual Active Priorities Group 1 Registers

ICV_BPR0: Interrupt Controller Virtual Binary Point Register 0

ICV_BPR1: Interrupt Controller Virtual Binary Point Register 1

ICV_CTLR: Interrupt Controller Virtual Control Register

ICV_DIR: Interrupt Controller Deactivate Virtual Interrupt Register

ICV_EOIR0: Interrupt Controller Virtual End Of Interrupt Register 0

ICV_EOIR1: Interrupt Controller Virtual End Of Interrupt Register 1

ICV_HPPIR0: Interrupt Controller Virtual Highest Priority Pending Interrupt Register 0

ICV_HPPIR1: Interrupt Controller Virtual Highest Priority Pending Interrupt Register 1

ICV_IAR0: Interrupt Controller Virtual Interrupt Acknowledge Register 0

ICV_IAR1: Interrupt Controller Virtual Interrupt Acknowledge Register 1

ICV_IGRPEN0: Interrupt Controller Virtual Interrupt Group 0 Enable register

ICV_IGRPEN1: Interrupt Controller Virtual Interrupt Group 1 Enable register

ICV_PMR: Interrupt Controller Virtual Interrupt Priority Mask Register

ICV_RPR: Interrupt Controller Virtual Running Priority Register

ID_AFR0: Auxiliary Feature Register 0

ID_DFR0: Debug Feature Register 0

ID_DFR1: Debug Feature Register 1

ID_ISAR0: Instruction Set Attribute Register 0

ID_ISAR1: Instruction Set Attribute Register 1

ID_ISAR2: Instruction Set Attribute Register 2

ID_ISAR3: Instruction Set Attribute Register 3

ID_ISAR4: Instruction Set Attribute Register 4

ID_ISAR5: Instruction Set Attribute Register 5

ID_ISAR6: Instruction Set Attribute Register 6

ID_MMFR0: Memory Model Feature Register 0

ID_MMFR1: Memory Model Feature Register 1

ID_MMFR2: Memory Model Feature Register 2

ID_MMFR3: Memory Model Feature Register 3

ID_MMFR4: Memory Model Feature Register 4

ID_MMFR5: Memory Model Feature Register 5

ID_PFR0: Processor Feature Register 0

ID_PFR1: Processor Feature Register 1

ID_PFR2: Processor Feature Register 2

IFAR: Instruction Fault Address Register

IFSR: Instruction Fault Status Register

ISR: Interrupt Status Register

JIDR: Jazelle ID Register

JMCR: Jazelle Main Configuration Register

JOSCR: Jazelle OS Control Register

MAIR0: Memory Attribute Indirection Register 0

MAIR1: Memory Attribute Indirection Register 1

MIDR: Main ID Register

MPIDR: Multiprocessor Affinity Register

MVBAR: Monitor Vector Base Address Register

MVFR0: Media and VFP Feature Register 0

MVFR1: Media and VFP Feature Register 1

MVFR2: Media and VFP Feature Register 2

NMRR: Normal Memory Remap Register

NSACR: Non-Secure Access Control Register

PAR: Physical Address Register

PMCCFILTR: Performance Monitors Cycle Count Filter Register

PMCCNTR: Performance Monitors Cycle Count Register

PMCEID0: Performance Monitors Common Event Identification register 0

PMCEID1: Performance Monitors Common Event Identification register 1

PMCEID2: Performance Monitors Common Event Identification register 2

PMCEID3: Performance Monitors Common Event Identification register 3

PMCNTENCLR: Performance Monitors Count Enable Clear register

PMCNTENSET: Performance Monitors Count Enable Set register

PMCR: Performance Monitors Control Register

PMEVCNTR<n>: Performance Monitors Event Count Registers

PMEVTYPER<n>: Performance Monitors Event Type Registers

PMINTENCLR: Performance Monitors Interrupt Enable Clear register

PMINTENSET: Performance Monitors Interrupt Enable Set register

PMMIR: Performance Monitors Machine Identification Register

PMOVSR: Performance Monitors Overflow Flag Status Register

PMOVSSET: Performance Monitors Overflow Flag Status Set register

PMSELR: Performance Monitors Event Counter Selection Register

PMSWINC: Performance Monitors Software Increment register

PMUSERENR: Performance Monitors User Enable Register

PMXEVCNTR: Performance Monitors Selected Event Count Register

PMXEVTYPER: Performance Monitors Selected Event Type Register

PRRR: Primary Region Remap Register

REVIDR: Revision ID Register

RMR: Reset Management Register

RVBAR: Reset Vector Base Address Register

SCR: Secure Configuration Register

SCTLR: System Control Register

SDCR: Secure Debug Control Register

SDER: Secure Debug Enable Register

SPSR: Saved Program Status Register

SPSR_abt: Saved Program Status Register (Abort mode)

SPSR_fiq: Saved Program Status Register (FIQ mode)

SPSR_hyp: Saved Program Status Register (Hyp mode)

SPSR_irq: Saved Program Status Register (IRQ mode)

SPSR_mon: Saved Program Status Register (Monitor mode)

SPSR_svc: Saved Program Status Register (Supervisor mode)

SPSR_und: Saved Program Status Register (Undefined mode)

TCMTR: TCM Type Register

TLBTR: TLB Type Register

TPIDRPRW: PL1 Software Thread ID Register

TPIDRURO: PL0 Read-Only Software Thread ID Register

TPIDRURW: PL0 Read/Write Software Thread ID Register

TRFCR: Trace Filter Control Register

TTBCR: Translation Table Base Control Register

TTBCR2: Translation Table Base Control Register 2

TTBR0: Translation Table Base Register 0

TTBR1: Translation Table Base Register 1

VBAR: Vector Base Address Register

VDFSR: Virtual SError Exception Syndrome Register

VDISR: Virtual Deferred Interrupt Status Register

VMPIDR: Virtualization Multiprocessor ID Register

VPIDR: Virtualization Processor ID Register

VTCR: Virtualization Translation Control Register

VTTBR: Virtualization Translation Table Base Register

13~~27~~/12~~09~~/2019 15~~18~~:13~~49~~

Copyright Â© 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AArch32 System Instructions

ATS12NSOPR: Address Translate Stages 1 and 2 Non-secure Only PL1 Read

ATS12NSOPW: Address Translate Stages 1 and 2 Non-secure Only PL1 Write

ATS12NSOUR: Address Translate Stages 1 and 2 Non-secure Only Unprivileged Read

ATS12NSOUW: Address Translate Stages 1 and 2 Non-secure Only Unprivileged Write

ATS1CPR: Address Translate Stage 1 Current state PL1 Read

ATS1CPRP: Address Translate Stage 1 Current state PL1 Read PAN

ATS1CPW: Address Translate Stage 1 Current state PL1 Write

ATS1CPWP: Address Translate Stage 1 Current state PL1 Write PAN

ATS1CUR: Address Translate Stage 1 Current state Unprivileged Read

ATS1CUW: Address Translate Stage 1 Current state Unprivileged Write

ATS1HR: Address Translate Stage 1 Hyp mode Read

ATS1HW: Address Translate Stage 1 Hyp mode Write

BPIALL: Branch Predictor Invalidate All

BPIALLIS: Branch Predictor Invalidate All, Inner Shareable

BPIMVA: Branch Predictor Invalidate by VA

CFPRCTX: Control Flow Prediction Restriction by Context

CP15DMB: Data Memory Barrier System instruction

CP15DSB: Data Synchronization Barrier System instruction

CP15ISB: Instruction Synchronization Barrier System instruction

CPPRCTX: Cache Prefetch Prediction Restriction by Context

DCCIMVAC: Data Cache line Clean and Invalidate by VA to PoC

DCCISW: Data Cache line Clean and Invalidate by Set/Way

DCCMVAC: Data Cache line Clean by VA to PoC

DCCMVAU: Data Cache line Clean by VA to PoU

DCCSW: Data Cache line Clean by Set/Way

DCIMVAC: Data Cache line Invalidate by VA to PoC

DCISW: Data Cache line Invalidate by Set/Way

DTLBIALL: Data TLB Invalidate All

DTLBIASID: Data TLB Invalidate by ASID match

DTLBIMVA: Data TLB Invalidate by VA

DVPRCTX: Data Value Prediction Restriction by Context

ICIALLU: Instruction Cache Invalidate All to PoU

ICIALLUIS: Instruction Cache Invalidate All to PoU, Inner Shareable

ICIMVAU: Instruction Cache line Invalidate by VA to PoU

ITLBIALL: Instruction TLB Invalidate All

ITLBIASID: Instruction TLB Invalidate by ASID match

ITLBIMVA: Instruction TLB Invalidate by VA

TLBIALL: TLB Invalidate All

TLBIALLH: TLB Invalidate All, Hyp mode

TLBIALLHIS: TLB Invalidate All, Hyp mode, Inner Shareable

TLBIALLIS: TLB Invalidate All, Inner Shareable

TLBIALLNSNH: TLB Invalidate All, Non-Secure Non-Hyp

TLBIALLNSNHIS: TLB Invalidate All, Non-Secure Non-Hyp, Inner Shareable

TLBIASID: TLB Invalidate by ASID match

TLBIASIDIS: TLB Invalidate by ASID match, Inner Shareable

TLBIIPAS2: TLB Invalidate by Intermediate Physical Address, Stage 2

TLBIIPAS2IS: TLB Invalidate by Intermediate Physical Address, Stage 2, Inner Shareable

TLBIIPAS2L: TLB Invalidate by Intermediate Physical Address, Stage 2, Last level

TLBIIPAS2LIS: TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, Inner Shareable

TLBIMVA: TLB Invalidate by VA

TLBIMVAA: TLB Invalidate by VA, All ASID

TLBIMVAAIS: TLB Invalidate by VA, All ASID, Inner Shareable

TLBIMVAAL: TLB Invalidate by VA, All ASID, Last level

TLBIMVAALIS: TLB Invalidate by VA, All ASID, Last level, Inner Shareable

TLBIMVAH: TLB Invalidate by VA, Hyp mode

TLBIMVAHIS: TLB Invalidate by VA, Hyp mode, Inner Shareable

TLBIMVAIS: TLB Invalidate by VA, Inner Shareable

TLBIMVAL: TLB Invalidate by VA, Last level

TLBIMVALH: TLB Invalidate by VA, Last level, Hyp mode

TLBIMVALHIS: TLB Invalidate by VA, Last level, Hyp mode, Inner Shareable

TLBIMVALIS: TLB Invalidate by VA, Last level, Inner Shareable

1327/1209/2019 1518:1349

Copyright Â© 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ACTLR, Auxiliary Control Register

The ACTLR characteristics are:

Purpose

Provides IMPLEMENTATION DEFINED configuration and control options for execution at EL1 and EL0.

Configuration

AArch32 System register ACTLR bits [31:0] are architecturally mapped to AArch64 System register ACTLR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ACTLR are UNKNOWN.

Some bits might define global configuration settings, and be common to the Secure and Non-secure instances of the register.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ACTLR is a 32-bit register.

Field descriptions

The ACTLR bit assignments are:



IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the ACTLR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TACR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TAC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return ACTLR_S;
        else
            return ACTLR_NS;
    else
        return ACTLR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return ACTLR_NS;
    else
        return ACTLR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return ACTLR_S;
    else
        return ACTLR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TACR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TAC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            ACTLR_S = R[t];
        else
            ACTLR_NS = R[t];
    else
        ACTLR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        ACTLR_NS = R[t];
    else
        ACTLR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        ACTLR_S = R[t];
    else
        ACTLR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ACTLR2, Auxiliary Control Register 2

The ACTLR2 characteristics are:

Purpose

Provides additional space to the ACTLR register to hold IMPLEMENTATION DEFINED trap functionality for execution at EL1 and EL0.

Configuration

AArch32 System register ACTLR2 bits [31:0] are architecturally mapped to AArch64 System register ACTLR_EL1[63:32] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ACTLR2 are UNKNOWN.

In Armv8.0 and Armv8.1, it is IMPLEMENTATION DEFINED whether this register is implemented, or whether it causes UNDEFINED exceptions when accessed. The implementation of this register can be detected by examining ID_MMFR4.AC2.

From Armv8.2 this register must be implemented.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ACTLR2 is a 32-bit register.

Field descriptions

The ACTLR2 bit assignments are:



IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the ACTLR2

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TACR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TAC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return ACTLR2_S;
        else
            return ACTLR2_NS;
    else
        return ACTLR2;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return ACTLR2_NS;
    else
        return ACTLR2;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return ACTLR2_S;
    else
        return ACTLR2_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TACR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TAC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            ACTLR2_S = R[t];
        else
            ACTLR2_NS = R[t];
    else
        ACTLR2 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        ACTLR2_NS = R[t];
    else
        ACTLR2 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        ACTLR2_S = R[t];
    else
        ACTLR2_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ADFSR, Auxiliary Data Fault Status Register

The ADFSR characteristics are:

Purpose

Provides additional IMPLEMENTATION DEFINED fault status information for Data Abort exceptions taken to EL1 modes, and EL3 modes when EL3 is implemented and is using AArch32.

Configuration

AArch32 System register ADFSR bits [31:0] are architecturally mapped to AArch64 System register AFSR0_EL1[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to ADFSR arearchitecturally UNKNOWN.values.

Attributes

ADFSR is a 32-bit register.

Field descriptions

The ADFSR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
IMPLEMENTATION DEFINED																															

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the ADFSR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return ADFSR_S;
        else
            return ADFSR_NS;
    else
        return ADFSR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return ADFSR_NS;
    else
        return ADFSR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return ADFSR_S;
    else
        return ADFSR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            ADFSR_S = R[t];
        else
            ADFSR_NS = R[t];
    else
        ADFSR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        ADFSR_NS = R[t];
    else
        ADFSR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        ADFSR_S = R[t];
    else
        ADFSR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AIDR, Auxiliary ID Register

The AIDR characteristics are:

Purpose

Provides IMPLEMENTATION DEFINED identification information.

The value of this register must be used in conjunction with the value of MIDR.

Configuration

AArch32 System register AIDR bits [31:0] are architecturally mapped to AArch64 System register AIDR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to AIDR are UNKNOWN.

Attributes

AIDR is a 32-bit register.

Field descriptions

The AIDR bit assignments are:



IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

Accessing the AIDR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b001	0b0000	0b0000	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return AIDR;
elsif PSTATE.EL == EL2 then
    return AIDR;
elsif PSTATE.EL == EL3 then
    return AIDR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AIFSR, Auxiliary Instruction Fault Status Register

The AIFSR characteristics are:

Purpose

Provides additional IMPLEMENTATION DEFINED fault status information for Prefetch Abort exceptions taken to EL1 modes, and EL3 modes when EL3 is implemented and is using AArch32.

Configuration

AArch32 System register AIFSR bits [31:0] are architecturally mapped to AArch64 System register AFSR1_EL1[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to AIFSR arearchitecturally UNKNOWN.values.

Attributes

AIFSR is a 32-bit register.

Field descriptions

The AIFSR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
IMPLEMENTATION DEFINED																															

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the AIFSR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return AIFSR_S;
        else
            return AIFSR_NS;
    else
        return AIFSR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return AIFSR_NS;
    else
        return AIFSR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return AIFSR_S;
    else
        return AIFSR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            AIFSR_S = R[t];
        else
            AIFSR_NS = R[t];
    else
        AIFSR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        AIFSR_NS = R[t];
    else
        AIFSR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        AIFSR_S = R[t];
    else
        AIFSR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMAIR0, Auxiliary Memory Attribute Indirection Register 0

The AMAIR0 characteristics are:

Purpose

When using the Long-descriptor format translation tables for stage 1 translations, provides IMPLEMENTATION DEFINED memory attributes for the memory regions specified by MAIR0.

Configuration

AArch32 System register AMAIR0 bits [31:0] are architecturally mapped to AArch64 System register AMAIR_EL1[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to AMAIR0 arearchitecturally UNKNOWN.values.

Attributes

AMAIR0 is a 32-bit register.

Field descriptions

The AMAIR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
IMPLEMENTATION DEFINED																															

This register is RES0 in the following cases:

- When an implementation does not provide any IMPLEMENTATION DEFINED memory attributes.
- When the Long-descriptor translation table format is not used.

If EL3 is implemented and is using AArch32:

- AMAIR0(S) gives the value for memory accesses from Secure state.
- AMAIR0(NS) gives the value for memory accesses from Non-secure states other than Hyp mode.

Any IMPLEMENTATION DEFINED memory attributes are additional qualifiers for the memory locations and must not change the architected behavior specified by MAIR0 and MAIR1.

In a typical implementation, AMAIR0 and AMAIR1 split into eight one-byte fields, corresponding to the MAIRn.Attr<n> fields, but the architecture does not require them to do so.

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the AMAIR0

Accesses to this register use the following encodings:

MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return AMAIR0_S;
        else
            return AMAIR0_NS;
    else
        return AMAIR0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return AMAIR0_NS;
    else
        return AMAIR0;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return AMAIR0_S;
    else
        return AMAIR0_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            AMAIR0_S = R[t];
        else
            AMAIR0_NS = R[t];
    else
        AMAIR0 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        AMAIR0_NS = R[t];
    else
        AMAIR0 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            AMAIR0_S = R[t];
        else
            AMAIR0_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMAIR1, Auxiliary Memory Attribute Indirection Register 1

The AMAIR1 characteristics are:

Purpose

When using the Long-descriptor format translation tables for stage 1 translations, provides IMPLEMENTATION DEFINED memory attributes for the memory regions specified by MAIR1.

Configuration

AArch32 System register AMAIR1 bits [31:0] are architecturally mapped to AArch64 System register AMAIR_EL1[63:32] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to AMAIR1 are UNKNOWN.

When EL3 is using AArch32, write access to AMAIR1(S) is disabled when the CP15SDISABLE signal is asserted HIGH.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AMAIR1 is a 32-bit register.

Field descriptions

The AMAIR1 bit assignments are:



This register is RES0 in the following cases:

- When an implementation does not provide any IMPLEMENTATION DEFINED memory attributes.
- When the Long-descriptor translation table format is not used.

If EL3 is implemented and is using AArch32:

- AMAIR1(S) gives the value for memory accesses from Secure state.
- AMAIR1(NS) gives the value for memory accesses from Non-secure states other than Hyp mode.

Any IMPLEMENTATION DEFINED memory attributes are additional qualifiers for the memory locations and must not change the architected behavior specified by MAIR0 and MAIR1.

In a typical implementation, AMAIR0 and AMAIR1 split into eight one-byte fields, corresponding to the MAIRn.Attr<n> fields, but the architecture does not require them to do so.

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the AMAIR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return AMAIR1_S;
        else
            return AMAIR1_NS;
    else
        return AMAIR1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return AMAIR1_NS;
    else
        return AMAIR1;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return AMAIR1_S;
    else
        return AMAIR1_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            AMAIR1_S = R[t];
        else
            AMAIR1_NS = R[t];
    else
        AMAIR1 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        AMAIR1_NS = R[t];
    else
        AMAIR1 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            AMAIR1_S = R[t];
        else
            AMAIR1_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMCNTENCLR1, Activity Monitors Count Enable Clear Register 1

The AMCNTENCLR1 characteristics are:

Purpose

Disable control bits for the auxiliary activity monitors event counters, AMEVCNTR1<n>.

Configuration

AArch32 System register AMCNTENCLR1 bits [31:0] are architecturally mapped to AArch64 System register AMCNTENCLR1_EL0[31:0] .

AArch32 System register AMCNTENCLR1 bits [31:0] are architecturally mapped to External register AMCNTENCLR1[31:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMCNTENCLR1 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AMCNTENCLR1 is a 32-bit register.

Field descriptions

The AMCNTENCLR1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																P<n>, bit [n]															

Bits [31:16]

Reserved, RES0.

P<n>, bit [n], for n = 0 to 15

Activity monitor event counter disable bit for AMEVCNTR1<n>.

Bits [31:16] are RES0. Bits [15:N] are RAZ/WI. N is the value in AMCGCR_EL0.CG1NC.

Possible values of each bit are:

P<n>	Meaning
0b0	When read, means that AMEVCNTR1<n> is disabled. When written, has no effect.
0b1	When read, means that AMEVCNTR1<n> is enabled. When written, disables AMEVCNTR1<n>.

On a Cold reset, this field resets to 0.

Accessing the AMCNTENCLR1

- ~~Accesses to the register are UNDEFINED.~~
- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If the number of auxiliary activity monitor event counters implemented is zero, reads and writes of AMCNTENCLR1 are UNDEFINED~~CONSTRAINED UNPREDICTABLE.~~, ~~and the following behaviors are permitted:~~

Note

The number of auxiliary activity monitor event counters implemented is zero exactly when AMCFGR.NCG == `0b0000`.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && AMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T13 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HAFGRTR_EL2.AMCNTEN1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMCNTENCLR1;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMCNTENCLR1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMCNTENCLR1;
elsif PSTATE.EL == EL3 then
    return AMCNTENCLR1;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0011	0b000

```
if PSTATE.EL == EL1 && EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
    AArch64.AArch32SystemAccessTrap(EL2, 0x03);
elsif PSTATE.EL == EL1 && EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
    AArch32.TakeHypTrapException(0x03);
elsif IsHighestEL(PSTATE.EL) then
    AMCNTENCLR1 = R[t];
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMCNTENSET1, Activity Monitors Count Enable Set Register 1

The AMCNTENSET1 characteristics are:

Purpose

Enable control bits for the auxiliary activity monitors event counters, AMEVCNTR1<n>.

Configuration

AArch32 System register AMCNTENSET1 bits [31:0] are architecturally mapped to AArch64 System register AMCNTENSET1_EL0[31:0] .

AArch32 System register AMCNTENSET1 bits [31:0] are architecturally mapped to External register AMCNTENSET1[31:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMCNTENSET1 are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AMCNTENSET1 is a 32-bit register.

Field descriptions

The AMCNTENSET1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																P<n>, bit [n]															

Bits [31:16]

Reserved, RES0.

P<n>, bit [n], for n = 0 to 15

Activity monitor event counter enable bit for AMEVCNTR1<n>.

Bits [31:16] are RES0. Bits [15:N] are RAZ/WI. N is the value in AMCGCR.CG1NC.

Possible values of each bit are:

P<n>	Meaning
0b0	When read, means that AMEVCNTR1<n> is disabled. When written, has no effect.
0b1	When read, means that AMEVCNTR1<n> is enabled. When written, enables AMEVCNTR1<n>.

On a Cold reset, this field resets to 0.

Accessing the AMCNTENSET1

- ~~Accesses to the register are UNDEFINED.~~
- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If the number of auxiliary activity monitor event counters implemented is zero, reads and writes of AMCNTENSET1 are UNDEFINED~~CONSTRAINED UNPREDICTABLE.~~, ~~and the following behaviors are permitted:~~

Note

The number of auxiliary activity monitor counters implemented is zero when AMCFGR.NCG == `0b0000`.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && AMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T13 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HAFGRTR_EL2.AMCNTEN1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMCNTENSET1;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMCNTENSET1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMCNTENSET1;
elsif PSTATE.EL == EL3 then
    return AMCNTENSET1;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0011	0b001

```
if PSTATE.EL == EL1 && EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
    AArch64.AArch32SystemAccessTrap(EL2, 0x03);
elsif PSTATE.EL == EL1 && EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
    AArch32.TakeHypTrapException(0x03);
elsif IsHighestEL(PSTATE.EL) then
    AMCNTENSET1 = R[t];
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMCR, Activity Monitors Control Register

The AMCR characteristics are:

Purpose

Global control register for the activity monitors implementation. AMCR is applicable to both the architected and the auxiliary counter groups.

Configuration

AArch32 System register AMCR bits [31:0] are architecturally mapped to AArch64 System register AMCR_EL0[31:0] .

AArch32 System register AMCR bits [31:0] are architecturally mapped to External register AMCR[31:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMCR are UNDEFINED.

Attributes

AMCR is a 32-bit register.

Field descriptions

The AMCR bit assignments are:



Bits [31:18]

Reserved, RES0.

CG1RZ, bit [17]

When ARMv8.6-AMU is implemented:

Counter Group 1 Read Zero.

CG1RZ	Meaning
0b0	System register reads of AMEVCNTR1<n> return the event count at all implemented and enabled Exception levels.
0b1	If the current Exception level is the highest implemented Exception level, system register reads of AMEVCNTR1<n> return the event count. Otherwise, reads of AMEVCNTR1<n> return a zero value.

Note

Reads from the memory-mapped view are unaffected by this field.

Otherwise:

Reserved, RES0.

Bits [16:11]

Reserved, RES0.

HDBG, bit [10]

This bit controls whether activity monitor counting is halted when the PE is halted in Debug state.

HDBG	Meaning
0b0	Activity monitors do not halt counting when the PE is halted in Debug state.
0b1	Activity monitors halt counting when the PE is halted in Debug state.

Bits [9:0]

Reserved, RES0.

Accessing the AMCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && AMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T13 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMCR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMCR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMCR;
elsif PSTATE.EL == EL3 then
    return AMCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && AMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T13 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        AMCR = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        AMCR = R[t];
elsif IsHighestELPSTATE.EL == EL2 then
    if HaveEL(PSTATE.ELEL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        AMCR = R[t];
elseelsif PSTATE.EL == EL3 then
    UNDEFINED;AMCR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMEVCNTR0<n>, Activity Monitors Event Counter Registers 0, n = 0 - 15

The AMEVCNTR0<n> characteristics are:

Purpose

Provides access to the architected activity monitor event counters.

Configuration

AArch32 System register AMEVCNTR0<n> bits [63:0] are architecturally mapped to AArch64 System register AMEVCNTR0<n>_EL0[63:0] .

AArch32 System register AMEVCNTR0<n> bits [63:0] are architecturally mapped to External register AMEVCNTR0<n>[63:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMEVCNTR0<n> are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AMEVCNTR0<n> is a 64-bit register.

Field descriptions

The AMEVCNTR0<n> bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ACNT																															
ACNT																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

ACNT, bits [63:0]

Architected activity monitor event counter n.

Value of architected activity monitor event counter n, where n is the number of this register and is a number from 0 to 15.

If ARMv8.6-AMU is implemented, HCR_EL2.AMVOFFEN is 1, SCR_EL3.AMVOFFEN is 1, HCR_EL2.{E2H, TGE} is not {1,1}, and EL2 is using AArch64 and is implemented in the current Security state, access to these registers at EL0 or EL1 return (PCount<63:0> - AMEVCNTVOFF0<n>_EL2<63:0>).

PCount is the physical count returned when AMEVCNTR0<n> is read from EL2 or EL3.

If the counter is enabled, writes to this register have UNPREDICTABLE results.

On a Cold reset, this field resets to `0`.

Accessing the AMEVCNTR0<n>

- ~~Accesses to the register are UNDEFINED.~~

- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If <n> is greater than or equal to the number of architected activity monitor event counters, reads and writes of AMEVCNTR0<n> are UNDEFINED~~CONSTRAINED UNPREDICTABLE~~.~~, and the following behaviors are permitted:~~

Note

AMCGCR.CG0NC identifies the number of architected activity monitor event counters.

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b000:n[3]	0b0:n[2:0]

```
if CRm == '0000'0 then
    if PSTATE.EL == EL0 then
        if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
            if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
                AArch64.AArch32SystemAccessTrap(EL2, 0x04);
            else
                AArch64.AArch32SystemAccessTrap(EL1, 0x04);
        elsif ELUsingAArch32(EL1) && AMUSERENR.EN == '0' then
            if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
                AArch64.AArch32SystemAccessTrap(EL2, 0x04);
            elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
                AArch32.TakeHypTrapException(0x00);
            else
                UNDEFINED;
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T0 ==
'1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3)
|| SCR_EL3.FGTEn == '1') && HAFGRTR_EL2.AMEVCNTR0<n>_EL0 == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        else
            return AMEVCNTR0[UInt(CRm<0>:opc1<2:0>)];
    elsif PSTATE.EL == EL1 then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        else
            return AMEVCNTR0[UInt(CRm<0>:opc1<2:0>)];
    elsif PSTATE.EL == EL2 then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        else
            return AMEVCNTR0[UInt(CRm<0>:opc1<2:0>)];
    elsif PSTATE.EL == EL3 then
        return AMEVCNTR0[UInt(CRm<0>:opc1<2:0>)];
else
    UNDEFINED;
```

MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b000:n[3]	0b0:n[2:0]

```
if CRm == '0000'0 then
    if PSTATE.EL == EL1 && EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif PSTATE.EL == EL1 && EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif IsHighestEL(PSTATE.EL) then
        AMEVCNTR0[UInt(CRm<0>:opc1<2:0>)] = R[t2]:R[t];
    else
        UNDEFINED;
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMEVCNTR1<n>, Activity Monitors Event Counter Registers 1, n = 0 - 15

The AMEVCNTR1<n> characteristics are:

Purpose

Provides access to the auxiliary activity monitor event counters.

Configuration

AArch32 System register AMEVCNTR1<n> bits [63:0] are architecturally mapped to AArch64 System register AMEVCNTR1<n>_EL0[63:0] .

AArch32 System register AMEVCNTR1<n> bits [63:0] are architecturally mapped to External register AMEVCNTR1<n>[63:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMEVCNTR1<n> are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

AMEVCNTR1<n> is a 64-bit register.

Field descriptions

The AMEVCNTR1<n> bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ACNT																															
ACNT																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

ACNT, bits [63:0]

Auxiliary activity monitor event counter n.

Value of auxiliary activity monitor event counter n, where n is the number of this register and is a number from 0 to 15.

If ARMv8.6-AMU is implemented, HCR_EL2.AMVOFFEN is 1, SCR_EL3.AMVOFFEN is 1, HCR_EL2.{E2H, TGE} is not {1,1}, EL2 is using AArch64 and is implemented in the current Security state, and AMCR_EL0.CG1RZ is 0, reads to these registers at EL0 or EL1 return (PCount<63:0> - AMEVCNTVOFF1<n>_EL2<63:0>).

PCount is the physical count returned when AMEVCNTR1<n> is read from EL2 or EL3.

If the counter is enabled, writes to this register have UNPREDICTABLE results.

On a Cold reset, this field resets to `0`.

Accessing the AMEVCNTR1<n>

- ~~Accesses to the register are UNDEFINED.~~

- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If <n> is greater than or equal to the number of auxiliary activity monitor event counters, reads and writes of AMEVCNTR1<n> are UNDEFINED~~CONSTRAINED UNPREDICTABLE~~.~~, and the following behaviors are permitted:~~

Note

AMCGCR.CG1NC identifies the number of auxiliary activity monitor event counters.

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b010:n[3]	~~0b0:~~n[2:0]

```
if CRm == '0100'100 then
    if PSTATE.EL == EL0 then
        if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
            if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
                AArch64.AArch32SystemAccessTrap(EL2, 0x04);
            else
                AArch64.AArch32SystemAccessTrap(EL1, 0x04);
        elsif ELUsingAArch32(EL1) && AMUSERENR.EN == '0' then
            if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
                AArch64.AArch32SystemAccessTrap(EL2, 0x04);
            elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
                AArch32.TakeHypTrapException(0x00);
            else
                UNDEFINED;
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T4 ==
'1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T4 == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3)
|| SCR_EL3.FGTEn == '1') && HAFGRTR_EL2.AMEVCNTR1<n>_EL0 == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        elsif !HighestELUsingAArch32() && AMCR_EL0.CG1RZ == '1' then
            Zeros();
        elsif HighestELUsingAArch32() && AMCR.CG1RZ == '1' then
            Zeros();
        else
            return AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)];
    elsif PSTATE.EL == EL1 then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T4 == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T4 == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        elsif !IsHighestEL(PSTATE.EL) && !HighestELUsingAArch32() && AMCR_EL0.CG1RZ == '1' then
            Zeros();
        elsif !IsHighestEL(PSTATE.EL) && HighestELUsingAArch32() && AMCR.CG1RZ == '1' then
            Zeros();
        else
            return AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)];
    elsif PSTATE.EL == EL2 then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        elsif !IsHighestEL(PSTATE.EL) && !HighestELUsingAArch32() && AMCR_EL0.CG1RZ == '1' then
            Zeros();
        elsif !IsHighestEL(PSTATE.EL) && HighestELUsingAArch32() && AMCR.CG1RZ == '1' then
            Zeros();
        else
            return AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)];
    elsif PSTATE.EL == EL3 then
        return AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)];
elsif CRm == '0101'101 then
    if PSTATE.EL == EL0 then
        if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
            if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
                AArch64.AArch32SystemAccessTrap(EL2, 0x04);
            else
                AArch64.AArch32SystemAccessTrap(EL1, 0x04);
        elsif ELUsingAArch32(EL1) && AMUSERENR.EN == '0' then
```

```
            if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
                AArch64.AArch32SystemAccessTrap(EL2, 0x04);
            elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
                AArch32.TakeHypTrapException(0x00);
            else
                UNDEFINED;
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T5 ==
'1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3)
|| SCR_EL3.FGTEn == '1') && HAFGRTR_EL2.AMEVCNTR1<n>_EL0 == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        elsif !HighestELUsingAArch32() && AMCR_EL0.CG1RZ == '1' then
            Zeros();
        elsif HighestELUsingAArch32() && AMCR.CG1RZ == '1' then
            Zeros();
        else
            return AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)];
    elsif PSTATE.EL == EL1 then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        elsif !IsHighestEL(PSTATE.EL) && !HighestELUsingAArch32() && AMCR_EL0.CG1RZ == '1' then
            Zeros();
        elsif !IsHighestEL(PSTATE.EL) && HighestELUsingAArch32() && AMCR.CG1RZ == '1' then
            Zeros();
        else
            return AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)];
    elsif PSTATE.EL == EL2 then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        elsif !IsHighestEL(PSTATE.EL) && !HighestELUsingAArch32() && AMCR_EL0.CG1RZ == '1' then
            Zeros();
        elsif !IsHighestEL(PSTATE.EL) && HighestELUsingAArch32() && AMCR.CG1RZ == '1' then
            Zeros();
        else
            return AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)];
    elsif PSTATE.EL == EL3 then
        return AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)];
else
    UNDEFINED;
```

```
MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b010:n[3]	0b0:n[2:0]

```
if CRm == 100 then
    if PSTATE.EL == EL0 then
        if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '01000' then
            if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
                AArch64.AArch32SystemAccessTrap(EL2, 0x04);
            else
                AArch64.AArch32SystemAccessTrap(EL1, 0x04);
        elsif ELUsingAArch32(EL1) && AMUSERENR.EN == '0' then
            if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
                AArch64.AArch32SystemAccessTrap(EL2, 0x04);
            elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
                AArch32.TakeHypTrapException(0x00);
            else
                UNDEFINED;
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T4 ==
'1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T4 == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        else
            AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)] = R[t2]:R[t];
    elsif PSTATE.EL == EL1 then
        if IsHighestELEL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T4 == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T4 == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        else
            AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)] = R[t2]:R[t];
    elsif PSTATE.EL == EL2 then
        if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        else
            AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)] = R[t2]:R[t];
    elseelsif PSTATE.EL == EL3 then
        UNDEFINED;AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)] = R[t2]:R[t];
elsif CRm == '0101'101 then
    if PSTATE.EL == EL0 then
        if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
            if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
                AArch64.AArch32SystemAccessTrap(EL2, 0x04);
            else
                AArch64.AArch32SystemAccessTrap(EL1, 0x04);
        elsif ELUsingAArch32(EL1) && AMUSERENR.EN == '0' then
            if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
                AArch64.AArch32SystemAccessTrap(EL2, 0x04);
            elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
                AArch32.TakeHypTrapException(0x00);
            else
                UNDEFINED;
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T5 ==
'1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
            AArch32.TakeHypTrapException(0x04);
```

```
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        else
            AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)] = R[t2]:R[t];
    elsif PSTATE.EL == EL1 then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
            AArch32.TakeHypTrapException(0x04);
        elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        else
            AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)] = R[t2]:R[t];
    elsif IsHighestELPSTATE.EL == EL2 then
        if HaveEL(PSTATE.ELEL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
            AArch64.AArch32SystemAccessTrap(EL3, 0x04);
        else
            AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)] = R[t2]:R[t];
    elseelsif PSTATE.EL == EL3 then
        UNDEFINED;AMEVCNTR1[UInt(CRm<0>:opc1<2:0>)] = R[t2]:R[t];
else
    UNDEFINED;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMEVTYPER0<n>, Activity Monitors Event Type Registers 0, n = 0 - 15

The AMEVTYPER0<n> characteristics are:

Purpose

Provides information on the events that an architected activity monitor event counter AMEVCNTR0<n> counts.

Configuration

AArch32 System register AMEVTYPER0<n> bits [31:0] are architecturally mapped to AArch64 System register AMEVTYPER0<n>_EL0[31:0] .

AArch32 System register AMEVTYPER0<n> bits [31:0] are architecturally mapped to External register AMEVTYPER0<n>[31:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMEVTYPER0<n> are UNDEFINED.

Attributes

AMEVTYPER0<n> is a 32-bit register.

Field descriptions

The AMEVTYPER0<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																evtCount															

Bits [31:16]

Reserved, RES0.

evtCount, bits [15:0]

Event to count. The event number of the event that is counted by the architected activity monitor event counter AMEVCNTR0<n>. The value of this field is architecturally mandated for each architected counter.

The following table shows the mapping between required event numbers and the corresponding counters:

evtCount	Meaning	Applies when
0x0011	Processor frequency cycles	When n == 0
0x4004	Constant frequency cycles	When n == 1
0x0008	Instructions retired	When n == 2
0x4005	Memory stall cycles	When n == 3

Accessing the AMEVTYPER0<n>

- ~~Accesses to the register are UNDEFINED.~~
- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If <n> is greater than or equal to the number of architected activity monitor event counters, reads and writes of AMEVTYPER0<n> are NDEFINED.

~~If <n> is greater than or equal to the number of architected activity monitor event counters, reads and writes of AMEVTYPER0<n> are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:~~

Note

AMCGCR.CG0NC identifies the number of architected activity monitor event counters.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b011:n[3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && AMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T13 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMEVTYPER0[UInt(CRm<0>:opc2<2:0>)];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMEVTYPER0[UInt(CRm<0>:opc2<2:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMEVTYPER0[UInt(CRm<0>:opc2<2:0>)];
elsif PSTATE.EL == EL3 then
    return AMEVTYPER0[UInt(CRm<0>:opc2<2:0>)];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMEVTYPER1<n>, Activity Monitors Event Type Registers 1, n = 0 - 15

The AMEVTYPER1<n> characteristics are:

Purpose

Provides information on the events that an auxiliary activity monitor event counter AMEVCNTR1<n> counts.

Configuration

AArch32 System register AMEVTYPER1<n> bits [31:0] are architecturally mapped to AArch64 System register AMEVTYPER1<n>_EL0[31:0] .

AArch32 System register AMEVTYPER1<n> bits [31:0] are architecturally mapped to External register AMEVTYPER1<n>[31:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMEVTYPER1<n> are UNDEFINED.

Attributes

AMEVTYPER1<n> is a 32-bit register.

Field descriptions

The AMEVTYPER1<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																evtCount															

Bits [31:16]

Reserved, RES0.

evtCount, bits [15:0]

Event to count. The event number of the event that is counted by the auxiliary activity monitor event counter AMEVCNTR1<n>.

It is IMPLEMENTATION DEFINED what values are supported by each counter.

If software writes a value to this field which is not supported by the corresponding counter AMEVCNTR1<n>, then:

- It is UNPREDICTABLE which event will be counted.
- The value read back is UNKNOWN.

The event counted by AMEVCNTR1<n> might be fixed at implementation. In this case, the field is read-only and writes are UNDEFINED.

If the corresponding counter AMEVCNTR1<n> is enabled, writes to this register have UNPREDICTABLE results.

Accessing the AMEVTYPER1<n>

- ~~Accesses to the register are UNDEFINED.~~

- ~~Accesses to the register behave as RAZ/WI.~~
- ~~Accesses to the register execute as a NOP.~~

If <n> is greater than or equal to the number of auxiliary activity monitor event counters, reads and writes of AMEVTYPER1<n> are UNDEFINED~~CONSTRAINED UNPREDICTABLE~~.~~, and the following behaviors are permitted:~~

Note

AMCGCR.CG1NC identifies the number of auxiliary activity monitor event counters.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b111:n[3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && AMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && AMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T13 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HAFGRTR_EL2.AMEVTYPER1<n>_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMEVTYPER1[UInt(CRm<0>:opc2<2:0>)];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMEVTYPER1[UInt(CRm<0>:opc2<2:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMEVTYPER1[UInt(CRm<0>:opc2<2:0>)];
elsif PSTATE.EL == EL3 then
    return AMEVTYPER1[UInt(CRm<0>:opc2<2:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b111:n[3]	n[2:0]

```
if PSTATE.EL == EL1 && EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
    AArch64.AArch32SystemAccessTrap(EL2, 0x03);
elsif PSTATE.EL == EL1 && EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
    AArch32.TakeHypTrapException(0x03);
elsif IsHighestEL(PSTATE.EL) then
    AMEVTYPER1[UInt(CRm<0>:opc2<2:0>)] = R[t];
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMUSERENR, Activity Monitors User Enable Register

The AMUSERENR characteristics are:

Purpose

Global user enable register for the activity monitors. Enables or disables EL0 access to the activity monitors. AMUSERENR is applicable to both the architected and the auxiliary counter groups.

Configuration

AArch32 System register AMUSERENR bits [31:0] are architecturally mapped to AArch64 System register AMUSERENR_EL0[31:0] .

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMUSERENR are UNDEFINED.

Attributes

AMUSERENR is a 32-bit register.

Field descriptions

The AMUSERENR bit assignments are:



Bits [31:1]

Reserved, RES0.

EN, bit [0]

Traps EL0 accesses to the activity monitors registers to EL1.

EN	Meaning
0b0	EL0 accesses to the activity monitors registers are trapped to EL1.
0b1	This control does not cause any instructions to be trapped. Software can access all activity monitor registers at EL0.

Note

- AMUSERENR can always be read at EL0 and is not governed by this bit.

Accessing the AMUSERENR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0010	0b011

```
if PSTATE.EL == EL0 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T13 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMUSERENR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMUSERENR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return AMUSERENR;
elsif PSTATE.EL == EL3 then
    return AMUSERENR;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0010	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T13
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        AMUSERENR = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TAM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        AMUSERENR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TAM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        AMUSERENR = R[t];
elsif PSTATE.EL == EL3 then
    AMUSERENR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

APSR, Application Program Status Register

The APSR characteristics are:

Purpose

Hold program status and control information.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to APSR are UNKNOWN.

Attributes

APSR is a 32-bit register.

Field descriptions

The APSR bit assignments are:



N, bit [31]

Negative condition flag. Set to bit[31] of the result of the last flag-setting instruction. If the result is regarded as a two's complement signed integer, then N is set to 1 if the result was negative, and N is set to 0 if the result was positive or zero.

Z, bit [30]

Zero condition flag. Set to 1 if the result of the last flag-setting instruction was zero, and to 0 otherwise. A result of zero often indicates an equal result from a comparison.

C, bit [29]

Carry condition flag. Set to 1 if the last flag-setting instruction resulted in a carry condition, for example an unsigned overflow on an addition.

V, bit [28]

Overflow condition flag. Set to 1 if the last flag-setting instruction resulted in an overflow condition, for example a signed overflow on an addition.

Q, bit [27]

Cumulative saturation bit. Set to 1 to indicate that overflow or saturation occurred in some instructions.

Bits [26:20]

Reserved, RES0.

GE, bits [19:16]

Greater than or Equal flags, for parallel addition and subtraction.

Bits [15:5]

Reserved, RES0.

Bit [4]

Reserved, RES1.

Bits [3:0]

Reserved, RES0.

It is permitted that, on a read of APSR:

- Bit[22] returns the value of PSTATE.PAN
- Bit[9] returns the value of PSTATE.E.
- Bits[8:6] return the value of PSTATE.{A, I, F}, the mask bits.
- Bit[4:0] returns the value of PSTATE.M[4:0]

Note

This is an exception to the general rule that an UNKNOWN field must not return information that cannot be obtained, at the current Privilege level, by an architected mechanism.

For more information see 'The Application Program State Register'.

Accessing the APSR

APSR can be read using the MRS instruction and written using the MSR (register) or MSR (immediate) instructions.

~~APSR can be read using the MRS instruction and written using the MSR (register) or MSR (immediate) instructions. For more details, see MRS, MSR (register), and MSR (immediate) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS12NSOPR, Address Translate Stages 1 and 2 Non-secure Only PL1 Read

The ATS12NSOPR characteristics are:

Purpose

Performs stage 1 and 2 address translations as defined for PL1 and the Non-secure state, with permissions as if reading from the given virtual address.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ATS12NSOPR are UNKNOWN.

Attributes

ATS12NSOPR is a 32-bit System instruction.

Field descriptions

The ATS12NSOPR input value bit assignments are:



Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. The resulting address is the PA that is the output address of the stage 2 translation.

Executing the ATS12NSOPR instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1000	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    ATS12NSOPR(R[t]);
elsif PSTATE.EL == EL3 then
    ATS12NSOPR(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS12NSOPW, Address Translate Stages 1 and 2 Non-secure Only PL1 Write

The ATS12NSOPW characteristics are:

Purpose

Performs stage 1 and 2 address translations as defined for PL1 and the Non-secure state, with permissions as if writing to the given virtual address.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ATS12NSOPW are UNKNOWN.

Attributes

ATS12NSOPW is a 32-bit System instruction.

Field descriptions

The ATS12NSOPW input value bit assignments are:



Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. The resulting address is the PA that is the output address of the stage 2 translation.

Executing the ATS12NSOPW instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    ATS12NSOPW(R[t]);
elsif PSTATE.EL == EL3 then
    ATS12NSOPW(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS12NSOUR, Address Translate Stages 1 and 2 Non-secure Only Unprivileged Read

The ATS12NSOUR characteristics are:

Purpose

Performs stage 1 and 2 address translations as defined for PL0 and the Non-secure state, with permissions as if reading from the given virtual address.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ATS12NSOUR are UNKNOWN.

Attributes

ATS12NSOUR is a 32-bit System instruction.

Field descriptions

The ATS12NSOUR input value bit assignments are:



Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. The resulting address is the PA that is the output address of the stage 2 translation.

Executing the ATS12NSOUR instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1000	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    ATS12NSOUR(R[t]);
elsif PSTATE.EL == EL3 then
    ATS12NSOUR(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS12NSOUW, Address Translate Stages 1 and 2 Non-secure Only Unprivileged Write

The ATS12NSOUW characteristics are:

Purpose

Performs stage 1 and 2 address translations as defined for PL0 and the Non-secure state, with permissions as if writing to the given virtual address.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ATS12NSOUW are UNKNOWN.

Attributes

ATS12NSOUW is a 32-bit System instruction.

Field descriptions

The ATS12NSOUW input value bit assignments are:



Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. The resulting address is the PA that is the output address of the stage 2 translation.

Executing the ATS12NSOUW instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1000	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    ATS12NSOUW(R[t]);
elsif PSTATE.EL == EL3 then
    ATS12NSOUW(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS1CPR, Address Translate Stage 1 Current state PL1 Read

The ATS1CPR characteristics are:

Purpose

Performs stage 1 address translation as defined for PL1 and the current Security state, with permissions as if reading from the given virtual address.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ATS1CPR are UNKNOWN.

Attributes

ATS1CPR is a 32-bit System instruction.

Field descriptions

The ATS1CPR input value bit assignments are:



Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. If EL2 is implemented and enabled in the current Security state, the resulting address is the IPA that is the output address of the stage 1 translation. Otherwise, the resulting address is a PA.

Executing the ATS1CPR instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ATS1CPR(R[t]);
elsif PSTATE.EL == EL2 then
    ATS1CPR(R[t]);
elsif PSTATE.EL == EL3 then
    ATS1CPR(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS1CPRP, Address Translate Stage 1 Current state PL1 Read PAN

The ATS1CPRP characteristics are:

Purpose

Performs a stage 1 address translation at PL1 and in the current Security state, where the value of PSTATE.PAN determines if a read from a location will generate a permission fault for a privileged access.

Configuration

This instruction is present only when AArch32 is supported at any Exception level and ARMv8.2-ATS1E1 is implemented. Otherwise, direct accesses to ATS1CPRP are UNDEFINED.

Attributes

ATS1CPRP is a 32-bit System instruction.

Field descriptions

The ATS1CPRP input value bit assignments are:



Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. If EL2 is implemented and enabled in the current Security state, the resulting address is the IPA that is the output address of the stage 1 translation. Otherwise, the resulting address is a PA.

Executing the ATS1CPRP instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ATS1CPRP(R[t]);
elsif PSTATE.EL == EL2 then
    ATS1CPRP(R[t]);
elsif PSTATE.EL == EL3 then
    ATS1CPRP(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS1CPW, Address Translate Stage 1 Current state PL1 Write

The ATS1CPW characteristics are:

Purpose

Performs stage 1 address translation as defined for PL1 and the current Security state, with permissions as if writing to the given virtual address.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ATS1CPW are UNKNOWN.

Attributes

ATS1CPW is a 32-bit System instruction.

Field descriptions

The ATS1CPW input value bit assignments are:



Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. If EL2 is implemented and enabled in the current Security state, the resulting address is the IPA that is the output address of the stage 1 translation. Otherwise, the resulting address is a PA.

Executing the ATS1CPW instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ATS1CPW(R[t]);
elsif PSTATE.EL == EL2 then
    ATS1CPW(R[t]);
elsif PSTATE.EL == EL3 then
    ATS1CPW(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS1CPWP, Address Translate Stage 1 Current state PL1 Write PAN

The ATS1CPWP characteristics are:

Purpose

When ARMv8.2-ATS1E1 is implemented, performs a stage 1 address translation at PL1 and in the current Security state, where the value of PSTATE.PAN determines if a write to the location will generate a permission fault for a privileged access.

Configuration

This instruction is present only when AArch32 is supported at any Exception level and ARMv8.2-ATS1E1 is implemented. Otherwise, direct accesses to ATS1CPWP are UNDEFINED.

Attributes

ATS1CPWP is a 32-bit System instruction.

Field descriptions

The ATS1CPWP input value bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Input address for translation																															

Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. If EL2 is implemented and enabled in the current Security state, the resulting address is the IPA that is the output address of the stage 1 translation. Otherwise, the resulting address is a PA.

Executing the ATS1CPWP instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ATS1CPWP(R[t]);
elsif PSTATE.EL == EL2 then
    ATS1CPWP(R[t]);
elsif PSTATE.EL == EL3 then
    ATS1CPWP(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS1CUR, Address Translate Stage 1 Current state Unprivileged Read

The ATS1CUR characteristics are:

Purpose

Performs stage 1 address translation as defined for PL0 and the current Security state, with permissions as if reading from the given virtual address.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ATS1CUR are UNKNOWN.

Attributes

ATS1CUR is a 32-bit System instruction.

Field descriptions

The ATS1CUR input value bit assignments are:



Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. If EL2 is implemented and enabled in the current Security state, the resulting address is the IPA that is the output address of the stage 1 translation. Otherwise, the resulting address is a PA.

Executing the ATS1CUR instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ATS1CUR(R[t]);
elsif PSTATE.EL == EL2 then
    ATS1CUR(R[t]);
elsif PSTATE.EL == EL3 then
    ATS1CUR(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS1CUW, Address Translate Stage 1 Current state Unprivileged Write

The ATS1CUW characteristics are:

Purpose

Performs stage 1 address translation as defined for PL0 and the current Security state, with permissions as if writing to the given virtual address.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ATS1CUW are UNKNOWN.

Attributes

ATS1CUW is a 32-bit System instruction.

Field descriptions

The ATS1CUW input value bit assignments are:



Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. If EL2 is implemented and enabled in the current Security state, the resulting address is the IPA that is the output address of the stage 1 translation. Otherwise, the resulting address is a PA.

Executing the ATS1CUW instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ATS1CUW(R[t]);
elsif PSTATE.EL == EL2 then
    ATS1CUW(R[t]);
elsif PSTATE.EL == EL3 then
    ATS1CUW(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS1HR, Address Translate Stage 1 Hyp mode Read

The ATS1HR characteristics are:

Purpose

Performs stage 1 address translation as defined for PL2 and the Non-secure state, with permissions as if reading from the given virtual address.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ATS1HR are UNKNOWN.

Attributes

ATS1HR is a 32-bit System instruction.

Field descriptions

The ATS1HR input value bit assignments are:



Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. The resulting address is the PA that is the output address of the translation.

Executing the ATS1HR instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0111	0b1000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ATS1HR(R[t]);
elsif PSTATE.EL == EL2 then
    ATS1HR(R[t]);
elsif PSTATE.EL == EL3 then
    ATS1HR(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ATS1HW, Address Translate Stage 1 Hyp mode Write

The ATS1HW characteristics are:

Purpose

Performs stage 1 address translation as defined for PL2 and the Non-secure state, with permissions as if writing to the given virtual address.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ATS1HW are UNKNOWN.

Attributes

ATS1HW is a 32-bit System instruction.

Field descriptions

The ATS1HW input value bit assignments are:



Bits [31:0]

Input address for translation. The resulting address can be read from the PAR.

This System instruction takes a VA as input. The resulting address is the PA that is the output address of the translation.

Executing the ATS1HW instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0111	0b1000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ATS1HW(R[t]);
elsif PSTATE.EL == EL2 then
    ATS1HW(R[t]);
elsif PSTATE.EL == EL3 then
    ATS1HW(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

BPIALL, Branch Predictor Invalidate All

The BPIALL characteristics are:

Purpose

Invalidate all entries from branch predictors.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to BPIALL are UNKNOWN.

In an implementation where the branch predictors are architecturally invisible, this instruction can execute as a NOP.

Attributes

BPIALL is a 32-bit System instruction.

Field descriptions

BPIALL ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the BPIALL instruction

The PE ignores the value of <Rt>. Software does not have to write a value to this register before issuing this instruction.

When HCR.FB is 1, at Non-secure EL1 this instruction executes as a BPIALLIS.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0101	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.FB == '1' then
        BPIALLIS();
    else
        BPIALL();
elsif PSTATE.EL == EL2 then
    BPIALL();
elsif PSTATE.EL == EL3 then
    BPIALL();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

BPIALLIS, Branch Predictor Invalidate All, Inner Shareable

The BPIALLIS characteristics are:

Purpose

Invalidate all entries from branch predictors Inner Shareable.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to BPIALLIS are UNKNOWN.

In an implementation where the branch predictors are architecturally invisible, this instruction can execute as a NOP.

Attributes

BPIALLIS is a 32-bit System instruction.

Field descriptions

BPIALLIS ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the BPIALLIS instruction

The PE ignores the value of <Rt>. Software does not have to write a value to this register before issuing this instruction.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0001	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        BPIALL();
elsif PSTATE.EL == EL2 then
    BPIALL();
elsif PSTATE.EL == EL3 then
    BPIALL();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

BPIMVA, Branch Predictor Invalidate by VA

The BPIMVA characteristics are:

Purpose

Invalidate virtual address from branch predictors.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to BPIMVA are UNKNOWN.

In an implementation where the branch predictors are architecturally invisible, this instruction can execute as a NOP.

Attributes

BPIMVA is a 32-bit System instruction.

Field descriptions

The BPIMVA input value bit assignments are:



Bits [31:0]

Virtual address to use.

Executing the BPIMVA instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0101	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        BPIMVA(R[t]);
elsif PSTATE.EL == EL2 then
    BPIMVA(R[t]);
elsif PSTATE.EL == EL3 then
    BPIMVA(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CCSIDR, Current Cache Size ID Register

The CCSIDR characteristics are:

Purpose

Provides information about the architecture of the currently selected cache.

When ARMv8.3-CCIDX is implemented, this register is used in conjunction with CCSIDR2.

Configuration

AArch32 System register CCSIDR bits [31:0] are architecturally mapped to AArch64 System register CCSIDR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CCSIDR are UNKNOWN.

The implementation includes one CCSIDR for each cache that it can access. CSSELR and the Security state select which Cache Size ID Register is accessible.

Attributes

CCSIDR is a 32-bit register.

Field descriptions

The CCSIDR bit assignments are:

When ARMv8.3-CCIDX is implemented:



Note

The parameters NumSets, Associativity, and LineSize in these registers define the architecturally visible parameters that are required for the cache maintenance by Set/Way instructions. They are not guaranteed to represent the actual microarchitectural features of a design. You cannot make any inference about the actual sizes of caches based on these parameters.

Bits [31:24]

Reserved, RES0.

Associativity, bits [23:3]

(Associativity of cache) - 1, therefore a value of 0 indicates an associativity of 1. The associativity does not have to be a power of 2.

LineSize, bits [2:0]

(Log_2(Number of bytes in cache line)) - 4. For example:

For a line length of 16 bytes: $Log_2(16) = 4$, LineSize entry = 0. This is the minimum line length.

For a line length of 32 bytes: $Log_2(32) = 5$, LineSize entry = 1.

Otherwise:



Note

The parameters NumSets, Associativity, and LineSize in these registers define the architecturally visible parameters that are required for the cache maintenance by Set/Way instructions. They are not guaranteed to represent the actual microarchitectural features of a design. You cannot make any inference about the actual sizes of caches based on these parameters.

Bits [31:28]

Reserved, UNKNOWN.

NumSets, bits [27:13]

(Number of sets in cache) - 1, therefore a value of 0 indicates 1 set in the cache. The number of sets does not have to be a power of 2.

Associativity, bits [12:3]

(Associativity of cache) - 1, therefore a value of 0 indicates an associativity of 1. The associativity does not have to be a power of 2.

LineSize, bits [2:0]

(Log_2(Number of bytes in cache line)) - 4. For example:

For a line length of 16 bytes: $Log_2(16) = 4$, LineSize entry = 0. This is the minimum line length.

For a line length of 32 bytes: $Log_2(32) = 5$, LineSize entry = 1.

Accessing the CCSIDR

If CSSELR.Level is programmed to a cache level that is not implemented, then on a read of the CCSIDR the behavior is CONSTRAINED UNPREDICTABLE, and can be one of the following:

- The CCSIDR read is treated as NOP.
- The CCSIDR read is UNDEFINED.
- The CCSIDR read returns an UNKNOWN value.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b001	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID4 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TID4 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return CCSIDR;
elsif PSTATE.EL == EL2 then
    return CCSIDR;
elsif PSTATE.EL == EL3 then
    return CCSIDR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CCSIDR2, Current Cache Size ID Register 2

The CCSIDR2 characteristics are:

Purpose

When ARMv8.3-CCIDX is implemented, in conjunction with CCSIDR, provides information about the architecture of the currently selected cache.

When ARMv8.3-CCIDX is not implemented, this register is not implemented.

Configuration

AArch32 System register CCSIDR2 bits [31:0] are architecturally mapped to AArch64 System register CCSIDR2_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level and ARMv8.3-CCIDX is implemented. Otherwise, direct accesses to CCSIDR2 are UNDEFINED.

The implementation includes one CCSIDR2 for each cache that it can access. CSSELR and the Security state select which Cache Size ID Register is accessible.

Attributes

CCSIDR2 is a 32-bit register.

Field descriptions

The CCSIDR2 bit assignments are:



Bits [31:24]

Reserved, RES0.

NumSets, bits [23:0]

(Number of sets in cache) - 1, therefore a value of 0 indicates 1 set in the cache. The number of sets does not have to be a power of 2.

Accessing the CCSIDR2

If CSSELR.Level is programmed to a cache level that is not implemented, then on a read of the CCSIDR2 the behavior is CONSTRAINED UNPREDICTABLE, and can be one of the following:

- The CCSIDR2 read is treated as NOP.
- The CCSIDR2 read is UNDEFINED.
- The CCSIDR2 read returns an UNKNOWN value.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b001	0b0000	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID4 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TID4 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return CCSIDR2;
elsif PSTATE.EL == EL2 then
    return CCSIDR2;
elsif PSTATE.EL == EL3 then
    return CCSIDR2;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CFPRCTX, Control Flow Prediction Restriction by Context

The CFPRCTX characteristics are:

Purpose

Control Flow Prediction Restriction by Context applies to all Control Flow Prediction Resources that predict execution based on information gathered within the target execution context or contexts.

When this instruction is complete and synchronized, control flow prediction does not permit later speculative execution within the target execution context to be observable through side channels.

This instruction is guaranteed to be complete following a DSB that covers both read and write behavior on the same PE as executed the original restriction instruction, and a subsequent context synchronization event is required to ensure that the effect of the completion of the instructions is synchronized to the current execution.

Note

This instruction does not require the invalidation of prediction structures so long as the behavior described for completion of this instruction is met by the implementation.

On some implementations the instruction is likely to take a significant number of cycles to execute. This instruction is expected to be used very rarely, such as on the roll-over of an ASID or VMID, but should not be used on every context switch.

Configuration

This instruction is present only when AArch32 is supported at any Exception level and ARMv8.0-PredInv is implemented. Otherwise, direct accesses to CFPRCTX are UNDEFINED.

Attributes

CFPRCTX is a 32-bit System instruction.

Field descriptions

The CFPRCTX input value bit assignments are:



Bits [31:28]

Reserved, RES0.

GVMID, bit [27]

Execution of this instruction applies to all VMIDs or a specified VMID.

GVMID	Meaning
0b0	Applies to specified VMID for an EL0 or EL1 context. For all other contexts this field is RES0.
0b1	Applies to all VMIDs for an EL0 or EL1 context. For all other contexts this field is RES0.

If the instruction is executed at EL0 or EL1, then this field has an Effective value of 0.

NS, bit [26]

Security State.

NS	Meaning
0b0	Secure state.
0b1	Non-secure state.

If the instruction is executed in Non-secure state, this field has an Effective value of 1.

EL, bits [25:24]

Exception Level.

EL	Meaning
0b00	EL0.
0b01	EL1.
0b10	EL2.
0b11	EL3.

If the instruction is executed at an exception level lower than the specified level, this instruction is treated as a NOP.

VMID, bits [23:16]

Only applies when bit[27] is 0 and either of:

- an EL1 context.
- an EL0 context when (HCR_EL2.E2H==0 or HCR_EL2.TGE==0) or EL2 is using AArch32 state.

Otherwise this field is RES0.

When the instruction is executed at EL1 then this field is treated as the current VMID.

When the instruction is executed at EL0 and (HCR_EL2.E2H==0 or HCR_EL2.TGE==0 or ELUsingAArch32(EL2)) then this field is treated as the current VMID.

When the instruction is executed at EL0 and (HCR_EL2.E2H==1 and HCR_EL2.TGE==1 and !ELUsingAArch32(EL2)) then this field is ignored.

Bits [15:9]

Reserved, RES0.

GASID, bit [8]

Execution of this instruction applies to all ASIDs or a specified ASID.

GASID	Meaning
0b0	Applies to specified ASID for an EL0 context. For all other contexts this field is RES0.
0b1	Applies to all ASID for an EL0 context. For all other contexts this field is RES0.

If the instruction is executed at EL0, then this field is treated as 0.

ASID, bits [7:0]

Only applies for an EL0 context and when bit[8] is 0.

Otherwise this field is RES0.

When the instruction is executed at EL0 then this field is treated as the current ASID.

Executing the CFPRCTX instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0011	0b100

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && SCTLR_EL1.EnRCTX ==
'0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && SCTLR.EnRCTX == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T7 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCTLR_EL2.EnRCTX ==
'0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        CFPRCTX(R[t]);
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x03);
    else
        CFPRCTX(R[t]);
elsif PSTATE.EL == EL2 then
    CFPRCTX(R[t]);
elsif PSTATE.EL == EL3 then
    CFPRCTX(R[t]);
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116~~134483bd14dc8e12a99c984cbfe3431cc1c9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CLIDR, Cache Level ID Register

The CLIDR characteristics are:

Purpose

Identifies the type of cache, or caches, that are implemented at each level and can be managed using the architected cache maintenance instructions that operate by set/way, up to a maximum of seven levels. Also identifies the Level of Coherence (LoC) and Level of Unification (LoU) for the cache hierarchy.

Configuration

AArch32 System register CLIDR bits [31:0] are architecturally mapped to AArch64 System register CLIDR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CLIDR are UNKNOWN.

Attributes

CLIDR is a 32-bit register.

Field descriptions

The CLIDR bit assignments are:

31 30	29 28 27	26 25 24	23 22 21	20 19 18	17 16 15	14 13 12	11 10 9	8 7 6	5 4 3	2 1 0
ICB	LoUU	LoC	LoUIS	Ctype7	Ctype6	Ctype5	Ctype4	Ctype3	Ctype2	Ctype1

ICB, bits [31:30]

Inner cache boundary. This field indicates the boundary for caching Inner Cacheable memory regions.

The possible values are:

ICB	Meaning
0b00	Not disclosed by this mechanism.
0b01	L1 cache is the highest Inner Cacheable level.
0b10	L2 cache is the highest Inner Cacheable level.
0b11	L3 cache is the highest Inner Cacheable level.

LoUU, bits [29:27]

Level of Unification Uniprocessor for the cache hierarchy.

LoC, bits [26:24]

Level of Coherence for the cache hierarchy.

LoUIS, bits [23:21]

Level of Unification Inner Shareable for the cache hierarchy.

Ctype<n>, bits [3(n-1)+2:3(n-1)], for n = 1 to 7

Cache Type fields. Indicate the type of cache that is implemented and can be managed using the architected cache maintenance instructions that operate by set/way at each level, from Level 1 up to a maximum of seven levels of cache hierarchy. Possible values of each field are:

Ctype<n>	Meaning
0b000	No cache.
0b001	Instruction cache only.
0b010	Data cache only.
0b011	Separate instruction and data caches.
0b100	Unified cache.

All other values are reserved.

If software reads the Cache Type fields from Ctype1 upwards, once it has seen a value of 000, no caches that can be managed using the architected cache maintenance instructions that operate by set/way exist at further-out levels of the hierarchy. So, for example, if Ctype3 is the first Cache Type field with a value of 000, the values of Ctype4 to Ctype7 must be ignored.

Accessing the CLIDR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b001	0b0000	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID4 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TID4 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return CLIDR;
elsif PSTATE.EL == EL2 then
    return CLIDR;
elsif PSTATE.EL == EL3 then
    return CLIDR;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTFRQ, Counter-timer Frequency register

The CNTFRQ characteristics are:

Purpose

This register is provided so that software can discover the frequency of the system counter. It must be programmed with this value as part of system initialization. The value of the register is not interpreted by hardware.

Configuration

AArch32 System register CNTFRQ bits [31:0] are architecturally mapped to AArch64 System register CNTFRQ_EL0[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to CNTFRQ arearchitecturally UNKNOWN.values.

Attributes

CNTFRQ is a 32-bit register.

Field descriptions

The CNTFRQ bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Clock frequency																															

Bits [31:0]

Clock frequency. Indicates the system counter clock frequency, in Hz.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTFRQ

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') &&
CNTKCTL_EL1.<EL0PCTEN,EL0VCTEN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PCTEN == '0' && CNTKCTL.PL0VCTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' &&
CNTHCTL_EL2.<EL0PCTEN,EL0VCTEN> == '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        return CNTFRQ;
elsif PSTATE.EL == EL1 then
    return CNTFRQ;
elsif PSTATE.EL == EL2 then
    return CNTFRQ;
elsif PSTATE.EL == EL3 then
    return CNTFRQ;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0000	0b000

```
if IsHighestEL(PSTATE.EL) then
    CNTFRQ = R[t];
else
    UNDEFINED;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHCTL, Counter-timer Hyp Control register

The CNTHCTL characteristics are:

Purpose

Controls the generation of an event stream from the physical counter, and access from Non-secure EL1 modes to the physical counter and the Non-secure EL1 physical timer.

Configuration

AArch32 System register CNTHCTL bits [31:0] are architecturally mapped to AArch64 System register CNTHCTL_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CNTHCTL are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHCTL is a 32-bit register.

Field descriptions

The CNTHCTL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0														EVNTIS	RES0									EVNTI				EVNTDIR	EVNTEN	PL1PCEN	PL1PCTEN

Bits [31:18]

Reserved, RES0.

EVNTIS, bit [17]

When ARMv8.6-ECV is implemented:

Controls the scale of the generation of the event stream.

EVNTIS	Meaning
0b0	The CNTHCTL.EVNTI field applies to CNTPCT[15:0].
0b1	The CNTHCTL.EVNTI field applies to CNTPCT[23:8].

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [16:8]

Reserved, RES0.

EVNTI, bits [7:4]

Selects which bit (0 to 15) of the counter register CNTPCT is the trigger for the event stream generated from that counter, when that stream is enabled.

This field resets to an architecturally UNKNOWN value.

EVNTDIR, bit [3]

Controls which transition of the counter register CNTPCT trigger bit, defined by EVNTI, generates an event when the event stream is enabled:

EVNTDIR	Meaning
0b0	A 0 to 1 transition of the trigger bit triggers an event.
0b1	A 1 to 0 transition of the trigger bit triggers an event.

This field resets to an architecturally UNKNOWN value.

EVNTEN, bit [2]

Enables the generation of an event stream from the counter register CNTPCT:

EVNTEN	Meaning
0b0	Disables the event stream.
0b1	Enables the event stream.

This field resets to an architecturally UNKNOWN value.

PL1PCEN, bit [1]

Traps Non-secure EL0 and EL1 accesses to the physical timer registers to Hyp mode.

PL1PCEN	Meaning
0b0	Non-secure EL0 and EL1 accesses to the CNTP_CTL, CNTP_CVAL, and CNTP_TVAL are trapped to Hyp mode, unless the it is trapped by CNTKCTL.PL0PTEN.
0b1	This control does not cause any instructions to be trapped.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 1 other than for the purpose of a direct read.

This field resets to an architecturally UNKNOWN value.

PL1PCTEN, bit [0]

Traps Non-secure EL0 and EL1 accesses to the physical counter register to Hyp mode.

PL1PCTEN	Meaning
0b0	Non-secure EL0 and EL1 accesses to the CNTPCT are trapped to Hyp mode, unless it is trapped by CNTKCTL.PL0PCTEN.
0b1	This control does not cause any instructions to be trapped.

If EL3 is implemented and EL2 is not implemented, behavior is as if this bit is 1 other than for the purpose of a direct read.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHCTL

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTHCTL;
elsif PSTATE.EL == EL3 then
    return CNTHCTL;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTHCTL = R[t];
elsif PSTATE.EL == EL3 then
    CNTHCTL = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHP_CTL, Counter-timer Hyp Physical Timer Control register

The CNTHP_CTL characteristics are:

Purpose

Control register for the Hyp mode physical timer.

Configuration

AArch32 System register CNTHP_CTL bits [31:0] are architecturally mapped to AArch64 System register CNTHP_CTL_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CNTHP_CTL are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 with EL2 using AArch32, or into EL3 with EL3 using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHP_CTL is a 32-bit register.

Field descriptions

The CNTHP_CTL bit assignments are:



Bits [31:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

In a system where the PE resets into EL2 or EL3, this field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTHP_TVAL continues to count down.

Note

Disabling the output signal might be a power-saving option.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

Accessing the CNTHP_CTL

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTHP_CTL;
elsif PSTATE.EL == EL3 then
    return CNTHP_CTL;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTHP_CTL = R[t];
elsif PSTATE.EL == EL3 then
    CNTHP_CTL = R[t];
```

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CTL_EL2;
    else
        return CNTP_CTL;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return CNTP_CTL_S;
        else
            return CNTP_CTL_NS;
    else
        return CNTP_CTL;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return CNTP_CTL_NS;
    else
        return CNTP_CTL;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return CNTP_CTL_S;
    else
        return CNTP_CTL_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CTL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CTL_EL2 = R[t];
    else
        CNTP_CTL = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            CNTP_CTL_S = R[t];
        else
            CNTP_CTL_NS = R[t];
    else
        CNTP_CTL = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        CNTP_CTL_NS = R[t];
    else
        CNTP_CTL = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        CNTP_CTL_S = R[t];
    else
        CNTP_CTL_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHP_CVAL, Counter-timer Hyp Physical CompareValue register

The CNTHP_CVAL characteristics are:

Purpose

Holds the compare value for the Hyp mode physical timer.

Configuration

AArch32 System register CNTHP_CVAL bits [63:0] are architecturally mapped to AArch64 System register CNTHP_CVAL_EL2[63:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CNTHP_CVAL are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHP_CVAL is a 64-bit register.

Field descriptions

The CNTHP_CVAL bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CompareValue																															
CompareValue																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CompareValue, bits [63:0]

Holds the EL2 physical timer CompareValue.

When CNTHP_CTL.ENABLE is 1, the timer condition is met when (CNTPCT - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTHP_CTL.ISTATUS is set to 1.
- If CNTHP_CTL.IMASK is 0, an interrupt is generated.

When CNTHP_CTL.ENABLE is 0, the timer condition is not met, but CNTPCT continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHP_CVAL

Accesses to this register use the following encodings:

MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b1110	0b0110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTHP_CVAL;
elsif PSTATE.EL == EL3 then
    return CNTHP_CVAL;
```

MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b1110	0b0110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTHP_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    CNTHP_CVAL = R[t2]:R[t];
```

MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b1110	0b0010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CVAL_EL2;
    else
        return CNTP_CVAL;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return CNTP_CVAL_S;
        else
            return CNTP_CVAL_NS;
    else
        return CNTP_CVAL;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return CNTP_CVAL_NS;
    else
        return CNTP_CVAL;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return CNTP_CVAL_S;
    else
        return CNTP_CVAL_NS;
```

MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b1110	0b0010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CVAL_EL2 = R[t2]:R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CVAL_EL2 = R[t2]:R[t];
    else
        CNTP_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            CNTP_CVAL_S = R[t2]:R[t];
        else
            CNTP_CVAL_NS = R[t2]:R[t];
    else
        CNTP_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        CNTP_CVAL_NS = R[t2]:R[t];
    else
        CNTP_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        CNTP_CVAL_S = R[t2]:R[t];
    else
        CNTP_CVAL_NS = R[t2]:R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

CNTHP_TVAL, Counter-timer Hyp Physical Timer TimerValue register

The CNTHP_TVAL characteristics are:

Purpose

Holds the timer value for the Hyp mode physical timer.

Configuration

AArch32 System register CNTHP_TVAL bits [31:0] are architecturally mapped to AArch64 System register CNTHP_TVAL_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CNTHP_TVAL are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CNTHP_TVAL is a 32-bit register.

Field descriptions

The CNTHP_TVAL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
TimerValue																															

TimerValue, bits [31:0]

The TimerValue view of the EL2 physical timer.

On a read of this register:

- If CNTHP_CTL.ENABLE is 0, the value returned is UNKNOWN.
- If CNTHP_CTL.ENABLE is 1, the value returned is (CNTHP_CVAL - CNTPCT).

On a write of this register, CNTHP_CVAL is set to (CNTPCT + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTHP_CTL.ENABLE is 1, the timer condition is met when (CNTPCT - CNTHP_CVAL) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTHP_CTL.ISTATUS is set to 1.
- If CNTHP_CTL.IMASK is 0, an interrupt is generated.

When CNTHP_CTL.ENABLE is 0, the timer condition is not met, but CNTPCT continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHP_TVAL

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTHP_TVAL;
elsif PSTATE.EL == EL3 then
    return CNTHP_TVAL;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTHP_TVAL = R[t];
elsif PSTATE.EL == EL3 then
    CNTHP_TVAL = R[t];
```

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_TVAL_EL2;
    else
        return CNTP_TVAL;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return CNTP_TVAL_S;
        else
            return CNTP_TVAL_NS;
    else
        return CNTP_TVAL;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return CNTP_TVAL_NS;
    else
        return CNTP_TVAL;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return CNTP_TVAL_S;
    else
        return CNTP_TVAL_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_TVAL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_TVAL_EL2 = R[t];
    else
        CNTP_TVAL = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            CNTP_TVAL_S = R[t];
        else
            CNTP_TVAL_NS = R[t];
    else
        CNTP_TVAL = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        CNTP_TVAL_NS = R[t];
    else
        CNTP_TVAL = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        CNTP_TVAL_S = R[t];
    else
        CNTP_TVAL_NS = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

CNTHPS_CTL, Counter-timer Secure Physical Timer Control Register (EL2)

The CNTHPS_CTL characteristics are:

Purpose

Provides AArch32 access to the Secure EL2 physical timer.

Note

The Secure EL2 timer is implemented by ARMv8.4-SecEL2. It is only accessible from AArch32 state when EL2 is using AArch64 and the value of SCR_EL3.{EEL2, NS} is {1, 0}.

Configuration

AArch32 System register CNTHPS_CTL bits [31:0] are architecturally mapped to AArch64 System register CNTHPS_CTL_EL2[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHPS_CTL are UNDEFINED.

Attributes

CNTHPS_CTL is a 32-bit register.

Field descriptions

The CNTHPS_CTL bit assignments are:



Bits [31:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the CNTHPS_CTL.ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the CNTHPS_CTL.ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTHPS_TVAL_EL2 continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHPS_CTL

This register is accessed using the encoding for CNTP_CTL.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CTL_EL2;
    else
        return CNTP_CTL;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return CNTP_CTL_S;
        else
            return CNTP_CTL_NS;
    else
        return CNTP_CTL;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return CNTP_CTL_NS;
    else
        return CNTP_CTL;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return CNTP_CTL_S;
    else
        return CNTP_CTL_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CTL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CTL_EL2 = R[t];
    else
        CNTP_CTL = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            CNTP_CTL_S = R[t];
        else
            CNTP_CTL_NS = R[t];
    else
        CNTP_CTL = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        CNTP_CTL_NS = R[t];
    else
        CNTP_CTL = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        CNTP_CTL_S = R[t];
    else
        CNTP_CTL_NS = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHPS_CVAL, Counter-timer Secure Physical Timer CompareValue Register (EL2)

The CNTHPS_CVAL characteristics are:

Purpose

Provides AArch32 access to the compare value for the Secure EL2 physical timer.

Note

The Secure EL2 timer is implemented by ARMv8.4-SecEL2. It is only accessible from AArch32 state when EL2 is using AArch64 and the value of SCR_EL3.{EEL2, NS} is {1, 0}.

Configuration

AArch32 System register CNTHPS_CVAL bits [63:0] are architecturally mapped to AArch64 System register CNTHPS_CVAL_EL2[63:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHPS_CVAL are UNDEFINED.

Attributes

CNTHPS_CVAL is a 64-bit register.

Field descriptions

The CNTHPS_CVAL bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CompareValue																															
CompareValue																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CompareValue, bits [63:0]

Holds the EL2 physical timer CompareValue.

When CNTHPS_CTL_EL2.ENABLE is 1, the timer condition is met when (CNTPCT_EL0 - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTHPS_CTL_EL2.ISTATUS is set to 1.
- If CNTHPS_CTL_EL2.IMASK is 0, an interrupt is generated.

When CNTHPS_CTL_EL2.ENABLE is 0, the timer condition is not met, but CNTPCT_EL0 continues to count

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHPS_CVAL

This register is accessed using the encoding for CNTP_CVAL.

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b0010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CVAL_EL2;
    else
        return CNTP_CVAL;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return CNTP_CVAL_S;
        else
            return CNTP_CVAL_NS;
    else
        return CNTP_CVAL;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return CNTP_CVAL_NS;
    else
        return CNTP_CVAL;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return CNTP_CVAL_S;
    else
        return CNTP_CVAL_NS;
```

MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b1110	0b0010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CVAL_EL2 = R[t2]:R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CVAL_EL2 = R[t2]:R[t];
    else
        CNTP_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            CNTP_CVAL_S = R[t2]:R[t];
        else
            CNTP_CVAL_NS = R[t2]:R[t];
    else
        CNTP_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        CNTP_CVAL_NS = R[t2]:R[t];
    else
        CNTP_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        CNTP_CVAL_S = R[t2]:R[t];
    else
        CNTP_CVAL_NS = R[t2]:R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHPS_TVAL, Counter-timer Secure Physical Timer TimerValue Register (EL2)

The CNTHPS_TVAL characteristics are:

Purpose

Provides AArch32 access to the timer value for the Secure EL2 physical timer.

Note

The Secure EL2 timer is implemented by ARMv8.4-SecEL2. It is only accessible from AArch32 state when EL2 is using AArch64 and the value of SCR_EL3.{EEL2, NS} is {1, 0}.

Configuration

AArch32 System register CNTHPS_TVAL bits [31:0] are architecturally mapped to AArch64 System register CNTHPS_TVAL_EL2[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHPS_TVAL are UNDEFINED.

Attributes

CNTHPS_TVAL is a 32-bit register.

Field descriptions

The CNTHPS_TVAL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
TimerValue																															

TimerValue, bits [31:0]

The TimerValue view of the EL2 physical timer.

On a read of this register:

- If CNTHPS_CTL_EL2.ENABLE is 0, the value returned is UNKNOWN.
- If CNTHPS_CTL_EL2.ENABLE is 1, the value returned is (CNTHPS_CVAL_EL2 - CNTPCT_EL0).

On a write of this register, CNTHPS_CVAL_EL2 is set to (CNTPCT_EL0 + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTHPS_CTL_EL2.ENABLE is 1, the timer condition is met when (CNTPCT_EL0 - CNTHPS_CVAL_EL2) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTHPS_CTL_EL2.ISTATUS is set to 1.
- If CNTHPS_CTL_EL2.IMASK is 0, an interrupt is generated.

When CNTHPS_CTL_EL2.ENABLE is 0, the timer condition is not met, but CNTPCT_EL0 continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTHPS_TVAL

This register is accessed using the encoding for CNTP_TVAL.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_TVAL_EL2;
    else
        return CNTP_TVAL;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return CNTP_TVAL_S;
        else
            return CNTP_TVAL_NS;
    else
        return CNTP_TVAL;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return CNTP_TVAL_NS;
    else
        return CNTP_TVAL;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return CNTP_TVAL_S;
    else
        return CNTP_TVAL_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_TVAL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_TVAL_EL2 = R[t];
    else
        CNTP_TVAL = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            CNTP_TVAL_S = R[t];
        else
            CNTP_TVAL_NS = R[t];
    else
        CNTP_TVAL = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        CNTP_TVAL_NS = R[t];
    else
        CNTP_TVAL = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        CNTP_TVAL_S = R[t];
    else
        CNTP_TVAL_NS = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

CNTHV_CTL, Counter-timer Virtual Timer Control register (EL2)

The CNTHV_CTL characteristics are:

Purpose

Provides AArch32 access to the control register for the EL2 virtual timer.

Note

The EL2 virtual timer is implemented by ARMv8.1-VHE. It is only accessible from AArch32 state when EL0 is using AArch32, EL2 is using AArch64, and the value of HCR_EL2.{E2H, TGE} is {1, 1}.

Configuration

AArch32 System register CNTHV_CTL bits [31:0] are architecturally mapped to AArch64 System register CNTHV_CTL_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level and ARMv8.1-VHE is implemented. Otherwise, direct accesses to CNTHV_CTL are UNDEFINED.

Attributes

CNTHV_CTL is a 32-bit register.

Field descriptions

The CNTHV_CTL bit assignments are:



Bits [31:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTHV_TVAL continues to count down.

Note

Disabling the output signal might be a power-saving option.

Accessing the CNTHV_CTL

This register is accessed using the encoding for CNTV_CTL.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CTL_EL2;
    else
        return CNTV_CTL;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        return CNTV_CTL;
elsif PSTATE.EL == EL2 then
    return CNTV_CTL;
elsif PSTATE.EL == EL3 then
    return CNTV_CTL;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CTL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CTL_EL2 = R[t];
    else
        CNTV_CTL = R[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        CNTV_CTL = R[t];
elsif PSTATE.EL == EL2 then
    CNTV_CTL = R[t];
elsif PSTATE.EL == EL3 then
    CNTV_CTL = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHV_CVAL, Counter-timer Virtual Timer CompareValue register (EL2)

The CNTHV_CVAL characteristics are:

Purpose

Provides AArch32 access to the compare value for the EL2 virtual timer.

Note

The EL2 virtual timer is implemented by ARMv8.1-VHE. It is only accessible from AArch32 state when EL0 is using AArch32, EL2 is using AArch64, and the value of HCR_EL2.{E2H, TGE} is {1, 1}.

Configuration

AArch32 System register CNTHV_CVAL bits [63:0] are architecturally mapped to AArch64 System register CNTHV_CVAL_EL2[63:0] .

This register is present only when ARMv8.1-VHE is implemented. Otherwise, direct accesses to CNTHV_CVAL are UNDEFINED.

Attributes

CNTHV_CVAL is a 64-bit register.

Field descriptions

The CNTHV_CVAL bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CompareValue																															
CompareValue																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CompareValue, bits [63:0]

Holds the EL2 virtual timer CompareValue.

When CNTHV_CTL.ENABLE is 1, the timer condition is met when (CNTVCT - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTHV_CTL.ISTATUS is set to 1.
- If CNTHV_CTL.IMASK is 0, an interrupt is generated.

When CNTHV_CTL.ENABLE is 0, the timer condition is not met, but CNTVCT continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

Accessing the CNTHV_CVAL

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b0011

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CVAL_EL2;
    else
        return CNTV_CVAL;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    else
        return CNTV_CVAL;
elsif PSTATE.EL == EL2 then
    return CNTV_CVAL;
elsif PSTATE.EL == EL3 then
    return CNTV_CVAL;
```

```
MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b0011

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CVAL_EL2 = R[t2]:R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CVAL_EL2 = R[t2]:R[t];
    else
        CNTV_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    else
        CNTV_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    CNTV_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    CNTV_CVAL = R[t2]:R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHV_TVAL, Counter-timer Virtual Timer TimerValue register (EL2)

The CNTHV_TVAL characteristics are:

Purpose

Provides AArch32 access to the timer value for the EL2 virtual timer.

Note

The EL2 virtual timer is implemented by ARMv8.1-VHE. It is only accessible from AArch32 state when EL0 is using AArch32, EL2 is using AArch64, and the value of HCR_EL2.{E2H, TGE} is {1, 1}.

Configuration

AArch32 System register CNTHV_TVAL bits [31:0] are architecturally mapped to AArch64 System register CNTHV_TVAL_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level and ARMv8.1-VHE is implemented. Otherwise, direct accesses to CNTHV_TVAL are UNDEFINED.

Attributes

CNTHV_TVAL is a 32-bit register.

Field descriptions

The CNTHV_TVAL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
TimerValue																															

TimerValue, bits [31:0]

The TimerValue view of the EL2 virtual timer.

On a read of this register:

- If CNTHV_CTL.ENABLE is 0, the value returned is UNKNOWN.
- If CNTHV_CTL.ENABLE is 1, the value returned is (CNTHV_CVAL - CNTVCT).

On a write of this register, CNTHV_CVAL is set to (CNTVCT + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTHV_CTL.ENABLE is 1, the timer condition is met when (CNTVCT - CNTHV_CVAL) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTHV_CTL.ISTATUS is set to 1.
- If CNTHV_CTL.IMASK is 0, an interrupt is generated.

When CNTHV_CTL.ENABLE is 0, the timer condition is not met, but CNTVCT continues to count, so the TimerValue view appears to continue to count down.

Accessing the CNTHV_TVAL

This register is accessed using the encoding for CNTV_TVAL.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_TVAL_EL2;
    else
        return CNTV_TVAL;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        return CNTV_TVAL;
elsif PSTATE.EL == EL2 then
    return CNTV_TVAL;
elsif PSTATE.EL == EL3 then
    return CNTV_TVAL;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_TVAL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_TVAL_EL2 = R[t];
    else
        CNTV_TVAL = R[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        CNTV_TVAL = R[t];
elsif PSTATE.EL == EL2 then
    CNTV_TVAL = R[t];
elsif PSTATE.EL == EL3 then
    CNTV_TVAL = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHVS_CTL, Counter-timer Secure Virtual Timer Control Register (EL2)

The CNTHVS_CTL characteristics are:

Purpose

Provides AArch32 access to the Secure EL2 virtual timer.

Note

The Secure EL2 timer is implemented by ARMv8.4-SecEL2. It is only accessible from AArch32 state when EL2 is using AArch64 and the value of SCR_EL3.{EEL2, NS} is {1, 0}.

Configuration

AArch32 System register CNTHVS_CTL bits [31:0] are architecturally mapped to AArch64 System register CNTHVS_CTL_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level and ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHVS_CTL are UNDEFINED.

Attributes

CNTHVS_CTL is a 32-bit register.

Field descriptions

The CNTHVS_CTL bit assignments are:

31 … 3	2	1	0
RES0	ISTATUS	IMASK	ENABLE

Bits [31:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D8.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTHVS_TVAL continues to count down.

Note

Disabling the output signal might be a power-saving option.

Accessing the CNTHVS_CTL

This register is accessed using the encoding for CNTV_CTL.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CTL_EL2;
    else
        return CNTV_CTL;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        return CNTV_CTL;
elsif PSTATE.EL == EL2 then
    return CNTV_CTL;
elsif PSTATE.EL == EL3 then
    return CNTV_CTL;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CTL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CTL_EL2 = R[t];
    else
        CNTV_CTL = R[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        CNTV_CTL = R[t];
elsif PSTATE.EL == EL2 then
    CNTV_CTL = R[t];
elsif PSTATE.EL == EL3 then
    CNTV_CTL = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHVS_CVAL, Counter-timer Secure Virtual Timer CompareValue Register (EL2)

The CNTHVS_CVAL characteristics are:

Purpose

Provides AArch32 access to the compare value for the Secure EL2 virtual timer.

Note

The Secure EL2 timer is implemented by ARMv8.4-SecEL2. It is only accessible from AArch32 state when EL2 is using AArch64 and the value of SCR_EL3.{EEL2, NS} is {1, 0}.

Configuration

AArch32 System register CNTHVS_CVAL bits [63:0] are architecturally mapped to AArch64 System register CNTHVS_CVAL_EL2[63:0] .

This register is present only when AArch32 is supported at any Exception level and ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHVS_CVAL are UNDEFINED.

Attributes

CNTHVS_CVAL is a 64-bit register.

Field descriptions

The CNTHVS_CVAL bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CompareValue																															
CompareValue																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CompareValue, bits [63:0]

Holds the EL2 virtual timer CompareValue.

When CNTHVS_CTL.ENABLE is 1, the timer condition is met when (CNTVCT - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTHVS_CTL.ISTATUS is set to 1.
- If CNTHVS_CTL.IMASK is 0, an interrupt is generated.

When CNTHVS_CTL.ENABLE is 0, the timer condition is not met, but CNTVCT continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

Accessing the CNTHVS_CVAL

This register is accessed using the encoding for CNTV_CVAL.

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b0011

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CVAL_EL2;
    else
        return CNTV_CVAL;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    else
        return CNTV_CVAL;
elsif PSTATE.EL == EL2 then
    return CNTV_CVAL;
elsif PSTATE.EL == EL3 then
    return CNTV_CVAL;
```

```
MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b0011

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CVAL_EL2 = R[t2]:R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CVAL_EL2 = R[t2]:R[t];
    else
        CNTV_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    else
        CNTV_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    CNTV_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    CNTV_CVAL = R[t2]:R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTHVS_TVAL, Counter-timer Secure Virtual Timer TimerValue Register (EL2)

The CNTHVS_TVAL characteristics are:

Purpose

Provides AArch32 access to the timer value for the Secure EL2 virtual timer.

Note

The Secure EL2 timer is implemented by ARMv8.4-SecEL2. It is only accessible from AArch32 state when EL2 is using AArch64 and the value of SCR_EL3.{EEL2, NS} is {1, 0}.

Configuration

AArch32 System register CNTHVS_TVAL bits [31:0] are architecturally mapped to AArch64 System register CNTHVS_TVAL_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level and ARMv8.4-SecEL2 is implemented. Otherwise, direct accesses to CNTHVS_TVAL are UNDEFINED.

Attributes

CNTHVS_TVAL is a 32-bit register.

Field descriptions

The CNTHVS_TVAL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
TimerValue																															

TimerValue, bits [31:0]

The TimerValue view of the EL2 virtual timer.

On a read of this register:

- If CNTHVS_CTL.ENABLE is 0, the value returned is UNKNOWN.
- If CNTHVS_CTL.ENABLE is 1, the value returned is (CNTHVS_CVAL - CNTVCT).

On a write of this register, CNTHVS_CVAL is set to (CNTVCT + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTHVS_CTL.ENABLE is 1, the timer condition is met when (CNTVCT - CNTHVS_CVAL) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTHVS_CTL.ISTATUS is set to 1.
- If CNTHVS_CTL.IMASK is 0, an interrupt is generated.

When CNTHVS_CTL.ENABLE is 0, the timer condition is not met, but CNTVCT continues to count, so the TimerValue view appears to continue to count down.

Accessing the CNTHVS_TVAL

This register is accessed using the encoding for CNTV_TVAL.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_TVAL_EL2;
    else
        return CNTV_TVAL;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        return CNTV_TVAL;
elsif PSTATE.EL == EL2 then
    return CNTV_TVAL;
elsif PSTATE.EL == EL3 then
    return CNTV_TVAL;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_TVAL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_TVAL_EL2 = R[t];
    else
        CNTV_TVAL = R[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT ==
'1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        CNTV_TVAL = R[t];
elsif PSTATE.EL == EL2 then
    CNTV_TVAL = R[t];
elsif PSTATE.EL == EL3 then
    CNTV_TVAL = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTKCTL, Counter-timer Kernel Control register

The CNTKCTL characteristics are:

Purpose

Controls the generation of an event stream from the virtual counter, and access from EL0 modes to the physical counter, virtual counter, EL1 physical timers, and the virtual timer.

Configuration

AArch32 System register CNTKCTL bits [31:0] are architecturally mapped to AArch64 System register CNTKCTL_EL1[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to CNTKCTL arearchitecturally UNKNOWN.values.

Attributes

CNTKCTL is a 32-bit register.

Field descriptions

The CNTKCTL bit assignments are:

31302928272625242322212019	18	17	16151413121110	9	8	7	6	5	4	3	2	1	0
RES0		EVNTIS	RES0	PL0PTEN	PL0VTEN	EVNTI				EVNTDIR	EVNTEN	PL0VCTEN	PL0PCTEN

Bits [31:18]

Reserved, RES0.

EVNTIS, bit [17]

When ARMv8.6-ECV is implemented:

Controls the scale of the generation of the event stream.

EVNTIS	Meaning
0b0	The CNTKCTL.EVNTI field applies to CNTVCT[15:0].
0b1	The CNTKCTL.EVNTI field applies to CNTVCT[23:8].

This control applies regardless of the value of the CNTHCTL_EL2.ECV bit.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [16:10]

Reserved, RES0.

PL0PTEN, bit [9]

Traps PL0 accesses to the physical timer registers to Undefined mode.

PL0PTEN	Meaning
0b0	PL0 accesses to the CNTP_CTL, CNTP_CVAL, and CNTP_TVAL registers are trapped to Undefined mode.
0b1	This control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

PL0VTEN, bit [8]

Traps PL0 accesses to the virtual timer registers to Undefined mode.

PL0VTEN	Meaning
0b0	PL0 accesses to the CNTV_CTL, CNTV_CVAL, and CNTV_TVAL registers are trapped to Undefined mode.
0b1	This control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

EVNTI, bits [7:4]

Selects which bit (0 to 15) of the counter register CNTVCT is the trigger for the event stream generated from that counter, when that stream is enabled.

This field resets to an architecturally UNKNOWN value.

EVNTDIR, bit [3]

Controls which transition of the counter register CNTVCT trigger bit, defined by EVNTI, generates an event when the event stream is enabled:

EVNTDIR	Meaning
0b0	A 0 to 1 transition of the trigger bit triggers an event.
0b1	A 1 to 0 transition of the trigger bit triggers an event.

This field resets to an architecturally UNKNOWN value.

EVNTEN, bit [2]

Enables the generation of an event stream from the counter register CNTVCT:

EVNTEN	Meaning
0b0	Disables the event stream.
0b1	Enables the event stream.

This field resets to an architecturally UNKNOWN value.

PL0VCTEN, bit [1]

Traps PL0 accesses to the frequency register and virtual counter register to Undefined mode.

PL0VCTEN	Meaning
0b0	PL0 accesses to the CNTVCT are trapped to Undefined mode. PL0 accesses to the CNTFRQ register are trapped to Undefined mode, if CNTKCTL.PL0PCTEN is also 0.
0b1	This control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

PL0PCTEN, bit [0]

Traps PL0 accesses to the frequency register and physical counter register to Undefined mode.

PL0PCTEN	Meaning
0b0	PL0 accesses to the CNTPCT are trapped to Undefined mode. PL0 accesses to the CNTFRQ register are trapped to Undefined mode, if CNTKCTL.PL0VCTEN is also 0.
0b1	This control does not cause any instructions to be trapped.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTKCTL

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    return CNTKCTL;
elsif PSTATE.EL == EL2 then
    return CNTKCTL;
elsif PSTATE.EL == EL3 then
    return CNTKCTL;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    CNTKCTL = R[t];
elsif PSTATE.EL == EL2 then
    CNTKCTL = R[t];
elsif PSTATE.EL == EL3 then
    CNTKCTL = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTP_CTL, Counter-timer Physical Timer Control register

The CNTP_CTL characteristics are:

Purpose

Control register for the EL1 physical timer.

Configuration

AArch32 System register CNTP_CTL bits [31:0] are architecturally mapped to AArch64 System register CNTP_CTL_EL0[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. If the PE resets into EL3 using AArch32 they apply only to the Secure instance of the register. Otherwise, RW directfields accessesin this register reset to CNTP_CTL arearchitecturally UNKNOWN.values.

Attributes

CNTP_CTL is a 32-bit register.

Field descriptions

The CNTP_CTL bit assignments are:



Bits [31:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTP_TVAL continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to 0.

Accessing the CNTP_CTL

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CTL_EL2;
    else
        return CNTP_CTL;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return CNTP_CTL_S;
        else
            return CNTP_CTL_NS;
    else
        return CNTP_CTL;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return CNTP_CTL_NS;
    else
        return CNTP_CTL;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return CNTP_CTL_S;
    else
        return CNTP_CTL_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CTL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CTL_EL2 = R[t];
    else
        CNTP_CTL = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            CNTP_CTL_S = R[t];
        else
            CNTP_CTL_NS = R[t];
    else
        CNTP_CTL = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        CNTP_CTL_NS = R[t];
    else
        CNTP_CTL = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        CNTP_CTL_S = R[t];
    else
        CNTP_CTL_NS = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTP_CVAL, Counter-timer Physical Timer CompareValue register

The CNTP_CVAL characteristics are:

Purpose

Holds the compare value for the EL1 physical timer.

Configuration

AArch32 System register CNTP_CVAL bits [63:0] are architecturally mapped to AArch64 System register CNTP_CVAL_EL0[63:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to CNTP_CVAL arearchitecturally UNKNOWN.values.

Attributes

CNTP_CVAL is a 64-bit register.

Field descriptions

The CNTP_CVAL bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CompareValue																															
CompareValue																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CompareValue, bits [63:0]

Holds the EL1 physical timer CompareValue.

When CNTP_CTL.ENABLE is 1, the timer condition is met when (CNTPCT - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTP_CTL.ISTATUS is set to 1.
- If CNTP_CTL.IMASK is 0, an interrupt is generated.

When CNTP_CTL.ENABLE is 0, the timer condition is not met, but CNTPCT continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTP_CVAL

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b0010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_CVAL_EL2;
    else
        return CNTP_CVAL;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return CNTP_CVAL_S;
        else
            return CNTP_CVAL_NS;
    else
        return CNTP_CVAL;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return CNTP_CVAL_NS;
    else
        return CNTP_CVAL;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return CNTP_CVAL_S;
    else
        return CNTP_CVAL_NS;
```

```
MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b0010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_CVAL_EL2 = R[t2]:R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_CVAL_EL2 = R[t2]:R[t];
    else
        CNTP_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            CNTP_CVAL_S = R[t2]:R[t];
        else
            CNTP_CVAL_NS = R[t2]:R[t];
    else
        CNTP_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        CNTP_CVAL_NS = R[t2]:R[t];
    else
        CNTP_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        CNTP_CVAL_S = R[t2]:R[t];
    else
        CNTP_CVAL_NS = R[t2]:R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTP_TVAL, Counter-timer Physical Timer TimerValue register

The CNTP_TVAL characteristics are:

Purpose

Holds the timer value for the EL1 physical timer.

Configuration

AArch32 System register CNTP_TVAL bits [31:0] are architecturally mapped to AArch64 System register CNTP_TVAL_EL0[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to CNTP_TVAL arearchitecturally UNKNOWN.values.

Attributes

CNTP_TVAL is a 32-bit register.

Field descriptions

The CNTP_TVAL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
TimerValue																															

TimerValue, bits [31:0]

The TimerValue view of the EL1 physical timer.

On a read of this register:

- If CNTP_CTL.ENABLE is 0, the value returned is UNKNOWN.
- If CNTP_CTL.ENABLE is 1, the value returned is (CNTP_CVAL - CNTPCT).

On a write of this register, CNTP_CVAL is set to (CNTPCT + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTP_CTL.ENABLE is 1, the timer condition is met when (CNTPCT - CNTP_CVAL) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTP_CTL.ISTATUS is set to 1.
- If CNTP_CTL.IMASK is 0, an interrupt is generated.

When CNTP_CTL.ENABLE is 0, the timer condition is not met, but CNTPCT continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTP_TVAL

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHPS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHP_TVAL_EL2;
    else
        return CNTP_TVAL;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return CNTP_TVAL_S;
        else
            return CNTP_TVAL_NS;
    else
        return CNTP_TVAL;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return CNTP_TVAL_NS;
    else
        return CNTP_TVAL;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return CNTP_TVAL_S;
    else
        return CNTP_TVAL_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0010	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0PTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' && CNTHCTL_EL2.EL1PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0PTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHPS_TVAL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHP_TVAL_EL2 = R[t];
    else
        CNTP_TVAL = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CNTHCTL_EL2.EL1PTEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCEN == '0' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            CNTP_TVAL_S = R[t];
        else
            CNTP_TVAL_NS = R[t];
    else
        CNTP_TVAL = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        CNTP_TVAL_NS = R[t];
    else
        CNTP_TVAL = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        CNTP_TVAL_S = R[t];
    else
        CNTP_TVAL_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTPCT, Counter-timer Physical Count register

The CNTPCT characteristics are:

Purpose

Holds the 64-bit physical count value.

Configuration

AArch32 System register CNTPCT bits [63:0] are architecturally mapped to AArch64 System register CNTPCT_EL0[63:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CNTPCT are UNKNOWN.

All reads to the CNTPCT occur in program order relative to reads to CNTPCTSS or CNTPCT.

Attributes

CNTPCT is a 64-bit register.

Field descriptions

The CNTPCT bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Physical count value																															
Physical count value																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Physical count value.

Accessing the CNTPCT

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b0000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') &&
CNTKCTL_EL1.EL0PCTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PCTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' &&
CNTHCTL_EL2.EL1PCTEN == '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' &&
CNTHCTL_EL2.EL0PCTEN == '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCTEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    else
        return CNTPCT;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CNTHCTL_EL2.EL1PCTEN == '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCTEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    else
        return CNTPCT;
elsif PSTATE.EL == EL2 then
    return CNTPCT;
elsif PSTATE.EL == EL3 then
    return CNTPCT;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTPCTSS, Counter-timer Self-Synchronized Physical Count register

The CNTPCTSS characteristics are:

Purpose

Holds the 64-bit physical count value.

Configuration

AArch32 System register CNTPCTSS bits [63:0] are architecturally mapped to AArch64 System register CNTPCTSS_EL0[63:0] .

This register is present only when AArch32 is supported at any Exception level and ARMv8.6-ECV is implemented. Otherwise, direct accesses to CNTPCTSS are UNDEFINED.

All reads to the CNTPCTSS occur in program order relative to reads to CNTPCT or CNTPCTSS.

This register is a self-synchronised view of the CNTPCT counter, and cannot be read speculatively.

Attributes

CNTPCTSS is a 64-bit register.

Field descriptions

The CNTPCTSS bit assignments are:



Bits [63:0]

Self-Synchronized Physical count value.

Accessing the CNTPCTSS

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b1000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') &&
CNTKCTL_EL1.EL0PCTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0PCTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '0' && CNTHCTL_EL2.EL1PCEN == '0'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '10' &&
CNTHCTL_EL2.EL1PCTEN == '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' &&
CNTHCTL_EL2.EL0PCTEN == '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCTEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    else
        return CNTPCTSS;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && CNTHCTL_EL2.EL1PCTEN == '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && CNTHCTL.PL1PCTEN == '0' then
        AArch32.TakeHypTrapException(0x04);
    else
        return CNTPCTSS;
elsif PSTATE.EL == EL2 then
    return CNTPCTSS;
elsif PSTATE.EL == EL3 then
    return CNTPCTSS;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTV_CTL, Counter-timer Virtual Timer Control register

The CNTV_CTL characteristics are:

Purpose

Control register for the virtual timer.

Configuration

AArch32 System register CNTV_CTL bits [31:0] are architecturally mapped to AArch64 System register CNTV_CTL_EL0[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to CNTV_CTL arearchitecturally UNKNOWN.values.

Attributes

CNTV_CTL is a 32-bit register.

Field descriptions

The CNTV_CTL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																													ISTATUS	IMASK	ENABLE

Bits [31:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTV_TVAL continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to 0.

Accessing the CNTV_CTL

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CTL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CTL_EL2;
    else
        return CNTV_CTL;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        return CNTV_CTL;
elsif PSTATE.EL == EL2 then
    return CNTV_CTL;
elsif PSTATE.EL == EL3 then
    return CNTV_CTL;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CTL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CTL_EL2 = R[t];
    else
        CNTV_CTL = R[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        CNTV_CTL = R[t];
elsif PSTATE.EL == EL2 then
    CNTV_CTL = R[t];
elsif PSTATE.EL == EL3 then
    CNTV_CTL = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTV_CVAL, Counter-timer Virtual Timer CompareValue register

The CNTV_CVAL characteristics are:

Purpose

Holds the compare value for the virtual timer.

Configuration

AArch32 System register CNTV_CVAL bits [63:0] are architecturally mapped to AArch64 System register CNTV_CVAL_EL0[63:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to CNTV_CVAL arearchitecturally UNKNOWN.values.

Attributes

CNTV_CVAL is a 64-bit register.

Field descriptions

The CNTV_CVAL bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CompareValue																															
CompareValue																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CompareValue, bits [63:0]

Holds the EL1 virtual timer CompareValue.

When CNTV_CTL.ENABLE is 1, the timer condition is met when (CNTVCT - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTV_CTL.ISTATUS is set to 1.
- If CNTV_CTL.IMASK is 0, an interrupt is generated.

When CNTV_CTL.ENABLE is 0, the timer condition is not met, but CNTVCT continues to count.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTV_CVAL

Accesses to this register use the following encodings:

MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b1110	0b0011

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_CVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_CVAL_EL2;
    else
        return CNTV_CVAL;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    else
        return CNTV_CVAL;
elsif PSTATE.EL == EL2 then
    return CNTV_CVAL;
elsif PSTATE.EL == EL3 then
    return CNTV_CVAL;
```

MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b1110	0b0011

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_CVAL_EL2 = R[t2]:R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_CVAL_EL2 = R[t2]:R[t];
    else
        CNTV_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    else
        CNTV_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    CNTV_CVAL = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    CNTV_CVAL = R[t2]:R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTV_TVAL, Counter-timer Virtual Timer TimerValue register

The CNTV_TVAL characteristics are:

Purpose

Holds the timer value for the virtual timer.

Configuration

AArch32 System register CNTV_TVAL bits [31:0] are architecturally mapped to AArch64 System register CNTV_TVAL_EL0[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to CNTV_TVAL arearchitecturally UNKNOWN.values.

Attributes

CNTV_TVAL is a 32-bit register.

Field descriptions

The CNTV_TVAL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
TimerValue																															

TimerValue, bits [31:0]

The TimerValue view of the virtual timer.

On a read of this register:

- If CNTV_CTL.ENABLE is 0, the value returned is UNKNOWN.
- If CNTV_CTL.ENABLE is 1, the value returned is (CNTV_CVAL - CNTVCT).

On a write of this register, CNTV_CVAL is set to (CNTVCT + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTP_CTL.ENABLE is 1, the timer condition is met when (CNTVCT - CNTP_CVAL) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTV_CTL.ISTATUS is set to 1.
- If CNTV_CTL.IMASK is 0, an interrupt is generated.

When CNTV_CTL.ENABLE is 0, the timer condition is not met, but CNTVCT continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTV_TVAL

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        return CNTHVS_TVAL_EL2;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        return CNTHV_TVAL_EL2;
    else
        return CNTV_TVAL;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        return CNTV_TVAL;
elsif PSTATE.EL == EL2 then
    return CNTV_TVAL;
elsif PSTATE.EL == EL3 then
    return CNTV_TVAL;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b0011	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTKCTL_EL1.EL0VTEN
== '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && CNTHCTL_EL2.EL0VTEN
== '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL1) && EL2Enabled() && HCR_EL2.<E2H,TGE> != '11' && CNTHCTL_EL2.EL1TVT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '0'
&& IsFeatureImplemented("ARMv8.4-SecEL2") then
        CNTHVS_TVAL_EL2 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCR_EL3.NS == '1'
then
        CNTHV_TVAL_EL2 = R[t];
    else
        CNTV_TVAL = R[t];
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> !=== '11') &&
CNTHCTL_EL2.EL1TVT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        CNTV_TVAL = R[t];
elsif PSTATE.EL == EL2 then
    CNTV_TVAL = R[t];
elsif PSTATE.EL == EL3 then
    CNTV_TVAL = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTVCT, Counter-timer Virtual Count register

The CNTVCT characteristics are:

Purpose

Holds the 64-bit virtual count value. The virtual count value is equal to the physical count value minus the virtual offset visible in CNTVOFF.

Configuration

AArch32 System register CNTVCT bits [63:0] are architecturally mapped to AArch64 System register CNTVCT_EL0[63:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CNTVCT are UNKNOWN.

The value of this register is the same as the value of CNTPCT in the following conditions:

- When EL2 is not implemented.
- When EL2 is implemented and is using AArch64, HCR_EL2.{E2H, TGE} is {1, 1}, and this register is read from Non-secure EL0.

All reads to the CNTVCT occur in program order relative to reads to CNTVCTSS or CNTVCT.

Attributes

CNTVCT is a 64-bit register.

Field descriptions

The CNTVCT bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Virtual count value																															
Virtual count value																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Virtual count value.

Accessing the CNTVCT

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b0001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') &&
CNTKCTL_EL1.EL0VCTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VCTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' &&
CNTHCTL_EL2.EL0VCTEN == '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') &&
CNTHCTL_EL2.EL1TVCT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    else
        return CNTVCT;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTHCTL_EL2.EL1TVCT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    else
        return CNTVCT;
elsif PSTATE.EL == EL2 then
    return CNTVCT;
elsif PSTATE.EL == EL3 then
    return CNTVCT;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTVCTSS, Counter-timer Self-Synchronized Virtual Count register

The CNTVCTSS characteristics are:

Purpose

Holds the 64-bit virtual count value. The virtual count value is equal to the physical count value visible in CNTPCT minus the virtual offset visible in CNTVOFF.

Configuration

AArch32 System register CNTVCTSS bits [63:0] are architecturally mapped to AArch64 System register CNTVCTSS_EL0[63:0] .

This register is present only when AArch32 is supported at any Exception level and ARMv8.6-ECV is implemented. Otherwise, direct accesses to CNTVCTSS are UNDEFINED.

All reads to the CNTVCTSS occur in program order relative to reads to CNTVCT or CNTVCTSS.

This register is a self-synchronised view of the CNTVCT counter, and cannot be read speculatively.

Attributes

CNTVCTSS is a 64-bit register.

Field descriptions

The CNTVCTSS bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Self-Synchronized Virtual count value																															
Self-Synchronized Virtual count value																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Self-Synchronized Virtual count value.

Accessing the CNTVCTSS

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b1001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') &&
CNTKCTL_EL1.EL0VCTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && CNTKCTL.PL0VCTEN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' &&
CNTHCTL_EL2.EL0VCTEN == '0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') &&
CNTHCTL_EL2.EL1TVCT == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    else
        return CNTVCTSS;
elsif PSTATE.EL == EL1 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && CNTHCTL_EL2.EL1TVCT
== '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    else
        return CNTVCTSS;
elsif PSTATE.EL == EL2 then
    return CNTVCTSS;
elsif PSTATE.EL == EL3 then
    return CNTVCTSS;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTVOFF, Counter-timer Virtual Offset register

The CNTVOFF characteristics are:

Purpose

Holds the 64-bit virtual offset. This is the offset between the physical count value visible in CNTPCT and the virtual count value visible in CNTVCT.

Configuration

AArch32 System register CNTVOFF bits [63:0] are architecturally mapped to AArch64 System register CNTVOFF_EL2[63:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CNTVOFF are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3 and the virtual counter uses a fixed virtual offset of zero.

Note

When EL2 is implemented and is using AArch64, if HCR_EL2.{E2H, TGE} is {1, 1}, the virtual counter uses a fixed virtual offset of zero when CNTVCT is read from Non-secure EL0.

~~When EL2 is implemented and can use AArch32, on a reset into an Exception level that is using AArch32 this register resets to an IMPLEMENTATION DEFINED value that might be UNKNOWN.~~

Attributes

CNTVOFF is a 64-bit register.

Field descriptions

The CNTVOFF bit assignments are:



Bits [63:0]

Virtual offset.

If the Generic counter is implemented at a size less than 64 bits, then this field is permitted to be implemented at the same width as the counter, and the upper bits are RES0.

The value of this field is treated as zero-extended in all counter calculations.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTVOFF

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b0100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    return CNTVOFF;
elsif PSTATE.EL == EL3 then
    return CNTVOFF;
```

```
MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1110	0b0100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    UNDEFINED;
elsif PSTATE.EL == EL2 then
    CNTVOFF = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    CNTVOFF = R[t2]:R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CONTEXTIDR, Context ID Register

The CONTEXTIDR characteristics are:

Purpose

Identifies the current Process Identifier and, when using the Short-descriptor translation table format, the Address Space Identifier.

The value of the whole of this register is called the Context ID and is used by:

- The debug logic, for Linked and Unlinked Context ID matching.
- The trace logic, to identify the current process.

The significance of this register is for debug and trace use only.

Configuration

AArch32 System register CONTEXTIDR bits [31:0] are architecturally mapped to AArch64 System register CONTEXTIDR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CONTEXTIDR are UNKNOWN.

The register format depends on whether address translation is using the Long-descriptor or the Short-descriptor translation table format.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CONTEXTIDR is a 32-bit register.

Field descriptions

The CONTEXTIDR bit assignments are:

When TTBCR.EAE == 0:



PROCID, bits [31:8]

Process Identifier. This field must be programmed with a unique value that identifies the current process.

This field resets to an architecturally UNKNOWN value.

ASID, bits [7:0]

Address Space Identifier. This field is programmed with the value of the current ASID.

This field resets to an architecturally UNKNOWN value.

When TTBCR.EAE == 1:



PROCID, bits [31:0]

Process Identifier. This field must be programmed with a unique value that identifies the current process.

This field resets to an architecturally UNKNOWN value.

Accessing the CONTEXTIDR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return CONTEXTIDR_S;
        else
            return CONTEXTIDR_NS;
    else
        return CONTEXTIDR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return CONTEXTIDR_NS;
    else
        return CONTEXTIDR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return CONTEXTIDR_S;
    else
        return CONTEXTIDR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            CONTEXTIDR_S = R[t];
        else
            CONTEXTIDR_NS = R[t];
    else
        CONTEXTIDR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        CONTEXTIDR_NS = R[t];
    else
        CONTEXTIDR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        CONTEXTIDR_S = R[t];
    else
        CONTEXTIDR_NS = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CP15DMB, Data Memory Barrier System instruction

The CP15DMB characteristics are:

Purpose

Performs a Data Memory Barrier.

Arm deprecates any use of this System instruction, and strongly recommends that software use the DMB instruction instead.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CP15DMB are UNKNOWN.

Attributes

CP15DMB is a 32-bit System instruction.

Field descriptions

CP15DMB ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the CP15DMB instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1010	0b101

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && SCTLR_EL1.CP15BEN
== '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCTLR_EL2.CP15BEN
== '0' then
        UNDEFINED;
    elsif ELUsingAArch32(EL1) && SCTLR.CP15BEN == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T7 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        CP15DMB();
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ELUsingAArch32(EL1) && SCTLR.CP15BEN == '0' then
        UNDEFINED;
    else
        CP15DMB();
elsif PSTATE.EL == EL2 then
    if HSCTLR.CP15BEN == '0' then
        UNDEFINED;
    else
        CP15DMB();
elsif PSTATE.EL == EL3 then
    CP15DMB();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CP15DSB, Data Synchronization Barrier System instruction

The CP15DSB characteristics are:

Purpose

Performs a Data Synchronization Barrier.

Arm deprecates any use of this System instruction, and strongly recommends that software use the DSB instruction instead.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CP15DSB are UNKNOWN.

Attributes

CP15DSB is a 32-bit System instruction.

Field descriptions

CP15DSB ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the CP15DSB instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1010	0b100

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && SCTLR_EL1.CP15BEN
== '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCTLR_EL2.CP15BEN
== '0' then
        UNDEFINED;
    elsif ELUsingAArch32(EL1) && SCTLR.CP15BEN == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T7 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        CP15DSB();
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ELUsingAArch32(EL1) && SCTLR.CP15BEN == '0' then
        UNDEFINED;
    else
        CP15DSB();
elsif PSTATE.EL == EL2 then
    if HSCTLR.CP15BEN == '0' then
        UNDEFINED;
    else
        CP15DSB();
elsif PSTATE.EL == EL3 then
    CP15DSB();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CP15ISB, Instruction Synchronization Barrier System instruction

The CP15ISB characteristics are:

Purpose

Performs an Instruction Synchronization Barrier.

Arm deprecates any use of this System instruction, and strongly recommends that software use the ISB instruction instead.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CP15ISB are UNKNOWN.

Attributes

CP15ISB is a 32-bit System instruction.

Field descriptions

CP15ISB ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the CP15ISB instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0101	0b100

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && SCTLR_EL1.CP15BEN
== '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCTLR_EL2.CP15BEN
== '0' then
        UNDEFINED;
    elsif ELUsingAArch32(EL1) && SCTLR.CP15BEN == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T7 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        CP15ISB();
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ELUsingAArch32(EL1) && SCTLR.CP15BEN == '0' then
        UNDEFINED;
    else
        CP15ISB();
elsif PSTATE.EL == EL2 then
    if HSCTLR.CP15BEN == '0' then
        UNDEFINED;
    else
        CP15ISB();
elsif PSTATE.EL == EL3 then
    CP15ISB();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CPACR, Architectural Feature Access Control Register

The CPACR characteristics are:

Purpose

Controls access to trace, and to Advanced SIMD and floating-point functionality from EL0, EL1, and EL3.

In an implementation that includes EL2, the CPACR has no effect on instructions executed at EL2.

Configuration

AArch32 System register CPACR bits [31:0] are architecturally mapped to AArch64 System register CPACR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CPACR are UNKNOWN.

Bits in the NSACR control Non-secure access to the CPACR fields. See the field descriptions for more information.

Note

In the register field descriptions, controls are described as applying at specified Privilege levels. This is because, in Secure state, a PL1 control:

- Applies to execution in a Secure EL3 mode when EL3 is using AArch32.
- Applies to execution in a Secure EL1 mode when EL3 is using AArch64.

See 'Security state, Exception levels, and AArch32 execution privilege' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.7.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

CPACR is a 32-bit register.

Field descriptions

The CPACR bit assignments are:



ASEDIS, bit [31]

Disables PL0 and PL1 execution of Advanced SIMD instructions.

ASEDIS	Meaning
0b0	This control permits execution of Advanced SIMD instructions at PL0 and PL1.
0b1	All instruction encodings that are Advanced SIMD instruction encodings, but are not also floating-point instruction encodings, are UNDEFINED at PL0 and PL1.

If the implementation does not include Advanced SIMD and floating-point functionality, this field is RES0. Otherwise, it is IMPLEMENTATION DEFINED whether this field is implemented as a RW field. If it is not implemented as a RW field, it is RAZ/WI.

If EL3 is implemented and is using AArch32, and the value of NSACR.NSASEDIS is 1, this field behaves as RAO/WI in Non-secure state, regardless of its actual value. This applies even if the field is implemented as RAZ/WI.

For the list of instructions affected by this field, see 'Controls of Advanced SIMD operation that do not apply to floating-point operation' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section E1.

See the description of CPACR.cp10 for a list of other controls that can disable or trap execution of Advanced SIMD instructions in AArch32 state.

This field resets to `0`.

Bits [30:29]

Reserved, RES0.

TRCDIS, bit [28]

Traps PL0 and PL1 System register accesses to all implemented trace registers to Undefined mode.

TRCDIS	Meaning
`0b0`	This control has no effect on PL0 and PL1 System register accesses to trace registers.
`0b1`	PL0 and PL1 System register accesses to all implemented trace registers are trapped to Undefined mode.

If the implementation does not include a PE trace unit, or does not include a System register interface to the PE trace unit registers, this field is RES0. Otherwise, it is IMPLEMENTATION DEFINED whether this field is implemented as a RW field. If it is not implemented as a RW field, it is RAZ/WI.

If EL3 is implemented and is using AArch32, and the value of NSACR.NSTRCDIS is 1, this field behaves as RAO/WI in Non-secure state, regardless of its actual value. This applies even if the field is implemented as RAZ/WI.

Note

- The ETMv4 architecture does not permit EL0 to access the trace registers. If the implementation includes an ETMv4 implementation, EL0 accesses to the trace registers are UNDEFINED.
- The architecture does not provide traps on trace register accesses through the optional memory-mapped external debug interface.

System register accesses to the trace registers can have side-effects. When a System register access is trapped, any side-effects that are normally associated with the access do not occur before the exception is taken.

This field resets to an architecturally UNKNOWN value.

Bits [27:24]

Reserved, RES0.

cp11, bits [23:22]

The value of this field is ignored. If this field is programmed with a different value to the cp10 field then this field is UNKNOWN on a direct read of the CPACR.

If the implementation does not include Advanced SIMD and floating-point functionality, this field is RES0.

In Non-secure state, if EL3 is implemented and is using AArch32, when the value of NSACR.cp10 is 0, this field behaves as RAZ/WI, regardless of its actual value.

This field resets to `0`.

cp10, bits [21:20]

Defines the access rights for the floating-point and Advanced SIMD functionality. Possible values of the field are:

cp10	Meaning
0b00	PL0 and PL1 accesses to floating-point and Advanced SIMD registers or instructions are UNDEFINED.
0b01	PL0 accesses to floating-point and Advanced SIMD registers or instructions are UNDEFINED.
0b10	Reserved. The effect of programming this field to this value is CONSTRAINED UNPREDICTABLE. See 'Unallocated values in fields of AArch32 System registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section J1.1.11.
0b11	This control permits full access to the floating-point and Advanced SIMD functionality from PL0 and PL1.

The floating-point and Advanced SIMD features controlled by these fields are:

- Execution of any floating-point or Advanced SIMD instruction.
- Any access to the Advanced SIMD and floating-point registers D0-D31 and their views as S0-S31 and Q0-Q15.
- Any access to the FPSCR, FPSID, MVFR0, MVFR1, MVFR2, or FPEXC System registers.

Note

The CPACR has no effect on floating-point and Advanced SIMD accesses from PL2. These can be disabled by the HCPTR.TCP10 field.

If the implementation does not include Advanced SIMD and floating-point functionality, this field is RES0.

In Non-secure state, if EL3 is implemented and is using AArch32, when the value of NSACR.cp10 is 0, this field behaves as RAZ/WI, regardless of its actual value.

Execution of floating-point and Advanced SIMD instructions in AArch32 state can be disabled or trapped by the following controls:

- CPACR.cp10, or, if executing at EL0, CPACR_EL1.FPEN.
- FPEXC.EN.
- If executing in Non-secure state:
  - HCPTR.TCP10, or if EL2 is using AArch64, CPTR_EL2.TFP.
  - NSACR.cp10, or if EL3 is using AArch64, CPTR_EL3.TFP.
- For Advanced SIMD instructions only:
  - CPACR.ASEDIS.
  - If executing in Non-secure state, HCPTR.TASE and NSACR.NSTRCDIS.

See the descriptions of the controls for more information.

This field resets to 0.

Bits [19:0]

Reserved, RES0.

Accessing the CPACR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TCPAC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TCPAC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return CPACR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return CPACR;
elsif PSTATE.EL == EL3 then
    return CPACR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && CPTR_EL2.TCPAC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCPTR.TCPAC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        CPACR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        CPACR = R[t];
elsif PSTATE.EL == EL3 then
    CPACR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CPPRCTX, Cache Prefetch Prediction Restriction by Context

The CPPRCTX characteristics are:

Purpose

Cache Prefetch Prediction Restriction by Context applies to all Cache Allocation Resources that predict cache allocations based on information gathered within the target execution context or contexts.

When this instruction is complete and synchronized, cache prefetch prediction does not permit later speculative execution within the target execution context to be observable through side channels.

This instruction applies to all:

- Instruction caches.
- Data caches.
- TLB prefetching hardware used by the executing PE that applies to the supplied context or contexts.

This instruction is guaranteed to be complete following a DSB that covers both read and write behavior on the same PE as executed the original restriction instruction, and a subsequent context synchronization event is required to ensure that the effect of the completion of the instructions is synchronized to the current execution.

Note

This instruction does not require the invalidation of Cache Allocation Resources so long as the behavior described for completion of this instruction is met by the implementation.

On some implementations the instruction is likely to take a significant number of cycles to execute. This instruction is expected to be used very rarely, such as on the roll-over of an ASID or VMID, but should not be used on every context switch.

Configuration

This instruction is present only when AArch32 is supported at any Exception level and ARMv8.0-PredInv is implemented. Otherwise, direct accesses to CPPRCTX are UNDEFINED.

Attributes

CPPRCTX is a 32-bit System instruction.

Field descriptions

The CPPRCTX input value bit assignments are:

31 30 29 28	27	26	25 24	23 22 21 20 19 18 17 16	15 14 13 12 11 10 9	8	7 6 5 4 3 2 1 0
RES0	GVMID	NS	EL	VMID	RES0	GASID	ASID

Bits [31:28]

Reserved, RES0.

GVMID, bit [27]

Execution of this instruction applies to all VMIDs or a specified VMID.

GVMID	Meaning
0b0	Applies to specified VMID for an EL0 or EL1 context. For all other contexts this field is RES0.
0b1	Applies to all VMIDs for an EL0 or EL1 context. For all other contexts this field is RES0.

If the instruction is executed at EL0 or EL1, then this field has an Effective value of 0.

NS, bit [26]

Security State.

NS	Meaning
0b0	Secure state.
0b1	Non-secure state.

If the instruction is executed in Non-secure state, this field is treated as 1.

EL, bits [25:24]

Exception Level.

EL	Meaning
0b00	EL0.
0b01	EL1.
0b10	EL2.
0b11	EL3.

If the instruction is executed at an exception level lower than the specified level, this instruction is treated as a NOP.

VMID, bits [23:16]

Only applies when bit[27] is 0 and either:

- an EL1 context.
- an EL0 context when (HCR_EL2.E2H==0 or HCR_EL2.TGE==0) or EL2 is using AArch32 state.

Otherwise this field is RES0.

When the instruction is executed at EL1 then this field is treated as the current VMID.

When the instruction is executed at EL0 and (HCR_EL2.E2H==0 or HCR_EL2.TGE==0 or ELUsingAArch32(EL2)) then this field is treated as the current VMID.

When the instruction is executed at EL0 and (HCR_EL2.E2H==1 and HCR_EL2.TGE==1 and !ELUsingAArch32(EL2)) then this field is ignored.

Bits [15:9]

Reserved, RES0.

GASID, bit [8]

Execution of this instruction applies to all ASIDs or a specified ASID.

GASID	Meaning
0b0	Applies to specified ASID for an EL0 context. For all other contexts this field is RES0.
0b1	Applies to all ASID for an EL0 context. For all other contexts this field is RES0.

If the instruction is executed at EL0, then this field has an Effective value of 0.

ASID, bits [7:0]

Only applies for an EL0 context and when bit[8] is 0.

Otherwise this field is RES0.

When the instruction is executed at EL0 then this field is treated as the current ASID.

Executing the CPPRCTX instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0011	0b111

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && SCTLR_EL1.EnRCTX ==
'0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && SCTLR.EnRCTX == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T7 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCTLR_EL2.EnRCTX ==
'0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        CPPRCTX(R[t]);
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x03);
    else
        CPPRCTX(R[t]);
elsif PSTATE.EL == EL2 then
    CPPRCTX(R[t]);
elsif PSTATE.EL == EL3 then
    CPPRCTX(R[t]);
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CPSR, Current Program Status Register

The CPSR characteristics are:

Purpose

Holds PE status and control information.

Configuration

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to CPSR arearchitecturally UNKNOWN.values.

Attributes

CPSR is a 32-bit register.

Field descriptions

The CPSR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
N	Z	C	V	Q	RES0			SSBS	PAN	DIT	RES0	GE				RES0						E	A	I	F	RES0	RES1	M			

N, bit [31]

Negative condition flag. Set to bit[31] of the result of the last flag-setting instruction. If the result is regarded as a two's complement signed integer, then N is set to 1 if the result was negative, and N is set to 0 if the result was positive or zero.

Z, bit [30]

Zero condition flag. Set to 1 if the result of the last flag-setting instruction was zero, and to 0 otherwise. A result of zero often indicates an equal result from a comparison.

C, bit [29]

Carry condition flag. Set to 1 if the last flag-setting instruction resulted in a carry condition, for example an unsigned overflow on an addition.

V, bit [28]

Overflow condition flag. Set to 1 if the last flag-setting instruction resulted in an overflow condition, for example a signed overflow on an addition.

Q, bit [27]

Cumulative saturation bit. Set to 1 to indicate that overflow or saturation occurred in some instructions.

Bits [26:24]

Reserved, RES0.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass Safe.

Prohibits speculative loads or stores which might practically allow a cache timing side channel.

A cache timing side channel might be exploited where a load or store uses an address that is derived from a register that is being loaded from memory using a load instruction speculatively read from a memory location. If PSTATE.SSBS is enabled, the address derived from the load instruction might be from earlier in the coherence order than the latest store to that memory location with the same virtual address.

SSBS	Meaning
0b0	Hardware is not permitted to load or store speculatively in the manner described.
0b1	Hardware is permitted to load or store speculatively in the manner described.

The value of this bit is usually set to the value described by the SCTLR.DSSBS bit on exceptions to any mode except Hyp mode, and the value described by HSCTLR.DSSBS on exceptions to Hyp mode.

This field resets to an IMPLEMENTATION DEFINED value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never.

PAN	Meaning
0b0	The translation system is the same as Armv8.0.
0b1	Disables privileged read and write accesses to addresses accessible at EL0.

The value of this bit is usually preserved on taking an exception, except in the following situations:

- When the target of the exception is EL1, and the value of the SCTLR.SPAN bit for the current Security state is 0, this bit is set to 1.
- When the target of the exception is EL3, from Secure state, and the value of the Secure SCTLR.SPAN is 0, this bit is set to 1.
- When the target of the exception is EL3, from Non-secure state, this bit is set to 0 regardless of the value of the Secure SCTLR.SPAN bit.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing.

DIT	Meaning
0b0	The architecture makes no statement about the timing properties of any instructions.
0b1	The architecture requires that: • The timing of every load and store instruction is insensitive to the value of the data being loaded or stored. • For certain data processing instructions, the instruction takes a time which is independent of: ◦ The values of the data supplied in any of its registers. ◦ The values of the NZCV flags. • For certain data processing instructions, the response of the instruction to asynchronous exceptions does not vary based on: ◦ The values of the data supplied in any of its registers. ◦ The values of the NZCV flags.

The data processing instructions affected by this bit are:

- All cryptographic instructions. These instructions are:
  - AESD, AESE, AESIMC, AESMC, SHA1C, SHA1H, SHA1M, SHA1P, SHA1SU0, SHA1SU1, SHA256H, SHA256H2, SHA256SU0, and SHA256SU1.
- A subset of those instructions which use the general-purpose register file. For these instructions, the effects of CPSR.DIT apply only if they do not use R15 as either their source or destination and pass their condition execution check. The instructions are:
  - BFI, BFC, CLZ, CMN, CMP, MLA, MLAS, MLS, MOVT, MUL, MULS, NOP, PKHBT, PKHTB, RBIT, REV, REV16, REVSH, RRX, SADD16, SADD8, SASX, SBFX, SHADD16, SHADD8, SHASX, SHSAX, SHSUB16, SHSUB8, SMLAL**, SMLAW*, SMLSD*, SMMLA*, SMMLS*, SMMUL*, SMUAD*, SMUL*, SSAX, SSUB16, SSUB8, SXTAB*, SXTAH, SXTB*, SXTH, TEQ, TST, UADD*, UASX, UBFX, UHADD*, UHASX, UHSAX, UHSUB*, UMAAL, UMLAL, UMLALS, UMULL, UMULLS, USADA8, USAX, USUB*, UXTAB*, UXTAH, UXTB*, UXTH, ADC (register-shifted register), ADCS (register-shifted register), ADD (register-shifted register), ADDS (register-shifted register), AND (register-shifted register), ANDS (register-shifted register), ASR (register-shifted register), ASRS (register-shifted register), BIC (register-shifted register), BICS (register-shifted register), EOR (register-shifted register), EORS (register-shifted register), LSL (register-shifted register), LSLS (register-shifted register), LSR (register-shifted register), LSRS (register-shifted register), MOV (register-shifted register), MOVS (register-shifted register), MVN (register-shifted register), MVNS (register-shifted register), ORR (register-shifted register), ORRS (register-shifted register), ROR (register-shifted register), RORS (register-shifted register), RSB (register-shifted register), RSBS (register-shifted register), RSC (register-shifted register), RSCS (register-shifted register), SBC (register-shifted register), SBCS (register-shifted register), SUB (register-shifted register), and SUBS (register-shifted register).
- A subset of those instructions which use the general-purpose register file. For these instructions, the effects of CPSR.DIT apply only if they do not use R15 as either their source or destination. The effects of CPSR.DIT do not depend on these instructions passing their condition execution check. These instructions are:
  - ADC (immediate), ADC (register), ADCS (immediate), ADCS (register), ADD (immediate), ADD (register), ADDS (immediate), ADDS (register), AND (immediate), AND (register), ANDS (immediate), ANDS (register), ASR (immediate), ASR (register), ASRS (immediate), ASRS (register), BIC (immediate), BIC (register), BICS (immediate), BICS (register), EOR (immediate), EOR (register), EORS (immediate), EORS (register), LSL (immediate), LSL (register), LSLS (immediate), LSLS (register), LSR (immediate), LSR (register), LSRS (immediate), LSRS (register), MOV (immediate), MOV (register), MOVS (immediate), MOVS (register), MVN (immediate), MVN (register), MVNS (immediate), MVNS (register), ORR (immediate), ORR (register), ORRS (immediate), ORRS (register), ROR (immediate), ROR (register), RORS (immediate), RORS (register), RSB (immediate), RSB (register), RSBS (immediate), RSBS (register), RSC (immediate), RSC (register), RSCS (immediate), RSCS (register), SBC (immediate), SBC (register), SBCS (immediate), SBCS (register), SUB (immediate), SUB (register), SUBS (immediate), and SUBS (register).
- A subset of those instructions which use the SIMD&FP register file. For these instructions, the effects of CPSR.DIT apply only if they pass their condition execution check. These instructions are:
  - CRC32B, CRC32H, CRC32W, CRC32CB, CRC32CH, CRC32CW, VABA*, VABD*, VABS, VACGE, VACGT, VACLE, VACLT, VADD (integer), VADDHN, VADDL, VADDW, VAND, VBIC, VBIF, VBIT, VBSL, VCGE, VCGT, VCLE, VCLS, VCLT, VCLZ, VCMP, VCMPE, VCNT, VDUP, VEOR, VEXT, VHADD, VHSUB, VMAX (integer), VMIN (integer), VMLA (integer), VMLAL, VMLS (integer), VMLSL, VMOV, VMOVL, VMOVN, VMUL (integer and polynomial), VMULL (integer and polynomial), VMVN, VNEG, VORN, VORR, VPADAL, VPADD (integer), VPADDL, VPMAX (integer),

VPMIN (integer), VRADDHN, VREV*, VRHADD, VRSHL, VRSHR, VRSHRN, VRSRA, VRSUBHN, VSELEQ, VSELGE, VSELGT, VSELVS, VSHL, VSHLL, VSHR, VSLI, VSRA, VSRI, VSUB (integer), VSUBHN, VSUBL, VSUBW, VSWP, VTBL, VTBX, VTRN, VTST, VUZP, and VZIP

This field resets to 0.

Otherwise:

Reserved, RES0.

Bit [20]

Reserved, RES0.

GE, bits [19:16]

Greater than or Equal flags, for parallel addition and subtraction.

Bits [15:10]

Reserved, RES0.

E, bit [9]

Endianness state bit. Controls the load and store endianness for data accesses:

E	Meaning
0b0	Little-endian operation
0b1	Big-endian operation.

Instruction fetches ignore this bit.

If an implementation does not provide Big-endian support, this bit is RES0. If it does not provide Little-endian support, this bit is RES1.

If an implementation provides Big-endian support but only at EL0, this bit is RES0 for an exception return to any Exception level other than EL0.

Likewise, if it provides Little-endian support only at EL0, this bit is RES1 for an exception return to any Exception level other than EL0.

When the reset value of the SCTLR.EE bit is defined by a configuration input signal, that value also applies to the CPSR.E bit on reset, and therefore applies to software execution from reset.

A, bit [8]

SError interrupt mask bit. The possible values of this bit are:

A	Meaning
0b0	Exception not masked.
0b1	Exception masked.

I, bit [7]

IRQ mask bit. The possible values of this bit are:

I	Meaning
0b0	Exception not masked.
0b1	Exception masked.

F, bit [6]

FIQ mask bit. The possible values of this bit are:

F	Meaning
0b0	Exception not masked.
0b1	Exception masked.

Bit [5]

Reserved, RES0.

Bit [4]

Reserved, RES1.

M, bits [3:0]

Current PE mode. Possible values are:

M	Meaning
0b0000	User.
0b0001	FIQ.
0b0010	IRQ.
0b0011	Supervisor.
0b0110	Monitor.
0b0111	Abort.
0b1010	Hyp.
0b1011	Undefined.
0b1111	System.

Accessing the CPSR

CPSR can be read using the MRS instruction and written using the MSR (register) or MSR (immediate) instructions.

~~CPSR can be read using the MRS instruction and written using the MSR (register) or MSR (immediate) instructions. For more details, see MRS, MSR (register), and MSR (immediate) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CSSELR, Cache Size Selection Register

The CSSELR characteristics are:

Purpose

Selects the current Cache Size ID Register, CCSIDR, by specifying the required cache level and the cache type, which is either instruction cache or data cache.

If ARMv8.3-CCIDX is implemented, CSSELR also selects the current CCSIDR2.

Configuration

AArch32 System register CSSELR bits [31:0] are architecturally mapped to AArch64 System register CSSELR_EL1[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to CSSELR arearchitecturally UNKNOWN.values.

Attributes

CSSELR is a 32-bit register.

Field descriptions

The CSSELR bit assignments are:



Bits [31:4]

Reserved, RES0.

Level, bits [3:1]

Cache level of required cache. Permitted values are:

Level	Meaning
0b000	Level 1 cache.
0b001	Level 2 cache.
0b010	Level 3 cache.
0b011	Level 4 cache.
0b100	Level 5 cache.
0b101	Level 6 cache.
0b110	Level 7 cache.

All other values are reserved.

If CSSELR.Level is programmed to a cache level that is not implemented, then the value for this field on a read of CSSELR is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

InD, bit [0]

Instruction not Data bit. Permitted values are:

InD	Meaning
0b0	Data or unified cache.
0b1	Instruction cache.

If CSSELR.Level is programmed to a cache level that is not implemented, then the value for this field on a read of CSSELR is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

Accessing the CSSELR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b010	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID4 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TID4 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return CSSELR_S;
        else
            return CSSELR_NS;
    else
        return CSSELR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return CSSELR_NS;
    else
        return CSSELR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return CSSELR_S;
    else
        return CSSELR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b010	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID4 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TID4 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            CSSELR_S = R[t];
        else
            CSSELR_NS = R[t];
    else
        CSSELR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        CSSELR_NS = R[t];
    else
        CSSELR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        CSSELR_S = R[t];
    else
        CSSELR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTR, Cache Type Register

The CTR characteristics are:

Purpose

Provides information about the architecture of the caches.

Configuration

AArch32 System register CTR bits [31:0] are architecturally mapped to AArch64 System register CTR_EL0[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to CTR are UNKNOWN.

Attributes

CTR is a 32-bit register.

Field descriptions

The CTR bit assignments are:



Bit [31]

Reserved, RES1.

Bit [30]

Reserved, RES0.

DIC, bit [29]

Instruction cache invalidation requirements for datainstruction to instructiondata coherence. The meaning of this bit is:

DIC	Meaning
0b0	Instruction cache invalidation to the Point of Unification is required for datainstruction to instructiondata coherence.
0b1	Instruction cache invalidationcleaning to the Point of Unification is not required for datainstruction to instructiondata coherence.

IDC, bit [28]

Data cache clean requirements for instruction to data coherence. The meaning of this bit is:

IDC	Meaning
0b0	Data cache clean to the Point of Unification is required for instruction to data coherence, unless CLIDR.LoC == 0b000 or (CLIDR.LoUIS == 0b000 && CLIDR.LoUU == 0b000).
0b1	Data cache clean to the Point of Unification is not required for instruction to data coherence.

CWG, bits [27:24]

Cache writeback granule. Log_2 of the number of words of the maximum size of memory that can be overwritten as a result of the eviction of a cache entry that has had a memory location in it modified.

A value of `0b0000` indicates that this register does not provide Cache writeback granule information and either:

- The architectural maximum of 512 words (2KB) must be assumed.
- The Cache writeback granule can be determined from maximum cache line size encoded in the Cache Size ID Registers.

Values greater than `0b1001` are reserved.

Arm recommends that an implementation that does not support cache write-back implements this field as `0b0001`. This applies, for example, to an implementation that supports only write-through caches.

ERG, bits [23:20]

Exclusives reservation granule. Log_2 of the number of words of the maximum size of the reservation granule that has been implemented for the Load-Exclusive and Store-Exclusive instructions.

The use of the value `0b0000` is deprecated.

The value `0b0001` and values greater than `0b1001` are reserved.

DminLine, bits [19:16]

Log_2 of the number of words in the smallest cache line of all the data caches and unified caches that are controlled by the PE.

L1Ip, bits [15:14]

Level 1 instruction cache policy. Indicates the indexing and tagging policy for the L1 instruction cache. Possible values of this field are:

L1Ip	Meaning
`0b00`	VMID aware Physical Index, Physical tag (VPIPT)
`0b01`	ASID-tagged Virtual Index, Virtual Tag (AIVIVT)
`0b10`	Virtual Index, Physical Tag (VIPT)
`0b11`	Physical Index, Physical Tag (PIPT)

The value `0b01` is reserved in Armv8.

The value `0b00` is permitted only in an implementation that includes ARMv8.2-PIPTV, otherwise the value is reserved.

Bits [13:4]

Reserved, RES0.

IminLine, bits [3:0]

Log_2 of the number of words in the smallest cache line of all the instruction caches that are controlled by the PE.

Accessing the CTR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return CTR;
elsif PSTATE.EL == EL2 then
    return CTR;
elsif PSTATE.EL == EL3 then
    return CTR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DACR, Domain Access Control Register

The DACR characteristics are:

Purpose

Defines the access permission for each of the sixteen memory domains.

Configuration

AArch32 System register DACR bits [31:0] are architecturally mapped to AArch64 System register DACR32_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DACR are UNKNOWN.

This register has no function when TTBCR.EAE is set to 1, to select the Long-descriptor translation table format.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DACR is a 32-bit register.

Field descriptions

The DACR bit assignments are:



D<n>, bits [2n+1:2n], for n = 0 to 15

Domain n access permission, where n = 0 to 15. Permitted values are:

D<n>	Meaning
0b00	No access. Any access to the domain generates a Domain fault.
0b01	Client. Accesses are checked against the permission bits in the translation tables.
0b11	Manager. Accesses are not checked against the permission bits in the translation tables.

The value 0b10 is reserved.

This field resets to an architecturally UNKNOWN value.

Accessing the DACR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0011	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return DACR_S;
        else
            return DACR_NS;
    else
        return DACR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return DACR_NS;
    else
        return DACR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return DACR_S;
    else
        return DACR_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0011	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            DACR_S = R[t];
        else
            DACR_NS = R[t];
    else
        DACR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        DACR_NS = R[t];
    else
        DACR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            DACR_S = R[t];
        else
            DACR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGAUTHSTATUS, Debug Authentication Status register

The DBGAUTHSTATUS characteristics are:

Purpose

Provides information about the state of the IMPLEMENTATION DEFINED authentication interface for debug.

Configuration

AArch32 System register DBGAUTHSTATUS bits [31:0] are architecturally mapped to AArch64 System register DBGAUTHSTATUS_EL1[31:0] .

AArch32 System register DBGAUTHSTATUS bits [31:0] are architecturally mapped to External register DBGAUTHSTATUS_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGAUTHSTATUS are UNKNOWN.

This register is required in all implementations.

Attributes

DBGAUTHSTATUS is a 32-bit register.

Field descriptions

The DBGAUTHSTATUS bit assignments are:



Bits [31:8]

Reserved, RES0.

SNID, bits [7:6]

When ARMv8.4-Debug is implemented:

Secure Non-Invasive Debug.

This field has the same value as DBGAUTHSTATUS.SID.

Otherwise:

Secure Non-Invasive Debug.

SNID	Meaning
0b00	Not implemented. EL3 is not implemented and the Effective value of SCR.NS is 1.
0b10	Implemented and disabled. ExternalSecureNoninvasiveDebugEnabled() == FALSE.
0b11	Implemented and enabled. ExternalSecureNoninvasiveDebugEnabled() == TRUE.

All other values are reserved.

SID, bits [5:4]

Secure Invasive Debug.

SID	Meaning
0b00	Not implemented. EL3 is not implemented and the Effective value of SCR_EL3.NS is 1.
0b10	Implemented and disabled. ExternalSecureInvasiveDebugEnabled() == FALSE.
0b11	Implemented and enabled. ExternalSecureInvasiveDebugEnabled() == TRUE.

All other values are reserved.

NSNID, bits [3:2]

When ARMv8.4-Debug is implemented:

Non-secure Non-invasive debug.

NSNID	Meaning
0b00	Not implemented. EL3 is not implemented and the Effective value of SCR.NS is 0.
0b11	Implemented and enabled. EL3 is implemented or the Effective value of SCR.NS is 1.

All other values are reserved.

Otherwise:

Non-secure Non-Invasive Debug.

NSNID	Meaning
0b00	Not implemented. EL3 is not implemented and the Effective value of SCR.NS is 0
0b10	Implemented and disabled. ExternalNoninvasiveDebugEnabled() == FALSE.
0b11	Implemented and enabled. ExternalNoninvasiveDebugEnabled() == TRUE.

All other values are reserved.

NSID, bits [1:0]

Non-secure Invasive Debug.

NSID	Meaning
0b00	Not implemented. EL3 is not implemented or the Effective value of SCR_EL3.NS is 0.
0b10	Implemented and disabled. ExternalInvasiveDebugEnabled() == FALSE.
0b11	Implemented and enabled. ExternalInvasiveDebugEnabled() == TRUE.

All other values are reserved.

Accessing the DBGAUTHSTATUS

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0111	0b1110	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGAUTHSTATUS;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGAUTHSTATUS;
elsif PSTATE.EL == EL3 then
    return DBGAUTHSTATUS;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGBCR<n>, Debug Breakpoint Control Registers, n = 0 - 15

The DBGBCR<n> characteristics are:

Purpose

Holds control information for a breakpoint. Forms breakpoint n together with value register DBGBVR<n>. If EL2 is implemented and this breakpoint supports Context matching, DBGBVR<n> can be associated with a Breakpoint Extended Value Register DBGBXVR<n> for VMID matching.

Configuration

AArch32 System register DBGBCR<n> bits [31:0] are architecturally mapped to AArch64 System register DBGBCR<n>_EL1[31:0] .

AArch32 System register DBGBCR<n> bits [31:0] are architecturally mapped to External register DBGBCR<n>_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGBCR<n> are UNKNOWN.

If breakpoint n is not implemented then accesses to this register are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGBCR<n> is a 32-bit register.

Field descriptions

The DBGBCR<n> bit assignments are:

31 30 29 28 27 26 25 24	23 22 21 20	19 18 17 16	15 14	13	12 11 10 9	8 7 6 5	4 3	2 1	0
RES0	BT	LBN	SSC	HMC	RES0	BAS	RES0	PMC	E

When the E field is zero, all the other fields in the register are ignored.

Bits [31:24]

Reserved, RES0.

BT, bits [23:20]

Breakpoint Type. Possible values are:

BT	Meaning
0b0000	Unlinked instruction address match. DBGBVR<n> is the address of an instruction.
0b0001	As 0b0000 with linking enabled.
0b0010	Unlinked Context ID match. When ARMv8.1-VHE is implemented, EL2 is using AArch64, and the Effective value of HCR_EL2.E2H is 1, if either the PE is executing at EL0 with HCR_EL2.TGE set to 0 or the PE is executing at EL2, then DBGBVR<n>.ContextID must match the CONTEXTIDR_EL2 value. Otherwise DBGBVR<n>.ContextID must match the CONTEXTIDR value.
0b0011	As 0b0010 with linking enabled.
0b0100	Unlinked instruction address mismatch. DBGBVR<n> is the address of an instruction to be stepped.
0b0101	As 0b0100 with linking enabled.
0b0110	Unlinked CONTEXTIDR_EL1 match. DBGBVR<n>.ContextID is a Context ID compared against CONTEXTIDR.
0b0111	As 0b0110 with linking enabled.
0b1000	Unlinked VMID match. DBGBXVR<n>.VMID is a VMID compared against VTTBR.VMID.
0b1001	As 0b1000 with linking enabled.
0b1010	Unlinked VMID and Context ID match. DBGBVR<n>.ContextID is a Context ID compared against CONTEXTIDR, and DBGBXVR<n>.VMID is a VMID compared against VTTBR.VMID.
0b1011	As 0b1010 with linking enabled.
0b1100	Unlinked CONTEXTIDR_EL2 match. DBGBXVR<n>.ContextID2 is a Context ID compared against CONTEXTIDR_EL2.
0b1101	As 0b1100 with linking enabled.
0b1110	Unlinked Full Context ID match. DBGBVR<n>.ContextID is compared against CONTEXTIDR, and DBGBXVR<n>.ContextID2 is compared against CONTEXTIDR_EL2.
0b1111	As 0b1110 with linking enabled.

For more information on Breakpoints and their constraints, see 'Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2.9 and 'Reserved DBGBCR<n>.BT values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

LBN, bits [19:16]

Linked breakpoint number. For Linked address matching breakpoints, this specifies the index of the Context-matching breakpoint linked to.

For all other breakpoint types this field is ignored and reads of the register return an UNKNOWN value.

This field is ignored when the value of DBGBCR<n>.E is 0.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

SSC, bits [15:14]

Security state control. Determines the Security states under which a Breakpoint debug event for breakpoint n is generated. This field must be interpreted along with the HMC and PMC fields, and there are constraints on the permitted values of the {HMC, SSC, PMC} fields.

For more information, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, and 'Reserved DBGBCR<n>.{SSC, HMC, PMC} values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

HMC, bit [13]

Higher mode control. Determines the debug perspective for deciding when a Breakpoint debug event for breakpoint n is generated. This field must be interpreted along with the SSC and PMC fields, and there are constraints on the permitted values of the {HMC, SSC, PMC} fields. For more information see the SSC, bits [15:14] description.

For more information on the operation of the SSC, HMC, and PMC fields, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Bits [12:9]

Reserved, RES0.

BAS, bits [8:5]

Byte address select. Defines which half-words an address-matching breakpoint matches, regardless of the instruction set and Execution state.

The permitted values depend on the breakpoint type.

For Address match breakpoints, the permitted values are:

BAS	Match instruction at	Constraint for debuggers
0b0011	DBGBVR<n>	Use for T32 instructions
0b1100	DBGBVR<n>+2	Use for T32 instructions
0b1111	DBGBVR<n>	Use for A32 instructions

All other values are reserved. For more information, see 'Reserved DBGBCR<n>.BAS values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

For more information on using the BAS field in Address Match breakpoints, see 'Using the BAS field in Address Match breakpoints' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

For Address mismatch breakpoints in an AArch32 stage 1 translation regime, the permitted values are:

BAS	Step instruction at	Constraint for debuggers
0b0000	-	Use for a match anywhere breakpoint
0b0011	DBGBVR<n>	Use for T32 instructions
0b1100	DBGBVR<n>+2	Use for T32 instructions
0b1111	DBGBVR<n>	Use for A32 instructions

All other values are reserved. For more information, see 'Reserved DBGBCR<n>.BAS values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

For more information on using the BAS field in address mismatch breakpoints, see 'Using the BAS field in Address Match breakpoints' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

For Context matching breakpoints, this field is RES1 and ignored.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Bits [4:3]

Reserved, RES0.

PMC, bits [2:1]

Privilege mode control. Determines the Exception level or levels at which a Breakpoint debug event for breakpoint n is generated. This field must be interpreted along with the SSC and HMC fields, and there are constraints on the permitted values of the {HMC, SSC, PMC} fields. For more information see the DBGBCR<n>.SSC description.

For more information on the operation of the SSC, HMC, and PMC fields, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

E, bit [0]

Enable breakpoint DBGBVR<n>. Possible values are:

E	Meaning
0b0	Breakpoint disabled.
0b1	Breakpoint enabled.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Accessing the DBGBCR<n>

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	n[3:0]	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBCR[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBCR[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL3 then
    if ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBCR[UInt(CRm<3:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	n[3:0]	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBCR[UInt(CRm<3:0>)] = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBCR[UInt(CRm<3:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBCR[UInt(CRm<3:0>)] = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGBVR<n>, Debug Breakpoint Value Registers, n = 0 - 15

The DBGBVR<n> characteristics are:

Purpose

Holds a value for use in breakpoint matching, either the virtual address of an instruction or a context ID. Forms breakpoint n together with control register DBGBCR<n>. If EL2 is implemented and this breakpoint supports Context matching, DBGBVR<n> can be associated with a Breakpoint Extended Value Register DBGBXVR<n> for VMID matching.

Configuration

AArch32 System register DBGBVR<n> bits [31:0] are architecturally mapped to AArch64 System register DBGBVR<n>_EL1[31:0] .

AArch32 System register DBGBVR<n> bits [31:0] are architecturally mapped to External register DBGBVR<n>_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGBVR<n> are UNKNOWN.

If breakpoint n is not implemented then accesses to this register are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

How this register is interpreted depends on the value of DBGBCR<n>.BT.

- When DBGBCR<n>.BT is `0b0x0x`, this register holds a virtual address.
- When DBGBCR<n>.BT is `0bxx1x`, this register holds a Context ID.

For other values of DBGBCR<n>.BT, this register is RES0.

Some breakpoints might not support Context ID comparison. For more information, see the description of the DBGDIDR.CTX_CMPs field.

Field descriptions

The DBGBVR<n> bit assignments are:

When DBGBCR<n>.BT == 0b0x0x:



VA[31:2], bits [31:2]

Bits[31:2] of the address value for comparison.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.

- On a Warm reset, the value of this field is unchanged.

Bits [1:0]

Reserved, RES0.

When DBGBCR<n>.BT == 0b001x:



ContextID, bits [31:0]

Context ID value for comparison.

The value is compared against CONTEXTIDR_EL2 when all of the following are true:

- CONTEXTIDR_EL2 is implemented.
- ~~ARMv8.1-VHE is implemented.~~
- HCR_EL2.{E2H, TGE} is {1,1}.
- The PE is executing at EL0.
- EL2 is using AArch64 and is enabled in the current Security state.~~state, and is using AArch64.~~

Otherwise, the value is compared against CONTEXTIDR.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

When DBGBCR<n>.BT == 0b101x and ~~HaveEL(~~EL2 is implemented:~~):~~



ContextID, bits [31:0]

Context ID value for comparison against CONTEXTIDR.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

When DBGBCR<n>.BT == 0bx11x, ~~HaveEL(~~EL2~~)~~ is implemented and (ARMv8.1-VHE is implemented or ARMv8.2-Debug is implemented)~~:~~:



ContextID, bits [31:0]

Context ID value for comparison against CONTEXTIDR.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Accessing the DBGBVR<n>

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	n[3:0]	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBVR[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBVR[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL3 then
    if ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBVR[UInt(CRm<3:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	n[3:0]	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBVR[UInt(CRm<3:0>)] = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBVR[UInt(CRm<3:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBVR[UInt(CRm<3:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGBXVR<n>, Debug Breakpoint Extended Value Registers, n = 0 - 15

The DBGBXVR<n> characteristics are:

Purpose

Holds a value for use in breakpoint matching, to support VMID matching. Used in conjunction with a control register DBGBCR<n> and a value register DBGBVR<n>, where EL2 is implemented and breakpoint n supports Context matching.

Configuration

AArch32 System register DBGBXVR<n> bits [31:0] are architecturally mapped to AArch64 System register DBGBVR<n>_EL1[63:32] .

AArch32 System register DBGBXVR<n> bits [31:0] are architecturally mapped to External register DBGBVR<n>_EL1[63:32] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGBXVR<n> are UNKNOWN.

Accesses to this register are UNDEFINED in any of the following cases:

- Breakpoint n is not implemented.
- Breakpoint n does not support Context matching.
- EL2 is not implemented.

For more information, see the description of the DBGDIDR.CTX_CMPs field.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

How this register is interpreted depends on the value of DBGBCR<n>.BT.

- When DBGBCR<n>.BT is `0b10xx`, this register holds a VMID.
- When DBGBCR<n>.BT is `0b11xx`, this register holds a Context ID.

For other values of DBGBCR<n>.BT, this register is RES0.

Field descriptions

The DBGBXVR<n> bit assignments are:

When DBGBCR<n>.BT == 0b10xx and ~~HaveEL(~~EL2 is implemented~~):~~

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																VMID[15:8]								VMID[7:0]							

Bits [31:16]

Reserved, RES0.

VMID[15:8], bits [15:8]

When ARMv8.1-VMID16 is implemented and VTCR_EL2.VS == 1:

Extension to VMID[7:0]. See VMID[7:0] for more details.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Otherwise:

Reserved, RES0.

VMID[7:0], bits [7:0]

~~The VMID is 8 bits in the following cases.~~

VMID value for comparison. The VMID is 8 bits when any of the following are true:

- EL2 is using AArch32.
- VTCR_EL2.VS is 0.
- ARMv8.1-VMID16 is not implemented.

~~When ARMv8.1-VMID16 is implemented and EL2 is using AArch64, it is IMPLEMENTATION DEFINED whether the VMID is 8 bits or 16 bits.~~

~~VMID[15:8] is RES0 if any of the following applies:~~

- ~~The implementation has an 8-bit VMID.~~
- ~~VTCR_EL2.VS has a value of 0.~~
- ~~EL2 is using AArch32.~~

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

When DBGBCR<n>.BT == 0b11xx and ~~HaveEL(~~EL2 is implemented:~~):~~

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
ContextID2																															

ContextID2, bits [31:0]

When ARMv8.1-VHE is implemented or ARMv8.2-Debug is implemented:

Context ID value for comparison against CONTEXTIDR_EL2.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Otherwise:

Reserved, RES0.

Accessing the DBGBXVR<n>

Accesses to this register use the following encodings:

MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0001	n[3:0]	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBXVR[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBXVR[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL3 then
    if ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGBXVR[UInt(CRm<3:0>)];
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0001	n[3:0]	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBXVR[UInt(CRm<3:0>)] = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBXVR[UInt(CRm<3:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGBXVR[UInt(CRm<3:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGCLAIMCLR, Debug CLAIM Tag Clear register

The DBGCLAIMCLR characteristics are:

Purpose

Used by software to read the values of the CLAIM tag bits, and to clear CLAIM tag bits to 0.

The architecture does not define any functionality for the CLAIM tag bits.

Note

CLAIM tags are typically used for communication between the debugger and target software.

Used in conjunction with the DBGCLAIMSET register.

Configuration

AArch32 System register DBGCLAIMCLR bits [31:0] are architecturally mapped to AArch64 System register DBGCLAIMCLR_EL1[31:0] .

AArch32 System register DBGCLAIMCLR bits [31:0] are architecturally mapped to External register DBGCLAIMCLR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGCLAIMCLR are UNKNOWN.

An implementation must include eight CLAIM tag bits.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGCLAIMCLR is a 32-bit register.

Field descriptions

The DBGCLAIMCLR bit assignments are:



Bits [31:8]

Reserved, RAZ/SBZ. Software can rely on these bits reading as zero, and must use a should-be-zero policy on writes. Implementations must ignore writes.

CLAIM, bits [7:0]

Read or clear CLAIM tag bits. Reading this field returns the current value of the CLAIM tag bits.

Writing a 1 to one of these bits clears the corresponding CLAIM tag bit to 0. This is an indirect write to the CLAIM tag bits. A single write operation can clear multiple CLAIM tag bits to 0.

Writing 0 to one of these bits has no effect.

The following resets apply:

~~On a Cold reset, this field resets to 0.~~

- On a Cold reset, this field resets to 0.
- On a Warm reset, the value of this field is unchanged.

Accessing the DBGCLAIMCLR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0111	0b1001	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGCLAIMCLR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGCLAIMCLR;
elsif PSTATE.EL == EL3 then
    return DBGCLAIMCLR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0111	0b1001	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGCLAIMCLR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGCLAIMCLR = R[t];
elsif PSTATE.EL == EL3 then
    DBGCLAIMCLR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGCLAIMSET, Debug CLAIM Tag Set register

The DBGCLAIMSET characteristics are:

Purpose

Used by software to set the CLAIM tag bits to 1.

The architecture does not define any functionality for the CLAIM tag bits.

Note

CLAIM tags are typically used for communication between the debugger and target software.

Used in conjunction with the DBGCLAIMCLR register.

Configuration

AArch32 System register DBGCLAIMSET bits [31:0] are architecturally mapped to AArch64 System register DBGCLAIMSET_EL1[31:0] .

AArch32 System register DBGCLAIMSET bits [31:0] are architecturally mapped to External register DBGCLAIMSET_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGCLAIMSET are UNKNOWN.

An implementation must include eight CLAIM tag bits.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGCLAIMSET is a 32-bit register.

Field descriptions

The DBGCLAIMSET bit assignments are:



Bits [31:8]

Reserved, RAZ/SBZ. Software can rely on these bits reading as zero, and must use a should-be-zero policy on writes. Implementations must ignore writes.

CLAIM, bits [7:0]

Set CLAIM tag bits.

This field is RAO.

Writing a 1 to one of these bits sets the corresponding CLAIM tag bit to 1. This is an indirect write to the CLAIM tag bits. A single write operation can set multiple CLAIM tag bits to 1.

Writing 0 to one of these bits has no effect.

On a Cold reset, this field resets to `0`.

Accessing the DBGCLAIMSET

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0111	0b1000	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGCLAIMSET;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGCLAIMSET;
elsif PSTATE.EL == EL3 then
    return DBGCLAIMSET;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0111	0b1000	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGCLAIMSET = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGCLAIMSET = R[t];
elsif PSTATE.EL == EL3 then
    DBGCLAIMSET = R[t];
```

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDCCINT, DCC Interrupt Enable Register

The DBGDCCINT characteristics are:

Purpose

Enables interrupt requests to be signaled based on the DCC status flags.

Configuration

AArch32 System register DBGDCCINT bits [31:0] are architecturally mapped to AArch64 System register MDCCINT_EL1[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to DBGDCCINT arearchitecturally UNKNOWN.values.

Attributes

DBGDCCINT is a 32-bit register.

Field descriptions

The DBGDCCINT bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0	RX	TX	RES0																												

Bit [31]

Reserved, RES0.

RX, bit [30]

DCC interrupt request enable control for DTRRX. Enables a common **COMMIRQ** interrupt request to be signaled based on the DCC status flags.

RX	Meaning
0b0	No interrupt request generated by DTRRX.
0b1	Interrupt request will be generated on RXfull == 1.

If legacy **COMMRX** and **COMMTX** signals are implemented, then these are not affected by the value of this bit.

On a Warm reset, this field resets to 0.

TX, bit [29]

DCC interrupt request enable control for DTRTX. Enables a common **COMMIRQ** interrupt request to be signaled based on the DCC status flags.

TX	Meaning
0b0	No interrupt request generated by DTRTX.
0b1	Interrupt request will be generated on TXfull == 0.

If legacy **COMMRX** and **COMMTX** signals are implemented, then these are not affected by the value of this bit.

On a Warm reset, this field resets to `0`.

Bits [28:0]

Reserved, RES0.

Accessing the DBGDCCINT

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDCCINT;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDCCINT;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return DBGDCCINT;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGDCCINT = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGDCCINT = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    else
        DBGDCCINT = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116~~134483bd14dc8c12a99c984cbfe3431cc1c9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDEVID, Debug Device ID register 0

The DBGDEVID characteristics are:

Purpose

Adds to the information given by the DBGDIDR by describing other features of the debug implementation.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGDEVID are UNKNOWN.

This register is required in all implementations.

Attributes

DBGDEVID is a 32-bit register.

Field descriptions

The DBGDEVID bit assignments are:

31 30 29 28	27 26 25 24	23 22 21 20	19 18 17 16	15 14 13 12	11 10 9 8	7 6 5 4	3 2 1 0
CIDMask	AuxRegs	DoubleLock	VirtExtns	VectorCatch	BPAddrMask	WPAddrMask	PCSample

CIDMask, bits [31:28]

Indicates the level of support for the Context ID matching breakpoint masking capability. Permitted values of this field are:

CIDMask	Meaning
0b0000	Context ID masking is not implemented.
0b0001	Context ID masking is implemented.

All other values are reserved. The value of this for Armv8 is 0b0000.

AuxRegs, bits [27:24]

Indicates support for Auxiliary registers. Permitted values for this field are:

AuxRegs	Meaning
0b0000	None supported.
0b0001	Support for External Debug Auxiliary Control Register, EDACR.

All other values are reserved.

DoubleLock, bits [23:20]

OS Double Lock implemented. Defined values are:

DoubleLock	Meaning
0b0000	OS Double Lock is not implemented. DBGOSDLR is RAZ/WI.
0b0001	OS Double Lock is implemented. DBGOSDLR is RW.

ARMv8.0-DoubleLock implements the functionality identified by the value 0b0001.

All other values are reserved.

VirtExtns, bits [19:16]

Indicates whether EL2 is implemented. Permitted values of this field are:

VirtExtns	Meaning
0b0000	EL2 is not implemented.
0b0001	EL2 is implemented.

All other values are reserved.

VectorCatch, bits [15:12]

Defines the form of Vector Catch exception implemented. Permitted values of this field are:

VectorCatch	Meaning
0b0000	Address matching Vector Catch exception implemented.
0b0001	Exception matching Vector Catch exception implemented.

All other values are reserved.

BPAddrMask, bits [11:8]

Indicates the level of support for the instruction address matching breakpoint masking capability. Permitted values of this field are:

BPAddrMask	Meaning
0b0000	Breakpoint address masking might be implemented. If not implemented, DBGBCR<n>[28:24] is RAZ/WI.
0b0001	Breakpoint address masking is implemented.
0b1111	Breakpoint address masking is not implemented. DBGBCR<n>[28:24] is RES0.

All other values are reserved. The value of this for Armv8 is 0b1111.

WPAddrMask, bits [7:4]

Indicates the level of support for the data address matching watchpoint masking capability. Permitted values of this field are:

WPAddrMask	Meaning
0b0000	Watchpoint address masking might be implemented. If not implemented, DBGWCR<n>.MASK (Address mask) is RAZ/WI.
0b0001	Watchpoint address masking is implemented.
0b1111	Watchpoint address masking is not implemented. DBGWCR<n>.MASK (Address mask) is RES0.

All other values are reserved. The value of this for Armv8 is 0b0001.

PCSample, bits [3:0]

Indicates the level of PC Sample-based Profiling support using external debug registers. Permitted values of this field are:

PCSample	Meaning
0b0000	PC Sample-based Profiling Extension is not implemented in the external debug registers space.
0b0010	Only EDPCSR and EDCIDSR are implemented. This option is only permitted if EL3 and EL2 are not implemented.
0b0011	EDPCSR, EDCIDSR, and EDVIDSR are implemented.

All other values are reserved.

When ARMv8.2-PCSample is implemented, the only permitted value is `0b0000`.

Note

ARMv8.2-PCSample implements the PC Sample-based Profiling Extension in the Performance Monitors register space, as indicated by the value of PMDEVID.PCSample.

Accessing the DBGDEVID

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0111	0b0010	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDEVID;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDEVID;
elsif PSTATE.EL == EL3 then
    return DBGDEVID;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDEVID1, Debug Device ID register 1

The DBGDEVID1 characteristics are:

Purpose

Adds to the information given by the DBGDIDR by describing other features of the debug implementation.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGDEVID1 are UNKNOWN.

This register is required in all implementations.

Attributes

DBGDEVID1 is a 32-bit register.

Field descriptions

The DBGDEVID1 bit assignments are:



Bits [31:4]

Reserved, RES0.

PCSROffset, bits [3:0]

This field indicates the offset applied to PC samples returned by reads of EDPCSR. Permitted values of this field in Armv8 are:

PCSROffset	Meaning
0b0000	EDPCSR is not implemented.
0b0010	EDPCSR implemented. Samples have no offset applied and do not sample the instruction set state in AArch32 state.

When ARMv8.2-PCSample is implemented, the only permitted value is 0b0000.

Note

ARMv8.2-PCSample implements the PC Sample-based Profiling Extension in the Performance Monitors register space, as indicated by the value of PMDEVID.PCSample.

Accessing the DBGDEVID1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0111	0b0001	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDEVID1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDEVID1;
elsif PSTATE.EL == EL3 then
    return DBGDEVID1;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116~~134483bd14dc8c12a99c984cbfe3431cc1c9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDEVID2, Debug Device ID register 2

The DBGDEVID2 characteristics are:

Purpose

Reserved for future descriptions of features of the debug implementation.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGDEVID2 are UNKNOWN.

Attributes

DBGDEVID2 is a 32-bit register.

Field descriptions

The DBGDEVID2 bit assignments are:



Bits [31:0]

Reserved, RES0.

Accessing the DBGDEVID2

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0111	0b0000	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDEVID2;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDEVID2;
elsif PSTATE.EL == EL3 then
    return DBGDEVID2;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDIDR, Debug ID Register

The DBGDIDR characteristics are:

Purpose

Specifies which version of the Debug architecture is implemented, and some features of the debug implementation.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGDIDR are UNKNOWN.

If EL1 cannot use AArch32 then the implementation of this register is OPTIONAL and deprecated.

Attributes

DBGDIDR is a 32-bit register.

Field descriptions

The DBGDIDR bit assignments are:



WRPs, bits [31:28]

The number of watchpoints implemented, minus 1.

Permitted values of this field are from `0b0001` for 2 implemented watchpoints, to `0b1111` for 16 implemented watchpoints.

The value of `0b0000` is reserved.

If AArch64 is implemented, this field has the same value as ID_AA64DFR0_EL1.WRPs.

BRPs, bits [27:24]

The number of breakpoints implemented, minus 1.

Permitted values of this field are from `0b0001` for 2 implemented breakpoint, to `0b1111` for 16 implemented breakpoints.

The value of `0b0000` is reserved.

If AArch64 is implemented, this field has the same value as ID_AA64DFR0_EL1.BRPs.

CTX_CMPs, bits [23:20]

The number of breakpoints that can be used for Context matching, minus 1.

Permitted values of this field are from `0b0000` for 1 Context matching breakpoint, to `0b1111` for 16 Context matching breakpoints.

The Context matching breakpoints must be the highest addressed breakpoints. For example, if six breakpoints are implemented and two are Context matching breakpoints, they must be breakpoints 4 and 5.

If AArch64 is implemented, this field has the same value as ID_AA64DFR0_EL1.CTX_CMPs.

Version, bits [19:16]

The Debug architecture version. Defined values are:

Version	Meaning
0b0001	Armv6, v6 Debug architecture.
0b0010	Armv6, v6.1 Debug architecture.
0b0011	Armv7, v7 Debug architecture, with baseline CP14 registers implemented.
0b0100	Armv7, v7 Debug architecture, with all CP14 registers implemented.
0b0101	Armv7, v7.1 Debug architecture.
0b0110	Armv8, v8 Debug architecture.
0b0111	Armv8.1, v8 Debug architecture, with Virtualization Host Extensions.
0b1000	Armv8.2, v8.2 Debug architecture.
0b1001	Armv8.4, v8.4 Debug architecture.

All other values are reserved.

In any Armv8 implementation, the values 0b0001, 0b0010, 0b0011, 0b0100, and 0b0101 are not permitted.

- If ARMv8.1-VHE is not implemented, the only permitted value is 0b0110.
- In an Armv8.0 implementation, the value 0b1000 or higher is not permitted.

Bit [15]

Reserved, RES1.

nSUHD_imp, bit [14]

In Armv7-A, was Secure User Halting Debug not implemented.

The value of this bit must match the value of the SE_imp bit.

Bit [13]

Reserved, RES0.

SE_imp, bit [12]

EL3 implemented. The meanings of the values of this bit are:

SE_imp	Meaning
0b0	EL3 not implemented.
0b1	EL3 implemented.

The value of this bit must match the value of the nSUHD_imp bit.

Bits [11:0]

Reserved, RES0.

Accessing the DBGDIDR

Arm deprecates any access to this register from EL0.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x05);
    elsif ELUsingAArch32(EL1) && DBGDSCRext.UDCCdis == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' || MDCR_EL2.<TDE,TDA> !=
'00') then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR.TGE == '1' || HDCR.<TDE,TDA> != '00') then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDIDR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDIDR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDIDR;
elsif PSTATE.EL == EL3 then
    return DBGDIDR;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDRAR, Debug ROM Address Register

The DBGDRAR characteristics are:

Purpose

Defines the base physical address of a 4KB-aligned memory-mapped debug component, usually a ROM table that locates and describes the memory-mapped debug components in the system. Armv8 deprecates any use of this register.

Configuration

AArch32 System register DBGDRAR bits [63:0] are architecturally mapped to AArch64 System register MDRAR_EL1[63:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGDRAR are UNKNOWN.

If EL1 cannot use AArch32 then the implementation of this register is OPTIONAL and deprecated.

Attributes

DBGDRAR is a 64-bit register that can also be accessed as a 32-bit value. If it is accessed as a 32-bit register, bits [31:0] are read.

Field descriptions

The DBGDRAR bit assignments are:



Bits [63:48]

Reserved, RES0.

ROMADDR[47:12], bits [47:12]

Bits[47:12] of the ROM table physical address.

If the physical address size in bits (PAsize) is less than 48 then the register bits corresponding to ROMADDR [47:PAsize] are RES0.

Bits [11:0] of the ROM table physical address are zero.

Arm strongly recommends that bits ROMADDR[(PAsize-1):32] are zero in any system that supports AArch32 at the highest implemented Exception level.

In an implementation that includes EL3, ROMADDR is an address in Non-secure memory. It is IMPLEMENTATION DEFINED whether the ROM table is also accessible in Secure memory.

Bits [11:2]

Reserved, RES0.

Valid, bits [1:0]

This field indicates whether the ROM Table address is valid. The permitted values of this field are:

Valid	Meaning
0b00	ROM Table address is not valid. Software must ignore ROMADDR.
0b11	ROM Table address is valid.

Other values are reserved.

Accessing the DBGDRAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x05);
    elsif ELUsingAArch32(EL1) && DBGDSCRext.UDCCdis == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' || MDCR_EL2.<TDE,TDRA> !=
'00') then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR.TGE == '1' || HDCR.<TDE,TDRA> != '00') then
        AArch32.TakeHypTrapException(0x05);
    else
        return DBGDRAR<31:0>;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDRA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDRA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    else
        return DBGDRAR<31:0>;
elsif PSTATE.EL == EL2 then
    return DBGDRAR<31:0>;
elsif PSTATE.EL == EL3 then
    return DBGDRAR<31:0>;
```

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1110	0b0001	0b0000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x0C);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x0C);
    elsif ELUsingAArch32(EL1) && DBGDSCRext.UDCCdis == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x0C);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' || MDCR_EL2.<TDE,TDRA> !=
'00') then
        AArch64.AArch32SystemAccessTrap(EL2, 0x0C);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR.TGE == '1' || HDCR.<TDE,TDRA> != '00') then
        AArch32.TakeHypTrapException(0x0C);
    else
        return DBGDRAR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDRA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x0C);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDRA> != '00' then
        AArch32.TakeHypTrapException(0x0C);
    else
        return DBGDRAR;
elsif PSTATE.EL == EL2 then
    return DBGDRAR;
elsif PSTATE.EL == EL3 then
    return DBGDRAR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDSAR, Debug Self Address Register

The DBGDSAR characteristics are:

Purpose

In earlier versions of the Arm Architecture, this register defines the offset from the base address defined in DBGDRAR of the physical base address of the debug registers for the PE. Armv8 deprecates any use of this register.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGDSAR are UNKNOWN.

If EL1 cannot use AArch32 then the implementation of this register is OPTIONAL and deprecated.

Attributes

DBGDSAR is a 64-bit register that can also be accessed as a 32-bit value. If it is accessed as a 32-bit register, bits [31:0] are read.

Field descriptions

The DBGDSAR bit assignments are:



Bits [63:2]

Reserved, RES0.

Bits [1:0]

Reserved, RAZ.

This field indicates whether the debug self address offset is valid. For ARMv8, this field is always `0b00`, the offset is not valid.

Accessing the DBGDSAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0010	0b0000	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x05);
    elsif ELUsingAArch32(EL1) && DBGDSCRext.UDCCdis == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' || MDCR_EL2.<TDE,TDRA> !=
'00') then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR.TGE == '1' || HDCR.<TDE,TDRA> != '00') then
        AArch32.TakeHypTrapException(0x05);
    else
        return DBGDSAR<31:0>;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDRA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDRA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    else
        return DBGDSAR<31:0>;
elsif PSTATE.EL == EL2 then
    return DBGDSAR<31:0>;
elsif PSTATE.EL == EL3 then
    return DBGDSAR<31:0>;
```

MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1110	0b0010	0b0000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x0C);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x0C);
    elsif ELUsingAArch32(EL1) && DBGDSCRext.UDCCdis == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x0C);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' || MDCR_EL2.<TDE,TDRA> !=
'00') then
        AArch64.AArch32SystemAccessTrap(EL2, 0x0C);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR.TGE == '1' || HDCR.<TDE,TDRA> != '00') then
        AArch32.TakeHypTrapException(0x0C);
    else
        return DBGDSAR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDRA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x0C);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDRA> != '00' then
        AArch32.TakeHypTrapException(0x0C);
    else
        return DBGDSAR;
elsif PSTATE.EL == EL2 then
    return DBGDSAR;
elsif PSTATE.EL == EL3 then
    return DBGDSAR;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDSCRext, Debug Status and Control Register, External View

The DBGDSCRext characteristics are:

Purpose

Main control register for the debug implementation.

Configuration

AArch32 System register DBGDSCRext bits [31:0] are architecturally mapped to AArch64 System register MDSCR_EL1[31:0] .

AArch32 System register DBGDSCRext bits [15:2] are architecturally mapped to AArch32 System register DBGDSCRint[15:2] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGDSCRext are UNKNOWN.

This register is required in all implementations.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGDSCRext is a 32-bit register.

Field descriptions

The DBGDSCRext bit assignments are:



TFO, bit [31]

When ARMv8.4-Trace is implemented:

Trace Filter override. Used for save/restore of EDSCR.TFO.

When the OS Lock is unlocked, DBGOSLSR.OSLK == 0, software must treat this bit as UNK/SBZP.

When the OS Lock is locked, DBGOSLSR.OSLK == 1, this bit holds the value of EDSCR.TFO. Reads and writes of this bit are indirect accesses to EDSCR.TFO.

Accessing this field has the following behavior:

- When DBGOSLSR.OSLK == 1, access to this field is **RW**.
- When DBGOSLSR.OSLK == 0, access to this field is **RO**.

Otherwise:

Reserved, RES0.

RXfull, bit [30]

DTRRX full. Used for save/restore of EDSCR.RXfull.

When DBGOSLSR.OSLK == 0, software must treat this bit as UNK/SBZP.

When DBGOSLSR.OSLK == 1, this bit holds the value of EDSCR.RXfull. Reads and writes of this bit are indirect accesses to EDSCR.RXfull.

Arm deprecates use of this bit other than for save/restore. Use DBGDSCRint to access the DTRRX full status.

The architected behavior of this field determines the value it returns after a reset.

Accessing this field has the following behavior:

- When DBGOSLSR.OSLK == 1, access to this field is **RW**.
- When DBGOSLSR.OSLK == 0, access to this field is **RO**.

TXfull, bit [29]

DTRTX full. Used for save/restore of EDSCR.TXfull.

When DBGOSLSR.OSLK == 0, software must treat this bit as UNK/SBZP.

When DBGOSLSR.OSLK == 1, this bit holds the value of EDSCR.TXfull. Reads and writes of this bit are indirect accesses to EDSCR.TXfull.

Arm deprecates use of this bit other than for save/restore. Use DBGDSCRint to access the DTRTX full status.

The architected behavior of this field determines the value it returns after a reset.

Accessing this field has the following behavior:

- When DBGOSLSR.OSLK == 1, access to this field is **RW**.
- When DBGOSLSR.OSLK == 0, access to this field is **RO**.

Bit [28]

Reserved, RES0.

RXO, bit [27]

Used for save/restore of EDSCR.RXO.

When DBGOSLSR.OSLK == 0, software must treat this bit as UNK/SBZP.

When DBGOSLSR.OSLK == 1, this bit holds the value of EDSCR.RXO. Reads and writes of this bit are indirect accesses to EDSCR.RXO.

The architected behavior of this field determines the value it returns after a reset.

Accessing this field has the following behavior:

- When DBGOSLSR.OSLK == 1, access to this field is **RW**.
- When DBGOSLSR.OSLK == 0, access to this field is **RO**.

TXU, bit [26]

Used for save/restore of EDSCR.TXU.

When DBGOSLSR.OSLK == 0, software must treat this bit as UNK/SBZP.

When DBGOSLSR.OSLK == 1, this bit holds the value of EDSCR.TXU. Reads and writes of this bit are indirect accesses to EDSCR.TXU.

The architected behavior of this field determines the value it returns after a reset.

Accessing this field has the following behavior:

- When DBGOSLSR.OSLK == 1, access to this field is **RW**.
- When DBGOSLSR.OSLK == 0, access to this field is **RO**.

Bits [25:24]

Reserved, RES0.

INTdis, bits [23:22]

Used for save/restore of EDSCR.INTdis.

When DBGOSLSR.OSLK == 0, this field is RO, and software must treat it as UNK/SBZP.

When DBGOSLSR.OSLK == 1, this field is RW and holds the value of EDSCR.INTdis. Reads and writes of this field are indirect accesses to EDSCR.INTdis.

The architected behavior of this field determines the value it returns after a reset.

Accessing this field has the following behavior:

- When DBGOSLSR.OSLK == 1, access to this field is **RW**.
- When DBGOSLSR.OSLK == 0, access to this field is **RO**.

TDA, bit [21]

Used for save/restore of EDSCR.TDA.

When DBGOSLSR.OSLK == 0, software must treat this bit as UNK/SBZP.

When DBGOSLSR.OSLK == 1, this bit holds the value of EDSCR.TDA. Reads and writes of this bit are indirect accesses to EDSCR.TDA.

The architected behavior of this field determines the value it returns after a reset.

Accessing this field has the following behavior:

- When DBGOSLSR.OSLK == 1, access to this field is **RW**.
- When DBGOSLSR.OSLK == 0, access to this field is **RO**.

Bit [20]

Reserved, RES0.

SC2, bit [19]

When ARMv8.0-PCSample is implemented, ARMv8.1-VHE is implemented and ARMv8.2-PCSample is not implemented:

Used for save/restore of EDSCR.SC2.

When DBGOSLSR.OSLK == 0, software must treat this bit as UNK/SBZP.

When DBGOSLSR.OSLK == 1, this bit holds the value of EDSCR.SC2. Reads and writes of this bit are indirect accesses to EDSCR.SC2.

Accessing this field has the following behavior:

- When DBGOSLSR.OSLK == 1, access to this field is **RW**.
- When DBGOSLSR.OSLK == 0, access to this field is **RO**.

Otherwise:

Reserved, RES0.

NS, bit [18]

Non-secure status. Returns the inverse of IsSecure().

Arm deprecates use of this field.

Access to this field is **RO**.

SPNIDdis, bit [17]

When HaveEL(EL3 is implemented):

Secure privileged profiling disabled status bit.

SPNIDdis	Meaning
0b0	Profiling allowed in Secure privileged modes.
0b1	Profiling prohibited in Secure privileged modes.

This field reads as 0 if any of the following applies, and reads as 1 otherwise:

- ARMv8.2-Debug is not implemented and ExternalSecureNoninvasiveDebugEnabled() returns TRUE.
- EL3 is using AArch32 and the value of SDCR.SPME is 1.
- EL3 is using AArch64 and the value of MDCR_EL3.SPME is 1.

Arm deprecates use of this field.

Access to this field is **RO**.

Otherwise:

Reserved, RES0.

SPIDdis, bit [16]

When HaveEL(EL3 is implemented):

Secure privileged AArch32 invasive self-hosted debug disabled status bit. The value of this bit depends on the value of SDCR.SPD and the pseudocode function AArch32.SelfHostedSecurePrivilegedInvasiveDebugEnabled().

SPIDdis	Meaning
0b0	Self-hosted debug enabled in Secure privileged AArch32 modes.
0b1	Self-hosted debug disabled in Secure privileged AArch32 modes.

This bit reads as 1 if any of the following is true and reads as 0 otherwise:

- EL3 is using AArch32 and SDCR.SPD has the value 0b10.
- EL3 is using AArch64 and MDCR_EL3.SPD32 has the value 0b10.
- EL3 is using AArch32, SDCR.SPD has the value 0b00, and AArch32.SelfHostedSecurePrivilegedInvasiveDebugEnabled() returns FALSE.
- EL3 is using AArch64, MDCR_EL3.SPD32 has the value 0b00, and AArch32.SelfHostedSecurePrivilegedInvasiveDebugEnabled() returns FALSE.

Arm deprecates use of this field.

Access to this field is **RO**.

Otherwise:

Reserved, RES0.

MDBGen, bit [15]

Monitor debug events enable. Enable Breakpoint, Watchpoint, and Vector Catch exceptions.

MDBGen	Meaning
0b0	Breakpoint, Watchpoint, and Vector Catch exceptions disabled.
0b1	Breakpoint, Watchpoint, and Vector Catch exceptions enabled.

On a Warm reset, this field resets to 0.

HDE, bit [14]

Used for save/restore of EDSCR.HDE.

When DBGOSLSR.OSLK == 0, software must treat this bit as UNK/SBZP.

When DBGOSLSR.OSLK == 1, this bit holds the value of EDSCR.HDE. Reads and writes of this bit are indirect accesses to EDSCR.HDE.

The architected behavior of this field determines the value it returns after a reset.

Accessing this field has the following behavior:

- When DBGOSLSR.OSLK == 1, access to this field is **RW**.
- When DBGOSLSR.OSLK == 0, access to this field is **RO**.

Bit [13]

Reserved, RES0.

UDCCdis, bit [12]

Traps EL0 accesses to the DCC registers to Undefined mode.

UDCCdis	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	EL0 accesses to the DBGDSCRint, DBGDTRRXint, DBGDTRTXint, DBGDIDR, DBGDSAR, and DBGDRAR are trapped to Undefined mode.

Note

All accesses to these registers are trapped, including LDC and STC accesses to DBGDTRTXint and DBGDTRRXint, and MRRC accesses to DBGDSAR and DBGDRAR.

Traps of EL0 accesses to the DBGDTRRXint and DBGDTRTXint are ignored in Debug state.

On a Warm reset, this field resets to 0.

Bits [11:7]

Reserved, RES0.

ERR, bit [6]

Used for save/restore of EDSCR.ERR.

When DBGOSLSR.OSLK == 0, software must treat this bit as UNK/SBZP.

When DBGOSLSR.OSLK == 1, this bit holds the value of EDSCR.ERR. Reads and writes of this bit are indirect accesses to EDSCR.ERR.

The architected behavior of this field determines the value it returns after a reset.

Accessing this field has the following behavior:

- When DBGOSLSR.OSLK == 1, access to this field is **RW**.
- When DBGOSLSR.OSLK == 0, access to this field is **RO**.

MOE, bits [5:2]

Method of Entry for debug exception. When a debug exception is taken to an Exception level using AArch32, this field is set to indicate the event that caused the exception:

MOE	Meaning
0b0001	Breakpoint.
0b0011	Software breakpoint (BKPT) instruction.
0b0101	Vector catch.
0b1010	Watchpoint.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bits [1:0]

Reserved, RES0.

Accessing the DBGDSCRext

Individual fields within this register might have restricted accessibility when the OS lock is unlocked, DBGOSLSR.OSLK == 0. See the field descriptions for more detail.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0010	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDSCRext;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDSCRext;
elsif PSTATE.EL == EL3 then
    return DBGDSCRext;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0010	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGDSCRext = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGDSCRext = R[t];
elsif PSTATE.EL == EL3 then
    DBGDSCRext = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDSCRint, Debug Status and Control Register, Internal View

The DBGDSCRint characteristics are:

Purpose

Main control register for the debug implementation. This is an internal, read-only view.

Configuration

AArch32 System register DBGDSCRint bits [30:29] are architecturally mapped to AArch64 System register MDCCSR_EL0[30:29] .

AArch32 System register DBGDSCRint bits [15:2] are architecturally mapped to AArch32 System register DBGDSCRext[15:2] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGDSCRint are UNKNOWN.

This register is required in all implementations.

DBGDSCRint.{NS, SPNIDdis, SPIDdis, MDBGen, UDCCdis, MOE} are UNKNOWN when the register is accessed at EL0. However, although these values are not accessible at EL0 by instructions that are neither UNPREDICTABLE nor return UNKNOWN values, it is permissible for an implementation to return the values of DBGDSCRext.{NS, SPNIDdis, SPIDdis, MDBGen, UDCCdis, MOE} for these fields at EL0.

It is also permissible for an implementation to return the same values as defined for a read of DBGDSCRint at EL1 or above. (This is the case even if the implementation does not support AArch32 at EL1 or above.)

Attributes

DBGDSCRint is a 32-bit register.

Field descriptions

The DBGDSCRint bit assignments are:



Bit [31]

Reserved, RES0.

RXfull, bit [30]

DTRRX full. Read-only view of the equivalent bit in the EDSCR.

TXfull, bit [29]

DTRTX full. Read-only view of the equivalent bit in the EDSCR.

Bits [28:19]

Reserved, RES0.

NS, bit [18]

Non-secure status.

Read-only view of the equivalent bit in the DBGDSCRext. Arm deprecates use of this field.

SPNIDdis, bit [17]

Secure privileged non-invasive debug disable.

Read-only view of the equivalent bit in the DBGDSCRext. Arm deprecates use of this field.

SPIDdis, bit [16]

Secure privileged invasive debug disable.

Read-only view of the equivalent bit in the DBGDSCRext. Arm deprecates use of this field.

MDBGen, bit [15]

Monitor debug events enable.

Read-only view of the equivalent bit in the DBGDSCRext.

Bits [14:13]

Reserved, RES0.

UDCCdis, bit [12]

User mode access to Debug Communications Channel disable.

Read-only view of the equivalent bit in the DBGDSCRext. Arm deprecates use of this field.

Bits [11:6]

Reserved, RES0.

MOE, bits [5:2]

Method of Entry for debug exception. When a debug exception is taken to an Exception level using AArch32, this field is set to indicate the event that caused the exception:

MOE	Meaning
0b0001	Breakpoint
0b0011	Software breakpoint (BKPT) instruction
0b0101	Vector catch
0b1010	Watchpoint

Read-only view of the equivalent bit in the DBGDSCRext.

Bits [1:0]

Reserved, RES0.

Accessing the DBGDSCRint

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0001	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x05);
    elsif ELUsingAArch32(EL1) && DBGDSCRext.UDCCdis == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' || MDCR_EL2.<TDE,TDA> !=
'00') then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (HCR.TGE == '1' || HDCR.<TDE,TDA> != '00') then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SDCR.TDCCMDCR_EL3.TDA == '1' then
        AArch32.TakeMonitorTrapException();AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDASDCR.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);AArch32.TakeMonitorTrapException();
    else
        return DBGDSCRint;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDSCRint;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDSCRint;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return DBGDSCRint;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDTRRXext, Debug OS Lock Data Transfer Register, Receive, External View

The DBGDTRRXext characteristics are:

Purpose

Used for save/restore of DBGDTRRXint. It is a component of the Debug Communications Channel.

Configuration

AArch32 System register DBGDTRRXext bits [31:0] are architecturally mapped to AArch64 System register OSDTRRX_EL1[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to DBGDTRRXext arearchitecturally UNKNOWN.values.

Attributes

DBGDTRRXext is a 32-bit register.

Field descriptions

The DBGDTRRXext bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Update DTRRX without side-effect																															

Bits [31:0]

Update DTRRX without side-effect.

Writes to this register update the value in DTRRX and do not change RXfull.

Reads of this register return the last value written to DTRRX and do not change RXfull.

For the full behavior of the Debug Communications Channel, see 'The Debug Communication Channel and Instruction Transfer Register' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter H4.

This field resets to an architecturally UNKNOWN value.

Accessing the DBGDTRRXext

Arm deprecates reads and writes of DBGDTRRXext through the System register interface when the OS Lock is unlocked, DBGOSLSR.OSLK == 0.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDTRRXext;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDTRRXext;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return DBGDTRRXext;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGDTRRXext = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGDTRRXext = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    else
        DBGDTRRXext = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDTRRXint, Debug Data Transfer Register, Receive

The DBGDTRRXint characteristics are:

Purpose

Transfers data from an external debugger to the PE. For example, it is used by a debugger transferring commands and data to a debug target. See Arch64-DBGDTR_EL0 for additional architectural mappings. It is a component of the Debug Communications Channel.

Configuration

AArch32 System register DBGDTRRXint bits [31:0] are architecturally mapped to AArch64 System register DBGDTRRX_EL0[31:0] .

AArch32 System register DBGDTRRXint bits [31:0] are architecturally mapped to External register DBGDTRRX_EL0[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to DBGDTRRXint arearchitecturally UNKNOWN.values.

Attributes

DBGDTRRXint is a 32-bit register.

Field descriptions

The DBGDTRRXint bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Update DTRRX																															

Bits [31:0]

Update DTRRX.

Reads of this register:

- If RXfull is set to 1, return the last value written to DTRRX.
- If RXfull is set to 0, return an UNKNOWN value.

After the read, RXfull is cleared to 0.

For the full behavior of the Debug Communications Channel, see The Debug Communication Channel and Instruction Transfer Register.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the DBGDTRRXint

Data can be stored to memory from this register using STC.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0101	0b000

```
if Halted() then
    return DBGDTRRXint;
elsif PSTATE.EL == EL0 then
    if !Halted() && !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x05);
    elsif !Halted() && ELUsingAArch32(EL1) && DBGDSCRext.UDCCdis == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif !Halted() && EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' ||
MDCR_EL2.<TDE,TDA> != '00') then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && (HCR.TGE == '1' || HDCR.<TDE,TDA>
!= '00') then
        AArch32.TakeHypTrapException(0x05);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && SDCR.TDCCMDCR_EL3.TDA == '1' then
        AArch32.TakeMonitorTrapException();AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDASDCR.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);AArch32.TakeMonitorTrapException();
    else
        return DBGDTRRXint;
elsif PSTATE.EL == EL1 then
    if !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif !Halted() && EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif !Halted() && EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif !Halted() && HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDTRRXint;
elsif PSTATE.EL == EL2 then
    if !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif !Halted() && HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDTRRXint;
elsif PSTATE.EL == EL3 then
    if PSTATE.M!Halted() !=&& M32_MonitorHaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1'
then
        AArch32.TakeMonitorTrapException();
    else
        return DBGDTRRXint;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDTRTXext, Debug OS Lock Data Transfer Register, Transmit

The DBGDTRTXext characteristics are:

Purpose

Used for save/restore of DBGDTRTXint. It is a component of the Debug Communication Channel.

Configuration

AArch32 System register DBGDTRTXext bits [31:0] are architecturally mapped to AArch64 System register OSDTRTX_EL1[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to DBGDTRTXext arearchitecturally UNKNOWN.values.

Attributes

DBGDTRTXext is a 32-bit register.

Field descriptions

The DBGDTRTXext bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Return DTRTX without side-effect																															

Bits [31:0]

Return DTRTX without side-effect.

Reads of this register return the value in DTRTX and do not change TXfull.

Writes of this register update the value in DTRTX and do not change TXfull.

For the full behavior of the Debug Communications Channel, see 'The Debug Communication Channel and Instruction Transfer Register' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter H4.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the DBGDTRTXext

Arm deprecates reads and writes of DBGDTRTXext through the System register interface when the OS Lock is unlocked, DBGOSLSR.OSLK == 0.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0011	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDTRTXext;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGDTRTXext;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return DBGDTRTXext;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0011	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGDTRTXext = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGDTRTXext = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    else
        DBGDTRTXext = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116~~134483bd14dc8c12a99c984cbfe3431cc1c9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDTRTXint, Debug Data Transfer Register, Transmit

The DBGDTRTXint characteristics are:

Purpose

Transfers data from the PE to an external debugger. For example, it is used by a debug target to transfer data to the debugger. See DBGDTR_EL0 for additional architectural mappings. It is a component of the Debug Communication Channel.

Configuration

AArch32 System register DBGDTRTXint bits [31:0] are architecturally mapped to AArch64 System register DBGDTRTX_EL0[31:0] .

AArch32 System register DBGDTRTXint bits [31:0] are architecturally mapped to External register DBGDTRTX_EL0[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to DBGDTRTXint arearchitecturally UNKNOWN.values.

Attributes

DBGDTRTXint is a 32-bit register.

Field descriptions

The DBGDTRTXint bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Return DTRTX																															

Bits [31:0]

Return DTRTX.

Writes to this register:

- If TXfull is set to 1, set DTRTX to UNKNOWN.
- If TXfull is set to 0, update the value in DTRTX.

After the write, TXfull is set to 1.

For the full behavior of the Debug Communications Channel, see The Debug Communication Channel and Instruction Transfer Register.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the DBGDTRTXint

Data can be loaded from memory into this register using LDC (immediate) and LDC (literal).

Accesses to this register use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0101	0b000

```
if Halted() then
    DBGDTRTXint = R[t];
elsif PSTATE.EL == EL0 then
    if !Halted() && !ELUsingAArch32(EL1) && MDSCR_EL1.TDCC == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x05);
    elsif !Halted() && ELUsingAArch32(EL1) && DBGDSCRext.UDCCdis == '1' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x05);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif !Halted() && EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && (HCR_EL2.TGE == '1' ||
MDCR_EL2.<TDE,TDA> != '00') then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && (HCR.TGE == '1' || HDCR.<TDE,TDA>
!= '00') then
        AArch32.TakeHypTrapException(0x05);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && SDCR.TDCCMDCR_EL3.TDA == '1' then
        AArch32.TakeMonitorTrapException();AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDASDCR.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);AArch32.TakeMonitorTrapException();
    else
        DBGDTRTXint = R[t];
elsif PSTATE.EL == EL1 then
    if !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif !Halted() && EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TDCC == '1' then
        AArch32.TakeHypTrapException(0x05);
    elsif !Halted() && EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif !Halted() && EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif !Halted() && HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGDTRTXint = R[t];
elsif PSTATE.EL == EL2 then
    if !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDCC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif !Halted() && HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1' then
        AArch32.TakeMonitorTrapException();
    elsif !Halted() && HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGDTRTXint = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M!Halted() !=&& M32_MonitorHaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TDCC == '1'
then
        AArch32.TakeMonitorTrapException();
    else
        DBGDTRTXint = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGOSDLR, Debug OS Double Lock Register

The DBGOSDLR characteristics are:

Purpose

Locks out the external debug interface.

Configuration

AArch32 System register DBGOSDLR bits [31:0] are architecturally mapped to AArch64 System register OSDLR_EL1[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to DBGOSDLR arearchitecturally UNKNOWN.values.

Attributes

DBGOSDLR is a 32-bit register.

Field descriptions

The DBGOSDLR bit assignments are:



Bits [31:1]

Reserved, RES0.

DLK, bit [0]

When ARMv8.0-DoubleLock is implemented:

OS Double Lock control bit.

DLK	Meaning
0b0	OS Double Lock unlocked.
0b1	OS Double Lock locked, if DBGPRCR.CORENPDRQ (Core no powerdown request) bit is set to 0 and the PE is in Non-debug state.

On a Warm reset, this field resets to 0.

Otherwise:

Reserved, RAZ/WI.

Accessing the DBGOSDLR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0001	0b0011	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDOSA> != '00' &&
(IsFeatureImplemented("ARMv8.0-DoubleLock") || boolean IMPLEMENTATION_DEFINED "Trapped by
MDCR_EL2.TDOSA") then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDOSA> != '00' &&
(IsFeatureImplemented("ARMv8.0-DoubleLock") || boolean IMPLEMENTATION_DEFINED "Trapped by
HDCR.TDOSA") then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' &&
(IsFeatureImplemented("ARMv8.0-DoubleLock") || boolean IMPLEMENTATION_DEFINED "Trapped by
MDCR_EL3.TDOSA") then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGOSDLR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' &&
(IsFeatureImplemented("ARMv8.0-DoubleLock") || boolean IMPLEMENTATION_DEFINED "Trapped by
MDCR_EL3.TDOSA") then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGOSDLR;
elsif PSTATE.EL == EL3 then
    return DBGOSDLR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0001	0b0011	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDOSA> != '00' &&
(IsFeatureImplemented("ARMv8.0-DoubleLock") || boolean IMPLEMENTATION_DEFINED "Trapped by
MDCR_EL2.TDOSA") then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDOSA> != '00' &&
(IsFeatureImplemented("ARMv8.0-DoubleLock") || boolean IMPLEMENTATION_DEFINED "Trapped by
HDCR.TDOSA") then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' &&
(IsFeatureImplemented("ARMv8.0-DoubleLock") || boolean IMPLEMENTATION_DEFINED "Trapped by
MDCR_EL3.TDOSA") then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGOSDLR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' &&
(IsFeatureImplemented("ARMv8.0-DoubleLock") || boolean IMPLEMENTATION_DEFINED "Trapped by
MDCR_EL3.TDOSA") then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGOSDLR = R[t];
elsif PSTATE.EL == EL3 then
    DBGOSDLR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGOSECCR, Debug OS Lock Exception Catch Control Register

The DBGOSECCR characteristics are:

Purpose

Provides a mechanism for an operating system to access the contents of EDECCR that are otherwise invisible to software, so it can save/restore the contents of EDECCR over powerdown on behalf of the external debugger.

Configuration

AArch32 System register DBGOSECCR bits [31:0] are architecturally mapped to AArch64 System register OSECCR_EL1[31:0] .

AArch32 System register DBGOSECCR bits [31:0] are architecturally mapped to External register EDECCR[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGOSECCR are UNKNOWN.

If DBGOSLSR.OSLK == 0 then DBGOSECCR returns an UNKNOWN value on reads and ignores writes.

Attributes

DBGOSECCR is a 32-bit register.

Field descriptions

The DBGOSECCR bit assignments are:

When DBGOSLSR.OSLK == 1:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
EDECCR																															

EDECCR, bits [31:0]

Used for save/restore to EDECCR over powerdown.

Reads or writes to this field are indirect accesses to EDECCR.

Accessing the DBGOSECCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0110	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGOSECCR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGOSECCR;
elsif PSTATE.EL == EL3 then
    return DBGOSECCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0110	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGOSECCR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGOSECCR = R[t];
elsif PSTATE.EL == EL3 then
    DBGOSECCR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGOSLAR, Debug OS Lock Access Register

The DBGOSLAR characteristics are:

Purpose

Provides a lock for the debug registers. The OS Lock also disables some debug exceptions and debug events.

Configuration

AArch32 System register DBGOSLAR bits [31:0] are architecturally mapped to AArch64 System register OSLAR_EL1[31:0] .

AArch32 System register DBGOSLAR bits [31:0] are architecturally mapped to External register OSLAR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGOSLAR are UNKNOWN.

Attributes

DBGOSLAR is a 32-bit register.

Field descriptions

The DBGOSLAR bit assignments are:



OSLAOS Lock Access, bits [31:0]

OS Lock Access. Writing the value `0xC5ACCE55` to the DBGOSLAR sets the OS lock to 1. Writing any other value sets the OS lock to 0.

Use DBGOSLSR.OSLK to check the current status of the lock.

Accessing the DBGOSLAR

Accesses to this register use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0001	0b0000	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDOSA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDOSA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGOSLAR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGOSLAR = R[t];
elsif PSTATE.EL == EL3 then
    DBGOSLAR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGOSLSR, Debug OS Lock Status Register

The DBGOSLSR characteristics are:

Purpose

Provides status information for the OS Lock.

Configuration

AArch32 System register DBGOSLSR bits [31:0] are architecturally mapped to AArch64 System register OSLSR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGOSLSR are UNKNOWN.

The OS Lock status is also visible in the external debug interface through EDPRSR.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGOSLSR is a 32-bit register.

Field descriptions

The DBGOSLSR bit assignments are:



Bits [31:4]

Reserved, RES0.

OSLM[1], bit [3]

This field is bit[1] of OSLM[1:0].

OS lock model implemented. Identifies the form of OS save and restore mechanism implemented.

OSLM	Meaning
0b00	OS Lock not implemented.
0b10	OS Lock implemented.

All other values are reserved. In an Armv8 implementation the value 0b00 is not permitted.

The OSLM field is split as follows:

- OSLM[1] is DBGOSLSR[3].
- OSLM[0] is DBGOSLSR[0].

nTT, bit [2]

Not 32-bit access. This bit is always RAZ. It indicates that a 32-bit access is needed to write the key to the OS Lock Access Register.

OSLK, bit [1]

OS Lock Status. The possible values are:

OSLK	Meaning
0b0	OS Lock unlocked.
0b1	OS Lock locked.

The OS Lock is locked and unlocked by writing to the OS Lock Access Register.

The following resets apply:

- On a Cold reset, this field resets to 1.
- On a Warm reset, the value of this field is unchanged.

OSLM[0], bit [0]

This field is bit[0] of OSLM[1:0].

See OSLM[1] for the field description.

Accessing the DBGOSLSR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0001	0b0001	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDOSA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDOSA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGOSLSR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGOSLSR;
elsif PSTATE.EL == EL3 then
    return DBGOSLSR;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGPRCR, Debug Power Control Register

The DBGPRCR characteristics are:

Purpose

Controls behavior of the PE on powerdown request.

Configuration

AArch32 System register DBGPRCR bits [31:0] are architecturally mapped to AArch64 System register DBGPRCR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGPRCR are UNKNOWN.

Bit [0] of this register is mapped to EDPRCR.CORENPDRQ, bit [0] of the external view of this register.

The other bits in these registers are not mapped to each other.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGPRCR is a 32-bit register.

Field descriptions

The DBGPRCR bit assignments are:



Bits [31:1]

Reserved, RES0.

CORENPDRQ, bit [0]

When ARMv8.3-DoPD is implemented:

Core no powerdown request. Requests emulation of powerdown.

This request is typically passed to an external power controller. This means that whether a request causes power up is dependent on the IMPLEMENTATION DEFINED nature of the system. The power controller must not allow the Core power domain to switch off while this bit is 1.

CORENPDRQ	Meaning
0b0	If the system responds to a powerdown request, it powers down Core power domain.
0b1	If the system responds to a powerdown request, it does not powerdown the Core power domain, but instead emulates a powerdown of that domain.

In an implementation that includes the recommended external debug interface, this bit drives the DBGNOPWRDWN signal.

It is IMPLEMENTATION DEFINED whether this bit is reset to the Cold reset value on exit from an IMPLEMENTATION DEFINED software-visible retention state. For more information about retention states see Core power domain power states.

Note

Writes to this bit are not prohibited by the IMPLEMENTATION DEFINED authentication interface. This means that a debugger can request emulation of powerdown regardless of whether invasive debug is permitted.

The following resets apply:

- On a Cold reset, this field is set to 1 if the powerup request is implemented and the powerup request has been asserted, and is set to 0 otherwise.
- On a Warm reset, the value of this field is unchanged.

Otherwise:

Core no powerdown request. Requests emulation of powerdown.

This request is typically passed to an external power controller. This means that whether a request causes power up is dependent on the IMPLEMENTATION DEFINED nature of the system. The power controller must not allow the Core power domain to switch off while this bit is 1.

CORENPDRQ	Meaning
0b0	If the system responds to a powerdown request, it powers down Core power domain.
0b1	If the system responds to a powerdown request, it does not powerdown the Core power domain, but instead emulates a powerdown of that domain.

In an implementation that includes the recommended external debug interface, this bit drives the DBGNOPWRDWN signal.

It is IMPLEMENTATION DEFINED whether this bit is reset to the value of EDPRCR.COREPURQ on exit from an IMPLEMENTATION DEFINED software-visible retention state. For more information about retention states see Core power domain power states.

Note

Writes to this bit are not prohibited by the IMPLEMENTATION DEFINED authentication interface. This means that a debugger can request emulation of powerdown regardless of whether invasive debug is permitted.

The following resets apply:

- On a Cold reset, this field resets to the value in EDPRCR.COREPURQ.
- On a Warm reset, the value of this field is unchanged.

Accessing the DBGPRCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0001	0b0100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDOSA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDOSA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGPRCR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGPRCR;
elsif PSTATE.EL == EL3 then
    return DBGPRCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0001	0b0100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDOSA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDOSA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGPRCR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDOSA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGPRCR = R[t];
elsif PSTATE.EL == EL3 then
    DBGPRCR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGVCR, Debug Vector Catch Register

The DBGVCR characteristics are:

Purpose

Controls Vector Catch debug events.

Configuration

AArch32 System register DBGVCR bits [31:0] are architecturally mapped to AArch64 System register DBGVCR32_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGVCR are UNKNOWN.

This register is required in all implementations.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGVCR is a 32-bit register.

Field descriptions

The DBGVCR bit assignments are:

When ~~HaveEL(~~EL3~~)~~ is implemented and ~~ELUsingAArch32(~~EL3 is using AArch32:~~):~~

31	30	29	28	27	26	25	24 23 22 21 20 19 18 17 16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
NSF	NSI	RES0	NSD	NSP	NSS	NSU	RES0	MF	MI	RES0	MD	MP	MS	RES0		SF	SI	RES0		SD	SP	SS	SU	RES0	

NSF, bit [31]

FIQ vector catch enable in Non-secure state.

The exception vector offset is `0x1C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSI, bit [30]

IRQ vector catch enable in Non-secure state.

The exception vector offset is `0x18`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [29]

Reserved, RES0.

NSD, bit [28]

Data Abort vector catch enable in Non-secure state.

The exception vector offset is `0x10`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSP, bit [27]

Prefetch Abort vector catch enable in Non-secure state.

The exception vector offset is `0x0C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSS, bit [26]

Supervisor Call (SVC) vector catch enable in Non-secure state.

The exception vector offset is `0x08`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSU, bit [25]

Undefined Instruction vector catch enable in Non-secure state.

The exception vector offset is `0x04`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bits [24:16]

Reserved, RES0.

MF, bit [15]

FIQ vector catch enable in Monitor mode.

The exception vector offset is `0x1C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

MI, bit [14]

IRQ vector catch enable in Monitor mode.

The exception vector offset is `0x18`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [13]

Reserved, RES0.

MD, bit [12]

Data Abort vector catch enable in Monitor mode.

The exception vector offset is `0x10`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

MP, bit [11]

Prefetch Abort vector catch enable in Monitor mode.

The exception vector offset is `0x0C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

MS, bit [10]

Secure Monitor Call (SMC) vector catch enable in Monitor mode.

The exception vector offset is `0x08`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bits [9:8]

Reserved, RES0.

SF, bit [7]

FIQ vector catch enable in Secure state.

The exception vector offset is `0x1C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SI, bit [6]

IRQ vector catch enable in Secure state.

The exception vector offset is `0x18`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [5]

Reserved, RES0.

SD, bit [4]

Data Abort vector catch enable in Secure state.

The exception vector offset is `0x10`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SP, bit [3]

Prefetch Abort vector catch enable in Secure state.

The exception vector offset is `0x0C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SS, bit [2]

Supervisor Call (SVC) vector catch enable in Secure state.

The exception vector offset is `0x08`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SU, bit [1]

Undefined Instruction vector catch enable in Secure state.

The exception vector offset is `0x04`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [0]

Reserved, RES0.

When ~~HaveEL(~~EL3~~)~~ is implemented and ~~!ELUsingAArch32(~~EL3 is using AArch64:~~):~~



NSF, bit [31]

FIQ vector catch enable in Non-secure state.

The exception vector offset is `0x1C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSI, bit [30]

IRQ vector catch enable in Non-secure state.

The exception vector offset is `0x18`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [29]

Reserved, RES0.

NSD, bit [28]

Data Abort vector catch enable in Non-secure state.

The exception vector offset is `0x10`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSP, bit [27]

Prefetch Abort vector catch enable in Non-secure state.

The exception vector offset is `0x0C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSS, bit [26]

Supervisor Call (SVC) vector catch enable in Non-secure state.

The exception vector offset is `0x08`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSU, bit [25]

Undefined Instruction vector catch enable in Non-secure state.

The exception vector offset is `0x04`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bits [24:8]

Reserved, RES0.

SF, bit [7]

FIQ vector catch enable in Secure state.

The exception vector offset is `0x1C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SI, bit [6]

IRQ vector catch enable in Secure state.

The exception vector offset is `0x18`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [5]

Reserved, RES0.

SD, bit [4]

Data Abort vector catch enable in Secure state.

The exception vector offset is `0x10`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SP, bit [3]

Prefetch Abort vector catch enable in Secure state.

The exception vector offset is `0x0C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SS, bit [2]

Supervisor Call (SVC) vector catch enable in Secure state.

The exception vector offset is `0x08`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

SU, bit [1]

Undefined Instruction vector catch enable in Secure state.

The exception vector offset is `0x04`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [0]

Reserved, RES0.

When ~~!HaveEL(~~EL3 is not implemented~~):~~



Bits [31:8]

Reserved, RES0.

F, bit [7]

FIQ vector catch enable.

The exception vector offset is `0x1C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

I, bit [6]

IRQ vector catch enable.

The exception vector offset is `0x18`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [5]

Reserved, RES0.

D, bit [4]

Data Abort vector catch enable.

The exception vector offset is `0x10`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P, bit [3]

Prefetch Abort vector catch enable.

The exception vector offset `0x0C`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

S, bit [2]

Supervisor Call (SVC) vector catch enable.

The exception vector offset is `0x08`.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

U, bit [1]

Undefined Instruction vector catch enable.

The exception vector offset is 0x04.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bit [0]

Reserved, RES0.

Accessing the DBGVCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0111	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGVCR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGVCR;
elsif PSTATE.EL == EL3 then
    return DBGVCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0111	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGVCR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGVCR = R[t];
elsif PSTATE.EL == EL3 then
    DBGVCR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGWCR<n>, Debug Watchpoint Control Registers, n = 0 - 15

The DBGWCR<n> characteristics are:

Purpose

Holds control information for a watchpoint. Forms watchpoint n together with value register DBGWVR<n>.

Configuration

AArch32 System register DBGWCR<n> bits [31:0] are architecturally mapped to AArch64 System register DBGWCR<n>_EL1[31:0] .

AArch32 System register DBGWCR<n> bits [31:0] are architecturally mapped to External register DBGWCR<n>_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGWCR<n> are UNKNOWN.

If watchpoint n is not implemented then accesses to this register are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGWCR<n> is a 32-bit register.

Field descriptions

The DBGWCR<n> bit assignments are:

31 30 29	28 27 26 25 24	23 22 21	20	19 18 17 16	15 14	13	12 11 10 9 8 7 6 5	4 3	2 1	0
RES0	MASK	RES0	WT	LBN	SSC	HMC	BAS	LSC	PAC	E

When the E field is zero, all the other fields in the register are ignored.

Bits [31:29]

Reserved, RES0.

MASK, bits [28:24]

Address mask. Only objects up to 2GB can be watched using a single mask.

MASK	Meaning
0b00000	No mask.
0b00001	Reserved.
0b00010	Reserved.

If programmed with a reserved value, a watchpoint must behave as if either:

- MASK has been programmed with a defined value, which might be 0 (no mask), other than for a direct read of DBGWCRn_EL1.
- The watchpoint is disabled.

Software must not rely on this property because the behavior of reserved values might change in a future revision of the architecture.

Other values mask the corresponding number of address bits, from `0b00011` masking 3 address bits (`0x00000007` mask for address) to `0b11111` masking 31 address bits (`0x7FFFFFFF` mask for address).

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Bits [23:21]

Reserved, RES0.

WT, bit [20]

Watchpoint type. Possible values are:

WT	Meaning
`0b0`	Unlinked data address match.
`0b1`	Linked data address match.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

LBN, bits [19:16]

Linked breakpoint number. For Linked data address watchpoints, this specifies the index of the Context-matching breakpoint linked to.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

SSC, bits [15:14]

Security state control. Determines the Security states under which a Watchpoint debug event for watchpoint n is generated. This field must be interpreted along with the HMC and PAC fields.

For more information, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, and 'Reserved DBGBCR<n>.{SSC, HMC, PMC} values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

HMC, bit [13]

Higher mode control. Determines the debug perspective for deciding when a Watchpoint debug event for watchpoint n is generated. This field must be interpreted along with the SSC and PAC fields.

For more information on the operation of the SSC, HMC, and PAC fields, see 'Execution conditions for which a watchpoint generates Watchpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

BAS, bits [12:5]

Byte address select. Each bit of this field selects whether a byte from within the word or double-word addressed by DBGWVR<n> is being watched.

BAS	Description
0bxxxxxxx1	Match byte at DBGWVR<n>
0bxxxxxx1x	Match byte at DBGWVR<n>+1
0bxxxxx1xx	Match byte at DBGWVR<n>+2
0bxxxx1xxx	Match byte at DBGWVR<n>+3

In cases where DBGWVR<n> addresses a double-word:

BAS	Description, if DBGWVR<n>[2] == 0
0bxxx1xxxx	Match byte at DBGWVR<n>+4
0bxx1xxxxx	Match byte at DBGWVR<n>+5
0bx1xxxxxx	Match byte at DBGWVR<n>+6
0b1xxxxxxx	Match byte at DBGWVR<n>+7

If DBGWVR<n>[2] == 1, only BAS[3:0] are used and BAS[7:4] are ignored. Arm deprecates setting DBGWVR<n>[2] == 1.

The valid values for BAS are non-zero binary numbers all of whose set bits are contiguous. All other values are reserved and must not be used by software. See 'Reserved DBGWCR<n>.BAS values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug)

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

LSC, bits [4:3]

Load/store control. This field enables watchpoint matching on the type of access being made. Possible values of this field are:

LSC	Meaning
0b01	Match instructions that load from a watchpointed address.
0b10	Match instructions that store to a watchpointed address.
0b11	Match instructions that load from or store to a watchpointed address.

All other values are reserved, but must behave as if the watchpoint is disabled. Software must not rely on this property as the behavior of reserved values might change in a future revision of the architecture.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

PAC, bits [2:1]

Privilege of access control. Determines the Exception level or levels at which a Watchpoint debug event for watchpoint n is generated. This field must be interpreted along with the SSC and HMC fields.

For more information on the operation of the SSC, HMC, and PAC fields, see 'Execution conditions for which a watchpoint generates Watchpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.

- On a Warm reset, the value of this field is unchanged.

E, bit [0]

Enable watchpoint n. Possible values are:

E	Meaning
0b0	Watchpoint disabled.
0b1	Watchpoint enabled.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Accessing the DBGWCR<n>

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	n[3:0]	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGWCR[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGWCR[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL3 then
    if ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGWCR[UInt(CRm<3:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	n[3:0]	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGWCR[UInt(CRm<3:0>)] = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGWCR[UInt(CRm<3:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGWCR[UInt(CRm<3:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGWFAR, Debug Watchpoint Fault Address Register

The DBGWFAR characteristics are:

Purpose

Previously returned information about the address of the instruction that accessed a watchpointed address. Is now deprecated and RES0.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGWFAR are UNKNOWN.

Attributes

DBGWFAR is a 32-bit register.

Field descriptions

The DBGWFAR bit assignments are:



Bits [31:0]

Reserved, RES0.

Accessing the DBGWFAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGWFAR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        return DBGWFAR;
elsif PSTATE.EL == EL3 then
    return DBGWFAR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGWFAR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    else
        DBGWFAR = R[t];
elsif PSTATE.EL == EL3 then
    DBGWFAR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGWVR<n>, Debug Watchpoint Value Registers, n = 0 - 15

The DBGWVR<n> characteristics are:

Purpose

Holds a data address value for use in watchpoint matching. Forms watchpoint n together with control register DBGWCR<n>.

Configuration

AArch32 System register DBGWVR<n> bits [31:0] are architecturally mapped to AArch64 System register DBGWVR<n>_EL1[31:0] .

AArch32 System register DBGWVR<n> bits [31:0] are architecturally mapped to External register DBGWVR<n>_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DBGWVR<n> are UNKNOWN.

If watchpoint n is not implemented then accesses to this register are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DBGWVR<n> is a 32-bit register.

Field descriptions

The DBGWVR<n> bit assignments are:



VA, bits [31:2]

Bits[31:2] of the address value for comparison.

Arm deprecates setting DBGWVR<n>[2] == 1.

The following resets apply:

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On a Warm reset, the value of this field is unchanged.

Bits [1:0]

Reserved, RES0.

Accessing the DBGWVR<n>

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	n[3:0]	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGWVR[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGWVR[UInt(CRm<3:0>)];
elsif PSTATE.EL == EL3 then
    if ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        return DBGWVR[UInt(CRm<3:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b000	0b0000	n[3:0]	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.<TDE,TDA> != '00' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.<TDE,TDA> != '00' then
        AArch32.TakeHypTrapException(0x05);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGWVR[UInt(CRm<3:0>)] = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x05);
    elsif ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGWVR[UInt(CRm<3:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ELUsingAArch32(EL1) && DBGOSLSR.OSLK == '0' && HaltingAllowed() && EDSCR.TDA == '1' then
        Halt(DebugHalt_SoftwareAccess);
    else
        DBGWVR[UInt(CRm<3:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DCCIMVAC, Data Cache line Clean and Invalidate by VA to PoC

The DCCIMVAC characteristics are:

Purpose

Clean and Invalidate data or unified cache line by virtual address to PoC.

Configuration

AArch32 System instruction DCCIMVAC performs the same function as AArch64 System instruction DC CIVAC.

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DCCIMVAC are UNKNOWN.

Attributes

DCCIMVAC is a 32-bit System instruction.

Field descriptions

The DCCIMVAC input value bit assignments are:



Bits [31:0]

Virtual address to use. No alignment restrictions apply to this VA.

Executing the DCCIMVAC instruction

Execution of this instruction might require an address translation from VA to PA, and that translation might fault. For more information, see 'AArch32 data cache maintenance instruction (DC*)' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1110	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TPCP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TPC == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        DCCIMVAC(R[t]);
elsif PSTATE.EL == EL2 then
    DCCIMVAC(R[t]);
elsif PSTATE.EL == EL3 then
    DCCIMVAC(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DCCISW, Data Cache line Clean and Invalidate by Set/Way

The DCCISW characteristics are:

Purpose

Clean and Invalidate data or unified cache line by set/way.

Configuration

AArch32 System instruction DCCISW performs the same function as AArch64 System instruction DC CISW.

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DCCISW are UNKNOWN.

Attributes

DCCISW is a 32-bit System instruction.

Field descriptions

The DCCISW input value bit assignments are:



SetWay, bits [31:4]

Contains two fields:

- Way, bits[31:32-A], the number of the way to operate on.
- Set, bits[B-1:L], the number of the set to operate on.

Bits[L-1:4] are RES0.

A = Log_2(ASSOCIATIVITY), L = Log_2(LINELEN), B = (L + S), S = Log_2(NSETS).

ASSOCIATIVITY, LINELEN (line length, in bytes), and NSETS (number of sets) have their usual meanings and are the values for the cache level being operated on. The values of A and S are rounded up to the next integer.

Level, bits [3:1]

Cache level to operate on, minus 1. For example, this field is 0 for operations on L1 cache, or 1 for operations on L2 cache.

Bit [0]

Reserved, RES0.

Executing the DCCISW instruction

If this instruction is executed with a set, way or level argument that is larger than the value supported by the implementation then the behavior is CONSTRAINED UNPREDICTABLE and one of the following occurs:

- The instruction is UNDEFINED
- The instruction performs cache maintenance on one of:
    - No cache lines.
    - A single arbitrary cache line.
    - Multiple arbitrary cache lines.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1110	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TSW == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TSW == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        DCCISW(R[t]);
elsif PSTATE.EL == EL2 then
    DCCISW(R[t]);
elsif PSTATE.EL == EL3 then
    DCCISW(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DCCMVAC, Data Cache line Clean by VA to PoC

The DCCMVAC characteristics are:

Purpose

Clean data or unified cache line by virtual address to PoC.

Configuration

AArch32 System instruction DCCMVAC performs the same function as AArch64 System instruction DC CVAC.

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DCCMVAC are UNKNOWN.

Attributes

DCCMVAC is a 32-bit System instruction.

Field descriptions

The DCCMVAC input value bit assignments are:



Bits [31:0]

Virtual address to use. No alignment restrictions apply to this VA.

Executing the DCCMVAC instruction

Execution of this instruction might require an address translation from VA to PA, and that translation might fault. For more information, see 'AArch32 data cache maintenance instruction (DC*)' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TPCP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TPC == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        DCCMVAC(R[t]);
elsif PSTATE.EL == EL2 then
    DCCMVAC(R[t]);
elsif PSTATE.EL == EL3 then
    DCCMVAC(R[t]);
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DCCMVAU, Data Cache line Clean by VA to PoU

The DCCMVAU characteristics are:

Purpose

Clean data or unified cache line by virtual address to PoU.

Configuration

AArch32 System instruction DCCMVAU performs the same function as AArch64 System instruction DC CVAU.

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DCCMVAU are UNKNOWN.

Attributes

DCCMVAU is a 32-bit System instruction.

Field descriptions

The DCCMVAU input value bit assignments are:



Bits [31:0]

Virtual address to use. No alignment restrictions apply to this VA.

Executing the DCCMVAU instruction

Execution of this instruction might require an address translation from VA to PA, and that translation might fault. For more information, see 'AArch32 data cache maintenance instruction (DC*)' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TPU == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TOCU == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TPU == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TOCU == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        DCCMVAU(R[t]);
elsif PSTATE.EL == EL2 then
    DCCMVAU(R[t]);
elsif PSTATE.EL == EL3 then
    DCCMVAU(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DCCSW, Data Cache line Clean by Set/Way

The DCCSW characteristics are:

Purpose

Clean data or unified cache line by set/way.

Configuration

AArch32 System instruction DCCSW performs the same function as AArch64 System instruction DC CSW.

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DCCSW are UNKNOWN.

Attributes

DCCSW is a 32-bit System instruction.

Field descriptions

The DCCSW input value bit assignments are:



SetWay, bits [31:4]

Contains two fields:

- Way, bits[31:32-A], the number of the way to operate on.
- Set, bits[B-1:L], the number of the set to operate on.

Bits[L-1:4] are RES0.

A = Log_2(ASSOCIATIVITY), L = Log_2(LINELEN), B = (L + S), S = Log_2(NSETS).

ASSOCIATIVITY, LINELEN (line length, in bytes), and NSETS (number of sets) have their usual meanings and are the values for the cache level being operated on. The values of A and S are rounded up to the next integer.

Level, bits [3:1]

Cache level to operate on, minus 1. For example, this field is 0 for operations on L1 cache, or 1 for operations on L2 cache.

Bit [0]

Reserved, RES0.

Executing the DCCSW instruction

If this instruction is executed with a set, way or level argument that is larger than the value supported by the implementation then the behavior is CONSTRAINED UNPREDICTABLE and one of the following occurs:

- The instruction is UNDEFINED

- The instruction performs cache maintenance on one of:
    - No cache lines.
    - A single arbitrary cache line.
    - Multiple arbitrary cache lines.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b1010	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TSW == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TSW == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        DCCISW(R[t]);
elsif PSTATE.EL == EL2 then
    DCCISW(R[t]);
elsif PSTATE.EL == EL3 then
    DCCISW(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DCIMVAC, Data Cache line Invalidate by VA to PoC

The DCIMVAC characteristics are:

Purpose

Invalidate data or unified cache line by virtual address to PoC.

Configuration

AArch32 System instruction DCIMVAC performs the same function as AArch64 System instruction DC IVAC.

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DCIMVAC are UNKNOWN.

Attributes

DCIMVAC is a 32-bit System instruction.

Field descriptions

The DCIMVAC input value bit assignments are:



Bits [31:0]

Virtual address to use. No alignment restrictions apply to this VA.

Executing the DCIMVAC instruction

It is IMPLEMENTATION DEFINED whether, when this instruction is executed, it can generate a watchpoint. If this instruction can generate a watchpoint this is prioritized in the same way as other watchpoints.

Execution of this instruction might require an address translation from VA to PA, and that translation might fault. For more information, see 'AArch32 data cache maintenance instruction (DC*)' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0110	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TPCP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TPC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<DC,VM> != '00' then
        DCCIMVAC(R[t]);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.<DC,VM> != '00' then
        DCCIMVAC(R[t]);
    else
        DCIMVAC(R[t]);
elsif PSTATE.EL == EL2 then
    DCIMVAC(R[t]);
elsif PSTATE.EL == EL3 then
    DCIMVAC(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DCISW, Data Cache line Invalidate by Set/Way

The DCISW characteristics are:

Purpose

Invalidate data or unified cache line by set/way.

Configuration

AArch32 System instruction DCISW performs the same function as AArch64 System instruction DC ISW.

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DCISW are UNKNOWN.

Attributes

DCISW is a 32-bit System instruction.

Field descriptions

The DCISW input value bit assignments are:



SetWay, bits [31:4]

Contains two fields:

- Way, bits[31:32-A], the number of the way to operate on.
- Set, bits[B-1:L], the number of the set to operate on.

Bits[L-1:4] are RES0.

A = Log_2(ASSOCIATIVITY), L = Log_2(LINELEN), B = (L + S), S = Log_2(NSETS).

ASSOCIATIVITY, LINELEN (line length, in bytes), and NSETS (number of sets) have their usual meanings and are the values for the cache level being operated on. The values of A and S are rounded up to the next integer.

Level, bits [3:1]

Cache level to operate on, minus 1. For example, this field is 0 for operations on L1 cache, or 1 for operations on L2 cache.

Bit [0]

Reserved, RES0.

Executing the DCISW instruction

If this instruction is executed with a set, way or level argument that is larger than the value supported by the implementation then the behavior is CONSTRAINED UNPREDICTABLE and one of the following occurs:

- The instruction is UNDEFINED

- The instruction performs cache maintenance on one of:
    - No cache lines.
    - A single arbitrary cache line.
    - Multiple arbitrary cache lines.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0110	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TSW == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TSW == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.SWIO == '1' then
        DCCISW(R[t]);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<DC,VM> != '00' then
        DCCISW(R[t]);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.SWIO == '1' then
        DCCISW(R[t]);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.<DC,VM> != '00' then
        DCCISW(R[t]);
    else
        DCISW(R[t]);
elsif PSTATE.EL == EL2 then
    DCISW(R[t]);
elsif PSTATE.EL == EL3 then
    DCISW(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DFAR, Data Fault Address Register

The DFAR characteristics are:

Purpose

Holds the virtual address of the faulting address that caused a synchronous Data Abort exception.

Configuration

AArch32 System register DFAR bits [31:0] are architecturally mapped to AArch64 System register FAR_EL1[31:0] .

AArch32 System register DFAR bits [31:0] (S) are architecturally mapped to AArch32 System register HDFAR[31:0] when HaveEL(EL2), is implemented, HaveEL(EL3) is implemented and the highest implemented Exception level is using AArch32 state.HighestELUsingAArch32().

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to DFAR arearchitecturally UNKNOWN.values.

Attributes

DFAR is a 32-bit register.

Field descriptions

The DFAR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
VA of faulting address of synchronous Data Abort exception																															

Bits [31:0]

VA of faulting address of synchronous Data Abort exception.

This field resets to an architecturally UNKNOWN value.

Accessing the DFAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T6 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T6 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return DFAR_S;
        else
            return DFAR_NS;
    else
        return DFAR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return DFAR_NS;
    else
        return DFAR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return DFAR_S;
    else
        return DFAR_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T6 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T6 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            DFAR_S = R[t];
        else
            DFAR_NS = R[t];
    else
        DFAR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        DFAR_NS = R[t];
    else
        DFAR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        DFAR_S = R[t];
    else
        DFAR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DFSR, Data Fault Status Register

The DFSR characteristics are:

Purpose

Holds status information about the last data fault.

Configuration

AArch32 System register DFSR bits [31:0] are architecturally mapped to AArch64 System register ESR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DFSR are UNKNOWN.

The current translation table format determines which format of the register is used.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DFSR is a 32-bit register.

Field descriptions

The DFSR bit assignments are:

When TTBCR.EAE == 0:



Bits [31:17]

Reserved, RES0.

FnV, bit [16]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
0b0	DFAR is valid.
0b1	DFAR is not valid, and holds an UNKNOWN value.

This field is only valid for a synchronous External abort other than a synchronous External abort on a translation table walk. It is RES0 for all other Data Abort exceptions.

This field resets to an architecturally UNKNOWN value.

AET, bits [15:14]

Asynchronous Error Type. When the RAS Extension is implemented, this field describes the state of the PE after taking an asynchronous Data Abort exception. Possible values are:

AET	Meaning
0b00	Uncontainable error (UC) or uncategorized.
0b01	Unrecoverable error (UEU).
0b10	Restartable error (UEO) or Corrected error (CE).
0b11	Recoverable error (UER).

When the RAS Extension is not implemented, or on a synchronous Data Abort, this field is RES0.

Note

Armv8.2 requires the implementation of the RAS Extension.

In the event of multiple errors taken as a single SError interrupt exception, the overall state of the PE is reported.

Note

Software can use this information to determine what recovery might be possible. The recovery software must also examine any implemented fault records to determine the location and extent of the error.

This field resets to an architecturally UNKNOWN value.

CM, bit [13]

Cache maintenance fault. For synchronous faults, this bit indicates whether a cache maintenance instruction generated the fault. The possible values of this bit are:

CM	Meaning
0b0	Abort not caused by execution of a cache maintenance instruction.
0b1	Abort caused by execution of a cache maintenance instruction, or on an address translation.

On a synchronous Data Abort on a translation table walk, this bit is UNKNOWN.

On an asynchronous fault, this bit is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

ExT, bit [12]

External abort type. This bit can be used to provide an IMPLEMENTATION DEFINED classification of External aborts.

In an implementation that does not provide any classification of External aborts, this bit is RES0.

For aborts other than External aborts this bit always returns 0.

This field resets to an architecturally UNKNOWN value.

WnR, bit [11]

Write not Read bit. Indicates whether the abort was caused by a write or a read instruction. The possible values of this bit are:

WnR	Meaning
0b0	Abort caused by a read instruction.
0b1	Abort caused by a write instruction.

For faults on the cache maintenance and address translation System instructions in the (coproc==0b1111) encoding space this bit always returns a value of 1.

This field resets to an architecturally UNKNOWN value.

FS[4], bit [10]

This field is bit[4] of FS[4:0].

Fault status bits. Possible values of FS[4:0] are:

FS	Meaning	Applies when
0b00001	Alignment fault.	
0b00010	Debug exception.	
0b00011	Access flag fault, level 1.	
0b00100	Fault on instruction cache maintenance.	
0b00101	Translation fault, level 1.	
0b00110	Access flag fault, level 2.	
0b00111	Translation fault, level 2.	
0b01000	Synchronous External abort, not on translation table walk.	
0b01001	Domain fault, level 1.	
0b01011	Domain fault, level 2.	
0b01100	Synchronous External abort, on translation table walk, level 1.	
0b01101	Permission fault, level 1.	
0b01110	Synchronous External abort, on translation table walk, level 2.	
0b01111	Permission fault, level 2.	
0b10000	TLB conflict abort.	
0b10100	IMPLEMENTATION DEFINED fault (Lockdown fault).	
0b10101	IMPLEMENTATION DEFINED fault (Unsupported Exclusive access fault).	
0b10110	SError interrupt.	
0b11000	SError interrupt, from a parity or ECC error on memory access.	When RAS is not implemented
0b11001	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b11100	Synchronous parity or ECC error on translation table walk, level 1.	When RAS is not implemented
0b11110	Synchronous parity or ECC error on translation table walk, level 2.	When RAS is not implemented

All other values are reserved.

~~When the RAS Extension is implemented, 0b11000, 0b11001, 0b11100, and 0b11110, are reserved.~~

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults on a Short-descriptor translation table lookup' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The FS field is split as follows:

- FS[4] is DFSR[10].
- FS[3:0] is DFSR[3:0].

This field resets to an architecturally UNKNOWN value.

LPAE, bit [9]

On taking a Data Abort exception, this bit is set as follows:

LPAE	Meaning
0b0	Using the Short-descriptor translation table formats.
0b1	Using the Long-descriptor translation table formats.

Hardware does not interpret this bit to determine the behavior of the memory system, and therefore software can set this bit to 0 or 1 without affecting operation.

This field resets to an architecturally UNKNOWN value.

Bit [8]

Reserved, RES0.

Domain, bits [7:4]

The domain of the fault address.

Arm deprecates any use of this field, see 'The Domain field in the DFSR' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field is UNKNOWN for certain faults where the DFSR is updated and reported using the Short-descriptor FSR encodings, see 'Validity of Domain field on faults that update the DFSR when using the Short-descriptor encodings' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

FS[3:0], bits [3:0]

This field is bits[3:0] of FS[4:0].

See FS[4] for the field description.

When TTBCR.EAE == 1:



Bits [31:17]

Reserved, RES0.

FnV, bit [16]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
0b0	DFAR is valid.
0b1	DFAR is not valid, and holds an UNKNOWN value.

This field is only valid for a synchronous External abort other than a synchronous External abort on a translation table walk. It is RES0 for all other Data Abort exceptions.

This field resets to an architecturally UNKNOWN value.

AET, bits [15:14]

Asynchronous Error Type. When the RAS Extension is implemented, this field describes the state of the PE after taking an asynchronous Data Abort exception. Possible values are:

AET	Meaning
0b00	Uncontainable error (UC) or uncategorized.
0b01	Unrecoverable error (UEU).
0b10	Restartable error (UEO) or Corrected error (CE).
0b11	Recoverable error (UER).

When the RAS Extension is not implemented, or on a synchronous Data Abort, this field is RES0.

Note

Armv8.2 requires the implementation of the RAS Extension.

In the event of multiple errors taken as a single SError interrupt exception, the overall state of the PE is reported.

Note

Software can use this information to determine what recovery might be possible. The recovery software must also examine any implemented fault records to determine the location and extent of the error.

This field resets to an architecturally UNKNOWN value.

CM, bit [13]

Cache maintenance fault. For synchronous faults, this bit indicates whether a cache maintenance instruction generated the fault. The possible values of this bit are:

CM	Meaning
0b0	Abort not caused by execution of a cache maintenance instruction.
0b1	Abort caused by execution of a cache maintenance instruction.

On a synchronous Data Abort on a translation table walk, this bit is UNKNOWN.

On an asynchronous fault, this bit is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

ExT, bit [12]

External abort type. This bit can be used to provide an IMPLEMENTATION DEFINED classification of External aborts.

In an implementation that does not provide any classification of External aborts, this bit is RES0.

For aborts other than External aborts this bit always returns 0.

This field resets to an architecturally UNKNOWN value.

WnR, bit [11]

Write not Read bit. Indicates whether the abort was caused by a write or a read instruction. The possible values of this bit are:

WnR	Meaning
0b0	Abort caused by a read instruction.
0b1	Abort caused by a write instruction.

For faults on the cache maintenance and address translation System instructions in the (coproc==0b1111) encoding space this bit always returns a value of 1.

This field resets to an architecturally UNKNOWN value.

Bit [10]

Reserved, RES0.

LPAE, bit [9]

On taking a Data Abort exception, this bit is set as follows:

LPAE	Meaning
0b0	Using the Short-descriptor translation table formats.
0b1	Using the Long-descriptor translation table formats.

Hardware does not interpret this bit to determine the behavior of the memory system, and therefore software can set this bit to 0 or 1 without affecting operation.

This field resets to an architecturally UNKNOWN value.

Bits [8:6]

Reserved, RES0.

STATUS, bits [5:0]

Fault status bits. Possible values of this field are:

STATUS	Meaning	Applies when
0b000000	Address size fault in translation table base register.TTBR0 or TTBR1.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk.	
0b010001	Asynchronous SError interrupt.	
0b010101	Synchronous External abort, on translation table walk, level 1.	
0b010110	Synchronous External abort, on translation table walk, level 2.	
0b010111	Synchronous External abort, on translation table walk, level 3.	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011001	Asynchronous SError interrupt, from a parity or ECC error on memory access.	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk, level 1.	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk, level 2.	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk, level 3.	When RAS is not implemented
0b100001	Alignment fault.	
0b100010	Debug exception.	
0b110000	TLB conflict abort.	
0b110100	IMPLEMENTATION DEFINED fault (Lockdown fault).	
0b110101	IMPLEMENTATION DEFINED fault (Unsupported Exclusive access fault).	

All other values are reserved.

~~When the RAS Extension is implemented, 0b011000, 0b011001, 0b011101, 0b011110, and 0b011111, are reserved.~~

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults on a Long-descriptor translation table lookup' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the DFSR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return DFSR_S;
        else
            return DFSR_NS;
    else
        return DFSR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return DFSR_NS;
    else
        return DFSR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return DFSR_S;
    else
        return DFSR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            DFSR_S = R[t];
        else
            DFSR_NS = R[t];
    else
        DFSR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        DFSR_NS = R[t];
    else
        DFSR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        DFSR_S = R[t];
    else
        DFSR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DISR, Deferred Interrupt Status Register

The DISR characteristics are:

Purpose

Records that an SError interrupt has been consumed by an ESB instruction.

Configuration

AArch32 System register DISR bits [31:0] are architecturally mapped to AArch64 System register DISR_EL1[31:0] when the highest implemented Exception level is using AArch64.

This register is present only when RAS is implemented. Otherwise, direct accesses to DISR are UNDEFINED.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

DISR is a 32-bit register.

Field descriptions

The DISR bit assignments are:

When the ESB instruction is executed at EL2:



A, bit [31]

Set to 1 when an ESB instruction defers an asynchronous SError interrupt. If the implementation does not include any sources of SError interrupt that can be synchronized by an Error Synchronization Barrier, then this bit is RES0.

This field resets to an architecturally UNKNOWN value.

Bits [30:12]

Reserved, RES0.

AET, bits [11:10]

Asynchronous Error Type. See the description of HSR.AET for an SError interrupt.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

External abort Type. See the description of HSR.EA for an SError interrupt.

This field resets to an architecturally UNKNOWN value.

Bits [8:6]

Reserved, RES0.

DFSC, bits [5:0]

Fault Status Code. See the description of HSR.DFSC for an SError interrupt.

This field resets to an architecturally UNKNOWN value.

When the ESB instruction is executed at EL0 or EL1 and where TTBCR.EAE == 0:



A, bit [31]

Set to 1 when an ESB instruction defers an asynchronous SError interrupt. If the implementation does not include any sources of SError interrupt that can be synchronized by an Error Synchronization Barrier, then this bit is RES0.

This field resets to an architecturally UNKNOWN value.

Bits [30:16]

Reserved, RES0.

AET, bits [15:14]

Asynchronous Error Type. See the description of DFSR.AET for an SError interrupt.

This field resets to an architecturally UNKNOWN value.

Bit [13]

Reserved, RES0.

ExT, bit [12]

External abort Type. See the description of DFSR.ExT for an SError interrupt.

This field resets to an architecturally UNKNOWN value.

Bit [11]

Reserved, RES0.

FS[4], bit [10]

This field is bit[4] of FS[4:0].

Fault Status Code. See the description of DFSR.FS for an SError interrupt.

The FS field is split as follows:

- FS[4] is DISR[10].
- FS[3:0] is DISR[3:0].

This field resets to an architecturally UNKNOWN value.

LPAE, bit [9]

Format.

LPAE	Meaning
0b0	Using the Short-descriptor translation table format.

This field resets to an architecturally UNKNOWN value.

Bits [8:4]

Reserved, RES0.

FS[3:0], bits [3:0]

This field is bits[3:0] of FS[4:0].

See FS[4] for the field description.

When the ESB instruction is executed at EL0 or EL1 and where TTBCR.EAE == 1:



A, bit [31]

Set to 1 when an ESB instruction defers an asynchronous SError interrupt. If the implementation does not include any sources of SError interrupt that can be synchronized by an Error Synchronization Barrier, then this bit is RES0.

This field resets to an architecturally UNKNOWN value.

Bits [30:16]

Reserved, RES0.

AET, bits [15:14]

Asynchronous Error Type. See the description of DFSR.AET for an SError interrupt.

This field resets to an architecturally UNKNOWN value.

Bit [13]

Reserved, RES0.

ExT, bit [12]

External abort Type. See the description of DFSR.ExT for an SError interrupt.

This field resets to an architecturally UNKNOWN value.

Bits [11:10]

Reserved, RES0.

LPAE, bit [9]

Format.

LPAE	Meaning
0b1	Using the Long-descriptor translation table format.

This field resets to an architecturally UNKNOWN value.

Bits [8:6]

Reserved, RES0.

STATUS, bits [5:0]

Fault Status Code. See the description of DFSR.FS~~DFSC~~ for an SError interrupt.

This field resets to an architecturally UNKNOWN value.

Accessing the DISR

An indirect write to DISR made by an ESB instruction does not require an explicit synchronization operation for the value that is written to be observed by a direct read of DISR occurring in program order after the ESB instruction.

DISR is RAZ/WI if EL3 is implemented, the PE is in Non-debug state, and any of the following apply:

- EL3 is using AArch64, SCR_EL3.EA == 1, and any of the following apply:
  - The PE is executing at EL2.
  - The PE is executing at EL1 and ((SCR_EL3.NS == 0 && SCR_EL3.EEL2 == 0) || HCR_EL2.AMO == 0).
- EL3 is using AArch32, SCR.EA == 1, and any of the following apply:
  - The PE is executing at EL2.
  - The PE is executing at EL1 and (SCR.NS == 0 || HCR.AMO == 0).

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.AMO == '1' then
        return VDISR_EL2;
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.AMO == '1' then
        return VDISR;
    else
        return DISR;
elsif PSTATE.EL == EL2 then
    return DISR;
elsif PSTATE.EL == EL3 then
    return DISR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.AMO == '1' then
        VDISR_EL2 = R[t];
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.AMO == '1' then
        VDISR = R[t];
    else
        DISR = R[t];
elsif PSTATE.EL == EL2 then
    DISR = R[t];
elsif PSTATE.EL == EL3 then
    DISR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DLR, Debug Link Register

The DLR characteristics are:

Purpose

In Debug state, holds the address to restart from.

Configuration

AArch32 System register DLR bits [31:0] are architecturally mapped to AArch64 System register DLR_EL0[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DLR are UNKNOWN.

Attributes

DLR is a 32-bit register.

Field descriptions

The DLR bit assignments are:



Bits [31:0]

Restart address.

Accessing the DLR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b011	0b0100	0b0101	0b001

```
if !Halted() then
    UNDEFINED;
else
    return DLR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b011	0b0100	0b0101	0b001

```
if !Halted() then
    UNDEFINED;
else
    DLR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DSPSR, Debug Saved Program Status Register

The DSPSR characteristics are:

Purpose

Holds the saved process state for Debug state. On entering Debug state, PSTATE information is written to this register. On exiting Debug state, values are copied from this register to PSTATE.

Configuration

AArch32 System register DSPSR bits [31:0] are architecturally mapped to AArch64 System register DSPSR_EL0[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to DSPSR arearchitecturally UNKNOWN.values.

Attributes

DSPSR is a 32-bit register.

Field descriptions

The DSPSR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
N	Z	C	V	Q	IT[1:0]		DIT	SSBS	PAN	SS	IL	GE				IT[7:2]						E	A	I	F	T	M[4:0]				

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on entering Debug state, and copied to PSTATE.N on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on entering Debug state, and copied to PSTATE.Z on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on entering Debug state, and copied to PSTATE.C on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on entering Debug state, and copied to PSTATE.V on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on entering Debug state, and copied to PSTATE.Q on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on entering Debug state, and copied to PSTATE.IT[1:0] on exiting Debug state.

On exiting Debug state DSPSR.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

DIT, bit [24]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on entering Debug state, and copied to PSTATE.DIT on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on entering Debug state, and copied to PSTATE.SSBS on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on entering Debug state, and copied to PSTATE.PAN on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SS, bit [21]

Software Step. Set to the value of PSTATE.SS on entering Debug state, and conditionally copied to PSTATE.SS on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on entering Debug state, and copied to PSTATE.IL on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on entering Debug state, and copied to PSTATE.GE on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on entering Debug state, and copied to PSTATE.IT[7:2] on exiting Debug state.

DSPSR.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on entering Debug state, and copied to PSTATE.E on exiting Debug state.

If the implementation does not support big-endian operation, DSPSR.E is RES0. If the implementation does not support little-endian operation, DSPSR.E is RES1. On exiting Debug state, if the implementation does not support big-endian operation at the Exception level being returned to, DSPSR.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, DSPSR.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on entering Debug state, and copied to PSTATE.A on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on entering Debug state, and copied to PSTATE.I on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on entering Debug state, and copied to PSTATE.F on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on entering Debug state, and copied to PSTATE.T on exiting Debug state.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on entering Debug state, and copied to PSTATE.M[4:0] on exiting Debug state.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10110	Monitor.
0b10111	Abort.
0b11010	Hyp.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If DSPSR.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, exiting Debug state is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the DSPSR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b011	0b0100	0b0101	0b000

```
if !Halted() then
    UNDEFINED;
else
    return DSPSR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b011	0b0100	0b0101	0b000

```
if !Halted() then
    UNDEFINED;
else
    DSPSR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DTLBIALL, Data TLB Invalidate All

The DTLBIALL characteristics are:

Purpose

Invalidate all cached copies of translation table entries from data TLBs that are from any level of the translation table walk. The entries that are invalidated are as follows:

- If executed at EL1, all entries that:
  - Would be required for the EL1&0 translation regime.
  - Match the current VMID, if EL2 is implemented and enabled in the current Security state.
- If executed in Secure state when EL3 is using AArch32, all entries that would be required for the Secure PL1&0 translation regime.
- If executed at EL2, and if EL2 is enabled in the current Security state, the stage 1 or stage 2 translation table entries that would be required for the Non-secure PL1&0 translation regime and matches the current VMID.

The invalidation only applies to the PE that executes this System instruction.

Arm deprecates the use of this System instruction. It is only provided for backwards compatibility with earlier versions of the Arm architecture.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DTLBIALL are UNKNOWN.

Attributes

DTLBIALL is a 32-bit System instruction.

Field descriptions

DTLBIALL ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the DTLBIALL instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        DTLBIALL();
elsif PSTATE.EL == EL2 then
    DTLBIALL();
elsif PSTATE.EL == EL3 then
    DTLBIALL();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DTLBIASID, Data TLB Invalidate by ASID match

The DTLBIASID characteristics are:

Purpose

Invalidate all cached copies of translation table entries from data TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used for the specified ASID, and either:
  - Is from a level of lookup above the final level.
  - Is a non-global entry from the final level of lookup.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation only applies to the PE that executes this System instruction.

Arm deprecates the use of this System instruction. It is only provided for backwards compatibility with earlier versions of the Arm architecture.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DTLBIASID are UNKNOWN.

Attributes

DTLBIASID is a 32-bit System instruction.

Field descriptions

The DTLBIASID input value bit assignments are:



Bits [31:8]

Reserved, RES0.

ASID, bits [7:0]

ASID value to match. Any TLB entries for non-global pages that match the ASID values will be affected by this System instruction.

Executing the DTLBIASID instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0110	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        DTLBIASID(R[t]);
elsif PSTATE.EL == EL2 then
    DTLBIASID(R[t]);
elsif PSTATE.EL == EL3 then
    DTLBIASID(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DTLBIMVA, Data TLB Invalidate by VA

The DTLBIMVA characteristics are:

Purpose

Invalidate all cached copies of translation table entries from data TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified address, and one of the following applies:
  - The entry is from a level of lookup above the final level and matches the specified ASID.
  - The entry is a global entry from the final level of lookup.
  - The entry is a non-global entry from the final level of lookup that matches the specified ASID.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation only applies to the PE that executes this System instruction.

Arm deprecates the use of this System instruction. It is only provided for backwards compatibility with earlier versions of the Arm architecture.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to DTLBIMVA are UNKNOWN.

Attributes

DTLBIMVA is a 32-bit System instruction.

Field descriptions

The DTLBIMVA input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Bits [11:8]

Reserved, RES0.

ASID, bits [7:0]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

Executing the DTLBIMVA instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0110	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        DTLBIMVA(R[t]);
elsif PSTATE.EL == EL2 then
    DTLBIMVA(R[t]);
elsif PSTATE.EL == EL3 then
    DTLBIMVA(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DVPRCTX, Data Value Prediction Restriction by Context

The DVPRCTX characteristics are:

Purpose

Data Value Prediction Restriction by Context applies to all Data Value Prediction Resources that predict execution based on information gathered within the target execution context or contexts.

When this instruction is complete and synchronized, data value prediction does not permit later speculative execution within the target execution context to be observable through side channels.

This instruction is guaranteed to be complete following a DSB that covers both read and write behavior on the same PE as executed the original restriction instruction, and a subsequent context synchronization event is required to ensure that the effect of the completion of the instructions is synchronized to the current execution.

Note

This instruction does not require the invalidation of prediction structures so long as the behavior described for completion of this instruction is met by the implementation.

On some implementations the instruction is likely to take a significant number of cycles to execute. This instruction is expected to be used very rarely, such as on the roll-over of an ASID or VMID, but should not be used on every context switch.

Configuration

This instruction is present only when AArch32 is supported at any Exception level and ARMv8.0-PredInv is implemented. Otherwise, direct accesses to DVPRCTX are UNDEFINED.

Attributes

DVPRCTX is a 32-bit System instruction.

Field descriptions

The DVPRCTX input value bit assignments are:



Bits [31:28]

Reserved, RES0.

GVMID, bit [27]

Execution of this instruction applies to all VMIDs or a specified VMID.

GVMID	Meaning
0b0	Applies to specified VMID for an EL0 or EL1 context. For all other contexts this field is RES0.
0b1	Applies to all VMIDs for an EL0 or EL1 context. For all other contexts this field is RES0.

If the instruction is executed at EL0 or EL1, then this field has an Effective value of 0.

NS, bit [26]

Security State.

NS	Meaning
0b0	Secure state.
0b1	Non-secure state.

If the instruction is executed in Non-secure state, this field has an Effective value of 1.

EL, bits [25:24]

Exception Level

EL	Meaning
0b00	EL0.
0b01	EL1.
0b10	EL2.
0b11	EL3.

If the instruction is executed at an exception level lower than the specified level, this instruction is treated as a NOP.

VMID, bits [23:16]

Only applies when bit[27] is 0 and either:

- an EL1 context.
- an EL0 context when (HCR_EL2.E2H==0 or HCR_EL2.TGE==0) or EL2 is using AArch32 state.

Otherwise this field is RES0.

When the instruction is executed at EL1 then this field is treated as the current VMID.

When the instruction is executed at EL0 and (HCR_EL2.E2H==0 or HCR_EL2.TGE==0 or ELUsingAArch32(EL2)) then this field is treated as the current VMID.

When the instruction is executed at EL0 and (HCR_EL2.E2H==1 and HCR_EL2.TGE==1 and !ELUsingAArch32(EL2)) then this field is ignored.

Bits [15:9]

Reserved, RES0.

GASID, bit [8]

Execution of this instruction applies to all ASIDs or a specified ASID.

GASID	Meaning
0b0	Applies to specified ASID for an EL0 context. For all other contexts this field is RES0.
0b1	Applies to all ASID for an EL0 context. For all other contexts this field is RES0.

If the instruction is executed at EL0, then this field has an Effective value of 0.

ASID, bits [7:0]

Only applies for an EL0 context and when bit[8] is 0.

Otherwise this field is RES0.

When the instruction is executed at EL0 then this field is treated as the current ASID.

Executing the DVPRCTX instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0011	0b101

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && !(EL2Enabled() && HCR_EL2.<E2H,TGE> == '11') && SCTLR_EL1.EnRCTX ==
'0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && SCTLR.EnRCTX == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T7 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> == '11' && SCTLR_EL2.EnRCTX ==
'0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        DVPRCTX(R[t]);
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.NV == '1' then
        AArch64.SystemAccessTrap(EL2, 0x03);
    else
        DVPRCTX(R[t]);
elsif PSTATE.EL == EL2 then
    DVPRCTX(R[t]);
elsif PSTATE.EL == EL3 then
    DVPRCTX(R[t]);
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ELR_hyp, Exception Link Register (Hyp mode)

The ELR_hyp characteristics are:

Purpose

When taking an exception to Hyp mode, holds the address to return to.

Configuration

AArch32 System register ELR_hyp bits [31:0] are architecturally mapped to AArch64 System register ELR_EL2[31:0] .

ThisOn registera isreset presentinto only whenan AArch32Exception islevel supportedthat atis anyusing ExceptionAArch32 level. Otherwise, direct accesses to ELR_hyp areis UNKNOWN.

Attributes

ELR_hyp is a 32-bit register.

Field descriptions

The ELR_hyp bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Return address																															

Bits [31:0]

Return address.

This field resets to an architecturally UNKNOWN value.

Accessing the ELR_hyp

ELR_hyp is accessible only at Hyp mode and Monitor mode.

ELR_hyp is accessible only at Hyp mode and Monitor mode. For more details, see MRS (banked register) and MSR (banked register) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Accesses to this register use the following encodings:

```
MRS{<c>}{<q>} <Rd>, ELR_hyp
```

R	M	M1
0b0	0b1	0b1110

```
MSR{<c>}{<q>} ELR_hyp, <Rn>
```

R	M	M1
0b0	0b1	0b1110

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRSELR, Error Record Select Register

The ERRSELR characteristics are:

Purpose

Selects an error record to be accessed through the Error Record System registers.

Configuration

AArch32 System register ERRSELR bits [31:0] are architecturally mapped to AArch64 System register ERRSELR_EL1[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRSELR are UNDEFINED.

If ERRIDR indicates that zero error records are implemented, then it is IMPLEMENTATION DEFINED whether ERRSELR is UNDEFINED or RES0.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ERRSELR is a 32-bit register.

Field descriptions

The ERRSELR bit assignments are:



Bits [31:16]

Reserved, RES0.

SEL, bits [15:0]

Selects the error record accessed through the ERX registers.

For example, if ERRSELR.SEL is set to 0x0004, then direct reads and writes of ERXSTATUS access ERR4STATUS.

If ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then all of the following apply:

- The value read back from ERRSELR.SEL is UNKNOWN.
- ~~The value read back from ERRSELR.SEL is UNKNOWN.~~
- ~~One of the following occurs:~~

One of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN error record is selected.~~
- ~~The ERX* registers are RAZ/WI.~~

The ERX* registers are RAZ/WI.

- ~~ERX* register reads and writes are NOPs.~~

ERX* register reads and writes are NOPs.

- ERX* register reads and writes are UNDEFINED.

- ~~ERX* register reads and writes are UNDEFINED.~~

This field resets to an architecturally UNKNOWN value.

Accessing the ERRSELR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERRSELR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERRSELR;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERRSELR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERRSELR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERRSELR = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERRSELR = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXADDR, Selected Error Record Address Register

The ERXADDR characteristics are:

Purpose

Accesses bits [31:0] of ERR<n>ADDR for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXADDR bits [31:0] are architecturally mapped to AArch64 System register ERXADDR_EL1[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXADDR are UNDEFINED.

Attributes

ERXADDR is a 32-bit register.

Field descriptions

The ERXADDR bit assignments are:

Bits [31:0]

ERXADDR accesses bits [31:0] of ERR<n>ADDR, where <n> is the value in ERRSELR.SEL.

Accessing the ERXADDR

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - ~~An UNKNOWN record is selected.~~
  - ~~ERXADDR is RAZ/WI.~~

  ERXADDR is RAZ/WI.
  - ~~Direct reads and writes of ERXADDR are NOPs.~~

  Direct reads and writes of ERXADDR are NOPs.
- Direct reads and writes of ERXADDR are UNDEFINED.
  - ~~Direct reads and writes of ERXADDR are UNDEFINED.~~

ERR<n>ADDR describes additional constraints that also apply when ERR<n>ADDR is accessed through ERXADDR.

Accesses to this register use the following encodings:

MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0100	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXADDR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXADDR;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXADDR;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0100	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXADDR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXADDR = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXADDR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXADDR2, Selected Error Record Address Register 2

The ERXADDR2 characteristics are:

Purpose

Accesses bits [63:32] of ERR<n>ADDR for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXADDR2 bits [31:0] are architecturally mapped to AArch64 System register ERXADDR_EL1[63:32] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXADDR2 are UNDEFINED.

Attributes

ERXADDR2 is a 32-bit register.

Field descriptions

The ERXADDR2 bit assignments are:

Bits [31:0]

ERXADDR2 accesses bits [63:32] of ERR<n>ADDR, where <n> is the value in ERRSELR.SEL.

Accessing the ERXADDR2

If ERRIDR.NUM == 0 or 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - An UNKNOWN record is selected.
  - ERXADDR2 is RAZ/WI.

  ERXADDR2 is RAZ/WI.
  - Direct reads and writes of ERXADDR2 are NOPs.

  Direct reads and writes of ERXADDR2 are NOPs.
- Direct reads and writes of ERXADDR2 are UNDEFINED.
  - Direct reads and writes of ERXADDR2 are UNDEFINED.

ERR<n>ADDR describes additional constraints that also apply when ERR<n>ADDR is accessed through ERXADDR2.

Accesses to this register use the following encodings:

MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0100	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXADDR2;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXADDR2;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXADDR2;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0100	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXADDR2 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXADDR2 = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXADDR2 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXCTLR, Selected Error Record Control Register

The ERXCTLR characteristics are:

Purpose

Accesses bits [31:0] of ERR<n>CTLR for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXCTLR bits [31:0] are architecturally mapped to AArch64 System register ERXCTLR_EL1[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXCTLR are UNDEFINED.

Attributes

ERXCTLR is a 32-bit register.

Field descriptions

The ERXCTLR bit assignments are:



Bits [31:0]

ERXCTLR accesses bits [31:0] of ERR<n>CTLR, where <n> is the value in ERRSELR.SEL.

Accessing the ERXCTLR

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - ~~An UNKNOWN record is selected.~~
  - ~~ERXCTLR is RAZ/WI.~~

  ERXCTLR is RAZ/WI.
  - ~~Direct reads and writes of ERXCTLR are NOPs.~~

  Direct reads and writes of ERXCTLR are NOPs.
- Direct reads and writes of ERXCTLR are UNDEFINED.
  - ~~Direct reads and writes of ERXCTLR are UNDEFINED.~~

If ERRSELR.SEL is not the index of the first error record owned by a node, then ERR<n>CTLR[31:0] is not present, meaning reads and writes of ERXCTLR are RES0.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0100	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXCTLR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXCTLR;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXCTLR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0100	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXCTLR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXCTLR = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXCTLR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXCTLR2, Selected Error Record Control Register 2

The ERXCTLR2 characteristics are:

Purpose

Accesses bits [63:32] of ERR<n>CTLR for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXCTLR2 bits [31:0] are architecturally mapped to AArch64 System register ERXCTLR_EL1[63:32] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXCTLR2 are UNDEFINED.

Attributes

ERXCTLR2 is a 32-bit register.

Field descriptions

The ERXCTLR2 bit assignments are:



Bits [31:0]

ERXCTLR2 accesses bits [63:32] of ERR<n>CTLR, where <n> is the value in ERRSELR.SEL.

Accessing the ERXCTLR2

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - ~~An UNKNOWN record is selected.~~
  - ~~ERXCTLR2 is RAZ/WI.~~

  ERXCTLR2 is RAZ/WI.
  - ~~Direct reads and writes of ERXCTLR2 are NOPs.~~

  Direct reads and writes of ERXCTLR2 are NOPs.
- Direct reads and writes of ERXCTLR2 are UNDEFINED.
  - ~~Direct reads and writes of ERXCTLR2 are UNDEFINED.~~

If ERRSELR.SEL is not the index of the first error record owned by a node, then ERR<n>CTLR[63:32] is not present, meaning reads and writes of ERXCTLR2 are RES0.

Accesses to this register use the following encodings:

MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXCTLR2;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXCTLR2;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXCTLR2;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXCTLR2 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXCTLR2 = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXCTLR2 = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXFR, Selected Error Record Feature Register

The ERXFR characteristics are:

Purpose

Accesses bits [31:0] of ERR<n>FR for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXFR bits [31:0] are architecturally mapped to AArch64 System register ERXFR_EL1[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXFR are UNDEFINED.

Attributes

ERXFR is a 32-bit register.

Field descriptions

The ERXFR bit assignments are:



Bits [31:0]

ERXFR accesses bits [31:0] of ERR<n>FR, where <n> is the value in ERRSELR.SEL.

Accessing the ERXFR

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - ~~An UNKNOWN record is selected.~~
  - ~~ERXFR is RAZ/WI.~~

  ERXFR is RAZ.
  - ~~Direct reads of ERXFR are NOPs.~~

  Direct reads of ERXFR are NOPs.
- Direct reads of ERXFR are UNDEFINED.
  - ~~Direct reads of ERXFR are UNDEFINED.~~

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2

0b1111	0b000	0b0101	0b0100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXFR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXFR;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXFR;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXFR2, Selected Error Record Feature Register 2

The ERXFR2 characteristics are:

Purpose

Accesses bits [63:32] of ERR<n>FR for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXFR2 bits [31:0] are architecturally mapped to AArch64 System register ERXFR_EL1[63:32] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXFR2 are UNDEFINED.

Attributes

ERXFR2 is a 32-bit register.

Field descriptions

The ERXFR2 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Bits [63:32] of ERR<n>FR																															

Bits [31:0]

ERXFR2 accesses bits [63:32] of ERR<n>FR, where <n> is the value in ERRSELR.SEL.

Accessing the ERXFR2

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - ~~An UNKNOWN record is selected.~~
  - ~~ERXFR2 is RAZ/WI.~~

  ERXFR2 is RAZ.
  - ~~Direct reads of ERXFR2 are NOPs.~~

  Direct reads of ERXFR2 are NOPs.
- Direct reads of ERXFR2 are UNDEFINED.
  - ~~Direct reads of ERXFR2 are UNDEFINED.~~

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2

0b1111	0b000	0b0101	0b0100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXFR2;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXFR2;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXFR2;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC0, Selected Error Record Miscellaneous Register 0

The ERXMISC0 characteristics are:

Purpose

Accesses bits [31:0] of ERR<n>MISC0 for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXMISC0 bits [31:0] are architecturally mapped to AArch64 System register ERXMISC0_EL1[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXMISC0 are UNDEFINED.

Attributes

ERXMISC0 is a 32-bit register.

Field descriptions

The ERXMISC0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Bits [31:0] of ERR<n>MISC0																															

Bits [31:0]

ERXMISC0 accesses bits [31:0] of ERR<n>MISC0, where <n> is the value in ERRSELR.SEL.

Accessing the ERXMISC0

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN record is selected.~~
- ~~ERXMISC0 is RAZ/WI.~~

  ERXMISC0 is RAZ/WI.
- ~~Direct reads and writes of ERXMISC0 are NOPs.~~

  Direct reads and writes of ERXMISC0 are NOPs.
- Direct reads and writes of ERXMISC0 are UNDEFINED.
- ~~Direct reads and writes of ERXMISC0 are UNDEFINED.~~

ERR<n>MISC0 describes additional constraints that also apply when ERR<n>MISC0 is accessed through ERXMISC0.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC0;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC0;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC0 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC0 = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC0 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC1, Selected Error Record Miscellaneous Register 1

The ERXMISC1 characteristics are:

Purpose

Accesses bits [63:32] of ERR<n>MISC0 for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXMISC1 bits [31:0] are architecturally mapped to AArch64 System register ERXMISC0_EL1[63:32] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXMISC1 are UNDEFINED.

Attributes

ERXMISC1 is a 32-bit register.

Field descriptions

The ERXMISC1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Bits [63:32] of ERR<n>MISC0																															

Bits [31:0]

ERXMISC1 accesses bits [63:32] of ERR<n>MISC0, where <n> is the value in ERRSELR.SEL.

Accessing the ERXMISC1

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN record is selected.~~
- ~~ERXMISC1 is RAZ/WI.~~

  ERXMISC1 is RAZ/WI.
- ~~Direct reads and writes of ERXMISC1 are NOPs.~~

  Direct reads and writes of ERXMISC1 are NOPs.
- Direct reads and writes of ERXMISC1 are UNDEFINED.
- ~~Direct reads and writes of ERXMISC1 are UNDEFINED.~~

ERR<n>MISC0 describes additional constraints that also apply when ERR<n>MISC0 is accessed through ERXMISC1.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC1;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC1;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC1 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC1 = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC1 = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC2, Selected Error Record Miscellaneous Register 2

The ERXMISC2 characteristics are:

Purpose

Accesses bits [31:0] of ERR<n>MISC1 for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXMISC2 bits [31:0] are architecturally mapped to AArch64 System register ERXMISC1_EL1[31:0] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXMISC2 are UNDEFINED.

Attributes

ERXMISC2 is a 32-bit register.

Field descriptions

The ERXMISC2 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Bits [31:0] of ERR<n>MISC1																															

Bits [31:0]

ERXMISC2 accesses bits [31:0] of ERR<n>MISC1, where <n> is the value in ERRSELR.SEL.

Accessing the ERXMISC2

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN record is selected.~~
- ~~ERXMISC2 is RAZ/WI.~~

  ERXMISC2 is RAZ/WI.
- ~~Direct reads and writes of ERXMISC2 are NOPs.~~

  Direct reads and writes of ERXMISC2 are NOPs.
- Direct reads and writes of ERXMISC2 are UNDEFINED.
- ~~Direct reads and writes of ERXMISC2 are UNDEFINED.~~

ERR<n>MISC1 describes additional constraints that also apply when ERR<n>MISC1 is accessed through ERXMISC2.

Accesses to this register use the following encodings:

MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC2;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC2;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC2;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC2 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC2 = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC2 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC3, Selected Error Record Miscellaneous Register 3

The ERXMISC3 characteristics are:

Purpose

Accesses bits [63:32] of ERR<n>MISC1 for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXMISC3 bits [31:0] are architecturally mapped to AArch64 System register ERXMISC1_EL1[63:32] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERXMISC3 are UNDEFINED.

Attributes

ERXMISC3 is a 32-bit register.

Field descriptions

The ERXMISC3 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Bits [63:32] of ERR<n>MISC1																															

Bits [31:0]

ERXMISC3 accesses bits [63:32] of ERR<n>MISC1, where <n> is the value in ERRSELR.SEL.

Accessing the ERXMISC3

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN record is selected.~~
- ~~ERXMISC3 is RAZ/WI.~~

  ERXMISC3 is RAZ/WI.
- ~~Direct reads and writes of ERXMISC3 are NOPs.~~

  Direct reads and writes of ERXMISC3 are NOPs.
- Direct reads and writes of ERXMISC3 are UNDEFINED.
- ~~Direct reads and writes of ERXMISC3 are UNDEFINED.~~

ERR<n>MISC1 describes additional constraints that also apply when ERR<n>MISC1 is accessed through ERXMISC3.

Accesses to this register use the following encodings:

MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC3;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC3;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC3;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC3 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC3 = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC3 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC4, Selected Error Record Miscellaneous Register 4

The ERXMISC4 characteristics are:

Purpose

Accesses bits [31:0] of ERR<n>MISC2 for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXMISC4 bits [31:0] are architecturally mapped to AArch64 System register ERXMISC2_EL1[31:0] .

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERXMISC4 are UNDEFINED.

Attributes

ERXMISC4 is a 32-bit register.

Field descriptions

The ERXMISC4 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Bits [31:0] of ERR<n>MISC2																															

Bits [31:0]

ERXMISC4 accesses bits [31:0] of ERR<n>MISC2, where <n> is the value in ERRSELR.SEL.

Accessing the ERXMISC4

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN record is selected.~~
- ~~ERXMISC4 is RAZ/WI.~~

  ERXMISC4 is RAZ/WI.
- ~~Direct reads and writes of ERXMISC4 are NOPs.~~

  Direct reads and writes of ERXMISC4 are NOPs.
- Direct reads and writes of ERXMISC4 are UNDEFINED.
- ~~Direct reads and writes of ERXMISC4 are UNDEFINED.~~

ERR<n>MISC2 describes additional constraints that also apply when ERR<n>MISC2 is accessed through ERXMISC4.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC4;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC4;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC4;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC4 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC4 = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC4 = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f211~~6134483bd14dc8c12a99c984cbfe3431cc1c9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC5, Selected Error Record Miscellaneous Register 5

The ERXMISC5 characteristics are:

Purpose

Accesses bits [63:32] of ERR<n>MISC2 for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXMISC5 bits [31:0] are architecturally mapped to AArch64 System register ERXMISC2_EL1[63:32] .

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERXMISC5 are UNDEFINED.

Attributes

ERXMISC5 is a 32-bit register.

Field descriptions

The ERXMISC5 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Bits [63:32] of ERR<n>MISC2																															

Bits [31:0]

ERXMISC5 accesses bits [63:32] of ERR<n>MISC2, where <n> is the value in ERRSELR.SEL.

Accessing the ERXMISC5

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN record is selected.~~
- ~~ERXMISC5 is RAZ/WI.~~

  ERXMISC5 is RAZ/WI.
- ~~Direct reads and writes of ERXMISC5 are NOPs.~~

  Direct reads and writes of ERXMISC5 are NOPs.
- Direct reads and writes of ERXMISC5 are UNDEFINED.
- ~~Direct reads and writes of ERXMISC5 are UNDEFINED.~~

ERR<n>MISC2 describes additional constraints that also apply when ERR<n>MISC2 is accessed through ERXMISC5.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC5;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC5;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC5;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC5 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC5 = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC5 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC6, Selected Error Record Miscellaneous Register 6

The ERXMISC6 characteristics are:

Purpose

Accesses bits [31:0] of ERR<n>MISC3 for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXMISC6 bits [31:0] are architecturally mapped to AArch64 System register ERXMISC3_EL1[31:0] .

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERXMISC6 are UNDEFINED.

Attributes

ERXMISC6 is a 32-bit register.

Field descriptions

The ERXMISC6 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Bits [31:0] of ERR<n>MISC3																															

Bits [31:0]

ERXMISC6 accesses bits [31:0] of ERR<n>MISC3, where <n> is the value in ERRSELR.SEL.

Accessing the ERXMISC6

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
  - ~~An UNKNOWN record is selected.~~
  - ~~ERXMISC6 is RAZ/WI.~~

  ERXMISC6 is RAZ/WI.
  - ~~Direct reads and writes of ERXMISC6 are NOPs.~~

  Direct reads and writes of ERXMISC6 are NOPs.
- Direct reads and writes of ERXMISC6 are UNDEFINED.
  - ~~Direct reads and writes of ERXMISC6 are UNDEFINED.~~

ERR<n>MISC3 describes additional constraints that also apply when ERR<n>MISC3 is accessed through ERXMISC6.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC6;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC6;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC6;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC6 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC6 = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC6 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERXMISC7, Selected Error Record Miscellaneous Register 7

The ERXMISC7 characteristics are:

Purpose

Accesses bits [63:32] of ERR<n>MISC3 for the error record <n> selected by ERRSELR.SEL.

Configuration

AArch32 System register ERXMISC7 bits [31:0] are architecturally mapped to AArch64 System register ERXMISC3_EL1[63:32] .

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERXMISC7 are UNDEFINED.

Attributes

ERXMISC7 is a 32-bit register.

Field descriptions

The ERXMISC7 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Bits [63:32] of ERR<n>MISC3																															

Bits [31:0]

ERXMISC7 accesses bits [63:32] of ERR<n>MISC3, where <n> is the value in ERRSELR.SEL.

Accessing the ERXMISC7

If ERRIDR.NUM == ~~0 or~~ 0x0000 or ERRSELR.SEL is set to a value greater than or equal to ERRIDR.NUM, then one of the following occurs:

- An UNKNOWN error record is selected.
- ~~An UNKNOWN record is selected.~~
- ~~ERXMISC7 is RAZ/WI.~~

  ERXMISC7 is RAZ/WI.
- ~~Direct reads and writes of ERXMISC7 are NOPs.~~

  Direct reads and writes of ERXMISC7 are NOPs.
- Direct reads and writes of ERXMISC7 are UNDEFINED.
- ~~Direct reads and writes of ERXMISC7 are UNDEFINED.~~

ERR<n>MISC3 describes additional constraints that also apply when ERR<n>MISC3 is accessed through ERXMISC7.

Accesses to this register use the following encodings:

MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC7;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC7;
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ERXMISC7;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0101	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TERR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC7 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.TERR == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC7 = R[t];
elsif PSTATE.EL == EL3 then
    if PSTATE.M != M32_Monitor && SCR.TERR == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ERXMISC7 = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

FCSEIDR, FCSE Process ID register

The FCSEIDR characteristics are:

Purpose

Identifies whether the Fast Context Switch Extension (FCSE) is implemented.

From Armv8, the FCSE is not implemented, so this register is RAZ/WI. Software can access this register to determine that the implementation does not include the FCSE.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to FCSEIDR are UNKNOWN.

Attributes

FCSEIDR is a 32-bit register.

Field descriptions

The FCSEIDR bit assignments are:



Bits [31:0]

Reserved, RAZ/WI.

Accessing the FCSEIDR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return FCSEIDR;
elsif PSTATE.EL == EL2 then
    return FCSEIDR;
elsif PSTATE.EL == EL3 then
    return FCSEIDR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        FCSEIDR = R[t];
elsif PSTATE.EL == EL2 then
    FCSEIDR = R[t];
elsif PSTATE.EL == EL3 then
    FCSEIDR = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

FPEXC, Floating-Point Exception Control register

The FPEXC characteristics are:

Purpose

Provides a global enable for the implemented Advanced SIMD and floating-point functionality, and reports floating-point status information.

Configuration

AArch32 System register FPEXC bits [31:0] are architecturally mapped to AArch64 System register FPEXC32_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to FPEXC are UNKNOWN.

Implemented only if the implementation includes the Advanced SIMD and floating-point functionality.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

FPEXC is a 32-bit register.

Field descriptions

The FPEXC bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
EX	EN	DEX	FP2V	VV	TFV	RES0															VECITR			IDF	RES0		IXF	UFF	OFF	DZF	IOF

EX, bit [31]

Exception bit. From Armv8, this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

EN, bit [30]

Enables access to the Advanced SIMD and floating-point functionality from all Exception levels, except that setting this field to 0 does not disable the following:

- VMSR accesses to the FPEXC or FPSID.
- VMRS accesses from the FPEXC, FPSID, MVFR0, MVFR1, or MVFR2.

EN	Meaning
0b0	Accesses to the FPSCR, and any of the SIMD and floating-point registers Q0-Q15, including their views as D0-D31 registers or S0-S31 registers, are UNDEFINED at all Exception levels.
0b1	This control permits access to the Advanced SIMD and floating-point functionality at all Exception levels.

Execution of floating-point and Advanced SIMD instructions in AArch32 state can be disabled or trapped by the following controls:

- CPACR.cp10, or, if executing at EL0, CPACR_EL1.FPEN.

- FPEXC.EN.
- If executing in Non-secure state:
  - HCPTR.TCP10, or if EL2 is using AArch64, CPTR_EL2.TFP.
  - NSACR.cp10, or if EL3 is using AArch64, CPTR_EL3.TFP.
- For Advanced SIMD instructions only:
  - CPACR.ASEDIS.
  - If executing in Non-secure state, HCPTR.TASE and NSACR.NSTRCDIS.

See the descriptions of the controls for more information.

Note

When executing at EL0 using AArch32:

- If EL1 is using AArch64 then behavior is as if the value of FPEXC.EN is 1.
- If EL2 is using AArch64 and enabled in the current Security state, and the value of HCR_EL2.{RW, TGE} is {1, 1}, then the behavior is as if the value of FPEXC.EN is 1.
- If EL2 is using AArch64 and enabled in the current Security state, and the value of HCR_EL2.{RW, TGE} is {0, 1}, then it is IMPLEMENTATION DEFINED whether the behavior is:
  - As if the value of FPEXC.EN is 1.
  - Determined by the value of FPEXC.EN, as described in this field description. However, Arm deprecates using the value of FPEXC.EN to determine behavior.

This field resets to `0`.

DEX, bit [29]

Defined synchronous exception on floating-point execution.

This field identifies whether a synchronous exception generated by the attempted execution of an instruction was generated by an unallocated encoding. The instruction must be in the encoding space that is identified by the pseudocode function ExecutingCP10or11Instr() returning TRUE. This field also indicates whether the FPEXC.TFV field is valid.

The meaning of this bit is:

DEX	Meaning
`0b0`	The exception was generated by the attempted execution of an unallocated instruction in the encoding space that is identified by the pseudocode function ExecutingCP10or11Instr(). If FPEXC.TFV is RW then it is invalid and UNKNOWN. If FPEXC.{IDF, IXF, UFF, OFF, DZF, IOF} are RW then they are invalid and UNKNOWN.
`0b1`	The exception was generated during the execution of an unallocated encoding. FPEXC.TFV is valid and indicates the cause of the exception.

On an exception that sets this bit to 1 the exception-handling routine must clear this bit to 0.

On an implementation that both does not support trapping of floating-point exceptions and implements the FPSCR.{Stride, Len} fields as RAZ, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

FP2V, bit [28]

FPINST2 instruction valid bit. From Armv8, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

VV, bit [27]

VECITR valid bit. From Armv8, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

TFV, bit [26]

Trapped Fault Valid bit. Valid only when the value of FPEXC.DEX is 1. When valid, it indicates the cause of the exception and therefore whether the FPEXC.{IDF, IXF, UFF, OFF, DZF, IOF} bits are valid.

TFV	Meaning
0b0	The exception was caused by the execution of a floating-point VABS, VADD, VDIV, VFMA, VFMS, VFNMA, VFNMS, VMLA, VMLS, VMOV, VMUL, VNEG, VNMLA, VNMLS, VNMUL, VSQRT, or VSUB instruction when one or both of FPSCR.{Stride, Len} was non-zero. If the FPEXC.{IDF, IXF, UFF, OFF, DZF, IOF} bits are RW then they are invalid and UNKNOWN.
0b1	FPEXC.{IDF, IXF, UFF, OFF, DZF, IOF} indicate the presence of trapped floating-point exceptions that had occurred at the time of the exception. Bits are set for all trapped exceptions that had occurred at the time of the exception.

This bit returns a status value and ignores writes.

When the value of FPEXC.DEX is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

On an implementation that supports the trapping of floating-point exceptions and implements FPSCR.{Stride, Len} as RAZ, this bit is RAO/WI.

This field resets to an architecturally UNKNOWN value.

Bits [25:11]

Reserved, RES0.

VECITR, bits [10:8]

Vector iteration count. From Armv8, this field is RES1.

This field resets to an architecturally UNKNOWN value.

IDF, bit [7]

Input Denormal trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether an Input Denormal exception occurred while FPSCR.IDE was 1:

IDF	Meaning
0b0	Input Denormal exception has not occurred.
0b1	Input Denormal exception has occurred.

Input Denormal exceptions can occur only when FPSCR.FZ is 1.

Note

A half-precision floating-point value that is flushed to zero because the value of FPSCR.FZ16 is 1 does not generate an Input Denormal exception.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

Bits [6:5]

Reserved, RES0.

IXF, bit [4]

Inexact trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether an Inexact exception occurred while FPSCR.IXE was 1:

IXF	Meaning
0b0	Inexact exception has not occurred.
0b1	Inexact exception has occurred.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

UFF, bit [3]

Underflow trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether an Underflow exception occurred while FPSCR.UFE was 1:

UFF	Meaning
0b0	Underflow exception has not occurred.
0b1	Underflow exception has occurred.

Underflow trapped exceptions can occur:

- On half-precision data-processing instructions only when FPSCR.FZ16 is 0.
- Otherwise only when FPSCR.FZ is 0.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

OFF, bit [2]

Overflow trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether an Overflow exception occurred while FPSCR.OFE was 1:

OFF	Meaning
0b0	Overflow exception has not occurred.
0b1	Overflow exception has occurred.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

DZF, bit [1]

Divide by Zero trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether a Divide by Zero exception occurred while FPSCR.DZE was 1:

DZF	Meaning
0b0	Divide by Zero exception has not occurred.
0b1	Divide by Zero exception has occurred.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

IOF, bit [0]

Invalid Operation trapped exception bit. Valid only when the value of FPEXC.TFV is 1. When valid, it indicates whether an Invalid Operation exception occurred while FPSCR.IOE was 1:

IOF	Meaning
0b0	Invalid Operation exception has not occurred.
0b1	Invalid Operation exception has occurred.

This bit must be cleared to 0 by the exception-handling routine.

When the value of FPEXC.TFV is 0 and this bit is RW, this bit is invalid and UNKNOWN.

On an implementation that does not support the trapping of floating-point exceptions this bit is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

Accessing the FPEXC

Accesses to this register use the following encodings:

```
VMRS{<c>}{<q>} <Rt>, <spec_reg>
```

reg
0b1000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if ELUsingAArch32(EL1) && ((ELUsingAArch32(EL3) && SCR.NS == '1' && NSACR.cp10 == '0') ||
CPACR.cp10 == '00') then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x08);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x08);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x08);
    else
        return FPEXC;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x00);
    else
        return FPEXC;
elsif PSTATE.EL == EL3 then
    if CPACR.cp10 == '00' then
        UNDEFINED;
    else
        return FPEXC;
```

```
VMSR{<c>}{<q>} <spec_reg>, <Rt>
```

reg
0b1000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if ELUsingAArch32(EL1) && ((ELUsingAArch32(EL3) && SCR.NS == '1' && NSACR.cp10 == '0') ||
CPACR.cp10 == '00') then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x08);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x08);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x08);
    else
        FPEXC = R[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x00);
    else
        FPEXC = R[t];
elsif PSTATE.EL == EL3 then
    if CPACR.cp10 == '00' then
        UNDEFINED;
    else
        FPEXC = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

FPSCR, Floating-Point Status and Control Register

The FPSCR characteristics are:

Purpose

Provides floating-point system status information and control.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to FPSCR are UNKNOWN.

The named fields in this register map to the equivalent fields in the AArch64 FPCR and FPSR.

It is IMPLEMENTATION DEFINED whether the Len and Stride fields can be programmed to non-zero values, which will cause some AArch32 floating-point instruction encodings to be UNDEFINED, or whether these fields are RAZ.

Implemented only if the implementation includes the Advanced SIMD and floating-point functionality.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

FPSCR is a 32-bit register.

Field descriptions

The FPSCR bit assignments are:



N, bit [31]

Negative condition flag. This is updated by floating-point comparison operations.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero condition flag. This is updated by floating-point comparison operations.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry condition flag. This is updated by floating-point comparison operations.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow condition flag. This is updated by floating-point comparison operations.

This field resets to an architecturally UNKNOWN value.

QC, bit [27]

Cumulative saturation bit, Advanced SIMD only. This bit is set to 1 to indicate that an Advanced SIMD integer operation has saturated since 0 was last written to this bit.

This field resets to an architecturally UNKNOWN value.

AHP, bit [26]

Alternative half-precision control bit:

AHP	Meaning
0b0	IEEE half-precision format selected.
0b1	Alternative half-precision format selected.

This bit is only used for conversions between half-precision floating-point and other floating-point formats.

The data-processing instructions added as part of the ARMv8.2-FP16 extension always use the IEEE half-precision format, and ignore the value of this bit.

This field resets to an architecturally UNKNOWN value.

DN, bit [25]

Default NaN mode control bit:

DN	Meaning
0b0	NaN operands propagate through to the output of a floating-point operation.
0b1	Any operation involving one or more NaNs returns the Default NaN.

The value of this bit only controls scalar floating-point arithmetic. Advanced SIMD arithmetic always uses the Default NaN setting, regardless of the value of the DN bit.

This field resets to an architecturally UNKNOWN value.

FZ, bit [24]

Flush-to-zero mode control bit:

FZ	Meaning
0b0	Flush-to-zero mode disabled. Behavior of the floating-point system is fully compliant with the IEEE 754 standard.
0b1	Flush-to-zero mode enabled.

The value of this bit only controls scalar floating-point arithmetic. Advanced SIMD arithmetic always uses the Flush-to-zero setting, regardless of the value of the FZ bit.

This bit has no effect on half-precision calculations.

This field resets to an architecturally UNKNOWN value.

RMode, bits [23:22]

Rounding Mode control field. The encoding of this field is:

RMode	Meaning
0b00	Round to Nearest (RN) mode.
0b01	Round towards Plus Infinity (RP) mode.
0b10	Round towards Minus Infinity (RM) mode.
0b11	Round towards Zero (RZ) mode.

The specified rounding mode is used by almost all scalar floating-point instructions. Advanced SIMD arithmetic always uses the Round to Nearest setting, regardless of the value of the RMode bits.

This field resets to an architecturally UNKNOWN value.

Stride, bits [21:20]

It is IMPLEMENTATION DEFINED whether this field is RW or RAZ.

If this field is RW and is set to a value other than zero, some floating-point instruction encodings are UNDEFINED. The instruction pseudocode identifies these instructions.

Arm strongly recommends that software never sets this field to a value other than zero.

The value of this field is ignored when processing Advanced SIMD instructions.

This field resets to an architecturally UNKNOWN value.

FZ16, bit [19]

When ARMv8.2-FP16 is implemented:

Flush-to-zero mode control bit on half-precision data-processing instructions:

FZ16	Meaning
0b0	Flush-to-zero mode disabled. Behavior of the floating-point system is fully compliant with the IEEE 754 standard.
0b1	Flush-to-zero mode enabled.

The value of this bit applies to both scalar and Advanced SIMD floating-point half-precision calculations.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Len, bits [18:16]

It is IMPLEMENTATION DEFINED whether this field is RW or RAZ.

If this field is RW and is set to a value other than zero, some floating-point instruction encodings are UNDEFINED. The instruction pseudocode identifies these instructions.

Arm strongly recommends that software never sets this field to a value other than zero.

The value of this field is ignored when processing Advanced SIMD instructions.

This field resets to an architecturally UNKNOWN value.

IDE, bit [15]

Input Denormal floating-point exception trap enable. Possible values are:

IDE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the IDC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the IDC bit. The trap handling software can decide whether to set the IDC bit to 1.

This bit is RW only if the implementation supports the trapping of floating-point exceptions. In an implementation that does not support floating-point exception trapping, this bit is RAZ/WI.

When this bit is RW, it applies only to floating-point operations. Advanced SIMD operations always use untrapped floating-point exception handling in AArch32 state.

This field resets to an architecturally UNKNOWN value.

Bits [14:13]

Reserved, RES0.

IXE, bit [12]

Inexact floating-point exception trap enable. Possible values are:

IXE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the IXC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the IXC bit. The trap handling software can decide whether to set the IXC bit to 1.

This bit is RW only if the implementation supports the trapping of floating-point exceptions. In an implementation that does not support floating-point exception trapping, this bit is RAZ/WI.

When this bit is RW, it applies only to floating-point operations. Advanced SIMD operations always use untrapped floating-point exception handling in AArch32 state.

This field resets to an architecturally UNKNOWN value.

UFE, bit [11]

Underflow floating-point exception trap enable. Possible values are:

UFE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the UFC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the UFC bit. The trap handling software can decide whether to set the UFC bit to 1.

This bit is RW only if the implementation supports the trapping of floating-point exceptions. In an implementation that does not support floating-point exception trapping, this bit is RAZ/WI.

When this bit is RW, it applies only to floating-point operations. Advanced SIMD operations always use untrapped floating-point exception handling in AArch32 state.

This field resets to an architecturally UNKNOWN value.

OFE, bit [10]

Overflow floating-point exception trap enable. Possible values are:

OFE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the OFC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the OFC bit. The trap handling software can decide whether to set the OFC bit to 1.

This bit is RW only if the implementation supports the trapping of floating-point exceptions. In an implementation that does not support floating-point exception trapping, this bit is RAZ/WI.

When this bit is RW, it applies only to floating-point operations. Advanced SIMD operations always use untrapped floating-point exception handling in AArch32 state.

This field resets to an architecturally UNKNOWN value.

DZE, bit [9]

Divide by Zero floating-point exception trap enable. Possible values are:

DZE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the DZC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the DZC bit. The trap handling software can decide whether to set the DZC bit to 1.

This bit is RW only if the implementation supports the trapping of floating-point exceptions. In an implementation that does not support floating-point exception trapping, this bit is RAZ/WI.

When this bit is RW, it applies only to floating-point operations. Advanced SIMD operations always use untrapped floating-point exception handling in AArch32 state.

This field resets to an architecturally UNKNOWN value.

IOE, bit [8]

Invalid Operation floating-point exception trap enable. Possible values are:

IOE	Meaning
0b0	Untrapped exception handling selected. If the floating-point exception occurs then the IOC bit is set to 1.
0b1	Trapped exception handling selected. If the floating-point exception occurs, the PE does not update the IOC bit. The trap handling software can decide whether to set the IOC bit to 1.

This bit is RW only if the implementation supports the trapping of floating-point exceptions. In an implementation that does not support floating-point exception trapping, this bit is RAZ/WI.

When this bit is RW, it applies only to floating-point operations. Advanced SIMD operations always use untrapped floating-point exception handling in AArch32 state.

This field resets to an architecturally UNKNOWN value.

IDC, bit [7]

Input Denormal cumulative floating-point exception bit. This bit is set to 1 to indicate that the Input Denormal floating-point exception has occurred since 0 was last written to this bit.

How VFP instructions update this bit depends on the value of the IDE bit.

Advanced SIMD instructions set this bit if the Input Denormal floating-point exception occurs in one or more of the floating-point calculations performed by the instruction, regardless of the value of the IDE bit.

This field resets to an architecturally UNKNOWN value.

Bits [6:5]

Reserved, RES0.

IXC, bit [4]

Inexact cumulative floating-point exception bit. This bit is set to 1 to indicate that the Inexact floating-point exception has occurred since 0 was last written to this bit.

How VFP instructions update this bit depends on the value of the IXE bit.

Advanced SIMD instructions set this bit if the Inexact floating-point exception occurs in one or more of the floating-point calculations performed by the instruction, regardless of the value of the IXE bit.

The criteria for the Inexact floating-point exception to occur are different in Flush-to-zero mode. For details, see 'Flush-to-zero'.

This field resets to an architecturally UNKNOWN value.

UFC, bit [3]

Underflow cumulative floating-point exception bit. This bit is set to 1 to indicate that the Underflow floating-point exception has occurred since 0 was last written to this bit.

How VFP instructions update this bit depends on the value of the UFE bit.

Advanced SIMD instructions set this bit if the Underflow floating-point exception occurs in one or more of the floating-point calculations performed by the instruction, regardless of the value of the UFE bit.

The criteria for the Underflow floating-point exception to occur are different in Flush-to-zero mode. For details, see 'Flush-to-zero'.

This field resets to an architecturally UNKNOWN value.

OFC, bit [2]

Overflow cumulative floating-point exception bit. This bit is set to 1 to indicate that the Overflow floating-point exception has occurred since 0 was last written to this bit.

How VFP instructions update this bit depends on the value of the OFE bit.

Advanced SIMD instructions set this bit if the Overflow floating-point exception occurs in one or more of the floating-point calculations performed by the instruction, regardless of the value of the OFE bit.

This field resets to an architecturally UNKNOWN value.

DZC, bit [1]

Divide by Zero cumulative floating-point exception bit. This bit is set to 1 to indicate that the Divide by Zero floating-point exception has occurred since 0 was last written to this bit.

How VFP instructions update this bit depends on the value of the DZE bit.

Advanced SIMD instructions set this bit if the Divide by Zero floating-point exception occurs in one or more of the floating-point calculations performed by the instruction, regardless of the value of the DZE bit.

This field resets to an architecturally UNKNOWN value.

IOC, bit [0]

Invalid Operation cumulative floating-point exception bit. This bit is set to 1 to indicate that the Invalid Operation floating-point exception has occurred since 0 was last written to this bit.

How VFP instructions update this bit depends on the value of the IOE bit.

Advanced SIMD instructions set this bit if the Invalid Operation floating-point exception occurs in one or more of the floating-point calculations performed by the instruction, regardless of the value of the IOE bit.

This field resets to an architecturally UNKNOWN value.

Accessing the FPSCR

Accesses to this register use the following encodings:

```
VMRS{<c>}{<q>} <Rt>, <spec_reg>
```

reg
0b0001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if CPACR_EL1.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL1, 0x07);
    elsif ELUsingAArch32(EL1) && ((ELUsingAArch32(EL3) && SCR.NS == '1' && NSACR.cp10 == '0') ||
CPACR.cp10 == '00') then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x08);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x08);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x08);
    else
        return FPSCR;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x00);
    else
        return FPSCR;
elsif PSTATE.EL == EL3 then
    if CPACR.cp10 == '00' then
        UNDEFINED;
    else
        return FPSCR;
```

```
VMSR{<c>}{<q>} <spec_reg>, <Rt>
```

reg
0b0001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if CPACR_EL1.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL1, 0x07);
    elsif ELUsingAArch32(EL1) && ((ELUsingAArch32(EL3) && SCR.NS == '1' && NSACR.cp10 == '0') ||
CPACR.cp10 == '00') then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x08);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x08);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x08);
    else
        FPSCR = R[t];
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x00);
    else
        FPSCR = R[t];
elsif PSTATE.EL == EL3 then
    if CPACR.cp10 == '00' then
        UNDEFINED;
    else
        FPSCR = R[t];
```

13~~27~~/1209/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

FPSID, Floating-Point System ID register

The FPSID characteristics are:

Purpose

Provides top-level information about the floating-point implementation.

This register largely duplicates information held in the MIDR. Arm deprecates use of it.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to FPSID are UNKNOWN.

Implemented only if the implementation includes the Advanced SIMD and floating-point functionality.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

FPSID is a 32-bit register.

Field descriptions

The FPSID bit assignments are:



Implementer, bits [31:24]

Implementer codes are the same as those used for the MIDR.

For an implementation by Arm this field is `0x41`, the ASCII code for A.

This field resets to an architecturally UNKNOWN value.

SW, bit [23]

Software bit. Defined values are:

SW	Meaning
`0b0`	The implementation provides a hardware implementation of the floating-point instructions.
`0b1`	The implementation supports only software emulation of the floating-point instructions.

In Armv8-A the only permitted value is `0b0`.

This field resets to an architecturally UNKNOWN value.

Subarchitecture, bits [22:16]

Subarchitecture version number. For an implementation by Arm, defined values are:

Subarchitecture	Meaning
0b0000000	VFPv1 architecture with an IMPLEMENTATION DEFINED subarchitecture.
0b0000001	VFPv2 architecture with Common VFP subarchitecture v1.
0b0000010	VFPv3 architecture, or later, with Common VFP subarchitecture v2. The VFP architecture version is indicated by the MVFR0 and MVFR1 registers.
0b0000011	VFPv3 architecture, or later, with Null subarchitecture. The entire floating-point implementation is in hardware, and no software support code is required. The VFP architecture version is indicated by the MVFR0 and MVFR1 registers. This value can be used only by an implementation that does not support the trap enable bits in the FPSCR.
0b0000100	VFPv3 architecture, or later, with Common VFP subarchitecture v3, and support for trap enable bits in FPSCR. The VFP architecture version is indicated by the MVFR0 and MVFR1 registers.

For a subarchitecture designed by Arm the most significant bit of this field, register bit[22], is 0. Values with a most significant bit of 0 that are not listed here are reserved.

When the subarchitecture designer is not Arm, the most significant bit of this field, register bit[22], must be 1. Each implementer must maintain its own list of subarchitectures it has designed, starting at subarchitecture version number 0x40.

In Armv8-A the permitted values are 0b0000011 and 0b0000100.

This field resets to an architecturally UNKNOWN value.

PartNum, bits [15:8]

An IMPLEMENTATION DEFINED part number for the floating-point implementation, assigned by the implementer.

This field resets to an architecturally UNKNOWN value.

Variant, bits [7:4]

An IMPLEMENTATION DEFINED variant number. Typically, this field distinguishes between different production variants of a single product.

This field resets to an architecturally UNKNOWN value.

Revision, bits [3:0]

An IMPLEMENTATION DEFINED revision number for the floating-point implementation.

This field resets to an architecturally UNKNOWN value.

Accessing the FPSID

Accesses to this register use the following encodings:

```
VMRS{<c>}{<q>} <Rt>, <spec_reg>
```

reg
0b0000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if ELUsingAArch32(EL1) && ((ELUsingAArch32(EL3) && SCR.NS == '1' && NSACR.cp10 == '0') ||
CPACR.cp10 == '00') then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x08);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x08);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x08);
    else
        return FPSID;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x00);
    else
        return FPSID;
elsif PSTATE.EL == EL3 then
    if CPACR.cp10 == '00' then
        UNDEFINED;
    else
        return FPSID;
```

```
VMSR{<c>}{<q>} <spec_reg>, <Rt>
```

reg
0b0000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if ELUsingAArch32(EL1) && ((ELUsingAArch32(EL3) && SCR.NS == '1' && NSACR.cp10 == '0') ||
CPACR.cp10 == '00') then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x08);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x08);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x08);
    else
        //no operation
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x00);
    else
        //no operation
elsif PSTATE.EL == EL3 then
    if CPACR.cp10 == '00' then
        UNDEFINED;
    else
        //no operation
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HACR, Hyp Auxiliary Configuration Register

The HACR characteristics are:

Purpose

Controls trapping to Hyp mode of IMPLEMENTATION DEFINED aspects of Non-secure EL1 or EL0 operation.

Configuration

AArch32 System register HACR bits [31:0] are architecturally mapped to AArch64 System register HACR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HACR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HACR is a 32-bit register.

Field descriptions

The HACR bit assignments are:



IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the HACR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HACR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HACR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HACR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HACR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HACTLR, Hyp Auxiliary Control Register

The HACTLR characteristics are:

Purpose

Controls IMPLEMENTATION DEFINED features of Hyp mode operation.

Configuration

AArch32 System register HACTLR bits [31:0] are architecturally mapped to AArch64 System register ACTLR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HACTLR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HACTLR is a 32-bit register.

Field descriptions

The HACTLR bit assignments are:



IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the HACTLR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HACTLR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HACTLR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HACTLR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HACTLR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HACTLR2, Hyp Auxiliary Control Register 2

The HACTLR2 characteristics are:

Purpose

Provides additional space to the HACTLR register to hold IMPLEMENTATION DEFINED trap functionality.

Configuration

AArch32 System register HACTLR2 bits [31:0] are architecturally mapped to AArch64 System register ACTLR_EL2[63:32] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HACTLR2 are UNKNOWN.

In Armv8.0 and Armv8.1, it is IMPLEMENTATION DEFINED whether this register is implemented, or whether it causes UNDEFINED exceptions when accessed. The implementation of this register can be detected by examining ID_MMFR4.AC2.

From Armv8.2 this register must be implemented.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HACTLR2 is a 32-bit register.

Field descriptions

The HACTLR2 bit assignments are:



IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the HACTLR2

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HACTLR2;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HACTLR2;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HACTLR2 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HACTLR2 = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HADFSR, Hyp Auxiliary Data Fault Status Register

The HADFSR characteristics are:

Purpose

Provides additional IMPLEMENTATION DEFINED syndrome information for Data Abort exceptions taken to Hyp mode.

Configuration

AArch32 System register HADFSR bits [31:0] are architecturally mapped to AArch64 System register AFSR0_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HADFSR are UNKNOWN.

This is an optional register. An implementation that does not require this register can implement it as RES0.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HADFSR is a 32-bit register.

Field descriptions

The HADFSR bit assignments are:



IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the HADFSR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0101	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HADFSR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HADFSR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0101	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HADFSR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HADFSR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HAIFSR, Hyp Auxiliary Instruction Fault Status Register

The HAIFSR characteristics are:

Purpose

Provides additional IMPLEMENTATION DEFINED syndrome information for Prefetch Abort exceptions taken to Hyp mode.

Configuration

AArch32 System register HAIFSR bits [31:0] are architecturally mapped to AArch64 System register AFSR1_EL2[31:0].

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HAIFSR are UNKNOWN.

This is an optional register. An implementation that does not require this register can implement it as RES0.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HAIFSR is a 32-bit register.

Field descriptions

The HAIFSR bit assignments are:



IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the HAIFSR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0101	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HAIFSR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HAIFSR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0101	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HAIFSR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HAIFSR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HAMAIR0, Hyp Auxiliary Memory Attribute Indirection Register 0

The HAMAIR0 characteristics are:

Purpose

Provides IMPLEMENTATION DEFINED memory attributes for the memory attribute encodings defined by HMAIR0. These IMPLEMENTATION DEFINED attributes can only provide additional qualifiers for the memory attribute encodings, and cannot change the memory attributes defined in HMAIR0.

Configuration

AArch32 System register HAMAIR0 bits [31:0] are architecturally mapped to AArch64 System register AMAIR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HAMAIR0 are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HAMAIR0 is a 32-bit register.

Field descriptions

The HAMAIR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
IMPLEMENTATION DEFINED																															

If an implementation does not provide any IMPLEMENTATION DEFINED memory attributes, this register is RES0.

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the HAMAIR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1010	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HAMAIR0;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HAMAIR0;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1010	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HAMAIR0 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HAMAIR0 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HAMAIR1, Hyp Auxiliary Memory Attribute Indirection Register 1

The HAMAIR1 characteristics are:

Purpose

Provides IMPLEMENTATION DEFINED memory attributes for the memory attribute encodings defined by HMAIR1. These IMPLEMENTATION DEFINED attributes can only provide additional qualifiers for the memory attribute encodings, and cannot change the memory attributes defined in HMAIR1.

Configuration

AArch32 System register HAMAIR1 bits [31:0] are architecturally mapped to AArch64 System register AMAIR_EL2[63:32] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HAMAIR1 are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HAMAIR1 is a 32-bit register.

Field descriptions

The HAMAIR1 bit assignments are:



If an implementation does not provide any IMPLEMENTATION DEFINED memory attributes, this register is RES0.

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the HAMAIR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1010	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HAMAIR1;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HAMAIR1;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1010	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HAMAIR1 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HAMAIR1 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HCPTR, Hyp Architectural Feature Trap Register

The HCPTR characteristics are:

Purpose

Controls:

- Trapping to Hyp mode of Non-secure access, at EL1 or EL0, to trace, and to Advanced SIMD and floating-point functionality.
- Hyp mode access to trace, and to Advanced SIMD and floating-point functionality.

Note

Accesses to this functionality:

- From Non-secure modes other than Hyp mode are also affected by settings in the CPACR and NSACR.
- From Hyp mode are also affected by settings in the NSACR.

Exceptions generated by the CPACR and NSACR controls are higher priority than those generated by the HCPTR controls.

Configuration

AArch32 System register HCPTR bits [31:0] are architecturally mapped to AArch64 System register CPTR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HCPTR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 with EL2 using AArch32, or into EL3 with EL3 using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HCPTR is a 32-bit register.

Field descriptions

The HCPTR bit assignments are:

31	30	29 28 27 26 25 24 23 22 21	20	19 18 17 16	15	14	13 12	11	10	9 8 7 6 5 4 3 2 1 0
TCPAC	TAM	RES0	TTA	RES0	TASE	RES0	RES1	TCP11	TCP10	RES1

TCPAC, bit [31]

Traps Non-secure EL1 accesses to the CPACR to Hyp mode.

TCPAC	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 accesses to the CPACR are trapped to Hyp mode.

Note

The CPACR is not accessible at EL0.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

TAM, bit [30]

When AMUv1 is implemented:

Trap Activity Monitor access. Traps Non-secure EL1 and EL0 accesses to all Activity Monitor registers to EL2.

TAM	Meaning
`0b0`	Accesses from Non-secure EL1 and EL0 to Activity Monitor registers are not trapped.
`0b1`	Accesses from Non-secure EL1 and EL0 to Activity Monitor registers are trapped to Hyp mode.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

Otherwise:

Reserved, RES0.

Bits [29:21]

Reserved, RES0.

TTA, bit [20]

Traps Non-secure System register accesses to all implemented trace registers to Hyp mode.

TTA	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Any Non-secure System register access to an implemented trace register is trapped to Hyp mode, unless the access is trapped to EL1 by a CPACR or NSACR control, or the access is from Non-secure EL0 and the definition of the register in the appropriate trace architecture specification indicates that the register is not accessible from EL0. A trapped instruction generates: • A Hyp Trap exception, if the exception is taken from Non-secure EL0 or EL1. • An Undefined Instruction exception taken to Hyp mode, if the exception is taken from Hyp mode.

If the implementation does not include a PE trace unit, or does not include a System register interface to the PE trace unit registers, it is IMPLEMENTATION DEFINED whether this bit:

- Is RES0.
- Is RES1.
- Can be written from Hyp mode, and from Secure Monitor mode when SCR.NS is 1.

If EL3 is implemented and is using AArch32, and the value of NSACR.NSTRCDIS is 1, in Non-secure state this field behaves as RAO/WI, regardless of its actual value.

Note

- The ETMv4 architecture does not permit EL0 to access the trace registers. If the implementation includes an ETMv4 implementation, EL0 accesses to the trace registers are UNDEFINED, and a resulting Undefined Instruction exception is higher priority than a HCPTR.TTA Hyp Trap exception.
- The architecture does not provide traps on trace register accesses through the optional memory-mapped debug interface.

System register accesses to the trace registers can have side-effects. When a System register access is trapped, any side-effects that are normally associated with the access do not occur before the exception is taken.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

Bits [19:16]

Reserved, RES0.

TASE, bit [15]

Traps Non-secure execution of Advanced SIMD instructions to Hyp mode when the value of HCPTR.TCP10 is 0.

TASE	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	When the value of HCPTR.TCP10 is 0, any attempt to execute an Advanced SIMD instruction in Non-secure state is trapped to Hyp mode, unless it is trapped to EL1 by a CPACR or NSACR control. A trapped instruction generates: • A Hyp Trap exception, if the exception is taken from Non-secure EL0 or EL1. • An Undefined Instruction exception taken to Hyp mode, if the exception is taken from Hyp mode.

When the value of HCPTR.TCP10 is 1, the value of this field is ignored.

If the implementation does not include Advanced SIMD and floating-point functionality, this field is RES1. Otherwise, it is IMPLEMENTATION DEFINED whether this field is implemented as a RW field. If it is not implemented as a RW field, then it is RAZ/WI.

If EL3 is implemented and is using AArch32, and the value of NSACR.NSASEDIS is 1, in Non-secure state this field behaves as RAO/WI, regardless of its actual value. This applies even if the field is implemented as RAZ/WI.

For the list of instructions affected by this field, see 'Controls of Advanced SIMD operation that do not apply to floating-point operation' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section E1.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

Bit [14]

Reserved, RES0.

Bits [13:12]

Reserved, RES1.

TCP11, bit [11]

The value of this field is ignored. If this field is programmed with a different value to the TCP10 bit then this field is UNKNOWN on a direct read of the HCPTR.

If the implementation does not include Advanced SIMD and floating-point functionality, this field is RES1.

If EL3 is implemented and is using AArch32, and the value of NSACR.cp10 is 0, in Non-secure state this field behaves as RAO/WI, regardless of its actual value.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

TCP10, bit [10]

Trap Non-secure accesses to Advanced SIMD and floating-point functionality to Hyp mode:

TCP10	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Any attempted access to Advanced SIMD and floating-point functionality from Non-secure state is trapped to Hyp mode, unless it is trapped to EL1 by a CPACR or NSACR control. A trapped instruction generates: • A Hyp Trap exception, if the exception is taken from Non-secure EL0 or EL1. • An Undefined Instruction exception taken to Hyp mode, if the exception is taken from Hyp mode.

The Advanced SIMD and floating-point features controlled by these fields are:

- Execution of any floating-point or Advanced SIMD instruction.
- Any access to the Advanced SIMD and floating-point registers D0-D31 and their views as S0-S31 and Q0-Q15.
- Any access to the FPSCR, FPSID, MVFR0, MVFR1, MVFR2, or FPEXC System registers.

If the implementation does not include Advanced SIMD and floating-point functionality, this field is RES1.

If EL3 is implemented and is using AArch32, and the value of NSACR.cp10 is 0, in Non-secure state this field behaves as RAO/WI, regardless of its actual value.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

Bits [9:0]

Reserved, RES1.

Accessing the HCPTR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return HCPTR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HCPTR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && CPTR_EL3.TCPAC == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        HCPTR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HCPTR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HCR, Hyp Configuration Register

The HCR characteristics are:

Purpose

Provides configuration controls for virtualization, including defining whether various Non-secure operations are trapped to Hyp mode.

Configuration

AArch32 System register HCR bits [31:0] are architecturally mapped to AArch64 System register HCR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HCR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 with EL2 using AArch32, or into EL3 with EL3 using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HCR is a 32-bit register.

Field descriptions

The HCR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4
RES0	TRVM	HCD	RES0	TGE	TVM	TTLB	TPU	TPC	TSW	TAC	TIDCP	TSC	TID3	TID2	TID1	TID0	TWE	TWI	DC	BSU		FB	VA	VI	VF	AMO	IMO

Bit [31]

Reserved, RES0.

TRVM, bit [30]

Trap Reads of Virtual Memory controls. Traps Non-secure EL1 reads of the virtual memory control registers to EL2, when EL2 is enabled in the current Security state.

The registers for which read accesses are trapped are as follows:

SCTLR, TTBR0, TTBR1, TTBCR, TTBCR2, DACR, DFSR, IFSR, DFAR, IFAR, ADFSR, AIFSR, PRRR, NMRR, MAIR0, MAIR1, AMAIR0, AMAIR1, CONTEXTIDR.

TRVM	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 read accesses to the specified Virtual Memory controls are trapped to EL2.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

HCD, bit [29]

When EL3 is not implemented:

HVC instruction disable. Disables Non-secure EL1 and EL2 execution of HVC instructions, when EL2 is enabled in the current Security state.

HCD	Meaning
0b0	HVC instruction execution is enabled at EL2 and EL1.
0b1	HVC instructions are UNDEFINED at EL2 and Non-secure EL1. The Undefined Instruction exception is taken to the Exception level at which the HVC instruction is executed.

Note

HVC instructions are always UNDEFINED at EL0.

~~This bit is only implemented if EL3 is not implemented. Otherwise, it is RES0.~~

In a system where the PE resets into EL2 or EL3, this field resets to 0.

Otherwise:

Reserved, RES0.

Bit [28]

Reserved, RES0.

TGE, bit [27]

Trap General Exceptions, from Non-secure EL0.

TGE	Meaning
0b0	This control has no effect on execution at EL0.
0b1	When EL2 is not enabled in the current Security state, this control has no effect on execution at EL0. When EL2 is enabled in the current Security state, then: • All exceptions that would be routed to EL1 are routed to EL2. • The SCTLR.M bit is treated as being 0 for all purposes other than returning the result of a direct read of SCTLR. • The HCR.{FMO, IMO, AMO} bits are treated as being 1 for all purposes other than returning the result of a direct read of HCR. • All virtual interrupts are disabled. • Any IMPLEMENTATION DEFINED mechanisms for signaling virtual interrupts are disabled. • An exception return to EL1 is treated as an illegal exception return. • Monitor mode execution of an MSR or CPS instruction that changes CPSR.M to a Non-secure EL1 mode is an illegal change to PSTATE.M. For more information see 'Illegal changes to PSTATE.M' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model).

Also, when HCR.TGE is 1:

- If EL3 is using AArch32, an attempt to change from a Secure PL1 mode to a Non-secure EL1 mode by changing SCR.NS from 0 to 1 results in SCR.NS remaining as 0.
- The HDCR.{TDRA, TDOSA, TDA, TDE} bits are ignored and treated as being 1 other than for the purpose of a direct read of HDCR.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

TVM, bit [26]

Trap Virtual Memory controls. Traps Non-secure EL1 writes to the virtual memory control registers to EL2, when EL2 is enabled in the current Security state.

The registers for which write accesses are trapped are as follows:

SCTLR, TTBR0, TTBR1, TTBCR, TTBCR2, DACR, DFSR, IFSR, DFAR, IFAR, ADFSR, AIFSR, PRRR, NMRR, MAIR0, MAIR1, AMAIR0, AMAIR1, CONTEXTIDR.

TVM	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 write accesses to the specified virtual memory control registers are trapped to EL2.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

TTLB, bit [25]

Trap TLB maintenance instructions. Traps Non-secure EL1 execution of a TLBI instruction to EL2, when EL2 is enabled in the current Security state.

This applies to the following instructions:

TLBIALLIS, TLBIMVAIS, TLBIASIDIS, TLBIMVAAIS, TLBIMVALIS, TLBIMVAALIS, ITLBIALL, ITLBIMVA, ITLBIASID, DTLBIALL, DTLBIMVA, DTLBIASID, TLBIALL, TLBIMVA, TLBIASID, TLBIMVAA, TLBIMVAL, TLBIMVAAL

TTLB	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 accesses to the specified TLB maintenance instructions are trapped to EL2.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

TPU, bit [24]

Trap cache maintenance instructions that operate to the Point of Unification. Traps Non-secure EL1 execution of those cache maintenance instructions to EL2, when EL2 is enabled in the current Security state.

This applies to the following instructions:

- ICIMVAU, ICIALLU, ICIALLUIS, DCCMVAU.

Note

An Undefined Instruction exception generated at EL0 is higher priority than this trap to EL2, and these instructions are always UNDEFINED at EL0.

TPU	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 execution of the specified cache maintenance instructions is trapped to EL2.

If the Point of Unification is before any level of data cache, it is IMPLEMENTATION DEFINED whether the execution of any data or unified cache clean by VA to the Point of Unification instruction can be trapped when the value of this control is 1.

If the Point of Unification is before any level of instruction cache, it is IMPLEMENTATION DEFINED whether the execution of any instruction cache invalidate to the Point of Unification instruction can be trapped when the value of this control is 1.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

TPC, bit [23]

Trap data or unified cache maintenance instructions that operate to the Point of Coherency. Traps Non-secure EL1 execution of those cache maintenance instructions to EL2, when EL2 is enabled in the current Security state.

This applies to the following instructions:

- DCIMVAC, DCCIMVAC, DCCMVAC.

Note

An Undefined Instruction exception generated at EL0 is higher priority than this trap to EL2, and these instructions are always UNDEFINED at EL0.

TPC	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 execution of the specified cache maintenance instructions is trapped to EL2.

If the Point of Coherency is before any level of data cache, it is IMPLEMENTATION DEFINED whether the execution of any data or unified cache clean, invalidate, or clean and invalidate instruction that operates by VA to the point of coherency can be trapped when the value of this control is 1.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

TSW, bit [22]

Trap data or unified cache maintenance instructions that operate by Set/Way. Traps Non-secure EL1 execution of those cache maintenance instructions by set/way to EL2, when EL2 is enabled in the current Security state.

This applies to the following instructions:

- DCISW, DCCSW, DCCISW.

Note

An Undefined Instruction exception generated at EL0 is higher priority than this trap to EL2, and these instructions are always UNDEFINED at EL0.

TSW	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 execution of the specified cache maintenance instructions is trapped to EL2.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

TAC, bit [21]

Trap Auxiliary Control Registers. Traps Non-secure EL1 accesses to the Auxiliary Control Registers to EL2, when EL2 is enabled in the current Security state, from both Execution states.

This applies to the following register accesses:

ACTLR and, if implemented, ACTLR2.

TAC	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 accesses to the specified registers are trapped to EL2.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

TIDCP, bit [20]

Trap IMPLEMENTATION DEFINED functionality. Traps Non-secure EL1 accesses to the encodings for IMPLEMENTATION DEFINED System Registers to EL2, when EL2 is enabled in the current Security state.

MCR and MRC instructions accessing the following encodings:

- All coproc==p15, CRn==c9, Opcode1 = {0-7}, CRm == {c0-c2, c5-c8}, opcode2 == {0-7}.
- All coproc==p15, CRn==c10, Opcode1 =={0-7}, CRm == {c0, c1, c4, c8}, opcode2 == {0-7}.
- All coproc==p15, CRn==c11, Opcode1=={0-7}, CRm == {c0-c8, c15}, opcode2 == {0-7}.

When HCR.TIDCP is set to 1, it is IMPLEMENTATION DEFINED whether any of this functionality accessed from Non-secure EL0 is trapped to EL2. Otherwise, it is UNDEFINED and the PE takes an Undefined Instruction exception to Non-secure Undefined mode.

TIDCP	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 accesses to the specified System register encodings for IMPLEMENTATION DEFINED functionality are trapped to EL2.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

TSC, bit [19]

Trap SMC instructions. Traps Non-secure EL1 execution of SMC instructions to Hyp mode.

TSC	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Any attempt to execute an SMC instruction at Non-secure EL1 is trapped to Hyp mode, regardless of the value of SCR.SCD.

The Armv8-A architecture permits, but does not require, this trap to apply to conditional SMC instructions that fail their condition code check, in the same way as with traps on other conditional instructions.

Note
- This trap is only implemented if the implementation includes EL3.
- SMC instructions are always UNDEFINED at PL0.
- This bit traps execution of the SMC instruction. It is not a routing control for the SMC exception. Hyp Trap exceptions and SMC exceptions have different preferred return addresses.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

TID3, bit [18]

Trap ID group 3. Traps Non-secure EL1 reads of the following registers to EL2, when EL2 is enabled in the current Security state, as follows:

- ID_PFR0, ID_PFR1, ID_DFR0, ID_AFR0, ID_MMFR0, ID_MMFR1, ID_MMFR2, ID_MMFR3, ID_ISAR0, ID_ISAR1, ID_ISAR2, ID_ISAR3, ID_ISAR4, ID_ISAR5, MVFR0, MVFR1, MVFR2.
- ID_MMFR4 and ID_MMFR5 are trapped unless implemented as RAZ, when it is IMPLEMENTATION DEFINED whether accesses to ID_MMFR4 or ID_MMFR5 are trapped.
- ID_ISAR6 is trapped unless implemented as RAZ, when it is IMPLEMENTATION DEFINED whether accesses to ID_ISAR6 are trapped.
- ID_DFR1 is trapped unless implemented as RAZ, when it is IMPLEMENTATION DEFINED whether accesses to ID_DFR1 are trapped.
- It is IMPLEMENTATION DEFINED whether this bit traps MRC accesses to registers not already mentioned, with coproc==p15, opc1 == 0, CRn == c0, CRm == {c2-c7}, opc2 == {0-7}.

TID3	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	The specified Non-secure EL1 read accesses to ID group 3 registers are trapped to EL2.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

TID2, bit [17]

Trap ID group 2. Traps the following register accesses to EL2, when EL2 is enabled in the current Security state:

- Non-secure EL1 and EL0 reads of the CTR, CCSIDR, CCSIDR2, CLIDR, and CSSELR.
- Non-secure EL1 and EL0 writes to the CSSELR.

TID2	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	The specified Non-secure EL1 and EL0 accesses to ID group 2 registers are trapped to EL2.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

TID1, bit [16]

Trap ID group 1. Traps Non-secure EL1 reads of the following registers to EL2, when EL2 is enabled in the current Security state:

TCMTR, TLBTR, REVIDR, AIDR.

TID1	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	The specified Non-secure EL1 read accesses to ID group 1 registers are trapped to EL2.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

TID0, bit [15]

Trap ID group 0. Traps the following register accesses to EL2, when EL2 is enabled in the current Security state:

- Non-secure EL1 reads of the JIDR and FPSID.
- If the JIDR is RAZ from Non-secure EL0, Non-secure EL0 reads of the JIDR.

Note

- It is IMPLEMENTATION DEFINED whether the JIDR is RAZ or UNDEFINED at EL0. If it is UNDEFINED at EL0 then the Undefined Instruction exception takes precedence over this trap.
- The FPSID is not accessible at EL0.
- Writes to the FPSID are ignored, and not trapped by this control.

TID0	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	The specified Non-secure EL1 read accesses to ID group 0 registers are trapped to EL2.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

TWE, bit [14]

Traps Non-secure EL0 and EL1 execution of WFE instructions to EL2, when EL2 is enabled in the current Security state.

TWE	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Any attempt to execute a WFE instruction at Non-secure EL0 or EL1 is trapped to EL2, if the instruction would otherwise have caused the PE to enter a low-power state and it is not trapped by SCTLR.nTWE.

The attempted execution of a conditional WFE instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE can complete at any time, even without a Wakeup event, the traps on WFE are not guaranteed to be taken, even if the WFE is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

TWI, bit [13]

Traps Non-secure EL0 and EL1 execution of WFI instructions to EL2, when EL2 is enabled in the current Security state.

TWI	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Any attempt to execute a WFI instruction at Non-secure EL0 or EL1 is trapped to EL2, if the instruction would otherwise have caused the PE to enter a low-power state and it is not trapped by SCTLR.nTWI.

The attempted execution of a conditional WFI instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFI can complete at any time, even without a Wakeup event, the traps on WFI are not guaranteed to be taken, even if the WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

DC, bit [12]

Default Cacheability.

DC	Meaning
0b0	This control has no effect on the Non-secure EL1&0 translation regime.
0b1	In Non-secure state: • The SCTLR.M field behaves as 0 for all purposes other than a direct read of the value of the field. • The HCR.VM field behaves as 1 for all purposes other than a direct read of the value of the field. • The memory type produced by the first stage of the EL1&0 translation regime is Normal Non-Shareable, Inner Write-Back Read-Allocate Write-Allocate, Outer Write-Back Read-Allocate Write-Allocate.

This field has no effect on the EL2 and EL3 translation regimes.

This field is permitted to be cached in a TLB.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

BSU, bits [11:10]

Barrier Shareability upgrade. This field determines the minimum shareability domain that is applied to any barrier instruction executed from Non-secure EL1 or Non-secure EL0:

BSU	Meaning
0b00	No effect.
0b01	Inner Shareable.
0b10	Outer Shareable.
0b11	Full system.

This value is combined with the specified level of the barrier held in its instruction, using the same principles as combining the shareability attributes from two stages of address translation.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

FB, bit [9]

Force broadcast. Causes the following instructions to be broadcast within the Inner Shareable domain when executed from Non-secure EL1:

BPIALL, TLBIALL, TLBIMVA, TLBIASID, DTLBIALL, DTLBIMVA, DTLBIASID, ITLBIALL, ITLBIMVA, ITLBIASID, TLBIMVAA, ICIALLU, TLBIMVAL, TLBIMVAAL.

FB	Meaning
0b0	This field has no effect on the operation of the specified instructions.
0b1	When one of the specified instruction is executed at Non-secure EL1, the instruction is broadcast within the Inner Shareable shareability domain.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

VA, bit [8]

Virtual SError interrupt exception.

VA	Meaning
0b0	This mechanism is not making a virtual SError interrupt pending.
0b1	A virtual SError interrupt is pending because of this mechanism.

The virtual SError interrupt is enabled only when the value of HCR.{TGE, AMO} is {0, 1}.

The Guest OS cannot distinguish the virtual exception from the corresponding physical exception.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

VI, bit [7]

Virtual IRQ exception.

VI	Meaning
0b0	This mechanism is not making a virtual IRQ pending.
0b1	A virtual IRQ is pending because of this mechanism.

The virtual IRQ is enabled only when the value of HCR.{TGE, IMO} is {0, 1}.

The Guest OS cannot distinguish the virtual exception from the corresponding physical exception.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

VF, bit [6]

Virtual FIQ exception.

VF	Meaning
0b0	This mechanism is not making a virtual FIQ pending.
0b1	A virtual FIQ is pending because of this mechanism.

The virtual FIQ is enabled only when the value of HCR.{TGE, FMO} is {0, 1}.

The Guest OS cannot distinguish the virtual exception from the corresponding physical exception.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

AMO, bit [5]

SError interrupt Mask Override. When this bit is set to 1, it overrides the effect of CPSR.A, and enables virtual exception signaling by the VA bit.

If the value of HCR.TGE is 0, then virtual SError interrupts are enabled in Non-secure state.

If the value of HCR.TGE is 1, then in Non-secure state the HCR.AMO bit behaves as 1 for all purposes other than a direct read of the value of the bit.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

IMO, bit [4]

IRQ Mask Override. When this bit is set to 1, it overrides the effect of CPSR.I, and enables virtual exception signaling by the VI bit.

If the value of HCR.TGE is 0, then Virtual IRQ interrupts are enabled in the Non-secure state.

If the value of HCR.TGE is 1, then in Non-secure state the HCR.IMO bit behaves as 1 for all purposes other than a direct read of the value of the bit.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

FMO, bit [3]

FIQ Mask Override. When this bit is set to 1, it overrides the effect of CPSR.F, and enables virtual exception signaling by the VF bit.

If the value of HCR.TGE is 0, then Virtual FIQ interrupts are enabled in the Non-secure state.

If the value of HCR.TGE is 1, then in Non-secure state the HCR.FMO bit behaves as 1 for all purposes other than a direct read of the value of the bit.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

PTW, bit [2]

Protected Table Walk. In the Non-secure PL1&0 translation regime, a translation table access made as part of a stage 1 translation table walk is subject to a stage 2 translation. The combining of the memory type attributes from the two stages of translation means the access might be made to a type of Device memory. If this occurs then the value of this bit determines the behavior:

PTW	Meaning
`0b0`	The translation table walk occurs as if it is to Normal Non-cacheable memory. This means it can be made speculatively.
`0b1`	The memory access generates a stage 2 Permission fault.

This field is permitted to be cached in a TLB.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

SWIO, bit [1]

Set/Way Invalidation Override. Causes Non-secure EL1 execution of the data cache invalidate by set/way instructions to perform a data cache clean and invalidate by set/way.

SWIO	Meaning
`0b0`	This control has no effect on the operation of data cache invalidate by set/way instructions.
`0b1`	Data cache invalidate by set/way instructions perform a data cache clean and invalidate by set/way.

When this bit is set to 1, DCISW performs the same invalidation as a DCCISW instruction.

As a result of changes to the behavior of DCISW, this bit is redundant in Armv8. This bit can be implemented as RES1.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

VM, bit [0]

Virtualization enable. Enables stage 2 address translation for the Non-secure EL1&0 translation regime.

VM	Meaning
0b0	Non-secure EL1&0 stage 2 address translation disabled.
0b1	Non-secure EL1&0 stage 2 address translation enabled.

If the HCR.DC bit is set to 1, then the behavior of the PE when executing in a Non-secure mode other than Hyp mode is consistent with HCR.VM being 1, regardless of the actual value of HCR.VM, other than the value returned by an explicit read of HCR.VM.

When the value of this bit is 1, data cache invalidate instructions executed at Non-secure EL1 perform a data cache clean and invalidate. For the invalidate by set/way instruction this behavior applies regardless of the value of the HCR.SWIO bit.

This bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

Accessing the HCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HCR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HCR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HCR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HCR2, Hyp Configuration Register 2

The HCR2 characteristics are:

Purpose

Provides additional configuration controls for virtualization.

Configuration

AArch32 System register HCR2 bits [31:0] are architecturally mapped to AArch64 System register HCR_EL2[63:32] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HCR2 are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 with EL2 using AArch32, or into EL3 with EL3 using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HCR2 is a 32-bit register.

Field descriptions

The HCR2 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0									TTLBIS	RES0	TOCU	RES0	TICAB	TID4	RES0										MIOCNCE	TEA	TERR	RES0			ID	CD

Bits [31:23]

Reserved, RES0.

TTLBIS, bit [22]

When ARMv8.2-EVT is implemented:

Trap TLB maintenance instructions that operate on the Inner Shareable domain. Traps execution of the following TLB maintenance instructions at EL1 to EL2:

TLBIALLIS, TLBIMVAIS, TLBIASIDIS, TLBIMVAAIS, TLBIMVALIS, TLBIMVAALIS

TTLBIS	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 execution of the specified TLB maintenance instructions is trapped to EL2.

If ARMv8.2-EVT is not implemented, this field is RES0.

When ARMv8.1-VHE and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

Otherwise:

Reserved, RES0.

Bit [21]

Reserved, RES0.

TOCU, bit [20]

When ARMv8.2-EVT is implemented:

Trap cache maintenance instructions that operate to the Point of Unification. Traps execution of those cache maintenance instructions at EL1 or EL0 using AArch64, and at EL1 using AArch32, to EL2.

This applies to the following instructions:

- When Non-secure EL0 is using AArch64, IC IVAU, DC CVAU. However, if the value of SCTLR_EL1.UCI is 0 these instructions are UNDEFINED at EL0 and any resulting exception is higher priority than this trap to EL2.
- When EL1 is using AArch64, IC IVAU, IC IALLU, DC CVAU.
- When Non-secure EL1 is using AArch32, ICIMVAU, ICIALLU, DCCMVAU.

Note

An exception generated because an instruction is UNDEFINED at EL0 is higher priority than this trap to EL2. In addition:

- IC IALLUIS and IC IALLU are always UNDEFINED at EL0 using AArch64.
- ICIMVAU, ICIALLU, ICIALLUIS, and DCCMVAU are always UNDEFINED at EL0 using AArch32.

TOCU	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure execution of the specified cache maintenance instructions is trapped to EL2.

If ARMv8.2-EVT is not implemented, this field is RES0.

If the Point of Unification is before any level of data cache, it is IMPLEMENTATION DEFINED whether the execution of any data or unified cache clean by VA to the Point of Unification instruction can be trapped when the value of this control is 1.

If the Point of Unification is before any level of instruction cache, it is IMPLEMENTATION DEFINED whether the execution of any instruction cache invalidate to the Point of Unification instruction can be trapped when the value of this control is 1.

When ARMv8.1-VHE is implemented, and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

Otherwise:

Reserved, RES0.

Bit [19]

Reserved, RES0.

TICAB, bit [18]

When ARMv8.2-EVT is implemented:

Trap ICIALLUIS cache maintenance instructions. Traps execution of those cache maintenance instructions at EL1 to EL2.

This applies to the following instructions:

ICIALLUIS.

TICAB	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 execution of the specified cache maintenance instructions is trapped to EL2.

If ARMv8.2-EVT is not implemented, this field is RES0.

If the Point of Unification is before any level of instruction cache, it is IMPLEMENTATION DEFINED whether the execution of any instruction cache invalidate to the Point of Unification instruction can be trapped when the value of this control is 1.

When ARMv8.1-VHE and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

Otherwise:

Reserved, RES0.

TID4, bit [17]

When ARMv8.2-EVT is implemented:

Trap ID group 4. Traps the following register accesses to EL2:

- EL1 reads of CCSIDR, CCSIDR2, CLIDR, and CSSELR.
- EL1 writes to CSSELR.

TID4	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	The specified Non-secure EL1 and EL0 accesses to ID group 4 registers are trapped to EL2.

If ARMv8.2-EVT is not implemented, this field is RES0.

When ARMv8.1-VHE is implemented and the value of HCR_EL2.{E2H, TGE} is {1, 1}, this field behaves as 0 for all purposes other than a direct read of the value of this bit.

Otherwise:

Reserved, RES0.

Bits [16:7]

Reserved, RES0.

MIOCNCE, bit [6]

Mismatched Inner/Outer Cacheable Non-Coherency Enable, for the Non-secure PL1&0 translation regime.

MIOCNCE	Meaning
0b0	For the Non-secure PL1&0 translation regime, for permitted accesses to a memory location that use a common definition of the Shareability and Cacheability of the location, there must be no loss of coherency if the Inner Cacheability attribute for those accesses differs from the Outer Cacheability attribute.
0b1	For the Non-secure PL1&0 translation regime, for permitted accesses to a memory location that use a common definition of the Shareability and Cacheability of the location, there might be a loss of coherency if the Inner Cacheability attribute for those accesses differs from the Outer Cacheability attribute.

For more information see 'Mismatched memory attributes' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section E2 (The AArch32 Application Level Memory Model).

This field can be implemented as RAZ/WI.

In a system where the PE resets into EL2 or EL3, this field resets to an architecturally UNKNOWN value.

TEA, bit [5]

Route synchronous External abort exceptions from EL0 and EL1 to EL2. If the RAS Extension is implemented, the possible values of this bit are:

TEA	Meaning
0b0	Does not route synchronous External abort exceptions from Non-secure EL0 and EL1 to EL2.
0b1	Route synchronous External abort exceptions from Non-secure EL0 and EL1 to EL2, if not routed to EL3.

When the RAS Extension is not implemented, this field is RES0.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

TERR, bit [4]

When RAS is implemented:

Trap Error record accesses from EL1 to EL2. Trap accesses to the following registers from EL1 to EL2:

ERRIDR, ERRSELR, ERXADDR, ERXADDR2, ERXCTLR, ERXCTLR2, ERXFR, ERXFR2, ERXMISC0, ERXMISC1, ERXMISC2, ERXMISC3, and ERXSTATUS. When ARMv8.4-RAS is implemented, ERXMISC4, ERXMISC5, ERXMISC6, and ERXMISC7.

TERR	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Accesses to the specified registers from EL1 generate a Trap exception to EL2.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

Otherwise:

Reserved, RES0.

Bits [3:2]

Reserved, RES0.

ID, bit [1]

Stage 2 Instruction access cacheability disable. For the Non-secure PL1&0 translation regime, when HCR.VM==1, this control forces all stage 2 translations for instruction accesses to Normal memory to be Non-cacheable.

ID	Meaning
0b0	This control has no effect on stage 2 of the Non-secure PL1&0 translation regime.
0b1	For the Non-secure PL1&0 translation regime, forces all stage 2 translations for instruction accesses to Normal memory to be Non-cacheable.

This bit has no effect on the EL2 translation regime.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to 0.

CD, bit [0]

Stage 2 Data access cacheability disable. When HCR.VM==1, this forces all stage 2 translations for data accesses and translation table walks to Normal memory to be Non-cacheable for the Non-secure PL1&0 translation regime.

CD	Meaning
0b0	This control has no effect on stage 2 of the Non-secure PL1&0 translation regime for data accesses and translation table walks.
0b1	For the Non-secure PL1&0 translation regime, forces all stage 2 translations for data accesses and translation table walks to Normal memory to be Non-cacheable.

This bit has no effect on the EL2 translation regime.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

Accessing the HCR2

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HCR2;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HCR2;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HCR2 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HCR2 = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HDCR, Hyp Debug Control Register

The HDCR characteristics are:

Purpose

Controls the trapping to Hyp mode of Non-secure accesses, at EL1 or lower, to functions provided by the debug and trace architectures and the Performance Monitors Extension.

Configuration

AArch32 System register HDCR bits [31:0] are architecturally mapped to AArch64 System register MDCR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HDCR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3, and other than for a direct read of the register, the PE behaves as if HDCR.HPMN == PMCR.N.

~~This register is in the Warm reset domain. Some or all RW fields of this register have defined reset values. On a Warm or Cold reset these apply only if the PE resets into EL2 with EL2 using AArch32, or into EL3 with EL3 using AArch32. Otherwise, on a Warm or Cold reset RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HDCR is a 32-bit register.

Field descriptions

The HDCR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0			MTPME	TDCC	HLP	RES0		HCCD	RES0			TTRF	RES0		HPMD	RES0				TDRA	TDOSA	TDA	TDE	HPME	TPM	TPMCR	HPMN				

Bits [31:29]

Reserved, RES0.

MTPME, bit [28]

When ARMv8.6-MTPMU is implemented and ~~!HaveEL(~~EL3 is not implemented~~:)~~:

Multi-threaded PMU Enable. Enables use of the PMEVTYPER<n>.MT bits.

MTPME	Meaning
0b0	ARMv8.6-MTPMU is disabled. The Effective value of PMEVTYPER<n>.MT is zero.
0b1	PMEVTYPER<n>.MT bits not affected by this bit.

If ARMv8.6-MTPMU is disabled for any other PE in the system that has the same level 1 Affinity as the PE, it is IMPLEMENTATION DEFINED whether the PE behaves as if this bit is 0.

On a Cold reset, in a system where the PE resets into EL2 or EL3, this field resets to 1.

Otherwise:

Reserved, RES0.

TDCC, bit [27]

When ARMv8.6-FGT is implemented:

Trap DCC. Traps use of the Debug Comms Channel at EL1 and EL0 to EL2.

TDCC	Meaning
0b0	This control does not cause any register accesses to be trapped.
0b1	If EL2 is implemented and enabled in the current Security state, accesses to the DCC registers at EL1 and EL0 generate a Hyp Trap exception, unless the access also generates a higher priority exception. Traps on the DCC data transfer registers are ignored when the PE is in Debug state.

The DCC registers trapped by this control are:

- DBGDTRRXext, DBGDTRTXext, DBGDSCRint, DBGDCCINT, and, when the PE is in Non-debug state, DBGDTRRXint and DBGDTRTXint.

The traps are reported with EC syndrome value:

- 0x05 for trapped MRC and MCR accesses with coproc == 0b1110.
- 0x06 for trapped LDC to DBGDTRTXint and STC from DBGDTRRXint.

When the PE is in Debug state, HDCR.TDCC does not trap any accesses to:

- DBGDTRRXint and DBGDTRTXint.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HLP, bit [26]

When ARMv8.5-PMU is implemented:

Hypervisor Long event counter enable. Determines when unsigned overflow is recorded by a counter overflow bit.

HLP	Meaning
0b0	Event counter overflow on increment that causes unsigned overflow of PMEVCNTR<n>[31:0].
0b1	Event counter overflow on increment that causes unsigned overflow of PMEVCNTR<n>[63:0].

If the highest implemented Exception level is using AArch32, it is IMPLEMENTATION DEFINED whether this bit is read/write or RAZ/WI.

If HDCR.HPMN is less than PMCR.N, this bit affects the operation of event counters in the range [HDCR.HPMN..(PMCR.N-1)]. Otherwise this bit has no effect on the operation of the event counters.

Note

The effect of HDCR.HPMN on the operation of this bit always applies if EL2 is implemented, at all Exception levels including EL2 and EL3, and regardless of whether EL2 is enabled in the current Security state.

For more information see the description of the HDCR.HPMN field.

Note

PMEVCNTR<n>[63:32] cannot be accessed directly in AArch32 state.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to `0`.

Otherwise:

Reserved, RES0.

Bits [25:24]

Reserved, RES0.

HCCD, bit [23]

When ARMv8.5-PMU is implemented:

Hypervisor Cycle Counter Disable. Prohibits PMCCNTR from counting at EL2.

HCCD	Meaning
`0b0`	Cycle counting by PMCCNTR is not affected by this bit.
`0b1`	Cycle counting by PMCCNTR is prohibited at EL2.

This bit does not affect the CPU_CYCLES event or any other event that counts cycles.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to `0`.

Otherwise:

Reserved, RES0.

Bits [22:20]

Reserved, RES0.

TTRF, bit [19]

When ARMv8.4-Trace is implemented:

Traps use of the Trace Filter Control registers at EL1 to EL2.

TTRF	Meaning
`0b0`	Accesses to TRFCR at EL1 are not affected by this control bit.
`0b1`	Accesses to TRFCR at EL1 generate a Hyp Trap exception.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to `0`.

Otherwise:

Reserved, RES0.

Bit [18]

Reserved, RES0.

HPMD, bit [17]

When ARMv8.1-PMU is implemented:

Guest Performance Monitors Disable. This control prohibits event counting at EL2.

HPMD	Meaning
0b0	Event counting allowed in Hyp mode.
0b1	Event counting prohibited in Hyp mode. If ARMv8.2-Debug is not implemented, event counting is prohibited unless enabled by the IMPLEMENTATION DEFINED authentication interface ExternalSecureNoninvasiveDebugEnabled().

This control applies only to:

- The event counters in the range [0..(HDCR.HPMN-1)].
- If PMCR.DP is set to 1, PMCCNTR.

The other event counters are unaffected. When PMCR.DP is set to 0, PMCCNTR is unaffected.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to 0.

Otherwise:

Reserved, RES0.

Bits [16:12]

Reserved, RES0.

TDRA, bit [11]

Trap Debug ROM Address register access. Traps Non-secure EL0 and EL1 System register accesses to the Debug ROM registers to Hyp mode.

TDRA	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL0 and EL1 System register accesses to the DBGDRAR or DBGDSAR are trapped to Hyp mode, unless it is trapped by DBGDSCRext.UDCCdis.

If HCR.TGE or HDCR.TDE is 1, behavior is as if this bit is 1 other than for the purpose of a direct read.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to 0.

TDOSA, bit [10]

When ARMv8.0-DoubleLock is implemented:

Trap debug OS-related register access. Traps Non-secure EL1 System register accesses to the powerdown debug registers to Hyp mode.

TDOSA	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL1 System register accesses to the powerdown debug registers are trapped to Hyp mode.

The registers for which accesses are trapped are as follows:

- DBGOSLSR, DBGOSLAR, DBGOSDLR, and DBGPRCR.
- Any IMPLEMENTATION DEFINED register with similar functionality that the implementation specifies as trapped by this bit.

Note

These registers are not accessible at EL0.

If HCR.TGE or HDCR.TDE is 1, behavior is as if this bit is 1 other than for the purpose of a direct read.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to `0`.

Otherwise:

Trap debug OS-related register access. Traps Non-secure EL1 System register accesses to the powerdown debug registers to Hyp mode.

TDOSA	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Non-secure EL1 System register accesses to the powerdown debug registers are trapped to Hyp mode.

The registers for which accesses are trapped are as follows:

- DBGOSLSR, DBGOSLAR, and DBGPRCR.
- Any IMPLEMENTATION DEFINED register with similar functionality that the implementation specifies as trapped by this bit.

It is IMPLEMENTATION DEFINED whether accesses to DBGOSDLR are trapped.

Note

These registers are not accessible at EL0.

If HCR.TGE or HDCR.TDE is 1, behavior is as if this bit is 1 other than for the purpose of a direct read.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to `0`.

TDA, bit [9]

Trap debug access. Traps Non-secure EL0 and EL1 System register accesses to those debug System registers in the (coproc==`0b1110`) encoding space that are not trapped by either of the following:

- HDCR.TDRA.
- HDCR.TDOSA.

TDA	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Non-secure EL0 or EL1 System register accesses to the debug registers, other than the registers trapped by HDCR.TDRA and HDCR.TDOSA, are trapped to Hyp mode, unless it is trapped by DBGDSCRext.UDCCdis.

Traps of AArch32 accesses to DBGDTRRXint and DBGDTRTXint are ignored in Debug state.

If HCR.TGE or HDCR.TDE is 1, behavior is as if this bit is 1 other than for the purpose of a direct read.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to `0`.

TDE, bit [8]

Trap Debug exceptions. The possible values of this bit are:

TDE	Meaning
`0b0`	This control has no effect on the routing of debug exceptions, and has no effect on Non-secure accesses to debug registers.
`0b1`	Debug exceptions generated at EL1 or EL0 are routed to EL2 when enabled in the current Security state. The HDCR.{TDRA, TDOSA, TDA} fields are treated as being 1 for all purposes other than returning the result of a direct read of the register.

When HCR.TGE == 1, the PE behaves as if the value of this field is 1 for all purposes other than returning the value of a direct read of the register.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to `0`.

HPME, bit [7]

When PMUv3 is implemented:

[HDCR.HPMN..(N-1)] event counters enable.

HPME	Meaning
`0b0`	Event counters in the range [HDCR.HPMN..(PMCR.N-1)] are disabled.
`0b1`	Event counters in the range [HDCR.HPMN..(PMCR.N-1)] are enabled by PMCNTENSET.

If HDCR.HPMN is less than PMCR.N, the event counters in the range [HDCR.HPMN..(PMCR.N-1)], are enabled and disabled by this bit. Otherwise this bit has no effect on the operation of the event counters.

Note

The effect of HDCR.HPMN on the operation of this bit applies regardless of whether EL2 is enabled in the current Security state.

For more information see the description of the HPMN field.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

TPM, bit [6]

When PMUv3 is implemented:

Trap Performance Monitors accesses. Traps Non-secure EL0 and EL1 accesses to all Performance Monitors registers to Hyp mode.

TPM	Meaning
`0b0`	This control does not cause any instructions to be trapped.
`0b1`	Non-secure EL0 and EL1 accesses to all Performance Monitors registers are trapped to Hyp mode.

Note

EL2 does not provide traps on Performance Monitor register accesses through the optional memory-mapped external debug interface.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to `0`.

Otherwise:

Reserved, RES0.

TPMCR, bit [5]

When PMUv3 is implemented:

Trap PMCR accesses. Traps Non-secure EL0 and EL1 accesses to the PMCR to Hyp mode.

TPMCR	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Non-secure EL0 and EL1 accesses to the PMCR are trapped to Hyp mode, unless it is trapped by PMUSERENR.EN.

Note

EL2 does not provide traps on Performance Monitor register accesses through the optional memory-mapped external debug interface.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to 0.

Otherwise:

Reserved, RES0.

HPMN, bits [4:0]

When PMUv3 is implemented:

Defines the number of event counters that are accessible from Non-secure EL1 modes, and from Non-secure EL0 modes if unprivileged access is enabled.

If HPMN is less than PMCR.N, HPMN divides the event counters into two ranges, [0..(HPMN-1)] and [HPMN..(PMCR.N-1)].

For an event counter in the range [0..(HPMN-1)]:

- The counter is accessible from EL1 and EL2, and from EL0 if unprivileged access to the counters is enabled.
- If ARMv8.5-PMU is implemented, PMCR.LP determines whether the counter overflows at PMEVCNTR<n>[31:0] or PMEVCNTR<n>[63:0].
- PMCR.E enables the operation of counters in this range.

Note

If HPMN is equal to PMCR.N, this applies to all event counters.

If HPMN is less than PMCR.N, for an event counter in the range [HPMN..(PMCR.N-1)]:

- The counter is accessible only from EL2 and from Secure state.
- If ARMv8.5-PMU is implemented, HDCR.HLP determines whether the counter overflows at PMEVCNTR<n>[31:0] or PMEVCNTR<n>[63:0].
- HDCR.HPME enables the operation of counters in this range.

If this field is set to 0, or to a value larger than PMCR.N, then the following CONSTRAINED UNPREDICTABLE behaviors apply:

- The value returned by a direct read of HDCR.HPMN is UNKNOWN.
- Either:
  - An UNKNOWN number of counters are reserved for EL2 use. That is, the PE behaves as if HDCR.HPMN is set to an UNKNOWN non-zero value less than or equal to PMCR.N.
  - All counters are reserved for EL2 use, meaning no counters are accessible from Non-secure EL1 and Non-secure EL0.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to the value in PMCR.N.

Otherwise:

Reserved, RES0.

Accessing the HDCR

Accesses to this register use the following encodings:

MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return HDCR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HDCR;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TDA == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        HDCR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HDCR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HDFAR, Hyp Data Fault Address Register

The HDFAR characteristics are:

Purpose

Holds the virtual address of the faulting address that caused a synchronous Data Abort exception that is taken to Hyp mode.

Configuration

AArch32 System register HDFAR bits [31:0] are architecturally mapped to AArch64 System register FAR_EL2[31:0] .

AArch32 System register HDFAR bits [31:0] are architecturally mapped to AArch32 System register DFAR[31:0] (S) when ~~HaveEL(~~EL2~~),~~ is implemented, ~~HaveEL(~~EL3~~)~~ is implemented and the highest implemented Exception level is using AArch32 state.~~HighestELUsingAArch32().~~

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HDFAR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HDFAR is a 32-bit register.

Field descriptions

The HDFAR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
VA of faulting address of synchronous Data Abort exception taken to Hyp mode																															

Bits [31:0]

VA of faulting address of synchronous Data Abort exception taken to Hyp mode.

On a Prefetch Abort exception, this register is UNKNOWN.

Any execution in a Non-secure EL1 or Non-secure EL0 mode makes this register UNKNOWN.

This field resets to an architecturally UNKNOWN value.

Accessing the HDFAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T6 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T6 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HDFAR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HDFAR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0110	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T6 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T6 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HDFAR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HDFAR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HIFAR, Hyp Instruction Fault Address Register

The HIFAR characteristics are:

Purpose

Holds the virtual address of the faulting address that caused a synchronous Prefetch Abort exception that is taken to Hyp mode.

Configuration

AArch32 System register HIFAR bits [31:0] are architecturally mapped to AArch64 System register FAR_EL2[63:32] .

AArch32 System register HIFAR bits [31:0] are architecturally mapped to AArch32 System register IFAR[31:0] (S) when ~~HaveEL(~~EL2~~),~~ is implemented, ~~HaveEL(~~EL3~~)~~ is implemented and the highest implemented Exception level is using AArch32 state.~~HighestELUsingAArch32().~~

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HIFAR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HIFAR is a 32-bit register.

Field descriptions

The HIFAR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
VA of faulting address of synchronous Prefetch Abort exception taken to Hyp mode																															

Bits [31:0]

VA of faulting address of synchronous Prefetch Abort exception taken to Hyp mode.

On a Data Abort exception, this register is UNKNOWN.

Any execution in a Non-secure EL1 or Non-secure EL0 mode makes this register UNKNOWN.

This field resets to an architecturally UNKNOWN value.

Accessing the HIFAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0110	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T6 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T6 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HIFAR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HIFAR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0110	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T6 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T6 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HIFAR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HIFAR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HMAIR0, Hyp Memory Attribute Indirection Register 0

The HMAIR0 characteristics are:

Purpose

Along with HMAIR1, provides the memory attribute encodings corresponding to the possible AttrIndx values in a Long-descriptor format translation table entry for stage 1 translations for memory accesses from Hyp mode.

AttrIndx[2] indicates the HMAIR register to be used:

- When AttrIndx[2] is 0, HMAIR0 is used.
- When AttrIndx[2] is 1, HMAIR1 is used.

Configuration

AArch32 System register HMAIR0 bits [31:0] are architecturally mapped to AArch64 System register MAIR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HMAIR0 are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HMAIR0 is a 32-bit register.

Field descriptions

The HMAIR0 bit assignments are:

When TTBCR.EAE == 1:



Attr<n>, bits [8n+7:8n], for n = 0 to 3

The memory attribute encoding for an AttrIndx[2:0] entry in a Long descriptor format translation table entry, where:

- AttrIndx[2:0] gives the value of <n> in Attr<n>.
- AttrIndx[2] defines which MAIR to access. Attr7 to Attr4 are in MAIR1, and Attr3 to Attr0 are in MAIR0.

Bits [7:4] are encoded as follows:

Attr<n>[7:4]	Meaning
0b0000	Device memory. See encoding of Attr<n>[3:0] for the type of Device memory.
0b00RW, RW not 0b00	Normal memory, Outer Write-Through Transient.
0b0100	Normal memory, Outer Non-cacheable.
0b01RW, RW not 0b00	Normal memory, Outer Write-Back Transient.
0b10RW	Normal memory, Outer Write-Through Non-transient.
0b11RW	Normal memory, Outer Write-Back Non-transient.

R = Outer Read-Allocate policy, W = Outer Write-Allocate policy.

The meaning of bits [3:0] depends on the value of bits [7:4]:

Attr<n>[3:0]	Meaning when Attr<n>[7:4] is 0b0000	Meaning when Attr<n>[7:4] is not 0b0000
0b0000	Device-nGnRnE memory	UNPREDICTABLE
0b00RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Through Transient
0b0100	Device-nGnRE memory	Normal memory, Inner Non-cacheable
0b01RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Back Transient
0b1000	Device-nGRE memory	Normal memory, Inner Write-Through Non-transient (RW=0b00)
0b10RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Through Non-transient
0b1100	Device-GRE memory	Normal memory, Inner Write-Back Non-transient (RW=0b00)
0b11RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Back Non-transient

R = Inner Read-Allocate policy, W = Inner Write-Allocate policy.

The R and W bits in some Attr<n> fields have the following meanings:

R or W	Meaning
0b0	No Allocate
0b1	Allocate

This field resets to an architecturally UNKNOWN value.

Accessing the HMAIR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HMAIR0;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HMAIR0;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HMAIR0 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HMAIR0 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HMAIR1, Hyp Memory Attribute Indirection Register 1

The HMAIR1 characteristics are:

Purpose

Along with HMAIR0, provides the memory attribute encodings corresponding to the possible AttrIndx values in a Long-descriptor format translation table entry for stage 1 translations for memory accesses from Hyp mode.

AttrIndx[2] indicates the HMAIR register to be used:

- When AttrIndx[2] is 0, HMAIR0 is used.
- When AttrIndx[2] is 1, HMAIR1 is used.

Configuration

AArch32 System register HMAIR1 bits [31:0] are architecturally mapped to AArch64 System register MAIR_EL2[63:32] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HMAIR1 are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HMAIR1 is a 32-bit register.

Field descriptions

The HMAIR1 bit assignments are:

When TTBCR.EAE == 1:



Attr<n>, bits [8(n-4)+7:8(n-4)], for n = 4 to 7

The memory attribute encoding for an AttrIndx[2:0] entry in a Long descriptor format translation table entry, where:

- AttrIndx[2:0] gives the value of <n> in Attr<n>.
- AttrIndx[2] defines which MAIR to access. Attr7 to Attr4 are in MAIR1, and Attr3 to Attr0 are in MAIR0.

Bits [7:4] are encoded as follows:

Attr<n>[7:4]	Meaning
0b0000	Device memory. See encoding of Attr<n>[3:0] for the type of Device memory.
0b00RW, RW not 0b00	Normal memory, Outer Write-Through Transient.
0b0100	Normal memory, Outer Non-cacheable.
0b01RW, RW not 0b00	Normal memory, Outer Write-Back Transient.
0b10RW	Normal memory, Outer Write-Through Non-transient.
0b11RW	Normal memory, Outer Write-Back Non-transient.

R = Outer Read-Allocate policy, W = Outer Write-Allocate policy.

The meaning of bits [3:0] depends on the value of bits [7:4]:

Attr<n>[3:0]	Meaning when Attr<n>[7:4] is 0b0000	Meaning when Attr<n>[7:4] is not 0b0000
0b0000	Device-nGnRnE memory	UNPREDICTABLE
0b00RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Through Transient
0b0100	Device-nGnRE memory	Normal memory, Inner Non-cacheable
0b01RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Back Transient
0b1000	Device-nGRE memory	Normal memory, Inner Write-Through Non-transient (RW=0b00)
0b10RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Through Non-transient
0b1100	Device-GRE memory	Normal memory, Inner Write-Back Non-transient (RW=0b00)
0b11RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Back Non-transient

R = Inner Read-Allocate policy, W = Inner Write-Allocate policy.

The R and W bits in some Attr<n> fields have the following meanings:

R or W	Meaning
0b0	No Allocate
0b1	Allocate

This field resets to an architecturally UNKNOWN value.

Accessing the HMAIR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1010	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HMAIR1;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HMAIR1;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1010	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HMAIR1 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HMAIR1 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HPFAR, Hyp IPA Fault Address Register

The HPFAR characteristics are:

Purpose

Holds the faulting IPA for some aborts on a stage 2 translation taken to Hyp mode.

Configuration

AArch32 System register HPFAR bits [31:0] are architecturally mapped to AArch64 System register HPFAR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HPFAR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HPFAR is a 32-bit register.

Field descriptions

The HPFAR bit assignments are:



Execution in any Non-secure mode other than Hyp mode makes this register UNKNOWN.

FIPA[39:12], bits [31:4]

Bits [39:12] of the faulting intermediate physical address.

This field resets to an architecturally UNKNOWN value.

Bits [3:0]

Reserved, RES0.

Accessing the HPFAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0110	0b0000	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T6 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T6 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HPFAR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HPFAR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0110	0b0000	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T6 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T6 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HPFAR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HPFAR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HRMR, Hyp Reset Management Register

The HRMR characteristics are:

Purpose

If EL2 is the highest implemented Exception level and this register is implemented:

- A write to the register at EL2 can request a Warm reset.
- If EL2 can use AArch32 and AArch64, this register specifies the Execution state that the PE boots into on a Warm reset.

Configuration

AArch32 System register HRMR bits [31:0] are architecturally mapped to AArch64 System register RMR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HRMR are UNKNOWN.

Only implemented if EL2 is the highest implemented Exception level. In this case:

- If EL2 can use AArch32 and AArch64 then this register must be implemented.
- If EL2 cannot use AArch64 then it is IMPLEMENTATION DEFINED whether the register is implemented.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HRMR is a 32-bit register.

Field descriptions

The HRMR bit assignments are:



Bits [31:2]

Reserved, RES0.

RR, bit [1]

Reset Request. Setting this bit to 1 requests a Warm reset.

This field resets to 0.

AA64, bit [0]

When EL2 can use AArch64, determines which Execution state the PE boots into after a Warm reset:

AA64	Meaning
0b0	AArch32.
0b1	AArch64.

On coming out of the Warm reset, execution starts at the IMPLEMENTATION DEFINED reset vector address of the specified Execution state.

If EL2 cannot use AArch64 this bit is RAZ/WI.

When implemented as a RW field, this field resets to 0 on a Cold reset.

Accessing the HRMR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b0000	0b010

```
if PSTATE.EL == EL1 && EL2Enabled() && IsHighestEL(EL2) && !ELUsingAArch32(EL2) && HSTR_EL2.T12 ==
'1' then
    AArch64.AArch32SystemAccessTrap(EL2, 0x03);
elsif PSTATE.EL == EL1 && EL2Enabled() && IsHighestEL(EL2) && ELUsingAArch32(EL2) && HSTR.T12 ==
'1' then
    AArch32.TakeHypTrapException(0x03);
elsif PSTATE.EL == EL2 && IsHighestEL(EL2) then
    return HRMR;
else
    UNDEFINED;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b0000	0b010

```
if PSTATE.EL == EL1 && EL2Enabled() && IsHighestEL(EL2) && !ELUsingAArch32(EL2) && HSTR_EL2.T12 ==
'1' then
    AArch64.AArch32SystemAccessTrap(EL2, 0x03);
elsif PSTATE.EL == EL1 && EL2Enabled() && IsHighestEL(EL2) && ELUsingAArch32(EL2) && HSTR.T12 ==
'1' then
    AArch32.TakeHypTrapException(0x03);
elsif PSTATE.EL == EL2 && IsHighestEL(EL2) then
    HRMR = R[t];
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HSCTLR, Hyp System Control Register

The HSCTLR characteristics are:

Purpose

Provides top level control of the system operation in Hyp mode.

Configuration

AArch32 System register HSCTLR bits [31:0] are architecturally mapped to AArch64 System register SCTLR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HSCTLR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 with EL2 using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HSCTLR is a 32-bit register.

Field descriptions

The HSCTLR bit assignments are:



DSSBS, bit [31]

When ARMv8.0-SSBS is implemented:

Default PSTATE.SSBS value on Exception Entry. The defined values are:

DSSBS	Meaning
0b0	PSTATE.SSBS is set to 0 on an exception to Hyp mode.
0b1	PSTATE.SSBS is set to 1 on an exception to Hyp mode.

In a system where the PE resets into EL2, this field resets to an IMPLEMENTATION DEFINED value.

Otherwise:

Reserved, RES0.

TE, bit [30]

T32 Exception Enable. This bit controls whether exceptions to EL2 are taken to A32 or T32 state:

TE	Meaning
0b0	Exceptions, including reset, taken to A32 state.
0b1	Exceptions, including reset, taken to T32 state.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Bits [29:28]

Reserved, RES1.

Bits [27:26]

Reserved, RES0.

EE, bit [25]

The value of the PSTATE.E bit on entry to Hyp mode, the endianness of stage 1 translation table walks in the EL2 translation regime, and the endianness of stage 2 translation table walks in the PL1&0 translation regime.

The possible values of this bit are:

EE	Meaning
0b0	Little-endian. PSTATE.E is cleared to 0 on entry to Hyp mode. Stage 1 translation table walks in the EL2 translation regime, and stage 2 translation table walks in the PL1&0 translation regime are little-endian.
0b1	Big-endian. PSTATE.E is set to 1 on entry to Hyp mode. Stage 1 translation table walks in the EL2 translation regime, and stage 2 translation table walks in the PL1&0 translation regime are big-endian.

If an implementation does not provide Big-endian support at Exception Levels higher than EL0, this bit is RES0.

If an implementation does not provide Little-endian support at Exception Levels higher than EL0, this bit is RES1.

In a system where the PE resets into EL2, this field resets to an IMPLEMENTATION DEFINED value.

Bit [24]

Reserved, RES0.

Bits [23:22]

Reserved, RES1.

Bits [21:20]

Reserved, RES0.

WXN, bit [19]

Write permission implies XN (Execute-never). For the EL2 translation regime, this bit can force all memory regions that are writable to be treated as XN. The possible values of this bit are:

WXN	Meaning
0b0	This control has no effect on memory access permissions.
0b1	Any region that is writable in the EL2 translation regime is forced to XN for accesses from software executing at EL2.

This bit applies only when HSCTLR.M bit is set.

The WXN bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Bit [18]

Reserved, RES1.

Bit [17]

Reserved, RES0.

Bit [16]

Reserved, RES1.

Bits [15:13]

Reserved, RES0.

I, bit [12]

Instruction access Cacheability control, for accesses at EL2:

I	Meaning
0b0	All instruction access to Normal memory from EL2 are Non-cacheable for all levels of instruction and unified cache. If the value of HSCTLR.M is 0, instruction accesses from stage 1 of the EL2 translation regime are to Normal, Outer Shareable, Inner Non-cacheable, Outer Non-cacheable memory.
0b1	All instruction access to Normal memory from EL2 can be cached at all levels of instruction and unified cache. If the value of HSCTLR.M is 0, instruction accesses from stage 1 of the EL2 translation regime are to Normal, Outer Shareable, Inner Write-Through, Outer Write-Through memory.

This bit has no effect on the PL1&0 translation regime.

In a system where the PE resets into EL2, this field resets to 0.

Bit [11]

Reserved, RES1.

Bits [10:9]

Reserved, RES0.

SED, bit [8]

SETEND instruction disable. Disables SETEND instructions at EL2.

SED	Meaning
0b0	SETEND instruction execution is enabled at EL2.
0b1	SETEND instructions are UNDEFINED at EL2.

If the implementation does not support mixed-endian operation at EL2, this bit is RES1.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

ITD, bit [7]

IT Disable. Disables some uses of IT instructions at EL2.

ITD	Meaning
0b0	All IT instruction functionality is enabled at EL2.
0b1	Any attempt at EL2 to execute any of the following is UNDEFINED: • All encodings of the IT instruction with hw1[3:0]!=1000. • All encodings of the subsequent instruction with the following values for hw1: ◦ 11xxxxxxxxxxxxxx: All 32-bit instructions, and the 16-bit instructions B, UDF, SVC, LDM, and STM. ◦ 1011xxxxxxxxxxxx: All instructions in Miscellaneous 16-bit instructions. ◦ 10100xxxxxxxxxxx: ADD Rd, PC, #imm ◦ 01001xxxxxxxxxxx: LDR Rd, [PC, #imm] ◦ 0100x1xxx1111xxx: ADD Rdn, PC; CMP Rn, PC; MOV Rd, PC; BX PC; BLX PC. ◦ 010001xx1xxxx111: ADD PC, Rm; CMP PC, Rm; MOV PC, Rm. This pattern also covers unpredictable cases with BLX Rn. These instructions are always UNDEFINED, regardless of whether they would pass or fail the condition code check that applies to them as a result of being in an IT block. It is IMPLEMENTATION DEFINED whether the IT instruction is treated as: • A 16-bit instruction, that can only be followed by another 16-bit instruction. • The first half of a 32-bit instruction. This means that, for the situations that are UNDEFINED, either the second 16-bit instruction or the 32-bit instruction is UNDEFINED. An implementation might vary dynamically as to whether IT is treated as a 16-bit instruction or the first half of a 32-bit instruction.

If an instruction in an active IT block that would be disabled by this field sets this field to 1 then behavior is CONSTRAINED UNPREDICTABLE. For more information see 'Changes to an ITD control by an instruction in an IT block' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section E1.2.4

ITD is optional, but if it is implemented in the SCTLR then it must also be implemented in the HSCTLR. If it is not implemented then this bit is RAZ/WI.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

Bit [6]

Reserved, RES0.

CP15BEN, bit [5]

System instruction memory barrier enable. Enables accesses to the DMB, DSB, and ISB System instructions in the (coproc==0b1111) encoding space from EL2:

CP15BEN	Meaning
0b0	EL2 execution of the CP15DMB, CP15DSB, and CP15ISB instructions is UNDEFINED.
0b1	EL2 execution of the CP15DMB, CP15DSB, and CP15ISB instructions is enabled.

CP15BEN is optional, but if it is implemented in the SCTLR then it must also be implemented in the HSCTLR. If it is not implemented then this bit is RAO/WI.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

LSMAOE, bit [4]

When ARMv8.2-LSMAOC is implemented:

Load Multiple and Store Multiple Atomicity and Ordering Enable.

LSMAOE	Meaning
0b0	For all memory accesses at EL2, A32 and T32 Load Multiple and Store Multiple can have an interrupt taken during the sequence memory accesses, and the memory accesses are not required to be ordered.
0b1	The ordering and interrupt behavior of A32 and T32 Load Multiple and Store Multiple at EL2 is as defined for Armv8.0.

This bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2, this field resets to 1.

Otherwise:

Reserved, RES1.

nTLSMD, bit [3]

When ARMv8.2-LSMAOC is implemented:

No Trap Load Multiple and Store Multiple to Device-nGRE/Device-nGnRE/Device-nGnRnE memory.

nTLSMD	Meaning
0b0	All memory accesses by A32 and T32 Load Multiple and Store Multiple at EL2 that are marked at stage 1 as Device-nGRE/Device-nGnRE/Device-nGnRnE memory are trapped and generate a stage 1 Alignment fault.
0b1	All memory accesses by A32 and T32 Load Multiple and Store Multiple at EL2 that are marked at stage 1 as Device-nGRE/Device-nGnRE/Device-nGnRnE memory are not trapped.

This bit is permitted to be cached in a TLB.

In a system where the PE resets into EL2, this field resets to 1.

Otherwise:

Reserved, RES1.

C, bit [2]

Cacheability control, for data accesses at EL2:

C	Meaning
0b0	All data access to Normal memory from EL2, and all accesses to the EL2 translation tables, are Non-cacheable for all levels of data and unified cache.
0b1	All data access to Normal memory from EL2, and all accesses to the EL2 translation tables, can be cached at all levels of data and unified cache.

This bit has no effect on the PL1&0 translation regime.

In a system where the PE resets into EL2, this field resets to 0.

A, bit [1]

Alignment check enable. This is the enable bit for Alignment fault checking at EL2:

A	Meaning
0b0	Alignment fault checking disabled when executing at EL2. Instructions that load or store one or more registers, other than load/store exclusive and load-acquire/store-release, do not check that the address being accessed is aligned to the size of the data element or data elements being accessed.
0b1	Alignment fault checking enabled when executing at EL2. All instructions that load or store one or more registers have an alignment check that the address being accessed is aligned to the size of the data element or data elements being accessed. If this check fails it causes an Alignment fault, which is taken as a Data Abort exception.

Load/store exclusive and load-acquire/store-release instructions have an alignment check regardless of the value of the A bit.

In a system where the PE resets into EL2, this field resets to an architecturally UNKNOWN value.

M, bit [0]

MMU enable for EL2 stage 1 address translation. Possible values of this bit are:

M	Meaning
0b0	EL2 stage 1 address translation disabled. See the HSCTLR.I field for the behavior of instruction accesses to Normal memory.
0b1	EL2 stage 1 address translation enabled.

In a system where the PE resets into EL2, this field resets to 0.

Accessing the HSCTLR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HSCTLR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HSCTLR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HSCTLR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HSCTLR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HSR, Hyp Syndrome Register

The HSR characteristics are:

Purpose

Holds syndrome information for an exception taken to Hyp mode.

Configuration

AArch32 System register HSR bits [31:0] are architecturally mapped to AArch64 System register ESR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HSR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HSR is a 32-bit register.

Field descriptions

The HSR bit assignments are:



Execution in any Non-secure PE mode other than Hyp mode makes this register UNKNOWN.

When an UNPREDICTABLE instruction is treated as UNDEFINED, and the exception is taken to EL2, the value of HSR is UNKNOWN. The value written to HSR must be consistent with a value that could be created as a result of an exception from the same Exception level that generated the exception as a result of a situation that is not UNPREDICTABLE at that Exception level, in order to avoid the possibility of a privilege violation.

EC, bits [31:26]

Exception Class. Indicates the reason for the exception that this register holds information about. Possible values of this field are:

EC	Meaning	ISS
0b000000	Unknown reason.	ISS encoding for exceptions with an unknown reason
0b000001	Trapped WFI or WFE instruction execution. Conditional WFE and WFI instructions that fail their condition code check do not cause an exception.	ISS encoding for Exception from a WFI or WFE instruction
0b000011	Trapped MCR or MRC access with (coproc==0b1111) that is not reported using EC 0b000000.	ISS encoding for Exception from an MCR or MRC access
0b000100	Trapped MCRR or MRRC access with (coproc==0b1111) that is not reported using EC 0b000000.	ISS encoding for Exception from an MCRR or MRRC access
0b000101	Trapped MCR or MRC access with (coproc==0b1110).	ISS encoding for Exception from an MCR or MRC access
0b000110	Trapped LDC or STC access. The only architected uses of these instructions are: • An STC to write data to memory from DBGDTRRXint. • An LDC to read data from memory to DBGDTRTXint.	ISS encoding for Exception from an LDC or STC instruction
0b000111	Access to Advanced SIMD or floating-point functionality trapped by a HCPTR.{TASE, TCP10} control. Excludes exceptions generated because Advanced SIMD and floating-point are not implemented. These are reported with EC value 0b000000.	ISS encoding for Exception from an access to SIMD or floating-point functionality, resulting from HCPTR
0b001000	Trapped VMRS access, from ID group trap, that is not reported using EC 0b000111.	ISS encoding for Exception from an MCR or MRC access
0b001100	Trapped MRRC access with (coproc==0b1110).	ISS encoding for Exception from an MCRR or MRRC access
0b001110	Illegal exception return to AArch32 state.	ISS encoding for Exception from an Illegal state or PC alignment fault
0b010001	Exception on SVC instruction execution in AArch32 state routed to EL2.	ISS encoding for Exception from HVC or SVC instruction execution
0b010010	HVC instruction execution in AArch32 state, when HVC is not disabled.	ISS encoding for Exception from HVC or SVC instruction execution
0b010011	Trapped execution of SMC instruction in AArch32 state.	ISS encoding for Exception from SMC instruction execution
0b100000	Prefetch Abort from a lower Exception level.	ISS encoding for Exception from a Prefetch Abort
0b100001	Prefetch Abort taken without a change in Exception level.	ISS encoding for Exception from a Prefetch Abort
0b100010	PC alignment fault exception.	ISS encoding for Exception from an Illegal state or PC alignment fault

0b100100	Data Abort from a lower Exception level.	ISS encoding for Exception from a Data Abort
0b100101	Data Abort taken without a change in Exception level.	ISS encoding for Exception from a Data Abort

All other EC values are reserved by Arm, and:

- Unused values in the range 0b000000 - 0b101100 (0x00 - 0x2C) are reserved for future use for synchronous exceptions.
- Unused values in the range 0b101101 - 0b111111 (0x2D - 0x3F) are reserved for future use, and might be used for synchronous or asynchronous exceptions.

The effect of programming this field to a reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Reserved values in System and memory-mapped registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.2.2.

This field resets to an architecturally UNKNOWN value.

IL, bit [25]

Instruction length bit. Indicates the size of the instruction that has been trapped to Hyp mode. When this bit is valid, possible values of this bit are:

IL	Meaning
0b0	16-bit instruction trapped.
0b1	32-bit instruction trapped.

This field is RES1 and not valid for the following cases:

- When the EC field is 0b000000, indicating an exception with an unknown reason.
- Prefetch Aborts.
- Data Aborts for which the HSR.ISS.ISV field is 0.
- When the EC value is 0b001110, indicating an Illegal state exception.

Note

This is a change from the behavior in Armv7, where the IL field is UNK/SBZP for the corresponding cases.

The IL field is not valid and is UNKNOWN on an exception from a PC alignment fault.

This field resets to an architecturally UNKNOWN value.

ISS, bits [24:0]

Instruction Specific Syndrome. Architecturally, this field can be defined independently for each defined Exception class. However, in practice, some ISS encodings are used for more than one Exception class.

ISS encoding for exceptions with an unknown reason



Bits [24:0]

Reserved, RES0.

This EC code is used for all exceptions that are not covered by any other EC value. This includes exceptions that are generated in the following situations:

- The attempted execution of an instruction bit pattern that has no allocated instruction or is not accessible in the current PE mode in the current Security state, including:

        - A read access using a System register encoding pattern that is not allocated for reads or that does not permit reads in the current PE mode and Security state.
        - A write access using a System register encoding pattern that is not allocated for writes or that does not permit writes in the current PE mode and Security state.
        - Instruction encodings that are unallocated.
        - Instruction encodings for instructions not implemented in the implementation.
    - In Debug state, the attempted execution of an instruction bit pattern that not accessible in Debug state.
    - In Non-debug state, the attempted execution of an instruction bit pattern that not accessible in Non-debug state.
    - The attempted execution of a short vector floating-point instruction.
    - In an implementation that does not include Advanced SIMD and floating-point functionality, an attempted access to Advanced SIMD or floating-point functionality under conditions where that access would be permitted if that functionality was present. This includes the attempted execution of an Advanced SIMD or floating-point instruction, and attempted accesses to Advanced SIMD and floating-point System registers.
    - An exception generated because of the value of one of the SCTLR.{ITD, SED, CP15BEN} control bits.
    - Attempted execution of:
        - An HVC instruction when disabled by HCR.HCD, SCR.HCE, or SCR_EL3.HCE.
        - An SMC instruction when disabled by SCR.SCD or SCR_EL3.SMD.
        - An HLT instruction when disabled by EDSCR.HDE.
    - An HVC instruction when disabled by HCR.HCD, SCR.HCE, or SCR_EL3.HCE.An SMC instruction when disabled by SCR.SCD or SCR_EL3.SMD.An HLT instruction when disabled by EDSCR.HDE.
    - An exception generated because of the attempted execution of an MSR (Banked register) or MRS (Banked register) instruction that would access a Banked register that is not accessible from the Security state and PE mode at which the instruction was executed.

An exception is generated only if the CONSTRAINED UNPREDICTABLE behavior of the instruction is that it is UNDEFINED, see 'MSR/MRS Banked registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.1.29 (CONSTRAINED UNPREDICTABLE behavior of EL2 features).

- Attempted execution, in Debug state, of:
    - A DCPS1 instruction in Non-secure state from EL0 when EL2 is using AArch32 and the value of HCR.TGE is 1.
    - A DCPS2 instruction at EL1 or EL0 when EL2 is not implemented, or when EL3 is using AArch32 and the value of SCR.NS is 0, or when EL3 is using AArch64 and the value of SCR_EL3.NS is 0.
    - A DCPS3 instruction when EL3 is not implemented, or when the value of EDSCR.SDD is 1.
- In Debug state when the value of EDSCR.SDD is 1, the attempted execution at EL2, EL1, or EL0 of an instruction that is configured to trap to EL3.

'Undefined Instruction exception, when HCR.TGE is set to 1' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model), describes the configuration settings for a trap that returns an HSR.EC value of `0b000000`.

ISS encoding for Exception from a WFI or WFE instruction



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
`0b0`	The COND field is not valid.
`0b1`	The COND field is valid.

When an A32 instruction is trapped, CV is set to 1.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

The condition code for the trapped instruction.

When an A32 instruction is trapped, CV is set to 1 and:

- If the instruction is conditional, COND is set to the condition code field value from the instruction.
- If the instruction is unconditional, COND is set to `0b1110`.

A conditional A32 instruction that is known to pass its condition code check can be presented either:

- With COND set to `0b1110`, the value for unconditional.
- With the COND value held in the instruction.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:

- CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
- CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.

For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Bits [19:1]

Reserved, RES0.

TI, bit [0]

Trapped instruction. Possible values of this bit are:

TI	Meaning
`0b0`	WFI trapped.
`0b1`	WFE trapped.

This field resets to an architecturally UNKNOWN value.

'Trapping use of the WFI and WFE instructions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model), describes the configuration settings for this trap.

ISS encoding for Exception from an MCR or MRC access



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
`0b0`	The COND field is not valid.
`0b1`	The COND field is valid.

When an A32 instruction is trapped, CV is set to 1.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

The condition code for the trapped instruction.

When an A32 instruction is trapped, CV is set to 1 and:

- If the instruction is conditional, COND is set to the condition code field value from the instruction.
- If the instruction is unconditional, COND is set to `0b1110`.

A conditional A32 instruction that is known to pass its condition code check can be presented either:

- With COND set to `0b1110`, the value for unconditional.
- With the COND value held in the instruction.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:

- CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
- CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.

For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Opc2, bits [19:17]

The Opc2 value from the issued instruction.

For a trapped VMRS access, holds the value `0b000`.

This field resets to an architecturally UNKNOWN value.

Opc1, bits [16:14]

The Opc1 value from the issued instruction.

For a trapped VMRS access, holds the value `0b111`.

This field resets to an architecturally UNKNOWN value.

CRn, bits [13:10]

The CRn value from the issued instruction.

For a trapped VMRS access, holds the reg field from the VMRS instruction encoding.

This field resets to an architecturally UNKNOWN value.

Bit [9]

Reserved, RES0.

Rt, bits [8:5]

The Rt value from the issued instruction, the general-purpose register used for the transfer.

This field resets to an architecturally UNKNOWN value.

CRm, bits [4:1]

The CRm value from the issued instruction.

For a trapped VMRS access, holds the value `0b0000`.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
`0b0`	Write to System register space. MCR instruction.
`0b1`	Read from System register space. MRC or VMRS instruction.

This field resets to an architecturally UNKNOWN value.

The following sections describe configuration settings for traps that are reported using EC value `0b000011`:

- 'Traps to Hyp mode of Non-secure EL0 and EL1 accesses to the ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model).
- 'Traps to Hyp mode of Non-secure EL0 and EL1 accesses to lockdown, DMA, and TCM operations' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Traps to Hyp mode of Non-secure EL1 execution of cache maintenance instructions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Traps to Hyp mode of Non-secure EL1 execution of TLB maintenance instructions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Traps to Hyp mode of Non-secure EL1 accesses to the Auxiliary Control Register' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Traps to Hyp mode of Non-secure EL0 and EL1 accesses to Performance Monitors registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Traps to Hyp mode of Non-secure EL0 and EL1 accesses to Activity Monitors registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Traps to Hyp mode of Non-secure EL1 accesses to the CPACR' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Traps to Hyp mode of Non-secure EL1 accesses to virtual memory control registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'General trapping to Hyp mode of Non-secure EL0 and EL1 accesses to System registers in the (coproc == 1111) encoding space' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.

The following sections describe configuration settings for traps that are reported using EC value `0b000101`:

- 'ID group 0, Primary device identification registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Traps to Hyp mode of Non-secure System register accesses to trace registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Trapping Non-secure System register accesses to Debug ROM registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Trapping Non-secure System register accesses to powerdown debug registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Trapping general Non-secure System register accesses to debug registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.

The following sections describes configuration settings for traps that are reported using EC value `0b001000`:

- 'ID group 0, Primary device identification registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'ID group 3, Detailed feature identification registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.

ISS encoding for Exception from an MCRR or MRRC access



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

When an A32 instruction is trapped, CV is set to 1.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

The condition code for the trapped instruction.

When an A32 instruction is trapped, CV is set to 1 and:

- If the instruction is conditional, COND is set to the condition code field value from the instruction.
- If the instruction is unconditional, COND is set to 0b1110.

A conditional A32 instruction that is known to pass its condition code check can be presented either:

- With COND set to 0b1110, the value for unconditional.
- With the COND value held in the instruction.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:

- CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
- CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.

For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to 0b1110, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Opc1, bits [19:16]

The Opc1 value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Bits [15:14]

Reserved, RES0.

Rt2, bits [13:10]

The Rt2 value from the issued instruction, the second general-purpose register used for the transfer.

This field resets to an architecturally UNKNOWN value.

Bit [9]

Reserved, RES0.

Rt, bits [8:5]

The Rt value from the issued instruction, the first general-purpose register used for the transfer.

This field resets to an architecturally UNKNOWN value.

CRm, bits [4:1]

The CRm value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
0b0	Write to System register space. MCRR instruction.
0b1	Read from System register space. MRRC instruction.

This field resets to an architecturally UNKNOWN value.

The following sections describe configuration settings for traps that are reported using EC value 0b000100:

- 'Traps to Hyp mode of Non-secure EL1 accesses to virtual memory control registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model).
- 'Traps to Hyp mode of Non-secure EL0 and EL1 accesses to Performance Monitors registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Traps to Hyp mode of Non-secure EL0 and EL1 accesses to Activity Monitors registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Traps to Hyp mode of Non-secure EL0 and EL1 accesses to the Generic Timer registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'General trapping to Hyp mode of Non-secure EL0 and EL1 accesses to System registers in the (coproc == 1111) encoding space' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.

The following sections describe configuration settings for traps that are reported using EC value 0b001100:

- 'Traps to Hyp mode of Non-secure System register accesses to trace registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Trapping Non-secure System register accesses to Debug ROM registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.

ISS encoding for Exception from an LDC or STC instruction



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

When an A32 instruction is trapped, CV is set to 1.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

The condition code for the trapped instruction.

When an A32 instruction is trapped, CV is set to 1 and:

- If the instruction is conditional, COND is set to the condition code field value from the instruction.
- If the instruction is unconditional, COND is set to `0b1110`.

A conditional A32 instruction that is known to pass its condition code check can be presented either:

- With COND set to `0b1110`, the value for unconditional.
- With the COND value held in the instruction.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:

- CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
- CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.

For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

imm8, bits [19:12]

The immediate value from the issued instruction.

This field resets to an architecturally UNKNOWN value.

Bits [11:9]

Reserved, RES0.

Rn, bits [8:5]

The Rn value from the issued instruction. Valid only when AM[2] is 0, indicating an immediate form of the LDC or STC instruction.

When AM[2] is 1, indicating a literal form of the LDC or STC instruction, this field is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

Offset, bit [4]

Indicates whether the offset is added or subtracted:

Offset	Meaning
`0b0`	Subtract offset.
`0b1`	Add offset.

This bit corresponds to the U bit in the instruction encoding.

This field resets to an architecturally UNKNOWN value.

AM, bits [3:1]

Addressing mode. The permitted values of this field are:

AM	Meaning
0b000	Immediate unindexed.
0b001	Immediate post-indexed.
0b010	Immediate offset.
0b011	Immediate pre-indexed.
0b100	Literal unindexed. LDC instruction in A32 instruction set only. For a trapped STC instruction or a trapped T32 LDC instruction this encoding is reserved.
0b110	Literal offset. LDC instruction only. For a trapped STC instruction, this encoding is reserved.

The values 0b101 and 0b111 are reserved. The effect of programming this field to a reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Unallocated values in fields of AArch32 System registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.1.11.

Bit [2] in this subfield indicates the instruction form, immediate or literal.

Bits [1:0] in this subfield correspond to the bits {P, W} in the instruction encoding.

This field resets to an architecturally UNKNOWN value.

Direction, bit [0]

Indicates the direction of the trapped instruction. The possible values of this bit are:

Direction	Meaning
0b0	Write to memory. STC instruction.
0b1	Read from memory. LDC instruction.

This field resets to an architecturally UNKNOWN value.

'Trapping general Non-secure System register accesses to debug registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 describes the configuration settings for the trap that is reported using EC value 0b000110.

ISS encoding for Exception from an access to SIMD or floating-point functionality, resulting from HCPTR



Excludes exceptions that occur because Advanced SIMD and floating-point functionality is not implemented, or because the value of HCR.TGE or HCR_EL2.TGE is 1. These are reported with EC value 0b000000.

CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
0b0	The COND field is not valid.
0b1	The COND field is valid.

When an A32 instruction is trapped, CV is set to 1.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

The condition code for the trapped instruction.

When an A32 instruction is trapped, CV is set to 1 and:

- If the instruction is conditional, COND is set to the condition code field value from the instruction.
- If the instruction is unconditional, COND is set to `0b1110`.

A conditional A32 instruction that is known to pass its condition code check can be presented either:

- With COND set to `0b1110`, the value for unconditional.
- With the COND value held in the instruction.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:

- CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
- CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.

For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field resets to an architecturally UNKNOWN value.

Bits [19:6]

Reserved, RES0.

TA, bit [5]

Indicates trapped use of Advanced SIMD functionality. The possible values of this bit are:

TA	Meaning
`0b0`	Exception was not caused by trapped use of Advanced SIMD functionality.
`0b1`	Exception was caused by trapped use of Advanced SIMD functionality.

Any use of an Advanced SIMD instruction that is not also a floating-point instruction that is trapped to Hyp mode because of a trap configured in the HCPTR sets this bit to 1.

For a list of these instructions, see 'Controls of Advanced SIMD operation that do not apply to floating-point operation' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section E1.

This field resets to an architecturally UNKNOWN value.

Bit [4]

Reserved, RES0.

coproc, bits [3:0]

When the TA field returns the value 1, this field returns the value `1010`, otherwise this field is RES0.

This field resets to an architecturally UNKNOWN value.

The following sections describe the configuration settings for the traps that are reported using EC value `0b000111`:

- 'General trapping to Hyp mode of Non-secure accesses to the SIMD and floating-point registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model).
- 'Traps to Hyp mode of Non-secure accesses to Advanced SIMD functionality' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.

ISS encoding for Exception from HVC or SVC instruction execution



Bits [24:16]

Reserved, RES0.

imm16, bits [15:0]

The value of the immediate field from the HVC or SVC instruction.

For an HVC instruction, this is the value of the imm16 field of the issued instruction.

For an SVC instruction:

- If the instruction is unconditional, then:
  - For the T32 instruction, this field is zero-extended from the imm8 field of the instruction.
  - For the A32 instruction, this field is the bottom 16 bits of the imm24 field of the instruction.
- For the T32 instruction, this field is zero-extended from the imm8 field of the instruction.For the A32 instruction, this field is the bottom 16 bits of the imm24 field of the instruction.
- If the instruction is conditional, this field is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

The HVC instruction is unconditional, and a conditional SVC instruction generates an exception only if it passes its condition code check. Therefore, the syndrome information for these exceptions does not require conditionality information.

'Supervisor Call exception, when HCR.TGE is set to 1' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model), describes the configuration settings for the trap reported with EC value `0b010001`.

ISS encoding for Exception from SMC instruction execution



CV, bit [24]

Condition code valid. Possible values of this bit are:

CV	Meaning
`0b0`	The COND field is not valid.
`0b1`	The COND field is valid.

When an A32 instruction is trapped, CV is set to 1.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether CV is set to 1 or set to 0. See the description of the COND field for more information.

This field is only valid if CCKNOWNPASS is 1, otherwise it is RES0.

This field resets to an architecturally UNKNOWN value.

COND, bits [23:20]

The condition code for the trapped instruction.

When an A32 instruction is trapped, CV is set to 1 and:

- If the instruction is conditional, COND is set to the condition code field value from the instruction.
- If the instruction is unconditional, COND is set to `0b1110`.

A conditional A32 instruction that is known to pass its condition code check can be presented either:

- With COND set to `0b1110`, the value for unconditional.
- With the COND value held in the instruction.

When a T32 instruction is trapped, it is IMPLEMENTATION DEFINED whether:

- CV is set to 0 and COND is set to an UNKNOWN value. Software must examine the SPSR.IT field to determine the condition, if any, of the T32 instruction.
- CV is set to 1 and COND is set to the condition code for the condition that applied to the instruction.

For an implementation that, for both A32 and T32 instructions, takes an exception on a trapped conditional instruction only if the instruction passes its condition code check, these definitions mean that when CV is set to 1 it is IMPLEMENTATION DEFINED whether the COND field is set to `0b1110`, or to the value of any condition that applied to the instruction.

This field is only valid if CCKNOWNPASS is 1, otherwise it is RES0.

This field resets to an architecturally UNKNOWN value.

CCKNOWNPASS, bit [19]

Indicates whether the instruction might have failed its condition code check.

CCKNOWNPASS	Meaning
`0b0`	The instruction was unconditional, or was conditional and passed its condition code check.
`0b1`	The instruction was conditional, and might have failed its condition code check.

This field resets to an architecturally UNKNOWN value.

Bits [18:0]

Reserved, RES0.

'Traps to Hyp mode of Non-secure EL1 execution of SMC instructions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model), describes the configuration settings for this trap, for instructions executed in Non-secure EL1.

ISS encoding for Exception from a Prefetch Abort



Bits [24:11]

Reserved, RES0.

FnV, bit [10]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
`0b0`	HIFAR is valid.
`0b1`	HIFAR is not valid, and holds an UNKNOWN value.

This field is only valid if the IFSC code is `0b010000`. It is RES0 for all other aborts.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

External abort type. This bit can provide an IMPLEMENTATION DEFINED classification of External aborts.

For any abort other than an External abort this bit returns a value of 0.

This field resets to an architecturally UNKNOWN value.

Bit [8]

Reserved, RES0.

S1PTW, bit [7]

For a stage 2 fault, indicates whether the fault was a stage 2 fault on an access made for a stage 1 translation table walk:

S1PTW	Meaning
0b0	Fault not on a stage 2 translation for a stage 1 translation table walk.
0b1	Fault on the stage 2 translation of an access for a stage 1 translation table walk.

For any abort other than a stage 2 fault this bit is RES0.

This field resets to an architecturally UNKNOWN value.

Bit [6]

Reserved, RES0.

IFSC, bits [5:0]

Instruction Fault Status Code. Possible values of this field are:

IFSC	Meaning	Applies when
0b000000	Address size fault in, translation table base register.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk.	
0b010101	Synchronous External abort, on translation table walk, level 1.	
0b010110	Synchronous External abort, on translation table walk, level 2.	
0b010111	Synchronous External abort, on translation table walk, level 3.	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk, level 1.	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk, level 2.	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk, level 3.	When RAS is not implemented
0b100010	Debug exception.	
0b110000	TLB conflict abort.	

All other values are reserved.

When the RAS Extension is implemented, 0b011000, 0b011101, 0b011110, and 0b011111, are reserved.

Note

Armv8.2 requires the implementation of the RAS Extension.

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults on a Long-descriptor translation table lookup' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

If the S1PTW bit is set, then the level refers the level of the stage2 translation that is translating a stage 1 translation walk.

This field resets to an architecturally UNKNOWN value.

The following sections describe cases where Prefetch Abort exceptions can be routed to Hyp mode, generating exceptions that are reported in the HSR with EC value 0b100000:

- 'Abort exceptions, when HCR.TGE is set to 1' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model).
- 'Routing Debug exceptions to Hyp mode' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.

ISS encoding for Exception from an Illegal state or PC alignment fault



Bits [24:0]

Reserved, RES0.

For more information about the Illegal state exception, see:

- 'Illegal changes to PSTATE.M' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model).
- 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'Legal exception returns that set PSTATE.IL to 1' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.
- 'The Illegal Execution state exception' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.

For more information about the PC alignment fault exception, see 'Branching to an unaligned PC' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, appendix A.

ISS encoding for Exception from a Data Abort



ISV, bit [24]

Instruction syndrome valid. Indicates whether the syndrome information in ISS[23:14] is valid.

ISV	Meaning
0b0	No valid instruction syndrome. ISS[23:14] are RES0.
0b1	ISS[23:14] hold a valid instruction syndrome.

This bit is 0 for all faults except Data Aborts generated by stage 2 address translations for which all the following apply to the instruction that generated the Data Abort exception:

- The instruction is an LDR, LDA, LDRT, LDRSH, LDRSHT, LDRH, LDAH, LDRHT, LDRSB, LDRSBT, LDRB, LDAB, LDRBT, STR, STL, STRT, STRH, STLH, STRHT, STRB, STLB, or STRBT instruction.
- The instruction is not performing register writeback.
- The instruction is not using the PC as a source or destination register.

For these cases, ISV is UNKNOWN if the exception was generated in Debug state in memory access mode, as described in 'Data Aborts in Memory access mode' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H4.3.2 (Memory access mode), and otherwise indicates whether ISS[23:14] hold a valid syndrome.

Note

In the A32 instruction set, LDR*T and STR*T instructions always perform register writeback and therefore never return a valid instruction syndrome.

When the RAS Extension is implemented, ISV is 0 for any synchronous External abort.

ISV is set to 0 on a stage 2 abort on a stage 1 translation table walk.

When the RAS Extension is not implemented, it is IMPLEMENTATION DEFINED whether ISV is set to 1 or 0 on a synchronous External abort on a stage 2 translation table walk.

This field resets to an architecturally UNKNOWN value.

SAS, bits [23:22]

Syndrome Access Size. When ISV is 1, indicates the size of the access attempted by the faulting operation.

SAS	Meaning
0b00	Byte
0b01	Halfword
0b10	Word
0b11	Doubleword

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

SSE, bit [21]

Syndrome Sign Extend. When ISV is 1, for a byte, halfword, or word load operation, indicates whether the data item must be sign extended. For these cases, the possible values of this bit are:

SSE	Meaning
0b0	Sign-extension not required.
0b1	Data item must be sign-extended.

For all other operations this bit is 0.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

Bit [20]

Reserved, RES0.

SRT, bits [19:16]

Syndrome Register transfer. When ISV is 1, the register number of the Rt operand of the faulting instruction.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

Bit [15]

Reserved, RES0.

AR, bit [14]

Acquire/Release. When ISV is 1, the possible values of this bit are:

AR	Meaning
0b0	Instruction did not have acquire/release semantics.
0b1	Instruction did have acquire/release semantics.

This field is UNKNOWN when the value of ISV is UNKNOWN.

This field is RES0 when the value of ISV is 0.

This field resets to an architecturally UNKNOWN value.

Bits [13:12]

Reserved, RES0.

AET, bits [11:10]

When RAS is implemented:

Asynchronous Error Type.

When the RAS Extension is implemented and the value returned in the DFSC field is `0b010001`, describes the state of the PE after taking the SError interrupt exception. The possible values of this field are:

AET	Meaning
`0b00`	Uncontainable error (UC) or uncategorized.
`0b01`	Unrecoverable error (UEU).
`0b10`	Restartable error (UEO) or Corrected error (CE).
`0b11`	Recoverable error (UER).

On a synchronous Data Abort, this field is RES0.

If multiple errors are taken as a single SError interrupt exception, the overall state of the PE is reported. For example, if both a Recoverable and Unrecoverable error occurred, the state is Unrecoverable.

Note

Software can use this information to determine what recovery might be possible. The recovery software must also examine any implemented fault records to determine the location and extent of the error.

When the RAS Extension is not implemented, or when DFSC is not `0b010001`:

- Bit[11] is RES0.
- Bit[10] forms the FnV field.

Note

Armv8.2 requires the implementation of the RAS Extension.

This field resets to an architecturally UNKNOWN value.

Otherwise:

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
`0b0`	HDFAR is valid.
`0b1`	HDFAR is not valid, and holds an UNKNOWN value.

When the RAS Extension is not implemented, this field is valid only if DFSC is `0b010000`. It is RES0 for all other aborts.

When the RAS Extension is implemented:

- If DFSC is `0b010000`, this field is valid.
- If DFSC is `0b010001`, this bit forms part of the AET field, becoming AET[0].
- This field is RES0 for all other aborts.

Note

Armv8.2 requires the implementation of the RAS Extension.

This field resets to an architecturally UNKNOWN value.

EA, bit [9]

External abort type. This bit can provide an IMPLEMENTATION DEFINED classification of External aborts.

For any abort other than an External abort this bit returns a value of 0.

This field resets to an architecturally UNKNOWN value.

CM, bit [8]

Cache maintenance. For a synchronous fault, identifies fault that comes from a cache maintenance or address translation instruction. For synchronous faults, the possible values of this bit are:

CM	Meaning
0b0	Fault not generated by a cache maintenance or address translation instruction.
0b1	Fault generated by a cache maintenance or address translation instruction.

For an asynchronous Data Abort exception, this bit is 0.

This field resets to an architecturally UNKNOWN value.

S1PTW, bit [7]

For a stage 2 fault, indicates whether the fault was a stage 2 fault on an access made for a stage 1 translation table walk:

S1PTW	Meaning
0b0	Fault not on a stage 2 translation for a stage 1 translation table walk.
0b1	Fault on the stage 2 translation of an access for a stage 1 translation table walk.

For any abort other than a stage 2 fault this bit is RES0.

This field resets to an architecturally UNKNOWN value.

WnR, bit [6]

Write not Read. Indicates whether a synchronous abort was caused by a write instruction or a read instruction. The possible values of this bit are:

WnR	Meaning
0b0	Abort caused by a read instruction.
0b1	Abort caused by a write instruction.

For faults on cache maintenance and address translation instructions, this bit always returns a value of 1.

On an asynchronous Data Abort:

- When the RAS Extension is not implemented, this bit is UNKNOWN.
- When the RAS Extension is implemented, this bit is RES0.

Note

Armv8.2 requires the implementation of the RAS Extension.

This field resets to an architecturally UNKNOWN value.

DFSC, bits [5:0]

Data Fault Status Code. Possible values of this field are:

DFSC	Meaning	Applies when
0b000000	Address size fault in, translation table base register.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk.	
0b010001	Asynchronous SError interrupt.	
0b010101	Synchronous External abort, on translation table walk, level 1.	
0b010110	Synchronous External abort, on translation table walk, level 2.	
0b010111	Synchronous External abort, on translation table walk, level 3.	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011001	Asynchronous SError interrupt, from a parity or ECC error on memory access.	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk, level 1.	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk, level 2.	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk, level 3.	When RAS is not implemented
0b100001	Alignment fault.	
0b100010	Debug exception.	
0b110000	TLB conflict abort.	
0b110100	IMPLEMENTATION DEFINED fault (Lockdown).	
0b110101	IMPLEMENTATION DEFINED fault (Unsupported Exclusive access).	

All other values are reserved.

~~When the RAS Extension is implemented, 0b011000, 0b011001, 0b011101, 0b011110, and 0b011111, are reserved.~~

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults on a Long-descriptor translation table lookup' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

If the S1PTW bit is set, then the level refers the level of the stage2 translation that is translating a stage 1 translation walk.

This field resets to an architecturally UNKNOWN value.

The following describe cases where Data Abort exceptions can be routed to Hyp mode, generating exceptions that are reported in the HSR with EC value 0b100100:

- 'Abort exceptions, when HCR.TGE is set to 1' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model).
- 'Routing Debug exceptions to EL2' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.

The following describe cases that can cause a Data Abort exception that is taken to Hyp mode, and reported in the HSR with EC value of `0b100000` or `0b100100`:

- 'Hyp mode control of Non-secure access permissions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1 (The AArch32 System Level Programmers' Model).
- 'Memory fault reporting in Hyp mode' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G1.

Accessing the HSR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HSR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HSR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0101	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HSR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HSR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HSTR, Hyp System Trap Register

The HSTR characteristics are:

Purpose

Controls trapping to Hyp mode of Non-secure accesses, at EL1 or lower, to System registers in the coproc == 0b1111 encoding space:

- By the CRn value used to access the register using MCR or MRC instruction.
- By the CRm value used to access the register using MCRR or MRRC instruction.

Configuration

AArch32 System register HSTR bits [31:0] are architecturally mapped to AArch64 System register HSTR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HSTR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 with EL2 using AArch32, or into EL3 with EL3 using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HSTR is a 32-bit register.

Field descriptions

The HSTR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																T15	T14	T13	T12	T11	T10	T9	T8	T7	T6	T5	T4	T3	T2	T1	T0

Bits [31:16]

Reserved, RES0.

T<n>, bit [n], for n = 0 to 15

Fields T14 and T4 are RES0.

The remaining fields control whether Non-secure EL0 and EL1 accesses, using MCR, MRC, MCRR, and MRRC instructions, to the System registers in the coproc == 0b1111 encoding space are trapped to Hyp mode:

T<n>	Meaning
0b0	This control has no effect on Non-secure EL0 or EL1 accesses to System registers.
0b1	Any Non-secure EL1 MCR or MRC access with coproc == 0b1111 and CRn == <n> is trapped to Hyp mode. A Non-secure EL0 MCR or MRC access with these values is trapped to Hyp mode only if the access is not UNDEFINED when the value of this field is 0. Any Non-secure EL1 MCRR or MRRC access with coproc == 0b1111 and CRm == <n> is trapped to Hyp mode. A Non-secure EL0 MCRR or MRRC access with these values is trapped to Hyp mode only if the access is not UNDEFINED when the value of this field is 0.

For example, when HSTR.T7 is 1, for instructions executed at Non-secure EL1:

- An MCR or MRC instruction with coproc set to 0b1111 and <CRn> set to c7 is trapped to Hyp mode.
- An MCRR or MRRC instruction with coproc set to 0b1111 and <CRm> set to c7 is trapped to Hyp mode.

In a system where the PE resets into EL2 or EL3, this field resets to 0.

Accessing the HSTR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HSTR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HSTR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0001	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HSTR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HSTR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HTCR, Hyp Translation Control Register

The HTCR characteristics are:

Purpose

The control register for stage 1 of the EL2 translation regime.

Note

This stage of translation always uses the Long-descriptor translation table format.

Configuration

AArch32 System register HTCR bits [31:0] are architecturally mapped to AArch64 System register TCR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HTCR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HTCR is a 32-bit register.

Field descriptions

The HTCR bit assignments are:

31	30	29	28	27	26	25	24	23	22:12	11	10	9	8	7:6	5:4	3:2	1	0
RES1	IMPLEMENTATION DEFINED	RES0	HWU62	HWU61	HWU60	HWU59	HPD	RES1	RES0	SH0	ORGN0	IRGN0	RES0	T0SZ				

Bit [31]

Reserved, RES1.

IMPLEMENTATION DEFINED, bit [30]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Bit [29]

Reserved, RES0.

HWU62, bit [28]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[62] of the stage 1 translation table Block or Page entry.

HWU62	Meaning
0b0	Bit[62] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[62] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of HTCR.HPD is 1.

The Effective value of this field is 0 if the value of HTCR.HPD is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU61, bit [27]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[61] of the stage 1 translation table Block or Page entry.

HWU61	Meaning
0b0	Bit[61] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[61] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of HTCR.HPD is 1.

The Effective value of this field is 0 if the value of HTCR.HPD is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU60, bit [26]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[60] of the stage 1 translation table Block or Page entry.

HWU60	Meaning
0b0	Bit[60] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[60] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of HTCR.HPD is 1.

The Effective value of this field is 0 if the value of HTCR.HPD is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU59, bit [25]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[59] of the stage 1 translation table Block or Page entry.

HWU59	Meaning
0b0	Bit[59] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[59] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of HTCR.HPD is 1.

The Effective value of this field is 0 if the value of HTCR.HPD is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HPD, bit [24]

When ARMv8.2-AA32HPD is implemented:

Hierarchical Permission Disables. This affects the hierarchical control bits, APTable, XNTable, and PXNTable, in the PL2 translation regime.

HPD	Meaning
0b0	Hierarchical permissions are enabled.
0b1	Hierarchical permissions are disabled.

When disabled, the permissions are treated as if the bits are zero.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [23]

Reserved, RES1.

Bits [22:14]

Reserved, RES0.

SH0, bits [13:12]

Shareability attribute for memory associated with translation table walks using HTTBR.

SH0	Meaning
0b00	Non-shareable.
0b10	Outer Shareable.
0b11	Inner Shareable.

Other values are reserved. The effect of programming this field to a Reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Unallocated values in fields of AArch32 System registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.1.11.

This field resets to an architecturally UNKNOWN value.

ORGN0, bits [11:10]

Outer cacheability attribute for memory associated with translation table walks using HTTBR.

ORGN0	Meaning
0b00	Normal memory, Outer Non-cacheable.
0b01	Normal memory, Outer Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Outer Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Outer Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

IRGN0, bits [9:8]

Inner cacheability attribute for memory associated with translation table walks using HTTBR.

IRGN0	Meaning
0b00	Normal memory, Inner Non-cacheable.
0b01	Normal memory, Inner Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Inner Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Inner Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

Bits [7:3]

Reserved, RES0.

T0SZ, bits [2:0]

The size offset of the memory region addressed by HTTBR. The region size is $2^{(32-T0SZ)}$ bytes.

This field resets to an architecturally UNKNOWN value.

Accessing the HTCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0010	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HTCR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HTCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0010	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HTCR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HTCR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HTPIDR, Hyp Software Thread ID Register

The HTPIDR characteristics are:

Purpose

Provides a location where software running in Hyp mode can store thread identifying information that is not visible to Non-secure software executing at EL0 or EL1, for hypervisor management purposes.

The PE makes no use of this register.

Configuration

AArch32 System register HTPIDR bits [31:0] are architecturally mapped to AArch64 System register TPIDR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HTPIDR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

Note

The PE never updates this register.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HTPIDR is a 32-bit register.

Field descriptions

The HTPIDR bit assignments are:



Bits [31:0]

Thread ID. Thread identifying information stored by software running at this Exception level.

This field resets to an architecturally UNKNOWN value.

Accessing the HTPIDR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1101	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HTPIDR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HTPIDR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1101	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HTPIDR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HTPIDR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HTRFCR, Hyp Trace Filter Control Register

The HTRFCR characteristics are:

Purpose

Provides EL2 controls for Trace.

Configuration

AArch32 System register HTRFCR bits [31:0] are architecturally mapped to AArch64 System register TRFCR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level and ARMv8.4-Trace is implemented. Otherwise, direct accesses to HTRFCR are UNDEFINED.

If EL2 is not implemented, this register is RES0 from Monitor mode when SCR.NS == 1.

~~This register is in the Warm reset domain. Some or all RW fields of this register have defined reset values. On a Warm or Cold reset these apply only if the PE resets into EL2 with EL2 using AArch32, or into EL3 with EL3 using AArch32. Otherwise, on a Warm or Cold reset RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HTRFCR is a 32-bit register.

Field descriptions

The HTRFCR bit assignments are:



Bits [31:7]

Reserved, RES0.

TS, bits [6:5]

Timestamp Control. Controls which timebase is used for trace timestamps.

TS	Meaning
0b00	The timestamp is controlled by TRFCR.TS.
0b01	Virtual timestamp. The traced timestamp is the physical counter value minus the value of CNTVOFF.
0b11	Physical timestamp. The traced timestamp is the physical counter value.

When SelfHostedTraceEnabled() == FALSE, this field is ignored.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to 0.

Bit [4]

Reserved, RES0.

CX, bit [3]

VMID Trace Enable.

CX	Meaning
0b0	VMID tracing is not allowed.
0b1	VMID tracing is allowed.

When SelfHostedTraceEnabled() == FALSE, this field is ignored.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to 0.

Bit [2]

Reserved, RES0.

E2TRE, bit [1]

EL2 Trace Enable.

E2TRE	Meaning
0b0	Tracing is prohibited at EL2.
0b1	Tracing is allowed at EL2.

When SelfHostedTraceEnabled() == FALSE, this field is ignored.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to 0.

E0HTRE, bit [0]

EL0 Trace Enable.

E0HTRE	Meaning
0b0	Tracing is prohibited at EL0 when HCR.TGE == 1.
0b1	Tracing is allowed at EL0 when HCR.TGE == 1.

This field is ignored if any of the following are true:

- The PE is in Secure state.
- SelfHostedTraceEnabled() == FALSE.
- HCR.TGE == 0.

On a Warm reset, in a system where the PE resets into EL2 or EL3, this field resets to 0.

Accessing the HTRFCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TTRF == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return HTRFCR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HTRFCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TTRF == '1' then
        AArch32.TakeMonitorTrapException();
    else
        HTRFCR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HTRFCR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HTTBR, Hyp Translation Table Base Register

The HTTBR characteristics are:

Purpose

Holds the base address of the translation table for the initial lookup for stage 1 of an address translation in the EL2 translation regime, and other information for this translation regime.

Configuration

AArch32 System register HTTBR bits [47:1] are architecturally mapped to AArch64 System register TTBR0_EL2[47:1] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HTTBR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HTTBR is a 64-bit register.

Field descriptions

The HTTBR bit assignments are:



Bits [63:48]

Reserved, RES0.

BADDR, bits [47:1]

Translation table base address, bits[47:x], Bits [x-1:1] are RES0, with the additional requirement that if bits[x-1:3] are not all zero, this is a misaligned translation table base address, with effects that are CONSTRAINED UNPREDICTABLE, and must be one of the following:

- Register bits [x-1:3] are treated as if all the bits are zero. The value read back from these bits is either the value written or zero.
- The result of the calculation of an address for a translation table walk using this register can be corrupted in those bits that are nonzero.

x is determined from the value of HTCR.T0SZ as follows:

- If HTCR.T0SZ is 0 or 1, x = 5 - HTCR.T0SZ.
- If HTCR.T0SZ is greater than 1, x = 14 - HTCR.T0SZ.

If bits[47:40] of the translation table base address are not zero, an Address size fault is generated.

This field resets to an architecturally UNKNOWN value.

CnP, bit [0]

When ARMv8.2-TTCNP is implemented:

Common not Private. This bit indicates whether each entry that is pointed to by HTTBR is a member of a common set that can be used by every PE in the Inner Shareable domain for which the value of HTTBR.CnP is 1.

CnP	Meaning
0b0	The translation table entries pointed to by HTTBR are permitted to differ from corresponding entries for HTTBR for other PEs in the Inner Shareable domain. This is not affected by the value of HTTBR.CnP on those other PEs.
0b1	The translation table entries pointed to by HTTBR are the same as the translation table entries pointed to by HTTBR on every other PE in the Inner Shareable domain for which the value of HTTBR.CnP is 1.

Note

If the value of the HTTBR.CnP bit is 1 on multiple PEs in the same Inner Shareable domain and those HTTBRs do not point to the same translation table entries when the other conditions specified for the case when the value of CnP is 1 apply, then the results of translations are CONSTRAINED UNPREDICTABLE, see 'CONSTRAINED UNPREDICTABLE behaviors due to caching of control or data values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Accessing the HTTBR

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b0010	0b0100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x04);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HTTBR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HTTBR;
```

```
MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b0010	0b0100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x04);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HTTBR = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HTTBR = R[t2]:R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

HVBAR, Hyp Vector Base Address Register

The HVBAR characteristics are:

Purpose

Holds the vector base address for any exception that is taken to Hyp mode.

Configuration

AArch32 System register HVBAR bits [31:0] are architecturally mapped to AArch64 System register VBAR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to HVBAR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

HVBAR is a 32-bit register.

Field descriptions

The HVBAR bit assignments are:



Bits [31:5]

Vector Base Address. Bits[31:5] of the base address of the exception vectors for exceptions taken to this Exception level. Bits[4:0] of an exception vector are the exception offset.

This field resets to an architecturally UNKNOWN value.

Bits [4:0]

Reserved, RES0.

Accessing the HVBAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return HVBAR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return HVBAR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    HVBAR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        HVBAR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_AP0R<n>, Interrupt Controller Active Priorities Group 0 Registers, n = 0 - 3

The ICC_AP0R<n> characteristics are:

Purpose

Provides information about Group 0 active priorities.

Configuration

AArch32 System register ICC_AP0R<n> bits [31:0] are architecturally mapped to AArch64 System register ICC_AP0R<n>_EL1[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to ICC_AP0R<n> arearchitecturally UNKNOWN.values.

Attributes

ICC_AP0R<n> is a 32-bit register.

Field descriptions

The ICC_AP0R<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
IMPLEMENTATION DEFINED																															

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to `0`.

The contents of these registers are IMPLEMENTATION DEFINED with the one architectural requirement that the value `0x00000000` is consistent with no interrupts being active.

Accessing the ICC_AP0R<n>

Writing to these registers with any value other than the last read value of the register (or `0x00000000` when there are no Group 0 active priorities) might result in UNPREDICTABLE behavior of the interrupt prioritization system, causing:

- Interrupts that should preempt execution to not preempt execution.
- Interrupts that should not preempt execution to preempt execution.

ICC_AP0R1 is only implemented in implementations that support 6 or more bits of preemption. ICC_AP0R2 and ICC_AP0R3 are only implemented in implementations that support 7 bits of preemption. Unimplemented registers are UNDEFINED.

Note

The number of bits of preemption is indicated by ICH_VTR.PREbits.

Writing to the active priority registers in any order other than the following order will result in UNPREDICTABLE behavior:

- ICC_AP0R<n>.
- Secure ICC_AP1R<n>.
- Non-secure ICC_AP1R<n>.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b1:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_AP0R[UInt(opc2<1:0>)];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_AP0R[UInt(opc2<1:0>)];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_AP0R[UInt(opc2<1:0>)];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_AP0R[UInt(opc2<1:0>)];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_AP0R[UInt(opc2<1:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b1:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_AP0R[UInt(opc2<1:0>)] = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_AP0R[UInt(opc2<1:0>)] = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_AP0R[UInt(opc2<1:0>)] = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_AP0R[UInt(opc2<1:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_AP0R[UInt(opc2<1:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_AP1R<n>, Interrupt Controller Active Priorities Group 1 Registers, n = 0 - 3

The ICC_AP1R<n> characteristics are:

Purpose

Provides information about Group 1 active priorities.

Configuration

AArch32 System register ICC_AP1R<n> bits [31:0] (S) are architecturally mapped to AArch64 System register ICC_AP1R<n>_EL1[31:0] (S) .

AArch32 System register ICC_AP1R<n> bits [31:0] (NS) are architecturally mapped to AArch64 System register ICC_AP1R<n>_EL1[31:0] (NS) .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. If the PE resets into EL3 using AArch32 they apply only to the Secure instance of the register. Otherwise, RW directfields accessesin this register reset to ICC_AP1R<n> arearchitecturally UNKNOWN.values.

Attributes

ICC_AP1R<n> is a 32-bit register.

Field descriptions

The ICC_AP1R<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
IMPLEMENTATION DEFINED																															

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to `0`.

The contents of these registers are IMPLEMENTATION DEFINED with the one architectural requirement that the value `0x00000000` is consistent with no interrupts being active.

Accessing the ICC_AP1R<n>

Writing to these registers with any value other than the last read value of the register (or `0x00000000` when there are no Group 1 active priorities) might result in UNPREDICTABLE behavior of the interrupt prioritization system, causing:

- Interrupts that should preempt execution to not preempt execution.
- Interrupts that should not preempt execution to preempt execution.

ICC_AP1R1 is only implemented in implementations that support 6 or more bits of preemption. ICC_AP1R2 and ICC_AP1R3 are only implemented in implementations that support 7 bits of preemption. Unimplemented registers are UNDEFINED.

Note

The number of bits of preemption is indicated by ICH_VTR.PREbits.

Writing to the active priority registers in any order other than the following order will result in UNPREDICTABLE behavior:

- ICC_AP0R<n>
- Secure ICC_AP1R<n>
- Non-secure ICC_AP1R<n>

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1001	0b0:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_AP1R[UInt(opc2<1:0>)];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_AP1R[UInt(opc2<1:0>)];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            return ICC_AP1R_S[UInt(opc2<1:0>)];
        else
            return ICC_AP1R_NS[UInt(opc2<1:0>)];
    else
        return ICC_AP1R[UInt(opc2<1:0>)];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        return ICC_AP1R_NS[UInt(opc2<1:0>)];
    else
        return ICC_AP1R[UInt(opc2<1:0>)];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            return ICC_AP1R_S[UInt(opc2<1:0>)];
        else
            return ICC_AP1R_NS[UInt(opc2<1:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1001	0b0:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_AP1R[UInt(opc2<1:0>)] = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_AP1R[UInt(opc2<1:0>)] = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            ICC_AP1R_S[UInt(opc2<1:0>)] = R[t];
        else
            ICC_AP1R_NS[UInt(opc2<1:0>)] = R[t];
    else
        ICC_AP1R[UInt(opc2<1:0>)] = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        ICC_AP1R_NS[UInt(opc2<1:0>)] = R[t];
    else
        ICC_AP1R[UInt(opc2<1:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            ICC_AP1R_S[UInt(opc2<1:0>)] = R[t];
        else
            ICC_AP1R_NS[UInt(opc2<1:0>)] = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_ASGI1R, Interrupt Controller Alias Software Generated Interrupt Group 1 Register

The ICC_ASGI1R characteristics are:

Purpose

Generates Group 1 SGIs for the Security state that is not the current Security state.

Configuration

AArch32 System register ICC_ASGI1R performs the same function as AArch64 System register ICC_ASGI1R_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_ASGI1R are UNKNOWN.

Under certain conditions a write to ICC_ASGI1R can generate Group 0 interrupts, see Forwarding an SGI to a target PE.

Attributes

ICC_ASGI1R is a 64-bit register.

Field descriptions

The ICC_ASGI1R bit assignments are:



Bits [63:56]

Reserved, RES0.

Aff3, bits [55:48]

The affinity 3 value of the affinity path of the cluster for which SGI interrupts will be generated.

If the IRM bit is 1, this field is RES0.

RS, bits [47:44]

RangeSelector

Controls which group of 16 values is represented by the TargetList field.

TargetList[n] represents aff0 value ((RS * 16) + n).

When ICC_CTLR_EL1.RSS==0, RS is RES0.

When ICC_CTLR_EL1.RSS==1 and GICD_TYPER.RSS==0, writing this register with RS != 0 is a CONSTRAINED UNPREDICTABLE choice of :

- The write is ignored.

- The RS field is treated as 0.

Bits [43:41]

Reserved, RES0.

IRM, bit [40]

Interrupt Routing Mode. Determines how the generated interrupts are distributed to PEs. Possible values are:

IRM	Meaning
0b0	Interrupts routed to the PEs specified by Aff3.Aff2.Aff1.<target list>.
0b1	Interrupts routed to all PEs in the system, excluding "self".

Aff2, bits [39:32]

The affinity 2 value of the affinity path of the cluster for which SGI interrupts will be generated.

If the IRM bit is 1, this field is RES0.

Bits [31:28]

Reserved, RES0.

INTID, bits [27:24]

The INTID of the SGI.

Aff1, bits [23:16]

The affinity 1 value of the affinity path of the cluster for which SGI interrupts will be generated.

If the IRM bit is 1, this field is RES0.

TargetList, bits [15:0]

Target List. The set of PEs for which SGI interrupts will be generated. Each bit corresponds to the PE within a cluster with an Affinity 0 value equal to the bit number.

If a bit is 1 and the bit does not correspond to a valid target PE, the bit must be ignored by the Distributor. It is IMPLEMENTATION DEFINED whether, in such cases, a Distributor can signal a system error.

Note

This restricts a system to sending targeted SGIs to PEs with an affinity 0 number that is less than 16. If SRE is set only for Secure EL3, software executing at EL3 might use the System register interface to generate SGIs. Therefore, the Distributor must always be able to receive and acknowledge Generate SGI packets received from CPU interface regardless of the ARE settings for a Security state. However, the Distributor might discard such packets.

If the IRM bit is 1, this field is RES0.

Accessing the ICC_ASGI1R

This register allows software executing in a Secure state to generate Non-secure Group 1 SGIs. It will also allow software executing in a Non-secure state to generate Secure Group 1 SGIs, if permitted by the settings of GICR_NSACR in the Redistributor corresponding to the target PE.

When GICD_CTLR.DS==0, Non-secure writes do not generate an interrupt for a target PE if not permitted by the GICR_NSACR register associated with the target PE. For more information see Use of control registers for SGI forwarding.

Note

Accesses from Secure Monitor mode are treated as Secure regardless of the value of SCR.NS.

Accesses to this register use the following encodings:

```
MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1100	0b0001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.FMO == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.IMO == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    else
        ICC_ASGI1R = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_ASGI1R = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_ASGI1R = R[t2]:R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_BPR0, Interrupt Controller Binary Point Register 0

The ICC_BPR0 characteristics are:

Purpose

Defines the point at which the priority value fields split into two parts, the group priority field and the subpriority field. The group priority field determines Group 0 interrupt preemption.

Configuration

AArch32 System register ICC_BPR0 bits [31:0] are architecturally mapped to AArch64 System register ICC_BPR0_EL1[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to ICC_BPR0 arearchitecturally UNKNOWN.values.

Attributes

ICC_BPR0 is a 32-bit register.

Field descriptions

The ICC_BPR0 bit assignments are:



Bits [31:3]

Reserved, RES0.

BinaryPoint, bits [2:0]

The value of this field controls how the 8-bit interrupt priority field is split into a group priority field, that determines interrupt preemption, and a subpriority field. This is done as follows:

Binary point value	Group priority field	Subpriority field	Field with binary point
0	[7:1]	[0]	ggggggg.s
1	[7:2]	[1:0]	gggggg.ss
2	[7:3]	[2:0]	ggggg.sss
3	[7:4]	[3:0]	gggg.ssss
4	[7:5]	[4:0]	ggg.sssss
5	[7:6]	[5:0]	gg.ssssss
6	[7]	[6:0]	g.sssssss
7	No preemption	[7:0]	.ssssssss

This field resets to an architecturally UNKNOWN value.

Accessing the ICC_BPR0

The minimum binary point value is derived from the number of implemented priority bits. The number of priority bits is IMPLEMENTATION DEFINED, and reported by ICC_CTLR.PRIbits and ICC_MCTLR.PRIbits.

An attempt to program the binary point field to a value less than the minimum value sets the field to the minimum value. On a reset, the binary point field is set to the minimum supported value.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_BPR0;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_BPR0;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_BPR0;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_BPR0;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_BPR0;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_BPR0 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_BPR0 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_BPR0 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_BPR0 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_BPR0 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_BPR1, Interrupt Controller Binary Point Register 1

The ICC_BPR1 characteristics are:

Purpose

Defines the point at which the priority value fields split into two parts, the group priority field and the subpriority field. The group priority field determines Group 1 interrupt preemption.

Configuration

AArch32 System register ICC_BPR1 bits [31:0] (S) are architecturally mapped to AArch64 System register ICC_BPR1_EL1[31:0] (S) .

AArch32 System register ICC_BPR1 bits [31:0] (NS) are architecturally mapped to AArch64 System register ICC_BPR1_EL1[31:0] (NS) .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_BPR1 are UNKNOWN.

In GIC implementations supporting two Security states, this register is Banked.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. If the PE resets into EL3 using AArch32 they apply only to the Secure instance of the register. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICC_BPR1 is a 32-bit register.

Field descriptions

The ICC_BPR1 bit assignments are:



Bits [31:3]

Reserved, RES0.

BinaryPoint, bits [2:0]

If the GIC is configured to use separate binary point fields for Group 0 and Group 1 interrupts, the value of this field controls how the 8-bit interrupt priority field is split into a group priority field, that determines interrupt preemption, and a subpriority field. For more information about priorities, see Priority grouping.

Writing 0 to this field will set this field to its reset value.

If EL3 is implemented and ICC_MCTLR.CBPR_EL1S is 1:

- Accesses to this register at EL3 not in Monitor mode access the state of ICC_BPR0.
- When SCR_EL3.EEL2 is 1 and HCR_EL2.IMO is 1, Secure accesses to this register at EL1 access the state of ICV_BPR1.
- Otherwise, Secure accesses to this register at EL1 access the state of ICC_BPR0.

If EL3 is implemented and ICC_MCTLR.CBPR_EL1NS is 1, Non-secure accesses to this register at EL1 or EL2 behave as follows, depending on the values of HCR.IMO and SCR.IRQ:

HCR.IMO	SCR_IRQ	Behavior
0b0	0b0	Non-secure EL1 and EL2 reads return ICC_BPR0 + 1 saturated to 0b111. Non-secure EL1 and EL2 writes are ignored.
0b0	0b1	Non-secure EL1 and EL2 accesses trap to EL3.
0b1	0b0	Non-secure EL1 accesses affect virtual interrupts. Non-secure EL2 reads return ICC_BPR0 + 1 saturated to 0b111. Non-secure EL2 writes ignored.
0b1	0b1	Non-secure EL1 accesses affect virtual interrupts. Non-secure EL2 accesses trap to EL3.

If EL3 is not implemented and ICC_CTLR.CBPR is 1, Non-secure accesses to this register at EL1 or EL2 behave as follows, depending on the values of HCR.IMO:

HCR.IMO	Behavior
0b0	Non-secure EL1 and EL2 reads return ICC_BPR0 + 1 saturated to 0b111. Non-secure EL1 and EL2 writes are ignored.
0b1	Non-secure EL1 accesses affect virtual interrupts. Non-secure EL2 reads return ICC_BPR0 + 1 saturated to 0b111. Non-secure EL2 writes are ignored.

This field resets to an IMPLEMENTATION DEFINED non-zero value.

Accessing the ICC_BPR1

When the PE resets into an Exception level that is using AArch32, the reset value is equal to:

- For the Secure copy of the register, the minimum value of ICC_BPR0 plus one.
- For the Non-secure copy of the register, the minimum value of ICC_BPR0.

Where the minimum value of ICC_BPR0 is IMPLEMENTATION DEFINED.

If EL3 is not implemented:

- If the PE is Secure this reset value is (minimum value of ICC_BPR0 plus one).
- If the PE is Non-secure this reset value is (minimum value of ICC_BPR0).

An attempt to program the binary point field to a value less than the reset value sets the field to the reset value.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_BPR1;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_BPR1;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            return ICC_BPR1_S;
        else
            return ICC_BPR1_NS;
    else
        return ICC_BPR1;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        return ICC_BPR1_NS;
    else
        return ICC_BPR1;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            return ICC_BPR1_S;
        else
            return ICC_BPR1_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_BPR1 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_BPR1 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            ICC_BPR1_S = R[t];
        else
            ICC_BPR1_NS = R[t];
    else
        ICC_BPR1 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        ICC_BPR1_NS = R[t];
    else
        ICC_BPR1 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            ICC_BPR1_S = R[t];
        else
            ICC_BPR1_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_CTLR, Interrupt Controller Control Register

The ICC_CTLR characteristics are:

Purpose

Controls aspects of the behavior of the GIC CPU interface and provides information about the features implemented.

Configuration

AArch32 System register ICC_CTLR bits [31:0] (S) are architecturally mapped to AArch64 System register ICC_CTLR_EL1[31:0] (S) .

AArch32 System register ICC_CTLR bits [31:0] (NS) are architecturally mapped to AArch64 System register ICC_CTLR_EL1[31:0] (NS) .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_CTLR are UNKNOWN.

Attributes

ICC_CTLR is a 32-bit register.

Field descriptions

The ICC_CTLR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0												ExtRange	RSS	RES0		A3V	SEIS	IDbits		PRIbits		RES0		PMHE	RES0					EOImode	CBPR

Bits [31:20]

Reserved, RES0.

ExtRange, bit [19]

Extended INTID range (read-only).

ExtRange	Meaning
0b0	CPU interface does not support INTIDs in the range 1024..8191. Behaviour is UNPREDICTABLE if the IRI delivers an interrupt in the range 1024 to 8191 to the CPU interface. **Note** Arm strongly recommends that the IRI is not configured to deliver interrupts in this range to a PE that does not support them.
0b1	CPU interface supports INTIDs in the range 1024..8191. All INTIDs in the range 1024..8191 are treated as requiring deactivation.

If EL3 is implemented, ICC_CTLR_EL1.ExtRange is an alias of ICC_CTLR_EL3.ExtRange.

RSS, bit [18]

Range Selector Support. Possible values are:

RSS	Meaning
0b0	Targeted SGIs with affinity level 0 values of 0 - 15 are supported.
0b1	Targeted SGIs with affinity level 0 values of 0 - 255 are supported.

This bit is read-only.

Bits [17:16]

Reserved, RES0.

A3V, bit [15]

Affinity 3 Valid. Read-only and writes are ignored. Possible values are:

A3V	Meaning
0b0	The CPU interface logic only supports zero values of Affinity 3 in SGI generation System registers.
0b1	The CPU interface logic supports non-zero values of Affinity 3 in SGI generation System registers.

If EL3 is implemented and using AArch32, this bit is an alias of ICC_MCTLR.A3V.

If EL3 is implemented and using AArch64, this bit is an alias of ICC_CTLR_EL3.A3V.

SEIS, bit [14]

SEI Support. Read-only and writes are ignored. Indicates whether the CPU interface supports local generation of SEIs:

SEIS	Meaning
0b0	The CPU interface logic does not support local generation of SEIs.
0b1	The CPU interface logic supports local generation of SEIs.

If EL3 is implemented and using AArch32, this bit is an alias of ICC_MCTLR.SEIS.

If EL3 is implemented and using AArch64, this bit is an alias of ICC_CTLR_EL3.SEIS.

IDbits, bits [13:11]

Identifier bits. Read-only and writes are ignored. The number of physical interrupt identifier bits supported:

IDbits	Meaning
0b000	16 bits.
0b001	24 bits.

All other values are reserved.

If EL3 is implemented and using AArch32, this field is an alias of ICC_MCTLR.IDbits.

If EL3 is implemented and using AArch64, this field is an alias of ICC_CTLR_EL3.IDbits.

PRIbits, bits [10:8]

Priority bits. Read-only and writes are ignored. The number of priority bits implemented, minus one.

An implementation that supports two Security states must implement at least 32 levels of physical priority (5 priority bits).

An implementation that supports only a single Security state must implement at least 16 levels of physical priority (4 priority bits).

Note

This field always returns the number of priority bits implemented, regardless of the Security state of the access or the value of GICD_CTLR.DS.

The division between group priority and subpriority is defined in the binary point registers ICC_BPR0 and ICC_BPR1.

If EL3 is implemented and using AArch32, physical accesses return the value from ICC_MCTLR.PRIbits.

If EL3 is implemented and using AArch64, physical accesses return the value from ICC_CTLR_EL3.PRIbits.

If EL3 is not implemented, physical accesses return the value from this field.

Bit [7]

Reserved, RES0.

PMHE, bit [6]

Priority Mask Hint Enable. Controls whether the priority mask register is used as a hint for interrupt distribution:

PMHE	Meaning
0b0	Disables use of ICC_PMR as a hint for interrupt distribution.
0b1	Enables use of ICC_PMR as a hint for interrupt distribution.

If EL3 is implemented:

- If EL3 is using AArch32, this bit is an alias of ICC_MCTLR.PMHE.
- If EL3 is using AArch64, this bit is an alias of ICC_CTLR_EL3.PMHE.
- If GICD_CTLR.DS == 0, this bit is read-only.
- If GICD_CTLR.DS == 1, this bit is read/write.

If EL3 is not implemented, it is IMPLEMENTATION DEFINED whether this bit is read-only or read-write:

- If this bit is read-only, an implementation can choose to make this field RAZ/WI or RAO/WI.
- If this bit is read/write, it resets to zero.

Bits [5:2]

Reserved, RES0.

EOImode, bit [1]

EOI mode for the current Security state. Controls whether a write to an End of Interrupt register also deactivates the interrupt:

EOImode	Meaning
0b0	ICC_EOIR0 and ICC_EOIR1 provide both priority drop and interrupt deactivation functionality. Accesses to ICC_DIR are UNPREDICTABLE.
0b1	ICC_EOIR0 and ICC_EOIR1 provide priority drop functionality only. ICC_DIR provides interrupt deactivation functionality.

If EL3 is implemented:

- If EL3 is using AArch32, this bit is an alias of ICC_MCTLR.EOImode_EL1{S, NS} where S or NS corresponds to the current Security state.
- If EL3 is using AArch64, this bit is an alias of ICC_CTLR_EL3.EOImode_EL1{S, NS} where S or NS corresponds to the current Security state.

If EL3 is not implemented, it is IMPLEMENTATION DEFINED whether this bit is read-only or read-write:

- If this bit is read-only, an implementation can choose to make this field RAZ/WI or RAO/WI.
- If this bit is read/write, it resets to zero.

CBPR, bit [0]

Common Binary Point Register. Controls whether the same register is used for interrupt preemption of both Group 0 and Group 1 interrupts:

CBPR	Meaning
0b0	ICC_BPR0 determines the preemption group for Group 0 interrupts only. ICC_BPR1 determines the preemption group for Group 1 interrupts.
0b1	ICC_BPR0 determines the preemption group for both Group 0 and Group 1 interrupts.

If EL3 is implemented:

- If EL3 is using AArch32, this bit is an alias of ICC_MCTLR.CBPR_EL1{S,NS} where S or NS corresponds to the current Security state.
- If EL3 is using AArch64, this bit is an alias of ICC_CTLR_EL3.CBPR_EL1{S,NS} where S or NS corresponds to the current Security state.
- If GICD_CTLR.DS == 0, this bit is read-only.
- If GICD_CTLR.DS == 1, this bit is read/write.

If EL3 is not implemented, it is IMPLEMENTATION DEFINED whether this bit is read-only or read-write:

- If this bit is read-only, an implementation can choose to make this field RAZ/WI or RAO/WI.
- If this bit is read/write, it resets to zero.

Accessing the ICC_CTLR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_CTLR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_CTLR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_CTLR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_CTLR;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            return ICC_CTLR_S;
        else
            return ICC_CTLR_NS;
    else
        return ICC_CTLR;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        return ICC_CTLR_NS;
    else
        return ICC_CTLR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            return ICC_CTLR_S;
        else
            return ICC_CTLR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_CTLR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_CTLR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_CTLR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_CTLR = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            ICC_CTLR_S = R[t];
        else
            ICC_CTLR_NS = R[t];
    else
        ICC_CTLR = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        ICC_CTLR_NS = R[t];
    else
        ICC_CTLR = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            ICC_CTLR_S = R[t];
        else
            ICC_CTLR_NS = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_DIR, Interrupt Controller Deactivate Interrupt Register

The ICC_DIR characteristics are:

Purpose

When interrupt priority drop is separated from interrupt deactivation, a write to this register deactivates the specified interrupt.

Configuration

AArch32 System register ICC_DIR performs the same function as AArch64 System register ICC_DIR_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_DIR are UNKNOWN.

Attributes

ICC_DIR is a 32-bit register.

Field descriptions

The ICC_DIR bit assignments are:



Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID of the interrupt to be deactivated.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICC_CTLR.IDbits and ICC_MCTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

Accessing the ICC_DIR

There are two cases when writing to ICC_DIR_EL1 that were UNPREDICTABLE for a corresponding GICv2 write to GICC_DIR:

- When EOImode == 0. GICv3 implementations must ignore such writes. In systems supporting system error generation, an implementation might generate an SEI.
- When EOImode == 1 but no EOI has been issued. The interrupt will be de-activated by the Distributor, however the active priority in the CPU interface for the interrupt will remain set (because no EOI was issued).

Accesses to this register use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TDIR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TDIR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_DIR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_DIR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_DIR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_DIR = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    else
        ICC_DIR = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_DIR = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_DIR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_EOIR0, Interrupt Controller End Of Interrupt Register 0

The ICC_EOIR0 characteristics are:

Purpose

A PE writes to this register to inform the CPU interface that it has completed the processing of the specified Group 0 interrupt.

Configuration

AArch32 System register ICC_EOIR0 performs the same function as AArch64 System register ICC_EOIR0_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_EOIR0 are UNKNOWN.

Attributes

ICC_EOIR0 is a 32-bit register.

Field descriptions

The ICC_EOIR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0								INTID																							

Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID from the corresponding ICC_IAR0 access.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICC_CTLR.IDbits and ICC_MCTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

If the EOImode bit for the current Exception level and Security state is 0, a write to this register drops the priority for the interrupt, and also deactivates the interrupt.

If the EOImode bit for the current Exception level and Security state is 1, a write to this register only drops the priority for the interrupt. Software must write to ICC_DIR to deactivate the interrupt.

The appropriate EOImode bit varies as follows:

- If EL3 is not implemented, the appropriate bit is ICC_CTLR.EOImode.
- If EL3 is implemented and the software is executing in Monitor mode, the appropriate bit is ICC_MCTLR.EOImode_EL3.
- If EL3 is implemented and the software is not executing in Monitor mode, the bit depends on the current Security state:
  - If the software is executing in Secure state, the bit is ICC_CTLR.EOImode in the Secure instance of ICC_CTLR. This is an alias of ICC_MCTLR.EOImode_EL1S.
  - If the software is executing in Non-secure state, the bit is ICC_CTLR.EOImode in the Non-secure instance of ICC_CTLR. This is an alias of ICC_MCTLR.EOImode_EL1NS.

Accessing the ICC_EOIR0

A write to this register must correspond to the most recent valid read by this PE from an Interrupt Acknowledge Register, and must correspond to the INTID that was read from ICC_IAR0, otherwise the system behavior is UNPREDICTABLE. A valid read is a read that returns a valid INTID that is not a special INTID.

A write of a Special INTID is ignored. See Special INTIDs, for more information.

Accesses to this register use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_EOIR0 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_EOIR0 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_EOIR0 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_EOIR0 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_EOIR0 = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_EOIR1, Interrupt Controller End Of Interrupt Register 1

The ICC_EOIR1 characteristics are:

Purpose

A PE writes to this register to inform the CPU interface that it has completed the processing of the specified Group 1 interrupt.

Configuration

AArch32 System register ICC_EOIR1 performs the same function as AArch64 System register ICC_EOIR1_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_EOIR1 are UNKNOWN.

Attributes

ICC_EOIR1 is a 32-bit register.

Field descriptions

The ICC_EOIR1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0								INTID																							

Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID from the corresponding ICC_IAR1 access.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICC_CTLR.IDbits and ICC_MCTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

If the EOImode bit for the current Exception level and Security state is 0, a write to this register drops the priority for the interrupt, and also deactivates the interrupt.

If the EOImode bit for the current Exception level and Security state is 1, a write to this register only drops the priority for the interrupt. Software must write to ICC_DIR to deactivate the interrupt.

The appropriate EOImode bit varies as follows:

- If EL3 is not implemented, the appropriate bit is ICC_CTLR.EOImode.
- If EL3 is implemented and the software is executing in Monitor mode, the appropriate bit is ICC_MCTLR.EOImode_EL3.
- If EL3 is implemented and the software is not executing in Monitor mode, the bit depends on the current Security state:
  - If the software is executing in Secure state, the bit is ICC_CTLR.EOImode in the Secure instance of ICC_CTLR. This is an alias of ICC_MCTLR.EOImode_EL1S.
  - If the software is executing in Non-secure state, the bit is ICC_CTLR.EOImode in the Non-secure instance of ICC_CTLR. This is an alias of ICC_MCTLR.EOImode_EL1NS.

Accessing the ICC_EOIR1

A write to this register must correspond to the most recent valid read by this PE from an Interrupt Acknowledge Register, and must correspond to the INTID that was read from ICC_IAR1, otherwise the system behavior is UNPREDICTABLE. A valid read is a read that returns a valid INTID that is not a special INTID.

A write of a Special INTID is ignored. See Special INTIDs, for more information.

Accesses to this register use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_EOIR1 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_EOIR1 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_EOIR1 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_EOIR1 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_EOIR1 = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_HPPIR0, Interrupt Controller Highest Priority Pending Interrupt Register 0

The ICC_HPPIR0 characteristics are:

Purpose

Indicates the highest priority pending Group 0 interrupt on the CPU interface.

Configuration

AArch32 System register ICC_HPPIR0 performs the same function as AArch64 System register ICC_HPPIR0_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_HPPIR0 are UNKNOWN.

Attributes

ICC_HPPIR0 is a 32-bit register.

Field descriptions

The ICC_HPPIR0 bit assignments are:



Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID of the highest priority pending interrupt, if that interrupt is observable at the current Security state and Exception level.

If the highest priority pending interrupt is not observable, this field contains a special INTID to indicate the reason. These special INTIDs can be one of: 1020, 1021, or 1023. See Special INTIDs, for more information.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICC_CTLR.IDbits and ICC_MCTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

Accessing the ICC_HPPIR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_HPPIR0;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_HPPIR0;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_HPPIR0;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_HPPIR0;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_HPPIR0;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_HPPIR1, Interrupt Controller Highest Priority Pending Interrupt Register 1

The ICC_HPPIR1 characteristics are:

Purpose

Indicates the highest priority pending Group 1 interrupt on the CPU interface.

Configuration

AArch32 System register ICC_HPPIR1 performs the same function as AArch64 System register ICC_HPPIR1_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_HPPIR1 are UNKNOWN.

Attributes

ICC_HPPIR1 is a 32-bit register.

Field descriptions

The ICC_HPPIR1 bit assignments are:



Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID of the highest priority pending interrupt, if that interrupt is observable at the current Security state and Exception level.

If the highest priority pending interrupt is not observable, this field contains a special INTID to indicate the reason. This special INTID can take the value 1023 only. See Special INTIDs, for more information.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICC_CTLR.IDbits and ICC_MCTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

Accessing the ICC_HPPIR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_HPPIR1;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_HPPIR1;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_HPPIR1;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_HPPIR1;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_HPPIR1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_HSRE, Interrupt Controller Hyp System Register Enable register

The ICC_HSRE characteristics are:

Purpose

Controls whether the System register interface or the memory-mapped interface to the GIC CPU interface is used for EL2.

Configuration

AArch32 System register ICC_HSRE bits [31:0] are architecturally mapped to AArch64 System register ICC_SRE_EL2[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to ICC_HSRE arearchitecturally UNKNOWN.values.

Attributes

ICC_HSRE is a 32-bit register.

Field descriptions

The ICC_HSRE bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																												Enable	DIB	DFB	SRE

Bits [31:4]

Reserved, RES0.

Enable, bit [3]

Enable. Enables lower Exception level access to ICC_SRE.

Enable	Meaning
0b0	Non-secure EL1 accesses to ICC_SRE trap to EL2.
0b1	Non-secure EL1 accesses to ICC_SRE do not trap to EL2.

If ICC_HSRE.SRE is RAO/WI, an implementation is permitted to make the Enable bit RAO/WI.

If ICC_HSRE.SRE is 0, the Enable bit behaves as 1 for all purposes other than reading the value of the bit.

This field resets to an architecturally UNKNOWN value.

DIB, bit [2]

Disable IRQ bypass.

DIB	Meaning
0b0	IRQ bypass enabled.
0b1	IRQ bypass disabled.

If EL3 is implemented and GICD_CTLR.DS is 0, this field is a read-only alias of ICC_MSRE.DIB.

If EL3 is implemented and GICD_CTLR.DS is 1, this field is a read-write alias of ICC_MSRE.DIB.

In systems that do not support IRQ bypass, this bit is RAO/WI.

This field resets to `0`.

DFB, bit [1]

Disable FIQ bypass.

DFB	Meaning
`0b0`	FIQ bypass enabled.
`0b1`	FIQ bypass disabled.

If EL3 is implemented and GICD_CTLR.DS is 0, this field is a read-only alias of ICC_MSRE.DFB.

If EL3 is implemented and GICD_CTLR.DS is 1, this field is a read-write alias of ICC_MSRE.DFB.

In systems that do not support FIQ bypass, this bit is RAO/WI.

This field resets to `0`.

SRE, bit [0]

System Register Enable.

SRE	Meaning
`0b0`	The memory-mapped interface must be used. Accesses at EL2 or below to any ICH_* System register, or any EL1 or EL2 ICC_* register other than ICC_SRE or ICC_HSRE, are UNDEFINED.
`0b1`	The System register interface to the ICH_* registers and the EL1 and EL2 ICC_* registers is enabled for EL2.

If software changes this bit from 1 to 0, the results are UNPREDICTABLE.

If an implementation supports only a System register interface to the GIC CPU interface, this bit is RAO/WI.

If EL3 is implemented and using AArch64:

- When ICC_SRE_EL3.SRE==0 this bit is RAZ/WI.

If EL3 is implemented using AArch32:

- When ICC_MSRE.SRE==0 this bit is RAZ/WI.

This field resets to `0`.

Accessing the ICC_HSRE

The GIC architecture permits, but does not require, that registers can be shared between memory-mapped registers and the equivalent System registers. This means that if the memory-mapped registers have been accessed while ICC_HSRE.SRE==0, then the System registers might be modified. Therefore, software must only rely on the reset values of the System registers if there has been no use of the GIC functionality while the memory-mapped registers are in use. Otherwise, the System register values must be treated as UNKNOWN.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1001	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && ICC_SRE_EL3.Enable == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif ICC_MSRE.Enable == '0' then
        UNDEFINED;
    else
        return ICC_HSRE;
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        UNDEFINED;
    else
        return ICC_HSRE;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1001	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && ICC_SRE_EL3.Enable == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif ICC_MSRE.Enable == '0' then
        UNDEFINED;
    else
        ICC_HSRE = R[t];
elsif PSTATE.EL == EL3 then
    if !EL2Enabled() then
        UNDEFINED;
    else
        ICC_HSRE = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_IAR0, Interrupt Controller Interrupt Acknowledge Register 0

The ICC_IAR0 characteristics are:

Purpose

The PE reads this register to obtain the INTID of the signaled Group 0 interrupt. This read acts as an acknowledge for the interrupt.

Configuration

AArch32 System register ICC_IAR0 performs the same function as AArch64 System register ICC_IAR0_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_IAR0 are UNKNOWN.

To allow software to ensure appropriate observability of actions initiated by GIC register accesses, the PE and CPU interface logic must ensure that reads of this register are self-synchronising when interrupts are masked by the PE (that is when PSTATE.{I,F} == {0,0}). This ensures that the effect of activating an interrupt on the signaling of interrupt exceptions is observed when a read of this register is architecturally executed so that no spurious interrupt exception occurs if interrupts are unmasked by an instruction immediately following the read. See Observability of the effects of accesses to the GIC registers, for more information.

Attributes

ICC_IAR0 is a 32-bit register.

Field descriptions

The ICC_IAR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0								INTID																							

Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID of the signaled interrupt.

This is the INTID of the highest priority pending interrupt, if that interrupt is of sufficient priority for it to be signaled to the PE, and if it can be acknowledged at the current Security state and Exception level.

If the highest priority pending interrupt is not observable, this field contains a special INTID to indicate the reason. These special INTIDs can be one of: 1020, 1021, or 1023. See Special INTIDs, for more information.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICC_CTLR.IDbits and ICC_MCTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

Accessing the ICC_IAR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_IAR0;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_IAR0;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IAR0;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IAR0;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_IAR0;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_IAR1, Interrupt Controller Interrupt Acknowledge Register 1

The ICC_IAR1 characteristics are:

Purpose

The PE reads this register to obtain the INTID of the signaled Group 1 interrupt. This read acts as an acknowledge for the interrupt.

Configuration

AArch32 System register ICC_IAR1 performs the same function as AArch64 System register ICC_IAR1_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_IAR1 are UNKNOWN.

To allow software to ensure appropriate observability of actions initiated by GIC register accesses, the PE and CPU interface logic must ensure that reads of this register are self-synchronising when interrupts are masked by the PE (that is when PSTATE.{I,F} == {0,0}). This ensures that the effect of activating an interrupt on the signaling of interrupt exceptions is observed when a read of this register is architecturally executed so that no spurious interrupt exception occurs if interrupts are unmasked by an instruction immediately following the read. See Observability of the effects of accesses to the GIC registers, for more information.

Attributes

ICC_IAR1 is a 32-bit register.

Field descriptions

The ICC_IAR1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0								INTID																							

Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID of the signaled interrupt.

This is the INTID of the highest priority pending interrupt, if that interrupt is of sufficient priority for it to be signaled to the PE, and if it can be acknowledged at the current Security state and Exception level.

If the highest priority pending interrupt is not observable, this field contains a special INTID to indicate the reason. This special INTID can take the value 1023 only. See Special INTIDs, for more information.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICC_CTLR.IDbits and ICC_MCTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

Accessing the ICC_IAR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_IAR1;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_IAR1;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IAR1;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IAR1;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_IAR1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_IGRPEN0, Interrupt Controller Interrupt Group 0 Enable register

The ICC_IGRPEN0 characteristics are:

Purpose

Controls whether Group 0 interrupts are enabled or not.

Configuration

AArch32 System register ICC_IGRPEN0 bits [31:0] are architecturally mapped to AArch64 System register ICC_IGRPEN0_EL1[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to ICC_IGRPEN0 arearchitecturally UNKNOWN.values.

Attributes

ICC_IGRPEN0 is a 32-bit register.

Field descriptions

The ICC_IGRPEN0 bit assignments are:



Bits [31:1]

Reserved, RES0.

Enable, bit [0]

Enables Group 0 interrupts.

Enable	Meaning
0b0	Group 0 interrupts are disabled.
0b1	Group 0 interrupts are enabled.

Virtual accesses to this register update ICH_VMCR.VENG0.

This field resets to 0.

Accessing the ICC_IGRPEN0

The lowest Exception level at which this register can be accessed is governed by the Exception level to which FIQ is routed. This routing depends on SCR.FIQ, SCR.NS and HCR.FMO.

If an interrupt is pending within the CPU interface when Enable becomes 0, the interrupt must be released to allow the Distributor to forward the interrupt to a different PE.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_IGRPEN0;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_IGRPEN0;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IGRPEN0;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IGRPEN0;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_IGRPEN0;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_IGRPEN0 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_IGRPEN0 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_IGRPEN0 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_IGRPEN0 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_IGRPEN0 = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_IGRPEN1, Interrupt Controller Interrupt Group 1 Enable register

The ICC_IGRPEN1 characteristics are:

Purpose

Controls whether Group 1 interrupts are enabled for the current Security state.

Configuration

AArch32 System register ICC_IGRPEN1 bits [31:0] (S) are architecturally mapped to AArch64 System register ICC_IGRPEN1_EL1[31:0] (S) .

AArch32 System register ICC_IGRPEN1 bits [31:0] (NS) are architecturally mapped to AArch64 System register ICC_IGRPEN1_EL1[31:0] (NS) .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. If the PE resets into EL3 using AArch32 they apply only to the Secure instance of the register. Otherwise, RW directfields accessesin this register reset to ICC_IGRPEN1 arearchitecturally UNKNOWN.values.

Attributes

ICC_IGRPEN1 is a 32-bit register.

Field descriptions

The ICC_IGRPEN1 bit assignments are:



Bits [31:1]

Reserved, RES0.

Enable, bit [0]

Enables Group 1 interrupts for the current Security state.

Enable	Meaning
0b0	Group 1 interrupts are disabled for the current Security state.
0b1	Group 1 interrupts are enabled for the current Security state.

Virtual accesses to this register update ICH_VMCR.VENG1.

If EL3 is present:

- This bit is a read/write alias of ICC_MGRPEN1.EnableGrp1{S, NS} as appropriate if EL3 is using AArch32, or ICC_IGRPEN1_EL3.EnableGrp1{S, NS} as appropriate if EL3 is using AArch64.
- When this register is accessed at EL3, the copy of this register appropriate to the current setting of SCR.NS is accessed.

This field resets to 0.

Accessing the ICC_IGRPEN1

The lowest Exception level at which this register can be accessed is governed by the Exception level to which IRQ is routed. This routing depends on SCR.IRQ, SCR.NS and HCR.IMO.

If an interrupt is pending within the CPU interface when Enable becomes 0, the interrupt must be released to allow the Distributor to forward the interrupt to a different PE.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_IGRPEN1;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_IGRPEN1;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            return ICC_IGRPEN1_S;
        else
            return ICC_IGRPEN1_NS;
    else
        return ICC_IGRPEN1;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        return ICC_IGRPEN1_NS;
    else
        return ICC_IGRPEN1;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            return ICC_IGRPEN1_S;
        else
            return ICC_IGRPEN1_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_IGRPEN1 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_IGRPEN1 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            ICC_IGRPEN1_S = R[t];
        else
            ICC_IGRPEN1_NS = R[t];
    else
        ICC_IGRPEN1 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        ICC_IGRPEN1_NS = R[t];
    else
        ICC_IGRPEN1 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            ICC_IGRPEN1_S = R[t];
        else
            ICC_IGRPEN1_NS = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_MCTLR, Interrupt Controller Monitor Control Register

The ICC_MCTLR characteristics are:

Purpose

Controls aspects of the behavior of the GIC CPU interface and provides information about the features implemented.

Configuration

AArch32 System register ICC_MCTLR bits [31:0] can be mapped to AArch64 System register ICC_CTLR_EL3[31:0] , but this is not architecturally mandated.

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to ICC_MCTLR arearchitecturally UNKNOWN.values.

Attributes

ICC_MCTLR is a 32-bit register.

Field descriptions

The ICC_MCTLR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3
RES0												ExtRange	RSS	nDS	RES0	A3V	SEIS	IDbits				PRIbits		RES0		PMHE	RM	EOImode_EL1NS	EOImode_EL1

Bits [31:20]

Reserved, RES0.

ExtRange, bit [19]

Extended INTID range (read-only).

ExtRange	Meaning
0b0	CPU interface does not support INTIDs in the range 1024..8191. Behavior is UNPREDICTABLE if the IRI delivers an interrupt in the range 1024 to 8191 to the CPU interface. **Note** Arm strongly recommends that the IRI is not configured to deliver interrupts in this range to a PE that does not support them.
0b1	CPU interface supports INTIDs in the range 1024..8191 All INTIDs in the range 1024..8191 are treated as requiring deactivation.

RSS, bit [18]

Range Selector Support. Possible values are:

RSS	Meaning
0b0	Targeted SGIs with affinity level 0 values of 0 - 15 are supported.
0b1	Targeted SGIs with affinity level 0 values of 0 - 255 are supported.

This bit is read-only.

nDS, bit [17]

Disable Security not supported. Read-only and writes are ignored. ~~Possible values are:~~

nDS	Meaning
0b0	The CPU interface logic supports disabling of security.
0b1	The CPU interface logic does not support disabling of security, and requires that security is not disabled.

Bit [16]

Reserved, RES0.

A3V, bit [15]

Affinity 3 Valid. Read-only and writes are ignored. ~~Possible values are:~~

A3V	Meaning
0b0	The CPU interface logic does not support non-zero values of the Aff3 field in SGI generation System registers.
0b1	The CPU interface logic supports non-zero values of the Aff3 field in SGI generation System registers.

If EL3 is present, ICC_CTLR.A3V~~AV3~~ is an alias of ICC_MCTLR.A3V

SEIS, bit [14]

SEI Support. Read-only and writes are ignored. Indicates whether the CPU interface supports generation of SEIs.~~SEIs:~~

SEIS	Meaning
0b0	The CPU interface logic does not support generation of SEIs.
0b1	The CPU interface logic supports generation of SEIs.

If EL3 is present, ICC_CTLR.SEIS is an alias of ICC_MCTLR.SEIS

IDbits, bits [13:11]

Identifier bits. Read-only and writes are ignored. Indicates~~The~~ the number of physical interrupt identifier bits supported.~~supported:~~

IDbits	Meaning
0b000	16 bits.
0b001	24 bits.

All other values are reserved.

If EL3 is present, ICC_CTLR.IDbits is an alias of ICC_MCTLR.IDbits

PRIbits, bits [10:8]

Priority bits. Read-only and writes are ignored. The number of priority bits implemented, minus one.

An implementation that supports two Security states must implement at least 32 levels of physical priority (5 priority bits).

An implementation that supports only a single Security state must implement at least 16 levels of physical priority (4 priority bits).

Note

This field always returns the number of priority bits implemented, regardless of the value of SCR.NS or the value of GICD_CTLR.DS.

The division between group priority and subpriority is defined in the binary point registers ICC_BPR0 and ICC_BPR1.

This field determines the minimum value of ICC_BPR0.

Bit [7]

Reserved, RES0.

PMHE, bit [6]

Priority Mask Hint Enable.

PMHE	Meaning
0b0	Disables use of the priority mask register as a hint for interrupt distribution.
0b1	Enables use of the priority mask register as a hint for interrupt distribution.

Software must write ICC_PMR to 0xFF before clearing this field to 0.

An implementation might choose to make this field RAO/WI.

If EL3 is present, ICC_CTLR.PMHE is an alias of ICC_MCTLR.PMHE.

This field resets to 0.

RM, bit [5]

SBZ.

The equivalent bit in AArch64 is the Routing Modifier bit. This feature is not supported when EL3 is using AArch32.

This field resets to an architecturally UNKNOWN value.

EOImode_EL1NS, bit [4]

EOI mode for interrupts handled at Non-secure EL1 and EL2. Controls whether a write to an End of Interrupt register also deactivates the interrupt.~~interrupt.~~

EOImode_EL1NS	Meaning
0b0	ICC_EOIR0 and ICC_EOIR1 provide both priority drop and interrupt deactivation functionality. Accesses to ICC_DIR are UNPREDICTABLE.
0b1	ICC_EOIR0 and ICC_EOIR1 provide priority drop functionality only. ICC_DIR provides interrupt deactivation functionality.

If EL3 is present, ICC_CTLR(NS).EOImode is an alias of ICC_MCTLR.EOImode_EL1NS.

This field resets to an architecturally UNKNOWN value.

EOImode_EL1S, bit [3]

EOI mode for interrupts handled at Secure EL1. Controls whether a write to an End of Interrupt register also deactivates the interrupt.~~interrupt.~~

EOImode_EL1S	Meaning
0b0	ICC_EOIR0 and ICC_EOIR1 provide both priority drop and interrupt deactivation functionality. Accesses to ICC_DIR are UNPREDICTABLE.
0b1	ICC_EOIR0 and ICC_EOIR1 provide priority drop functionality only. ICC_DIR provides interrupt deactivation functionality.

If EL3 is present, ICC_CTLR(S).EOImode is an alias of ICC_MCTLR.EOImode_EL1S.

This field resets to an architecturally UNKNOWN value.

EOImode_EL3, bit [2]

EOI mode for interrupts handled at EL3. Controls whether a write to an End of Interrupt register also deactivates the interrupt.~~interrupt:~~

EOImode_EL3	Meaning
0b0	ICC_EOIR0 and ICC_EOIR1 provide both priority drop and interrupt deactivation functionality. Accesses to ICC_DIR are UNPREDICTABLE.
0b1	ICC_EOIR0 and ICC_EOIR1 provide priority drop functionality only. ICC_DIR provides interrupt deactivation functionality.

This field resets to an architecturally UNKNOWN value.

CBPR_EL1NS, bit [1]

Common Binary Point Register, EL1 Non-secure. Controls whether the same register is used for interrupt preemption of both Group 0 and Group 1 Non-secure interrupts at EL1 and EL2.~~EL2:~~

CBPR_EL1NS	Meaning
0b0	ICC_BPR0 determines the preemption group for Group 0 interrupts only. ICC_BPR1 determines the preemption group for Non-secure Group 1 interrupts.
0b1	ICC_BPR0 determines the preemption group for Group 0 interrupts and Non-secure Group 1 interrupts. Non-secure accesses to GICC_BPR and ICC_BPR1 access the state of ICC_BPR0.

If EL3 is present, ICC_CTLR(NS).CBPR is an alias of ICC_MCTLR.CBPR_EL1NS.

This field resets to an architecturally UNKNOWN value.

CBPR_EL1S, bit [0]

Common Binary Point Register, EL1 Secure. Controls whether the same register is used for interrupt preemption of both Group 0 and Group 1 Secure interrupts in Secure non-Monitor modes.~~modes:~~

CBPR_EL1S	Meaning
0b0	ICC_BPR0 determines the preemption group for Group 0 interrupts only. ICC_BPR1 determines the preemption group for Secure Group 1 interrupts.
0b1	ICC_BPR0 determines the preemption group for Group 0 interrupts and Secure Group 1 interrupts. Secure EL1 accesses, or EL3 accesses when not in Monitor mode, to ICC_BPR1 access the state of ICC_BPR0.

If EL3 is present, ICC_CTLR(S).CBPR is an alias of ICC_MCTLR.CBPR_EL1S.

This field resets to an architecturally UNKNOWN value.

Accessing the ICC_MCTLR

This register is only accessible when executing in Monitor mode.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b110	0b1100	0b1100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_MCTLR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b110	0b1100	0b1100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_MCTLR = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_MGRPEN1, Interrupt Controller Monitor Interrupt Group 1 Enable register

The ICC_MGRPEN1 characteristics are:

Purpose

Controls whether Group 1 interrupts are enabled or not.

Configuration

AArch32 System register ICC_MGRPEN1 bits [31:0] can be mapped to AArch64 System register ICC_IGRPEN1_EL3[31:0] , but this is not architecturally mandated.

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to ICC_MGRPEN1 arearchitecturally UNKNOWN.values.

Attributes

ICC_MGRPEN1 is a 32-bit register.

Field descriptions

The ICC_MGRPEN1 bit assignments are:



Bits [31:2]

Reserved, RES0.

EnableGrp1S, bit [1]

Enables Group 1 interrupts for the Secure state.

EnableGrp1S	Meaning
0b0	Secure Group 1 interrupts are disabled.
0b1	Secure Group 1 interrupts are enabled.

The Secure ICC_IGRPEN1.Enable bit is a read/write alias of the ICC_MGRPEN1.EnableGrp1S bit.

If the highest priority pending interrupt for that PE is a Group 1 interrupt using 1 of N model, then the interrupt will target another PE as a result of the Enable bit changing from 1 to 0.

This field resets to 0.

EnableGrp1NS, bit [0]

Enables Group 1 interrupts for the Non-secure state.

EnableGrp1NS	Meaning
0b0	Non-secure Group 1 interrupts are disabled.
0b1	Non-secure Group 1 interrupts are enabled.

The Non-secure ICC_IGRPEN1.Enable bit is a read/write alias of the ICC_MGRPEN1.EnableGrp1NS bit.

If the highest priority pending interrupt for that PE is a Group 1 interrupt using 1 of N model, then the interrupt will target another PE as a result of the Enable bit changing from 1 to 0.

This field resets to `0`.

Accessing the ICC_MGRPEN1

If an interrupt is pending within the CPU interface when an Enable bit becomes 0, the interrupt must be released to allow the Distributor to forward the interrupt to a different PE.

This register is only accessible when executing in Monitor mode.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b110	0b1100	0b1100	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_MGRPEN1;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b110	0b1100	0b1100	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_MGRPEN1 = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_MSRE, Interrupt Controller Monitor System Register Enable register

The ICC_MSRE characteristics are:

Purpose

Controls whether the System register interface or the memory-mapped interface to the GIC CPU interface is used for EL3.

Configuration

AArch32 System register ICC_MSRE bits [31:0] can be mapped to AArch64 System register ICC_SRE_EL3[31:0] , but this is not architecturally mandated.

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to ICC_MSRE arearchitecturally UNKNOWN. values.

Attributes

ICC_MSRE is a 32-bit register.

Field descriptions

The ICC_MSRE bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																												Enable	DIB	DFB	SRE

Bits [31:4]

Reserved, RES0.

Enable, bit [3]

Enable. Enables lower Exception level access to ICC_SRE and ICC_HSRE.

Enable	Meaning
0b0	Secure EL1 accesses to Secure ICC_SRE trap to EL3. EL2 accesses to Non-secure ICC_SRE and ICC_HSRE trap to EL3. Non-secure EL1 accesses to ICC_SRE trap to EL3, unless these accesses are trapped to EL2 as a result of ICC_HSRE.Enable == 0.
0b1	Secure EL1 accesses to Secure ICC_SRE do not trap to EL3. EL2 accesses to Non-secure ICC_SRE and ICC_HSRE do not trap to EL3. Non-secure EL1 accesses to ICC_SRE do not trap to EL3.

If ICC_MSRE.SRE is RAO/WI, an implementation is permitted to make the Enable bit RAO/WI.

If ICC_MSRE.SRE is 0, the Enable bit behaves as 1 for all purposes other than reading the value of the bit.

This field resets to an architecturally UNKNOWN value.

DIB, bit [2]

Disable IRQ bypass.

DIB	Meaning
0b0	IRQ bypass enabled.
0b1	IRQ bypass disabled.

In systems that do not support IRQ bypass, this bit is RAO/WI.

This field resets to 0.

DFB, bit [1]

Disable FIQ bypass.

DFB	Meaning
0b0	FIQ bypass enabled.
0b1	FIQ bypass disabled.

In systems that do not support FIQ bypass, this bit is RAO/WI.

This field resets to 0.

SRE, bit [0]

System Register Enable.

SRE	Meaning
0b0	The memory-mapped interface must be used. Accesses at EL3 or below to any ICH_* System register, or any EL1, EL2, or EL3 ICC_* register other than ICC_SRE, ICC_HSRE, or ICC_MSRE, are UNDEFINED.
0b1	The System register interface to the ICH_* registers and the EL1, EL2, and EL3 ICC_* registers is enabled for EL3.

If software changes this bit from 1 to 0, the results are UNPREDICTABLE.

If an implementation supports only a System register interface to the GIC CPU interface, this bit is RAO/WI.

This field resets to 0.

Accessing the ICC_MSRE

This register is always System register accessible.

The GIC architecture permits, but does not require, that registers can be shared between memory-mapped registers and the equivalent System registers. This means that if the memory-mapped registers have been accessed while ICC_MSRE.SRE==0, then the System registers might be modified. Therefore, software must only rely on the reset values of the System registers if there has been no use of the GIC functionality while the memory-mapped registers are in use. Otherwise, the System register values must be treated as UNKNOWN.

This register is only accessible when executing in Monitor mode.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b110	0b1100	0b1100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return ICC_MSRE;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b110	0b1100	0b1100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        ICC_MSRE = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_PMR, Interrupt Controller Interrupt Priority Mask Register

The ICC_PMR characteristics are:

Purpose

Provides an interrupt priority filter. Only interrupts with a higher priority than the value in this register are signaled to the PE.

Configuration

AArch32 System register ICC_PMR bits [31:0] are architecturally mapped to AArch64 System register ICC_PMR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_PMR are UNKNOWN.

To allow software to ensure appropriate observability of actions initiated by GIC register accesses, the PE and CPU interface logic must ensure that writes to this register are self-synchronising. This ensures that no interrupts below the written PMR value will be taken after a write to this register is architecturally executed. See Observability of the effects of accesses to the GIC registers, for more information.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICC_PMR is a 32-bit register.

Field descriptions

The ICC_PMR bit assignments are:



Bits [31:8]

Reserved, RES0.

Priority, bits [7:0]

The priority mask level for the CPU interface. If the priority of an interrupt is higher than the value indicated by this field, the interface signals the interrupt to the PE.

The possible priority field values are as follows:

Implemented priority bits	Possible priority field values	Number of priority levels
[7:0]	0x00-0xFF (0-255), all values	256
[7:1]	0x00-0xFE (0-254), even values only	128
[7:2]	0x00-0xFC (0-252), in steps of 4	64
[7:3]	0x00-0xF8 (0-248), in steps of 8	32
[7:4]	0x00-0xF0 (0-240), in steps of 16	16

Unimplemented priority bits are RAZ/WI.

This field resets to 0.

Accessing the ICC_PMR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0100	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_PMR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_PMR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_PMR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_PMR;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_PMR;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_PMR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_PMR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0100	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_PMR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_PMR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_PMR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_PMR = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    else
        ICC_PMR = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_PMR = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_PMR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_RPR, Interrupt Controller Running Priority Register

The ICC_RPR characteristics are:

Purpose

Indicates the Running priority of the CPU interface.

Configuration

AArch32 System register ICC_RPR performs the same function as AArch64 System register ICC_RPR_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_RPR are UNKNOWN.

Attributes

ICC_RPR is a 32-bit register.

Field descriptions

The ICC_RPR bit assignments are:



Bits [31:8]

Reserved, RES0.

Priority, bits [7:0]

The current running priority on the CPU interface. This is the group priority of the current active interrupt.

The priority returned is the group priority as if the BPR for the current Exception level and Security state was set to the minimum value of BPR for the number of implemented priority bits.

Note

If 8 bits of priority are implemented the group priority is bits[7:1] of the priority.

Accessing the ICC_RPR

If there are no active interrupts on the CPU interface, or all active interrupts have undergone a priority drop, the value returned is the Idle priority.

Software cannot determine the number of implemented priority bits from a read of this register.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1011	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_RPR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_RPR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_RPR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_RPR;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_RPR;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_RPR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_RPR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_SGI0R, Interrupt Controller Software Generated Interrupt Group 0 Register

The ICC_SGI0R characteristics are:

Purpose

Generates Secure Group 0 SGIs.

Configuration

AArch32 System register ICC_SGI0R performs the same function as AArch64 System register ICC_SGI0R_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_SGI0R are UNKNOWN.

Attributes

ICC_SGI0R is a 64-bit register.

Field descriptions

The ICC_SGI0R bit assignments are:



Bits [63:56]

Reserved, RES0.

Aff3, bits [55:48]

The affinity 3 value of the affinity path of the cluster for which SGI interrupts will be generated.

If the IRM bit is 1, this field is RES0.

RS, bits [47:44]

RangeSelector

Controls which group of 16 values is represented by the TargetList field.

TargetList[n] represents aff0 value ((RS * 16) + n).

When ICC_CTLR_EL1.RSS==0, RS is RES0.

When ICC_CTLR_EL1.RSS==1 and GICD_TYPER.RSS==0, writing this register with RS != 0 is a CONSTRAINED UNPREDICTABLE choice of :

- The write is ignored.
- The RS field is treated as 0.

Bits [43:41]

Reserved, RES0.

IRM, bit [40]

Interrupt Routing Mode. Determines how the generated interrupts are distributed to PEs. Possible values are:

IRM	Meaning
0b0	Interrupts routed to the PEs specified by Aff3.Aff2.Aff1.<target list>.
0b1	Interrupts routed to all PEs in the system, excluding "self".

Aff2, bits [39:32]

The affinity 2 value of the affinity path of the cluster for which SGI interrupts will be generated.

If the IRM bit is 1, this field is RES0.

Bits [31:28]

Reserved, RES0.

INTID, bits [27:24]

The INTID of the SGI.

Aff1, bits [23:16]

The affinity 1 value of the affinity path of the cluster for which SGI interrupts will be generated.

If the IRM bit is 1, this field is RES0.

TargetList, bits [15:0]

Target List. The set of PEs for which SGI interrupts will be generated. Each bit corresponds to the PE within a cluster with an Affinity 0 value equal to the bit number.

If a bit is 1 and the bit does not correspond to a valid target PE, the bit must be ignored by the Distributor. It is IMPLEMENTATION DEFINED whether, in such cases, a Distributor can signal a system error.

Note

This restricts a system to sending targeted SGIs to PEs with an affinity 0 number that is less than 16. If SRE is set only for Secure EL3, software executing at EL3 might use the System register interface to generate SGIs. Therefore, the Distributor must always be able to receive and acknowledge Generate SGI packets received from CPU interface regardless of the ARE settings for a Security state. However, the Distributor might discard such packets.

If the IRM bit is 1, this field is RES0.

Accessing the ICC_SGI0R

This register allows software executing in a Secure state to generate Group 0 SGIs. It will also allow software executing in a Non-secure state to generate Group 0 SGIs, if permitted by the settings of GICR_NSACR in the Redistributor corresponding to the target PE.

When GICD_CTLR.DS==0, Non-secure writes do not generate an interrupt for a target PE if not permitted by the GICR_NSACR register associated with the target PE. For more information see Use of control registers for SGI forwarding.

Note

Accesses from Secure Monitor mode are treated as Secure regardless of the value of SCR.NS.

Accesses to this register use the following encodings:

```
MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1100	0b0010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.FMO == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.IMO == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    else
        ICC_SGI0R = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_SGI0R = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_SGI0R = R[t2]:R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_SGI1R, Interrupt Controller Software Generated Interrupt Group 1 Register

The ICC_SGI1R characteristics are:

Purpose

Generates Group 1 SGIs for the current Security state.

Configuration

AArch32 System register ICC_SGI1R performs the same function as AArch64 System register ICC_SGI1R_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICC_SGI1R are UNKNOWN.

Under certain conditions a write to ICC_SGI1R can generate Group 0 interrupts, see Forwarding an SGI to a target PE.

Attributes

ICC_SGI1R is a 64-bit register.

Field descriptions

The ICC_SGI1R bit assignments are:



Bits [63:56]

Reserved, RES0.

Aff3, bits [55:48]

The affinity 3 value of the affinity path of the cluster for which SGI interrupts will be generated.

If the IRM bit is 1, this field is RES0.

RS, bits [47:44]

RangeSelector

Controls which group of 16 values is represented by the TargetList field.

TargetList[n] represents aff0 value ((RS * 16) + n).

When ICC_CTLR_EL1.RSS==0, RS is RES0.

When ICC_CTLR_EL1.RSS==1 and GICD_TYPER.RSS==0, writing this register with RS != 0 is a CONSTRAINED UNPREDICTABLE choice of :

- The write is ignored.

- The RS field is treated as 0.

Bits [43:41]

Reserved, RES0.

IRM, bit [40]

Interrupt Routing Mode. Determines how the generated interrupts are distributed to PEs. Possible values are:

IRM	Meaning
0b0	Interrupts routed to the PEs specified by Aff3.Aff2.Aff1.<target list>.
0b1	Interrupts routed to all PEs in the system, excluding "self".

Aff2, bits [39:32]

The affinity 2 value of the affinity path of the cluster for which SGI interrupts will be generated.

If the IRM bit is 1, this field is RES0.

Bits [31:28]

Reserved, RES0.

INTID, bits [27:24]

The INTID of the SGI.

Aff1, bits [23:16]

The affinity 1 value of the affinity path of the cluster for which SGI interrupts will be generated.

If the IRM bit is 1, this field is RES0.

TargetList, bits [15:0]

Target List. The set of PEs for which SGI interrupts will be generated. Each bit corresponds to the PE within a cluster with an Affinity 0 value equal to the bit number.

If a bit is 1 and the bit does not correspond to a valid target PE, the bit must be ignored by the Distributor. It is IMPLEMENTATION DEFINED whether, in such cases, a Distributor can signal a system error.

Note

This restricts a system to sending targeted SGIs to PEs with an affinity 0 number that is less than 16. If SRE is set only for Secure EL3, software executing at EL3 might use the System register interface to generate SGIs. Therefore, the Distributor must always be able to receive and acknowledge Generate SGI packets received from CPU interface regardless of the ARE settings for a Security state. However, the Distributor might discard such packets.

If the IRM bit is 1, this field is RES0.

Accessing the ICC_SGI1R

Note

Accesses from Secure Monitor mode are treated as Secure regardless of the value of SCR.NS.

Accesses to this register use the following encodings:

```
MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1100	0b0000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.FMO == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.IMO == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    else
        ICC_SGI1R = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_SGI1R = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_SGI1R = R[t2]:R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICC_SRE, Interrupt Controller System Register Enable register

The ICC_SRE characteristics are:

Purpose

Controls whether the System register interface or the memory-mapped interface to the GIC CPU interface is used for EL0 and EL1.

Configuration

AArch32 System register ICC_SRE bits [31:0] (S) are architecturally mapped to AArch64 System register ICC_SRE_EL1[31:0] (S) .

AArch32 System register ICC_SRE bits [31:0] (NS) are architecturally mapped to AArch64 System register ICC_SRE_EL1[31:0] (NS) .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. If the PE resets into EL3 using AArch32 they apply only to the Secure instance of the register. Otherwise, RW directfields accessesin this register reset to ICC_SRE arearchitecturally UNKNOWN.values.

Attributes

ICC_SRE is a 32-bit register.

Field descriptions

The ICC_SRE bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																													DIB	DFB	SRE

Bits [31:3]

Reserved, RES0.

DIB, bit [2]

Disable IRQ bypass.

DIB	Meaning
0b0	IRQ bypass enabled.
0b1	IRQ bypass disabled.

If EL3 is implemented and GICD_CTLR.DS == 0, this field is a read-only alias of ICC_MSRE.DIB.

If EL3 is implemented and GICD_CTLR.DS == 1, and EL2 is not implemented, this field is a read-write alias of ICC_MSRE.DIB.

If EL3 is not implemented and EL2 is implemented, this field is a read-only alias ofor GICD_CTLR.DS == 1, and EL2 is implemented, this field is a read-only alias of ICC_HSRE.DIB.

If GICD_CTLR.DS == 1 and EL2 is implemented, this field is a read-only alias of ICC_HSRE.DIB.

In systems that do not support IRQ bypass, this field is RAO/WI.

This field resets to 0.

DFB, bit [1]

Disable FIQ bypass.

DFB	Meaning
0b0	FIQ bypass enabled.
0b1	FIQ bypass disabled.

If EL3 is implemented and GICD_CTLR.DS == 0, this field is a read-only alias of ICC_MSRE.DFB.

If EL3 is implemented and GICD_CTLR.DS == 1, and EL2 is not implemented, this field is a read-write alias of ICC_MSRE.DFB.

If EL3 is not implemented and EL2 is implemented, this field is a read-only alias of~~or~~ ~~GICD_CTLR.DS == 1, and EL2 is implemented, this field is a read-only alias of~~ ICC_HSRE.DFB.

If GICD_CTLR.DS == 1 and EL2 is implemented, this field is a read-only alias of ICC_HSRE.DFB.

In systems that do not support FIQ bypass, this field is RAO/WI.

This field resets to 0.

SRE, bit [0]

System Register Enable.

SRE	Meaning
0b0	The memory-mapped interface must be used. Accesses at EL1 to any ICC_* System register other than ICC_SRE are UNDEFINED.
0b1	The System register interface for the current Security state is enabled.

If software changes this bit from 1 to 0 in the Secure instance of this register, the results are UNPREDICTABLE.

If an implementation supports only a System register interface to the GIC CPU interface, this bit is RAO/WI.

If EL3 is implemented and using AArch64:

- When ICC_SRE_EL3.SRE==0 the Secure copy of this bit is RAZ/WI.
- When ICC_SRE_EL3.SRE==0 the Non-secure copy of this bit is RAZ/WI.

If EL3 is implemented and using AArch32:

- When ICC_MSRE.SRE==0 the Secure copy of this bit is RAZ/WI.
- When ICC_MSRE.SRE==0 the Non-secure copy of this bit is RAZ/WI.

If EL2 is implemented and using AArch64:

- When ICC_SRE_EL2.SRE==0 the Non-secure copy of this bit is RAZ/WI.

If EL2 is implemented and using AArch32:

- When ICC_HSRE.SRE==0 the Non-secure copy of this bit is RAZ/WI.

This field resets to 0.

Accessing the ICC_SRE

The GIC architecture permits, but does not require, that registers can be shared between memory-mapped registers and the equivalent System registers. This means that if the memory-mapped registers have been accessed while ICC_SRE.SRE==0, then the System registers might be modified. Therefore, software must only rely on the reset values of the System registers if there has been no use of the GIC functionality while the memory-mapped registers are in use. Otherwise, the System register values must be treated as UNKNOWN.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && ICC_SRE_EL3.Enable == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif ICC_MSRE.Enable == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) then
        if SCR_EL3.NS == '0' then
            return ICC_SRE_S;
        else
            return ICC_SRE_NS;
    else
        return ICC_SRE;
elsif PSTATE.EL == EL3 then
    if SCR_EL3.NS == '0' then
        return ICC_SRE_S;
    else
        return ICC_SRE_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && ICC_SRE_EL3.Enable == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif ICC_MSRE.Enable == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) then
        if SCR_EL3.NS == '0' then
            ICC_SRE_S = R[t];
        else
            ICC_SRE_NS = R[t];
    else
        ICC_SRE = R[t];
elsif PSTATE.EL == EL3 then
    if SCR_EL3.NS == '0' then
        ICC_SRE_S = R[t];
    else
        ICC_SRE_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICH_AP0R<n>, Interrupt Controller Hyp Active Priorities Group 0 Registers, n = 0 - 3

The ICH_AP0R<n> characteristics are:

Purpose

Provides information about Group 0 active priorities for EL2.

Configuration

AArch32 System register ICH_AP0R<n> bits [31:0] are architecturally mapped to AArch64 System register ICH_AP0R<n>_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICH_AP0R<n> are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICH_AP0R<n> is a 32-bit register.

Field descriptions

The ICH_AP0R<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
P31	P30	P29	P28	P27	P26	P25	P24	P23	P22	P21	P20	P19	P18	P17	P16	P15	P14	P13	P12	P11	P10	P9	P8	P7	P6	P5	P4	P3	P2	P1	P0

P<x>, bit [x], for x = 0 to 31

Provides the access to the virtual active priorities for Group 0 interrupts. Possible values of each bit are:

P<x>	Meaning
0b0	There is no Group 0 interrupt active at the priority corresponding to that bit.
0b1	There is a Group 0 interrupt active at the priority corresponding to that bit.

The correspondence between priority levels and bits depends on the number of bits of priority that are implemented.

If 5 bits of preemption are implemented (bits [7:3] of priority), then there are 32 preemption levels, and the active state of these preemption levels are held in ICH_AP0R0 in the bits corresponding to Priority[7:3].

If 6 bits of preemption are implemented (bits [7:2] of priority), then there are 64 preemption levels, and:

- The active state of preemption levels 0 - 124 are held in ICH_AP0R0 in the bits corresponding to 0:Priority[6:2].
- The active state of preemption levels 128 - 252 are held in ICH_AP0R1 in the bits corresponding to 1:Priority[6:2].

If 7 bits of preemption are implemented (bits [7:1] of priority), then there are 128 preemption levels, and:

- The active state of preemption levels 0 - 62 are held in ICH_AP0R0 in the bits corresponding to 00:Priority[5:1].
- The active state of preemption levels 64 - 126 are held in ICH_AP0R1 in the bits corresponding to 01:Priority[5:1].
- The active state of preemption levels 128 - 190 are held in ICH_AP0R2 in the bits corresponding to 10:Priority[5:1].
- The active state of preemption levels 192 - 254 are held in ICH_AP0R3 in the bits corresponding to 11:Priority[5:1].

Note

Having the bit corresponding to a priority set to 1 in both ICH_AP0R<n> and ICH_AP1R<n> might result in UNPREDICTABLE behavior of the interrupt prioritization system for virtual interrupts.

This field resets to 0.

Accessing the ICH_AP0R<n>

ICH_AP0R1 is only implemented in implementations that support 6 or more bits of preemption. ICH_AP0R2 and ICH_AP0R3 are only implemented in implementations that support 7 bits of preemption. Unimplemented registers are UNDEFINED.

Note

The number of bits of preemption is indicated by ICH_VTR.PREbits

Writing to the active priority registers in any order other than the following order will result in UNPREDICTABLE behavior:

- ICH_AP0R<n>
- ICH_AP1R<n>

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1000	0b0:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_AP0R[UInt(opc2<1:0>)];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_AP0R[UInt(opc2<1:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1000	0b0:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_AP0R[UInt(opc2<1:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_AP0R[UInt(opc2<1:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICH_AP1R<n>, Interrupt Controller Hyp Active Priorities Group 1 Registers, n = 0 - 3

The ICH_AP1R<n> characteristics are:

Purpose

Provides information about Group 1 active priorities for EL2.

Configuration

AArch32 System register ICH_AP1R<n> bits [31:0] are architecturally mapped to AArch64 System register ICH_AP1R<n>_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICH_AP1R<n> are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICH_AP1R<n> is a 32-bit register.

Field descriptions

The ICH_AP1R<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
P31	P30	P29	P28	P27	P26	P25	P24	P23	P22	P21	P20	P19	P18	P17	P16	P15	P14	P13	P12	P11	P10	P9	P8	P7	P6	P5	P4	P3	P2	P1	P0

P<x>, bit [x], for x = 0 to 31

Group 1 interrupt active priorities. Possible values of each bit are:

P<x>	Meaning
0b0	There is no Group 1 interrupt active at the priority corresponding to that bit.
0b1	There is a Group 1 interrupt active at the priority corresponding to that bit.

The correspondence between priority levels and bits depends on the number of bits of priority that are implemented.

If 5 bits of preemption are implemented (bits [7:3] of priority), then there are 32 preemption levels, and the active state of these preemption levels are held in ICH_AP1R0 in the bits corresponding to Priority[7:3].

If 6 bits of preemption are implemented (bits [7:2] of priority), then there are 64 preemption levels, and:

- The active state of preemption levels 0 - 124 are held in ICH_AP1R0 in the bits corresponding to 0:Priority[6:2].
- The active state of preemption levels 128 - 252 are held in ICH_AP1R1 in the bits corresponding to 1:Priority[6:2].

If 7 bits of preemption are implemented (bits [7:1] of priority), then there are 128 preemption levels, and:

- The active state of preemption levels 0 - 62 are held in ICH_AP1R0 in the bits corresponding to 00:Priority[5:1].
- The active state of preemption levels 64 - 126 are held in ICH_AP1R1 in the bits corresponding to 01:Priority[5:1].
- The active state of preemption levels 128 - 190 are held in ICH_AP1R2 in the bits corresponding to 10:Priority[5:1].
- The active state of preemption levels 192 - 254 are held in ICH_AP1R3 in the bits corresponding to 11:Priority[5:1].

Note

Having the bit corresponding to a priority set to 1 in both ICH_AP0R<n> and ICH_AP1R<n> might result in UNPREDICTABLE behavior of the interrupt prioritization system for virtual interrupts.

This field resets to `0`.

Accessing the ICH_AP1R<n>

ICH_AP1R1 is only implemented in implementations that support 6 or more bits of preemption. ICH_AP1R2 and ICH_AP1R3 are only implemented in implementations that support 7 bits of preemption. Unimplemented registers are UNDEFINED.

Note

The number of bits of preemption is indicated by ICH_VTR.PREbits

Writing to the active priority registers in any order other than the following order will result in UNPREDICTABLE behavior:

- ICH_AP0R<n>
- ICH_AP1R<n>

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1001	0b0:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_AP1R[UInt(opc2<1:0>)];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_AP1R[UInt(opc2<1:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1001	0b0:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_AP1R[UInt(opc2<1:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_AP1R[UInt(opc2<1:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICH_EISR, Interrupt Controller End of Interrupt Status Register

The ICH_EISR characteristics are:

Purpose

Indicates which List registers have outstanding EOI maintenance interrupts.

Configuration

AArch32 System register ICH_EISR bits [31:0] are architecturally mapped to AArch64 System register ICH_EISR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICH_EISR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICH_EISR is a 32-bit register.

Field descriptions

The ICH_EISR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																Status<n>, bit [n], for n = 0 to 15															

Bits [31:16]

Reserved, RES0.

Status<n>, bit [n], for n = 0 to 15

EOI maintenance interrupt status bit for List register <n>:

Status<n>	Meaning
0b0	List register <n>, ICH_LR<n>, does not have an EOI maintenance interrupt.
0b1	List register <n>, ICH_LR<n>, has an EOI maintenance interrupt that has not been handled.

For any ICH_LR<n>, the corresponding status bit is set to 1 if all of the following are true:

- ICH_LRC<n>.State is 0b00.
- ICH_LRC<n>.HW is 0.
- ICH_LRC<n>.EOI (bit [9]) is 1, indicating that when the interrupt corresponding to that List register is deactivated, a maintenance interrupt is asserted.

This field resets to 0.

Accessing the ICH_EISR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1011	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_EISR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_EISR;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICH_ELRSR, Interrupt Controller Empty List Register Status Register

The ICH_ELRSR characteristics are:

Purpose

Indicates which List registers contain valid interrupts.

Configuration

AArch32 System register ICH_ELRSR bits [31:0] are architecturally mapped to AArch64 System register ICH_ELRSR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICH_ELRSR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

Attributes

ICH_ELRSR is a 32-bit register.

Field descriptions

The ICH_ELRSR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																Status<n>, bit [n], for n = 0 to 15															

Bits [31:16]

Reserved, RES0.

Status<n>, bit [n], for n = 0 to 15

Status bit for List register <n>, ICH_LR<n>:

Status<n>	Meaning
0b0	List register ICH_LR<n>, if implemented, contains a valid interrupt. Using this List register can result in overwriting a valid interrupt.
0b1	List register ICH_LR<n> does not contain a valid interrupt. The List register is empty and can be used without overwriting a valid interrupt or losing an EOI maintenance interrupt.

For any List register <n>, the corresponding status bit is set to 1 if ICH_LRC<n>.State is 0b00 and either ICH_LRC<n>.HW is 1 or ICH_LRC<n>.EOI (bit [9]) is 0.

Accessing the ICH_ELRSR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1011	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_ELRSR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_ELRSR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICH_HCR, Interrupt Controller Hyp Control Register

The ICH_HCR characteristics are:

Purpose

Controls the environment for VMs.

Configuration

AArch32 System register ICH_HCR bits [31:0] are architecturally mapped to AArch64 System register ICH_HCR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICH_HCR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICH_HCR is a 32-bit register.

Field descriptions

The ICH_HCR bit assignments are:



EOIcount, bits [31:27]

This field is incremented whenever a successful write to a virtual EOIR or DIR register would have resulted in a virtual interrupt deactivation. That is either:

- A virtual write to EOIR with a valid interrupt identifier that is not in the LPI range (that is < 8192) when EOI mode is zero and no List Register was found.
- A virtual write to DIR with a valid interrupt identifier that is not in the LPI range (that is < 8192) when EOI mode is one and no List Register was found.

This allows software to manage more active interrupts than there are implemented List Registers.

It is CONSTRAINED UNPREDICTABLE whether a virtual write to EOIR that does not clear a bit in the Active Priorities registers (ICH_AP0R<n>/ICH_AP1R<n>) increments EOIcount. Permitted behaviors are:

- Increment EOIcount.
- Leave EOIcount unchanged.

This field resets to `0`.

Bits [26:15]

Reserved, RES0.

TDIR, bit [14]

Trap Non-secure EL1 writes to ICC_DIR and ICV_DIR.

TDIR	Meaning
0b0	Non-secure EL1 writes of ICC_DIR and ICV_DIR are not trapped to EL2, unless trapped by other mechanisms.
0b1	Non-secure EL1 writes of ICV_DIR are trapped to EL2. It is IMPLEMENTATION DEFINED whether Non-secure writes of ICC_DIR are trapped. Not trapping ICC_DIR writes is DEPRECATED.

Support for this bit is OPTIONAL, with support indicated by ICH_VTR.

If the implementation does not support this trap, this bit is RES0.

Arm deprecates not including this trap bit.

This field resets to 0.

TSEI, bit [13]

Trap all locally generated SEIs. This bit allows the hypervisor to intercept locally generated SEIs that would otherwise be taken at Non-secure EL1.

TSEI	Meaning
0b0	Locally generated SEIs do not cause a trap to EL2.
0b1	Locally generated SEIs trap to EL2.

If ICH_VTR.SEIS is 0, this bit is RES0.

This field resets to 0.

TALL1, bit [12]

Trap all Non-secure EL1 accesses to ICC_* and ICV_* System registers for Group 1 interrupts to EL2.

TALL1	Meaning
0b0	Non-secure EL1 accesses to ICC_* and ICV_* registers for Group 1 interrupts proceed as normal.
0b1	Non-secure EL1 accesses to ICC_* and ICV_* registers for Group 1 interrupts trap to EL2.

This field resets to 0.

TALL0, bit [11]

Trap all Non-secure EL1 accesses to ICC_* and ICV_* System registers for Group 0 interrupts to EL2.

TALL0	Meaning
0b0	Non-secure EL1 accesses to ICC_* and ICV_* registers for Group 0 interrupts proceed as normal.
0b1	Non-secure EL1 accesses to ICC_* and ICV_* registers for Group 0 interrupts trap to EL2.

This field resets to 0.

TC, bit [10]

Trap all Non-secure EL1 accesses to System registers that are common to Group 0 and Group 1 to EL2.

TC	Meaning
0b0	Non-secure EL1 accesses to common registers proceed as normal.
0b1	Non-secure EL1 accesses to common registers trap to EL2.

This affects accesses to ICC_SGI0R, ICC_SGI1R, ICC_ASGI1R, ICC_CTLR, ICC_DIR, ICC_PMR, ICC_RPR, ICV_CTLR, ICV_DIR, ICV_PMR, and ICV_RPR.

This field resets to 0.

BitBits [9:8]

Reserved, RES0.

vSGIEOICount, bit [8]

When GICv4.1 is implemented:

Controls whether deactivation of virtual SGIs can increment ICH_HCR_EL2.EOIcount

vSGIEOICount	Meaning
0b0	Deactivation of virtual SGIs can increment ICH_HCR.EOIcount.
0b1	Deactivation of virtual SGIs does not increment ICH_HCR.EOIcount.

This field resets to 0.

Otherwise:

Reserved, RES0.

VGrp1DIE, bit [7]

VM Group 1 Disabled Interrupt Enable. Enables the signaling of a maintenance interrupt while signaling of Group 1 interrupts from the virtual CPU interface to the connected vPE is disabled:

VGrp1DIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when ICH_VMCR.VENG1 is 0.

This field resets to 0.

VGrp1EIE, bit [6]

VM Group 1 Enabled Interrupt Enable. Enables the signaling of a maintenance interrupt while signaling of Group 1 interrupts from the virtual CPU interface to the connected vPE is enabled:

VGrp1EIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when ICH_VMCR.VENG1 is 1.

This field resets to 0.

VGrp0DIE, bit [5]

VM Group 0 Disabled Interrupt Enable. Enables the signaling of a maintenance interrupt while signaling of Group 0 interrupts from the virtual CPU interface to the connected vPE is disabled:

VGrp0DIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when ICH_VMCR.VENG0 is 0.

This field resets to 0.

VGrp0EIE, bit [4]

VM Group 0 Enabled Interrupt Enable. Enables the signaling of a maintenance interrupt while signaling of Group 0 interrupts from the virtual CPU interface to the connected vPE is enabled:

VGrp0EIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when ICH_VMCR.VENG0 is 1.

This field resets to 0.

NPIE, bit [3]

No Pending Interrupt Enable. Enables the signaling of a maintenance interrupt when there are no List registers with the State field set to 0b01 (pending):

NPIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled while the List registers contain no interrupts in the pending state.

This field resets to 0.

LRENPIE, bit [2]

List Register Entry Not Present Interrupt Enable. Enables the signaling of a maintenance interrupt while the virtual CPU interface does not have a corresponding valid List register entry for an EOI request:

LRENPIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt is asserted while the EOIcount field is not 0.

This field resets to 0.

UIE, bit [1]

Underflow Interrupt Enable. Enables the signaling of a maintenance interrupt when the List registers are empty, or hold only one valid entry:

UIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt is asserted if none, or only one, of the List register entries is marked as a valid interrupt.

This field resets to 0.

En, bit [0]

Enable. Global enable bit for the virtual CPU interface:

En	Meaning
0b0	Virtual CPU interface operation disabled.
0b1	Virtual CPU interface operation enabled.

When this field is set to 0:

- The virtual CPU interface does not signal any maintenance interrupts.
- The virtual CPU interface does not signal any virtual interrupts.
- A read of ICV_IAR0, ICV_IAR1, GICV_IAR or GICV_AIAR returns a spurious interrupt ID.

This field resets to 0.

Accessing the ICH_HCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_HCR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_HCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_HCR = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_HCR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICH_LRC<n>, Interrupt Controller List Registers, n = 0 - 15

The ICH_LRC<n> characteristics are:

Purpose

Provides interrupt context information for the virtual CPU interface.

Configuration

AArch32 System register ICH_LRC<n> bits [31:0] are architecturally mapped to AArch64 System register ICH_LR<n>_EL2[63:32] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICH_LRC<n> are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

If list register n is not implemented, then accesses to this register are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICH_LRC<n> is a 32-bit register.

Field descriptions

The ICH_LRC<n> bit assignments are:

31 30	29	28	27 26 25 24	23 22 21 20 19 18 17 16	15 14 13	12 11 10 9 8 7 6 5 4 3 2 1 0
State	HW	Group	RES0	Priority	RES0	pINTID

State, bits [31:30]

The state of the interrupt:

State	Meaning
0b00	Invalid (Inactive).
0b01	Pending.
0b10	Active.
0b11	Pending and active.

The GIC updates these state bits as virtual interrupts proceed through the interrupt life cycle. Entries in the invalid state are ignored, except for the purpose of generating virtual maintenance interrupts.

For hardware interrupts, the pending and active state is held in the physical Distributor rather than the virtual CPU interface. A hypervisor must only use the pending and active state for software originated interrupts, which are typically associated with virtual devices, or SGIs.

This field resets to 0.

HW, bit [29]

Indicates whether this virtual interrupt maps directly to a hardware interrupt, meaning that it corresponds to a physical interrupt. Deactivation of the virtual interrupt also causes the deactivation of the physical interrupt with the INTID that the pINTID field indicates.

HW	Meaning
0b0	The interrupt is triggered entirely by software. No notification is sent to the Distributor when the virtual interrupt is deactivated.
0b1	The interrupt maps directly to a hardware interrupt. A deactivate interrupt request is sent to the Distributor when the virtual interrupt is deactivated, using the pINTID field from this register to indicate the physical INTID. If ICH_VMCR.VEOIM is 0, this request corresponds to a write to ICC_EOIR0 or ICC_EOIR1. Otherwise, it corresponds to a write to ICC_DIR.

This field resets to 0.

Group, bit [28]

Indicates the group for this virtual interrupt.

Group	Meaning
0b0	This is a Group 0 virtual interrupt. ICH_VMCR.VFIQEn determines whether it is signaled as a virtual IRQ or as a virtual FIQ, and ICH_VMCR.VENG0 enables signaling of this interrupt to the virtual machine.
0b1	This is a Group 1 virtual interrupt, signaled as a virtual IRQ. ICH_VMCR.VENG1 enables the signaling of this interrupt to the virtual machine. If ICH_VMCR.VCBPR is 0, then ICC_BPR1 determines if a pending Group 1 interrupt has sufficient priority to preempt current execution. Otherwise, ICH_LR<n> determines preemption.

This field resets to 0.

Bits [27:24]

Reserved, RES0.

Priority, bits [23:16]

The priority of this interrupt.

It is IMPLEMENTATION DEFINED how many bits of priority are implemented, though at least five bits must be implemented. Unimplemented bits are RES0 and start from bit[16] up to bit[18]. The number of implemented bits can be discovered from ICH_VTR.PRIbits.

This field resets to 0.

Bits [15:13]

Reserved, RES0.

pINTID, bits [12:0]

Physical INTID, for hardware interrupts.

When ICH_LRC<n>.HW is 0 (there is no corresponding physical interrupt), this field has the following meaning:

- Bits[12:10] : RES0.
- Bit[9] : EOI. If this bit is 1, then when the interrupt identified by vINTID is deactivated, an EOI maintenance interrupt is asserted.

- Bits[8:0] : Reserved, RES0.

When ICH_LRC<n>.HW is 1 (there is a corresponding physical interrupt):

- This field indicates the physical INTID. This field is only required to implement enough bits to hold a valid value for the implemented INTID size. Any unused higher order bits are RES0.
- When ICC_CTLR_EL1.ExtRange is 0, then bits[44:42] of this field are RES0.
- If the value of pINTID is not a valid INTID, behavior is UNPREDICTABLE. If the value of pINTID indicates a PPI, this field applies to the PPI associated with this same physical PE ID as the virtual CPU interface requesting the deactivation.

A hardware physical identifier is only required in List Registers for interrupts that require deactivation. This means only 13 bits of Physical INTID are required, regardless of the number specified by ICC_CTLR.IDbits.

This field resets to `0`.

Accessing the ICH_LRC<n>

ICH_LR<n> and ICH_LRC<n> can be updated independently.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b111:n[3]	n[2:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_LRC[UInt(CRm<0>:opc2<2:0>)];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_LRC[UInt(CRm<0>:opc2<2:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b111:n[3]	n[2:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_LRC[UInt(CRm<0>:opc2<2:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_LRC[UInt(CRm<0>:opc2<2:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICH_LR<n>, Interrupt Controller List Registers, n = 0 - 15

The ICH_LR<n> characteristics are:

Purpose

Provides interrupt context information for the virtual CPU interface.

Configuration

AArch32 System register ICH_LR<n> bits [31:0] are architecturally mapped to AArch64 System register ICH_LR<n>_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICH_LR<n> are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

If list register n is not implemented, then accesses to this register are UNDEFINED.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICH_LR<n> is a 32-bit register.

Field descriptions

The ICH_LR<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
vINTID																															

vINTID, bits [31:0]

Virtual INTID of the interrupt.

If the value of vINTID is 1020-1023 and ICH_LRC<n>.State!=0b00 (Inactive), behavior is UNPREDICTABLE.

Behavior is UNPREDICTABLE if two or more List Registers specify the same vINTID when:

- ICH_LRC<n>.State == 01.
- ICH_LRC<n>.State == 10.
- ICH_LRC<n>.State == 11.

It is IMPLEMENTATION DEFINED how many bits are implemented, though at least 16 bits must be implemented. Unimplemented bits are RES0. The number of implemented bits can be discovered from ICH_VTR.IDbits.

Note

When a VM is using memory-mapped access to the GIC, software must ensure that the correct source PE ID is provided in bits[12:10].

This field resets to 0.

Accessing the ICH_LR<n>

ICH_LR<n> and ICH_LRC<n> can be updated independently.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b110:n[3]	n[2:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_LR[UInt(CRm<0>:opc2<2:0>)];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_LR[UInt(CRm<0>:opc2<2:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b110:n[3]	n[2:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_LR[UInt(CRm<0>:opc2<2:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_LR[UInt(CRm<0>:opc2<2:0>)] = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICH_MISR, Interrupt Controller Maintenance Interrupt State Register

The ICH_MISR characteristics are:

Purpose

Indicates which maintenance interrupts are asserted.

Configuration

AArch32 System register ICH_MISR bits [31:0] are architecturally mapped to AArch64 System register ICH_MISR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICH_MISR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICH_MISR is a 32-bit register.

Field descriptions

The ICH_MISR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								VGrp1D	VGrp1E	VGrp0D	VGrp0E	NP	LRENP	U	EOI

Bits [31:8]

Reserved, RES0.

VGrp1D, bit [7]

vPE Group 1 Disabled.

VGrp1D	Meaning
0b0	vPE Group 1 Disabled maintenance interrupt not asserted.
0b1	vPE Group 1 Disabled maintenance interrupt asserted.

This maintenance interrupt is asserted when ICH_HCR.VGrp1DIE is ~~==~~1 and ICH_VMCR.VENG0 is ~~VMGrp1En==~~0.

This field resets to 0.

VGrp1E, bit [6]

vPE Group 1 Enabled.

VGrp1E	Meaning
0b0	vPE Group 1 Enabled maintenance interrupt not asserted.
0b1	vPE Group 1 Enabled maintenance interrupt asserted.

This maintenance interrupt is asserted when ICH_HCR.VGrp1EIE is ==1 and ICH_VMCR.VENG1 is ~~VMGrp1En==~~1.

This field resets to 0.

VGrp0D, bit [5]

vPE Group 0 Disabled.

VGrp0D	Meaning
0b0	vPE Group 0 Disabled maintenance interrupt not asserted.
0b1	vPE Group 0 Disabled maintenance interrupt asserted.

This maintenance interrupt is asserted when ICH_HCR.VGrp0DIE is ==1 and ICH_VMCR.VENG0 is ~~VMGrp0En==~~0.

This field resets to 0.

VGrp0E, bit [4]

vPE Group 0 Enabled.

VGrp0E	Meaning
0b0	vPE Group 0 Enabled maintenance interrupt not asserted.
0b1	vPE Group 0 Enabled maintenance interrupt asserted.

This maintenance interrupt is asserted when ICH_HCR.VGrp0EIE is ==1 and ICH_VMCR.VENG0 is ~~VMGrp0En==~~1.

This field resets to 0.

NP, bit [3]

No Pending.

NP	Meaning
0b0	No Pending maintenance interrupt not asserted.
0b1	No Pending maintenance interrupt asserted.

This maintenance interrupt is asserted when ICH_HCR.NPIE is ==1 and no List register is in pending state.

This field resets to 0.

LRENP, bit [2]

List Register Entry Not Present.

LRENP	Meaning
0b0	List Register Entry Not Present maintenance interrupt not asserted.
0b1	List Register Entry Not Present maintenance interrupt asserted.

This maintenance interrupt is asserted when ICH_HCR.LRENPIE is ==1 and ICH_HCR.EOIcount is non-zero.

This field resets to 0.

U, bit [1]

Underflow.

U	Meaning
0b0	Underflow maintenance interrupt not asserted.
0b1	Underflow maintenance interrupt asserted.

This maintenance interrupt is asserted when ICH_HCR.UIE is ==1 and zero or one of the List register entries are marked as a valid interrupt, that is, if the corresponding ICH_LRC<n>.State bits do not equal 0x0.

This field resets to 0.

EOI, bit [0]

End Of Interrupt.

EOI	Meaning
0b0	End Of Interrupt maintenance interrupt not asserted.
0b1	End Of Interrupt maintenance interrupt asserted.

This maintenance interrupt is asserted when at least one bit in ICH_EISR is 1.

This field resets to 0.

Accessing the ICH_MISR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1011	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_MISR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_MISR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICH_VMCR, Interrupt Controller Virtual Machine Control Register

The ICH_VMCR characteristics are:

Purpose

Enables the hypervisor to save and restore the virtual machine view of the GIC state.

Configuration

AArch32 System register ICH_VMCR bits [31:0] are architecturally mapped to AArch64 System register ICH_VMCR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICH_VMCR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICH_VMCR is a 32-bit register.

Field descriptions

The ICH_VMCR bit assignments are:



VPMR, bits [31:24]

Virtual Priority Mask. The priority mask level for the virtual CPU interface. If the priority of a pending virtual interrupt is higher than the value indicated by this field, the interface signals the virtual interrupt to the PE.

This field is an alias of ICV_PMR.Priority.

This field resets to an architecturally UNKNOWN value.

VBPR0, bits [23:21]

Virtual Binary Point Register, Group 0. Defines the point at which the priority value fields split into two parts, the group priority field and the subpriority field. The group priority field determines Group 0 interrupt preemption, and also determines Group 1 interrupt preemption if ICH_VMCR.VCBPR == 1.

This field is an alias of ICV_BPR0.BinaryPoint.

This field resets to an architecturally UNKNOWN value.

VBPR1, bits [20:18]

Virtual Binary Point Register, Group 1. Defines the point at which the priority value fields split into two parts, the group priority field and the subpriority field. The group priority field determines Group 1 interrupt preemption if ICH_VMCR.VCBPR == 0.

This field is an alias of ICV_BPR1.BinaryPoint.

This field resets to an architecturally UNKNOWN value.

Bits [17:10]

Reserved, RES0.

VEOIM, bit [9]

Virtual EOI mode. Controls whether a write to an End of Interrupt register also deactivates the virtual interrupt:

VEOIM	Meaning
0b0	ICV_EOIR0 and ICV_EOIR1 provide both priority drop and interrupt deactivation functionality. Accesses to ICV_DIR are UNPREDICTABLE.
0b1	ICV_EOIR0 and ICV_EOIR1 provide priority drop functionality only. ICV_DIR provides interrupt deactivation functionality.

This bit is an alias of ICV_CTLR.EOImode.

This field resets to an architecturally UNKNOWN value.

Bits [8:5]

Reserved, RES0.

VCBPR, bit [4]

Virtual Common Binary Point Register. Possible values of this bit are:

VCBPR	Meaning
0b0	ICV_BPR0 determines the preemption group for virtual Group 0 interrupts only. ICV_BPR1 determines the preemption group for virtual Group 1 interrupts.
0b1	ICV_BPR0 determines the preemption group for both virtual Group 0 and virtual Group 1 interrupts. Reads of ICV_BPR1 return ICV_BPR0 plus one, saturated to 0b111. Writes to ICV_BPR1 are ignored.

This field is an alias of ICV_CTLR.CBPR.

This field resets to an architecturally UNKNOWN value.

VFIQEn, bit [3]

Virtual FIQ enable. Possible values of this bit are:

VFIQEn	Meaning
0b0	Group 0 virtual interrupts are presented as virtual IRQs.
0b1	Group 0 virtual interrupts are presented as virtual FIQs.

This bit is an alias of GICV_CTLR.FIQEn.

In implementations where the Non-secure copy of ICC_SRE.SRE is always 1, this bit is RES1.

This field resets to an architecturally UNKNOWN value.

VAckCtl, bit [2]

Virtual AckCtl. Possible values of this bit are:

VAckCtl	Meaning
0b0	If the highest priority pending interrupt is Group 1, a read of GICV_IAR or GICV_HPPIR returns an INTID of 1022.
0b1	If the highest priority pending interrupt is Group 1, a read of GICV_IAR or GICV_HPPIR returns the INTID of the corresponding interrupt.

This bit is an alias of GICV_CTLR.AckCtl.

This field is supported for backwards compatibility with GICv2. Arm deprecates the use of this field.

In implementations where the Non-secure copy of ICC_SRE.SRE is always 1, this bit is RES0.

This field resets to an architecturally UNKNOWN value.

VENG1, bit [1]

Virtual Group 1 interrupt enable. Possible values of this bit are:

VENG1	Meaning
0b0	Virtual Group 1 interrupts are disabled.
0b1	Virtual Group 1 interrupts are enabled.

This bit is an alias of ICV_IGRPEN1.Enable.

This field resets to an architecturally UNKNOWN value.

VENG0, bit [0]

Virtual Group 0 interrupt enable. Possible values of this bit are:

VENG0	Meaning
0b0	Virtual Group 0 interrupts are disabled.
0b1	Virtual Group 0 interrupts are enabled.

This bit is an alias of ICV_IGRPEN0.Enable.

This field resets to an architecturally UNKNOWN value.

Accessing the ICH_VMCR

When EL2 is using System register access, EL1 using either System register or memory-mapped access must be supported.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1011	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_VMCR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_VMCR;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1011	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_VMCR = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICH_VMCR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICH_VTR, Interrupt Controller VGIC Type Register

The ICH_VTR characteristics are:

Purpose

Reports supported GIC virtualisartion features.

Configuration

AArch32 System register ICH_VTR bits [31:0] are architecturally mapped to AArch64 System register ICH_VTR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICH_VTR are UNKNOWN.

If EL2 is not implemented, all bits in this register are RES0 from EL3, except for nV4, which is RES1 from EL3.

Attributes

ICH_VTR is a 32-bit register.

Field descriptions

The ICH_VTR bit assignments are:



PRIbits, bits [31:29]

Priority bits. The number of virtual priority bits implemented, minus one.

An implementation must implement at least 32 levels of virtual priority (5 priority bits).

This field is an alias of ICV_CTLR.PRIbits.

PREbits, bits [28:26]

The number of virtual preemption bits implemented, minus one.

An implementation must implement at least 32 levels of virtual preemption priority (5 preemption bits).

The value of this field must be less than or equal to the value of ICH_VTR.PRIbits.

IDbits, bits [25:23]

The number of virtual interrupt identifier bits supported:

IDbits	Meaning
0b000	16 bits.
0b001	24 bits.

All other values are reserved.

This field is an alias of ICV_CTLR.IDbits.

SEIS, bit [22]

SEI Support. Indicates whether the virtual CPU interface supports generation of SEIs:

SEIS	Meaning
0b0	The virtual CPU interface logic does not support generation of SEIs.
0b1	The virtual CPU interface logic supports generation of SEIs.

This bit is an alias of ICV_CTLR.SEIS.

A3V, bit [21]

Affinity 3 Valid. Possible values are:

A3V	Meaning
0b0	The virtual CPU interface logic only supports zero values of Affinity 3 in SGI generation System registers.
0b1	The virtual CPU interface logic supports non-zero values of Affinity 3 in SGI generation System registers.

This bit is an alias of ICV_CTLR.A3V.

nV4, bit [20]

Direct injection of virtual interrupts not supported. Possible values are:

nV4	Meaning
0b0	The CPU interface logic supports direct injection of virtual interrupts.
0b1	The CPU interface logic does not support direct injection of virtual interrupts.

In GICv3 this bit is RES1.

TDS, bit [19]

Separate trapping of Non-secure EL1 writes to ICV_DIR supported.

TDS	Meaning
0b0	Implementation does not support ICH_HCR.TDIR.
0b1	Implementation supports ICH_HCR.TDIR.

Bits [18:5]

Reserved, RES0.

ListRegs, bits [4:0]

The number of implemented List registers, minus one. For example, a value of 0b01111 indicates that the maximum of 16 List registers are implemented.

Accessing the ICH_VTR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1100	0b1011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_VTR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICH_VTR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICIALLU, Instruction Cache Invalidate All to PoU

The ICIALLU characteristics are:

Purpose

Invalidate all instruction caches to PoU. If branch predictors are architecturally visible, also flush branch predictors.

Configuration

AArch32 System instruction ICIALLU performs the same function as AArch64 System instruction IC IALLU.

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICIALLU are UNKNOWN.

Attributes

ICIALLU is a 32-bit System instruction.

Field descriptions

ICIALLU ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the ICIALLU instruction

The PE ignores the value of <Rt>. Software does not have to write a value to this register before issuing this instruction.

When HCR.FB is 1, at Non-secure EL1 this instruction executes as a ICIALLUIS.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TPU == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TOCU == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TPU == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TOCU == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.FB == '1' then
        ICIALLUIS();
    else
        ICIALLU();
elsif PSTATE.EL == EL2 then
    ICIALLU();
elsif PSTATE.EL == EL3 then
    ICIALLU();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICIALLUIS, Instruction Cache Invalidate All to PoU, Inner Shareable

The ICIALLUIS characteristics are:

Purpose

Invalidate all instruction caches Inner Shareable to PoU. If branch predictors are architecturally visible, also flush branch predictors.

Configuration

AArch32 System instruction ICIALLUIS performs the same function as AArch64 System instruction IC IALLUIS.

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICIALLUIS are UNKNOWN.

Attributes

ICIALLUIS is a 32-bit System instruction.

Field descriptions

ICIALLUIS ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the ICIALLUIS instruction

The PE ignores the value of <Rt>. Software does not have to write a value to this register before issuing this instruction.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TPU == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TICAB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TOCU == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TPU == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TICAB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TOCU == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ICIALLU();
elsif PSTATE.EL == EL2 then
    ICIALLU();
elsif PSTATE.EL == EL3 then
    ICIALLU();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICIMVAU, Instruction Cache line Invalidate by VA to PoU

The ICIMVAU characteristics are:

Purpose

Invalidate instruction cache line by virtual address to PoU.

Configuration

AArch32 System instruction ICIMVAU performs the same function as AArch64 System instruction IC IVAU.

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICIMVAU are UNKNOWN.

Attributes

ICIMVAU is a 32-bit System instruction.

Field descriptions

The ICIMVAU input value bit assignments are:



Bits [31:0]

Virtual address to use. No alignment restrictions apply to this VA.

Executing the ICIMVAU instruction

Execution of this instruction might require an address translation from VA to PA, and that translation might fault. For more information, see 'AArch32 instruction cache maintenance instruction (IC*)' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0101	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TPU == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TOCU == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TPU == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TOCU == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ICIMVAU(R[t]);
elsif PSTATE.EL == EL2 then
    ICIMVAU(R[t]);
elsif PSTATE.EL == EL3 then
    ICIMVAU(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_AP0R<n>, Interrupt Controller Virtual Active Priorities Group 0 Registers, n = 0 - 3

The ICV_AP0R<n> characteristics are:

Purpose

Provides information about virtual Group 0 active priorities.

Configuration

AArch32 System register ICV_AP0R<n> bits [31:0] are architecturally mapped to AArch64 System register ICV_AP0R<n>_EL1[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to ICV_AP0R<n> arearchitecturally UNKNOWN.values.

Attributes

ICV_AP0R<n> is a 32-bit register.

Field descriptions

The ICV_AP0R<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
IMPLEMENTATION DEFINED																															

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to `0`.

The contents of these registers are IMPLEMENTATION DEFINED with the one architectural requirement that the value `0x00000000` is consistent with no interrupts being active.

Accessing the ICV_AP0R<n>

Writing to these registers with any value other than the last read value of the register (or `0x00000000` when there are no Group 0 active priorities) might result in UNPREDICTABLE behavior of the virtual interrupt prioritization system, causing:

- Interrupts that should preempt execution to not preempt execution.
- Interrupts that should not preempt execution to preempt execution.

ICV_AP0R1 is only implemented in implementations that support 6 or more bits of priority. ICV_AP0R2 and ICV_AP0R3 are only implemented in implementations that support 7 bits of priority. Unimplemented registers are UNDEFINED.

Writing to the active priority registers in any order other than the following order might result in UNPREDICTABLE behavior of the interrupt prioritization system:

- ICV_AP0R<n>.
- ICV_AP1R<n>.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b1:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_AP0R[UInt(opc2<1:0>)];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_AP0R[UInt(opc2<1:0>)];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_AP0R[UInt(opc2<1:0>)];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_AP0R[UInt(opc2<1:0>)];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_AP0R[UInt(opc2<1:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b1:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_AP0R[UInt(opc2<1:0>)] = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_AP0R[UInt(opc2<1:0>)] = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_AP0R[UInt(opc2<1:0>)] = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_AP0R[UInt(opc2<1:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_AP0R[UInt(opc2<1:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_AP1R<n>, Interrupt Controller Virtual Active Priorities Group 1 Registers, n = 0 - 3

The ICV_AP1R<n> characteristics are:

Purpose

Provides information about virtual Group 1 active priorities.

Configuration

AArch32 System register ICV_AP1R<n> bits [31:0] are architecturally mapped to AArch64 System register ICV_AP1R<n>_EL1[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. If the PE resets into EL3 using AArch32 they apply only to the Secure instance of the register. Otherwise, RW directfields accessesin this register reset to ICV_AP1R<n> arearchitecturally UNKNOWN.values.

Attributes

ICV_AP1R<n> is a 32-bit register.

Field descriptions

The ICV_AP1R<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
IMPLEMENTATION DEFINED																															

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to `0`.

The contents of these registers are IMPLEMENTATION DEFINED with the one architectural requirement that the value `0x00000000` is consistent with no interrupts being active.

Accessing the ICV_AP1R<n>

Writing to these registers with any value other than the last read value of the register (or `0x00000000` when there are no Group 1 active priorities) might result in UNPREDICTABLE behavior of the virtual interrupt prioritization system, causing:

- Interrupts that should preempt execution to not preempt execution.
- Interrupts that should not preempt execution to preempt execution.

ICV_AP1R1 is only implemented in implementations that support 6 or more bits of priority. ICV_AP1R2 and ICV_AP1R3 are only implemented in implementations that support 7 bits of priority. Unimplemented registers are UNDEFINED.

Writing to the active priority registers in any order other than the following order might result in UNPREDICTABLE behavior of the interrupt prioritization system:

- ICV_AP0R<n>.
- ICV_AP1R<n>.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1001	0b0:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_AP1R[UInt(opc2<1:0>)];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_AP1R[UInt(opc2<1:0>)];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            return ICC_AP1R_S[UInt(opc2<1:0>)];
        else
            return ICC_AP1R_NS[UInt(opc2<1:0>)];
    else
        return ICC_AP1R[UInt(opc2<1:0>)];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        return ICC_AP1R_NS[UInt(opc2<1:0>)];
    else
        return ICC_AP1R[UInt(opc2<1:0>)];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            return ICC_AP1R_S[UInt(opc2<1:0>)];
        else
            return ICC_AP1R_NS[UInt(opc2<1:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1001	0b0:n[1:0]

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_AP1R[UInt(opc2<1:0>)] = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_AP1R[UInt(opc2<1:0>)] = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            ICC_AP1R_S[UInt(opc2<1:0>)] = R[t];
        else
            ICC_AP1R_NS[UInt(opc2<1:0>)] = R[t];
    else
        ICC_AP1R[UInt(opc2<1:0>)] = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        ICC_AP1R_NS[UInt(opc2<1:0>)] = R[t];
    else
        ICC_AP1R[UInt(opc2<1:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            ICC_AP1R_S[UInt(opc2<1:0>)] = R[t];
        else
            ICC_AP1R_NS[UInt(opc2<1:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_BPR0, Interrupt Controller Virtual Binary Point Register 0

The ICV_BPR0 characteristics are:

Purpose

Defines the point at which the priority value fields split into two parts, the group priority field and the subpriority field. The group priority field determines virtual Group 0 interrupt preemption.

Configuration

AArch32 System register ICV_BPR0 bits [31:0] are architecturally mapped to AArch64 System register ICV_BPR0_EL1[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to ICV_BPR0 arearchitecturally UNKNOWN.values.

Attributes

ICV_BPR0 is a 32-bit register.

Field descriptions

The ICV_BPR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																													BinaryPoint		

Bits [31:3]

Reserved, RES0.

BinaryPoint, bits [2:0]

The value of this field controls how the 8-bit interrupt priority field is split into a group priority field, that determines interrupt preemption, and a subpriority field. This is done as follows:

Binary point value	Group priority field	Subpriority field	Field with binary point
0	[7:1]	[0]	ggggggg.s
1	[7:2]	[1:0]	gggggg.ss
2	[7:3]	[2:0]	ggggg.sss
3	[7:4]	[3:0]	gggg.ssss
4	[7:5]	[4:0]	ggg.sssss
5	[7:6]	[5:0]	gg.ssssss
6	[7]	[6:0]	g.sssssss
7	No preemption	[7:0]	.ssssssss

This field resets to an architecturally UNKNOWN value.

Accessing the ICV_BPR0

The minimum binary point value is derived from the number of implemented priority bits. The number of priority bits is IMPLEMENTATION DEFINED, and reported by ICV_CTLR.PRIbits.

An attempt to program the binary point field to a value less than the minimum value sets the field to the minimum value. On a reset, the binary point field is set to the minimum supported value.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_BPR0;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_BPR0;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_BPR0;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_BPR0;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_BPR0;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_BPR0 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_BPR0 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_BPR0 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_BPR0 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_BPR0 = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_BPR1, Interrupt Controller Virtual Binary Point Register 1

The ICV_BPR1 characteristics are:

Purpose

Defines the point at which the priority value fields split into two parts, the group priority field and the subpriority field. The group priority field determines virtual Group 1 interrupt preemption.

Configuration

AArch32 System register ICV_BPR1 bits [31:0] are architecturally mapped to AArch64 System register ICV_BPR1_EL1[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. If the PE resets into EL3 using AArch32 they apply only to the Secure instance of the register. Otherwise, RW directfields accessesin this register reset to ICV_BPR1 arearchitecturally UNKNOWN.values.

Attributes

ICV_BPR1 is a 32-bit register.

Field descriptions

The ICV_BPR1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																													BinaryPoint		

Bits [31:3]

Reserved, RES0.

BinaryPoint, bits [2:0]

If the GIC is configured to use separate binary point fields for virtual Group 0 and virtual Group 1 interrupts, the value of this field controls how the 8-bit interrupt priority field is split into a group priority field, that determines interrupt preemption, and a subpriority field. This is done as follows:

Binary point value	Group priority field	Subpriority field	Field with binary point
0	-	-	-
1	[7:1]	[0]	ggggggg.s
2	[7:2]	[1:0]	gggggg.ss
3	[7:3]	[2:0]	ggggg.sss
4	[7:4]	[3:0]	gggg.ssss
5	[7:5]	[4:0]	ggg.sssss
6	[7:6]	[5:0]	gg.ssssss
7	[7]	[6:0]	g.sssssss

Writing 0 to this field will set this field to its reset value.

If ICV_CTLR.CBPR is set to 1, Non-secure EL1 reads return ICV_BPR0 + 1 saturated to `0b111`. Non-secure EL1 writes are ignored.

This field resets to an IMPLEMENTATION DEFINED non-zero value.

Accessing the ICV_BPR1

The reset value is IMPLEMENTATION DEFINED, but is equal to the minimum value of ICV_BPR0 plus one.

An attempt to program the binary point field to a value less than the reset value sets the field to the reset value.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_BPR1;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_BPR1;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            return ICC_BPR1_S;
        else
            return ICC_BPR1_NS;
    else
        return ICC_BPR1;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        return ICC_BPR1_NS;
    else
        return ICC_BPR1;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            return ICC_BPR1_S;
        else
            return ICC_BPR1_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_BPR1 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_BPR1 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            ICC_BPR1_S = R[t];
        else
            ICC_BPR1_NS = R[t];
    else
        ICC_BPR1 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        ICC_BPR1_NS = R[t];
    else
        ICC_BPR1 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            ICC_BPR1_S = R[t];
        else
            ICC_BPR1_NS = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_CTLR, Interrupt Controller Virtual Control Register

The ICV_CTLR characteristics are:

Purpose

Controls aspects of the behavior of the GIC virtual CPU interface and provides information about the features implemented.

Configuration

AArch32 System register ICV_CTLR bits [31:0] are architecturally mapped to AArch64 System register ICV_CTLR_EL1[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to ICV_CTLR arearchitecturally UNKNOWN.values.

Attributes

ICV_CTLR is a 32-bit register.

Field descriptions

The ICV_CTLR bit assignments are:

31 30 29 28 27 26 25 24 23 22 21 20	19	18	17 16	15	14	13 12 11	10 9 8	7 6 5 4 3 2	1	0
RES0	ExtRange	RSS	RES0	A3V	SEIS	IDbits	PRIbits	RES0	EOImode	CBPR

Bits [31:20]

Reserved, RES0.

ExtRange, bit [19]

Extended INTID range (read-only).

ExtRange	Meaning
0b0	CPU interface does not support INTIDs in the range 1024..8191. Behaviour is UNPREDICTABLE if the IRI delivers an interrupt in the range 1024 to 8191 to the CPU interface. **Note** Arm strongly recommends that the IRI is not configured to deliver interrupts in this range to a PE that does not support them.
0b1	CPU interface supports INTIDs in the range 1024..8191. All INTIDs in the range 1024..8191 are treated as requiring deactivation.

ICV_CTLR.ExtRange is an alias of ICC_CTLR.ExtRange.

RSS, bit [18]

Range Selector Support. Possible values are:

RSS	Meaning
0b0	Targeted SGIs with affinity level 0 values of 0 - 15 are supported.
0b1	Targeted SGIs with affinity level 0 values of 0 - 255 are supported.

This bit is read-only.

Bits [17:16]

Reserved, RES0.

A3V, bit [15]

Affinity 3 Valid. Read-only and writes are ignored. Possible values are:

A3V	Meaning
0b0	The virtual CPU interface logic only supports zero values of Affinity 3 in SGI generation System registers.
0b1	The virtual CPU interface logic supports non-zero values of Affinity 3 in SGI generation System registers.

SEIS, bit [14]

SEI Support. Read-only and writes are ignored. Indicates whether the virtual CPU interface supports local generation of SEIs:

SEIS	Meaning
0b0	The virtual CPU interface logic does not support local generation of SEIs.
0b1	The virtual CPU interface logic supports local generation of SEIs.

IDbits, bits [13:11]

Identifier bits. Read-only and writes are ignored. The number of virtual interrupt identifier bits supported:

IDbits	Meaning
0b000	16 bits.
0b001	24 bits.

All other values are reserved.

PRIbits, bits [10:8]

Priority bits. Read-only and writes are ignored. The number of priority bits implemented, minus one.

An implementation must implement at least 32 levels of physical priority (5 priority bits).

Note

This field always returns the number of priority bits implemented.

The division between group priority and subpriority is defined in the binary point registers ICV_BPR0 and ICV_BPR1.

Bits [7:2]

Reserved, RES0.

EOImode, bit [1]

Virtual EOI mode. Controls whether a write to an End of Interrupt register also deactivates the virtual interrupt:

EOImode	Meaning
0b0	ICV_EOIR0 and ICV_EOIR1 provide both priority drop and interrupt deactivation functionality. Accesses to ICV_DIR are UNPREDICTABLE.
0b1	ICV_EOIR0 and ICV_EOIR1 provide priority drop functionality only. ICV_DIR provides interrupt deactivation functionality.

This field resets to an architecturally UNKNOWN value.

CBPR, bit [0]

Common Binary Point Register. Controls whether the same register is used for interrupt preemption of both virtual Group 0 and virtual Group 1 interrupts:

CBPR	Meaning
0b0	ICV_BPR0 determines the preemption group for virtual Group 0 interrupts only. ICV_BPR1 determines the preemption group for virtual Group 1 interrupts.
0b1	ICV_BPR0 determines the preemption group for both virtual Group 0 and virtual Group 1 interrupts. Reads of ICV_BPR1 return ICV_BPR0 plus one, saturated to 0b111. Writes to ICV_BPR1 are ignored.

This field resets to an architecturally UNKNOWN value.

Accessing the ICV_CTLR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_CTLR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_CTLR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_CTLR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_CTLR;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            return ICC_CTLR_S;
        else
            return ICC_CTLR_NS;
    else
        return ICC_CTLR;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        return ICC_CTLR_NS;
    else
        return ICC_CTLR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            return ICC_CTLR_S;
        else
            return ICC_CTLR_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_CTLR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_CTLR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_CTLR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_CTLR = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            ICC_CTLR_S = R[t];
        else
            ICC_CTLR_NS = R[t];
    else
        ICC_CTLR = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        ICC_CTLR_NS = R[t];
    else
        ICC_CTLR = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            ICC_CTLR_S = R[t];
        else
            ICC_CTLR_NS = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_DIR, Interrupt Controller Deactivate Virtual Interrupt Register

The ICV_DIR characteristics are:

Purpose

When interrupt priority drop is separated from interrupt deactivation, a write to this register deactivates the specified virtual interrupt.

Configuration

AArch32 System register ICV_DIR bits [31:0] performs the same function as AArch64 System register ICV_DIR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICV_DIR are UNKNOWN.

Attributes

ICV_DIR is a 32-bit register.

Field descriptions

The ICV_DIR bit assignments are:



Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID of the virtual interrupt to be deactivated.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICV_CTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

Accessing the ICV_DIR

When EOImode == 0, writes are ignored. In systems supporting system error generation, an implementation might generate an SEI.

Accesses to this register use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TDIR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TDIR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_DIR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_DIR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_DIR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_DIR = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    else
        ICC_DIR = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_DIR = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_DIR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_EOIR0, Interrupt Controller Virtual End Of Interrupt Register 0

The ICV_EOIR0 characteristics are:

Purpose

A PE writes to this register to inform the CPU interface that it has completed the processing of the specified virtual Group 0 interrupt.

Configuration

AArch32 System register ICV_EOIR0 performs the same function as AArch64 System register ICV_EOIR0_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICV_EOIR0 are UNKNOWN.

Attributes

ICV_EOIR0 is a 32-bit register.

Field descriptions

The ICV_EOIR0 bit assignments are:



Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID from the corresponding ICV_IAR0 access.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICV_CTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

If the ICV_CTLR.EOImode bit is 0, a write to this register drops the priority for the virtual interrupt, and also deactivates the virtual interrupt.

If the ICV_CTLR.EOImode bit is 1, a write to this register only drops the priority for the virtual interrupt. Software must write to ICV_DIR to deactivate the virtual interrupt.

Accessing the ICV_EOIR0

A write to this register must correspond to the most recent valid read by this vPE from a Virtual Interrupt Acknowledge Register, and must correspond to the INTID that was read from ICV_IAR0, otherwise the system behavior is UNPREDICTABLE. A valid read is a read that returns a valid INTID that is not a special INTID.

Accesses to this register use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_EOIR0 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_EOIR0 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_EOIR0 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_EOIR0 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_EOIR0 = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_EOIR1, Interrupt Controller Virtual End Of Interrupt Register 1

The ICV_EOIR1 characteristics are:

Purpose

A PE writes to this register to inform the CPU interface that it has completed the processing of the specified virtual Group 1 interrupt.

Configuration

AArch32 System register ICV_EOIR1 performs the same function as AArch64 System register ICV_EOIR1_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICV_EOIR1 are UNKNOWN.

Attributes

ICV_EOIR1 is a 32-bit register.

Field descriptions

The ICV_EOIR1 bit assignments are:



Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID from the corresponding ICV_IAR1 access.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICV_CTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

If the ICV_CTLR.EOImode bit is 0, a write to this register drops the priority for the virtual interrupt, and also deactivates the virtual interrupt.

If the ICV_CTLR.EOImode bit is 1, a write to this register only drops the priority for the virtual interrupt. Software must write to ICV_DIR to deactivate the virtual interrupt.

Accessing the ICV_EOIR1

A write to this register must correspond to the most recent valid read by this vPE from a Virtual Interrupt Acknowledge Register, and must correspond to the INTID that was read from ICV_IAR1, otherwise the system behavior is UNPREDICTABLE. A valid read is a read that returns a valid INTID that is not a special INTID.

Accesses to this register use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_EOIR1 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_EOIR1 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_EOIR1 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_EOIR1 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_EOIR1 = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_HPPIR0, Interrupt Controller Virtual Highest Priority Pending Interrupt Register 0

The ICV_HPPIR0 characteristics are:

Purpose

Indicates the highest priority pending virtual Group 0 interrupt on the virtual CPU interface.

Configuration

AArch32 System register ICV_HPPIR0 performs the same function as AArch64 System register ICV_HPPIR0_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICV_HPPIR0 are UNKNOWN.

Attributes

ICV_HPPIR0 is a 32-bit register.

Field descriptions

The ICV_HPPIR0 bit assignments are:



Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID of the highest priority pending virtual interrupt.

If the highest priority pending interrupt is not observable, this field contains a special INTID to indicate the reason. This special INTID can take the value 1023 only. See Special INTIDs, for more information.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICV_CTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

Accessing the ICV_HPPIR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_HPPIR0;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_HPPIR0;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_HPPIR0;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_HPPIR0;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_HPPIR0;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_HPPIR1, Interrupt Controller Virtual Highest Priority Pending Interrupt Register 1

The ICV_HPPIR1 characteristics are:

Purpose

Indicates the highest priority pending virtual Group 1 interrupt on the virtual CPU interface.

Configuration

AArch32 System register ICV_HPPIR1 performs the same function as AArch64 System register ICV_HPPIR1_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICV_HPPIR1 are UNKNOWN.

Attributes

ICV_HPPIR1 is a 32-bit register.

Field descriptions

The ICV_HPPIR1 bit assignments are:



Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID of the highest priority pending virtual interrupt.

If the highest priority pending interrupt is not observable, this field contains a special INTID to indicate the reason. This special INTID can take the value 1023 only. See Special INTIDs, for more information.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICV_CTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

Accessing the ICV_HPPIR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_HPPIR1;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_HPPIR1;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_HPPIR1;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_HPPIR1;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_HPPIR1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_IAR0, Interrupt Controller Virtual Interrupt Acknowledge Register 0

The ICV_IAR0 characteristics are:

Purpose

The PE reads this register to obtain the INTID of the signaled virtual Group 0 interrupt. This read acts as an acknowledge for the interrupt.

Configuration

AArch32 System register ICV_IAR0 performs the same function as AArch64 System register ICV_IAR0_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICV_IAR0 are UNKNOWN.

To allow software to ensure appropriate observability of actions initiated by GIC register accesses, the PE and CPU interface logic must ensure that reads of this register are self-synchronising when interrupts are masked by the PE (that is when PSTATE.{I,F} == {0,0}). This ensures that the effect of activating an interrupt on the signaling of interrupt exceptions is observed when a read of this register is architecturally executed so that no spurious interrupt exception occurs if interrupts are unmasked by an instruction immediately following the read. See Observability of the effects of accesses to the GIC registers, for more information.

Attributes

ICV_IAR0 is a 32-bit register.

Field descriptions

The ICV_IAR0 bit assignments are:



Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID of the signaled virtual interrupt.

This is the INTID of the highest priority pending virtual interrupt, if that interrupt is of sufficient priority for it to be signaled to the PE, and if it can be acknowledged.

If the highest priority pending interrupt is not observable, this field contains a special INTID to indicate the reason. This special INTID can take the value 1023 only. See Special INTIDs, for more information.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICV_CTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

Accessing the ICV_IAR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_IAR0;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_IAR0;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IAR0;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IAR0;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_IAR0;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_IAR1, Interrupt Controller Virtual Interrupt Acknowledge Register 1

The ICV_IAR1 characteristics are:

Purpose

The PE reads this register to obtain the INTID of the signaled virtual Group 1 interrupt. This read acts as an acknowledge for the interrupt.

Configuration

AArch32 System register ICV_IAR1 performs the same function as AArch64 System register ICV_IAR1_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICV_IAR1 are UNKNOWN.

To allow software to ensure appropriate observability of actions initiated by GIC register accesses, the PE and CPU interface logic must ensure that reads of this register are self-synchronising when interrupts are masked by the PE (that is when PSTATE.{I,F} == {0,0}). This ensures that the effect of activating an interrupt on the signaling of interrupt exceptions is observed when a read of this register is architecturally executed so that no spurious interrupt exception occurs if interrupts are unmasked by an instruction immediately following the read. See Observability of the effects of accesses to the GIC registers, for more information.

Attributes

ICV_IAR1 is a 32-bit register.

Field descriptions

The ICV_IAR1 bit assignments are:



Bits [31:24]

Reserved, RES0.

INTID, bits [23:0]

The INTID of the signaled virtual interrupt.

This is the INTID of the highest priority pending virtual interrupt, if that interrupt is of sufficient priority for it to be signaled to the PE, and if it can be acknowledged.

If the highest priority pending interrupt is not observable, this field contains a special INTID to indicate the reason. This special INTID can take the value 1023 only. See Special INTIDs, for more information.

This field has either 16 or 24 bits implemented. The number of implemented bits can be found in ICV_CTLR.IDbits. If only 16 bits are implemented, bits [23:16] of this register are RES0.

Accessing the ICV_IAR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_IAR1;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_IAR1;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IAR1;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IAR1;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_IAR1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_IGRPEN0, Interrupt Controller Virtual Interrupt Group 0 Enable register

The ICV_IGRPEN0 characteristics are:

Purpose

Controls whether virtual Group 0 interrupts are enabled or not.

Configuration

AArch32 System register ICV_IGRPEN0 bits [31:0] are architecturally mapped to AArch64 System register ICV_IGRPEN0_EL1[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to ICV_IGRPEN0 arearchitecturally UNKNOWN.values.

Attributes

ICV_IGRPEN0 is a 32-bit register.

Field descriptions

The ICV_IGRPEN0 bit assignments are:



Bits [31:1]

Reserved, RES0.

Enable, bit [0]

Enables virtual Group 0 interrupts.

Enable	Meaning
0b0	Virtual Group 0 interrupts are disabled.
0b1	Virtual Group 0 interrupts are enabled.

This field resets to 0.

Accessing the ICV_IGRPEN0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_IGRPEN0;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_IGRPEN0;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IGRPEN0;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_IGRPEN0;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_IGRPEN0;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_IGRPEN0 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_IGRPEN0 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_IGRPEN0 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.FIQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.FIQ == '1' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_IGRPEN0 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_IGRPEN0 = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_IGRPEN1, Interrupt Controller Virtual Interrupt Group 1 Enable register

The ICV_IGRPEN1 characteristics are:

Purpose

Controls whether virtual Group 1 interrupts are enabled for the current Security state.

Configuration

AArch32 System register ICV_IGRPEN1 bits [31:0] are architecturally mapped to AArch64 System register ICV_IGRPEN1_EL1[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. If the PE resets into EL3 using AArch32 they apply only to the Secure instance of the register. Otherwise, RW directfields accessesin this register reset to ICV_IGRPEN1 arearchitecturally UNKNOWN.values.

Attributes

ICV_IGRPEN1 is a 32-bit register.

Field descriptions

The ICV_IGRPEN1 bit assignments are:



Bits [31:1]

Reserved, RES0.

Enable, bit [0]

Enables virtual Group 1 interrupts.

Enable	Meaning
0b0	Virtual Group 1 interrupts are disabled.
0b1	Virtual Group 1 interrupts are enabled.

This field resets to 0.

Accessing the ICV_IGRPEN1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_IGRPEN1;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_IGRPEN1;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            return ICC_IGRPEN1_S;
        else
            return ICC_IGRPEN1_NS;
    else
        return ICC_IGRPEN1;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        return ICC_IGRPEN1_NS;
    else
        return ICC_IGRPEN1;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            return ICC_IGRPEN1_S;
        else
            return ICC_IGRPEN1_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1100	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif ICC_SRE.SRE == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TALL1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TALL1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_IGRPEN1 = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_IGRPEN1 = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        if SCR.NS == '0' then
            ICC_IGRPEN1_S = R[t];
        else
            ICC_IGRPEN1_NS = R[t];
    else
        ICC_IGRPEN1 = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.IRQ == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.IRQ == '1' then
        AArch32.TakeMonitorTrapException();
    elsif HaveEL(EL3) then
        ICC_IGRPEN1_NS = R[t];
    else
        ICC_IGRPEN1 = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            ICC_IGRPEN1_S = R[t];
        else
            ICC_IGRPEN1_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_PMR, Interrupt Controller Virtual Interrupt Priority Mask Register

The ICV_PMR characteristics are:

Purpose

Provides a virtual interrupt priority filter. Only virtual interrupts with a higher priority than the value in this register are signaled to the PE.

Configuration

AArch32 System register ICV_PMR bits [31:0] are architecturally mapped to AArch64 System register ICV_PMR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICV_PMR are UNKNOWN.

To allow software to ensure appropriate observability of actions initiated by GIC register accesses, the PE and CPU interface logic must ensure that writes to this register are self-synchronising. This ensures that no interrupts below the written PMR value will be taken after a write to this register is architecturally executed. See Observability of the effects of accesses to the GIC registers, for more information.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

ICV_PMR is a 32-bit register.

Field descriptions

The ICV_PMR bit assignments are:



Bits [31:8]

Reserved, RES0.

Priority, bits [7:0]

The priority mask level for the virtual CPU interface. If the priority of a virtual interrupt is higher than the value indicated by this field, the interface signals the virtual interrupt to the PE.

The possible priority field values are as follows:

Implemented priority bits	Possible priority field values	Number of priority levels
[7:0]	0x00-0xFF (0-255), all values	256
[7:1]	0x00-0xFE (0-254), even values only	128
[7:2]	0x00-0xFC (0-252), in steps of 4	64
[7:3]	0x00-0xF8 (0-248), in steps of 8	32
[7:4]	0x00-0xF0 (0-240), in steps of 16	16

Unimplemented priority bits are RAZ/WI.

This field resets to 0.

Accessing the ICV_PMR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0100	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_PMR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_PMR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_PMR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_PMR;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_PMR;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_PMR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_PMR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0100	0b0110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        ICV_PMR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        ICV_PMR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        ICV_PMR = R[t];
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        ICV_PMR = R[t];
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    else
        ICC_PMR = R[t];
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    else
        ICC_PMR = R[t];
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        ICC_PMR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ICV_RPR, Interrupt Controller Virtual Running Priority Register

The ICV_RPR characteristics are:

Purpose

Indicates the Running priority of the virtual CPU interface.

Configuration

AArch32 System register ICV_RPR performs the same function as AArch64 System register ICV_RPR_EL1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ICV_RPR are UNKNOWN.

Attributes

ICV_RPR is a 32-bit register.

Field descriptions

The ICV_RPR bit assignments are:



Bits [31:8]

Reserved, RES0.

Priority, bits [7:0]

The current running priority on the virtual CPU interface. This is the group priority of the current active virtual interrupt.

The priority returned is the group priority as if the BPR for the current Exception level and Security state was set to the minimum value of BPR for the number of implemented priority bits.

Note

If 8 bits of priority are implemented the group priority is bits[7:1] of the priority.

Accessing the ICV_RPR

If there are no active interrupts on the virtual CPU interface, or all active interrupts have undergone a priority drop, the value returned is the Idle priority.

Software cannot determine the number of implemented priority bits from a read of this register.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b1011	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && ICH_HCR_EL2.TC == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ICH_HCR.TC == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.FMO == '1' then
        return ICV_RPR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.IMO == '1' then
        return ICV_RPR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.FMO == '1' then
        return ICV_RPR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.IMO == '1' then
        return ICV_RPR;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SCR.<IRQ,FIQ> == '11'
then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_RPR;
elsif PSTATE.EL == EL2 then
    if ICC_HSRE.SRE == '0' then
        UNDEFINED;
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && SCR_EL3.<IRQ,FIQ> == '11' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.<IRQ,FIQ> == '11' then
        AArch32.TakeMonitorTrapException();
    else
        return ICC_RPR;
elsif PSTATE.EL == EL3 then
    if ICC_MSRE.SRE == '0' then
        UNDEFINED;
    else
        return ICC_RPR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_AFR0, Auxiliary Feature Register 0

The ID_AFR0 characteristics are:

Purpose

Provides information about the IMPLEMENTATION DEFINED features of the PE in AArch32 state.

Must be interpreted with the Main ID Register, MIDR.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_AFR0 bits [31:0] are architecturally mapped to AArch64 System register ID_AFR0_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_AFR0 are UNKNOWN.

Attributes

ID_AFR0 is a 32-bit register.

Field descriptions

The ID_AFR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																IMPLEMENTATION DEFINED				IMPLEMENTATION DEFINED				IMPLEMENTATION DEFINED				IMPLEMENTATION DEFINED			

Bits [31:16]

Reserved, RES0.

IMPLEMENTATION DEFINED, bits [15:12]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [11:8]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [7:4]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED, bits [3:0]

IMPLEMENTATION DEFINED.

Accessing the ID_AFR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0001	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_AFR0;
elsif PSTATE.EL == EL2 then
    return ID_AFR0;
elsif PSTATE.EL == EL3 then
    return ID_AFR0;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_DFR0, Debug Feature Register 0

The ID_DFR0 characteristics are:

Purpose

Provides top level information about the debug system in AArch32 state.

Must be interpreted with the Main ID Register, MIDR.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_DFR0 bits [31:0] are architecturally mapped to AArch64 System register ID_DFR0_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_DFR0 are UNKNOWN.

Attributes

ID_DFR0 is a 32-bit register.

Field descriptions

The ID_DFR0 bit assignments are:



TraceFilt, bits [31:28]

Armv8.4 Self-hosted Trace Extension version. Defined values are:

TraceFilt	Meaning
0b0000	Armv8.4 Self-hosted Trace Extension not implemented.
0b0001	Armv8.4 Self-hosted Trace Extension implemented.

All other values are reserved.

ARMv8.4-Trace implements the functionality added by the value 0b0001.

From Armv8.3, the permitted values are 0b0000 and 0b0001.

PerfMon, bits [27:24]

Performance Monitors Extension version.

This field does not follow the standard ID scheme, but uses the alternative ID scheme described in Alternative ID scheme used for the Performance Monitors Extension version.

Defined values are:

PerfMon	Meaning
0b0000	Performance Monitors Extension not implemented.
0b0001	Performance Monitors Extension version 1 implemented, PMUv1.
0b0010	Performance Monitors Extension version 2 implemented, PMUv2.
0b0011	Performance Monitors Extension version 3 implemented, PMUv3.
0b0100	PMUv3 for Armv8.1. As 0b0011, and also includes support for: • Extended 16-bit PMEVTYPER<n>.evtCount field. • If EL2 is implemented, the HDCR.HPMD control bit.
0b0101	PMUv3 for Armv8.4. As 0b0100 and also includes support for the PMMIR register.
0b0110	PMUv3 for Armv8.5. As 0b0101 and also includes support for: • 64-bit event counters. • If EL2 is implemented, the HDCR.HCCD control bit. • If EL3 is implemented, the SDCR.SCCD control bit.
0b1111	IMPLEMENTATION DEFINED form of performance monitors supported, PMUv3 not supported. Arm does not recommend this value in new implementations.

ARMv8.1-PMU implements the functionality added by the value 0b0100.

ARMv8.4-PMU implements the functionality added by the value 0b0101.

ARMv8.5-PMU implements the functionality added by the value 0b0110.

All other values are reserved.

In any Armv8 implementation, the values 0b0001 and 0b0010 are not permitted.

From Armv8.1, the value 0b0011 is not permitted.

From Armv8.4, the value 0b0100 is not permitted.

From Armv8.5, the value 0b0101 is not permitted.

Note

In Armv7, the value 0b0000 can mean that PMUv1 is implemented. PMUv1 is not permitted in an Armv8 implementation.

MProfDbg, bits [23:20]

M Profile Debug. Support for memory-mapped debug model for M profile processors. Defined values are:

MProfDbg	Meaning
0b0000	Not supported.
0b0001	Support for M profile Debug architecture, with memory-mapped access.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0000.

MMapTrc	Meaning
0b0000	Not supported.
0b0001	Support for Arm trace architecture, with memory-mapped access.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

See the ETM Architecture Specification for more information.

CopTrc, bits [15:12]

Support for System registers-based trace model, using registers in the coproc == 0b1110 encoding space. Defined values are:

CopTrc	Meaning
0b0000	Not supported.
0b0001	Support for Arm trace architecture, with System registers access.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

See the ETM Architecture Specification for more information.

BitsMMapTrc, bits [19:1216]

Reserved,Memory Mapped Trace. Support for memory-mapped trace model. Defined values are: RES0.

MMapDbg, bits [11:8]

Memory Mapped Debug. Support for v7 memory-mapped debug model, for A and R profile processors.

In Armv8-A, this field is RES0.

The optional memory map defined by Armv8 is not compatible with Armv7.

CopSDbg, bits [7:4]

Support for a System registers-based Secure debug model, using registers in the coproc = 0b1110 encoding space, for an A profile processor that includes EL3.

If EL3 is not implemented and the implemented Security state is Non-secure state, this field is RES0. Otherwise, this field reads the same as bits [3:0].

CopDbg, bits [3:0]

Support for System registers-based debug model, using registers in the coproc == 0b1110 encoding space, for A and R profile processors. Defined values are:

CopDbg	Meaning
0b0000	Not supported.
0b0010	Support for Armv6, v6 Debug architecture, with System registers access.
0b0011	Support for Armv6, v6.1 Debug architecture, with System registers access.
0b0100	Support for Armv7, v7 Debug architecture, with System registers access.
0b0101	Support for Armv7, v7.1 Debug architecture, with System registers access.
0b0110	Support for Armv8 debug architecture, with System registers access.
0b0111	Support for Armv8 debug architecture, with System registers access, and Virtualization Host extensions.
0b1000	Support for Armv8.2 debug architecture.
0b1001	Support for Armv8.4 debug architecture.

All other values are reserved.

In any Armv8 implementation, the values 0b0000, 0b0010, 0b0011, 0b0100, and 0b0101 are not permitted.

If ARMv8.1-VHE is not implemented, the only permitted value is 0b0110.

In an Armv8.0 implementation, the value 0b1000 is not permitted.

Accessing the ID_DFR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0001	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_DFR0;
elsif PSTATE.EL == EL2 then
    return ID_DFR0;
elsif PSTATE.EL == EL3 then
    return ID_DFR0;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_DFR1, Debug Feature Register 1

The ID_DFR1 characteristics are:

Purpose

Provides top level information about the debug system in AArch32.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_DFR1 bits [31:0] are architecturally mapped to AArch64 System register ID_DFR1_EL1[31:0] .

This register is present only when~~from~~ AArch32 is supported at any Exception level.~~Armv8.6.~~ Otherwise, direct accesses to ID_DFR1 are RES0.

Note

Prior to the introduction of the features described by this register, this register was unnamed and reserved, RES0 from EL1, EL2, and EL3.

Attributes

ID_DFR1 is a 32-bit register.

Field descriptions

The ID_DFR1 bit assignments are:



Bits [31:4]

Reserved, RES0.

MTPMU, bits [3:0]

~~**From Armv8.6:**~~

Multi-threaded PMU extension. Defined values are:

MTPMU	Meaning
0b0000	ARMv8.6-MTPMU not implemented. If PMUv3 is implemented, it is IMPLEMENTATION DEFINED whether PMEVTYPER<n>.MT are read/write or RES0.
0b0001	ARMv8.6-MTPMU implemented and PMEVTYPER<n>.MT are read/write. When ARMv8.6-MTPMU is disabled, the Effective values of PMEVTYPER<n>.MT are 0.
0b1111	ARMv8.6-MTPMU not implemented. If PMUv3 is implemented, PMEVTYPER<n>.MT are RES0.

All other values are reserved.

ARMv8.6-MTPMU implements the functionality identified by the value `0b0001`.

In an Armv8.6-compliant implementation that includes PMUv3, the value `0b0000` is not permitted.

In an implementation that does not include PMUv3, the value `0b0001` is not permitted.

Otherwise:

~~Reserved, RES0.~~

Accessing the ID_DFR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0011	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!IsZero(ID_DFR1) || boolean
IMPLEMENTATION_DEFINED "ID_DFR1 trapped by HCR_EL2.TID3") && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && (!IsZero(ID_DFR1) || boolean
IMPLEMENTATION_DEFINED "ID_DFR1 trapped by HCR.TID3") && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_DFR1;
elsif PSTATE.EL == EL2 then
    return ID_DFR1;
elsif PSTATE.EL == EL3 then
    return ID_DFR1;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR0, Instruction Set Attribute Register 0

The ID_ISAR0 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR1, ID_ISAR2, ID_ISAR3, ID_ISAR4, and ID_ISAR5.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_ISAR0 bits [31:0] are architecturally mapped to AArch64 System register ID_ISAR0_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_ISAR0 are UNKNOWN.

Attributes

ID_ISAR0 is a 32-bit register.

Field descriptions

The ID_ISAR0 bit assignments are:

31 30 29 28	27 26 25 24	23 22 21 20	19 18 17 16	15 14 13 12	11 10 9 8	7 6 5 4	3 2 1 0
RES0	Divide	Debug	Coproc	CmpBranch	BitField	BitCount	Swap

Bits [31:28]

Reserved, RES0.

Divide, bits [27:24]

Indicates the implemented Divide instructions. Defined values are:

Divide	Meaning
0b0000	None implemented.
0b0001	Adds SDIV and UDIV in the T32 instruction set.
0b0010	As for 0b0001, and adds SDIV and UDIV in the A32 instruction set.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

Debug, bits [23:20]

Indicates the implemented Debug instructions. Defined values are:

Debug	Meaning
0b0000	None implemented.
0b0001	Adds BKPT.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

Coproc, bits [19:16]

Indicates the implemented System register access instructions. Defined values are:

Coproc	Meaning
0b0000	None implemented, except for instructions separately attributed by the architecture to provide access to AArch32 System registers and System instructions.
0b0001	Adds generic CDP, LDC, MCR, MRC, and STC.
0b0010	As for 0b0001, and adds generic CDP2, LDC2, MCR2, MRC2, and STC2.
0b0011	As for 0b0010, and adds generic MCRR and MRRC.
0b0100	As for 0b0011, and adds generic MCRR2 and MRRC2.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

CmpBranch, bits [15:12]

Indicates the implemented combined Compare and Branch instructions in the T32 instruction set. Defined values are:

CmpBranch	Meaning
0b0000	None implemented.
0b0001	Adds CBNZ and CBZ.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

BitField, bits [11:8]

Indicates the implemented BitField instructions. Defined values are:

BitField	Meaning
0b0000	None implemented.
0b0001	Adds BFC, BFI, SBFX, and UBFX.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

BitCount, bits [7:4]

Indicates the implemented Bit Counting instructions. Defined values are:

BitCount	Meaning
0b0000	None implemented.
0b0001	Adds CLZ.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

Swap, bits [3:0]

Indicates the implemented Swap instructions in the A32 instruction set. Defined values are:

Swap	Meaning
0b0000	None implemented.
0b0001	Adds SWP and SWPB.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

Accessing the ID_ISAR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_ISAR0;
elsif PSTATE.EL == EL2 then
    return ID_ISAR0;
elsif PSTATE.EL == EL3 then
    return ID_ISAR0;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR1, Instruction Set Attribute Register 1

The ID_ISAR1 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0, ID_ISAR2, ID_ISAR3, ID_ISAR4, and ID_ISAR5.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_ISAR1 bits [31:0] are architecturally mapped to AArch64 System register ID_ISAR1_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_ISAR1 are UNKNOWN.

Attributes

ID_ISAR1 is a 32-bit register.

Field descriptions

The ID_ISAR1 bit assignments are:

31 30 29 28	27 26 25 24	23 22 21 20	19 18 17 16	15 14 13 12	11 10 9 8	7 6 5 4	3 2 1 0
Jazelle	Interwork	Immediate	IfThen	Extend	Except_AR	Except	Endian

Jazelle, bits [31:28]

Indicates the implemented Jazelle extension instructions. Defined values are:

Jazelle	Meaning
0b0000	No support for Jazelle.
0b0001	Adds the BXJ instruction, and the J bit in the PSR. This setting might indicate a trivial implementation of the Jazelle extension.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

Interwork, bits [27:24]

Indicates the implemented Interworking instructions. Defined values are:

Interwork	Meaning
0b0000	None implemented.
0b0001	Adds the BX instruction, and the T bit in the PSR.
0b0010	As for 0b0001, and adds the BLX instruction. PC loads have BX-like behavior.
0b0011	As for 0b0010, and guarantees that data-processing instructions in the A32 instruction set with the PC as the destination and the S bit clear have BX-like behavior.

All other values are reserved.

In Armv8-A the only permitted value is 0b0011.

Immediate, bits [23:20]

Indicates the implemented data-processing instructions with long immediates. Defined values are:

Immediate	Meaning
0b0000	None implemented.
0b0001	Adds: • The MOVT instruction • The MOV instruction encodings with zero-extended 16-bit immediates. • The T32 ADD and SUB instruction encodings with zero-extended 12-bit immediates, and the other ADD, ADR, and SUB encodings cross-referenced by the pseudocode for those encodings.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

IfThen, bits [19:16]

Indicates the implemented If-Then instructions in the T32 instruction set. Defined values are:

IfThen	Meaning
0b0000	None implemented.
0b0001	Adds the IT instructions, and the IT bits in the PSRs.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

Extend, bits [15:12]

Indicates the implemented Extend instructions. Defined values are:

Extend	Meaning
0b0000	No scalar sign-extend or zero-extend instructions are implemented, where scalar instructions means non-Advanced SIMD instructions.
0b0001	Adds the SXTB, SXTH, UXTB, and UXTH instructions.
0b0010	As for 0b0001, and adds the SXTB16, SXTAB, SXTAB16, SXTAH, UXTB16, UXTAB, UXTAB16, and UXTAH instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

Except_AR, bits [11:8]

Indicates the implemented A and R profile exception-handling instructions. Defined values are:

Except_AR	Meaning
0b0000	None implemented.
0b0001	Adds the SRS and RFE instructions, and the A and R profile forms of the CPS instruction.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

Except, bits [7:4]

Indicates the implemented exception-handling instructions in the A32 instruction set. Defined values are:

Except	Meaning
0b0000	Not implemented. This indicates that the User bank and Exception return forms of the LDM and STM instructions are not implemented.
0b0001	Adds the LDM (exception return), LDM (user registers), and STM (user registers) instruction versions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

Endian, bits [3:0]

Indicates the implemented Endian instructions. Defined values are:

Endian	Meaning
0b0000	None implemented.
0b0001	Adds the SETEND instruction, and the E bit in the PSRs.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0001.

Accessing the ID_ISAR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_ISAR1;
elsif PSTATE.EL == EL2 then
    return ID_ISAR1;
elsif PSTATE.EL == EL3 then
    return ID_ISAR1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR2, Instruction Set Attribute Register 2

The ID_ISAR2 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0, ID_ISAR1, ID_ISAR3, ID_ISAR4, and ID_ISAR5.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_ISAR2 bits [31:0] are architecturally mapped to AArch64 System register ID_ISAR2_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_ISAR2 are UNKNOWN.

Attributes

ID_ISAR2 is a 32-bit register.

Field descriptions

The ID_ISAR2 bit assignments are:



Reversal, bits [31:28]

Indicates the implemented Reversal instructions. Defined values are:

Reversal	Meaning
0b0000	None implemented.
0b0001	Adds the REV, REV16, and REVSH instructions.
0b0010	As for 0b0001, and adds the RBIT instruction.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

PSR_AR, bits [27:24]

Indicates the implemented A and R profile instructions to manipulate the PSR. Defined values are:

PSR_AR	Meaning
0b0000	None implemented.
0b0001	Adds the MRS and MSR instructions, and the exception return forms of data-processing instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

The exception return forms of the data-processing instructions are:

- In the A32 instruction set, data-processing instructions with the PC as the destination and the S bit set. These instructions might be affected by the WithShifts attribute.
- In the T32 instruction set, the SUBS PC,LR,#N instruction.

MultU, bits [23:20]

Indicates the implemented advanced unsigned Multiply instructions. Defined values are:

MultU	Meaning
0b0000	None implemented.
0b0001	Adds the UMULL and UMLAL instructions.
0b0010	As for 0b0001, and adds the UMAAL instruction.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

MultS, bits [19:16]

Indicates the implemented advanced signed Multiply instructions. Defined values are:

MultS	Meaning
0b0000	None implemented.
0b0001	Adds the SMULL and SMLAL instructions.
0b0010	As for 0b0001, and adds the SMLABB, SMLABT, SMLALBB, SMLALBT, SMLALTB, SMLALTT, SMLATB, SMLATT, SMLAWB, SMLAWT, SMULBB, SMULBT, SMULTB, SMULTT, SMULWB, and SMULWT instructions. Also adds the Q bit in the PSRs.
0b0011	As for 0b0010, and adds the SMLAD, SMLADX, SMLALD, SMLALDX, SMLSD, SMLSDX, SMLSLD, SMLSLDX, SMMLA, SMMLAR, SMMLS, SMMLSR, SMMUL, SMMULR, SMUAD, SMUADX, SMUSD, and SMUSDX instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0011.

Mult, bits [15:12]

Indicates the implemented additional Multiply instructions. Defined values are:

Mult	Meaning
0b0000	No additional instructions implemented. This means only MUL is implemented.
0b0001	Adds the MLA instruction.
0b0010	As for 0b0001, and adds the MLS instruction.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

MultiAccessInt, bits [11:8]

Indicates the support for interruptible multi-access instructions. Defined values are:

MultiAccessInt	Meaning
0b0000	No support. This means the LDM and STM instructions are not interruptible.
0b0001	LDM and STM instructions are restartable.
0b0010	LDM and STM instructions are continuable.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

MemHint, bits [7:4]

Indicates the implemented Memory Hint instructions. Defined values are:

MemHint	Meaning
0b0000	None implemented.
0b0001	Adds the PLD instruction.
0b0010	Adds the PLD instruction. (0b0001 and 0b0010 have identical effects.)
0b0011	As for 0b0001 (or 0b0010), and adds the PLI instruction.
0b0100	As for 0b0011, and adds the PLDW instruction.

All other values are reserved.

In Armv8-A the only permitted value is 0b0100.

LoadStore, bits [3:0]

Indicates the implemented additional load/store instructions. Defined values are:

LoadStore	Meaning
0b0000	No additional load/store instructions implemented.
0b0001	Adds the LDRD and STRD instructions.
0b0010	As for 0b0001, and adds the Load Acquire (LDAB, LDAH, LDA, LDAEXB, LDAEXH, LDAEX, LDAEXD) and Store Release (STLB, STLH, STL, STLEXB, STLEXH, STLEX, STLEXD) instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

Accessing the ID_ISAR2

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0010	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_ISAR2;
elsif PSTATE.EL == EL2 then
    return ID_ISAR2;
elsif PSTATE.EL == EL3 then
    return ID_ISAR2;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR3, Instruction Set Attribute Register 3

The ID_ISAR3 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0, ID_ISAR1, ID_ISAR2, ID_ISAR4, and ID_ISAR5.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_ISAR3 bits [31:0] are architecturally mapped to AArch64 System register ID_ISAR3_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_ISAR3 are UNKNOWN.

Attributes

ID_ISAR3 is a 32-bit register.

Field descriptions

The ID_ISAR3 bit assignments are:



T32EE, bits [31:28]

Indicates the implemented T32EE instructions. Defined values are:

T32EE	Meaning
0b0000	None implemented.
0b0001	Adds the ENTERX and LEAVEX instructions, and modifies the load behavior to include null checking.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

TrueNOP, bits [27:24]

Indicates the implemented true NOP instructions. Defined values are:

TrueNOP	Meaning
0b0000	None implemented. This means there are no NOP instructions that do not have any register dependencies.
0b0001	Adds true NOP instructions in both the T32 and A32 instruction sets. This also permits additional NOP-compatible hints.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

T32Copy, bits [23:20]

Indicates the support for T32 non flag-setting MOV instructions. Defined values are:

T32Copy	Meaning
0b0000	Not supported. This means that in the T32 instruction set, encoding T1 of the MOV (register) instruction does not support a copy from a low register to a low register.
0b0001	Adds support for T32 instruction set encoding T1 of the MOV (register) instruction, copying from a low register to a low register.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

TabBranch, bits [19:16]

Indicates the implemented Table Branch instructions in the T32 instruction set. Defined values are:

TabBranch	Meaning
0b0000	None implemented.
0b0001	Adds the TBB and TBH instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

SynchPrim, bits [15:12]

Used in conjunction with ID_ISAR4.SynchPrim_frac to indicate the implemented Synchronization Primitive instructions. Defined values are:

SynchPrim	Meaning
0b0000	If SynchPrim_frac == 0b000, no Synchronization Primitives implemented.
0b0001	If SynchPrim_frac == 0b000, adds the LDREX and STREX instructions. If SynchPrim_frac == 0b011, also adds the CLREX, LDREXB, STREXB, and STREXH instructions.
0b0010	If SynchPrim_frac == 0b000, as for [0b001, 0b011] and also adds the LDREXD and STREXD instructions.

All other combinations of SynchPrim and SynchPrim_frac are reserved.

In Armv8-A the only permitted value is 0b0010.

SVC, bits [11:8]

Indicates the implemented SVC instructions. Defined values are:

SVC	Meaning
0b0000	Not implemented.
0b0001	Adds the SVC instruction.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

SIMD, bits [7:4]

Indicates the implemented SIMD instructions. Defined values are:

SIMD	Meaning
0b0000	None implemented.
0b0001	Adds the SSAT and USAT instructions, and the Q bit in the PSRs.
0b0011	As for 0b0001, and adds the PKHBT, PKHTB, QADD16, QADD8, QASX, QSUB16, QSUB8, QSAX, SADD16, SADD8, SASX, SEL, SHADD16, SHADD8, SHASX, SHSUB16, SHSUB8, SHSAX, SSAT16, SSUB16, SSUB8, SSAX, SXTAB16, SXTB16, UADD16, UADD8, UASX, UHADD16, UHADD8, UHASX, UHSUB16, UHSUB8, UHSAX, UQADD16, UQADD8, UQASX, UQSUB16, UQSUB8, UQSAX, USAD8, USADA8, USAT16, USUB16, USUB8, USAX, UXTAB16, and UXTB16 instructions. Also adds support for the GE[3:0] bits in the PSRs.

All other values are reserved.

In Armv8-A the only permitted value is 0b0011.

The SIMD field relates only to implemented instructions that perform SIMD operations on the general-purpose registers. In an implementation that supports floating-point and Advanced SIMD instructions, MVFR0, MVFR1, and MVFR2 give information about the implemented Advanced SIMD instructions.

Saturate, bits [3:0]

Indicates the implemented Saturate instructions. Defined values are:

Saturate	Meaning
0b0000	None implemented. This means no non-Advanced SIMD saturate instructions are implemented.
0b0001	Adds the QADD, QDADD, QDSUB, and QSUB instructions, and the Q bit in the PSRs.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

Accessing the ID_ISAR3

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0010	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_ISAR3;
elsif PSTATE.EL == EL2 then
    return ID_ISAR3;
elsif PSTATE.EL == EL3 then
    return ID_ISAR3;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR4, Instruction Set Attribute Register 4

The ID_ISAR4 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0, ID_ISAR1, ID_ISAR2, ID_ISAR3, and ID_ISAR5.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_ISAR4 bits [31:0] are architecturally mapped to AArch64 System register ID_ISAR4_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_ISAR4 are UNKNOWN.

Attributes

ID_ISAR4 is a 32-bit register.

Field descriptions

The ID_ISAR4 bit assignments are:

31 30 29 28	27 26 25 24	23 22 21 20	19 18 17 16	15 14 13 12	11 10 9 8	7 6 5 4	3 2 1 0
SWP_frac	PSR_M	SynchPrim_frac	Barrier	SMC	Writeback	WithShifts	Unpriv

SWP_frac, bits [31:28]

Indicates support for the memory system locking the bus for SWP or SWPB instructions. Defined values are:

SWP_frac	Meaning
0b0000	SWP or SWPB instructions not implemented.
0b0001	SWP or SWPB implemented but only in a uniprocessor context. SWP and SWPB do not guarantee whether memory accesses from other masters can come between the load memory access and the store memory access of the SWP or SWPB.

All other values are reserved. This field is valid only if ~~the~~ ID_ISAR0.Swap~~Swap_instrs field~~ is 0b0000.

In Armv8-A, the only permitted value is 0b0000.

PSR_M, bits [27:24]

Indicates the implemented M profile instructions to modify the PSRs. Defined values are:

PSR_M	Meaning
0b0000	None implemented.
0b0001	Adds the M profile forms of the CPS, MRS, and MSR instructions.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0000.

SynchPrim_frac, bits [23:20]

Used in conjunction with ID_ISAR3.SynchPrim to indicate the implemented Synchronization Primitive instructions. Possible values are:

SynchPrim_frac	Meaning
0b0000	If SynchPrim == 0b0000, no Synchronization Primitives implemented. If SynchPrim == 0b0001, adds the LDREX and STREX instructions. If SynchPrim == 0b0010, also adds the CLREX, LDREXB, LDREXH, STREXB, STREXH, LDREXD, and STREXD instructions.
0b0011	If SynchPrim == 0b0001, adds the LDREX, STREX, CLREX, LDREXB, LDREXH, STREXB, and STREXH instructions.

All other combinations of SynchPrim and SynchPrim_frac are reserved.

In Armv8-A, the only permitted value is 0b0000.

Barrier, bits [19:16]

Indicates the implemented Barrier instructions in the A32 and T32 instruction sets. Defined values are:

Barrier	Meaning
0b0000	None implemented. Barrier operations are provided only as System instructions in the (coproc==0b1111) encoding space.
0b0001	Adds the DMB, DSB, and ISB barrier instructions.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

SMC, bits [15:12]

Indicates the implemented SMC instructions. Defined values are:

SMC	Meaning
0b0000	None implemented.
0b0001	Adds the SMC instruction.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

Writeback, bits [11:8]

Indicates the support for Writeback addressing modes. Defined values are:

Writeback	Meaning
0b0000	Basic support. Only the LDM, STM, PUSH, POP, SRS, and RFE instructions support writeback addressing modes. These instructions support all of their writeback addressing modes.
0b0001	Adds support for all of the writeback addressing modes.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0001.

WithShifts, bits [7:4]

Indicates the support for instructions with shifts. Defined values are:

WithShifts	Meaning
0b0000	Nonzero shifts supported only in MOV and shift instructions.
0b0001	Adds support for shifts of loads and stores over the range LSL 0-3.
0b0011	As for 0b0001, and adds support for other constant shift options, both on load/store and other instructions.
0b0100	As for 0b0011, and adds support for register-controlled shift options.

All other values are reserved.

In Armv8-A the only permitted value is 0b0100.

Unpriv, bits [3:0]

Indicates the implemented unprivileged instructions. Defined values are:

Unpriv	Meaning
0b0000	None implemented. No T variant instructions are implemented.
0b0001	Adds the LDRBT, LDRT, STRBT, and STRT instructions.
0b0010	As for 0b0001, and adds the LDRHT, LDRSBT, LDRSHT, and STRHT instructions.

All other values are reserved.

In Armv8-A, the only permitted value is 0b0010.

Accessing the ID_ISAR4

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0010	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_ISAR4;
elsif PSTATE.EL == EL2 then
    return ID_ISAR4;
elsif PSTATE.EL == EL3 then
    return ID_ISAR4;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR5, Instruction Set Attribute Register 5

The ID_ISAR5 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0, ID_ISAR1, ID_ISAR2, ID_ISAR3, and ID_ISAR4.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_ISAR5 bits [31:0] are architecturally mapped to AArch64 System register ID_ISAR5_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_ISAR5 are UNKNOWN.

Attributes

ID_ISAR5 is a 32-bit register.

Field descriptions

The ID_ISAR5 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
VCMA				RDM				RES0				CRC32				SHA2				SHA1				AES				SEVL			

VCMA, bits [31:28]

~~**From Armv8.3:**~~

Indicates AArch32 support for complex number addition and multiplication where numbers are stored in vectors. Defined values are:

VCMA	Meaning
0b0000	The VCMLA and VCADD instructions are not implemented in AArch32.
0b0001	The VCMLA and VCADD instructions are implemented in AArch32.

All other values are reserved.

~~**RDM, bits [27:24]**~~

~~**From Armv8.1:**~~

~~Indicates whether the VQRDMLAH and VQRDMLSH instructions are implemented in AArch32 state. Defined values are:~~

ARMv8.3-CompNum implements~~In Armv8.0, Armv8.1 and Armv8.2~~ the functionality~~only~~ identified~~permitted~~ by~~value is~~ 0b0001~~0b0000~~.

From Armv8.3, the only permitted value is 0b0001.

From Armv8.3 the only permitted value is 0b0001. This feature is identified as ARMv8.3-CompNum.

Otherwise:

RDM, bits [27:24]

Indicates support for the VQRDMLAH and VQRDMLSH instructions in AArch32 state. Defined values are:

Reserved, RES0.

RDM	Meaning
0b0000	No VQRDMLAH and VQRDMLSH instructions implemented.
0b0001	VQRDMLAH and VQRDMLSH instructions implemented.

All other values are reserved.

ARMv8.1-RDMA implements the functionality identified by the value 0b0001.

Otherwise:

Reserved, RES0.

From Armv8.1, the only permitted value is 0b0001.

Bits [23:20]

Reserved, RES0.

CRC32, bits [19:16]

Indicates supportswhether for the CRC32 instructions are implemented in AArch32 state. Defined values are:

CRC32	Meaning
0b0000	No CRC32 instructions implemented.
0b0001	CRC32B, CRC32H, CRC32W, CRC32CB, CRC32CH, and CRC32CW instructions implemented.

All other values are reserved.

In Armv8.0 the permitted values are 0b0000 and 0b0001.

From Armv8.1, the only permitted value is 0b0001.

SHA2, bits [15:12]

Indicates supportswhether for the SHA2 instructions are implemented in AArch32 state.

SHA2	Meaning
0b0000	No SHA2 instructions implemented.
0b0001	SHA256H, SHA256H2, SHA256SU0, and SHA256SU1 implemented.

All other values are reserved.

In Armv8-A, the permitted values are 0b0000 and 0b0001.

SHA1, bits [11:8]

Indicates supportwhether for the SHA1 instructions are implemented in AArch32 state. Defined values are:

SHA1	Meaning
0b0000	No SHA1 instructions implemented.
0b0001	SHA1C, SHA1P, SHA1M, SHA1H, SHA1SU0, and SHA1SU1 implemented.

All other values are reserved.

In Armv8-A the permitted values are `0b0000` and `0b0001`.

AES, bits [7:4]

Indicates support~~whether~~ for the AES instructions ~~are implemented~~ in AArch32 state. Defined values are:

AES	Meaning
`0b0000`	No AES instructions implemented.
`0b0001`	AESE, AESD, AESMC, and AESIMC implemented.
`0b0010`	As for `0b0001`, plus VMULL (polynomial) instructions operating on 64-bit data quantities.

All other values are reserved.

In Armv8-A the permitted values are `0b0000` and `0b0010`.

SEVL, bits [3:0]

Indicates support~~whether~~ for the SEVL instruction ~~is implemented~~ in AArch32 state. Defined values are:

SEVL	Meaning
`0b0000`	SEVL is implemented as a NOP.
`0b0001`	SEVL is implemented as Send Event Local.

All other values are reserved.

In Armv8-A the only permitted value is `0b0001`.

Accessing the ID_ISAR5

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0010	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_ISAR5;
elsif PSTATE.EL == EL2 then
    return ID_ISAR5;
elsif PSTATE.EL == EL3 then
    return ID_ISAR5;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_ISAR6, Instruction Set Attribute Register 6

The ID_ISAR6 characteristics are:

Purpose

Provides information about the instruction sets implemented by the PE in AArch32 state.

Must be interpreted with ID_ISAR0, ID_ISAR1, ID_ISAR2, ID_ISAR3, ID_ISAR4 and ID_ISAR5.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_ISAR6 bits [31:0] are architecturally mapped to AArch64 System register ID_ISAR6_EL1[31:0] .

This register is present only when AArch32 ~~from~~ is ~~Armv8.2.~~ supported at any Exception level. Otherwise, direct accesses to ID_ISAR6 are UNKNOWN ~~RES0 from EL1, EL2, and EL3.~~

Note

Prior to the introduction of the features described by this register, this register was unnamed and reserved, RES0 from EL1, EL2, and EL3.

Attributes

ID_ISAR6 is a 32-bit register.

Field descriptions

The ID_ISAR6 bit assignments are:

31 30 29 28	27 26 25 24	23 22 21 20	19 18 17 16	15 14 13 12	11 10 9 8	7 6 5 4	3 2 1 0
RES0	I8MM	BF16	SPECRES	SB	FHM	DP	JSCVT

Bits [31:28]

Reserved, RES0.

I8MM, bits [27:24]

~~When ARMv8.2-AA32I8MM is implemented:~~

Indicates support for Advanced SIMD and floating-point Int8 matrix multiplication instructions in AArch32 state. Defined values are:

I8MM	Meaning
0b0000	Int8 matrix multiplication instructions are not implemented.
0b0001	VSMMLA, VSUDOT, VUMMLA, VUSMMLA, and VUSDOT instructions are implemented.

All other values are reserved.

ARMv8.2-AA32I8MM implements the functionality identified by 0b0001.

Otherwise:

Reserved, RES0.

BF16, bits [23:20]

When ARMv8.2-AA32BF16 is implemented:

From Armv8.2, the permitted values are `0b0000` and `0b0001`.

BF16, bits [23:20]

Indicates support for Advanced SIMD and floating-point BFloat16 instructions in AArch32 state. Defined values are:

BF16	Meaning
`0b0000`	BFloat16 instructions are not implemented.
`0b0001`	VCVT, VCVTB, VCVTT, VDOT, VFMAL, and VMMLA instructions with BF16 operand or result types are implemented.

All other values are reserved.

ARMv8.2-AA32BF16 implements the functionality identified by `0b0001`.

Otherwise:

Reserved, RES0.

From Armv8.2, the permitted values are `0b0000` and `0b0001`.

SPECRES, bits [19:16]

Indicates support for Speculation invalidation instructions in AArch32 state. Defined values are:

SPECRES	Meaning
`0b0000`	CFPRCTX, DVPRCTX, and CPPRCTX instructions are not implemented.
`0b0001`	CFPRCTX, DVPRCTX, and CPPRCTX instructions are implemented.

All other values are reserved.

From Armv8.5, the only permitted value is `0b0001`.

SB, bits [15:12]

Indicates support for SB instruction in AArch32 state. Defined values are:

SB	Meaning
`0b0000`	SB instruction is not implemented.
`0b0001`	SB instruction is implemented.

All other values are reserved.

From Armv8.5, the only permitted value is `0b0001`.

FHM, bits [11:8]

From Armv8.2:

Indicates support for Advanced SIMD and floating-point VFMAL and VFMSL instructions in AArch32 state. Defined values are:

FHM	Meaning
0b0000	VFMAL and VMFSL instructions not implemented.
0b0001	VFMAL and VMFSL instructions implemented.

ARMv8.2-FHM implements the functionality identified by the value 0b0001.

~~Reserved, RES0.~~

~~**DP, bits [7:4]**~~

~~**From Armv8.2:**~~

~~**Otherwise:**~~
DP, bits [7:4]

Indicates support for dot product instructions in AArch32 state. Defined values are:

DP	Meaning
0b0000	No dot product instructions implemented.
0b0001	VUDOT and VSDOT instructions implemented.

All other values are reserved.

ARMv8.2-DotProd implements the functionality identified by the value 0b0001.

~~Reserved, RES0.~~

~~**JSCVT, bits [3:0]**~~

~~**From Armv8.3:**~~

~~**Otherwise:**~~
JSCVT, bits [3:0]

Indicates support for the Javascript conversion instruction in AArch32 state. Defined values are:

JSCVT	Meaning
0b0000	The VJCVT instruction is not implemented.
0b0001	The VJCVT instruction is implemented.

All other values are reserved.

In Armv8.0, Armv8.1 and Armv8.2 the only permitted value is 0b0000.

ARMv8.3-JSConv implements the functionality identified by 0b0001.

~~From Armv8.3 the only permitted value is 0b0001. This feature is identified as ARMv8.3-JSConv.~~

~~**Otherwise:**~~

~~Reserved, RES0.~~

From Armv8.3, if Advanced SIMD or Floating-point is implemented, the only permitted value is 0b0001.

From Armv8.3, if Advanced SIMD or Floating-point is not implemented, the only permitted value is 0b0000.

Accessing the ID_ISAR6

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0010	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!IsZero(ID_ISAR6) || boolean
IMPLEMENTATION_DEFINED "ID_ISAR6 trapped by HCR_EL2.TID3") && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && (!IsZero(ID_ISAR6) || boolean
IMPLEMENTATION_DEFINED "ID_ISAR6 trapped by HCR.TID3") && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_ISAR6;
elsif PSTATE.EL == EL2 then
    return ID_ISAR6;
elsif PSTATE.EL == EL3 then
    return ID_ISAR6;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR0, Memory Model Feature Register 0

The ID_MMFR0 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

Must be interpreted with ID_MMFR1, ID_MMFR2, ID_MMFR3, and ID_MMFR4.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_MMFR0 bits [31:0] are architecturally mapped to AArch64 System register ID_MMFR0_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_MMFR0 are UNKNOWN.

Attributes

ID_MMFR0 is a 32-bit register.

Field descriptions

The ID_MMFR0 bit assignments are:



InnerShr, bits [31:28]

Innermost Shareability. Indicates the innermost shareability domain implemented. Defined values are:

InnerShr	Meaning
0b0000	Implemented as Non-cacheable.
0b0001	Implemented with hardware coherency support.
0b1111	Shareability ignored.

All other values are reserved.

From Armv8 the permitted values are 0b0000, 0b0001, and 0b1111.

This field is valid only if the implementation supports two levels of shareability, as indicated by ID_MMFR0.ShareLvl having the value 0b0001.

When ID_MMFR0.ShareLvl is zero, this field is ~~UNK.~~ UNKNOWN.

FCSE, bits [27:24]

Indicates whether the implementation includes the FCSE. Defined values are:

FCSE	Meaning
0b0000	Not supported.
0b0001	Support for FCSE.

All other values are reserved.

From Armv8 the only permitted value is `0b0000`.

AuxReg, bits [23:20]

Auxiliary Registers. Indicates support for Auxiliary registers. Defined values are:

AuxReg	Meaning
`0b0000`	None supported.
`0b0001`	Support for Auxiliary Control Register only.
`0b0010`	Support for Auxiliary Fault Status Registers (AIFSR and ADFSR) and Auxiliary Control Register.

All other values are reserved.

From Armv8 the only permitted value is `0b0010`.

Note

Accesses to unimplemented Auxiliary registers are UNDEFINED.

TCM, bits [19:16]

Indicates support for TCMs and associated DMAs. Defined values are:

TCM	Meaning
`0b0000`	Not supported.
`0b0001`	Support is IMPLEMENTATION DEFINED. Armv7 requires this setting.
`0b0010`	Support for TCM only, Armv6 implementation.
`0b0011`	Support for TCM and DMA, Armv6 implementation.

All other values are reserved.

In Armv8-A the only permitted value is `0b0000`.

ShareLvl, bits [15:12]

Shareability Levels. Indicates the number of shareability levels implemented. Defined values are:

ShareLvl	Meaning
`0b0000`	One level of shareability implemented.
`0b0001`	Two levels of shareability implemented.

All other values are reserved.

From Armv8 the only permitted value is `0b0001`.

OuterShr, bits [11:8]

Outermost Shareability. Indicates the outermost shareability domain implemented. Defined values are:

OuterShr	Meaning
`0b0000`	Implemented as Non-cacheable.
`0b0001`	Implemented with hardware coherency support.
`0b1111`	Shareability ignored.

All other values are reserved.

From Armv8 the permitted values are `0b0000`, `0b0001`, and `0b1111`.

PMSA, bits [7:4]

Indicates support for a PMSA. Defined values are:

PMSA	Meaning
0b0000	Not supported.
0b0001	Support for IMPLEMENTATION DEFINED PMSA.
0b0010	Support for PMSAv6, with a Cache Type Register implemented.
0b0011	Support for PMSAv7, with support for memory subsections. Armv7-R profile.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

VMSA, bits [3:0]

Indicates support for a VMSA. Defined values are:

VMSA	Meaning
0b0000	Not supported.
0b0001	Support for IMPLEMENTATION DEFINED VMSA.
0b0010	Support for VMSAv6, with Cache and TLB Type Registers implemented.
0b0011	Support for VMSAv7, with support for remapping and the Access flag. ARMv7-A profile.
0b0100	As for 0b0011, and adds support for the PXN bit in the Short-descriptor translation table format descriptors.
0b0101	As for 0b0100, and adds support for the Long-descriptor translation table format.

All other values are reserved.

In Armv8-A the only permitted value is 0b0101.

Accessing the ID_MMFR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0001	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_MMFR0;
elsif PSTATE.EL == EL2 then
    return ID_MMFR0;
elsif PSTATE.EL == EL3 then
    return ID_MMFR0;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR1, Memory Model Feature Register 1

The ID_MMFR1 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

Must be interpreted with ID_MMFR0, ID_MMFR2, ID_MMFR3, and ID_MMFR4.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_MMFR1 bits [31:0] are architecturally mapped to AArch64 System register ID_MMFR1_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_MMFR1 are UNKNOWN.

Attributes

ID_MMFR1 is a 32-bit register.

Field descriptions

The ID_MMFR1 bit assignments are:

31 30 29 28	27 26 25 24	23 22 21 20	19 18 17 16	15 14 13 12	11 10 9 8	7 6 5 4	3 2 1 0
BPred	L1TstCln	L1Uni	L1Hvd	L1UniSW	L1HvdSW	L1UniVA	L1HvdVA

BPred, bits [31:28]

Branch Predictor. Indicates branch predictor management requirements. Defined values are:

BPred	Meaning
0b0000	No branch predictor, or no MMU present. Implies a fixed MPU configuration.
0b0001	Branch predictor requires flushing on: • Enabling or disabling a stage of address translation. • Writing new data to instruction locations. • Writing new mappings to the translation tables. • Changes to the TTBR0, TTBR1, or TTBCR registers. • Changes to the ContextID or ASID, or to the FCSE ProcessID if this is supported.
0b0010	Branch predictor requires flushing on: • Enabling or disabling a stage of address translation. • Writing new data to instruction locations. • Writing new mappings to the translation tables. • Any change to the TTBR0, TTBR1, or TTBCR registers without a change to the corresponding ContextID or ASID, or FCSE ProcessID if this is supported.
0b0011	Branch predictor requires flushing only on writing new data to instruction locations.
0b0100	For execution correctness, branch predictor requires no flushing at any time.

All other values are reserved.

In Armv8-A the permitted values are `0b0010`, `0b0011`, or `0b0100`. For values other than `0b0000` and `0b0100` the Arm Architecture Reference Manual, or the product documentation, might give more information about the required maintenance.

L1TstCln, bits [27:24]

Level 1 cache Test and Clean. Indicates the supported Level 1 data cache test and clean operations, for Harvard or unified cache implementations. Defined values are:

L1TstCln	Meaning
`0b0000`	None supported.
`0b0001`	Supported Level 1 data cache test and clean operations are: • Test and clean data cache.
`0b0010`	As for 0001, and adds: • Test, clean, and invalidate data cache.

All other values are reserved.

In Armv8-A the only permitted value is `0b0000`.

L1Uni, bits [23:20]

Level 1 Unified cache. Indicates the supported entire Level 1 cache maintenance operations for a unified cache implementation. Defined values are:

L1Uni	Meaning
`0b0000`	None supported.
`0b0001`	Supported entire Level 1 cache operations are: • Invalidate cache, including branch predictor if appropriate. • Invalidate branch predictor, if appropriate.
`0b0010`	As for 0001, and adds: • Clean cache, using a recursive model that uses the cache dirty status bit. • Clean and invalidate cache, using a recursive model that uses the cache dirty status bit.

All other values are reserved.

In Armv8-A the only permitted value is `0b0000`.

L1Hvd, bits [19:16]

Level 1 Harvard cache. Indicates the supported entire Level 1 cache maintenance operations for a Harvard cache implementation. Defined values are:

L1Hvd	Meaning
`0b0000`	None supported.
`0b0001`	Supported entire Level 1 cache operations are: • Invalidate instruction cache, including branch predictor if appropriate. • Invalidate branch predictor, if appropriate.
`0b0010`	As for 0001, and adds: • Invalidate data cache. • Invalidate data cache and instruction cache, including branch predictor if appropriate.
`0b0011`	As for 0010, and adds: • Clean data cache, using a recursive model that uses the cache dirty status bit. • Clean and invalidate data cache, using a recursive model that uses the cache dirty status bit.

All other values are reserved.

In Armv8-A the only permitted value is `0b0000`.

L1UniSW, bits [15:12]

Level 1 Unified cache by Set/Way. Indicates the supported Level 1 cache line maintenance operations by set/way, for a unified cache implementation. Defined values are:

L1UniSW	Meaning
0b0000	None supported.
0b0001	Supported Level 1 unified cache line maintenance operations by set/way are: • Clean cache line by set/way.
0b0010	As for 0001, and adds: • Clean and invalidate cache line by set/way.
0b0011	As for 0010, and adds: • Invalidate cache line by set/way.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

L1HvdSW, bits [11:8]

Level 1 Harvard cache by Set/Way. Indicates the supported Level 1 cache line maintenance operations by set/way, for a Harvard cache implementation. Defined values are:

L1HvdSW	Meaning
0b0000	None supported.
0b0001	Supported Level 1 Harvard cache line maintenance operations by set/way are: • Clean data cache line by set/way. • Clean and invalidate data cache line by set/way.
0b0010	As for 0001, and adds: • Invalidate data cache line by set/way.
0b0011	As for 0010, and adds: • Invalidate instruction cache line by set/way

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

L1UniVA, bits [7:4]

Level 1 Unified cache by Virtual Address. Indicates the supported Level 1 cache line maintenance operations by VA, for a unified cache implementation. Defined values are:

L1UniVA	Meaning
0b0000	None supported.
0b0001	Supported Level 1 unified cache line maintenance operations by VA are: • Clean cache line by VA. • Invalidate cache line by VA. • Clean and invalidate cache line by VA.
0b0010	As for 0001, and adds: • Invalidate branch predictor by VA, if branch predictor is implemented.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

L1HvdVA, bits [3:0]

Level 1 Harvard cache by Virtual Address. Indicates the supported Level 1 cache line maintenance operations by VA, for a Harvard cache implementation. Defined values are:

L1HvdVA	Meaning
0b0000	None supported.
0b0001	Supported Level 1 Harvard cache line maintenance operations by VA are: • Clean data cache line by VA. • Invalidate data cache line by VA. • Clean and invalidate data cache line by VA. • Clean instruction cache line by VA.
0b0010	As for 0001, and adds: • Invalidate branch predictor by VA, if branch predictor is implemented.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

Accessing the ID_MMFR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0001	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_MMFR1;
elsif PSTATE.EL == EL2 then
    return ID_MMFR1;
elsif PSTATE.EL == EL3 then
    return ID_MMFR1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR2, Memory Model Feature Register 2

The ID_MMFR2 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

Must be interpreted with ID_MMFR0, ID_MMFR1, ID_MMFR3, and ID_MMFR4.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_MMFR2 bits [31:0] are architecturally mapped to AArch64 System register ID_MMFR2_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_MMFR2 are UNKNOWN.

Attributes

ID_MMFR2 is a 32-bit register.

Field descriptions

The ID_MMFR2 bit assignments are:



HWAccFlg, bits [31:28]

Hardware Access Flag. In earlier versions of the Arm Architecture, this field indicates support for a Hardware Access flag, as part of the VMSAv7 implementation. Defined values are:

HWAccFlg	Meaning
0b0000	Not supported.
0b0001	Support for VMSAv7 Access flag, updated in hardware.

All other values are reserved.

From Armv8 the only permitted value is 0b000.

WFIStall, bits [27:24]

Wait For Interrupt Stall. Indicates the support for Wait For Interrupt (WFI) stalling. Defined values are:

WFIStall	Meaning
0b0000	Not supported.
0b0001	Support for WFI stalling.

All other values are reserved.

From Armv8 the permitted values are 0b000 and 0b001.

MemBarr, bits [23:20]

Memory Barrier. Indicates the supported memory barrier System instructions in the (coproc==1111) encoding space:

MemBarr	Meaning
0b0000	None supported.
0b0001	Supported memory barrier System instructions are: • Data Synchronization Barrier (DSB).
0b0010	As for 0b001, and adds: • Instruction Synchronization Barrier (ISB). • Data Memory Barrier (DMB).

All other values are reserved.

From Armv8 the only permitted value is 0b010.

Arm deprecates the use of these operations. ID_ISAR4.Barrier_instrs indicates the level of support for the preferred barrier instructions.

UniTLB, bits [19:16]

Unified TLB. Indicates the supported TLB maintenance operations, for a unified TLB implementation. Defined values are:

UniTLB	Meaning
0b0000	Not supported.
0b0001	Supported unified TLB maintenance operations are: • Invalidate all entries in the TLB. • Invalidate TLB entry by VA.
0b0010	As for 0b001, and adds: • Invalidate TLB entries by ASID match.
0b0011	As for 0b010, and adds: • Invalidate instruction TLB and data TLB entries by VA All ASID. This is a shared unified TLB operation
0b0100	As for 0b011, and adds: • Invalidate Hyp mode unified TLB entry by VA. • Invalidate entire Non-secure PL1&0 unified TLB. • Invalidate entire Hyp mode unified TLB.
0b0101	As for 0b100, and adds the following operations: TLBIMVALIS, TLBIMVAALIS, TLBIMVALHIS, TLBIMVAL, TLBIMVAAL,TLBIMVALH.
0b0110	As for 0b101, and adds the following operations: TLBIIPAS2IS, TLBIIPAS2LIS, TLBIIPAS2, TLBIIPAS2L.

All other values are reserved.

In Armv8-A the only permitted value is 0b110.

HvdTLB, bits [15:12]

If the Unified TLB field (UniTLB, bits [19:16]) is not 0000, then the meaning of this field is IMPLEMENTATION DEFINED. Arm deprecates the use of this field by software.

L1HvdRng, bits [11:8]

Level 1 Harvard cache Range. Indicates the supported Level 1 cache maintenance range operations, for a Harvard cache implementation. Defined values are:

L1HvdRng	Meaning
0b0000	Not supported.
0b0001	Supported Level 1 Harvard cache maintenance range operations are: • Invalidate data cache range by VA. • Invalidate instruction cache range by VA. • Clean data cache range by VA. • Clean and invalidate data cache range by VA.

All other values are reserved.

From Armv8 the only permitted value is `0b0000`.

L1HvdBG, bits [7:4]

Level 1 Harvard cache Background fetch. Indicates the supported Level 1 cache background fetch operations, for a Harvard cache implementation. When supported, background fetch operations are non-blocking operations. Defined values are:

L1HvdBG	Meaning
0b0000	Not supported.
0b0001	Supported Level 1 Harvard cache background fetch operations are: • Fetch instruction cache range by VA. • Fetch data cache range by VA.

All other values are reserved.

From Armv8 the only permitted value is `0b0000`.

L1HvdFG, bits [3:0]

Level 1 Harvard cache Foreground fetch. Indicates the supported Level 1 cache foreground fetch operations, for a Harvard cache implementation. When supported, foreground fetch operations are blocking operations. Defined values are:

L1HvdFG	Meaning
0b0000	Not supported.
0b0001	Supported Level 1 Harvard cache foreground fetch operations are: • Fetch instruction cache range by VA. • Fetch data cache range by VA.

All other values are reserved.

From Armv8 the only permitted value is `0b0000`.

Accessing the ID_MMFR2

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0001	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_MMFR2;
elsif PSTATE.EL == EL2 then
    return ID_MMFR2;
elsif PSTATE.EL == EL3 then
    return ID_MMFR2;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR3, Memory Model Feature Register 3

The ID_MMFR3 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

Must be interpreted with ID_MMFR0, ID_MMFR1, ID_MMFR2, and ID_MMFR4.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_MMFR3 bits [31:0] are architecturally mapped to AArch64 System register ID_MMFR3_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_MMFR3 are UNKNOWN.

Attributes

ID_MMFR3 is a 32-bit register.

Field descriptions

The ID_MMFR3 bit assignments are:

31 30 29 28	27 26 25 24	23 22 21 20	19 18 17 16	15 14 13 12	11 10 9 8	7 6 5 4	3 2 1 0
Supersec	CMemSz	CohWalk	PAN	MaintBcst	BPMaint	CMaintSW	CMaintVA

Supersec, bits [31:28]

Supersections. On a VMSA implementation, indicates whether Supersections are supported. Defined values are:

Supersec	Meaning
0b0000	Supersections supported.
0b1111	Supersections not supported.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b1111.

CMemSz, bits [27:24]

Cached Memory Size. Indicates the physical memory size supported by the caches. Defined values are:

CMemSz	Meaning
0b0000	4GB, corresponding to a 32-bit physical address range.
0b0001	64GB, corresponding to a 36-bit physical address range.
0b0010	1TB or more, corresponding to a 40-bit or larger physical address range.

All other values are reserved.

In Armv8-A the permitted values are 0b0000, 0b0001, and 0b0010.

CohWalk, bits [23:20]

Coherent Walk. Indicates whether Translation table updates require a clean to the Point of Unification. Defined values are:

CohWalk	Meaning
0b0000	Updates to the translation tables require a clean to the Point of Unification to ensure visibility by subsequent translation table walks.
0b0001	Updates to the translation tables do not require a clean to the Point of Unification to ensure visibility by subsequent translation table walks.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

PAN, bits [19:16]

~~From Armv8.1:~~

Privileged Access Never. Indicates support for the PAN bit in CPSR, SPSR, and DSPSR in AArch32 state. Defined values are:

PAN	Meaning
0b0000	PAN not supported.
0b0001	PAN supported.
0b0010	PAN supported and ATS1CPRP and ATS1CPWP instructions supported.

All other values are reserved.

ARMv8.1-PAN implements the functionality identified by the value 0b0001.

ARMv8.2-ATS1E1 implements the functionality added by the value 0b0010.

In Armv8.1 the value 0b0000 is not permitted.

From Armv8.2, the only permitted value is 0b0010.

~~Otherwise:~~

~~Reserved, RES0.~~

MaintBcst, bits [15:12]

Maintenance Broadcast. Indicates whether Cache, TLB, and branch predictor operations are broadcast. Defined values are:

MaintBcst	Meaning
0b0000	Cache, TLB, and branch predictor operations only affect local structures.
0b0001	Cache and branch predictor operations affect structures according to shareability and defined behavior of instructions. TLB operations only affect local structures.
0b0010	Cache, TLB, and branch predictor operations affect structures according to shareability and defined behavior of instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

BPMaint, bits [11:8]

Branch Predictor Maintenance. Indicates the supported branch predictor maintenance operations in an implementation with hierarchical cache maintenance operations. Defined values are:

BPMaint	Meaning
0b0000	None supported.
0b0001	Supported branch predictor maintenance operations are: • Invalidate all branch predictors.
0b0010	As for 0001, and adds: • Invalidate branch predictors by VA.

All other values are reserved.

In Armv8-A the only permitted value is 0b0010.

CMaintSW, bits [7:4]

Cache Maintenance by Set/Way. Indicates the supported cache maintenance operations by set/way, in an implementation with hierarchical caches. Defined values are:

CMaintSW	Meaning
0b0000	None supported.
0b0001	Supported hierarchical cache maintenance instructions by set/way are: • Invalidate data cache by set/way. • Clean data cache by set/way. • Clean and invalidate data cache by set/way.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

In a unified cache implementation, the data cache maintenance operations apply to the unified caches.

CMaintVA, bits [3:0]

Cache Maintenance by Virtual Address. Indicates the supported cache maintenance operations by VA, in an implementation with hierarchical caches. Defined values are:

CMaintVA	Meaning
0b0000	None supported.
0b0001	Supported hierarchical cache maintenance operations by VA are: • Invalidate data cache by VA. • Clean data cache by VA. • Clean and invalidate data cache by VA. • Invalidate instruction cache by VA. • Invalidate all instruction cache entries.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

In a unified cache implementation, data cache maintenance operations apply to the unified caches, and the instruction cache maintenance instructions are not implemented.

Accessing the ID_MMFR3

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2

0b1111	0b000	0b0000	0b0001	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_MMFR3;
elsif PSTATE.EL == EL2 then
    return ID_MMFR3;
elsif PSTATE.EL == EL3 then
    return ID_MMFR3;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR4, Memory Model Feature Register 4

The ID_MMFR4 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

Must be interpreted with ID_MMFR0, ID_MMFR1, ID_MMFR2, and ID_MMFR3.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_MMFR4 bits [31:0] are architecturally mapped to AArch64 System register ID_MMFR4_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_MMFR4 are UNKNOWN.

Attributes

ID_MMFR4 is a 32-bit register.

Field descriptions

The ID_MMFR4 bit assignments are:

31 30 29 28	27 26 25 24	23 22 21 20	19 18 17 16	15 14 13 12	11 10 9 8	7 6 5 4	3 2 1 0
EVT	CCIDX	LSM	HPDS	CnP	XNX	AC2	SpecSEI

EVT, bits [31:28]

~~When ARMv8.2-EVT is implemented:~~

Enhanced Virtualization Traps. If EL2 is implemented, indicates support for the HCR2.{TTLBIS, TOCU, TICAB, TID4} traps. Defined values are:

EVT	Meaning
0b0000	HCR2.{TTLBIS, TOCU, TICAB, TID4} traps are not supported.
0b0001	HCR2.{TOCU, TICAB, TID4} traps are supported. HCR2.TTLBIS trap is not supported.
0b0010	HCR2.{TTLBIS, TOCU, TICAB, TID4} traps are supported.

All other values are reserved.

ARMv8.2-EVT implements~~In Armv8.0,~~ the functionality~~only~~ identified~~permitted~~ by~~value~~ the values~~is~~ 0b0001~~0b0000~~ and 0b0010.

If EL2 is not implemented, the only permitted value is 0b0000.

~~From Armv8.1, the permitted values are 0b0000, 0b0001, and 0b0010.~~

From Armv8.1~~Armv8.5~~, the permitted values are~~:~~ 0b0000 and 0b0001.

- ~~0b0000 when EL2 is not implemented.~~
- ~~0b0010 when EL2 is implemented. This feature is identified as ARMv8.2-EVT.~~

Otherwise:

Reserved, RES0.

CCIDX, bits [27:24]

From Armv8.3:

From Armv8.5, if EL2 is implemented, the only permitted value is 0b0010.

CCIDX, bits [27:24]

Support for use of the revised CCSIDR format and the presence of the CCSIDR2 is indicated. Defined values are:

CCIDX	Meaning
0b0000	32-bit format implemented for all levels of the CCSIDR, and the CCSIDR2 register is not implemented.
0b0001	64-bit format implemented for all levels of the CCSIDR, and the CCSIDR2 register is implemented.

All other values are reserved.

ARMv8.3-CCIDX implements the functionality identified by 0b0001.

From Armv8.3, the permitted values are 0b0000 and 0b0001. This feature is identified as ARMv8.3-CCIDX.

Otherwise:

Reserved, RAZ.

LSM, bits [23:20]

From Armv8.2:

From Armv8.3, the permitted values are 0b0000 and 0b0001.

LSM, bits [23:20]

Indicates support for LSMAOE and nTLSMD bits in HSCTLR and SCTLR. Defined values are:

LSM	Meaning
0b0000	LSMAOE and nTLSMD bits not supported.
0b0001	LSMAOE and nTLSMD bits supported.

All other values are reserved.

ARMv8.2-LSMAOC implements the functionality identified by the value 0b0001.

Otherwise:

Reserved, RAZ.

HPDS, bits [19:16]

From Armv8.2:

From Armv8.2, the permitted values are 0b0000 and 0b0001.

HPDS, bits [19:16]

Hierarchical permission disables bits in translation tables. Defined values are:

HPDS	Meaning
0b0000	Disabling of hierarchical controls not supported.
0b0001	Supports disabling of hierarchical controls using the TTBCR2.HPD0, TTBCR2.HPD1, and HTCR.HPD bits.
0b0010	As for value 0b0001, and adds possible hardware allocation of bits[62:59] of the translation table descriptors from the final lookup level for IMPLEMENTATION DEFINED use.

All other values are reserved.

ARMv8.2-AA32HPD implements the functionality identified by the value 0b0001.

ARMv8.2-TTPBHA implements the functionality added by the value 0b0010.

Note

The value 0b0000 implies that the encoding for TTBCR2 is UNDEFINED.

~~Reserved, RAZ.~~

~~CnP, bits [15:12]~~

~~From Armv8.2:~~

~~Otherwise:~~
CnP, bits [15:12]

Common not Private translations. Defined values are:

CnP	Meaning
0b0000	Common not Private translations not supported.
0b0001	Common not Private translations supported.

All other values are reserved.

ARMv8.2-TTCNP implements the functionality identified by the value 0b0001.

From Armv8.2 the only permitted value is 0b0001.

~~Reserved, RAZ.~~

~~XNX, bits [11:8]~~

~~From Armv8.2:~~

~~Otherwise:~~
XNX, bits [11:8]

Support for execute-never control distinction by Exception level at stage 2. Defined values are:

XNX	Meaning
0b0000	Distinction between EL0 and EL1 execute-never control at stage 2 not supported.
0b0001	Distinction between EL0 and EL1 execute-never control at stage 2 supported.

All other values are reserved.

ARMv8.2-TTS2UXN implements the functionality identified by the value 0b0001.

When ARMv8.2-TTS2UXN is implemented:

- If all of the following conditions are true, it is IMPLEMENTATION DEFINED whether the value of ID_MMFR4.XNX is 0b0000 or 0b0001:
  - ID_AA64MMFR1_EL1.XNX ==1.

    - EL2 cannot use AArch32.
    - EL1 can use AArch32.
- If EL2 can use AArch32 then the only permitted value is `0b0001`.

~~Otherwise:~~

~~Reserved, RAZ.~~

AC2, bits [7:4]

Indicates the extension of the ACTLR and HACTLR registers using ACTLR2 and HACTLR2. Defined values are:

AC2	Meaning
`0b0000`	ACTLR2 and HACTLR2 are not implemented.
`0b0001`	ACTLR2 and HACTLR2 are implemented.

All other values are reserved.

In Armv8.0 and Armv8.1 the permitted values are `0b0000` and `0b0001`.

From Armv8.2, the only permitted value is `0b0001`.

SpecSEI, bits [3:0]

~~When RAS is implemented:~~

Describes whether the PE can generate SError interrupt exceptions from speculative reads of memory, including speculative instruction fetches. The defined values of this field are:

SpecSEI	Meaning
`0b0000`	The PE never generates an SError interrupt due to an External abort on a speculative read.
`0b0001`	The PE might generate an SError interrupt due to an External abort on a speculative read.

All other values are reserved.

~~Otherwise:~~

~~Reserved, RES0. This provides no information about whether the PE generates a speculative SError interrupt.~~

Accessing the ID_MMFR4

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0010	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!IsZero(ID_MMFR4) || boolean
IMPLEMENTATION_DEFINED "ID_MMFR4 trapped by HCR_EL2.TID3") && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && (!IsZero(ID_MMFR4) || boolean
IMPLEMENTATION_DEFINED "ID_MMFR4 trapped by HCR.TID3") && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_MMFR4;
elsif PSTATE.EL == EL2 then
    return ID_MMFR4;
elsif PSTATE.EL == EL3 then
    return ID_MMFR4;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_MMFR5, Memory Model Feature Register 5

The ID_MMFR5 characteristics are:

Purpose

Provides information about the implemented memory model and memory management support in AArch32 state.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_MMFR5 bits [31:0] are architecturally mapped to AArch64 System register ID_MMFR5_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_MMFR5 are UNKNOWN.

Attributes

ID_MMFR5 is a 32-bit register.

Field descriptions

The ID_MMFR5 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																												ETS			

Bits [31:4]

Reserved, RES0.

ETS, bits [3:0]

~~**From Armv8.0:**~~

Support for Enhanced Translation Synchronization. Defined values are:

ETS	Meaning
0b0000	Enhanced Translation Synchronization is not supported.
0b0001	Enhanced Translation Synchronization is supported.

All other values are reserved.

ARMv8.0-ETS implements the functionality identified by the value 0b0001.

From Armv8.0, the permitted values are 0b0000 and 0b0001.

~~**Otherwise:**~~

~~Reserved, RES0.~~

Accessing the ID_MMFR5

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0011	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && (!IsZero(ID_MMFR5) || boolean
IMPLEMENTATION_DEFINED "ID_MMFR5 trapped by HCR_EL2.TID3") && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && (!IsZero(ID_MMFR5) || boolean
IMPLEMENTATION_DEFINED "ID_MMFR5 trapped by HCR.TID3") && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_MMFR5;
elsif PSTATE.EL == EL2 then
    return ID_MMFR5;
elsif PSTATE.EL == EL3 then
    return ID_MMFR5;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_PFR0, Processor Feature Register 0

The ID_PFR0 characteristics are:

Purpose

Gives top-level information about the instruction sets and other features supported by the PE in AArch32 state.

Must be interpreted with ID_PFR1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_PFR0 bits [31:0] are architecturally mapped to AArch64 System register ID_PFR0_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_PFR0 are UNKNOWN.

Attributes

ID_PFR0 is a 32-bit register.

Field descriptions

The ID_PFR0 bit assignments are:



RAS, bits [31:28]

RAS Extension version. Defined values are:

RAS	Meaning
0b0000	No RAS Extension.
0b0001	RAS Extension present.
0b0010	ARMv8.4-RAS present. As 0b0001, and adds support for additional ERXMISC<m> System registers. Error records accessed through System registers conform to RAS System Architecture v1.1, which includes simplifications to ERR<n>STATUS and support for the optional RAS Timestamp Extension.

All other values are reserved.

From Armv8.4, when ARMv8.4-DFE is not implemented, and ERRIDR.NUM is zero, the permitted values are IMPLEMENTATION DEFINED 0b0001 or 0b0010. Otherwise from Armv8.4 the only permitted value is 0b0010.

ARMv8.4-RAS implements the functionality identified by the value 0b0010.

In Armv8.2, the only permitted value is 0b0001.

In Armv8.1 and Armv8.0, the permitted values are 0b0000 and 0b0001.

DIT, bits [27:24]

From Armv8.4:

Data Independent Timing. Defined values are:

DIT	Meaning
0b0000	AArch32 does not guarantee constant execution time of any instructions.
0b0001	AArch32 provides the CPSR.DIT mechanism to guarantee constant execution time of certain instructions.

All other values are reserved.

ARMv8.4-DIT implements the functionality identified by the value 0b0001.

From Armv8.4, the only permitted value is 0b0001.

Reserved, RES0.

AMU, bits [23:20]

From Armv8.4:

Otherwise:
AMU, bits [23:20]

Activity Monitors Extension. Defined values are:

AMU	Meaning
0b0000	Activity Monitors Extension is not implemented.
0b0001	AMUv1 for Armv8.4 is implemented.
0b0010	AMUv1 for Armv8.6 is implemented. As 0b0001 and adds support for virtualization of the activity monitor event counters.

All other values are reserved.

AMUv1 implements the functionality identified by the value 0b0001.

ARMv8.6-AMU implements the functionality identified by the value 0b0010.

Reserved, RES0.

CSV2, bits [19:16]

From Armv8.5:

Otherwise:
CSV2, bits [19:16]

Speculative use of out of context branch targets. Defined values are:

CSV2	Meaning
0b0000	This Device does not disclose whether branch targets trained in one hardware described context can affect speculative execution in a different hardware described context.
0b0001	Branch targets trained in one hardware described context can only affect speculative execution in a different hardware described context in a hard-to-determine way.

From Armv8.5, the only permitted value is 0b0001.

All other values are reserved.

Otherwise:

Reserved, RES0.

ARMv8.0-CSV2 implements the functionality identified by 0b0001.

From Armv8.5, the only permitted value is 0b0001.

State3, bits [15:12]

T32EE instruction set support. Defined values are:

State3	Meaning
0b0000	Not implemented.
0b0001	T32EE instruction set implemented.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

State2, bits [11:8]

Jazelle extension support. Defined values are:

State2	Meaning
0b0000	Not implemented.
0b0001	Jazelle extension implemented, without clearing of JOSCR.CV on exception entry.
0b0010	Jazelle extension implemented, with clearing of JOSCR.CV on exception entry.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

State1, bits [7:4]

T32 instruction set support. Defined values are:

State1	Meaning
0b0000	T32 instruction set not implemented.
0b0001	T32 encodings before the introduction of Thumb-2 technology implemented: • All instructions are 16-bit. • A BL or BLX is a pair of 16-bit instructions • 32-bit instructions other than BL and BLX cannot be encoded.
0b0011	T32 encodings after the introduction of Thumb-2 technology implemented, for all 16-bit and 32-bit T32 basic instructions.

All other values are reserved.

In Armv8-A the only permitted value is 0b0011.

State0, bits [3:0]

A32 instruction set support. Defined values are:

State0	Meaning
0b0000	A32 instruction set not implemented.
0b0001	A32 instruction set implemented.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

Accessing the ID_PFR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_PFR0;
elsif PSTATE.EL == EL2 then
    return ID_PFR0;
elsif PSTATE.EL == EL3 then
    return ID_PFR0;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_PFR1, Processor Feature Register 1

The ID_PFR1 characteristics are:

Purpose

Gives information about the AArch32 programmers' model.

Must be interpreted with ID_PFR0.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_PFR1 bits [31:0] are architecturally mapped to AArch64 System register ID_PFR1_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_PFR1 are UNKNOWN.

Attributes

ID_PFR1 is a 32-bit register.

Field descriptions

The ID_PFR1 bit assignments are:



GIC, bits [31:28]

System register GIC CPU interface. Defined values are:

GIC	Meaning
0b0000	GIC CPU interface system registers not implemented.
0b0001	System register interface to versions 3.0 and 4.0 of the GIC CPU interface is supported.
0b0011	System register interface to version 4.1 of the GIC CPU interface is supported.

All other values are reserved.

Virt_frac, bits [27:24]

Virtualization fractional field. When the Virtualization field is 0b0000, determines the support for features from the ARMv7 Virtualization Extensions. Defined values are:

Virt_frac	Meaning
0b0000	No features from the ARMv7 Virtualization Extensions are implemented.
0b0001	The following features of the ARMv7 Virtualization Extensions are implemented: • The SCR.SIF bit, if EL3 is implemented. • The modifications to the SCR.AW and SCR.FW bits described in the Virtualization Extensions, if EL3 is implemented. • The MSR (banked register) and MRS (banked register) instructions. • The ERET instruction.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 when EL2 is implemented.
- 0b0001 when EL2 is not implemented.

This field is only valid when the value of ID_PFR1.Virtualization is 0, otherwise it holds the value 0b0000.

Note

The ID_ISAR registers do not identify whether the instructions added by the ARMv7 Virtualization Extensions are implemented.

Sec_frac, bits [23:20]

Security fractional field. When the Security field is 0b0000, determines the support for features from the ARMv7 Security Extensions. Defined values are:

Sec_frac	Meaning
0b0000	No features from the ARMv7 Security Extensions are implemented.
0b0001	The following features from the ARMv7 Security Extensions are implemented: • The VBAR register. • The TTBCR.PD0 and TTBCR.PD1 bits.
0b0010	As for 0b0001, plus the ability to access Secure or Non-secure physical memory is supported.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 when EL3 is implemented.
- 0b0001 or 0b0010 when EL3 is not implemented.

This field is only valid when the value of ID_PFR1.Security is 0, otherwise it holds the value 0b0000.

GenTimer, bits [19:16]

Generic Timer support. Defined values are:

GenTimer	Meaning
0b0000	Generic Timer is not implemented.
0b0001	Generic Timer is implemented.
0b0010	Generic Timer is implemented, and also includes support for CNTHCTL.EVNTIS and CNTKCTL.EVNTIS fields, and CNTPCTSS and CNTVCTSSCNTVCVSS counter views.

All other values are reserved.

ARMv8.6-ECV implements the functionality identified by the value 0b0010.

From Armv8.0 to Armv8.4, the only permitted value is 0b0001.

From Armv8.6, the only permitted value is 0b0010.

Virtualization, bits [15:12]

Virtualization support. Defined values are:

Virtualization	Meaning
0b0000	EL2, Hyp mode, and the HVC instruction not implemented.
0b0001	EL2, Hyp mode, the HVC instruction, and all the features described by Virt_frac == 0b0001 implemented.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 when EL2 is not implemented.
- 0b0001 when EL2 is implemented.

In an implementation that includes EL2, if EL2 cannot use AArch32 but EL1 can use AArch32 then this field has the value 0b0001.

Note

The ID_ISARs do not identify whether the HVC instruction is implemented.

MProgMod, bits [11:8]

M profile programmers' model support. Defined values are:

MProgMod	Meaning
0b0000	Not supported.
0b0010	Support for two-stack programmers' model.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

Security, bits [7:4]

Security support. Defined values are:

Security	Meaning
0b0000	EL3, Monitor mode, and the SMC instruction not implemented.
0b0001	EL3, Monitor mode, the SMC instruction, and all the features described by Sec_frac == 0b0001 implemented.
0b0010	As for 0b0001, and adds the ability to set the NSACR.RFR bit. Not permitted in Armv8 as the NSACR.RFR bit is RES0.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 when EL3 is not implemented.
- 0b0001 when EL3 is implemented.

In an implementation that includes EL3, if EL3 cannot use AArch32 but EL1 can use AArch32 then this field has the value 0b0001.

ProgMod, bits [3:0]

Support for the standard programmers' model for ARMv4 and later. Model must support User, FIQ, IRQ, Supervisor, Abort, Undefined, and System modes. Defined values are:

ProgMod	Meaning
0b0000	Not supported.
0b0001	Supported.

All other values are reserved.

In Armv8-A the only permitted value is 0b0001.

Accessing the ID_PFR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_PFR1;
elsif PSTATE.EL == EL2 then
    return ID_PFR1;
elsif PSTATE.EL == EL3 then
    return ID_PFR1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ID_PFR2, Processor Feature Register 2

The ID_PFR2 characteristics are:

Purpose

Gives information about the AArch32 programmers' model.

Must be interpreted with ID_PFR0 and ID_PFR1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register ID_PFR2 bits [31:0] are architecturally mapped to AArch64 System register ID_PFR2_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ID_PFR2 are UNKNOWN.

Attributes

ID_PFR2 is a 32-bit register.

Field descriptions

The ID_PFR2 bit assignments are:



Bits [31:12]

Reserved, RES0.

RAS_frac, bits [11:8]

From Armv8.4:

RAS Extension fractional field.

RAS_frac	Meaning
0b0000	If ID_PFR0.RAS == 0b0001, RAS Extension implemented.
0b0001	If ID_PFR0.RAS == 0b0001, as 0b0000 and adds support for additional ERXMISC<m> System registers. Error records accessed through System registers conform to RAS System Architecture v1.1, which includes simplifications to ERR<n>STATUS and support for the optional RAS Timestamp Extension.

All other values are reserved.

This field is valid only if ID_PFR0.RAS == 0b0001.

Otherwise:

Reserved, RES0.

SSBS, bits [7:4]

From Armv8.5:

Speculative Store Bypassing controls in AArch64 state. Defined values are:

SSBS	Meaning
0b0000	AArch32 provides no mechanism to control the use of Speculative Store Bypassing.
0b0001	AArch32 provides the PSTATE.SSBS mechanism to mark regions that are Speculative Store Bypass Safe.

From Armv8.0, the permitted values are 0b0000 and 0b0001.

From Armv8.5, the only permitted value is 0b0001.

All other values are reserved.

Otherwise:

Reserved, RES0.

CSV3, bits [3:0]

From Armv8.5:

Speculative use of faulting data. Defined values are:

CSV3	Meaning
0b0000	This Device does not disclose whether data loaded under speculation with a permission or domain fault can be used to form an address or generate condition codes or SVE predicate values to be used by instructions newer than the load in the speculative sequence
0b0001	Data loaded under speculation with a permission or domain fault cannot be used to form an address or generate condition codes or SVE predicate values to be used by instructions newer than the load in the speculative sequence

From Armv8.0, the permitted values are 0b0000 and 0b0001.

From Armv8.5, the only permitted value is 0b0001.

All other values are reserved.

Otherwise:

Reserved, RES0.

Accessing the ID_PFR2

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0011	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ID_PFR2;
elsif PSTATE.EL == EL2 then
    return ID_PFR2;
elsif PSTATE.EL == EL3 then
    return ID_PFR2;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

IFAR, Instruction Fault Address Register

The IFAR characteristics are:

Purpose

Holds the virtual address of the faulting address that caused a synchronous Prefetch Abort exception.

Configuration

AArch32 System register IFAR bits [31:0] are architecturally mapped to AArch64 System register FAR_EL1[63:32] .

AArch32 System register IFAR bits [31:0] (S) are architecturally mapped to AArch32 System register HIFAR[31:0] when ~~HaveEL(~~EL2~~),~~ is implemented, ~~HaveEL(~~EL3~~)~~ is implemented and the highest implemented Exception level is using AArch32 state.~~HighestELUsingAArch32().~~

AArch32 System register IFAR bits [31:0] (S) are architecturally mapped to AArch64 System register FAR_EL2[63:32] when ~~HaveEL(~~EL2 is implemented.~~).~~

This~~RW~~ register~~fields~~ is~~in~~ present~~this~~ only when~~register~~ AArch32~~reset~~ is supported at any Exception level. Otherwise, direct accesses to IFAR are~~architecturally~~ UNKNOWN.~~values.~~

Attributes

IFAR is a 32-bit register.

Field descriptions

The IFAR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
VA of faulting address of synchronous Prefetch Abort exception																															

Bits [31:0]

VA of faulting address of synchronous Prefetch Abort exception.

This field resets to an architecturally UNKNOWN value.

Accessing the IFAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0110	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T6 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T6 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return IFAR_S;
        else
            return IFAR_NS;
    else
        return IFAR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return IFAR_NS;
    else
        return IFAR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return IFAR_S;
    else
        return IFAR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0110	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T6 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T6 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            IFAR_S = R[t];
        else
            IFAR_NS = R[t];
    else
        IFAR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        IFAR_NS = R[t];
    else
        IFAR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        IFAR_S = R[t];
    else
        IFAR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

IFSR, Instruction Fault Status Register

The IFSR characteristics are:

Purpose

Holds status information about the last instruction fault.

Configuration

AArch32 System register IFSR bits [31:0] are architecturally mapped to AArch64 System register IFSR32_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to IFSR are UNKNOWN.

The current translation table format determines which format of the register is used.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

IFSR is a 32-bit register.

Field descriptions

The IFSR bit assignments are:

When TTBCR.EAE == 0:



Bits [31:17]

Reserved, RES0.

FnV, bit [16]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
0b0	IFAR is valid.
0b1	IFAR is not valid, and holds an UNKNOWN value.

This field is only valid for a synchronous External abort other than a synchronous External abort on a translation table walk. It is RES0 for all other Prefetch Abort exceptions.

This field resets to an architecturally UNKNOWN value.

Bits [15:13]

Reserved, RES0.

ExT, bit [12]

External abort type. This bit can be used to provide an IMPLEMENTATION DEFINED classification of External aborts.

In an implementation that does not provide any classification of External aborts, this bit is RES0.

For aborts other than External aborts this bit always returns 0.

This field resets to an architecturally UNKNOWN value.

Bit [11]

Reserved, RES0.

FS[4], bit [10]

This field is bit[4] of FS[4:0].

Fault Status bits. Bits [10] and [3:0] are interpreted together.

FS	Meaning	Applies when
0b00001	PC alignment fault.	
0b00010	Debug exception.	
0b00011	Access flag fault, level 1.	
0b00101	Translation fault, level 1.	
0b00110	Access flag fault, level 2.	
0b00111	Translation fault, level 2.	
0b01000	Synchronous External abort, not on translation table walk.	
0b01001	Domain fault, level 1.	
0b01011	Domain fault, level 2.	
0b01100	Synchronous External abort, on translation table walk, level 1.	
0b01101	Permission fault, level 1.	
0b01110	Synchronous External abort, on translation table walk, level 2.	
0b01111	Permission fault, level 2.	
0b10000	TLB conflict abort.	
0b10100	IMPLEMENTATION DEFINED fault (Lockdown fault).	
0b11001	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b11100	Synchronous parity or ECC error on translation table walk, level 1.	When RAS is not implemented
0b11110	Synchronous parity or ECC error on translation table walk, level 2.	When RAS is not implemented

All other values are reserved.

~~When the RAS Extension is implemented, 0b11001, 0b11100, and 0b11110, are reserved.~~

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults on a Short-descriptor translation table lookup' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The FS field is split as follows:

- FS[4] is IFSR[10].
- FS[3:0] is IFSR[3:0].

This field resets to an architecturally UNKNOWN value.

LPAE, bit [9]

On taking a Data Abort exception, this bit is set as follows:

LPAE	Meaning
0b0	Using the Short-descriptor translation table formats.
0b1	Using the Long-descriptor translation table formats.

Hardware does not interpret this bit to determine the behavior of the memory system, and therefore software can set this bit to 0 or 1 without affecting operation.

This field resets to an architecturally UNKNOWN value.

Bits [8:4]

Reserved, RES0.

FS[3:0], bits [3:0]

This field is bits[3:0] of FS[4:0].

See FS[4] for the field description.

When TTBCR.EAE == 1:



Bits [31:17]

Reserved, RES0.

FnV, bit [16]

FAR not Valid, for a synchronous External abort other than a synchronous External abort on a translation table walk.

FnV	Meaning
0b0	IFAR is valid.
0b1	IFAR is not valid, and holds an UNKNOWN value.

This field is only valid for a synchronous External abort other than a synchronous External abort on a translation table walk. It is RES0 for all other Prefetch Abort exceptions.

This field resets to an architecturally UNKNOWN value.

Bits [15:13]

Reserved, RES0.

ExT, bit [12]

External abort type. This bit can be used to provide an IMPLEMENTATION DEFINED classification of External aborts.

In an implementation that does not provide any classification of External aborts, this bit is RES0.

For aborts other than External aborts this bit always returns 0.

This field resets to an architecturally UNKNOWN value.

Bits [11:10]

Reserved, RES0.

LPAE, bit [9]

On taking a Data Abort exception, this bit is set as follows:

LPAE	Meaning
0b0	Using the Short-descriptor translation table formats.
0b1	Using the Long-descriptor translation table formats.

Hardware does not interpret this bit to determine the behavior of the memory system, and therefore software can set this bit to 0 or 1 without affecting operation.

This field resets to an architecturally UNKNOWN value.

Bits [8:6]

Reserved, RES0.

STATUS, bits [5:0]

Fault status bits. Possible values of this field are:

STATUS	Meaning	Applies when
0b000000	Address size fault in translation table base register.TTBR0 ~~or~~ ~~TTBR1~~.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk.	
0b010101	Synchronous External abort, on translation table walk, level 1.	
0b010110	Synchronous External abort, on translation table walk, level 2.	
0b010111	Synchronous External abort, on translation table walk, level 3.	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk, level 1.	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk, level 2.	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk, level 3.	When RAS is not implemented
0b100001	PC alignment fault.	
0b100010	Debug exception.	
0b110000	TLB conflict abort.	

All other values are reserved.

When the RAS Extension is implemented, 0b011000, 0b011101, 0b011110, and 0b011111, are reserved.

For more information about the lookup level associated with a fault, see 'The level associated with MMU faults on a Long-descriptor translation table lookup' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the IFSR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return IFSR_S;
        else
            return IFSR_NS;
    else
        return IFSR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return IFSR_NS;
    else
        return IFSR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return IFSR_S;
    else
        return IFSR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0101	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T5 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T5 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            IFSR_S = R[t];
        else
            IFSR_NS = R[t];
    else
        IFSR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        IFSR_NS = R[t];
    else
        IFSR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        IFSR_S = R[t];
    else
        IFSR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ISR, Interrupt Status Register

The ISR characteristics are:

Purpose

Shows the pending status of the IRQ, FIQ, or SError.

When executing at EL2, EL3, or Secure EL1, when SCR_EL3.EEL2 == 0b0, this shows the pending status of the physical interrupts.

When executing at Non-secure EL1, or at Secure EL1, when SCR_EL3.EEL2 == 0b01:

- If the HCR.{IMO,FMO,AMO} bit has a value of 1, the corresponding ISR.{I,F,A} bit shows the pending status of the virtual IRQ, FIQ, or SError.
- If the HCR.{IMO,FMO,AMO} bit has a value of 0, the corresponding ISR.{I,F,A} bit shows the pending status of the physical IRQ, FIQ, or SError.

Configuration

AArch32 System register ISR bits [31:0] are architecturally mapped to AArch64 System register ISR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ISR are UNKNOWN.

Attributes

ISR is a 32-bit register.

Field descriptions

The ISR bit assignments are:



Bits [31:9]

Reserved, RES0.

A, bit [8]

SError interrupt pending bit:

A	Meaning
0b0	No pending SError interrupt.
0b1	An SError interrupt is pending.

If the SError interrupt is edge-triggered, this field is cleared to zero when the physical SError interrupt is taken.

I, bit [7]

IRQ pending bit. Indicates whether an IRQ interrupt is pending:

I	Meaning
0b0	No pending IRQ.
0b1	An IRQ interrupt is pending.

F, bit [6]

FIQ pending bit. Indicates whether an FIQ interrupt is pending.

F	Meaning
0b0	No pending FIQ.
0b1	An FIQ interrupt is pending.

Bits [5:0]

Reserved, RES0.

Accessing the ISR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return ISR;
elsif PSTATE.EL == EL2 then
    return ISR;
elsif PSTATE.EL == EL3 then
    return ISR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ITLBIALL, Instruction TLB Invalidate All

The ITLBIALL characteristics are:

Purpose

Invalidate all cached copies of translation table entries from instruction TLBs that are from any level of the translation table walk. The entries that are invalidated are as follows:

- If executed at EL1, all entries that:
  - Would be required for the EL1&0 translation regime.
  - Match the current VMID, if EL2 is implemented and enabled in the current Security state.
- If executed in Secure state when EL3 is using AArch32, all entries that would be required for the Secure PL1&0 translation regime.
- If executed at EL2, and if EL2 is enabled in the curent Security state, the stage 1 or stage 2 translation table entries that would be required for the Non-secure PL1&0 translation regime and matches the current VMID.

The invalidation only applies to the PE that executes this System instruction.

Arm deprecates the use of this System instruction. It is only provided for backwards compatibility with earlier versions of the Arm architecture.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ITLBIALL are UNKNOWN.

Attributes

ITLBIALL is a 32-bit System instruction.

Field descriptions

ITLBIALL ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the ITLBIALL instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0101	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ITLBIALL();
elsif PSTATE.EL == EL2 then
    ITLBIALL();
elsif PSTATE.EL == EL3 then
    ITLBIALL();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ITLBIASID, Instruction TLB Invalidate by ASID match

The ITLBIASID characteristics are:

Purpose

Invalidate all cached copies of translation table entries from instruction TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used for the specified ASID, and either:
  - Is from a level of lookup above the final level.
  - Is a non-global entry from the final level of lookup.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation only applies to the PE that executes this System instruction.

Arm deprecates the use of this System instruction. It is only provided for backwards compatibility with earlier versions of the Arm architecture.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ITLBIASID are UNKNOWN.

Attributes

ITLBIASID is a 32-bit System instruction.

Field descriptions

The ITLBIASID input value bit assignments are:



Bits [31:8]

Reserved, RES0.

ASID, bits [7:0]

ASID value to match. Any TLB entries for non-global pages that match the ASID values will be affected by this System instruction.

Executing the ITLBIASID instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0101	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && -ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ITLBIASID(R[t]);
elsif PSTATE.EL == EL2 then
    ITLBIASID(R[t]);
elsif PSTATE.EL == EL3 then
    ITLBIASID(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ITLBIMVA, Instruction TLB Invalidate by VA

The ITLBIMVA characteristics are:

Purpose

Invalidate all cached copies of translation table entries from instruction TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified address, and one of the following applies:
  - The entry is from a level of lookup above the final level and matches the specified ASID.
  - The entry is a global entry from the final level of lookup.
  - The entry is a non-global entry from the final level of lookup that matches the specified ASID.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation only applies to the PE that executes this System instruction.

Arm deprecates the use of this System instruction. It is only provided for backwards compatibility with earlier versions of the Arm architecture.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to ITLBIMVA are UNKNOWN.

Attributes

ITLBIMVA is a 32-bit System instruction.

Field descriptions

The ITLBIMVA input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Bits [11:8]

Reserved, RES0.

ASID, bits [7:0]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this operation, regardless of the value of the ASID field.

Executing the ITLBIMVA instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0101	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        ITLBIASID(R[t]);
elsif PSTATE.EL == EL2 then
    ITLBIASID(R[t]);
elsif PSTATE.EL == EL3 then
    ITLBIASID(R[t]);
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707~~6134483bd14dc8e12a99e984cbfe3431cc1e9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

JIDR, Jazelle ID Register

The JIDR characteristics are:

Purpose

A Jazelle register, which identified the Jazelle architecture version.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to JIDR are UNKNOWN.

Attributes

JIDR is a 32-bit register.

Field descriptions

The JIDR bit assignments are:



Bits [31:0]

Reserved, RAZ.

Accessing the JIDR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b111	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    if boolean IMPLEMENTATION_DEFINED "JIDR UNDEFINED at EL0" then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HCR_EL2.TID0 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID0 == '1' then
        AArch32.TakeHypTrapException(0x05);
    else
        return JIDR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x05);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID0 == '1' then
        AArch32.TakeHypTrapException(0x05);
    else
        return JIDR;
elsif PSTATE.EL == EL2 then
    return JIDR;
elsif PSTATE.EL == EL3 then
    return JIDR;
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

JMCR, Jazelle Main Configuration Register

The JMCR characteristics are:

Purpose

A Jazelle register, which provides control of the Jazelle extension.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to JMCR are UNKNOWN.

Attributes

JMCR is a 32-bit register.

Field descriptions

The JMCR bit assignments are:



Bits [31:0]

Reserved, RAZ/WI.

Accessing the JMCR

For accesses from EL0 it is IMPLEMENTATION DEFINED whether the register is RW or UNDEFINED.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b111	0b0010	0b0000	0b000

```
if PSTATE.EL == EL0 then
    if boolean IMPLEMENTATION_DEFINED "JMCR UNDEFINED at EL0" then
        UNDEFINED;
    else
        return JMCR;
elsif PSTATE.EL == EL1 then
    return JMCR;
elsif PSTATE.EL == EL2 then
    return JMCR;
elsif PSTATE.EL == EL3 then
    return JMCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b111	0b0010	0b0000	0b000

```
if PSTATE.EL == EL0 then
    if boolean IMPLEMENTATION_DEFINED "JMCR UNDEFINED at EL0" then
        UNDEFINED;
    else
        //no operation
elsif PSTATE.EL == EL1 then
    //no operation
elsif PSTATE.EL == EL2 then
    //no operation
elsif PSTATE.EL == EL3 then
    //no operation
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

JOSCR, Jazelle OS Control Register

The JOSCR characteristics are:

Purpose

A Jazelle register, which provides operating system control of the Jazelle Extension.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to JOSCR are UNKNOWN.

Attributes

JOSCR is a 32-bit register.

Field descriptions

The JOSCR bit assignments are:



Bits [31:0]

Reserved, RAZ/WI.

Accessing the JOSCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1110	0b111	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    if boolean IMPLEMENTATION_DEFINED "JOSCR UNDEFINED at EL0" then
        UNDEFINED;
    else
        return JOSCR;
elsif PSTATE.EL == EL1 then
    return JOSCR;
elsif PSTATE.EL == EL2 then
    return JOSCR;
elsif PSTATE.EL == EL3 then
    return JOSCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2

0b1110	0b111	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    if boolean IMPLEMENTATION_DEFINED "JOSCR UNDEFINED at EL0" then
        UNDEFINED;
    else
        //no operation
elsif PSTATE.EL == EL1 then
    //no operation
elsif PSTATE.EL == EL2 then
    //no operation
elsif PSTATE.EL == EL3 then
    //no operation
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MAIR0, Memory Attribute Indirection Register 0

The MAIR0 characteristics are:

Purpose

Along with MAIR1, provides the memory attribute encodings corresponding to the possible AttrIndx values in a Long-descriptor format translation table entry for stage 1 translations.

AttrIndx[2] indicates the MAIR register to be used:

- When AttrIndx[2] is 0, MAIR0 is used.
- When AttrIndx[2] is 1, MAIR1 is used.

Configuration

AArch32 System register MAIR0 bits [31:0] are architecturally mapped to AArch64 System register MAIR_EL1[31:0] when TTBCR.EAE == 1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to MAIR0 are UNKNOWN.

MAIR0 and PRRR are the same register, with a different view depending on the value of TTBCR.EAE:

- When it is set to 0, the register is as described in PRRR.
- When it is set to 1, the register is as described in MAIR0.

When EL3 is using AArch32, write access to MAIR0(S) is disabled when the CP15SDISABLE signal is asserted HIGH.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

MAIR0 is a 32-bit register.

Field descriptions

The MAIR0 bit assignments are:

When TTBCR.EAE == 1:



Attr<n>, bits [8n+7:8n], for n = 0 to 3

The memory attribute encoding for an AttrIndx[2:0] entry in a Long descriptor format translation table entry, where:

- AttrIndx[2:0] gives the value of <n> in Attr<n>.
- AttrIndx[2] defines which MAIR to access. Attr7 to Attr4 are in MAIR1, and Attr3 to Attr0 are in MAIR0.

Bits [7:4] are encoded as follows:

Attr<n>[7:4]	Meaning
0b0000	Device memory. See encoding of Attr<n>[3:0] for the type of Device memory.
0b00RW, RW not 0b00	Normal memory, Outer Write-Through Transient.
0b0100	Normal memory, Outer Non-cacheable.
0b01RW, RW not 0b00	Normal memory, Outer Write-Back Transient.
0b10RW	Normal memory, Outer Write-Through Non-transient.
0b11RW	Normal memory, Outer Write-Back Non-transient.

R = Outer Read-Allocate policy, W = Outer Write-Allocate policy.

The meaning of bits [3:0] depends on the value of bits [7:4]:

Attr<n>[3:0]	Meaning when Attr<n>[7:4] is 0b0000	Meaning when Attr<n>[7:4] is not 0b0000
0b0000	Device-nGnRnE memory	UNPREDICTABLE
0b00RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Through Transient
0b0100	Device-nGnRE memory	Normal memory, Inner Non-cacheable
0b01RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Back Transient
0b1000	Device-nGRE memory	Normal memory, Inner Write-Through Non-transient (RW=0b00)
0b10RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Through Non-transient
0b1100	Device-GRE memory	Normal memory, Inner Write-Back Non-transient (RW=0b00)
0b11RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Back Non-transient

R = Inner Read-Allocate policy, W = Inner Write-Allocate policy.

The R and W bits in some Attr<n> fields have the following meanings:

R or W	Meaning
0b0	No Allocate
0b1	Allocate

This field resets to an architecturally UNKNOWN value.

Accessing the MAIR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return MAIR0_S;
        else
            return MAIR0_NS;
    else
        return MAIR0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return MAIR0_NS;
    else
        return MAIR0;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return MAIR0_S;
    else
        return MAIR0_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            MAIR0_S = R[t];
        else
            MAIR0_NS = R[t];
    else
        MAIR0 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        MAIR0_NS = R[t];
    else
        MAIR0 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            MAIR0_S = R[t];
        else
            MAIR0_NS = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MAIR1, Memory Attribute Indirection Register 1

The MAIR1 characteristics are:

Purpose

Along with MAIR0, provides the memory attribute encodings corresponding to the possible AttrIndx values in a Long-descriptor format translation table entry for stage 1 translations.

AttrIndx[2] indicates the MAIR register to be used:

- When AttrIndx[2] is 0, MAIR0 is used.
- When AttrIndx[2] is 1, MAIR1 is used.

Configuration

AArch32 System register MAIR1 bits [31:0] are architecturally mapped to AArch64 System register MAIR_EL1[63:32] when TTBCR.EAE == 1.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to MAIR1 are UNKNOWN.

MAIR1 and NMRR are the same register, with a different view depending on the value of TTBCR.EAE:

- When it is set to 0, the register is as described in NMRR.
- When it is set to 1, the register is as described in MAIR1.

When EL3 is using AArch32, write access to MAIR1(S) is disabled when the CP15SDISABLE signal is asserted HIGH.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

MAIR1 is a 32-bit register.

Field descriptions

The MAIR1 bit assignments are:

When TTBCR.EAE == 1:



Attr<n>, bits [8(n-4)+7:8(n-4)], for n = 4 to 7

The memory attribute encoding for an AttrIndx[2:0] entry in a Long descriptor format translation table entry, where:

- AttrIndx[2:0] gives the value of <n> in Attr<n>.
- AttrIndx[2] defines which MAIR to access. Attr7 to Attr4 are in MAIR1, and Attr3 to Attr0 are in MAIR0.

Bits [7:4] are encoded as follows:

Attr<n>[7:4]	Meaning
0b0000	Device memory. See encoding of Attr<n>[3:0] for the type of Device memory.
0b00RW, RW not 0b00	Normal memory, Outer Write-Through Transient.
0b0100	Normal memory, Outer Non-cacheable.
0b01RW, RW not 0b00	Normal memory, Outer Write-Back Transient.
0b10RW	Normal memory, Outer Write-Through Non-transient.
0b11RW	Normal memory, Outer Write-Back Non-transient.

R = Outer Read-Allocate policy, W = Outer Write-Allocate policy.

The meaning of bits [3:0] depends on the value of bits [7:4]:

Attr<n>[3:0]	Meaning when Attr<n>[7:4] is 0b0000	Meaning when Attr<n>[7:4] is not 0b0000
0b0000	Device-nGnRnE memory	UNPREDICTABLE
0b00RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Through Transient
0b0100	Device-nGnRE memory	Normal memory, Inner Non-cacheable
0b01RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Back Transient
0b1000	Device-nGRE memory	Normal memory, Inner Write-Through Non-transient (RW=0b00)
0b10RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Through Non-transient
0b1100	Device-GRE memory	Normal memory, Inner Write-Back Non-transient (RW=0b00)
0b11RW, RW not 0b00	UNPREDICTABLE	Normal memory, Inner Write-Back Non-transient

R = Inner Read-Allocate policy, W = Inner Write-Allocate policy.

The R and W bits in some Attr<n> fields have the following meanings:

R or W	Meaning
0b0	No Allocate
0b1	Allocate

This field resets to an architecturally UNKNOWN value.

Accessing the MAIR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return MAIR1_S;
        else
            return MAIR1_NS;
    else
        return MAIR1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return MAIR1_NS;
    else
        return MAIR1;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return MAIR1_S;
    else
        return MAIR1_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            MAIR1_S = R[t];
        else
            MAIR1_NS = R[t];
    else
        MAIR1 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        MAIR1_NS = R[t];
    else
        MAIR1 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            MAIR1_S = R[t];
        else
            MAIR1_NS = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MIDR, Main ID Register

The MIDR characteristics are:

Purpose

Provides identification information for the PE, including an implementer code for the device and a device ID number.

Configuration

AArch32 System register MIDR bits [31:0] are architecturally mapped to AArch64 System register MIDR_EL1[31:0] .

AArch32 System register MIDR bits [31:0] are architecturally mapped to External register MIDR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to MIDR are UNKNOWN.

Some fields of the MIDR are IMPLEMENTATION DEFINED. For details of the values of these fields for a particular Armv8 implementation, and any implementation-specific significance of these values, see the product documentation.

Attributes

MIDR is a 32-bit register.

Field descriptions

The MIDR bit assignments are:



Implementer, bits [31:24]

The Implementer code. This field must hold an implementer code that has been assigned by Arm. Assigned codes include the following:

Hex representation	Implementer
0x00	Reserved for software use
0xC0	Ampere Computing
0x41	Arm Limited
0x42	Broadcom Corporation
0x43	Cavium Inc.
0x44	Digital Equipment Corporation
0x46	Fujitsu Ltd.
0x49	Infineon Technologies AG
0x4D	Motorola or Freescale Semiconductor Inc.
0x4E	NVIDIA Corporation
0x50	Applied Micro Circuits Corporation
0x51	Qualcomm Inc.
0x56	Marvell International Ltd.
0x69	Intel Corporation

Arm can assign codes that are not published in this manual. All values not assigned by Arm are reserved and must not be used.

Variant, bits [23:20]

An IMPLEMENTATION DEFINED variant number. Typically, this field is used to distinguish between different product variants, or major revisions of a product.

Architecture, bits [19:16]

The permitted values of this field are:

Architecture	Meaning
0b0001	Armv4.
0b0010	Armv4T.
0b0011	Armv5 (obsolete).
0b0100	Armv5T.
0b0101	Armv5TE.
0b0110	Armv5TEJ.
0b0111	Armv6.
0b1111	Architectural features are individually identified in the ID_* registers, see 'ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K12.5.3.

All other values are reserved.

PartNum, bits [15:4]

An IMPLEMENTATION DEFINED primary part number for the device.

On processors implemented by Arm, if the top four bits of the primary part number are 0x0 or 0x7, the variant and architecture are encoded differently.

Revision, bits [3:0]

An IMPLEMENTATION DEFINED revision number for the device.

Accessing the MIDR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) then
        return VPIDR_EL2<31:0>;
    elsif EL2Enabled() && ELUsingAArch32(EL2) then
        return VPIDR;
    else
        return MIDR;
elsif PSTATE.EL == EL2 then
    return MIDR;
elsif PSTATE.EL == EL3 then
    return MIDR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPIDR, Multiprocessor Affinity Register

The MPIDR characteristics are:

Purpose

In a multiprocessor system, provides an additional PE identification mechanism for scheduling purposes.

Configuration

AArch32 System register MPIDR bits [31:0] are architecturally mapped to AArch64 System register MPIDR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to MPIDR are UNKNOWN.

In a uniprocessor system Arm recommends that each Aff<n> field of this register returns a value of 0.

Attributes

MPIDR is a 32-bit register.

Field descriptions

The MPIDR bit assignments are:



M, bit [31]

Indicates whether this implementation includes the functionality introduced by the ARMv7 Multiprocessing Extensions. The possible values of this bit are:

M	Meaning
0b0	This implementation does not include the ARMv7 Multiprocessing Extensions functionality.
0b1	This implementation includes the ARMv7 Multiprocessing Extensions functionality.

From Armv8, this bit is RAO.

U, bit [30]

Indicates a Uniprocessor system, as distinct from PE 0 in a multiprocessor system. The possible values of this bit are:

U	Meaning
0b0	Processor is part of a multiprocessor system.
0b1	Processor is part of a uniprocessor system.

Bits [29:25]

Reserved, RES0.

MT, bit [24]

Indicates whether the lowest level of affinity consists of logical PEs that are implemented using a multithreading type approach. See the description of Aff0 for more information about affinity levels. The possible values of this bit are:

MT	Meaning
0b0	Performance of PEs at the lowest affinity level, or PEs with MPIDR.MT set to 1, different affinity level 0 values, and the same values for affinity level 1 and higher, is largely independent.
0b1	Performance of PEs at the lowest affinity level, or PEs with MPIDR.MT set to 1, different affinity level 0 values, and the same values for affinity level 1 and higher, is very interdependent.

Aff2, bits [23:16]

Affinity level 2. See the description of Aff0 for more information.

Aff1, bits [15:8]

Affinity level 1. See the description of Aff0 for more information.

Aff0, bits [7:0]

Affinity level 0. This is the affinity level that is most significant for determining PE behavior. Higher affinity levels are increasingly less significant in determining PE behavior. The assigned value of the MPIDR.{Aff2, Aff1, Aff0} or MPIDR_EL1.{Aff3, Aff2, Aff1, Aff0} set of fields of each PE must be unique within the system as a whole.

Accessing the MPIDR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) then
        return VMPIDR_EL2<31:0>;
    elsif EL2Enabled() && ELUsingAArch32(EL2) then
        return VMPIDR;
    else
        return MPIDR;
elsif PSTATE.EL == EL2 then
    return MPIDR;
elsif PSTATE.EL == EL3 then
    return MPIDR;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MVBAR, Monitor Vector Base Address Register

The MVBAR characteristics are:

Purpose

When EL3 is implemented and can use AArch32, holds the vector base address for any exception that is taken to Monitor mode.

Secure software must program the MVBAR with the required initial value as part of the PE boot sequence.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to MVBAR are UNKNOWN.

It is IMPLEMENTATION DEFINED whether MVBAR[0] has a fixed value and ignored writes, or takes the last value written to it.

On a reset into EL3 using AArch32, the reset value of MVBAR is an IMPLEMENTATION DEFINED choice between the following:

- ~~MVBAR[0] = 0.~~
- MVBAR[31:5] = an IMPLEMENTATION DEFINED value, which might be UNKNOWN, MVBAR[4:1] =~~.~~ RES0, and MVBAR[0] = 0.
- MVBAR[31~~4~~:1] = an IMPLEMENTATION DEFINED~~RES0~~ value that is bits[31:1] of the AArch32 reset address, and MVBAR[0] = 1.~~.~~

~~And:~~

- ~~MVBAR[31:1] = an IMPLEMENTATION DEFINED value that is bits[31:1] of the AArch32 reset address.~~
- ~~MVBAR[0] = 1.~~

Attributes

MVBAR is a 32-bit register.

Field descriptions

The MVBAR bit assignments are:

When programmed with a vector base address:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Vector Base Address																											Reserved					

Bits [31:5]

Vector Base Address. Bits[31:5] of the base address of the exception vectors for exceptions taken to this Exception level. Bits[4:0] of an exception vector are the exception offset.

Reserved, bits [4:0]

Reserved, see Configurations.

Accessing the MVBAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if IsHighestEL(EL1) then
        return RVBAR;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if IsHighestEL(EL2) then
        return RVBAR;
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    return MVBAR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        MVBAR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MVFR0, Media and VFP Feature Register 0

The MVFR0 characteristics are:

Purpose

Describes the features provided by the AArch32 Advanced SIMD and Floating-point implementation.

Must be interpreted with MVFR1 and MVFR2.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register MVFR0 bits [31:0] are architecturally mapped to AArch64 System register MVFR0_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to MVFR0 are UNKNOWN.

Implemented only if the implementation includes Advanced SIMD and floating-point instructions.

Attributes

MVFR0 is a 32-bit register.

Field descriptions

The MVFR0 bit assignments are:



FPRound, bits [31:28]

Floating-Point Rounding modes. Indicates whether the floating-point implementation provides support for rounding modes. Defined values are:

FPRound	Meaning
0b0000	Not implemented, or only Round to Nearest mode supported, except that Round towards Zero mode is supported for VCVT instructions that always use that rounding mode regardless of the FPSCR setting.
0b0001	All rounding modes supported.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0001.

FPShVec, bits [27:24]

Short Vectors. Indicates whether the floating-point implementation provides support for the use of short vectors. Defined values are:

FPShVec	Meaning
0b0000	Short vectors not supported.
0b0001	Short vector operation supported.

All other values are reserved.

In Armv8-A the only permitted value is 0b0000.

FPSqrt, bits [23:20]

Square Root. Indicates whether the floating-point implementation provides support for the ARMv6 VFP square root operations. Defined values are:

FPSqrt	Meaning
0b0000	Not supported in hardware.
0b0001	Supported.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0001.

The VSQRT.F32 instruction also requires the single-precision floating-point attribute, bits [7:4], and the VSQRT.F64 instruction also requires the double-precision floating-point attribute, bits [11:8].

FPDivide, bits [19:16]

Indicates whether the floating-point implementation provides support for VFP divide operations. Defined values are:

FPDivide	Meaning
0b0000	Not supported in hardware.
0b0001	Supported.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0001.

The VDIV.F32 instruction also requires the single-precision floating-point attribute, bits [7:4], and the VDIV.F64 instruction also requires the double-precision floating-point attribute, bits [11:8].

FPTrap, bits [15:12]

Floating Point Exception Trapping. Indicates whether the floating-point implementation provides support for exception trapping. Defined values are:

FPTrap	Meaning
0b0000	Not supported.
0b0001	Supported.

All other values are reserved.

A value of 0b0001 indicates that, when the corresponding trap is enabled, a floating-point exception generates an exception.

FPDP, bits [11:8]

Double Precision. Indicates whether the floating-point implementation provides support for double-precision operations. Defined values are:

FPDP	Meaning
0b0000	Not supported in hardware.
0b0001	Supported, VFPv2.
0b0010	Supported, VFPv3, VFPv4, or Armv8. VFPv3 and Armv8 add an instruction to load a double-precision floating-point constant, and conversions between double-precision and fixed-point values.

All other values are reserved.

In Armv8-A the permitted values are `0b0000` and `0b0010`.

A value of `0b0001` or `0b0010` indicates support for all VFP double-precision instructions in the supported version of VFP, except that, in addition to this field being nonzero:

- VSQRT.F64 is only available if the Square root field is `0b0001`.
- VDIV.F64 is only available if the Divide field is `0b0001`.
- Conversion between double-precision and single-precision is only available if the single-precision field is nonzero.

FPSP, bits [7:4]

Single Precision. Indicates whether the floating-point implementation provides support for single-precision operations. Defined values are:

FPSP	Meaning
`0b0000`	Not supported in hardware.
`0b0001`	Supported, VFPv2.
`0b0010`	Supported, VFPv3 or VFPv4. VFPv3 adds an instruction to load a single-precision floating-point constant, and conversions between single-precision and fixed-point values.

All other values are reserved.

In Armv8-A the permitted values are `0b0000` and `0b0010`.

A value of `0b0001` or `0b0010` indicates support for all VFP single-precision instructions in the supported version of VFP, except that, in addition to this field being nonzero:

- VSQRT.F32 is only available if the Square root field is `0b0001`.
- VDIV.F32 is only available if the Divide field is `0b0001`.
- Conversion between double-precision and single-precision is only available if the double-precision field is nonzero.

SIMDReg, bits [3:0]

Advanced SIMD registers. Indicates whether the Advanced SIMD and floating-point implementation provides support for the Advanced SIMD and floating-point register bank. Defined values are:

SIMDReg	Meaning
`0b0000`	The implementation has no Advanced SIMD and floating-point support.
`0b0001`	The implementation includes floating-point support with 16 x 64-bit registers.
`0b0010`	The implementation includes Advanced SIMD and floating-point support with 32 x 64-bit registers.

All other values are reserved.

In Armv8-A the permitted values are `0b0000` and `0b0010`.

Accessing the MVFR0

Accesses to this register use the following encodings:

```
VMRS{<c>}{<q>} <Rt>, <spec_reg>
```

reg
0b0111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if ELUsingAArch32(EL1) && ((ELUsingAArch32(EL3) && SCR.NS == '1' && NSACR.cp10 == '0') ||
CPACR.cp10 == '00') then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x08);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x08);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x08);
    else
        return MVFR0;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x00);
    else
        return MVFR0;
elsif PSTATE.EL == EL3 then
    if CPACR.cp10 == '00' then
        UNDEFINED;
    else
        return MVFR0;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MVFR1, Media and VFP Feature Register 1

The MVFR1 characteristics are:

Purpose

Describes the features provided by the AArch32 Advanced SIMD and Floating-point implementation.

Must be interpreted with MVFR0 and MVFR2.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register MVFR1 bits [31:0] are architecturally mapped to AArch64 System register MVFR1_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to MVFR1 are UNKNOWN.

Implemented only if the implementation includes Advanced SIMD and floating-point instructions.

Attributes

MVFR1 is a 32-bit register.

Field descriptions

The MVFR1 bit assignments are:



SIMDFMAC, bits [31:28]

Advanced SIMD Fused Multiply-Accumulate. Indicates whether the Advanced SIMD implementation provides fused multiply accumulate instructions. Defined values are:

SIMDFMAC	Meaning
0b0000	Not implemented.
0b0001	Implemented.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0001.

The Advanced SIMD and floating-point implementations must provide the same level of support for these instructions.

FPHP, bits [27:24]

Floating Point Half Precision. Indicates the level of half-precision floating-point support. Defined values are:

FPHP	Meaning
0b0000	Not supported.
0b0001	Floating-point half-precision conversion instructions are supported for conversion between single-precision and half-precision.
0b0010	As for 0b0001, and adds instructions for conversion between double-precision and half-precision.
0b0011	As for 0b0010, and adds support for half-precision floating-point arithmetic.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 in an implementation without floating-point support.
- 0b0010 in an implementation with floating-point support that does not include the ARMv8.2-FP16 extension.
- 0b0011 in an implementation with floating-point support that includes the ARMv8.2-FP16 extension.

The level of support indicated by this field must be equivalent to the level of support indicated by the SIMDHP field, meaning the permitted values are:

Half Precision instructions supported	FPHP	SIMDHP
No support	0b0000	0b0000
Conversions only	0b0010	0b0001
Conversions and arithmetic	0b0011	0b0010

SIMDHP, bits [23:20]

Advanced SIMD Half Precision. Indicates the level of half-precision floating-point support. Defined values are:

SIMDHP	Meaning
0b0000	Not supported.
0b0001	SIMD half-precision conversion instructions are supported for conversion between single-precision and half-precision.
0b0010	As for 0b0001, and adds support for half-precision floating-point arithmetic.

All other values are reserved.

In Armv8-A the permitted values are:

- 0b0000 in an implementation without SIMD floating-point support.
- 0b0010 in an implementation with SIMD floating-point support that does not include the ARMv8.2-FP16 extension.
- 0b0011 in an implementation with SIMD floating-point support that includes the ARMv8.2-FP16 extension.

The level of support indicated by this field must be equivalent to the level of support indicated by the FPHP field, meaning the permitted values are:

Half Precision instructions supported	FPHP	SIMDHP
No support	0b0000	0b0000
Conversions only	0b0010	0b0001
Conversions and arithmetic	0b0011	0b0010

SIMDSP, bits [19:16]

Advanced SIMD Single Precision. Indicates whether the Advanced SIMD and floating-point implementation provides single-precision floating-point instructions. Defined values are:

SIMDSP	Meaning
0b0000	Not implemented.
0b0001	Implemented. This value is permitted only if the SIMDInt field is 0b0001.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0001.

SIMDInt, bits [15:12]

Advanced SIMD Integer. Indicates whether the Advanced SIMD and floating-point implementation provides integer instructions. Defined values are:

SIMDInt	Meaning
0b0000	Not implemented.
0b0001	Implemented.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0001.

SIMDLS, bits [11:8]

Advanced SIMD Load/Store. Indicates whether the Advanced SIMD and floating-point implementation provides load/store instructions. Defined values are:

SIMDLS	Meaning
0b0000	Not implemented.
0b0001	Implemented.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0001.

FPDNaN, bits [7:4]

Default NaN mode. Indicates whether the floating-point implementation provides support only for the Default NaN mode. Defined values are:

FPDNaN	Meaning
0b0000	Not implemented, or hardware supports only the Default NaN mode.
0b0001	Hardware supports propagation of NaN values.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0001.

FPFtZ, bits [3:0]

Flush to Zero mode. Indicates whether the floating-point implementation provides support only for the Flush-to-Zero mode of operation. Defined values are:

FPFtZ	Meaning
0b0000	Not implemented, or hardware supports only the Flush-to-Zero mode of operation.
0b0001	Hardware supports full denormalized number arithmetic.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0001.

Accessing the MVFR1

Accesses to this register use the following encodings:

```
VMRS{<c>}{<q>} <Rt>, <spec_reg>
```

reg
0b0110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if ELUsingAArch32(EL1) && ((ELUsingAArch32(EL3) && SCR.NS == '1' && NSACR.cp10 == '0') ||
CPACR.cp10 == '00') then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x08);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x08);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x08);
    else
        return MVFR1;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x00);
    else
        return MVFR1;
elsif PSTATE.EL == EL3 then
    if CPACR.cp10 == '00' then
        UNDEFINED;
    else
        return MVFR1;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MVFR2, Media and VFP Feature Register 2

The MVFR2 characteristics are:

Purpose

Describes the features provided by the AArch32 Advanced SIMD and Floating-point implementation.

Must be interpreted with MVFR0 and MVFR1.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G7.1.3.

Configuration

AArch32 System register MVFR2 bits [31:0] are architecturally mapped to AArch64 System register MVFR2_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to MVFR2 are UNKNOWN.

Implemented only if the implementation includes Advanced SIMD and floating-point instructions.

Attributes

MVFR2 is a 32-bit register.

Field descriptions

The MVFR2 bit assignments are:



Bits [31:8]

Reserved, RES0.

FPMisc, bits [7:4]

Indicates whether the floating-point implementation provides support for miscellaneous VFP features.

FPMisc	Meaning
0b0000	Not implemented, or no support for miscellaneous features.
0b0001	Support for Floating-point selection.
0b0010	As 0b0001, and Floating-point Conversion to Integer with Directed Rounding modes.
0b0011	As 0b0010, and Floating-point Round to Integer Floating-point.
0b0100	As 0b0011, and Floating-point MaxNum and MinNum.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0100.

SIMDMisc, bits [3:0]

Indicates whether the Advanced SIMD implementation provides support for miscellaneous Advanced SIMD features.

SIMDMisc	Meaning
0b0000	Not implemented, or no support for miscellaneous features.
0b0001	Floating-point Conversion to Integer with Directed Rounding modes.
0b0010	As 0b0001, and Floating-point Round to Integer Floating-point.
0b0011	As 0b0010, and Floating-point MaxNum and MinNum.

All other values are reserved.

In Armv8-A the permitted values are 0b0000 and 0b0011.

Accessing the MVFR2

Accesses to this register use the following encodings:

```
VMRS{<c>}{<q>} <Rt>, <spec_reg>
```

reg
0b0101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if ELUsingAArch32(EL1) && ((ELUsingAArch32(EL3) && SCR.NS == '1' && NSACR.cp10 == '0') ||
CPACR.cp10 == '00') then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H != '1' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x08);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID3 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x08);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID3 == '1' then
        AArch32.TakeHypTrapException(0x08);
    else
        return MVFR2;
elsif PSTATE.EL == EL2 then
    if HCR_EL2.E2H == '0' && CPTR_EL2.TFP == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif HCR_EL2.E2H == '1' && CPTR_EL2.FPEN == 'x0' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x07);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && ((ELUsingAArch32(EL3) && SCR.NS == '1' &&
NSACR.cp10 == '0') || HCPTR.TCP10 == '1') then
        AArch32.TakeHypTrapException(0x00);
    else
        return MVFR2;
elsif PSTATE.EL == EL3 then
    if CPACR.cp10 == '00' then
        UNDEFINED;
    else
        return MVFR2;
```

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

NMRR, Normal Memory Remap Register

The NMRR characteristics are:

Purpose

Provides additional mapping controls for memory regions that are mapped as Normal memory by their entry in the PRRR.

Used in conjunction with the PRRR.

Configuration

AArch32 System register NMRR bits [31:0] are architecturally mapped to AArch64 System register MAIR_EL1[63:32] when TTBCR.EAE == 0.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to NMRR are UNKNOWN.

MAIR1 and NMRR are the same register, with a different view depending on the value of TTBCR.EAE:

- When it is set to 0, the register is as described in NMRR.
- When it is set to 1, the register is as described in MAIR1.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

NMRR is a 32-bit register.

Field descriptions

The NMRR bit assignments are:

When TTBCR.EAE == 0:

31 30	29 28	27 26	25 24	23 22	21 20	19 18	17 16	15 14	13 12	11 10	9 8	7 6	5 4	3 2	1 0
OR7	OR6	OR5	OR4	OR3	OR2	OR1	OR0	IR7	IR6	IR5	IR4	IR3	IR2	IR1	IR0

OR<n>, bits [2n+17:2n+16], for n = 0 to 7

Outer Cacheable property mapping for memory attributes n, if the region is mapped as Normal memory by the PRRR.TR<n> entry. n is the value of the TEX[0], C, and B bits concatenated. The possible values of this field are:

OR<n>	Meaning
0b00	Region is Non-cacheable.
0b01	Region is Write-Back, Write-Allocate.
0b10	Region is Write-Through, no Write-Allocate.
0b11	Region is Write-Back, no Write-Allocate.

The meaning of the field with n = 6 is IMPLEMENTATION DEFINED and might differ from the meaning given here. This is because the meaning of the attribute combination {TEX[0] = 1, C = 1, B = 0} is IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

IR<n>, bits [2n+1:2n], for n = 0 to 7

Inner Cacheable property mapping for memory attributes n, if the region is mapped as Normal memory by the PRRR.TR<n> entry. n is the value of the TEX[0], C, and B bits concatenated. The possible values of this field are:

IR<n>	Meaning
0b00	Region is Non-cacheable.
0b01	Region is Write-Back, Write-Allocate.
0b10	Region is Write-Through, no Write-Allocate.
0b11	Region is Write-Back, no Write-Allocate.

The meaning of the field with n = 6 is IMPLEMENTATION DEFINED and might differ from the meaning given here. This is because the meaning of the attribute combination {TEX[0] = 1, C = 1, B = 0} is IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the NMRR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return NMRR_S;
        else
            return NMRR_NS;
    else
        return NMRR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return NMRR_NS;
    else
        return NMRR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return NMRR_S;
    else
        return NMRR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            NMRR_S = R[t];
        else
            NMRR_NS = R[t];
    else
        NMRR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        NMRR_NS = R[t];
    else
        NMRR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            NMRR_S = R[t];
        else
            NMRR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

NSACR, Non-Secure Access Control Register

The NSACR characteristics are:

Purpose

When EL3 is implemented and can use AArch32, defines the Non-secure access permissions to Trace, Advanced SIMD and floating-point functionality. Also includes IMPLEMENTATION DEFINED bits that can define Non-secure access permissions for IMPLEMENTATION DEFINED functionality.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to NSACR are UNKNOWN.

Note

In AArch64 state, the NSACR controls are replaced by controls in CPTR_EL3.

~~Some or all RW fields of this register have defined reset values. These apply whenever the register is accessible. This means they apply when the PE resets into EL3 using AArch32.~~

Attributes

NSACR is a 32-bit register.

Field descriptions

The NSACR bit assignments are:



If EL3 is implemented and is using AArch64 then:

- Any read of the NSACR from Non-secure EL2 or Non-secure EL1 returns a value of `0x00000C00`.
- Any read or write to NSACR from Secure EL1 is trapped as an exception to EL3.

If EL3 is not implemented, then any read of the NSACR from EL2 or EL1 returns a value of `0x00000C00`.

Bits [31:21]

Reserved, RES0.

NSTRCDIS, bit [20]

Disables Non-secure System register accesses to all implemented trace registers.

NSTRCDIS	Meaning
0b0	This control has no effect on: • System register access to implemented trace registers. • The behavior of CPACR.TRCDIS and HCPTR.TTA.
0b1	Non-secure System register accesses to all implemented trace registers are disabled, meaning: • CPACR.TRCDIS behaves as RAO/WI in Non-secure state, regardless of its actual value. • HCPTR.TTA behaves as RAO/WI, regardless of its actual value.

The implementation of this field must correspond to the implementation of the CPACR.TRCDIS field:

- If CPACR.TRCDIS is RAZ/WI, this field is RAZ/WI.
- If CPACR.TRCDIS is RW, this field is RW.

Note

- The ETMv4 architecture does not permit EL0 to access the trace registers. If the implementation includes an ETMv4 implementation, EL0 accesses to the trace registers are UNDEFINED.
- The architecture does not provide Non-secure access controls on trace register accesses through the optional memory-mapped external debug interface.

System register accesses to the trace registers can have side-effects. When a System register access is trapped, any side-effects that are normally associated with the access do not occur before the exception is taken.

In a system where the PE resets into EL3, this field resets to 0.

Bit [19]

Reserved, RES0.

IMPLEMENTATION DEFINED, bits [18:16]

IMPLEMENTATION DEFINED.

NSASEDIS, bit [15]

Disables Non-secure access to the Advanced SIMD functionality.

NSASEDIS	Meaning
0b0	This control has no effect on: • Non-secure access to Advanced SIMD functionality. • The behavior of CPACR.ASEDIS and HCPTR.TASE.
0b1	Non-secure access to the Advanced SIMD functionality is disabled, meaning: • CPACR.ASEDIS behaves as RAO/WI in Non-secure state, regardless of its actual value. • HCPTR.TASE behaves as RAO/WI, regardless of its actual value.

The implementation of this field must correspond to the implementation of the CPACR.ASEDIS field:

- If CPACR.ASEDIS is RES0, this field is RES0. If the implementation does not include Advanced SIMD and floating-point functionality, this field is RES0.
- If CPACR.ASEDIS is RAZ/WI, this field is RAZ/WI.
- If CPACR.ASEDIS is RW, this field is RW.

In a system where the PE resets into EL3, this field resets to 0.

Bits [14:12]

Reserved, RES0.

cp11, bit [11]

The value of this field is ignored. If this field is programmed with a different value to the cp10 field then this field is UNKNOWN on a direct read of the NSACR.

If the implementation does not include Advanced SIMD and floating-point functionality, this field is RES0.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

cp10, bit [10]

Enable Non-secure access to the Advanced SIMD and floating-point features. Possible values of the fields are:

cp10	Meaning
0b0	Advanced SIMD and floating-point features can be accessed only from Secure state. Any attempt to access this functionality from Non-secure state is UNDEFINED. When the PE is in Non-secure state: • The CPACR.{cp11, cp10} fields ignore writes and read as 0b00, access denied. • The HCPTR.{TCP11, TCP10} fields behave as RAO/WI, regardless of their actual values.
0b1	Advanced SIMD and floating-point features can be accessed from both Security states.

If Non-secure access to the Advanced SIMD and floating-point functionality is enabled, the CPACR must be checked to determine the level of access that is permitted.

The Advanced SIMD and floating-point features controlled by these fields are:

- Execution of any floating-point or Advanced SIMD instruction.
- Any access to the Advanced SIMD and floating-point registers D0-D31 and their views as S0-S31 and Q0-Q15.
- Any access to the FPSCR, FPSID, MVFR0, MVFR1, MVFR2, or FPEXC System registers.

If the implementation does not include Advanced SIMD and floating-point functionality, this field is RES0.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Bits [9:0]

Reserved, RES0.

Accessing the NSACR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0001	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif !HaveEL(EL3) || (!ELUsingAArch32(EL3) && SCR_EL3.NS == '1') then
        return Zeros(20):'1100':Zeros(8);
    else
        return NSACR;
elsif PSTATE.EL == EL2 then
    if !HaveEL(EL3) || (!ELUsingAArch32(EL3) && SCR_EL3.NS == '1') then
        return Zeros(20):'1100':Zeros(8);
    else
        return NSACR;
elsif PSTATE.EL == EL3 then
    return NSACR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0001	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        NSACR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PAR, Physical Address Register

The PAR characteristics are:

Purpose

Returns the output address (OA) from an Address translation instruction that executed successfully, or fault information if the instruction did not execute successfully.

Configuration

AArch32 System register PAR bits [63:0] are architecturally mapped to AArch64 System register PAR_EL1[63:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to PAR are UNKNOWN.

PAR is accessed as a 32-bit value:

- When the PE is not in Hyp mode and is using the Short-descriptor translation table format.
- When the PE is in Hyp mode and executes an ATS12NSOPR, ATS12NSOPW, ATS12NSOUR, or ATS12NSOUW instruction and the value of HCR.VM is 0 and the value of TTBCR.EAE is 0.

In these cases, PAR[63:32] is RES0.

Otherwise, the PAR is accessed as a 64-bit value, if any of the following is true:

- When using the Long-descriptor translation table format.
- If the stage 1 address translation is disabled and TTBCR.EAE is set to 1.
- In an implementation that includes EL2, for the result of an ATS1Cxx instruction performed from Hyp mode.

For PL1&0 stage 1 translations, TTBCR.EAE selects the translation table format.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PAR is a 64-bit register that can also be accessed as a 32-bit value. If it is accessed as a 32-bit register, accesses read and write bits[31:0] and do not modify bits[63:32].

The Configurations section specifies the cases where each PAR format is used.

Field descriptions

The PAR bit assignments are:

When the instruction returned a 32-bit value to the PAR, PAR.F==0:



This section describes the register value returned by the successful execution of an Address translation instruction. Software might subsequently write a different value to the register, and that write does not affect the operation of the PE.

On a successful conversion, the PAR can return a value that indicates the resulting attributes, rather than the values that appear in the translation table descriptors. More precisely:

- Memory attribute fields are permitted to report the resulting attributes, as determined by any permitted implementation choices and any applicable configuration bits, instead of reporting the values that appear in the translation table descriptors. This applies to the NOS, SH, Inner, and Outer fields.
- See the NS bit description for constraints on the value it returns.

Bits [63:32]

Reserved, RES0.

PA, bits [31:12]

Output address. The output address (OA) corresponding to the supplied input address. This field returns address bits[31:12].

This field resets to an architecturally UNKNOWN value.

LPAE, bit [11]

When updating the PAR with the result of the translation operation, this bit is set as follows:

LPAE	Meaning
0b0	Short-descriptor translation table format used. This means the PAR returned a 32-bit value.

This field resets to an architecturally UNKNOWN value.

NOS, bit [10]

Not Outer Shareable. When the returned value of PAR.SH is 1, indicates the Shareability attribute for the physical memory region:

NOS	Meaning
0b0	Memory region is Outer Shareable.
0b1	Memory region is Inner Shareable.

When the returned value of PAR.SH is 0 the value returned to this field is UNKNOWN.

The value returned in this field can be the resulting attribute, as determined by any permitted implementation choices and any applicable configuration bits, instead of the value that appears in the translation table descriptor.

This field resets to an architecturally UNKNOWN value.

NS, bit [9]

Non-secure. The NS attribute for a translation table entry from a Secure translation regime.

For a result from a Secure translation regime, this bit reflects the Security state of the physical address space of the translation. This means it reflects the effect of the NSTable bits of earlier levels of the translation table walk if those NSTable bits have an effect on the translation.

For a result from a Non-secure translation regime, this bit is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

IMPLEMENTATION DEFINED, bit [8]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

SH, bit [7]

Shareability. Indicates whether the physical memory region is Non-shareable:

SH	Meaning
0b0	Memory is Non-shareable.
0b1	Memory is shareable, and PAR.NOS indicates whether the region is Outer Shareable or Inner Shareable.

The value returned in this field can be the resulting attribute, as determined by any permitted implementation choices and any applicable configuration bits, instead of the value that appears in the translation table descriptor.

This field resets to an architecturally UNKNOWN value.

Inner[2:0], bits [6:4]

Inner cacheability attribute for the region. Permitted values are:

Inner[2:0]	Meaning
0b000	Non-cacheable.
0b001	Device-nGnRnE.
0b011	Device-nGnRE.
0b101	Write-Back, Write-Allocate.
0b110	Write-Through.
0b111	Write-Back, no Write-Allocate.

The values 0b010 and 0b100 are reserved.

The value returned in this field can be the resulting attribute, as determined by any permitted implementation choices and any applicable configuration bits, instead of the value that appears in the translation table descriptor.

This field resets to an architecturally UNKNOWN value.

Outer[1:0], bits [3:2]

Outer cacheability attribute for the region. Permitted values are:

Outer[1:0]	Meaning
0b00	Non-cacheable.
0b01	Write-Back, Write-Allocate.
0b10	Write-Through, no Write-Allocate.
0b11	Write-Back, no Write-Allocate.

The value returned in this field can be the resulting attribute, as determined by any permitted implementation choices and any applicable configuration bits, instead of the value that appears in the translation table descriptor.

This field resets to an architecturally UNKNOWN value.

SS, bit [1]

Supersection. Used to indicate if the result is a Supersection:

SS	Meaning
0b0	Result is not a Supersection. PAR[31:12] contains OA[31:12].
0b1	Result is a Supersection, and: • PAR[31:24] contains OA[31:24]. • PAR[23:16] contains OA[39:32]. • PAR[15:12] contains 0b0000. If an implementation supports less than 40 bits of physical address, the bits in the PAR field that correspond to physical address bits that are not implemented are UNKNOWN.

This field resets to an architecturally UNKNOWN value.

F, bit [0]

Indicates whether the instruction performed a successful address translation.

F	Meaning
0b0	Address translation completed successfully.

This field resets to an architecturally UNKNOWN value.

When the instruction returned a 32-bit value to the PAR, PAR.F==1:



This section describes the register value returned by a fault on the execution of an Address translation instruction. Software might subsequently write a different value to the register, and that write does not affect the operation of the PE.

Bits [63:32]

Reserved, RES0.

IMPLEMENTATION DEFINED, bits [31:16]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Bits [15:12]

Reserved, RES0.

LPAE, bit [11]

When updating the PAR with the result of the translation operation, this bit is set as follows:

LPAE	Meaning
0b0	Short-descriptor translation table format used. This means the PAR returned a 32-bit value.

This field resets to an architecturally UNKNOWN value.

Bits [10:7]

Reserved, RES0.

FS[5],, bitbits [6:1]

Fault status bits,bits. externalBits abort[12,10,3:0] type.from Provides anthe IMPLEMENTATION DEFINED classification of an External abort. Values are as in in the DFSR.ExT, fieldindicating when using the Short-descriptorsource translationof tablethe format.abort.

In an implementation that does not provide any classification of External aborts, this bit is RES0.

For aborts other than External aborts this bit always returns 0.

This field resets to an architecturally UNKNOWN value.

FS[4:0], bits [5:1]

Fault status bits. Values are as in the DFSR.FS field when using the Short-descriptor translation table format.

FS[4:0]	Meaning	Applies when
0b00001	Alignment fault.	
0b00011	Access flag fault, level 1.	
0b00100	Fault on instruction cache maintenance.	
0b00101	Translation fault, level 1.	
0b00110	Access flag fault, level 2.	
0b00111	Translation fault, level 2.	
0b01001	Domain fault, level 1.	
0b01011	Domain fault, level 2.	
0b01100	Synchronous External abort, on translation table walk, level 1.	
0b01101	Permission fault, level 1.	
0b01110	Synchronous External abort, on translation table walk, level 2.	
0b01111	Permission fault, level 2.	
0b10000	TLB conflict abort.	
0b11001	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b11100	Synchronous parity or ECC error on translation table walk, level 1.	When RAS is not implemented
0b11110	Synchronous parity or ECC error on translation table walk, level 2.	When RAS is not implemented

This field resets to an UNKNOWN value.

F, bit [0]

Indicates whether the instruction performed a successful address translation.

F	Meaning
0b1	Address translation aborted.

This field resets to an architecturally UNKNOWN value.

When the instruction returned a 64-bit value to the PAR, PAR.F==0:



This section describes the register value returned by the successful execution of an Address translation instruction. Software might subsequently write a different value to the register, and that write does not affect the operation of the PE.

On a successful conversion, the PAR can return a value that indicates the resulting attributes, rather than the values that appear in the translation table descriptors. More precisely:

- Memory attribute fields are permitted to report the resulting attributes, as determined by any permitted implementation choices and any applicable configuration bits, instead of reporting the values that appear in the translation table descriptors. This applies to the ATTR and SH fields.
- See the NS bit description for constraints on the value it returns.

ATTR, bits [63:56]

Memory attributes for the returned output address. This field uses the same encoding as the Attr<n> fields in MAIR0 and MAIR1.

The value returned in this field can be the resulting attribute, as determined by any permitted implementation choices and any applicable configuration bits, instead of the value that appears in the translation table descriptor.

This field resets to an architecturally UNKNOWN value.

Bits [55:40]

Reserved, RES0.

PA, bits [39:12]

Output address. The output address (OA) corresponding to the supplied input address. This field returns address bits[39:12].

This field resets to an architecturally UNKNOWN value.

LPAE, bit [11]

When updating the PAR with the result of the translation operation, this bit is set as follows:

LPAE	Meaning
0b1	Long-descriptor translation table format used. This means the PAR returned a 64-bit value.

This field resets to an architecturally UNKNOWN value.

IMPLEMENTATION DEFINED, bit [10]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

NS, bit [9]

Non-secure. The NS attribute for a translation table entry from a Secure translation regime.

For a result from a Secure translation regime, this bit reflects the Security state of the physical address space of the translation. This means it reflects the effect of the NSTable bits of earlier levels of the translation table walk if those NSTable bits have an effect on the translation.

For a result from a Non-secure translation regime, this bit is UNKNOWN.

This field resets to an architecturally UNKNOWN value.

SH, bits [8:7]

Shareability attribute, for the returned output address. Permitted values are:

SH	Meaning
0b00	Non-shareable.
0b10	Outer Shareable.
0b11	Inner Shareable.

The value 0b01 is reserved.

Note

This field returns the value 0b10 for:

- Any type of Device memory.
- Normal memory with both Inner Non-cacheable and Outer Non-cacheable attributes.

The value returned in this field can be the resulting attribute, as determined by any permitted implementation choices and any applicable configuration bits, instead of the value that appears in the translation table descriptor.

This field resets to an architecturally UNKNOWN value.

Bits [6:1]

Reserved, RES0.

F, bit [0]

Indicates whether the instruction performed a successful address translation.

F	Meaning
0b0	Address translation completed successfully.

This field resets to an architecturally UNKNOWN value.

When the instruction returned a 64-bit value to the PAR, PAR.F==1:



This section describes the register value returned by a fault on the execution of an Address translation instruction. Software might subsequently write a different value to the register, and that write does not affect the operation of the PE.

IMPLEMENTATION DEFINED, bits [63:56]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

IMPLEMENTATION DEFINED, bits [55:52]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

IMPLEMENTATION DEFINED, bits [51:48]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Bits [47:12]

Reserved, RES0.

LPAE, bit [11]

When updating the PAR with the result of the translation operation, this bit is set as follows:

LPAE	Meaning
0b1	Long-descriptor translation table format used. This means the PAR returned a 64-bit value.

This field resets to an architecturally UNKNOWN value.

Bit [10]

Reserved, RES0.

FSTAGE, bit [9]

Indicates the translation stage at which the translation aborted:

FSTAGE	Meaning
0b0	Translation aborted because of a fault in the stage 1 translation.
0b1	Translation aborted because of a fault in the stage 2 translation.

This field resets to an architecturally UNKNOWN value.

S2WLK, bit [8]

If this bit is set to 1, it indicates the translation aborted because of a stage 2 fault during a stage 1 translation table walk.

This field resets to an architecturally UNKNOWN value.

Bit [7]

Reserved, RES0.

FST, bits [6:1]

Fault status field. Values are as in the DFSR.STATUS and IFSR.STATUS fields when using the Long-descriptor translation table format.

FST	Meaning	Applies when
0b000000	Address size fault in translation table base register.	
0b000001	Address size fault, level 1.	
0b000010	Address size fault, level 2.	
0b000011	Address size fault, level 3.	
0b000101	Translation fault, level 1.	
0b000110	Translation fault, level 2.	
0b000111	Translation fault, level 3.	
0b001001	Access flag fault, level 1.	
0b001010	Access flag fault, level 2.	
0b001011	Access flag fault, level 3.	
0b001101	Permission fault, level 1.	
0b001110	Permission fault, level 2.	
0b001111	Permission fault, level 3.	
0b010000	Synchronous External abort, not on translation table walk.	
0b010101	Synchronous External abort, on translation table walk, level 1.	
0b010110	Synchronous External abort, on translation table walk, level 2.	
0b010111	Synchronous External abort, on translation table walk, level 3.	
0b011000	Synchronous parity or ECC error on memory access, not on translation table walk.	When RAS is not implemented
0b011001	Asynchronous SError interrupt, from a parity or ECC error on memory access.	When RAS is not implemented
0b011101	Synchronous parity or ECC error on memory access on translation table walk, level 1.	When RAS is not implemented
0b011110	Synchronous parity or ECC error on memory access on translation table walk, level 2.	When RAS is not implemented
0b011111	Synchronous parity or ECC error on memory access on translation table walk, level 3.	When RAS is not implemented
0b100001	Alignment fault.	
0b110000	TLB conflict abort.	

This field resets to an architecturally UNKNOWN value.

F, bit [0]

Indicates whether the instruction performed a successful address translation.

F	Meaning
0b1	Address translation aborted.

This field resets to an architecturally UNKNOWN value.

Accessing the PAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return PAR_S<31:0>;
        else
            return PAR_NS<31:0>;
    else
        return PAR<31:0>;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return PAR_NS<31:0>;
    else
        return PAR<31:0>;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return PAR_S<31:0>;
    else
        return PAR_NS<31:0>;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0111	0b0100	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            PAR_S = ZeroExtend(R[t]);
        else
            PAR_NS = ZeroExtend(R[t]);
    else
        PAR = ZeroExtend(R[t]);
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        PAR_NS = ZeroExtend(R[t]);
    else
        PAR = ZeroExtend(R[t]);
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        PAR_S = ZeroExtend(R[t]);
    else
        PAR_NS = ZeroExtend(R[t]);
```

MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b0111	0b0000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return PAR_S;
        else
            return PAR_NS;
    else
        return PAR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return PAR_NS;
    else
        return PAR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return PAR_S;
    else
        return PAR_NS;
```

MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b0111	0b0000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T7 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T7 == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            PAR_S = R[t2]:R[t];
        else
            PAR_NS = R[t2]:R[t];
    else
        PAR = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        PAR_NS = R[t2]:R[t];
    else
        PAR = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        PAR_S = R[t2]:R[t];
    else
        PAR_NS = R[t2]:R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCCFILTR, Performance Monitors Cycle Count Filter Register

The PMCCFILTR characteristics are:

Purpose

Determines the modes in which the Cycle Counter, PMCCNTR, increments.

Configuration

AArch32 System register PMCCFILTR bits [31:0] are architecturally mapped to AArch64 System register PMCCFILTR_EL0[31:0] .

AArch32 System register PMCCFILTR bits [31:0] are architecturally mapped to External register PMCCFILTR_EL0[31:0] .

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMCCFILTR are UNDEFINED.

Attributes

PMCCFILTR is a 32-bit register.

Field descriptions

The PMCCFILTR bit assignments are:



P, bit [31]

Privileged filtering bit. Controls counting in EL1.

If EL3 is implemented, then counting in Non-secure EL1 is further controlled by the PMCCFILTR.NSK bit.

P	Meaning
0b0	Count cycles in EL1.
0b1	Do not count cycles in EL1.

On a Warm reset, this field resets to 0.

U, bit [30]

User filtering bit. Controls counting in EL0.

If EL3 is implemented, then counting in Non-secure EL0 is further controlled by the PMCCFILTR.NSU bit.

U	Meaning
0b0	Count cycles in EL0.
0b1	Do not count cycles in EL0.

On a Warm reset, this field resets to `0`.

NSK, bit [29]

When ~~HaveEL(~~EL3 is implemented~~):~~

Non-secure EL1 (kernel) modes filtering bit. Controls counting in Non-secure EL1.

If the value of this bit is equal to the value of PMCCFILTR.P, cycles in Non-secure EL1 are counted.

Otherwise, cycles in Non-secure EL1 are not counted.

On a Warm reset, this field resets to `0`.

Otherwise:

Reserved, RES0.

NSU, bit [28]

When ~~HaveEL(~~EL3 is implemented~~):~~

Non-secure EL0 (Unprivileged) filtering. Controls counting in Non-secure EL0.

If the value of this bit is equal to the value of PMCCFILTR.U, cycles in Non-secure EL0 are counted.

Otherwise, cycles in Non-secure EL0 are not counted.

On a Warm reset, this field resets to `0`.

Otherwise:

Reserved, RES0.

NSH, bit [27]

When ~~HaveEL(~~EL2 is implemented~~):~~

~~Non-secure~~ EL2 (Hyp mode) filtering bit. Controls counting in ~~Non-secure~~ EL2.

NSH	Meaning
`0b0`	Do not count cycles in EL2.
`0b1`	Count cycles in EL2.

On a Warm reset, this field resets to `0`.

Otherwise:

Reserved, RES0.

Bits [26:0]

Reserved, RES0.

Accessing the PMCCFILTR

PMCCFILTR can also be accessed by using PMXEVTYPER with PMSELR.SEL set to `0b11111`.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b1111	0b111

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMCCFILTR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCCFILTR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCCFILTR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCCFILTR;
elsif PSTATE.EL == EL3 then
    return PMCCFILTR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b1111	0b111

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMCCFILTR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCCFILTR = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCCFILTR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCCFILTR = R[t];
elsif PSTATE.EL == EL3 then
    PMCCFILTR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCCNTR, Performance Monitors Cycle Count Register

The PMCCNTR characteristics are:

Purpose

Holds the value of the processor Cycle Counter, CCNT, that counts processor clock cycles. See 'Time as measured by the Performance Monitors cycle counter' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile for more information.

PMCCFILTR determines the modes and states in which the PMCCNTR can increment.

Configuration

AArch32 System register PMCCNTR bits [63:0] are architecturally mapped to AArch64 System register PMCCNTR_EL0[63:0] .

AArch32 System register PMCCNTR bits [63:0] are architecturally mapped to External register PMCCNTR_EL0[63:0] .

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMCCNTR are UNDEFINED.

All counters are subject to any changes in clock frequency, including clock stopping caused by the WFI and WFE instructions. This means that it is CONSTRAINED UNPREDICTABLE whether or not PMCCNTR continues to increment when clocks are stopped by WFI and WFE instructions.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PMCCNTR is a 64-bit register that can also be accessed as a 32-bit value. If it is accessed as a 32-bit register, accesses read and write bits [31:0] and do not modify bits [63:32].

Field descriptions

The PMCCNTR bit assignments are:



CCNT, bits [63:0]

Cycle count. Depending on the values of PMCR.{LC,D}, this field increments in one of the following ways:

- Every processor clock cycle.
- Every 64th processor clock cycle.

Writing 1 to PMCR.C sets this field to 0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMCCNTR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1101	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.<CR,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.<CR,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMCCNTR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCCNTR<31:0>;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCCNTR<31:0>;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCCNTR<31:0>;
elsif PSTATE.EL == EL3 then
    return PMCCNTR<31:0>;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1101	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMCCNTR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCCNTR = ZeroExtend(R[t]);
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCCNTR = ZeroExtend(R[t]);
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCCNTR = ZeroExtend(R[t]);
elsif PSTATE.EL == EL3 then
    PMCCNTR = ZeroExtend(R[t]);
```

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1001	0b0000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.<CR,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && PMUSERENR.<CR,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMCCNTR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x04);
    else
        return PMCCNTR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x04);
    else
        return PMCCNTR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x04);
    else
        return PMCCNTR;
elsif PSTATE.EL == EL3 then
    return PMCCNTR;
```

```
MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b1001	0b0000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x04);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x04);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMCCNTR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x04);
    else
        PMCCNTR = R[t2]:R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x04);
    else
        PMCCNTR = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x04);
    else
        PMCCNTR = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    PMCCNTR = R[t2]:R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCEID0, Performance Monitors Common Event Identification register 0

The PMCEID0 characteristics are:

Purpose

Defines which common architectural events and common microarchitectural events are implemented, or counted, using PMU events in the range `0x0000` to `0x001F`

When the value of a bit in the register is 1 the corresponding common event is implemented and counted.

Note

Arm recommends that, if a common event is never counted, the value of the corresponding register bit is 0.

For more information about the common events and the use of the PMCEIDn registers see The section describing 'Event numbers and common events' in chapter D5 'The Performance Monitors Extension' of the Arm Architecture Reference Manual, for Armv8-A architecture profile.

Configuration

AArch32 System register PMCEID0 bits [31:0] are architecturally mapped to AArch64 System register PMCEID0_EL0[31:0] .

AArch32 System register PMCEID0 bits [31:0] are architecturally mapped to External register PMCEID0[31:0] .

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMCEID0 are UNDEFINED.

Attributes

PMCEID0 is a 32-bit register.

Field descriptions

The PMCEID0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7
ID31	ID30	ID29	ID28	ID27	ID26	ID25	ID24	ID23	ID22	ID21	ID20	ID19	ID18	ID17	ID16	ID15	ID14	ID13	ID12	ID11	ID10	ID9	ID8	ID

ID<n>, bit [n], for n = 0 to 31

ID[n] corresponds to common event n.

For each bit:

ID<n>	Meaning
`0b0`	The common event is not implemented, or not counted.
`0b1`	The common event is implemented.

A bit that corresponds to a reserved event number is reserved. The value might be used in a future revision of the architecture to identify an additional common event.

Note

Such an event might be added retrospectively to an earlier version of the PMU architecture, provided the event does not require any additional PMU features and has an event number that can be represented in the PMCEID<n> registers of that earlier version of the PMU architecture.

Accessing the PMCEID0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b110

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID0;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID0;
elsif PSTATE.EL == EL3 then
    return PMCEID0;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCEID1, Performance Monitors Common Event Identification register 1

The PMCEID1 characteristics are:

Purpose

Defines which common architectural events and common microarchitectural events are implemented, or counted, using PMU events in the range `0x0020` to `0x003F`.

When the value of a bit in the register is 1 the corresponding common event is implemented and counted.

Note

Arm recommends that, if a common event is never counted, the value of the corresponding register bit is 0.

For more information about the common events and the use of the PMCEIDn registers see The section describing 'Event numbers and common events' in chapter D5 'The Performance Monitors Extension' of the Arm Architecture Reference Manual, for Armv8-A architecture profile.

Configuration

AArch32 System register PMCEID1 bits [31:0] are architecturally mapped to AArch64 System register PMCEID1_EL0[31:0] .

AArch32 System register PMCEID1 bits [31:0] are architecturally mapped to External register PMCEID1[31:0] .

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMCEID1 are UNDEFINED.

Attributes

PMCEID1 is a 32-bit register.

Field descriptions

The PMCEID1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7
ID31	ID30	ID29	ID28	ID27	ID26	ID25	ID24	ID23	ID22	ID21	ID20	ID19	ID18	ID17	ID16	ID15	ID14	ID13	ID12	ID11	ID10	ID9	ID8	ID

ID<n>, bit [n], for n = 0 to 31

ID[n] corresponds to common event (`0x0020` + n).

For each bit:

ID<n>	Meaning
`0b0`	The common event is not implemented, or not counted.
`0b1`	The common event is implemented.

A bit that corresponds to a reserved event number is reserved. The value might be used in a future revision of the architecture to identify an additional common event.

Note

Such an event might be added retrospectively to an earlier version of the PMU architecture, provided the event does not require any additional PMU features and has an event number that can be represented in the PMCEID<n> registers of that earlier version of the PMU architecture.

Accessing the PMCEID1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b111

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID1;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID1;
elsif PSTATE.EL == EL3 then
    return PMCEID1;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCEID2, Performance Monitors Common Event Identification register 2

The PMCEID2 characteristics are:

Purpose

Defines which common architectural events and common microarchitectural events are implemented, or counted, using PMU events in the range `0x4000` to `0x401F`.

When the value of a bit in the register is 1 the corresponding common event is implemented and counted.

Note

Arm recommends that, if a common event is never counted, the value of the corresponding register bit is 0.

For more information about the common events and the use of the PMCEIDn registers see The section describing 'Event numbers and common events' in chapter D5 'The Performance Monitors Extension' of the Arm Architecture Reference Manual, for Armv8-A architecture profile.

Configuration

AArch32 System register PMCEID2 bits [31:0] are architecturally mapped to AArch64 System register PMCEID0_EL0[63:32] .

AArch32 System register PMCEID2 bits [31:0] are architecturally mapped to External register PMCEID2[63:32] .

This register is present only when AArch32 is supported at any Exception level and ARMv8.1-PMU is implemented. Otherwise, direct accesses to PMCEID2 are UNDEFINED.

Attributes

PMCEID2 is a 32-bit register.

Field descriptions

The PMCEID2 bit assignments are:



IDhi<n>, bit [n], for n = 0 to 31

IDhi[n] corresponds to common event (`0x4000` + n).

For each bit:

IDhi<n>	Meaning
`0b0`	The common event is not implemented, or not counted.
`0b1`	The common event is implemented.

A bit that corresponds to a reserved event number is reserved. The value might be used in a future revision of the architecture to identify an additional common event.

Note

Such an event might be added retrospectively to an earlier version of the PMU architecture, provided the event does not require any additional PMU features and has an event number that can be represented in the PMCEID<n> registers of that earlier version of the PMU architecture.

Accessing the PMCEID2

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1110	0b100

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID2;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID2;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID2;
elsif PSTATE.EL == EL3 then
    return PMCEID2;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCEID3, Performance Monitors Common Event Identification register 3

The PMCEID3 characteristics are:

Purpose

Defines which common architectural events and common microarchitectural events are implemented, or counted, using PMU events in the range `0x4020` to `0x403F`.

When the value of a bit in the register is 1 the corresponding common event is implemented and counted.

Note

Arm recommends that, if a common event is never counted, the value of the corresponding register bit is 0.

For more information about the common events and the use of the PMCEIDn registers see The section describing 'Event numbers and common events' in chapter D5 'The Performance Monitors Extension' of the Arm Architecture Reference Manual, for Armv8-A architecture profile.

Configuration

AArch32 System register PMCEID3 bits [31:0] are architecturally mapped to AArch64 System register PMCEID1_EL0[63:32] .

AArch32 System register PMCEID3 bits [31:0] are architecturally mapped to External register PMCEID3[63:32] .

This register is present only when AArch32 is supported at any Exception level and ARMv8.1-PMU is implemented. Otherwise, direct accesses to PMCEID3 are UNDEFINED.

Attributes

PMCEID3 is a 32-bit register.

Field descriptions

The PMCEID3 bit assignments are:



IDhi<n>, bit [n], for n = 0 to 31

IDhi[n] corresponds to common event (`0x4020` + n).

For each bit:

IDhi<n>	Meaning
`0b0`	The common event is not implemented, or not counted.
`0b1`	The common event is implemented.

A bit that corresponds to a reserved event number is reserved. The value might be used in a future revision of the architecture to identify an additional common event.

Note

Such an event might be added retrospectively to an earlier version of the PMU architecture, provided the event does not require any additional PMU features and has an event number that can be represented in the PMCEID<n> registers of that earlier version of the PMU architecture.

Accessing the PMCEID3

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1110	0b101

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID3;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID3;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCEID3;
elsif PSTATE.EL == EL3 then
    return PMCEID3;
```

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCNTENCLR, Performance Monitors Count Enable Clear register

The PMCNTENCLR characteristics are:

Purpose

Disables the Cycle Count Register, PMCCNTR, and any implemented event counters PMEVCNTR<n>. Reading this register shows which counters are enabled.

PMCNTENCLR is used in conjunction with the PMCNTENSET register.

Configuration

AArch32 System register PMCNTENCLR bits [31:0] are architecturally mapped to AArch64 System register PMCNTENCLR_EL0[31:0] .

AArch32 System register PMCNTENCLR bits [31:0] are architecturally mapped to External register PMCNTENCLR_EL0[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMCNTENCLR are UNDEFINED.

Attributes

PMCNTENCLR is a 32-bit register.

Field descriptions

The PMCNTENCLR bit assignments are:



C, bit [31]

PMCCNTR disable bit. Disables the cycle counter register. Possible values are:

C	Meaning
0b0	When read, means the cycle counter is disabled. When written, has no effect.
0b1	When read, means the cycle counter is enabled. When written, disables the cycle counter.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter disable bit for PMEVCNTR<n>.

If N is less than 31, then bits [30:N] are RAZ/WI. When EL2 is implemented and enabled in the current Security state, in EL1 and EL0, N is the value in MDCR_EL2.HPMN if EL2 is using AArch64, or in HDCR.HPMN if EL2 is using AArch32. Otherwise, N is the value in PMCR.N.

P<n>	Meaning
0b0	When read, means that PMEVCNTR<n> is disabled. When written, has no effect.
0b1	When read, means that PMEVCNTR<n> is enabled. When written, disables PMEVCNTR<n>.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMCNTENCLR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMCNTEN == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCNTENCLR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCNTENCLR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCNTENCLR;
elsif PSTATE.EL == EL3 then
    return PMCNTENCLR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMCNTEN == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCNTENCLR = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCNTENCLR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCNTENCLR = R[t];
elsif PSTATE.EL == EL3 then
    PMCNTENCLR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCNTENSET, Performance Monitors Count Enable Set register

The PMCNTENSET characteristics are:

Purpose

Enables the Cycle Count Register, PMCCNTR, and any implemented event counters PMEVCNTR<n>. Reading this register shows which counters are enabled.

PMCNTENSET is used in conjunction with the PMCNTENCLR register.

Configuration

AArch32 System register PMCNTENSET bits [31:0] are architecturally mapped to AArch64 System register PMCNTENSET_EL0[31:0] .

AArch32 System register PMCNTENSET bits [31:0] are architecturally mapped to External register PMCNTENSET_EL0[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMCNTENSET are UNDEFINED.

Attributes

PMCNTENSET is a 32-bit register.

Field descriptions

The PMCNTENSET bit assignments are:



C, bit [31]

PMCCNTR enable bit. Enables the cycle counter register. Possible values are:

C	Meaning
0b0	When read, means the cycle counter is disabled. When written, has no effect.
0b1	When read, means the cycle counter is enabled. When written, enables the cycle counter.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter enable bit for PMEVCNTR<n>.

If N is less than 31, then bits [30:N] are RAZ/WI. When EL2 is implemented and enabled in the current Security state, in EL1 and EL0, N is the value in MDCR_EL2.HPMN if EL2 is using AArch64, or in HDCR.HPMN if EL2 is using AArch32. Otherwise, N is the value in PMCR.N.

P<n>	Meaning
0b0	When read, means that PMEVCNTR<n> is disabled. When written, has no effect.
0b1	When read, means that PMEVCNTR<n> event counter is enabled. When written, enables PMEVCNTR<n>.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMCNTENSET

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMCNTEN == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCNTENSET;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCNTENSET;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCNTENSET;
elsif PSTATE.EL == EL3 then
    return PMCNTENSET;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMCNTEN == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCNTENSET = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCNTENSET = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCNTENSET = R[t];
elsif PSTATE.EL == EL3 then
    PMCNTENSET = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCR, Performance Monitors Control Register

The PMCR characteristics are:

Purpose

Provides details of the Performance Monitors implementation, including the number of counters implemented, and configures and controls the counters.

Configuration

AArch32 System register PMCR bits [31:0] are architecturally mapped to AArch64 System register PMCR_EL0[31:0] .

AArch32 System register PMCR bits [7:0] are architecturally mapped to External register PMCR_EL0[7:0] .

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMCR are UNDEFINED.

Attributes

PMCR is a 32-bit register.

Field descriptions

The PMCR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
IMP								IDCODE								N					RES0			LP	LC	DP	X	D	C	P	E

IMP, bits [31:24]

Implementer code. This field has an IMPLEMENTATION DEFINED value.

If this field is zero, then PMCR.IDCODE is RES0 and software must use MIDR to identify the PE.

Otherwise this field and PMCR.IDCODE identify the PMU implementation to software. The implementer codes are allocated by Arm. A non-zero value has the same interpretation as MIDR.Implementer.

Access to this field is **RO**.

IDCODE, bits [23:16]

When PMCR.IMP != 0x00:

Identification code. This field has an IMPLEMENTATION DEFINED value.

Each implementer must maintain a list of identification codes that are specific to the implementer. A specific implementation is identified by the combination of the implementer code and the identification code.

Access to this field is **RO**.

Otherwise:

Reserved, RES0.

N, bits [15:11]

Indicates the number of event counters implemented. This value is in the range of `0b00000`-`0b111111`. If the value is `0b00000` then only PMCCNTR is implemented. If the value is `0b111111` PMCCNTR and 31 event counters are implemented.

In an implementation that includes EL2:

- If EL2 is using AArch32, reads of this field from Non-secure EL1 and Non-secure EL0 return the value of HDCR.HPMN.
- If EL2 is using AArch64 and enabled in the current Security state, reads of this field from EL1 and EL0 return the value of MDCR_EL2.HPMN.

Access to this field is **RO**.

Bits [10:8]

Reserved, RES0.

LP, bit [7]

When ARMv8.5-PMU is implemented:

Long event counter enable. Determines when unsigned overflow is recorded by a counter overflow bit.

LP	Meaning
`0b0`	Event counter overflow on increment that causes unsigned overflow of PMEVCNTR<n>[31:0].
`0b1`	Event counter overflow on increment that causes unsigned overflow of PMEVCNTR<n>[63:0].

If the highest implemented Exception level is using AArch32, it is IMPLEMENTATION DEFINED whether this bit is RW or RAZ/WI.

If EL2 is implemented and HDCR.HPMN or MDCR_EL2.HPMN is less than PMCR.N, this bit does not affect the operation of event counters in the range [HDCR.HPMN..(PMCR.N-1)] or [MDCR_EL2.HPMN..(PMCR.N-1)].

PMEVCNTR<n>[63:32] cannot be accessed directly in AArch32 state.

Note

The effect of HDCR.HPMN or MDCR_EL2.HPMN on the operation of this bit always applies if EL2 is implemented, at all Exception levels including EL2 and EL3, and regardless of whether EL2 is enabled in the current Security state. For more information, see the description of HDCR.HPMN or MDCR_EL2.HPMN.

On a Warm reset, this field resets to `0`.

Otherwise:

Reserved, RES0.

LC, bit [6]

Long cycle counter enable. Determines when unsigned overflow is recorded by the cycle counter overflow bit.

LC	Meaning
0b0	Cycle counter overflow on increment that causes unsigned overflow of PMCCNTR[31:0].
0b1	Cycle counter overflow on increment that causes unsigned overflow of PMCCNTR[63:0].

Arm deprecates use of PMCR.LC = 0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

DP, bit [5]

When ~~HaveEL(~~EL3~~)~~ is implemented or (ARMv8.1-PMU is implemented and ~~HaveEL(~~EL2 is implemented):~~)~~:

Disable cycle counter when event counting is prohibited.

DP	Meaning
0b0	Cycle counting by PMCCNTR is not affected by this bit.
0b1	When event counting for counters in the range [0..(HDCR.HPMN-1)] or [0..(MDCR_EL2.HPMN-1)] is prohibited, cycle counting by PMCCNTR is disabled.

For more information about the interaction between the Performance Monitors and EL3, see 'Effect of EL3 and EL2' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile

On a Warm reset, this field resets to 0.

Otherwise:

Reserved, RES0.

X, bit [4]

When the implementation includes an PMU event export bus:

Enable export of events in an IMPLEMENTATION DEFINED PMU event export bus.

X	Meaning
0b0	Do not export events.
0b1	Export events where not prohibited.

This field enables the exporting of events over an IMPLEMENTATION DEFINED PMU event export bus to another device, for example to an OPTIONAL PE trace unit.

No events are exported when counting is prohibited.

This field does not affect the generation of Performance Monitors overflow interrupt requests or signaling to a cross-trigger interface (CTI) that can be implemented as signals exported from the PE.

On a Warm reset, this field resets to 0.

Otherwise:

Reserved, RAZ/WI.

D, bit [3]

Clock divider. The possible values of this bit are:

D	Meaning
0b0	When enabled, PMCCNTR counts every clock cycle.
0b1	When enabled, PMCCNTR counts once every 64 clock cycles.

If PMCR.LC == 1, this bit is ignored and the cycle counter counts every clock cycle.

Arm deprecates use of PMCR.D = 1.

On a Warm reset, this field resets to 0.

C, bit [2]

Cycle counter reset. The effects of writing to this bit are:

C	Meaning
0b0	No action.
0b1	Reset PMCCNTR to zero.

This bit is always RAZ.

Note

Resetting PMCCNTR does not change the cycle counter overflow bit.

The value of PMCR_EL0.LC is ignored, and bits [63:0] of all affected event counters are reset.

Access to this field is **WO**.

P, bit [1]

Event counter reset. The effects of writing to this bit are:

P	Meaning
0b0	No action.
0b1	Reset all event counters accessible in the current Exception level, not including PMCCNTR, to zero.

This bit is always RAZ.

In EL0 and EL1:

- If EL2 is implemented and enabled in the current Security state, and HDCR.HPMN or MDCR_EL2.HPMN is less than PMCR_EL0.N, a write of 1 to this bit does not reset event counters in the range [HDCR.HPMN..(PMCR.N-1)] or [MDCR_EL2.HPMN..(PMCR.N-1)].
- If EL2 is not implemented, EL2 is disabled in the current Security state, or HDCR.HPMN or MDCR_EL2.HPMN is equal to PMCR_EL0.N, a write of 1 to this bit resets all the event counters.

In EL2 and EL3, a write of 1 to this bit resets all the event counters.

Note

Resetting the event counters does not change the event counter overflow bits.

If ARMv8.5-PMU is implemented, the values of HDCR.HLP and PMCR.LP are ignored and bits [63:0] of all affected event counters are reset.

Access to this field is **WO**.

E, bit [0]

Enable.

E	Meaning
0b0	All event counters in the range [0..(PMN-1)] and PMCCNTR, are disabled.
0b1	All event counters in the range [0..(PMN-1)] and PMCCNTR, are enabled by PMCNTENSET.

If EL2 is implemented then:

- If EL2 is using AArch32, PMN is HDCR.HPMN.
- If EL2 is using AArch64, PMN is MDCR_EL2.HPMN.
- If PMN is less than PMCR.N, this bit does not affect the operation of event counters in the range [PMN..(PMCR.N-1)].

If EL2 is not implemented, PMN is PMCR.N.

Note

The effect of MDCR_EL2.HPMN or HDCR.HPMN on the operation of this bit always applies if EL2 is implemented, at all Exception levels including EL2 and EL3, regardless of whether EL2 is enabled in the current Security state. For more information, see the description of MDCR_EL2.HPMN or HDCR.HPMN.

On a Warm reset, this field resets to `0`.

Accessing the PMCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMCR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPMCR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMCR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPMCR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMCR;
elsif PSTATE.EL == EL3 then
    return PMCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b000

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMCR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMCR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPMCR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCR = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPMCR == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPMCR == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMCR = R[t];
elsif PSTATE.EL == EL3 then
    PMCR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMEVCNTR<n>, Performance Monitors Event Count Registers, n = 0 - 30

The PMEVCNTR<n> characteristics are:

Purpose

Holds event counter n, which counts events, where n is 0 to 30.

Configuration

AArch32 System register PMEVCNTR<n> bits [31:0] are architecturally mapped to AArch64 System register PMEVCNTR<n>_EL0[31:0] .

AArch32 System register PMEVCNTR<n> bits [31:0] are architecturally mapped to External register PMEVCNTR<n>_EL0[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMEVCNTR<n> are UNDEFINED.

Attributes

PMEVCNTR<n> is a 32-bit register.

Field descriptions

The PMEVCNTR<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Event counter n																															

Bits [31:0]

Event counter n. Value of event counter n, where n is the number of this register and is a number from 0 to 30.

If ARMv8.5-PMU is implemented, the event counter is 64 bits and only the least-significant part of the event counter is accessible in AArch32 state:

- Reads from PMEVCNTR<n> return bits [31:0] of the counter.
- Writes to PMEVCNTR<n> update bits [31:0] and leave bits [63:32] unchanged.
- There is no means to access bits [63:32] directly from AArch32 state.
- If the implementation does not support AArch64 at any Exception level, bits [63:32] are not required to be implemented.

If ARMv8.5-PMU is not implemented, the event counter is 32 bits.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMEVCNTR<n>

PMEVCNTR<n> can also be accessed by using PMXEVCNTR with PMSELR.SEL set to the value of <n>.

If ARMv8.6-FGT is implemented, and EL2 <n> is greater implemented than and or enabled equal in to the number current of Security accessible counters state, then and the EL1 behavior is of using AArch64, for permitted reads and writes of at EL0: PMEVCNTR<n> is as follows:

- If <n> is an unimplemented event counter, the access is UNDEFINED.
- Otherwise, the if access <n> is trapped greater than or equal to EL2. MDCR_EL2.HPMN, the access is trapped to EL2.

If ARMv8.6-FGT is not implemented, and <n> is greater than or equal to the number above of behaviors accessible do counters, not then reads and writes of apply: PMEVCNTR<n> are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

If <n> is greater than or equal to the number of accessible counters, then reads and writes of PMEVCNTR<n> are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

- Accesses to the register are UNDEFINED.
- Accesses to the register behave as RAZ/WI.
- Accesses to the register execute as a NOP
- If EL2 is implemented and enabled in the current Security state, and <n> is less than the number of implemented counters, accesses from EL1 or permitted accesses from EL0 are trapped to EL2.

Note

In EL0, an access is permitted if it is enabled by PMUSERENR.{ER,EN} or PMUSERENR_EL0.{ER,EN}.

If EL2 is implemented and enabled in the current Security state, at EL0 and EL1:

- If EL2 is using AArch32, HDCR.HPMN identifies the number of accessible counters.
- If EL2 is using AArch64, MDCR_EL2.HPMN identifies the number of accessible counters.

Otherwise, the number of accessible counters is the number of implemented counters. See HDCR.HPMN and MDCR_EL2.HPMN for more details.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b10:n[4:3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.<ER,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.<ER,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMEVCNTR[UInt(CRm<1:0>:opc2<2:0>)];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMEVCNTR[UInt(CRm<1:0>:opc2<2:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMEVCNTR[UInt(CRm<1:0>:opc2<2:0>)];
elsif PSTATE.EL == EL3 then
    return PMEVCNTR[UInt(CRm<1:0>:opc2<2:0>)];
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b10:n[4:3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMEVCNTR[UInt(CRm<1:0>:opc2<2:0>)] = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMEVCNTR[UInt(CRm<1:0>:opc2<2:0>)] = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMEVCNTR[UInt(CRm<1:0>:opc2<2:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    PMEVCNTR[UInt(CRm<1:0>:opc2<2:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMEVTYPER<n>, Performance Monitors Event Type Registers, n = 0 - 30

The PMEVTYPER<n> characteristics are:

Purpose

Configures event counter n, where n is 0 to 30.

Configuration

AArch32 System register PMEVTYPER<n> bits [31:0] are architecturally mapped to AArch64 System register PMEVTYPER<n>_EL0[31:0] .

AArch32 System register PMEVTYPER<n> bits [31:0] are architecturally mapped to External register PMEVTYPER<n>_EL0[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMEVTYPER<n> are UNDEFINED.

Attributes

PMEVTYPER<n> is a 32-bit register.

Field descriptions

The PMEVTYPER<n> bit assignments are:



P, bit [31]

Privileged filtering bit. Controls counting in EL1.

If EL3 is implemented, then counting in Non-secure EL1 is further controlled by the PMEVTYPER<n>.NSK bit.

P	Meaning
0b0	Count events in EL1.
0b1	Do not count events in EL1.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

U, bit [30]

User filtering bit. Controls counting in EL0.

If EL3 is implemented, then counting in Non-secure EL0 is further controlled by the PMEVTYPER<n>.NSU bit.

U	Meaning
0b0	Count events in EL0.
0b1	Do not count events in EL0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSK, bit [29]

When ~~HaveEL(~~EL3 is implemented~~):~~

Non-secure EL1 (kernel) modes filtering bit. Controls counting in Non-secure EL1.

If the value of this bit is equal to the value of PMEVTYPER<n>.P, events in Non-secure EL1 are counted.

Otherwise, events in Non-secure EL1 are not counted.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NSU, bit [28]

When ~~HaveEL(~~EL3 is implemented~~):~~

Non-secure EL0 (Unprivileged) filtering. Controls counting in Non-secure EL0.

If the value of this bit is equal to the value of PMEVTYPER<n>.U, events in Non-secure EL0 are counted.

Otherwise, events in Non-secure EL0 are not counted.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NSH, bit [27]

When ~~HaveEL(~~EL2 is implemented~~):~~

~~Non-secure~~ EL2 (Hyp mode) filtering bit. Controls counting in ~~Non-secure~~ EL2.

NSH	Meaning
0b0	Do not count events in EL2.
0b1	Count events in EL2.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [26]

Reserved, RES0.

MT, bit [25]

When (ARMv8.6-MTPMU is implemented and enabled) or an IMPLEMENTATION DEFINED multi-threaded PMU Extension is implemented:

Multithreading.

MT	Meaning
0b0	Count events only on controlling PE.
0b1	Count events from any PE with the same affinity at level 1 and above as this PE.

Note

- When the lowest level of affinity consists of logical PEs that are implemented using a multi-threading type approach, an implementation is described as multi-threaded. That is, the performance of PEs at the lowest affinity level is highly interdependent.
- Events from a different thread of a multithreaded implementation are not Attributable to the thread counting the event.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [24:16]

Reserved, RES0.

evtCount[15:10], bits [15:10]

When ARMv8.1-PMU is implemented:

Extension to evtCount[9:0]. See evtCount[9:0] for more details.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

evtCount[9:0], bits [9:0]

Event to count. The event number of the event that is counted by event counter PMEVCNTR<n>.

Software must program this field with an event that is supported by the PE being programmed.

The ranges of event numbers allocated to each type of event are shown in Allocation of the PMU event number space.

If evtCount is programmed to an event that is reserved or not supported by the PE, the behavior depends on the value written:

- For the range `0x0000` to `0x003F`, no events are counted, and the value returned by a direct or external read of the evtCount field is the value written to the field.
- If 16-bit evtCount is implemented, for the range `0x4000` to `0x403F`, no events are counted, and the value returned by a direct or external read of the evtCount field is the value written to the field.
- For IMPLEMENTATION DEFINED events, it is UNPREDICTABLE what event, if any, is counted, and the value returned by a direct or external read of the evtCount field is UNKNOWN.

Note

UNPREDICTABLE means the event must not expose privileged information.

Arm recommends that the behavior across a family of implementations is defined such that if a given implementation does not include an event from a set of common IMPLEMENTATION DEFINED events, then no event is counted and the value read back on evtCount is the value written.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMEVTYPER<n>

PMEVTYPER<n> can also be accessed by using PMXEVTYPER with PMSELR.SEL set to n.

If ARMv8.6-FGT is implemented, and EL2 <n> is greater implemented than and or enabled equal in to the number current of Security accessible counters state, then and the EL1 behavior is of using AArch64, for permitted reads and writes of at EL0: PMEVTYPER<n> is as follows:

- If <n> is an unimplemented event counter, the access is UNDEFINED.
- Otherwise, the if access <n> is trapped greater than or equal to EL2. MDCR_EL2.HPMN, the access is trapped to EL2.

If ARMv8.6-FGT is not implemented, and <n> is greater than or equal to the number above of behaviors accessible do counters, not then reads and writes of apply: PMEVTYPER<n> are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

If <n> is greater or equal to the number of accessible counters, then reads and writes of PMEVTYPER<n> are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

- Accesses to the register are UNDEFINED.
- Accesses to the register behave as RAZ/WI.
- Accesses to the register execute as a `NOP`.
- If EL2 is implemented and enabled in the current Security state, and <n> is less than the number of implemented counters, accesses from EL1 or permitted accesses from EL0 are trapped to EL2.

Note

In EL0, an access is permitted if it is enabled by PMUSERENR.EN or PMUSERENR_EL0.EN.

If EL2 is implemented and enabled in the current Security state, at EL0 and EL1:

- If EL2 is using AArch32, HDCR.HPMN identifies the number of accessible counters.
- If EL2 is using AArch64, MDCR_EL2.HPMN identifies the number of accessible counters.

Otherwise, the number of accessible counters is the number of implemented counters. See HDCR.HPMN and MDCR_EL2.HPMN for more details.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b11:n[4:3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMEVTYPER[UInt(CRm<1:0>:opc2<2:0>)];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMEVTYPER[UInt(CRm<1:0>:opc2<2:0>)];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMEVTYPER[UInt(CRm<1:0>:opc2<2:0>)];
elsif PSTATE.EL == EL3 then
    return PMEVTYPER[UInt(CRm<1:0>:opc2<2:0>)];
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1110	0b11:n[4:3]	n[2:0]

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMEVTYPER[UInt(CRm<1:0>:opc2<2:0>)] = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMEVTYPER[UInt(CRm<1:0>:opc2<2:0>)] = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMEVTYPER[UInt(CRm<1:0>:opc2<2:0>)] = R[t];
elsif PSTATE.EL == EL3 then
    PMEVTYPER[UInt(CRm<1:0>:opc2<2:0>)] = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMINTENCLR, Performance Monitors Interrupt Enable Clear register

The PMINTENCLR characteristics are:

Purpose

Disables the generation of interrupt requests on overflows from the Cycle Count Register, PMCCNTR, and the event counters PMEVCNTR<n>. Reading the register shows which overflow interrupt requests are enabled.

PMINTENCLR is used in conjunction with the PMINTENSET register.

Configuration

AArch32 System register PMINTENCLR bits [31:0] are architecturally mapped to AArch64 System register PMINTENCLR_EL1[31:0] .

AArch32 System register PMINTENCLR bits [31:0] are architecturally mapped to External register PMINTENCLR_EL1[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMINTENCLR are UNDEFINED.

Attributes

PMINTENCLR is a 32-bit register.

Field descriptions

The PMINTENCLR bit assignments are:



C, bit [31]

PMCCNTR overflow interrupt request disable bit. Possible values are:

C	Meaning
0b0	When read, means the cycle counter overflow interrupt request is disabled. When written, has no effect.
0b1	When read, means the cycle counter overflow interrupt request is enabled. When written, disables the cycle count overflow interrupt request.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter overflow interrupt request disable bit for PMEVCNTR<n>.

If N is less than 31, then bits [30:N] are RAZ/WI. When EL2 is implemented and enabled in the current Security state, in EL1, N is the value in MDCR_EL2.HPMN if EL2 is using AArch64, or in HDCR.HPMN if EL2 is using AArch32. Otherwise, N is the value in PMCR.N.

P<n>	Meaning
0b0	When read, means that the PMEVCNTR<n> event counter interrupt request is disabled. When written, has no effect.
0b1	When read, means that the PMEVCNTR<n> event counter interrupt request is enabled. When written, disables the PMEVCNTR<n> interrupt request.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMINTENCLR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1110	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMINTENCLR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMINTENCLR;
elsif PSTATE.EL == EL3 then
    return PMINTENCLR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1110	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMINTENCLR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMINTENCLR = R[t];
elsif PSTATE.EL == EL3 then
    PMINTENCLR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMINTENSET, Performance Monitors Interrupt Enable Set register

The PMINTENSET characteristics are:

Purpose

Enables the generation of interrupt requests on overflows from the Cycle Count Register, PMCCNTR, and the event counters PMEVCNTR<n>. Reading the register shows which overflow interrupt requests are enabled.

PMINTENSET is used in conjunction with the PMINTENCLR register.

Configuration

AArch32 System register PMINTENSET bits [31:0] are architecturally mapped to AArch64 System register PMINTENSET_EL1[31:0] .

AArch32 System register PMINTENSET bits [31:0] are architecturally mapped to External register PMINTENSET_EL1[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMINTENSET are UNDEFINED.

Attributes

PMINTENSET is a 32-bit register.

Field descriptions

The PMINTENSET bit assignments are:



C, bit [31]

PMCCNTR overflow interrupt request enable bit. Possible values are:

C	Meaning
0b0	When read, means the cycle counter overflow interrupt request is disabled. When written, has no effect.
0b1	When read, means the cycle counter overflow interrupt request is enabled. When written, enables the cycle count overflow interrupt request.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter overflow interrupt request enable bit for PMEVCNTR<n>.

If N is less than 31, then bits [30:N] are RAZ/WI. When EL2 is implemented and enabled in the current Security state, in EL1, N is the value in MDCR_EL2.HPMN if EL2 is using AArch64, or in HDCR.HPMN if EL2 is using AArch32. Otherwise, N is the value in PMCR.N.

P<n>	Meaning
0b0	When read, means that the PMEVCNTR<n> event counter interrupt request is disabled. When written, has no effect.
0b1	When read, means that the PMEVCNTR<n> event counter interrupt request is enabled. When written, enables the PMEVCNTR<n> interrupt request.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMINTENSET

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1110	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMINTENSET;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMINTENSET;
elsif PSTATE.EL == EL3 then
    return PMINTENSET;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1110	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMINTENSET = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMINTENSET = R[t];
elsif PSTATE.EL == EL3 then
    PMINTENSET = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMMIR, Performance Monitors Machine Identification Register

The PMMIR characteristics are:

Purpose

Describes Performance Monitors parameters specific to the implementation to software.

Configuration

This register is present only when AArch32 is supported at any Exception level and ARMv8.4-PMU is implemented. Otherwise, direct accesses to PMMIR are UNDEFINED.

Attributes

PMMIR is a 32-bit register.

Field descriptions

The PMMIR bit assignments are:



Bits [31:8]

Reserved, RES0.

SLOTS, bits [7:0]

Operation width. The largest value by which the STALL_SLOT event might increment by in a single cycle. If the STALL_SLOT event is not implemented, this field might read as zero.

Accessing the PMMIR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1110	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMMIR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMMIR;
elsif PSTATE.EL == EL3 then
    return PMMIR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMOVSR, Performance Monitors Overflow Flag Status Register

The PMOVSR characteristics are:

Purpose

Contains the state of the overflow bit for the Cycle Count Register, PMCCNTR, and each of the implemented event counters PMEVCNTR<n>. Writing to this register clears these bits.

Configuration

AArch32 System register PMOVSR bits [31:0] are architecturally mapped to AArch64 System register PMOVSCLR_EL0[31:0] .

AArch32 System register PMOVSR bits [31:0] are architecturally mapped to External register PMOVSCLR_EL0[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMOVSR are UNDEFINED.

Attributes

PMOVSR is a 32-bit register.

Field descriptions

The PMOVSR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
C	P<n>, bit [n]																														

C, bit [31]

Cycle counter overflow clear bit. Possible values are:

C	Meaning
0b0	When read, means the cycle counter has not overflowed since this bit was last cleared. When written, has no effect.
0b1	When read, means the cycle counter has overflowed since this bit was last cleared. When written, clears the cycle counter overflow bit to 0.

PMCR.LC controls whether an overflow is detected from unsigned overflow of PMCCNTR[31:0] or unsigned overflow of PMCCNTR[63:0].

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter overflow clear bit for PMEVCNTR<n>.

If N is less than 31, then bits [30:N] are RAZ/WI. When EL2 is implemented and enabled in the current Security state, in EL1 and EL0, N is the value in MDCR_EL2.HPMN if EL2 is using AArch64, or in HDCR.HPMN if EL2 is using AArch32. Otherwise, N is the value in PMCR.N.

P<n>	Meaning
0b0	When read, means that PMEVCNTR<n> has not overflowed since this bit was last cleared. When written, has no effect.
0b1	When read, means that PMEVCNTR<n> has overflowed since this bit was last cleared. When written, clears the PMEVCNTR<n> overflow bit to 0.

If ARMv8.5-PMU is implemented, MDCR_EL2.HLP, HDCR.HLP, and PMCR.LP control whether an overflow is detected from unsigned overflow of PMEVCNTR<n>[31:0] or unsigned overflow of PMEVCNTR<n>[63:0]. PMEVCNTR<n>[63:32] cannot be accessed directly in AArch32 state.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMOVSR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b011

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMOVS == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMOVSR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMOVSR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMOVSR;
elsif PSTATE.EL == EL3 then
    return PMOVSR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b011

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMOVS == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMOVSR = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMOVSR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMOVSR = R[t];
elsif PSTATE.EL == EL3 then
    PMOVSR = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMOVSSET, Performance Monitors Overflow Flag Status Set register

The PMOVSSET characteristics are:

Purpose

Sets the state of the overflow bit for the Cycle Count Register, PMCCNTR, and each of the implemented event counters PMEVCNTR<n>.

Configuration

AArch32 System register PMOVSSET bits [31:0] are architecturally mapped to AArch64 System register PMOVSSET_EL0[31:0] .

AArch32 System register PMOVSSET bits [31:0] are architecturally mapped to External register PMOVSSET_EL0[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMOVSSET are UNDEFINED.

Attributes

PMOVSSET is a 32-bit register.

Field descriptions

The PMOVSSET bit assignments are:



C, bit [31]

Cycle counter overflow set bit.

C	Meaning
0b0	When read, means the cycle counter has not overflowed since this bit was last cleared. When written, has no effect.
0b1	When read, means the cycle counter has overflowed since this bit was last cleared. When written, sets the cycle counter overflow bit to 1.

PMCR.LC controls whether an overflow is detected from unsigned overflow of PMCCNTR[31:0] or unsigned overflow of PMCCNTR[63:0].

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter overflow set bit for PMEVCNTR<n>.

If N is less than 31, then bits [30:N] are RAZ/WI. When EL2 is implemented and enabled in the current Security state, in EL1 and EL0, N is the value in MDCR_EL2.HPMN if EL2 is using AArch64, or in HDCR.HPMN if EL2 is using AArch32. Otherwise, N is the value in PMCR.N.

P<n>	Meaning
0b0	When read, means that PMEVCNTR<n> has not overflowed since this bit was last cleared. When written, has no effect.
0b1	When read, means that PMEVCNTR<n> has overflowed since this bit was last . When written, sets the PMEVCNTR<n> overflow bit to 1.

If ARMv8.5-PMU is implemented, MDCR_EL2.HLP, HDCR.HLP, and PMCR.LP control whether an overflow is detected from unsigned overflow of PMEVCNTR<n>[31:0] or unsigned overflow of PMEVCNTR<n>[63:0]. PMEVCNTR<n>[63:32] cannot be accessed directly in AArch32 state.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMOVSSET

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1110	0b011

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMOVS == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMOVSSET;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMOVSSET;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMOVSSET;
elsif PSTATE.EL == EL3 then
    return PMOVSSET;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1110	0b011

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMOVS == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMOVSSET = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMOVSSET = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMOVSSET = R[t];
elsif PSTATE.EL == EL3 then
    PMOVSSET = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMSELR, Performance Monitors Event Counter Selection Register

The PMSELR characteristics are:

Purpose

Selects the current event counter PMEVCNTR<n> or the cycle counter, CCNT.

PMSELR is used in conjunction with PMXEVTYPER to determine the event that increments a selected event counter, and the modes and states in which the selected counter increments.

It is also used in conjunction with PMXEVCNTR, to determine the value of a selected event counter.

Configuration

AArch32 System register PMSELR bits [31:0] are architecturally mapped to AArch64 System register PMSELR_EL0[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMSELR are UNDEFINED.

Attributes

PMSELR is a 32-bit register.

Field descriptions

The PMSELR bit assignments are:



Bits [31:5]

Reserved, RES0.

SEL, bits [4:0]

Selects event counter, PMEVCNTR<n>, where n is the value held in this field. This value identifies which event counter is accessed when a subsequent access to PMXEVTYPER or PMXEVCNTR occurs.

This field can take any value from 0 (`0b00000`) to (PMCR.N)-1, or 31 (`0b11111`).

When PMSELR.SEL is `0b11111`, it selects the cycle counter and:

- A read of the PMXEVTYPER returns the value of PMCCFILTR.
- A write of the PMXEVTYPER writes to PMCCFILTR.
- A read or write of PMXEVCNTR has CONSTRAINED UNPREDICTABLE effects. See PMXEVCNTR for more details.

For details of the results of accesses to event counters, see PMXEVTYPER and PMXEVCNTR.

For information about the number of counters accessible at each Exception level, see HDCR.HPMN and MDCR_EL2.HPMN.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMSELR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b101

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.<ER,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.<ER,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMSELR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMSELR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMSELR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMSELR;
elsif PSTATE.EL == EL3 then
    return PMSELR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2

0b1111	0b000	0b1001	0b1100	0b101

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.<ER,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.<ER,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMSELR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMSELR = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMSELR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMSELR = R[t];
elsif PSTATE.EL == EL3 then
    PMSELR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMSWINC, Performance Monitors Software Increment register

The PMSWINC characteristics are:

Purpose

Increments a counter that is configured to count the Software increment event, event `0x00`. For more information, see 'SW_INCR' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D5.

Configuration

AArch32 System register PMSWINC bits [31:0] are architecturally mapped to AArch64 System register PMSWINC_EL0[31:0] .

AArch32 System register PMSWINC bits [31:0] are architecturally mapped to External register PMSWINC_EL0[31:0] .

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMSWINC are UNDEFINED.

Attributes

PMSWINC is a 32-bit register.

Field descriptions

The PMSWINC bit assignments are:



Bit [31]

Reserved, RES0.

P<n>, bit [n], for n = 0 to 30

Event counter software increment bit for PMEVCNTR<n>.

If N is less than 31, then bits [30:N] are WI. When EL2 is implemented and enabled in the current Security state, in EL1 and EL0, N is the value in MDCR_EL2.HPMN if EL2 is using AArch64, or in HDCR.HPMN if EL2 is using AArch32. Otherwise, N is the value in PMCR.N.

P<n>	Meaning
0b0	No action. The write to this bit is ignored.
0b1	If PMEVCNTR<n> is enabled and configured to count the software increment event, increments PMEVCNTR<n> by 1. If PMEVCNTR<n> is disabled, or not configured to count the software increment event, the write to this bit is ignored.

Accessing the PMSWINC

Accesses to this register use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1100	0b100

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.<SW,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.<SW,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMSWINC_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMSWINC = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMSWINC = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMSWINC = R[t];
elsif PSTATE.EL == EL3 then
    PMSWINC = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMUSERENR, Performance Monitors User Enable Register

The PMUSERENR characteristics are:

Purpose

Enables or disables User mode access to the Performance Monitors.

Configuration

AArch32 System register PMUSERENR bits [31:0] are architecturally mapped to AArch64 System register PMUSERENR_EL0[31:0] .

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMUSERENR are UNDEFINED.

Attributes

PMUSERENR is a 32-bit register.

Field descriptions

The PMUSERENR bit assignments are:



Bits [31:4]

Reserved, RES0.

ER, bit [3]

Event counter read trap control:

ER	Meaning
0b0	EL0 reads of the PMXEVCNTR and PMEVCNTR<n>, and EL0 RW access to the PMSELR, are trapped to Undefined mode if PMUSERENR.EN is also 0.
0b1	Overrides PMUSERENR.EN and enables RO access to PMXEVCNTR and PMEVCNTR<n>, and RW access to PMSELR.

On a Warm reset, this field resets to 0.

CR, bit [2]

Cycle counter read trap control:

CR	Meaning
0b0	EL0 reads of the PMCCNTR are trapped to Undefined mode if PMUSERENR.EN is also 0.
0b1	Overrides PMUSERENR.EN and enables access to PMCCNTR.

On a Warm reset, this field resets to 0.

SW, bit [1]

Software increment write trap control:

SW	Meaning
0b0	EL0 writes to the PMSWINC are trapped to Undefined mode if PMUSERENR.EN is also 0.
0b1	Overrides PMUSERENR.EN and enables access to PMSWINC.

On a Warm reset, this field resets to 0.

EN, bit [0]

Traps EL0 accesses to the Performance Monitors registers to Undefined mode, as follows:

- PMCR, PMOVSR, PMSELR, PMCEID0, PMCEID1, PMCCNTR, PMXEVTYPER, PMXEVNTR, PMCNTENSET, PMCNTENCLR, PMOVSSET, PMEVCNTR<n>, PMEVTYPER<n>, PMCCFILTR, PMSWINC.
- If ARMv8.1-PMU is implemented, PMCEID2, and PMCEID3.
- If ARMv8.4-PMU is implemented, PMMIR.

EN	Meaning
0b0	While at EL0, accessesPMUSERENR is always RO. Accesses to the specifiedother registersPerformance atMonitors EL0registers are trapped to Undefined mode, unless overriddenenabled by one of PMUSERENR.{ER, CR, SW}.
0b1	While at EL0, software can access all ofPMU theregisters specified registers.exceptPMINTENSET and PMINTENCLR.

On a Warm reset, this field resets to 0.

Accessing the PMUSERENR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1110	0b000

```
if PSTATE.EL == EL0 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMUSERENR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMUSERENR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMUSERENR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMUSERENR;
elsif PSTATE.EL == EL3 then
    return PMUSERENR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1110	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMUSERENR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMUSERENR = R[t];
elsif PSTATE.EL == EL3 then
    PMUSERENR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMXEVCNTR, Performance Monitors Selected Event Count Register

The PMXEVCNTR characteristics are:

Purpose

Reads or writes the value of the selected event counter, PMEVCNTR<n>. PMSELR.SEL determines which event counter is selected.

Configuration

AArch32 System register PMXEVCNTR bits [31:0] are architecturally mapped to AArch64 System register PMXEVCNTR_EL0[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMXEVCNTR are UNDEFINED.

Attributes

PMXEVCNTR is a 32-bit register.

Field descriptions

The PMXEVCNTR bit assignments are:



PMEVCNTR<n>, bits [31:0]

Value of the selected event counter, PMEVCNTR<n>, where n is the value stored in PMSELR.SEL.

If ARMv8.5-PMU is implemented, the event counter is 64 bits and only the least-significant part of the event counter is accessible in AArch32 state:

- Reads from PMXEVCNTR return bits [31:0] of the counter.
- Writes to PMXEVCNTR update bits [31:0] and leave bits [63:32] unchanged.
- There is no means to access bits [63:32] directly from AArch32 state.
- If the implementation does not support AArch64 at any Exception level, bits [63:32] are not required to be implemented.

If ARMv8.5-PMU is not implemented, the event counter is 32 bits.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMXEVCNTR

If ARMv8.6-FGT is implemented~~, EL2 is implemented~~ and ~~enabled in the current Security state, and EL1 is using AArch64, for permitted reads and writes at EL0:~~ PMSELR.SEL is greater than or equal to the number of accessible counters, then the behavior of permitted reads and writes of PMXEVCNTR is as follows:

- If PMSELR.SEL selectsis an unimplemented event counter, the access is UNDEFINED.
- Otherwise, the access is trapped to EL2.if PMSELR.SEL is greater than or equal to MDCR_EL2.HPMN, the access is trapped to EL2.

If PMSELR.SEL is greater than or equal to the number of accessible counters then reads and writes of PMXEVCNTR are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

If ARMv8.6-FGT is not implemented, andor the above behaviors do not apply: PMSELR.SEL is greater than or equal to the number of accessible counters, then reads and writes of PMXEVCNTR are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

- Accesses to the register are UNDEFINED.
- Accesses to the register behave as RAZ/WI.
- Accesses to the register execute as a NOP
- Accesses to the register behave as if PMSELR.SEL has an UNKNOWN value less than the number of counters accessible at the current Exception level and Security state.
- If EL2 is implemented and enabled in the current Security state, and PMSELR.SEL is less than the number of implemented counters, accesses from EL1 or permitted accesses from EL0 are trapped to EL2.

Note

In EL0, an access is permitted if it is enabled by PMUSERENR.{ER,EN} or PMUSERENR_EL0.{ER,EN}.

If EL2 is implemented and enabled in the current Security state, at EL0 and EL1:

- If EL2 is using AArch32, HDCR.HPMN identifies the number of accessible counters.
- If EL2 is using AArch64, MDCR_EL2.HPMN identifies the number of accessible counters.

Otherwise, the number of accessible counters is the number of implemented counters. See HDCR.HPMN and MDCR_EL2.HPMN for more details.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1101	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.<ER,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.<ER,EN> == '00' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMXEVCNTR;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMXEVCNTR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMXEVCNTR;
elsif PSTATE.EL == EL3 then
    return PMXEVCNTR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1101	0b010

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMEVCNTRn_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMXEVCNTR = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMXEVCNTR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMXEVCNTR = R[t];
elsif PSTATE.EL == EL3 then
    PMXEVCNTR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMXEVTYPER, Performance Monitors Selected Event Type Register

The PMXEVTYPER characteristics are:

Purpose

When PMSELR.SEL selects an event counter, this accesses a PMEVTYPER<n> register. When PMSELR.SEL selects the cycle counter, this accesses PMCCFILTR.

Configuration

AArch32 System register PMXEVTYPER bits [31:0] are architecturally mapped to AArch64 System register PMXEVTYPER_EL0[31:0] .

This register is present only when AArch32 is supported at any Exception level and PMUv3 is implemented. Otherwise, direct accesses to PMXEVTYPER are UNDEFINED.

Attributes

PMXEVTYPER is a 32-bit register.

Field descriptions

The PMXEVTYPER bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Event type register or PMCCFILTR																															

Bits [31:0]

Event type register or PMCCFILTR.

When PMSELR.SEL == 31, this register accesses PMCCFILTR.

Otherwise, this register accesses PMEVTYPER<n> where n is the value in PMSELR.SEL.

Accessing the PMXEVTYPER

If ARMv8.6-FGT is implemented, ~~EL2 is implemented~~ and ~~enabled in the current Security state, and EL1 is using AArch64, for permitted reads and writes at EL0:~~ PMSELR.SEL is not 31 and is greater than or equal to the number of accessible counters, then the behavior of permitted reads and writes of PMXEVTYPER is as follows:

- If PMSELR.SEL selects~~is~~ an unimplemented event counter, the access is UNDEFINED.
- Otherwise, the access is trapped to EL2.~~if PMSELR.SEL is not 31, and is greater than or equal to MDCR_EL2.HPMN, the access is trapped to EL2.~~

~~If PMSELR.SEL is not 31, and is greater than or equal to the number of accessible counters then reads and writes of PMXEVTYPER are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:~~

If ARMv8.6-FGT is not implemented, and~~or the above behaviors do not apply:~~ PMSELR.SEL is not 31 and is greater than or equal to the number of accessible counters, then reads and writes of PMXEVTYPER are CONSTRAINED UNPREDICTABLE, and the following behaviors are permitted:

- Accesses to the register are UNDEFINED.
- Accesses to the register behave as RAZ/WI.

- Accesses to the register execute as a `NOP`
- Accesses to the register behave as if PMSELR.SEL has an UNKNOWN value less than the number of counters accessible at the current Exception level and Security state.
- Accesses to the register behave as if PMSELR.SEL is 31.
- If EL2 is implemented and enabled in the current Security state, and PMSELR.SEL is less than the number of implemented counters, accesses from EL1 or permitted accesses from EL0 are trapped to EL2.

Note

In EL0, an access is permitted if it is enabled by PMUSERENR.EN or PMUSERENR_EL0.EN.

If EL2 is implemented and enabled in the current Security state, at EL0 and EL1:

- If EL2 is using AArch32, HDCR.HPMN identifies the number of accessible counters.
- If EL2 is using AArch64, MDCR_EL2.HPMN identifies the number of accessible counters.

Otherwise, the number of accessible counters is the number of implemented counters. See HDCR.HPMN and MDCR_EL2.HPMN for more details.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1101	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGRTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMXEVTYPER;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMXEVTYPER;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        return PMXEVTYPER;
elsif PSTATE.EL == EL3 then
    return PMXEVTYPER;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1001	0b1101	0b001

```
if PSTATE.EL == EL0 then
    if !ELUsingAArch32(EL1) && PMUSERENR_EL0.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        else
            AArch64.AArch32SystemAccessTrap(EL1, 0x03);
    elsif ELUsingAArch32(EL1) && PMUSERENR.EN == '0' then
        if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TGE == '1' then
            AArch64.AArch32SystemAccessTrap(EL2, 0x03);
        elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TGE == '1' then
            AArch32.TakeHypTrapException(0x00);
        else
            UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T9 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HDFGWTR_EL2.PMEVTYPERn_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMXEVTYPER = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T9 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T9 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TPM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMXEVTYPER = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TPM == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        PMXEVTYPER = R[t];
elsif PSTATE.EL == EL3 then
    PMXEVTYPER = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PRRR, Primary Region Remap Register

The PRRR characteristics are:

Purpose

Controls the top level mapping of the TEX[0], C, and B memory region attributes.

Configuration

AArch32 System register PRRR bits [31:0] are architecturally mapped to AArch64 System register MAIR_EL1[31:0] when TTBCR.EAE == 0.

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to PRRR are UNKNOWN.

MAIR0 and PRRR are the same register, with a different view depending on the value of TTBCR.EAE:

- When it is set to 0, the register is as described in PRRR.
- When it is set to 1, the register is as described in MAIR0.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

PRRR is a 32-bit register.

Field descriptions

The PRRR bit assignments are:

When TTBCR.EAE == 0:

31	30	29	28	27	26	25	24	23222120	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
NOS7	NOS6	NOS5	NOS4	NOS3	NOS2	NOS1	NOS0	RES0	NS1	NS0	DS1	DS0	TR7	TR6	TR5	TR4	TR3	TR2	TR1	TR0								

NOS<n>, bit [n+24], for n = 0 to 7

Not Outer Shareable. NOS<n> is the Outer Shareable property for memory attributes n, if the region is mapped as Normal memory that is not Inner Non-cacheable, Outer Non-cacheable, and the appropriate PRRR.{NS0, NS1} field identifies the region as shareable. n is the value of the concatenation of the {TEX[0], C, B} bits from the translation table descriptor. The possible values of each NOS<n> field other than NOS6 are:

NOS<n>	Meaning
0b0	Memory region is Outer Shareable.
0b1	Memory region is Inner Shareable.

The value of this bit is ignored if the region is:

- Device memory
- Normal memory that is at least one of:
  - Inner Non-cacheable, Outer Non-cacheable.
  - Identified by the appropriate PRRR.{NS0, NS1} field as Non-shareable.

The meaning of the NOS6 field is IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Bits [23:20]

Reserved, RES0.

NS1, bit [19]

Mapping of S = 1 attribute for Normal memory regions. This field is used in determining the Shareability of a memory region that is mapped to Normal memory and both:

- Is not Inner Non-cacheable, Outer Non-cacheable.
- Has the S bit in the translation table descriptor set to 1.

The possible values of this bit are:

NS1	Meaning
0b0	Region is Non-shareable.
0b1	Region is shareable. The value of the appropriate PRRR.NOS<n> field determines whether the region is Inner Shareable or Outer Shareable.

This field resets to an architecturally UNKNOWN value.

NS0, bit [18]

Mapping of S = 0 attribute for Normal memory regions. This field is used in determining the Shareability of a memory region that is mapped to Normal memory and both:

- Is not Inner Non-cacheable, Outer Non-cacheable.
- Has the S bit in the translation table descriptor set to 0.

The possible values of this bit are:

NS0	Meaning
0b0	Region is Non-shareable.
0b1	Region is shareable. The value of the appropriate PRRR.NOS<n> field determines whether the region is Inner Shareable or Outer Shareable.

This field resets to an architecturally UNKNOWN value.

DS1, bit [17]

Mapping of S = 1 attribute for Device memory. From Armv8, all types of Device memory are Outer Shareable, and therefore this bit is RES1.

This field resets to an architecturally UNKNOWN value.

DS0, bit [16]

Mapping of S = 0 attribute for Device memory. From Armv8, all types of Device memory are Outer Shareable, and therefore this bit is RES1.

This field resets to an architecturally UNKNOWN value.

TR<n>, bits [2n+1:2n], for n = 0 to 7

TR<n> is the primary TEX mapping for memory attributes n, and defines the mapped memory type for a region with attributes n. n is the value of the concatenation of the {TEX[0], C, B} bits from the translation table descriptor. The possible values for each field other than TR6 are:

TR<n>	Meaning
0b00	Device-nGnRnE memory
0b01	Device-nGnRE memory
0b10	Normal memory

The value `0b11` is reserved. The effect of programming a field to `0b11` is CONSTRAINED UNPREDICTABLE, see 'Unallocated values in fields of AArch32 System registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.1.11.

The meaning of the TR6 field is IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the PRRR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return PRRR_S;
        else
            return PRRR_NS;
    else
        return PRRR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return PRRR_NS;
    else
        return PRRR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return PRRR_S;
    else
        return PRRR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1010	0b0010	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T10 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T10 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            PRRR_S = R[t];
        else
            PRRR_NS = R[t];
    else
        PRRR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        PRRR_NS = R[t];
    else
        PRRR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            PRRR_S = R[t];
        else
            PRRR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

REVIDR, Revision ID Register

The REVIDR characteristics are:

Purpose

Provides implementation-specific minor revision information.

Configuration

AArch32 System register REVIDR bits [31:0] are architecturally mapped to AArch64 System register REVIDR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to REVIDR are UNKNOWN.

If REVIDR has the same value as MIDR, then its contents have no significance.

Attributes

REVIDR is a 32-bit register.

Field descriptions

The REVIDR bit assignments are:



IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

Accessing the REVIDR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0000	0b110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return REVIDR;
elsif PSTATE.EL == EL2 then
    return REVIDR;
elsif PSTATE.EL == EL3 then
    return REVIDR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

RMR, Reset Management Register

The RMR characteristics are:

Purpose

If EL1 or EL3 is the highest implemented Exception level and this register is implemented:

- A write to the register at the highest implemented Exception level can request a Warm reset.
- If the highest implemented Exception level can use AArch32 and AArch64, this register specifies the Execution state that the PE boots into on a Warm reset.

Configuration

AArch32 System register RMR bits [31:0] are architecturally mapped to AArch64 System register RMR_EL1[31:0] when the highest implemented Exception level is EL1.~~IsHighestEL(EL1).~~

AArch32 System register RMR bits [31:0] are architecturally mapped to AArch64 System register RMR_EL3[31:0] when ~~HaveEL(~~EL3 is implemented.~~).~~

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to RMR are UNKNOWN.

Only implemented if EL1 or EL3 is the highest implemented Exception level. In this case:

- If the highest implemented Exception level can use AArch32 and AArch64 then this register must be implemented.
- If the highest implemented Exception level cannot use AArch64 then it is IMPLEMENTATION DEFINED whether the register is implemented.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

RMR is a 32-bit register.

Field descriptions

The RMR bit assignments are:



Bits [31:2]

Reserved, RES0.

RR, bit [1]

Reset Request. Setting this bit to 1 requests a Warm reset.

This field resets to 0.

AA64, bit [0]

When the highest implemented Exception level can use AArch64, determines which Execution state the PE boots into after a Warm reset:

AA64	Meaning
0b0	AArch32.
0b1	AArch64.

On coming out of the Warm reset, execution starts at the IMPLEMENTATION DEFINED reset vector address of the specified Execution state.

If the highest implemented Exception level cannot use AArch64 this bit is RAZ/WI.

When implemented as a RW field, this field resets to 0 on a Cold reset.

Accessing the RMR

When EL3 is implemented, Arm deprecates accessing this register from any PE mode other than Monitor mode.

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b0000	0b010

```
if PSTATE.EL IN {EL3, EL1} && IsHighestEL(PSTATE.EL) then
    return RMR;
else
    UNDEFINED;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b0000	0b010

```
if PSTATE.EL IN {EL3, EL1} && IsHighestEL(PSTATE.EL) then
    RMR = R[t];
else
    UNDEFINED;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

RVBAR, Reset Vector Base Address Register

The RVBAR characteristics are:

Purpose

If EL3 is not implemented, contains the IMPLEMENTATION DEFINED address that execution starts from after reset when executing in AArch32 state.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to RVBAR are UNKNOWN.

This register is only implemented if the highest Exception level implemented is capable of using AArch32, and is not EL3.

Attributes

RVBAR is a 32-bit register.

Field descriptions

The RVBAR bit assignments are:



Bits [31:1]

Reset Address[31:1]. Bits [31:1] of the IMPLEMENTATION DEFINED address that execution starts from after reset when executing in 32-bit state.

Bit [0]

Reserved, RES1.

Accessing the RVBAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b0000	0b001

```
if PSTATE.EL ==IN EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if IsHighestEL(EL1) then
        return RVBAR;
    elsif EL2Enabled() && !ELUsingAArch32({EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsifEL1} EL2Enabled() && ELUsingAArch32IsHighestEL(EL2PSTATE.EL) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    if IsHighestEL(EL2) then
        return RVBAR;
else
    else
        UNDEFINED;
elsif PSTATE.EL == EL3 then
    return MVBAR;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SCR, Secure Configuration Register

The SCR characteristics are:

Purpose

When EL3 is implemented and can use AArch32, defines the configuration of the current Security state. It specifies:

- The Security state, either Secure or Non-secure.
- What mode the PE branches to if an IRQ, FIQ, or External abort occurs.
- Whether the CPSR.F or CPSR.A bits can be modified when SCR.NS==1.

Configuration

AArch32 System register SCR bits [31:0] can be mapped to AArch64 System register SCR_EL3[31:0] , but this is not architecturally mandated.

ThisSome or all RW fields of this register ishave presentdefined only whenreset AArch32values. These apply whenever the register is supportedaccessible. This atmeans anythey Exceptionapply level. Otherwise,when directthe accessesPE toresets SCRinto areEL3 using AArch32. UNKNOWN.

Attributes

SCR is a 32-bit register.

Field descriptions

The SCR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																TERR	RES0	TWE	TWI	RES0		SIF	HCE	SCD	nET	AW	FW	EA	FIQ	IRQ	NS

Bits [31:16]

Reserved, RES0.

TERR, bit [15]

When RAS is implemented:

Trap Error record accesses. Generate a Monitor Trap exception on accesses to the following registers from modes other than Monitor mode:

ERRIDR, ERRSELR, ERXADDR, ERXADDR2, ERXCTLR, ERXCTLR2, ERXFR, ERXFR2, ERXMISC0, ERXMISC1, ERXMISC2, ERXMISC3, and ERXSTATUS. When ARMv8.4-RAS is implemented, ERXMISC4, ERXMISC5, ERXMISC6, ERXMISC7.

TERR	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Accesses to the specified registers from modes other than Monitor mode generate a Monitor Trap exception.

In a system where the PE resets into EL3, this field resets to 0.

Otherwise:

Reserved, RES0.

Bit [14]

Reserved, RES0.

TWE, bit [13]

Traps WFE instructions to Monitor mode.

TWE	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Any attempt to execute a WFE instruction in any mode other than Monitor mode is trapped to Monitor mode, if the instruction would otherwise have caused the PE to enter a low-power state and the attempted execution does not generate an exception that is taken to EL1 or EL2 by SCTLR.nTWE or HCR.TWE. Any exception that is taken to EL1 or to EL2 has priority over this trap.

The attempted execution of a conditional WFE instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE or WFI can complete at any time, even without a Wakeup event, the traps on WFE of WFI are not guaranteed to be taken, even if the WFE or WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

In a system where the PE resets into EL3, this field resets to 0.

TWI, bit [12]

Traps WFI instructions to Monitor mode.

TWI	Meaning
0b0	This control does not cause any instructions to be trapped.
0b1	Any attempt to execute a WFI instruction in any mode other than Monitor mode is trapped to Monitor mode, if the instruction would otherwise have caused the PE to enter a low-power state and the attempted execution does not generate an exception that is taken to EL1 or EL2 by SCTLR.nTWI or HCR.TWI. Any exception that is taken to EL1 or to EL2 has priority over this trap.

The attempted execution of a conditional WFI instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE or WFI can complete at any time, even without a Wakeup event, the traps on WFE of WFI are not guaranteed to be taken, even if the WFE or WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

In a system where the PE resets into EL3, this field resets to 0.

Bits [11:10]

Reserved, RES0.

SIF, bit [9]

Secure instruction fetch. When the PE is in Secure state, this bit disables instruction fetch from Non-secure memory. The possible values for this bit are:

SIF	Meaning
0b0	Secure state instruction fetches from Non-secure memory are permitted.
0b1	Secure state instruction fetches from Non-secure memory are not permitted.

This bit is permitted to be cached in a TLB.

In a system where the PE resets into EL3, this field resets to 0.

HCE, bit [8]

Hypervisor Call instruction enable. If EL2 is implemented, enables execution of HVC instructions at Non-secure EL1 and EL2.

HCE	Meaning
0b0	HVC instructions are: • UNDEFINED at Non-secure EL1. The Undefined Instruction exception is taken from PL1 to PL1. • UNPREDICTABLE at EL2. Behavior is one of the following: ◦ The instruction is UNDEFINED. ◦ The instruction executes as a NOP.
0b1	HVC instructions are enabled at Non-secure EL1 and EL2.

Note

HVC instructions are always UNDEFINED at EL0 and in Secure state.

If EL2 is not implemented, this bit is RES0 and HVC is UNDEFINED.

In a system where the PE resets into EL3, this field resets to 0.

SCD, bit [7]

Secure Monitor Call disable. Disables SMC instructions.

SCD	Meaning
0b0	SMC instructions are enabled.
0b1	In Non-secure state, SMC instructions are UNDEFINED. The Undefined Instruction exception is taken from the current Exception level to the current Exception level. In Secure state, behavior is one of the following: • The instruction is UNDEFINED. • The instruction executes as a NOP.

Note

SMC instructions are always UNDEFINED at PL0.

In a system where the PE resets into EL3, this field resets to 0.

nET, bit [6]

Not Early Termination. This bit disables early termination. The possible values of this bit are:

nET	Meaning
0b0	Early termination permitted. Execution time of data operations can depend on the data values.
0b1	Disable early termination. The number of cycles required for data operations is forced to be independent of the data values.

This IMPLEMENTATION DEFINED mechanism can disable data dependent timing optimizations from multiplies and data operations. It can provide system support against information leakage that might be exploited by timing correlation types of attack.

On implementations that do not support early termination or do not support disabling early termination, this bit is RES0.

In a system where the PE resets into EL3, this field resets to 0.

AW, bit [5]

When the value of SCR.EA is 1 and the value of HCR.AMO is 0, this bit controls whether CPSR.A masks an External abort taken from Non-secure state, and the possible values of this bit are:

AW	Meaning
0b0	External aborts taken from Non-secure state are not masked by CPSR.A, and are taken to EL3. External aborts taken from Secure state are masked by CPSR.A.
0b1	External aborts taken from either Security state are masked by CPSR.A. When CPSR.A is 0, the abort is taken to EL3.

When SCR.EA is 0 or HCR.AMO is 1, this bit has no effect.

In a system where the PE resets into EL3, this field resets to 0.

FW, bit [4]

When the value of SCR.FIQ is 1 and the value of HCR.FMO is 0, this bit controls whether CPSR.F masks an FIQ interrupt taken from Non-secure state, and the possible values of this bit are:

FW	Meaning
0b0	An FIQ taken from Non-secure state is not masked by CPSR.F, and is taken to EL3. An FIQ taken from Secure state is masked by CPSR.F.
0b1	An FIQ taken from either Security state is masked by CPSR.F. When CPSR.F is 0, the FIQ is taken to EL3.

When SCR.FIQ is 0 or HCR.FMO is 1, this bit has no effect.

In a system where the PE resets into EL3, this field resets to 0.

EA, bit [3]

External Abort handler. This bit controls which mode takes External aborts. The possible values of this bit are:

EA	Meaning
0b0	External aborts taken to Abort mode.
0b1	External aborts taken to Monitor mode.

In a system where the PE resets into EL3, this field resets to 0.

FIQ, bit [2]

FIQ handler. This bit controls which mode takes FIQ exceptions. The possible values of this bit are:

FIQ	Meaning
0b0	FIQs taken to FIQ mode.
0b1	FIQs taken to Monitor mode.

In a system where the PE resets into EL3, this field resets to 0.

IRQ, bit [1]

IRQ handler. This bit controls which mode takes IRQ exceptions. The possible values of this bit are:

IRQ	Meaning
0b0	IRQs taken to IRQ mode.
0b1	IRQs taken to Monitor mode.

In a system where the PE resets into EL3, this field resets to 0.

NS, bit [0]

Non-secure bit. Except when the PE is in Monitor mode, this bit determines the Security state of the PE:

NS	Meaning
0b0	PE is in Secure state.
0b1	PE is in Non-secure state.

If the HCR.TGE bit is set, an attempt to change from a Secure PL1 mode to a Non-secure EL1 mode by changing the SCR.NS bit from 0 to 1 results in the SCR.NS bit remaining as 0.

In a system where the PE resets into EL3, this field resets to 0.

Accessing the SCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return SCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0001	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    SCR = R[t];
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SCTLR, System Control Register

The SCTLR characteristics are:

Purpose

Provides the top level control of the system, including its memory system.

Configuration

AArch32 System register SCTLR bits [31:0] are architecturally mapped to AArch64 System register SCTLR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to SCTLR are UNKNOWN.

Some bits in the register are read-only. These bits relate to non-configurable features of an implementation, and are provided for compatibility with previous versions of the architecture.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. If the PE resets into EL3 using AArch32 they apply only to the Secure instance of the register. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SCTLR is a 32-bit register.

Field descriptions

The SCTLR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6
DSSBS	TE	AFE	TRE	RES0		EE	RES0	SPAN	RES1	RES0	UWXN	WXN	nTWE	RES0	nTWI	RES0		V	I	RES1	EnRCTX	RES0	SED	ITD	UNK

DSSBS, bit [31]

When ARMv8.0-SSBS is implemented:

Default PSTATE.SSBS value on Exception Entry. The defined values are:

DSSBS	Meaning
0b0	PSTATE.SSBS is set to 0 on an exception to any mode in this security state except Hyp mode
0b1	PSTATE.SSBS is set to 1 on an exception to any mode in this security state except Hyp mode

Note

When EL3 is implemented and is using AArch32, this bit is banked between the two Security states.

This field resets to an IMPLEMENTATION DEFINED value.

Otherwise:

Reserved, RES0.

TE, bit [30]

T32 Exception Enable. This bit controls whether exceptions to an Exception Level that is executing at PL1 are taken to A32 or T32 state:

TE	Meaning
0b0	Exceptions, including reset, taken to A32 state.
0b1	Exceptions, including reset, taken to T32 state.

This field resets to an IMPLEMENTATION DEFINED choice between:

- 0.
- A value determined by an input configuration signal.

AFE, bit [29]

Access Flag Enable. When using the Short-descriptor translation table format for the PL1&0 translation regime, this bit enables use of the AP[0] bit in the translation descriptors as the Access flag, and restricts access permissions in the translation descriptors to the simplified model. The possible values of this bit are:

AFE	Meaning
0b0	In the translation table descriptors, AP[0] is an access permissions bit. The full range of access permissions is supported. No Access flag is implemented.
0b1	In the translation table descriptors, AP[0] is the Access flag. Only the simplified model for access permissions is supported.

When using the Long-descriptor translation table format, the VMSA behaves as if this bit is set to 1, regardless of the value of this bit.

The AFE bit is permitted to be cached in a TLB.

This field resets to 0.

TRE, bit [28]

TEX remap enable. This bit enables remapping of the TEX[2:1] bits in the PL1&0 translation regime for use as two translation table bits that can be managed by the operating system. Enabling this remapping also changes the scheme used to describe the memory region attributes in the VMSA. The possible values of this bit are:

TRE	Meaning
0b0	TEX remap disabled. TEX[2:0] are used, with the C and B bits, to describe the memory region attributes.
0b1	TEX remap enabled. TEX[2:1] are reassigned for use as bits managed by the operating system. The TEX[0], C, and B bits are used to describe the memory region attributes, with the MMU remap registers.

When the value of TTBCR.EAE is 1, this bit is RES1.

The TRE bit is permitted to be cached in a TLB.

This field resets to 0.

Bits [27:26]

Reserved, RES0.

EE, bit [25]

The value of the PSTATE.E bit on branch to an exception vector or coming out of reset, and the endianness of stage 1 translation table walks in the PL1&0 translation regime.

The possible values of this bit are:

EE	Meaning
0b0	Little-endian. PSTATE.E is cleared to 0 on taking an exception or coming out of reset. Stage 1 translation table walks in the PL1&0 translation regime are little-endian.
0b1	Big-endian. PSTATE.E is set to 1 on taking an exception or coming out of reset. Stage 1 translation table walks in the PL1&0 translation regime are big-endian.

If an implementation does not provide Big-endian support for data accesses at Exception Levels higher than EL0, this bit is RES0.

If an implementation does not provide Little-endian support for data accesses at Exception Levels higher than EL0, this bit is RES1.

This field resets to an IMPLEMENTATION DEFINED choice between:

- 0.
- A value determined by an input configuration signal.

Bit [24]

Reserved, RES0.

SPAN, bit [23]

When ARMv8.1-PAN is implemented:

Set Privileged Access Never, on taking an exception to EL1 from either Secure or Non-secure state, or to EL3 from Secure state when EL3 is using AArch32.

SPAN	Meaning
0b0	CPSR.PAN is set to 1 in the following situations: • In Non-secure state, on taking an exception to EL1. • In Secure state, when EL3 is using AArch64, on taking an exception to EL1. • In Secure state, when EL3 is using AArch32, on taking an exception to EL3.
0b1	The value of CPSR.PAN is left unchanged on taking an exception to EL1.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

Bit [22]

Reserved, RES1.

Bit [21]

Reserved, RES0.

UWXN, bit [20]

Unprivileged write permission implies PL1 XN (Execute-never). This bit can force all memory regions that are writable at PL0 to be treated as XN for accesses from software executing at PL1. The possible values of this bit are:

UWXN	Meaning
0b0	This control has no effect on memory access permissions.
0b1	Any region that is writable at PL0 forced to XN for accesses from software executing at PL1.

The UWXN bit is permitted to be cached in a TLB.

This field resets to `0`.

WXN, bit [19]

Write permission implies XN (Execute-never). For the PL1&0 translation regime, this bit can force all memory regions that are writable to be treated as XN. The possible values of this bit are:

WXN	Meaning
`0b0`	This control has no effect on memory access permissions.
`0b1`	Any region that is writable in the PL1&0 translation regime is forced to XN for accesses from software executing at PL1 or PL0.

This bit applies only when SCTLR.M bit is set.

The WXN bit is permitted to be cached in a TLB.

This field resets to `0`.

nTWE, bit [18]

Traps EL0 execution of WFE instructions to Undefined mode.

nTWE	Meaning
`0b0`	Any attempt to execute a WFE instruction at EL0 is trapped to Undefined mode, if the instruction would otherwise have caused the PE to enter a low-power state.
`0b1`	This control does not cause any instructions to be trapped.

The attempted execution of a conditional WFE instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE or WFI can complete at any time, even without a Wakeup event, the traps on WFE of WFI are not guaranteed to be taken, even if the WFE or WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

This field resets to `1`.

Bit [17]

Reserved, RES0.

nTWI, bit [16]

Traps EL0 execution of WFI instructions to Undefined mode.

nTWI	Meaning
`0b0`	Any attempt to execute a WFI instruction at EL0 is trapped to Undefined mode, if the instruction would otherwise have caused the PE to enter a low-power state.
`0b1`	This control does not cause any instructions to be trapped.

The attempted execution of a conditional WFI instruction is only trapped if the instruction passes its condition code check.

Note

Since a WFE or WFI can complete at any time, even without a Wakeup event, the traps on WFE of WFI are not guaranteed to be taken, even if the WFE or

> WFI is executed when there is no Wakeup event. The only guarantee is that if the instruction does not complete in finite time in the absence of a Wakeup event, the trap will be taken.

This field resets to 1.

Bits [15:14]

Reserved, RES0.

V, bit [13]

Vectors bit. This bit selects the base address of the exception vectors for exceptions taken to a PE mode other than Monitor mode or Hyp mode:

V	Meaning
0b0	Normal exception vectors. Base address is held in VBAR.
0b1	High exception vectors (Hivecs), base address 0xFFFF0000. This base address cannot be remapped.

This field resets to an IMPLEMENTATION DEFINED choice between:

- 0.
- A value determined by an input configuration signal.

I, bit [12]

Instruction access Cacheability control, for accesses at EL1 and EL0:

I	Meaning
0b0	All instruction access to Normal memory from PL1 and PL0 are Non-cacheable for all levels of instruction and unified cache. If the value of SCTLR.M is 0, instruction accesses from stage 1 of the PL1&0 translation regime are to Normal, Outer Shareable, Inner Non-cacheable, Outer Non-cacheable memory.
0b1	All instruction access to Normal memory from PL1 and PL0 can be cached at all levels of instruction and unified cache. If the value of SCTLR.M is 0, instruction accesses from stage 1 of the PL1&0 translation regime are to Normal, Outer Shareable, Inner Write-Through, Outer Write-Through memory.

Instruction accesses to Normal memory from EL1 and EL0 are Cacheable regardless of the value of the SCTLR.I bit if either:

- EL2 is using AArch32 and the value of HCR.DC is 1.
- EL2 is using AArch64 and the value of HCR_EL2.DC is 1.

This field resets to 0.

Bit [11]

Reserved, RES1.

EnRCTX, bit [10]

When ARMv8.0-CSV2 is implemented:

Enable EL0 Access to the AArch32 CFPRCTX, DVPRCTX and CPPRCTX instructions. The defined values are:

EnRCTX	Meaning
0b0	EL0 access to these instructions is disabled, and these instructions are trapped to EL1.
0b1	EL0 access to these instructions is enabled.

Note

When EL3 is implemented and is using AArch32, this bit is banked between the two Security states.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [9]

Reserved, RES0.

SED, bit [8]

SETEND instruction disable. Disables SETEND instructions at PL0 and PL1.

SED	Meaning
0b0	SETEND instruction execution is enabled at PL0 and PL1.
0b1	SETEND instructions are UNDEFINED at PL0 and PL1.

If the implementation does not support mixed-endian operation at any Exception level, this bit is RES1.

This field resets to 0.

ITD, bit [7]

IT Disable. Disables some uses of IT instructions at PL1 and PL0.

ITD	Meaning
0b0	All IT instruction functionality is enabled at PL1 and PL0.
0b1	Any attempt at PL1 or PL0 to execute any of the following is UNDEFINED: • All encodings of the IT instruction with hw1[3:0]!=1000. • All encodings of the subsequent instruction with the following values for hw1: ◦ 11xxxxxxxxxxxxxx: All 32-bit instructions, and the 16-bit instructions B, UDF, SVC, LDM, and STM. ◦ 1011xxxxxxxxxxxx: All instructions in Miscellaneous 16-bit instructions. ◦ 10100xxxxxxxxxxx: ADD Rd, PC, #imm ◦ 01001xxxxxxxxxxx: LDR Rd, [PC, #imm] ◦ 0100x1xxx1111xxx: ADD Rdn, PC; CMP Rn, PC; MOV Rd, PC; BX PC; BLX PC. ◦ 010001xx1xxxx111: ADD PC, Rm; CMP PC, Rm; MOV PC, Rm. This pattern also covers unpredictable cases with BLX Rn. These instructions are always UNDEFINED, regardless of whether they would pass or fail the condition code check that applies to them as a result of being in an IT block. It is IMPLEMENTATION DEFINED whether the IT instruction is treated as: • A 16-bit instruction, that can only be followed by another 16-bit instruction. • The first half of a 32-bit instruction. This means that, for the situations that are UNDEFINED, either the second 16-bit instruction or the 32-bit instruction is UNDEFINED. An implementation might vary dynamically as to whether IT is treated as a 16-bit instruction or the first half of a 32-bit instruction.

If an instruction in an active IT block that would be disabled by this field sets this field to 1 then behavior is CONSTRAINED UNPREDICTABLE. For more information see 'Changes to an ITD control by an instruction in an IT block' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section E1.2.4.

ITD is optional, but if it is implemented in the SCTLR then it must also be implemented in the SCTLR_EL1. If it is not implemented then this bit is RAZ/WI.

This field resets to `0`.

UNK, bit [6]

Writes to this bit are IGNORED. Reads of this bit return an UNKNOWN value.

This field resets to an architecturally UNKNOWN value.

CP15BEN, bit [5]

System instruction memory barrier enable. Enables accesses to the DMB, DSB, and ISB System instructions in the (coproc==`0b1111`) encoding space from PL1 and PL0:

CP15BEN	Meaning
`0b0`	PL0 and PL1 execution of the CP15DMB, CP15DSB, and CP15ISB instructions is UNDEFINED.
`0b1`	PL0 and PL1 execution of the CP15DMB, CP15DSB, and CP15ISB instructions is enabled.

CP15BEN is optional, but if it is implemented in the SCTLR then it must also be implemented in the SCTLR_EL1. If it is not implemented then this bit is RAO/WI.

This field resets to `1`.

LSMAOE, bit [4]

When ARMv8.2-LSMAOC is implemented:

Load Multiple and Store Multiple Atomicity and Ordering Enable.

LSMAOE	Meaning
`0b0`	For all memory accesses at EL1 or EL0, A32 and T32 Load Multiple and Store Multiple can have an interrupt taken during the sequence memory accesses, and the memory accesses are not required to be ordered.
`0b1`	The ordering and interrupt behavior of A32 and T32 Load Multiple and Store Multiple at EL1 or EL0 is as defined for Armv8.0.

This bit is permitted to be cached in a TLB.

This field resets to `1`.

Otherwise:

Reserved, RES1.

nTLSMD, bit [3]

When ARMv8.2-LSMAOC is implemented:

No Trap Load Multiple and Store Multiple to Device-nGRE/Device-nGnRE/Device-nGnRnE memory.

nTLSMD	Meaning
0b0	All memory accesses by A32 and T32 Load Multiple and Store Multiple at EL1 or EL0 that are marked at stage 1 as Device-nGRE/Device-nGnRE/Device-nGnRnE memory are trapped and generate a stage 1 Alignment fault.
0b1	All memory accesses by A32 and T32 Load Multiple and Store Multiple at EL1 or EL0 that are marked at stage 1 as Device-nGRE/Device-nGnRE/Device-nGnRnE memory are not trapped.

This bit is permitted to be cached in a TLB.

This field resets to 1.

Otherwise:

Reserved, RES1.

C, bit [2]

Cacheability control, for data accesses at EL1 and EL0:

C	Meaning
0b0	All data access to Normal memory from PL1 and PL0, and all accesses to the PL1&0 stage 1 translation tables, are Non-cacheable for all levels of data and unified cache.
0b1	All data access to Normal memory from PL1 and PL0, and all accesses to the PL1&0 stage 1 translation tables, can be cached at all levels of data and unified cache.

The PE ignores SCLTR.C for Non-secure state and data accesses to Normal memory from EL1 and EL0 are Cacheable if either:

- EL2 is using AArch32 and the value of HCR.DC is 1.
- EL2 is using AArch64 and the value of HCR_EL2.DC is 1.

This field resets to 0.

A, bit [1]

Alignment check enable. This is the enable bit for Alignment fault checking at PL1 and PL0:

A	Meaning
0b0	Alignment fault checking disabled when executing at PL1 or PL0. Instructions that load or store one or more registers, other than load/store exclusive and load-acquire/store-release, do not check that the address being accessed is aligned to the size of the data element(s) being accessed.
0b1	Alignment fault checking enabled when executing at PL1 or PL0. All instructions that load or store one or more registers have an alignment check that the address being accessed is aligned to the size of the data element(s) being accessed. If this check fails it causes an Alignment fault, which is taken as a Data Abort exception.

Load/store exclusive and load-acquire/store-release instructions have an alignment check regardless of the value of the A bit.

This field resets to 0.

M, bit [0]

MMU enable for EL1 and EL0 stage 1 address translation. Possible values of this bit are:

M	Meaning
0b0	EL1 and EL0 stage 1 address translation disabled. See the SCTLR.I field for the behavior of instruction accesses to Normal memory.
0b1	EL1 and EL0 stage 1 address translation enabled.

In the Non-secure state the PE behaves as if the value of the SCTLR.M field is 0 for all purposes other than returning the value of a direct read of the field if either:

- EL2 is using AArch32 and the value of HCR.{DC, TGE} is not {0, 0}.
- EL2 is using AArch64 and the value of HCR_EL2.{DC, TGE} is not {0, 0}.

This field resets to 0.

Accessing the SCTLR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return SCTLR_S;
        else
            return SCTLR_NS;
    else
        return SCTLR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return SCTLR_NS;
    else
        return SCTLR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return SCTLR_S;
    else
        return SCTLR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            SCTLR_S = R[t];
        else
            SCTLR_NS = R[t];
    else
        SCTLR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        SCTLR_NS = R[t];
    else
        SCTLR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            SCTLR_S = R[t];
        else
            SCTLR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SDCR, Secure Debug Control Register

The SDCR characteristics are:

Purpose

Provides EL3 configuration options for self-hosted debug, trace, and the Performance Monitors Extension.

Configuration

AArch32 System register SDCR bits [31:0] can be mapped to AArch64 System register MDCR_EL3[31:0] , but this is not architecturally mandated.

ThisSome or all RW fields of this register ishave presentdefined only whenreset AArch32values. These apply whenever the register is supportedaccessible. This atmeans anythey Exceptionapply level. Otherwise,when directthe accessesPE toresets SDCRinto areEL3 using AArch32. UNKNOWN.

Attributes

SDCR is a 32-bit register.

Field descriptions

The SDCR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0			MTPME	TDCC	RES0			SCCD	RES0	EPMAD	EDAD	TTRF	STE	SPME	RES0	SPD	RES0														

Bits [31:29]

Reserved, RES0.

MTPME, bit [28]

When ARMv8.6-MTPMU is implemented:

Multi-threaded PMU Enable. Enables use of the PMEVTYPER<n>.MT bits.

MTPME	Meaning
0b0	ARMv8.6-MTPMU is disabled. The Effective value of PMEVTYPER<n>.MT is zero.
0b1	PMEVTYPER<n>.MT bits not affected by this bit.

If ARMv8.6-MTPMU is disabled for any other PE in the system that has the same level 1 Affinity as the PE, it is IMPLEMENTATION DEFINED whether the PE behaves as if this bit is 0.

On a Cold reset, in a system where the PE resets into EL3, this field resets to 1.

Otherwise:

Reserved, RES0.

TDCC, bit [27]

When ARMv8.6-FGT is implemented:

Trap DCC. Traps use of the Debug Comms Channel in modes other than Monitor mode to Monitor mode.

TDCC	Meaning
0b0	This control does not cause any register accesses to be trapped.
0b1	Accesses to the DCC registers in modes other than Monitor mode generate a Monitor Trap exception, unless the access also generates a higher priority exception. Traps on the DCC data transfer registers are ignored when the PE is in Debug state.

The DCC registers trapped by this control are:

- DBGDTRRXext, DBGDTRTXext, DBGDSCRint, DBGDCCINT, and, when the PE is in Non-debug state, DBGDTRRXint and DBGDTRTXint.

When the PE is in Debug state, SDCR.TDCC does not trap any accesses to:

- DBGDTRRXint and DBGDTRTXint.

In a system where the PE resets into EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [26:24]

Reserved, RES0.

SCCD, bit [23]

When ARMv8.5-PMU is implemented:

Secure Cycle Counter Disable. Prohibits PMCCNTR from counting in Secure state.

SCCD	Meaning
0b0	Cycle counting by PMCCNTR is not affected by this bit.
0b1	Cycle counting by PMCCNTR is prohibited in Secure state.

This bit does not affect the CPU_CYCLES event or any other event that counts cycles.

In a system where the PE resets into EL3, this field resets to 0.

Otherwise:

Reserved, RES0.

Bit [22]

Reserved, RES0.

EPMAD, bit [21]

When ARMv8.4-Debug is implemented and PMUv3 is implemented:

External Performance Monitors Non-secure access disable. Controls Non-secure access to Performance Monitors registers by an external debugger.

EPMAD	Meaning
0b0	Non-secure access to the Performance Monitors registers from an external debugger is permitted.
0b1	Non-secure access to the Performance Monitors registers from an external debugger is not permitted.

If the Performance Monitors Extension does not support external debug interface accesses this bit is RES0.

Otherwise, if EL3 is not implemented and the Effective value of SCR.NS is 0b0, then the Effective value of this field is 0b1.

In a system where the PE resets into EL3, this field resets to 0.

When PMUv3 is implemented:

External Performance Monitors access disable. Controls access to Performance Monitors registers by an external debugger.

EPMAD	Meaning
0b0	Access to Performance Monitors registers from an external debugger is permitted.
0b1	Access to Performance Monitors registers from an external debugger is not permitted, unless overridden by the IMPLEMENTATION DEFINED authentication interface.

If the Performance Monitors Extension does not support external debug interface accesses this bit is RES0.

Otherwise, if EL3 is not implemented and the Effective value of SCR.NS is 0b0, then the Effective value of this field is 0b1.

In a system where the PE resets into EL3, this field resets to 0.

Otherwise:

Reserved, RES0.

EDAD, bit [20]

When ARMv8.4-Debug is implemented:

External debug Non-secure access disable. Controls Non-secure access to breakpoint, watchpoint, and OSLAR_EL1 registers by an external debugger.

EDAD	Meaning
0b0	Non-secure access to debug registers from an external debugger is permitted.
0b1	Non-secure access to breakpoint registers, watchpoint registers, and OSLAR_EL1 from an external debugger is not permitted.

If EL3 is not implemented and the Effective value of SCR.NS is 0b0, then the Effective value of this field is 0b1.

In a system where the PE resets into EL3, this field resets to 0.

When ARMv8.2-Debug is implemented:

External debug access disable. Controls access to breakpoint, watchpoint, and OSLAR_EL1 registers by an external debugger.

EDAD	Meaning
0b0	Access to debug registers from an external debugger is permitted.
0b1	Access to breakpoint registers, watchpoint registers and OSLAR_EL1 from an external debugger is not permitted, unless overridden by the IMPLEMENTATION DEFINED authentication interface.

If EL3 is not implemented and the Effective value of SCR.NS is 0b0, then the Effective value of this field is 0b1.

In a system where the PE resets into EL3, this field resets to 0.

Otherwise:

External debug access disable. Controls access to breakpoint, watchpoint, and optionally OSLAR_EL1 registers by an external debugger.

EDAD	Meaning
0b0	Access to debug registers from an external debugger is permitted.
0b1	Access to breakpoint registers and watchpoint registers from an external debugger is not permitted, unless overridden by the IMPLEMENTATION DEFINED authentication interface. It is IMPLEMENTATION DEFINED whether access to the OSLAR_EL1 register from an external debugger is permitted or not permitted.

If EL3 is not implemented and the Effective value of SCR.NS is 0b0, then the Effective value of this field is 0b1.

In a system where the PE resets into EL3, this field resets to 0.

TTRF, bit [19]

When ARMv8.4-Trace is implemented:

Trap Trace Filter controls. Controls whether accesses at EL2 and EL1 to the trace filter control registers are trapped to EL3.

TTRF	Meaning
0b0	Accesses to HTRFCR and TRFCR registers are not affected by this control bit.
0b1	When not in Monitor mode, accesses to HTRFCR and TRFCR registers generate a Monitor Trap exception, unless the access generates a higher priority exception.

In a system where the PE resets into EL3, this field resets to 0.

Otherwise:

Reserved, RES0.

STE, bit [18]

When ARMv8.4-Trace is implemented:

Secure Trace Enable. This bit enables tracing in Secure state and controls the level of authentication required by an external debugger to enable external tracing.

STE	Meaning
0b0	Trace is prohibited in Secure state unless overridden by the IMPLEMENTATION DEFINED authentication interface.
0b1	Trace in Secure state is not affected by this bit.

This bit also controls the level of authentication required by an external debugger to enable external tracing. See 'Register controls to enable self-hosted trace' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

If EL3 is not implemented and the Effective value of SCR.NS is `0b0`, the PE behaves as if this bit is set to `0b1`.

In a system where the PE resets into EL3, this field resets to `0`.

Otherwise:

Reserved, RES0.

SPME, bit [17]

When ARMv8.2-Debug is implemented and PMUv3 is implemented:

Secure Performance Monitors enable. This allows event counting in Secure state.

SPME	Meaning
`0b0`	Event counting prohibited in Secure state.
`0b1`	Event counting allowed in Secure state.

If EL3 is not implemented and the Effective value of SCR.NS is `0b0`, then the Effective value of this bit is `0b1`.

In a system where the PE resets into EL3, this field resets to `0`.

When PMUv3 is implemented:

Secure Performance Monitors enable. This allows event counting in Secure state.

SPME	Meaning
`0b0`	Event counting prohibited in Secure state, unless ExternalSecureNoninvasiveDebugEnabled() is TRUE.
`0b1`	Event counting allowed in Secure state.

If EL3 is not implemented and the Effective value of SCR.NS is `0b0`, then the Effective value of this bit is `0b1`.

In a system where the PE resets into EL3, this field resets to `0`.

Otherwise:

Reserved, RES0.

Bit [16]

Reserved, RES0.

SPD, bits [15:14]

AArch32 Secure self-hosted Privileged Debug. Enables or disables debug exceptions from EL3, other than Breakpoint Instruction exceptions

SPD	Meaning
`0b00`	Legacy mode. Debug exceptions from EL3 are enabled by the authentication interface.
`0b10`	Secure privileged debug disabled. Debug exceptions from EL3 are disabled.
`0b11`	Secure privileged debug enabled. Debug exceptions from EL3 are enabled.

Other values are reserved, and have the CONSTRAINED UNPREDICTABLE behavior that they must have the same behavior as `0b00`. Software must not rely on this property as the behavior of reserved values might change in a future revision of the architecture.

This field has no effect on Breakpoint Instruction exceptions. These are always enabled.

This field is ignored in Non-secure state.

If debug exceptions from EL3 are enabled, then debug exceptions from Secure EL0 are also enabled.

Otherwise, debug exceptions from Secure EL0 are enabled only if the value of SDER.SUIDEN is `0b1`.

If EL3 is not implemented and the Effective value of SCR.NS is `0b0`, then the Effective value of this field is `0b11`.

In a system where the PE resets into EL3, this field resets to `0`.

Bits [13:0]

Reserved, RES0.

Accessing the SDCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return SDCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif !ELUsingAArch32(EL2) && SCR_EL3.<NS,EEL2> == '01' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif !ELUsingAArch32(EL3) && SCR_EL3.NS == '0' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        SDCR = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SDER, Secure Debug Enable Register

The SDER characteristics are:

Purpose

Controls invasive and non-invasive debug in the Secure EL0 mode.

Configuration

AArch32 System register SDER bits [31:0] are architecturally mapped to AArch64 System register SDER32_EL3[31:0] .

This register is present only when AArch32 is supported at any Exception level, or ~~HaveEL(~~EL3 is implemented~~)~~ or the implemented Security state is Secure state. Otherwise, direct accesses to SDER are UNDEFINED.

This register is ignored by the PE when one or more of the following are true:

- The PE is in Non-secure state.
- EL1 is using AArch64.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

SDER is a 32-bit register.

Field descriptions

The SDER bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																														SUNIDEN	SUIDEN

Bits [31:2]

Reserved, RES0.

SUNIDEN, bit [1]

Secure User Non-Invasive Debug Enable.

SUNIDEN	Meaning
0b0	This bit does not affect Performance Monitors event counting at Secure EL0
0b1	If EL3 or EL1 is using AArch32, Performance Monitors event counting is allowed in Secure EL0.

On a Warm reset, this field resets to 0.

SUIDEN, bit [0]

Secure User Invasive Debug Enable.

SUIDEN	Meaning
0b0	This bit does not affect the generation of debug exceptions at Secure EL0.
0b1	If EL3 or EL1 is using AArch32, debug exceptions from Secure EL0 are enabled.

On a Warm reset, this field resets to 0.

Accessing the SDER

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif (!HaveEL(EL3) || !ELUsingAArch32(EL3)) && SCR_EL3.NS == '0' then
        return SDER;
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    return SDER;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0001	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif (!HaveEL(EL3) || !ELUsingAArch32(EL3)) && SCR_EL3.NS == '0' then
        SDER = R[t];
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    UNDEFINED;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        SDER = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR, Saved Program Status Register

The SPSR characteristics are:

Purpose

Holds the saved process state for the current mode.

Configuration

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. Otherwise, RW directfields accessesin this register reset to SPSR arearchitecturally UNKNOWN.values.

Attributes

SPSR is a 32-bit register.

Field descriptions

The SPSR bit assignments are:



N, bit [31]

Set to the value of PSTATE.N on taking an exception to the current mode, and copied to PSTATE.N on executing an exception return operation in the current mode.

Z, bit [30]

Set to the value of PSTATE.Z on taking an exception to the current mode, and copied to PSTATE.Z on executing an exception return operation in the current mode.

C, bit [29]

Set to the value of PSTATE.C on taking an exception to the current mode, and copied to PSTATE.C on executing an exception return operation in the current mode.

V, bit [28]

Set to the value of PSTATE.V on taking an exception to the current mode, and copied to PSTATE.V on executing an exception return operation in the current mode.

Q, bit [27]

Set to the value of PSTATE.Q on taking an exception to the current mode, and copied to PSTATE.Q on executing an exception return operation in the current mode.

IT[1:0], bits [26:25]

IT block state bits for the T32 IT (If-Then) instruction. See IT[7:2] for explanation of this field.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass Safe. This bit is set to the value of PSTATE.SSBS on taking an exception to the current mode, and copied to PSTATE.SSBS on executing an exception return operation in the current mode.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. This bit is set to the value of PSTATE.PAN on taking an exception to the current mode, and copied to PSTATE.PAN on executing an exception return operation in the current mode.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. This bit is set to the value of PSTATE.DIT on taking an exception to the current mode, and copied to PSTATE.DIT on executing an exception return operation in the current mode.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state bit. Shows the value of PSTATE.IL immediately before the exception was taken.

GE, bits [19:16]

Greater than or Equal flags, for parallel addition and subtraction.

IT[7:2], bits [15:10]

IT block state bits for the T32 IT (If-Then) instruction. This field must be interpreted in two parts.

- IT[7:5] holds the base condition for the IT block. The base condition is the top 3 bits of the condition code specified by the first condition field of the IT instruction.
- IT[4:0] encodes the size of the IT block, which is the number of instructions that are to be conditionally executed, by the position of the least significant 1 in this field. It also encodes the value of the least significant bit of the condition code for each instruction in the block.

The IT field is `0b00000000` when no IT block is active.

E, bit [9]

Endianness state bit. Controls the load and store endianness for data accesses:

E	Meaning
0b0	Little-endian operation
0b1	Big-endian operation.

Instruction fetches ignore this bit.

If an implementation does not provide Big-endian support, this bit is RES0. If it does not provide Little-endian support, this bit is RES1.

If an implementation provides Big-endian support but only at EL0, this bit is RES0 for an exception return to any Exception level other than EL0.

Likewise, if it provides Little-endian support only at EL0, this bit is RES1 for an exception return to any Exception level other than EL0.

When the reset value of the SCTLR.EE bit is defined by a configuration input signal, that value also applies to the CPSR.E bit on reset, and therefore applies to software execution from reset.

A, bit [8]

SError interrupt mask bit.

A	Meaning
0b0	Exception not masked.
0b1	Exception masked.

I, bit [7]

IRQ mask bit.

I	Meaning
0b0	Exception not masked.
0b1	Exception masked.

F, bit [6]

FIQ mask bit.

F	Meaning
0b0	Exception not masked.
0b1	Exception masked.

T, bit [5]

T32 Instruction set state bit. Determines the AArch32 instruction set state that the exception was taken from.

T	Meaning
0b0	Taken from A32 state.
0b1	Taken from T32 state.

M[4], bit [4]

Execution state that the exception was taken from.

M[4]	Meaning
0b1	Exception taken from AArch32.

M[3:0], bits [3:0]

AArch32 mode that an exception was taken from.

M[3:0]	Meaning	Applies when
0b0000	User.	
0b0001	FIQ.	
0b0010	IRQ.	
0b0011	Supervisor.	
0b0110	Monitor (only valid in Secure state, if EL3 is implemented and can use AArch32).	When EL3 is implemented and EL3 is capable of using AArch32
0b0111	Abort.	
0b1010	Hyp.	
0b1011	Undefined.	
0b1111	System.	

Other values are reserved.

Accessing the SPSR

SPSR can be read using the MRS instruction and written using the MSR (register) or MSR (immediate) instructions.

~~SPSR can be read using the MRS instruction and written using the MSR (register) or MSR (immediate) instructions. For more details, see MRS, MSR (register), and MSR (immediate) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_abt, Saved Program Status Register (Abort mode)

The SPSR_abt characteristics are:

Purpose

Holds the saved process state when an exception is taken to Abort mode.

Configuration

AArch32 System register SPSR_abt bits [31:0] are architecturally mapped to AArch64 System register SPSR_abt[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to SPSR_abt arearchitecturally UNKNOWN.values.

Attributes

SPSR_abt is a 32-bit register.

Field descriptions

The SPSR_abt bit assignments are:

31	30	29	28	27	26 25	24	23	22	21	20	19 18 17 16	15 14 13 12 11 10	9	8	7	6	5	4 3 2 1 0
N	Z	C	V	Q	IT[1:0]	J	SSBS	PAN	DIT	IL	GE	IT[7:2]	E	A	I	F	T	M[4:0]

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to Abort mode, and copied to PSTATE.N on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to Abort mode, and copied to PSTATE.Z on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to Abort mode, and copied to PSTATE.C on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to Abort mode, and copied to PSTATE.V on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to Abort mode, and copied to PSTATE.Q on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to Abort mode, and copied to PSTATE.IT[1:0] on executing an exception return operation in Abort mode.

On executing an exception return operation in Abort mode SPSR_abt.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. ~~Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.~~

Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to Abort mode, and copied to PSTATE.SSBS on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to Abort mode, and copied to PSTATE.PAN on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to Abort mode, and copied to PSTATE.DIT on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to Abort mode, and copied to PSTATE.IL on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to Abort mode, and copied to PSTATE.GE on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to Abort mode, and copied to PSTATE.IT[7:2] on executing an exception return operation in Abort mode.

SPSR_abt.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to Abort mode, and copied to PSTATE.E on executing an exception return operation in Abort mode.

If the implementation does not support big-endian operation, SPSR_abt.E is RES0. If the implementation does not support little-endian operation, SPSR_abt.E is RES1. On executing an exception return operation in Abort mode, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_abt.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_abt.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to Abort mode, and copied to PSTATE.A on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to Abort mode, and copied to PSTATE.I on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to Abort mode, and copied to PSTATE.F on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to Abort mode, and copied to PSTATE.T on executing an exception return operation in Abort mode.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on taking an exception to Abort mode, and copied to PSTATE.M[4:0] on executing an exception return operation in Abort mode.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10111	Abort.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If SPSR_abt.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in Abort mode is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_abt

SPSR_abt is accessible in all modes other than User mode and Abort mode.

~~SPSR_abt is accessible in all modes other than User mode and Abort mode. For more details, see MRS (banked register) and MSR (banked register) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

```
MRS{<c>}{<q>} <Rd>, SPSR_abt
```

R	M	M1
0b1	0b1	0b0100

```
MSR{<c>}{<q>} SPSR_abt, <Rn>
```

R	M	M1
0b1	0b1	0b0100

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_fiq, Saved Program Status Register (FIQ mode)

The SPSR_fiq characteristics are:

Purpose

Holds the saved process state when an exception is taken to FIQ mode.

Configuration

AArch32 System register SPSR_fiq bits [31:0] are architecturally mapped to AArch64 System register SPSR_fiq[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to SPSR_fiq arearchitecturally UNKNOWN.values.

Attributes

SPSR_fiq is a 32-bit register.

Field descriptions

The SPSR_fiq bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
N	Z	C	V	Q	IT[1:0]		J	SSBS	PAN	DIT	IL	GE				IT[7:2]						E	A	I	F	T	M[4:0]				

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to FIQ mode, and copied to PSTATE.N on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to FIQ mode, and copied to PSTATE.Z on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to FIQ mode, and copied to PSTATE.C on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to FIQ mode, and copied to PSTATE.V on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to FIQ mode, and copied to PSTATE.Q on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to FIQ mode, and copied to PSTATE.IT[1:0] on executing an exception return operation in FIQ mode.

On executing an exception return operation in FIQ mode SPSR_fiq.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. ~~Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.~~

Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to FIQ mode, and copied to PSTATE.SSBS on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to FIQ mode, and copied to PSTATE.PAN on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to FIQ mode, and copied to PSTATE.DIT on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to FIQ mode, and copied to PSTATE.IL on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to FIQ mode, and copied to PSTATE.GE on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to FIQ mode, and copied to PSTATE.IT[7:2] on executing an exception return operation in FIQ mode.

SPSR_fiq.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to FIQ mode, and copied to PSTATE.E on executing an exception return operation in FIQ mode.

If the implementation does not support big-endian operation, SPSR_fiq.E is RES0. If the implementation does not support little-endian operation, SPSR_fiq.E is RES1. On executing an exception return operation in FIQ mode, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_fiq.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_fiq.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to FIQ mode, and copied to PSTATE.A on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to FIQ mode, and copied to PSTATE.I on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to FIQ mode, and copied to PSTATE.F on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to FIQ mode, and copied to PSTATE.T on executing an exception return operation in FIQ mode.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on taking an exception to FIQ mode, and copied to PSTATE.M[4:0] on executing an exception return operation in FIQ mode.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10111	Abort.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If SPSR_fiq.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in FIQ mode is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_fiq

SPSR_fiq is accessible in all modes other than User mode and FIQ mode.

~~SPSR_fiq is accessible in all modes other than User mode and FIQ mode. For more details, see MRS (banked register) and MSR (banked register) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

```
MRS{<c>}{<q>} <Rd>, SPSR_fiq
```

R	M	M1
0b1	0b0	0b1110

```
MSR{<c>}{<q>} SPSR_fiq, <Rn>
```

R	M	M1
0b1	0b0	0b1110

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_hyp, Saved Program Status Register (Hyp mode)

The SPSR_hyp characteristics are:

Purpose

Holds the saved process state when an exception is taken to Hyp mode.

Configuration

AArch32 System register SPSR_hyp bits [31:0] are architecturally mapped to AArch64 System register SPSR_EL2[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to SPSR_hyp arearchitecturally UNKNOWN.values.

Attributes

SPSR_hyp is a 32-bit register.

Field descriptions

The SPSR_hyp bit assignments are:

31	30	29	28	27	26 25	24	23 22	21	20	19 18 17 16	15 14 13 12 11 10	9	8	7	6	5	4 3 2 1 0
N	Z	C	V	Q	IT[1:0]	J	SSBS	PAN	DIT	IL	GE	IT[7:2]		E	A	I	F	T	M[4:0]

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to Hyp mode, and copied to PSTATE.N on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to Hyp mode, and copied to PSTATE.Z on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to Hyp mode, and copied to PSTATE.C on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to Hyp mode, and copied to PSTATE.V on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to Hyp mode, and copied to PSTATE.Q on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to Hyp mode, and copied to PSTATE.IT[1:0] on executing an exception return operation in Hyp mode.

On executing an exception return operation in Hyp mode SPSR_hyp.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. ~~Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.~~

Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to Hyp mode, and copied to PSTATE.SSBS on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to Hyp mode, and copied to PSTATE.PAN on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to Hyp mode, and copied to PSTATE.DIT on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to Hyp mode, and copied to PSTATE.IL on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to Hyp mode, and copied to PSTATE.GE on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to Hyp mode, and copied to PSTATE.IT[7:2] on executing an exception return operation in Hyp mode.

SPSR_hyp.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to Hyp mode, and copied to PSTATE.E on executing an exception return operation in Hyp mode.

If the implementation does not support big-endian operation, SPSR_hyp.E is RES0. If the implementation does not support little-endian operation, SPSR_hyp.E is RES1. On executing an exception return operation in Hyp mode, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_hyp.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_hyp.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to Hyp mode, and copied to PSTATE.A on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to Hyp mode, and copied to PSTATE.I on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to Hyp mode, and copied to PSTATE.F on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to Hyp mode, and copied to PSTATE.T on executing an exception return operation in Hyp mode.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on taking an exception to Hyp mode, and copied to PSTATE.M[4:0] on executing an exception return operation in Hyp mode.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10111	Abort.
0b11010	Hyp.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If SPSR_hyp.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in Hyp mode is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_hyp

SPSR_hyp is accessible only in Monitor mode.

~~SPSR_hyp is accessible only in Monitor mode. For more details, see MRS (banked register) and MSR (banked register) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

```
MRS{<c>}{<q>} <Rd>, SPSR_hyp
```

R	M	M1
0b1	0b1	0b1110

```
MSR{<c>}{<q>} SPSR_hyp, <Rn>
```

R	M	M1
0b1	0b1	0b1110

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_irq, Saved Program Status Register (IRQ mode)

The SPSR_irq characteristics are:

Purpose

Holds the saved process state when an exception is taken to IRQ mode.

Configuration

AArch32 System register SPSR_irq bits [31:0] are architecturally mapped to AArch64 System register SPSR_irq[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to SPSR_irq arearchitecturally UNKNOWN.values.

Attributes

SPSR_irq is a 32-bit register.

Field descriptions

The SPSR_irq bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
N	Z	C	V	Q	IT[1:0]		J	SSBS	PAN	DIT	IL	GE				IT[7:2]						E	A	I	F	T	M[4:0]				

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to IRQ mode, and copied to PSTATE.N on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to IRQ mode, and copied to PSTATE.Z on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to IRQ mode, and copied to PSTATE.C on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to IRQ mode, and copied to PSTATE.V on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to IRQ mode, and copied to PSTATE.Q on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to IRQ mode, and copied to PSTATE.IT[1:0] on executing an exception return operation in IRQ mode.

On executing an exception return operation in IRQ mode SPSR_irq.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. ~~Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.~~

Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to IRQ mode, and copied to PSTATE.SSBS on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to IRQ mode, and copied to PSTATE.PAN on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to IRQ mode, and copied to PSTATE.DIT on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to IRQ mode, and copied to PSTATE.IL on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to IRQ mode, and copied to PSTATE.GE on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to IRQ mode, and copied to PSTATE.IT[7:2] on executing an exception return operation in IRQ mode.

SPSR_irq.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to IRQ mode, and copied to PSTATE.E on executing an exception return operation in IRQ mode.

If the implementation does not support big-endian operation, SPSR_irq.E is RES0. If the implementation does not support little-endian operation, SPSR_irq.E is RES1. On executing an exception return operation in IRQ mode, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_irq.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_irq.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to IRQ mode, and copied to PSTATE.A on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to IRQ mode, and copied to PSTATE.I on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to IRQ mode, and copied to PSTATE.F on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to IRQ mode, and copied to PSTATE.T on executing an exception return operation in IRQ mode.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on taking an exception to IRQ mode, and copied to PSTATE.M[4:0] on executing an exception return operation in IRQ mode.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10111	Abort.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If SPSR_irq.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in IRQ mode is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_irq

SPSR_irq is accessible in all modes other than User mode and IRQ mode.

~~SPSR_irq is accessible in all modes other than User mode and IRQ mode. For more details, see MRS (banked register) and MSR (banked register) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

```
MRS{<c>}{<q>} <Rd>, SPSR_irq
```

R	M	M1
0b1	0b1	0b0000

```
MSR{<c>}{<q>} SPSR_irq, <Rn>
```

R	M	M1
0b1	0b1	0b0000

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_mon, Saved Program Status Register (Monitor mode)

The SPSR_mon characteristics are:

Purpose

Holds the saved process state when an exception is taken to Monitor mode.

Configuration

AArch32 System register SPSR_mon bits [31:0] can be mapped to AArch64 System register SPSR_EL3[31:0] , but this is not architecturally mandated.

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to SPSR_mon arearchitecturally UNKNOWN.values.

Attributes

SPSR_mon is a 32-bit register.

Field descriptions

The SPSR_mon bit assignments are:

31	30	29	28	27	26 25	24	23	22	21	20	19 18 17 16	15 14 13 12 11 10	9	8	7	6	5	4 3 2 1 0
N	Z	C	V	Q	IT[1:0]	J	SSBS	PAN	DIT	IL	GE	IT[7:2]	E	A	I	F	T	M[4:0]

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to Monitor mode, and copied to PSTATE.N on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to Monitor mode, and copied to PSTATE.Z on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to Monitor mode, and copied to PSTATE.C on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to Monitor mode, and copied to PSTATE.V on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to Monitor mode, and copied to PSTATE.Q on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to Monitor mode, and copied to PSTATE.IT[1:0] on executing an exception return operation in Monitor mode.

On executing an exception return operation in Monitor mode SPSR_mon.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. ~~Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.~~

Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to Monitor mode, and copied to PSTATE.SSBS on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to Monitor mode, and copied to PSTATE.PAN on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to Monitor mode, and copied to PSTATE.DIT on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to Monitor mode, and copied to PSTATE.IL on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to Monitor mode, and copied to PSTATE.GE on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to Monitor mode, and copied to PSTATE.IT[7:2] on executing an exception return operation in Monitor mode.

SPSR_mon.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to Monitor mode, and copied to PSTATE.E on executing an exception return operation in Monitor mode.

If the implementation does not support big-endian operation, SPSR_mon.E is RES0. If the implementation does not support little-endian operation, SPSR_mon.E is RES1. On executing an exception return operation in Monitor mode, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_mon.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_mon.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to Monitor mode, and copied to PSTATE.A on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to Monitor mode, and copied to PSTATE.I on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to Monitor mode, and copied to PSTATE.F on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to Monitor mode, and copied to PSTATE.T on executing an exception return operation in Monitor mode.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on taking an exception to Monitor mode, and copied to PSTATE.M[4:0] on executing an exception return operation in Monitor mode.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10110	Monitor.
0b10111	Abort.
0b11010	Hyp.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If SPSR_mon.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in Monitor mode is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_mon

SPSR_mon is only accessible in EL3 modes other than Monitor mode.

~~SPSR_mon is only accessible in EL3 modes other than Monitor mode. For more details, see MRS (banked register) and MSR (banked register) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

```
MRS{<c>}{<q>} <Rd>, SPSR_mon
```

R	M	M1
0b1	0b1	0b1100

```
MSR{<c>}{<q>} SPSR_mon, <Rn>
```

R	M	M1
0b1	0b1	0b1100

13~~27~~/1209/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_svc, Saved Program Status Register (Supervisor mode)

The SPSR_svc characteristics are:

Purpose

Holds the saved process state when an exception is taken to Supervisor mode.

Configuration

AArch32 System register SPSR_svc bits [31:0] are architecturally mapped to AArch64 System register SPSR_EL1[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to SPSR_svc arearchitecturally UNKNOWN.values.

Attributes

SPSR_svc is a 32-bit register.

Field descriptions

The SPSR_svc bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
N	Z	C	V	Q	IT[1:0]		J	SSBS	PAN	DIT	IL	GE				IT[7:2]						E	A	I	F	T	M[4:0]				

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to Supervisor mode, and copied to PSTATE.N on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to Supervisor mode, and copied to PSTATE.Z on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to Supervisor mode, and copied to PSTATE.C on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to Supervisor mode, and copied to PSTATE.V on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to Supervisor mode, and copied to PSTATE.Q on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to Supervisor mode, and copied to PSTATE.IT[1:0] on executing an exception return operation in Supervisor mode.

On executing an exception return operation in Supervisor mode SPSR_svc.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. ~~Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.~~

Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to Supervisor mode, and copied to PSTATE.SSBS on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to Supervisor mode, and copied to PSTATE.PAN on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to Supervisor mode, and copied to PSTATE.DIT on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to Supervisor mode, and copied to PSTATE.IL on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to Supervisor mode, and copied to PSTATE.GE on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to Supervisor mode, and copied to PSTATE.IT[7:2] on executing an exception return operation in Supervisor mode.

SPSR_svc.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to Supervisor mode, and copied to PSTATE.E on executing an exception return operation in Supervisor mode.

If the implementation does not support big-endian operation, SPSR_svc.E is RES0. If the implementation does not support little-endian operation, SPSR_svc.E is RES1. On executing an exception return operation in Supervisor mode, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_svc.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_svc.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to Supervisor mode, and copied to PSTATE.A on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to Supervisor mode, and copied to PSTATE.I on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to Supervisor mode, and copied to PSTATE.F on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to Supervisor mode, and copied to PSTATE.T on executing an exception return operation in Supervisor mode.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on taking an exception to Supervisor mode, and copied to PSTATE.M[4:0] on executing an exception return operation in Supervisor mode.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10111	Abort.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If SPSR_svc.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in Supervisor mode is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_svc

SPSR_svc is accessible in all modes other than User mode and Supervisor mode.

~~SPSR_svc is accessible in all modes other than User mode and Supervisor mode. For more details, see MRS (banked register) and MSR (banked register) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

```
MRS{<c>}{<q>} <Rd>, SPSR_svc
```

R	M	M1
0b1	0b1	0b0010

```
MSR{<c>}{<q>} SPSR_svc, <Rn>
```

R	M	M1
0b1	0b1	0b0010

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

SPSR_und, Saved Program Status Register (Undefined mode)

The SPSR_und characteristics are:

Purpose

Holds the saved process state when an exception is taken to Undefined mode.

Configuration

AArch32 System register SPSR_und bits [31:0] are architecturally mapped to AArch64 System register SPSR_und[31:0] .

ThisRW registerfields isin presentthis only whenregister AArch32reset is supported at any Exception level. Otherwise, direct accesses to SPSR_und arearchitecturally UNKNOWN.values.

Attributes

SPSR_und is a 32-bit register.

Field descriptions

The SPSR_und bit assignments are:

31	30	29	28	27	26 25	24	23	22	21	20	19 18 17 16	15 14 13 12 11 10	9	8	7	6	5	4 3 2 1 0
N	Z	C	V	Q	IT[1:0]	J	SSBS	PAN	DIT	IL	GE	IT[7:2]	E	A	I	F	T	M[4:0]

N, bit [31]

Negative Condition flag. Set to the value of PSTATE.N on taking an exception to Undefined mode, and copied to PSTATE.N on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

Z, bit [30]

Zero Condition flag. Set to the value of PSTATE.Z on taking an exception to Undefined mode, and copied to PSTATE.Z on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

C, bit [29]

Carry Condition flag. Set to the value of PSTATE.C on taking an exception to Undefined mode, and copied to PSTATE.C on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

V, bit [28]

Overflow Condition flag. Set to the value of PSTATE.V on taking an exception to Undefined mode, and copied to PSTATE.V on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

Q, bit [27]

Overflow or saturation flag. Set to the value of PSTATE.Q on taking an exception to Undefined mode, and copied to PSTATE.Q on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

IT[1:0], bits [26:25]

If-Then. Set to the value of PSTATE.IT[1:0] on taking an exception to Undefined mode, and copied to PSTATE.IT[1:0] on executing an exception return operation in Undefined mode.

On executing an exception return operation in Undefined mode SPSR_und.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

J, bit [24]

RES0.

In previous versions of the architecture, the {J, T} bits determined the AArch32 Instruction set state. ~~Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.~~

Armv8 does not support either Jazelle state or T32EE state, and the T bit determines the Instruction set state.

SSBS, bit [23]

When ARMv8.0-SSBS is implemented:

Speculative Store Bypass. Set to the value of PSTATE.SSBS on taking an exception to Undefined mode, and copied to PSTATE.SSBS on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

PAN, bit [22]

When ARMv8.1-PAN is implemented:

Privileged Access Never. Set to the value of PSTATE.PAN on taking an exception to Undefined mode, and copied to PSTATE.PAN on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DIT, bit [21]

When ARMv8.4-DIT is implemented:

Data Independent Timing. Set to the value of PSTATE.DIT on taking an exception to Undefined mode, and copied to PSTATE.DIT on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IL, bit [20]

Illegal Execution state. Set to the value of PSTATE.IL on taking an exception to Undefined mode, and copied to PSTATE.IL on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

GE, bits [19:16]

Greater than or Equal flags. Set to the value of PSTATE.GE on taking an exception to Undefined mode, and copied to PSTATE.GE on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

IT[7:2], bits [15:10]

If-Then. Set to the value of PSTATE.IT[7:2] on taking an exception to Undefined mode, and copied to PSTATE.IT[7:2] on executing an exception return operation in Undefined mode.

SPSR_und.IT must contain a value that is valid for the instruction being returned to.

This field resets to an architecturally UNKNOWN value.

E, bit [9]

Endianness. Set to the value of PSTATE.E on taking an exception to Undefined mode, and copied to PSTATE.E on executing an exception return operation in Undefined mode.

If the implementation does not support big-endian operation, SPSR_und.E is RES0. If the implementation does not support little-endian operation, SPSR_und.E is RES1. On executing an exception return operation in Undefined mode, if the implementation does not support big-endian operation at the Exception level being returned to, SPSR_und.E is RES0, and if the implementation does not support little-endian operation at the Exception level being returned to, SPSR_und.E is RES1.

This field resets to an architecturally UNKNOWN value.

A, bit [8]

SError interrupt mask. Set to the value of PSTATE.A on taking an exception to Undefined mode, and copied to PSTATE.A on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

I, bit [7]

IRQ interrupt mask. Set to the value of PSTATE.I on taking an exception to Undefined mode, and copied to PSTATE.I on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

F, bit [6]

FIQ interrupt mask. Set to the value of PSTATE.F on taking an exception to Undefined mode, and copied to PSTATE.F on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

T, bit [5]

T32 Instruction set state. Set to the value of PSTATE.T on taking an exception to Undefined mode, and copied to PSTATE.T on executing an exception return operation in Undefined mode.

This field resets to an architecturally UNKNOWN value.

M[4:0], bits [4:0]

Mode. Set to the value of PSTATE.M[4:0] on taking an exception to Undefined mode, and copied to PSTATE.M[4:0] on executing an exception return operation in Undefined mode.

M[4:0]	Meaning
0b10000	User.
0b10001	FIQ.
0b10010	IRQ.
0b10011	Supervisor.
0b10111	Abort.
0b11011	Undefined.
0b11111	System.

Other values are reserved. If SPSR_und.M[4:0] has a Reserved value, or a value for an unimplemented Exception level, executing an exception return operation in Undefined mode is an illegal return event, as described in 'Illegal return events from AArch32 state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Accessing the SPSR_und

SPSR_und is accessible in all modes other than User mode and Undefined mode.

~~SPSR_und is accessible in all modes other than User mode and Undefined mode. For more details, see MRS (banked register) and MSR (banked register) in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Accesses to this register use the following encodings:

```
MRS{<c>}{<q>} <Rd>, SPSR_und
```

R	M	M1
0b1	0b1	0b0110

```
MSR{<c>}{<q>} SPSR_und, <Rn>
```

R	M	M1
0b1	0b1	0b0110

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TCMTR, TCM Type Register

The TCMTR characteristics are:

Purpose

Provides information about the implementation of the TCM.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TCMTR are UNKNOWN.

If EL1 or above can use AArch32 then this register must be implemented.

Attributes

TCMTR is a 32-bit register.

Field descriptions

The TCMTR bit assignments are:



IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

Accessing the TCMTR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return TCMTR;
elsif PSTATE.EL == EL2 then
    return TCMTR;
elsif PSTATE.EL == EL3 then
    return TCMTR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIALL, TLB Invalidate All

The TLBIALL characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that are from any level of the translation table walk. The entries that are invalidated are as follows:

- If executed at EL1, all entries that:
  - Would be required for the EL1&0 translation regime.
  - Match the current VMID, if EL2 is implemented and enabled in the current Security state.
- If executed in Secure state when EL3 is using AArch32, all entries that would be required for the Secure PL1&0 translation regime.
- If executed at EL2, and if EL2 is enabled in the current Security state, the stage 1 or stage 2 translation table entries that would be required for the PL1&0 translation regime and matches the current VMID.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIALL are UNKNOWN.

Attributes

TLBIALL is a 32-bit System instruction.

Field descriptions

TLBIALL ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBIALL instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0111	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.FB == '1' then
        TLBIALLIS();
    else
        TLBIALL();
elsif PSTATE.EL == EL2 then
    TLBIALL();
elsif PSTATE.EL == EL3 then
    TLBIALL();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIALLH, TLB Invalidate All, Hyp mode

The TLBIALLH characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that are from any level of the translation table walk that would be required for the Non-secure EL2 translation regime.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIALLH are UNKNOWN.

Attributes

TLBIALLH is a 32-bit System instruction.

Field descriptions

TLBIALLH ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBIALLH instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1000	0b0111	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIALLH();
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    else
        TLBIALLH();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIALLHIS, TLB Invalidate All, Hyp mode, Inner Shareable

The TLBIALLHIS characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that are from any level of the translation table walk that would be required for the Non-secure EL2 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIALLHIS are UNKNOWN.

Attributes

TLBIALLHIS is a 32-bit System instruction.

Field descriptions

TLBIALLHIS ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBIALLHIS instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1000	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIALLHIS();
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    else
        TLBIALLHIS();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIALLIS, TLB Invalidate All, Inner Shareable

The TLBIALLIS characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that are from any level of the translation table walk. The entries that are invalidated are as follows:

- If executed at EL1, all entries that:
  - Would be required for the EL1&0 translation regime.
  - Match the current VMID, if EL2 is implemented and enabled in the current Security state.
- If executed in Secure state when EL3 is using AArch32, all entries that would be required for the Secure PL1&0 translation regime.
- If executed at EL2 and if EL2 is enabled in the current Security state, the stage 1 or stage 2 translation table entries that would be required for the PL1&0 translation regime and matches the current VMID.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIALLIS are UNKNOWN.

Attributes

TLBIALLIS is a 32-bit System instruction.

Field descriptions

TLBIALLIS ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBIALLIS instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0011	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TTLBIS == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        TLBIALLIS();
elsif PSTATE.EL == EL2 then
    TLBIALLIS();
elsif PSTATE.EL == EL3 then
    TLBIALLIS();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIALLNSNH, TLB Invalidate All, Non-Secure Non-Hyp

The TLBIALLNSNH characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that are from any level of the translation table walk that would be required for stage 1 or stage 2 of the Non-secure PL1&0 translation regime, regardless of the associated VMID.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIALLNSNH are UNKNOWN.

Attributes

TLBIALLNSNH is a 32-bit System instruction.

Field descriptions

TLBIALLNSNH ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBIALLNSNH instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1000	0b0111	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIALLNSNH();
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    else
        TLBIALLNSNH();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIALLNSNHIS, TLB Invalidate All, Non-Secure Non-Hyp, Inner Shareable

The TLBIALLNSNHIS characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that are from any level of the translation table walk that would be required for stage 1 or stage 2 of the Non-secure PL1&0 translation regime, regardless of the associated VMID.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIALLNSNHIS are UNKNOWN.

Attributes

TLBIALLNSNHIS is a 32-bit System instruction.

Field descriptions

TLBIALLNSNHIS ignores the value in the register specified by the instruction encoding. Software does not have to write a value to the register before issuing this instruction.

Executing the TLBIALLNSNHIS instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1000	0b0011	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIALLNSNHIS();
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    else
        TLBIALLNSNHIS();
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIASID, TLB Invalidate by ASID match

The TLBIASID characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used for the specified ASID, and either:
  - Is from a level of lookup above the final level.
  - Is a non-global entry from the final level of lookup.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIASID are UNKNOWN.

Attributes

TLBIASID is a 32-bit System instruction.

Field descriptions

The TLBIASID input value bit assignments are:



Bits [31:8]

Reserved, RES0.

ASID, bits [7:0]

ASID value to match. Any TLB entries for non-global pages that match the ASID values will be affected by this System instruction.

Executing the TLBIASID instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0111	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.FB == '1' then
        TLBIASIDIS(R[t]);
    else
        TLBIASID(R[t]);
elsif PSTATE.EL == EL2 then
    TLBIASID(R[t]);
elsif PSTATE.EL == EL3 then
    TLBIASID(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIASIDIS, TLB Invalidate by ASID match, Inner Shareable

The TLBIASIDIS characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used for the specified ASID, and either:
  - Is from a level of lookup above the final level.
  - Is a non-global entry from the final level of lookup.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIASIDIS are UNKNOWN.

Attributes

TLBIASIDIS is a 32-bit System instruction.

Field descriptions

The TLBIASIDIS input value bit assignments are:



Bits [31:8]

Reserved, RES0.

ASID, bits [7:0]

ASID value to match. Any TLB entries for non-global pages that match the ASID values will be affected by this System instruction.

Executing the TLBIASIDIS instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0011	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TTLBIS == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        TLBIASIDIS(R[t]);
elsif PSTATE.EL == EL2 then
    TLBIASIDIS(R[t]);
elsif PSTATE.EL == EL3 then
    TLBIASIDIS(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIIPAS2, TLB Invalidate by Intermediate Physical Address, Stage 2

The TLBIIPAS2 characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 2 only translation table entry, from any level of the translation table walk.
- SCR.NS is 1.
- The entry would be used for the specified IPA.
- The entry would be used with the current VMID.
- The entry would be required for the PL1&0 translation regime.

The invalidation is not required to apply to caching structures that combine stage 1 and stage 2 translation table entries.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIIPAS2 are UNKNOWN.

Note

This System instruction is not implemented in architecture versions before Armv8.

Attributes

TLBIIPAS2 is a 32-bit System instruction.

Field descriptions

The TLBIIPAS2 input value bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0				IPA[39:12]																											

Bits [31:28]

Reserved, RES0.

IPA[39:12], bits [27:0]

Bits[39:12] of the intermediate physical address to match.

Executing the TLBIIPAS2 instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1000	0b0100	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIIPAS2(R[t]);
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    elsif SCR.NS == '0' then
        //no operation
    else
        TLBIIPAS2(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIIPAS2IS, TLB Invalidate by Intermediate Physical Address, Stage 2, Inner Shareable

The TLBIIPAS2IS characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 2 only translation table entry, from any level of the translation table walk.
- SCR.NS is 1.
- The entry would be used for the specified IPA.
- The entry would be used with the current VMID.
- The entry would be required for the PL1&0 translation regime.

The invalidation is not required to apply to caching structures that combine stage 1 and stage 2 translation table entries.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIIPAS2IS are UNKNOWN.

Note

This System instruction is not implemented in architecture versions before Armv8.

Attributes

TLBIIPAS2IS is a 32-bit System instruction.

Field descriptions

The TLBIIPAS2IS input value bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0				IPA[39:12]																											

Bits [31:28]

Reserved, RES0.

IPA[39:12], bits [27:0]

Bits[39:12] of the intermediate physical address to match.

Executing the TLBIIPAS2IS instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1000	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIIPAS2(R[t]);
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    elsif SCR.NS == '0' then
        //no operation
    else
        TLBIIPAS2(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIIPAS2L, TLB Invalidate by Intermediate Physical Address, Stage 2, Last level

The TLBIIPAS2L characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 2 only translation table entry, from the final level of the translation table walk.
- SCR.NS is 1.
- The entry would be used for the specified IPA.
- The entry would be used with the current VMID.
- The entry would be required for the PL1&0 translation regime.

The invalidation is not required to apply to caching structures that combine stage 1 and stage 2 translation table entries.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIIPAS2L are UNKNOWN.

Note

This System instruction is not implemented in architecture versions before Armv8.

Attributes

TLBIIPAS2L is a 32-bit System instruction.

Field descriptions

The TLBIIPAS2L input value bit assignments are:



Bits [31:28]

Reserved, RES0.

IPA[39:12], bits [27:0]

Bits[39:12] of the intermediate physical address to match.

Executing the TLBIIPAS2L instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1000	0b0100	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIIPAS2(R[t]);
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    elsif SCR.NS == '0' then
        //no operation
    else
        TLBIIPAS2(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIIPAS2LIS, TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, Inner Shareable

The TLBIIPAS2LIS characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 2 only translation table entry, from the final level of the translation table walk.
- SCR.NS is 1.
- The entry would be used for the specified IPA.
- The entry would be used with the current VMID.
- The entry would be required for the PL1&0 translation regime.

The invalidation is not required to apply to caching structures that combine stage 1 and stage 2 translation table entries.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIIPAS2LIS are UNKNOWN.

Note

This System instruction is not implemented in architecture versions before Armv8.

Attributes

TLBIIPAS2LIS is a 32-bit System instruction.

Field descriptions

The TLBIIPAS2LIS input value bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0				IPA[39:12]																											

Bits [31:28]

Reserved, RES0.

IPA[39:12], bits [27:0]

Bits[39:12] of the intermediate physical address to match.

Executing the TLBIIPAS2LIS instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1000	0b0000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIIPAS2IS(R[t]);
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    elsif SCR.NS == '0' then
        //no operation
    else
        TLBIIPAS2IS(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVA, TLB Invalidate by VA

The TLBIMVA characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified address, and one of the following applies:
  - The entry is from a level of lookup above the final level and matches the specified ASID.
  - The entry is a global entry from the final level of lookup.
  - The entry is a non-global entry from the final level of lookup that matches the specified ASID.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVA are UNKNOWN.

Attributes

TLBIMVA is a 32-bit System instruction.

Field descriptions

The TLBIMVA input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any TLB entries that match the ASID value and VA value will be affected by this operation.

Bits [11:8]

Reserved, RES0.

ASID, bits [7:0]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

Executing the TLBIMVA instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0111	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.FB == '1' then
        TLBIMVAIS(R[t]);
    else
        TLBIMVA(R[t]);
elsif PSTATE.EL == EL2 then
    TLBIMVA(R[t]);
elsif PSTATE.EL == EL3 then
    TLBIMVA(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVAA, TLB Invalidate by VA, All ASID

The TLBIMVAA characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- The entry would be used to translate the specified address.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVAA are UNKNOWN.

Attributes

TLBIMVAA is a 32-bit System instruction.

Field descriptions

The TLBIMVAA input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any unlocked TLB entries that match the VA will be affected by this System instruction, regardless of the ASID.

Bits [11:0]

Reserved, RES0.

Executing the TLBIMVAA instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2

0b1111	0b000	0b1000	0b0111	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.FB == '1' then
        TLBIMVAAIS(R[t]);
    else
        TLBIMVAA(R[t]);
elsif PSTATE.EL == EL2 then
    TLBIMVAA(R[t]);
elsif PSTATE.EL == EL3 then
    TLBIMVAA(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVAAIS, TLB Invalidate by VA, All ASID, Inner Shareable

The TLBIMVAAIS characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry, from any level of the translation table walk.
- The entry would be used to translate the specified address.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVAAIS are UNKNOWN.

Attributes

TLBIMVAAIS is a 32-bit System instruction.

Field descriptions

The TLBIMVAAIS input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any unlocked TLB entries that match the VA will be affected by this System instruction, regardless of the ASID.

Bits [11:0]

Reserved, RES0.

Executing the TLBIMVAAIS instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0011	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TTLBIS == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        TLBIMVAAIS(R[t]);
elsif PSTATE.EL == EL2 then
    TLBIMVAAIS(R[t]);
elsif PSTATE.EL == EL3 then
    TLBIMVAAIS(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVAAL, TLB Invalidate by VA, All ASID, Last level

The TLBIMVAAL characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry, from the final level of the translation table walk.
- The entry would be used to translate the specified address.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVAAL are UNKNOWN.

Note

This System instruction is not implemented in architecture versions before Armv8.

Attributes

TLBIMVAAL is a 32-bit System instruction.

Field descriptions

The TLBIMVAAL input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any unlocked TLB entries that match the VA will be affected by this System instruction, regardless of the ASID.

Bits [11:0]

Reserved, RES0.

Executing the TLBIMVAAL instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0111	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.FB == '1' then
        TLBIMVAALIS(R[t]);
    else
        TLBIMVAAL(R[t]);
elsif PSTATE.EL == EL2 then
    TLBIMVAAL(R[t]);
elsif PSTATE.EL == EL3 then
    TLBIMVAAL(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVAALIS, TLB Invalidate by VA, All ASID, Last level, Inner Shareable

The TLBIMVAALIS characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry, from the final level of the translation table walk.
- The entry would be used to translate the specified address.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVAALIS are UNKNOWN.

Note

This System instruction is not implemented in architecture versions before Armv8.

Attributes

TLBIMVAALIS is a 32-bit System instruction.

Field descriptions

The TLBIMVAALIS input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any unlocked TLB entries that match the VA will be affected by this System instruction, regardless of the ASID.

Bits [11:0]

Reserved, RES0.

Executing the TLBIMVAALIS instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0011	0b111

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TTLBIS == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        TLBIMVAALIS(R[t]);
elsif PSTATE.EL == EL2 then
    TLBIMVAALIS(R[t]);
elsif PSTATE.EL == EL3 then
    TLBIMVAALIS(R[t]);
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVAH, TLB Invalidate by VA, Hyp mode

The TLBIMVAH characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that are from any level of the translation table walk that would be required for the Non-secure EL2 translation regime and used to translate the specified address.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVAH are UNKNOWN.

Attributes

TLBIMVAH is a 32-bit System instruction.

Field descriptions

The TLBIMVAH input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Bits [11:0]

Reserved, RES0.

Executing the TLBIMVAH instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1000	0b0111	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIMVAH(R[t]);
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    else
        TLBIMVAH(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVAHIS, TLB Invalidate by VA, Hyp mode, Inner Shareable

The TLBIMVAHIS characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that are from any level of the translation table walk that would be required for the Non-secure EL2 translation regime and used to translate the specified address.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVAHIS are UNKNOWN.

Attributes

TLBIMVAHIS is a 32-bit System instruction.

Field descriptions

The TLBIMVAHIS input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Bits [11:0]

Reserved, RES0.

Executing the TLBIMVAHIS instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2

0b1111	0b100	0b1000	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIMVAHIS(R[t]);
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    else
        TLBIMVAHIS(R[t]);
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVAIS, TLB Invalidate by VA, Inner Shareable

The TLBIMVAIS characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified address, and one of the following applies:
  - The entry is from a level of lookup above the final level and matches the specified ASID.
  - The entry is a global entry from the final level of lookup.
  - The entry is a non-global entry from the final level of lookup that matches the specified ASID.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVAIS are UNKNOWN.

Attributes

TLBIMVAIS is a 32-bit System instruction.

Field descriptions

The TLBIMVAIS input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Bits [11:8]

Reserved, RES0.

ASID, bits [7:0]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

Executing the TLBIMVAIS instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0011	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TTLBIS == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        TLBIMVAIS(R[t]);
elsif PSTATE.EL == EL2 then
    TLBIMVAIS(R[t]);
elsif PSTATE.EL == EL3 then
    TLBIMVAIS(R[t]);
```

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVAL, TLB Invalidate by VA, Last level

The TLBIMVAL characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified address, and one of the following applies:
  - The entry is a global entry from the final level of lookup.
  - The entry is a non-global entry from the final level of lookup that matches the specified ASID.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVAL are UNKNOWN.

This System instruction is not implemented in architecture versions before Armv8.

Attributes

TLBIMVAL is a 32-bit System instruction.

Field descriptions

The TLBIMVAL input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Bits [11:8]

Reserved, RES0.

ASID, bits [7:0]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

Executing the TLBIMVAL instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0111	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.FB == '1' then
        TLBIMVALIS(R[t]);
    else
        TLBIMVAL(R[t]);
elsif PSTATE.EL == EL2 then
    TLBIMVAL(R[t]);
elsif PSTATE.EL == EL3 then
    TLBIMVAL(R[t]);
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVALH, TLB Invalidate by VA, Last level, Hyp mode

The TLBIMVALH characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that are from the final level of the translation table walk that would be required for the Non-secure EL2 translation regime and used to translate the specified address.

The invalidation only applies to the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVALH are UNKNOWN.

This System instruction is not implemented in architecture versions before Armv8.

Attributes

TLBIMVALH is a 32-bit System instruction.

Field descriptions

The TLBIMVALH input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Bits [11:0]

Reserved, RES0.

Executing the TLBIMVALH instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1000	0b0111	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIMVALH(R[t]);
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    else
        TLBIMVALH(R[t]);
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVALHIS, TLB Invalidate by VA, Last level, Hyp mode, Inner Shareable

The TLBIMVALHIS characteristics are:

Purpose

If EL2 is implemented, invalidate all cached copies of translation table entries from TLBs that are from the final level of the translation table walk that would be required for the Non-secure EL2 translation regime and used to translate the specified address.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVALHIS are UNKNOWN.

This System instruction is not implemented in architecture versions before Armv8.

Attributes

TLBIMVALHIS is a 32-bit System instruction.

Field descriptions

The TLBIMVALHIS input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Bits [11:0]

Reserved, RES0.

Executing the TLBIMVALHIS instruction

If this instruction is executed in a Secure privileged mode other than Monitor mode, then the behavior is CONSTRAINED UNPREDICTABLE, and one of the following behaviors must occur:

- The instruction is UNDEFINED.
- The instruction is treated as a NOP.
- The instruction executes as if it had been executed in Monitor mode.

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b1000	0b0011	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    TLBIMVALHIS(R[t]);
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        UNDEFINED;
    else
        TLBIMVALHIS(R[t]);
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBIMVALIS, TLB Invalidate by VA, Last level, Inner Shareable

The TLBIMVALIS characteristics are:

Purpose

Invalidate all cached copies of translation table entries from TLBs that meet the following requirements:

- The entry is a stage 1 translation table entry.
- The entry would be used to translate the specified address, and one of the following applies:
  - The entry is a global entry from the final level of lookup.
  - The entry is a non-global entry from the final level of lookup that matches the specified ASID.
- If EL2 is implemented and enabled in the current Security state, the entry would be used with the current VMID.

From the entries that match these requirements, the entries that are invalidated are required for the following translation regime:

- If executed at Secure EL1 when EL3 is using AArch64, the Secure EL1&0 translation regime.
- If executed in Secure state when EL3 is using AArch32, the Secure PL1&0 translation regime.
- If executed in Non-secure state, the Non-secure PL1&0 translation regime.

The invalidation applies to all PEs in the same Inner Shareable shareability domain as the PE that executes this System instruction.

Configuration

This instruction is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBIMVALIS are UNKNOWN.

This System instruction is not implemented in architecture versions before Armv8.

Attributes

TLBIMVALIS is a 32-bit System instruction.

Field descriptions

The TLBIMVALIS input value bit assignments are:



VA, bits [31:12]

Virtual address to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Bits [11:8]

Reserved, RES0.

ASID, bits [7:0]

ASID value to match. Any TLB entries that match the ASID value and VA value will be affected by this System instruction.

Global TLB entries that match the VA value will be affected by this System instruction, regardless of the value of the ASID field.

Executing the TLBIMVALIS instruction

Accesses to this instruction use the following encodings:

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1000	0b0011	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T8 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T8 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLB == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TTLBIS == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR.TTLB == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR2.TTLBIS == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        TLBIMVAL(R[t]);
elsif PSTATE.EL == EL2 then
    TLBIMVAL(R[t]);
elsif PSTATE.EL == EL3 then
    TLBIMVAL(R[t]);
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TLBTR, TLB Type Register

The TLBTR characteristics are:

Purpose

Provides information about the TLB implementation. The register must define whether the implementation provides separate instruction and data TLBs, or a unified TLB. Normally, the IMPLEMENTATION DEFINED information in this register includes the number of lockable entries in the TLB.

Configuration

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TLBTR are UNKNOWN.

Attributes

TLBTR is a 32-bit register.

Field descriptions

The TLBTR bit assignments are:



IMPLEMENTATION DEFINED, bits [31:1]

IMPLEMENTATION DEFINED.

nU, bit [0]

Not Unified TLB. Indicates whether the implementation has a unified TLB:

nU	Meaning
0b0	Unified TLB.
0b1	Separate Instruction and Data TLBs.

Accessing the TLBTR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TID1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TID1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        return TLBTR;
elsif PSTATE.EL == EL2 then
    return TLBTR;
elsif PSTATE.EL == EL3 then
    return TLBTR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TPIDRPRW, PL1 Software Thread ID Register

The TPIDRPRW characteristics are:

Purpose

Provides a location where software executing at EL1 or higher can store thread identifying information that is not visible to software executing at EL0, for OS management purposes.

The PE makes no use of this register.

Configuration

AArch32 System register TPIDRPRW bits [31:0] are architecturally mapped to AArch64 System register TPIDR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TPIDRPRW are UNKNOWN.

Note

The PE never updates this register.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

TPIDRPRW is a 32-bit register.

Field descriptions

The TPIDRPRW bit assignments are:



Bits [31:0]

Thread ID. Thread identifying information stored by software running at this Exception level.

This field resets to an architecturally UNKNOWN value.

Accessing the TPIDRPRW

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0000	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return TPIDRPRW_S;
        else
            return TPIDRPRW_NS;
    else
        return TPIDRPRW;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return TPIDRPRW_NS;
    else
        return TPIDRPRW;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return TPIDRPRW_S;
    else
        return TPIDRPRW_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0000	0b100

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            TPIDRPRW_S = R[t];
        else
            TPIDRPRW_NS = R[t];
    else
        TPIDRPRW = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        TPIDRPRW_NS = R[t];
    else
        TPIDRPRW = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        TPIDRPRW_S = R[t];
    else
        TPIDRPRW_NS = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TPIDRURO, PL0 Read-Only Software Thread ID Register

The TPIDRURO characteristics are:

Purpose

Provides a location where software executing at EL1 or higher can store thread identifying information that is visible to software executing at EL0, for OS management purposes.

The PE makes no use of this register.

Configuration

AArch32 System register TPIDRURO bits [31:0] are architecturally mapped to AArch64 System register TPIDRRO_EL0[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TPIDRURO are UNKNOWN.

Note

The PE never updates this register.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

TPIDRURO is a 32-bit register.

Field descriptions

The TPIDRURO bit assignments are:



Bits [31:0]

Thread ID. Thread identifying information stored by software running at this Exception level.

This field resets to an architecturally UNKNOWN value.

Accessing the TPIDRURO

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0000	0b011

```
if PSTATE.EL == EL0 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T13 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HFGRTR_EL2.TPIDRRO_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        return TPIDRURO;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return TPIDRURO_S;
        else
            return TPIDRURO_NS;
    else
        return TPIDRURO;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return TPIDRURO_NS;
    else
        return TPIDRURO;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return TPIDRURO_S;
    else
        return TPIDRURO_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            TPIDRURO_S = R[t];
        else
            TPIDRURO_NS = R[t];
    else
        TPIDRURO = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        TPIDRURO_NS = R[t];
    else
        TPIDRURO = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        TPIDRURO_S = R[t];
    else
        TPIDRURO_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TPIDRURW, PL0 Read/Write Software Thread ID Register

The TPIDRURW characteristics are:

Purpose

Provides a location where software executing at EL0 can store thread identifying information, for OS management purposes.

The PE makes no use of this register.

Configuration

AArch32 System register TPIDRURW bits [31:0] are architecturally mapped to AArch64 System register TPIDR_EL0[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TPIDRURW are UNKNOWN.

Note

The PE never updates this register.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

TPIDRURW is a 32-bit register.

Field descriptions

The TPIDRURW bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Thread ID																															

Bits [31:0]

Thread ID. Thread identifying information stored by software running at this Exception level.

This field resets to an architecturally UNKNOWN value.

Accessing the TPIDRURW

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0000	0b010

```
if PSTATE.EL == EL0 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T13 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HFGRTR_EL2.TPIDR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        return TPIDRURW;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return TPIDRURW_S;
        else
            return TPIDRURW_NS;
    else
        return TPIDRURW;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return TPIDRURW_NS;
    else
        return TPIDRURW;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return TPIDRURW_S;
    else
        return TPIDRURW_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1101	0b0000	0b010

```
if PSTATE.EL == EL0 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.<E2H,TGE> != '11' && HSTR_EL2.T13 == '1'
then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL1) && HCR_EL2.<E2H,TGE> != '11' && (!HaveEL(EL3) ||
SCR_EL3.FGTEn == '1') && HFGWTR_EL2.TPIDR_EL0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    else
        TPIDRURW = R[t];
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T13 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T13 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            TPIDRURW_S = R[t];
        else
            TPIDRURW_NS = R[t];
    else
        TPIDRURW = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        TPIDRURW_NS = R[t];
    else
        TPIDRURW = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        TPIDRURW_S = R[t];
    else
        TPIDRURW_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TRFCR, Trace Filter Control Register

The TRFCR characteristics are:

Purpose

Provides EL1 controls for Trace.

Configuration

AArch32 System register TRFCR bits [31:0] are architecturally mapped to AArch64 System register TRFCR_EL1[31:0] .

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and ARMv8.4-Trace is implemented. Otherwise, direct accesses to TRFCR are UNDEFINED.

Attributes

TRFCR is a 32-bit register.

Field descriptions

The TRFCR bit assignments are:



Bits [31:7]

Reserved, RES0.

TS, bits [6:5]

Timestamp Control. Controls which timebase is used for trace timestamps.

TS	Meaning	Applies when
0b01	Virtual timestamp. The traced timestamp is the physical counter value, minus the value of CNTVOFF.	
0b10	Guest Physical timestamp. The traced timestamp is the physical counter value, minus the value of CNTPOFF_EL2.	When ARMv8.6-ECV is implemented
0b11	Physical timestamp. The traced timestamp is the physical counter value.	

All other values are reserved.

This field is ignored if any of the following are true:

- SelfHostedTraceEnabled() == FALSE.
- HTRFCR.TS is not 0b00.

IfWhen EL2 is implemented and enabled in the current Security state, the physical counter uses a fixed physical offset of zero if either of the following are true: ARMv8.6-ECV is implemented, the physical counter uses a fixed physical offset of zero if any of the following are true:

- When EL2 is implemented and enabled in the current Security state and is using AArch32.
- CNTHCTL_EL2.ECV is 0.
- SCR_EL3.ECVEn is 0.
- HCR_EL2.{E2H, TGE} is {1, 1}.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Bits [4:2]

Reserved, RES0.

E1TRE, bit [1]

EL1 Trace Enable.

E1TRE	Meaning
0b0	Tracing is prohibited in PL1 modes.
0b1	Tracing is allowed in PL1 modes.

This field is ignored if SelfHostedTraceEnabled() == FALSE.

On a Warm reset, this field resets to 0.

E0TRE, bit [0]

EL0 Trace Enable.

E0TRE	Meaning
0b0	Tracing is prohibited at EL0.
0b1	Tracing is allowed at EL0.

This field is ignored if any of the following are true:

- SelfHostedTraceEnabled() == FALSE.
- EL2 is implemented and enabled in the current security state and HCR.TGE == 1.

On a Warm reset, this field resets to 0.

Accessing the TRFCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif SCR.NS == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TTRF == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TTRF == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SDCR.TTRF == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return TRFCR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TTRF == '1' then
        AArch32.TakeMonitorTrapException();
    else
        return TRFCR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return TRFCR;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0001	0b0010	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T1 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T1 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif SCR.NS == '0' then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && MDCR_EL2.TTRF == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HDCR.TTRF == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && PSTATE.M != M32_Monitor && SDCR.TTRF == '1' then
        AArch32.TakeMonitorTrapException();
    else
        TRFCR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && !ELUsingAArch32(EL3) && MDCR_EL3.TTRF == '1' then
        AArch64.AArch32SystemAccessTrap(EL3, 0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SDCR.TTRF == '1' then
        AArch32.TakeMonitorTrapException();
    else
        TRFCR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        TRFCR = R[t];
```

13~~27~~/1209/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TTBCR, Translation Table Base Control Register

The TTBCR characteristics are:

Purpose

The control register for stage 1 of the PL1&0 translation regime. Its controls include:

- Where the VA range is split between addresses translated using TTBR0 and addresses translated using TTBR1.
- The translation table format used by this stage of translation.

From Armv8.2, when the value of TTBCR.{EAE, T2E} is {1, 1}, TTBCR is used with TTBCR2.

Configuration

AArch32 System register TTBCR bits [31:0] are architecturally mapped to AArch64 System register TCR_EL1[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TTBCR are UNKNOWN.

The current translation table format determines which format of the register is used.

Some RW fields of this register have defined reset values. These apply only if the PE resets into an Exception level that is using AArch32. If the PE resets into EL3 using AArch32 then:

- The EAE bit resets to 0 in both the Secure and the Non-secure instances of the register.
- Other reset values apply only to the Secure instance of the register.

Attributes

TTBCR is a 32-bit register.

Field descriptions

The TTBCR bit assignments are:

When TTBCR.EAE == 0:



EAE, bit [31]

Extended Address Enable. The meanings of the possible values of this bit are:

EAE	Meaning
0b0	Use the VMSAv8-32 translation system with the Short-descriptor translation table format.

This field resets to 0.

Bits [30:6]

Reserved, RES0.

PD1, bit [5]

Translation table walk disable for translations using TTBR1. This bit controls whether a translation table walk is performed on a TLB miss, for an address that is translated using TTBR1. The encoding of this bit is:

PD1	Meaning
0b0	Perform translation table walks using TTBR1.
0b1	A TLB miss on an address that is translated using TTBR1 generates a Translation fault. No translation table walk is performed.

This field resets to 0.

PD0, bit [4]

Translation table walk disable for translations using TTBR0. This bit controls whether a translation table walk is performed on a TLB miss for an address that is translated using TTBR0. The encoding of this bit is:

PD0	Meaning
0b0	Perform translation table walks using TTBR0.
0b1	A TLB miss on an address that is translated using TTBR0 generates a Translation fault. No translation table walk is performed.

This field resets to 0.

Bit [3]

Reserved, RES0.

N, bits [2:0]

Indicate the width of the base address held in TTBR0. In TTBR0, the base address field is bits[31:14-N]. The value of N also determines:

- Whether TTBR0 or TTBR1 is used as the base address for translation table walks.
- The size of the translation table pointed to by TTBR0.

N can take any value from 0 to 7, that is, from 0b000 to 0b111.

When N has its reset value of 0, the translation table base is compatible with Armv5 and Armv6.

This field resets to 0.

When TTBCR.EAE == 1:



EAE, bit [31]

Extended Address Enable. The meanings of the possible values of this bit are:

EAE	Meaning
0b1	Use the VMSAv8-32 translation system with the Long-descriptor translation table format.

This field resets to 0.

IMPLEMENTATION DEFINED, bit [30]

IMPLEMENTATION DEFINED.

This field resets to 0.

SH1, bits [29:28]

Shareability attribute for memory associated with translation table walks using TTBR1. Defined values are:

SH1	Meaning
0b00	Non-shareable.
0b10	Outer Shareable.
0b11	Inner Shareable.

Other values are reserved. The effect of programming this field to a Reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Unallocated values in fields of AArch32 System registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.1.11.

This field resets to 0.

ORGN1, bits [27:26]

Outer cacheability attribute for memory associated with translation table walks using TTBR1.

ORGN1	Meaning
0b00	Normal memory, Outer Non-cacheable.
0b01	Normal memory, Outer Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Outer Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Outer Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to 0.

IRGN1, bits [25:24]

Inner cacheability attribute for memory associated with translation table walks using TTBR1.

IRGN1	Meaning
0b00	Normal memory, Inner Non-cacheable.
0b01	Normal memory, Inner Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Inner Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Inner Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to 0.

EPD1, bit [23]

Translation table walk disable for translations using TTBR1. This bit controls whether a translation table walk is performed on a TLB miss, for an address that is translated using TTBR1. The encoding of this bit is:

EPD1	Meaning
0b0	Perform translation table walks using TTBR1.
0b1	A TLB miss on an address that is translated using TTBR1 generates a Translation fault. No translation table walk is performed.

This field resets to 0.

A1, bit [22]

Selects whether TTBR0 or TTBR1 defines the ASID. The encoding of this bit is:

A1	Meaning
0b0	TTBR0.ASID defines the ASID.
0b1	TTBR1.ASID defines the ASID.

This field resets to 0.

Bits [21:19]

Reserved, RES0.

T1SZ, bits [18:16]

See 'Selecting between TTBR0 and TTBR1, VMSAv8-32 Long-descriptor translation table format' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile for how TTBCR.{T1SZ, T0SZ} determine the input address ranges and memory region sizes translated using TTBR0 and TTBR1.

This field resets to 0.

Bits [15:14]

Reserved, RES0.

SH0, bits [13:12]

Shareability attribute for memory associated with translation table walks using TTBR0.

SH0	Meaning
0b00	Non-shareable
0b10	Outer Shareable
0b11	Inner Shareable

Other values are reserved. The effect of programming this field to a Reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Unallocated values in fields of AArch32 System registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.1.11.

This field resets to 0.

ORGN0, bits [11:10]

Outer cacheability attribute for memory associated with translation table walks using TTBR0.

ORGN0	Meaning
0b00	Normal memory, Outer Non-cacheable.
0b01	Normal memory, Outer Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Outer Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Outer Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to 0.

IRGN0, bits [9:8]

Inner cacheability attribute for memory associated with translation table walks using TTBR0.

IRGN0	Meaning
0b00	Normal memory, Inner Non-cacheable.
0b01	Normal memory, Inner Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Inner Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Inner Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to 0.

EPD0, bit [7]

Translation table walk disable for translations using TTBR0. This bit controls whether a translation table walk is performed on a TLB miss, for an address that is translated using TTBR0. The encoding of this bit is:

EPD0	Meaning
0b0	Perform translation table walks using TTBR0.
0b1	A TLB miss on an address that is translated using TTBR0 generates a Translation fault. No translation table walk is performed.

This field resets to 0.

T2E, bit [6]

When ARMv8.2-AA32HPD is implemented:

TTBCR2 Enable.

T2E	Meaning
0b0	TTBCR2 is disabled. The contents of TTBCR2 are treated as 0 for all purposes other than reading or writing the register.
0b1	TTBCR2 is enabled.

If TTBCR.EAE==0, then the behavior is as if the bit is 0.

Otherwise:

Reserved, RES0.

Bits [5:3]

Reserved, RES0.

T0SZ, bits [2:0]

See 'Selecting between TTBR0 and TTBR1, VMSAv8-32 Long-descriptor translation table format' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile for how TTBCR.{T1SZ, T0SZ} determine the input address ranges and memory region sizes translated using TTBR0 and TTBR1.

This field resets to 0.

Accessing the TTBCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0010	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return TTBCR_S;
        else
            return TTBCR_NS;
    else
        return TTBCR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return TTBCR_NS;
    else
        return TTBCR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return TTBCR_S;
    else
        return TTBCR_NS;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0010	0b0000	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            TTBCR_S = R[t];
        else
            TTBCR_NS = R[t];
    else
        TTBCR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        TTBCR_NS = R[t];
    else
        TTBCR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            TTBCR_S = R[t];
        else
            TTBCR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TTBCR2, Translation Table Base Control Register 2

The TTBCR2 characteristics are:

Purpose

The second control register for stage 1 of the PL1&0 translation regime.

If ARMv8.2-AA32HPD is not implemented then this register is not implemented and its encoding is UNDEFINED. Otherwise:

- When the value of TTBCR.{EAE, T2E} is not {1, 1} the contents of TTBCR2 are treated as zero for all purposes other than reading or writing the register.
- When the value of TTBCR.{EAE, T2E} is {1, 1} TTBCR2 is used with TTBCR.

Configuration

AArch32 System register TTBCR2 bits [31:0] are architecturally mapped to AArch64 System register TCR_EL1[63:32] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when AArch32 is supported at any Exception level and ARMv8.2-AA32HPD is implemented. Otherwise, direct accesses to TTBCR2 are UNDEFINED.

Attributes

TTBCR2 is a 32-bit register.

Field descriptions

The TTBCR2 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4
RES0													HWU162	HWU161	HWU160	HWU159	HWU062	HWU061	HWU060	HWU059	HPD1	HPD0	RE				

Bits [31:19]

Reserved, RES0.

HWU162, bit [18]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[62] of the stage 1 translation table Block or Page entry for translations using TTBR1.

HWU162	Meaning
0b0	For translations using TTBR1, bit[62] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR1, bit[62] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TTBCR2.HPD1 is 1.

The Effective value of this field is 0 if the value of TTBCR2.HPD1 is 0 or the value of TTBCR.T2E is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU161, bit [17]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[61] of the stage 1 translation table Block or Page entry for translations using TTBR1.

HWU161	Meaning
0b0	For translations using TTBR1, bit[61] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR1, bit[61] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TTBCR2.HPD1 is 1.

The Effective value of this field is 0 if the value of TTBCR2.HPD1 is 0 or the value of TTBCR.T2E is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU160, bit [16]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[60] of the stage 1 translation table Block or Page entry for translations using TTBR1.

HWU160	Meaning
0b0	For translations using TTBR1, bit[60] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR1, bit[60] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TTBCR2.HPD1 is 1.

The Effective value of this field is 0 if the value of TTBCR2.HPD1 is 0 or the value of TTBCR.T2E is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU159, bit [15]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[59] of the stage 1 translation table Block or Page entry for translations using TTBR1.

HWU159	Meaning
0b0	For translations using TTBR1, bit[59] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR1, bit[59] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TTBCR2.HPD1 is 1.

The Effective value of this field is 0 if the value of TTBCR2.HPD1 is 0 or the value of TTBCR.T2E is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU062, bit [14]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[62] of the stage 1 translation table Block or Page entry for translations using TTBR0.

HWU062	Meaning
0b0	For translations using TTBR0, bit[62] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR0, bit[62] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TTBCR2.HPD0 is 1.

The Effective value of this field is 0 if the value of TTBCR2.HPD0 is 0 or the value of TTBCR.T2E is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU061, bit [13]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[61] of the stage 1 translation table Block or Page entry for translations using TTBR0.

HWU061	Meaning
0b0	For translations using TTBR0, bit[61] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR0, bit[61] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TTBCR2.HPD0 is 1.

The Effective value of this field is 0 if the value of TTBCR2.HPD0 is 0 or the value of TTBCR.T2E is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU060, bit [12]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[60] of the stage 1 translation table Block or Page entry for translations using TTBR0.

HWU060	Meaning
0b0	For translations using TTBR0, bit[60] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR0, bit[60] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TTBCR2.HPD0 is 1.

The Effective value of this field is 0 if the value of TTBCR2.HPD0 is 0 or the value of TTBCR.T2E is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU059, bit [11]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[59] of the stage 1 translation table Block or Page entry for translations using TTBR0.

HWU059	Meaning
0b0	For translations using TTBR0, bit[59] of each stage 1 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	For translations using TTBR0, bit[59] of each stage 1 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose if the value of TTBCR2.HPD0 is 1.

The Effective value of this field is 0 if the value of TTBCR2.HPD0 is 0 or the value of TTBCR.T2E is 0.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HPD1, bit [10]

Hierarchical Permission Disables. This affects the hierarchical control bits, APTable, XNTable, and PXNTable, in the translation tables pointed to by TTBR1.

HPD1	Meaning
0b0	Hierarchical permissions are enabled.
0b1	Hierarchical permissions are disabled if TTBCR.T2E == 1.

When disabled, the permissions are treated as if the bits are 0.

The Effective value of this field is 0 if the value of TTBCR.T2E is 0.

This field resets to an architecturally UNKNOWN value.

HPD0, bit [9]

Hierarchical Permission Disables. This affects the hierarchical control bits, APTable, XNTable, and PXNTable, in the translation tables pointed to by TTBR0.

HPD0	Meaning
0b0	Hierarchical permissions are enabled.
0b1	Hierarchical permissions are disabled if TTBCR.T2E ==1.

When disabled, the permissions are treated is as if the bits are 0.

The Effective value of this field is 0 if the value of TTBCR.T2E is 0.

This field resets to an architecturally UNKNOWN value.

Bits [8:0]

Reserved, RES0.

Accessing the TTBCR2

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0010	0b0000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return TTBCR2_S;
        else
            return TTBCR2_NS;
    else
        return TTBCR2;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return TTBCR2_NS;
    else
        return TTBCR2;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return TTBCR2_S;
    else
        return TTBCR2_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0010	0b0000	0b011

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            TTBCR2_S = R[t];
        else
            TTBCR2_NS = R[t];
    else
        TTBCR2 = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        TTBCR2_NS = R[t];
    else
        TTBCR2 = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            TTBCR2_S = R[t];
        else
            TTBCR2_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TTBR0, Translation Table Base Register 0

The TTBR0 characteristics are:

Purpose

Holds the base address of the translation table for the initial lookup for stage 1 of the translation of an address from the lower VA range in the PL1&0 translation regime, and other information for this translation regime.

Configuration

AArch32 System register TTBR0 bits [63:0] are architecturally mapped to AArch64 System register TTBR0_EL1[63:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TTBR0 are UNKNOWN.

TTBCR.EAE determines which TTBR0 format is used:

- TTBCR.EAE == 0b0: 32-bit format is used. TTBR0[63:32] are ignored.
- TTBCR.EAE == 0b1: 64-bit format is used.

When EL3 is using AArch32, write access to TTBR0(S) is disabled when the CP15SDISABLE signal is asserted HIGH.

Used in conjunction with the TTBCR. When the 64-bit TTBR0 format is used, cacheability and shareability information is held in the TTBCR, not in TTBR0.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

TTBR0 is a 64-bit register that can also be accessed as a 32-bit value. If it is accessed as a 32-bit register, accesses read and write bits [31:0] and do not modify bits [63:32].

Field descriptions

The TTBR0 bit assignments are:

When TTBCR.EAE == 0:



Bits [63:32]

Reserved, RES0.

TTB0, bits [31:7]

Translation table base address, bits[31:x], where x is 14-(TTBCR.N). Register bits [x-1:7] are RES0, with the additional requirement that if these bits are not all zero, this is a misaligned translation table base address, with effects that are CONSTRAINED UNPREDICTABLE, and must be one of the following:

- Register bits [x-1:7] are treated as if all the bits are zero. The value read back from these bits is either the value written or zero.

- The result of the calculation of an address for a translation table walk using this register can be corrupted in those bits that are nonzero.

This field resets to an architecturally UNKNOWN value.

IRGN[0], bit [6]

This field is bit[0] of IRGN[1:0].

Inner region bits. Bits [0,6] of this register together indicate the Inner Cacheability attributes for the memory associated with the translation table walks. The possible values of IRGN[1:0] are:

IRGN	Meaning
0b00	Normal memory, Inner Non-cacheable.
0b01	Normal memory, Inner Write-Back Write-Allocate Cacheable.
0b10	Normal memory, Inner Write-Through Cacheable.
0b11	Normal memory, Inner Write-Back no Write-Allocate Cacheable.

Note

The encoding of the IRGN bits is counter-intuitive, with register bit[6] being IRGN[0] and register bit[0] being IRGN[1]. This encoding is chosen to give a consistent encoding of memory region types and to ensure that software written for ARMv7 without the Multiprocessing Extensions can run unmodified on an implementation that includes the functionality introduced by the ARMv7 Multiprocessing Extensions.

The IRGN field is split as follows:

- IRGN[0] is TTBR0[6].
- IRGN[1] is TTBR0[0].

This field resets to an architecturally UNKNOWN value.

NOS, bit [5]

Not Outer Shareable. When the value of TTBR0.S is 1, indicates whether the memory associated with a translation table walk is Inner Shareable or Outer Shareable:

NOS	Meaning
0b0	Memory is Outer Shareable.
0b1	Memory is Inner Shareable.

This bit is ignored when the value of TTBR0.S is 0.

This field resets to an architecturally UNKNOWN value.

RGN, bits [4:3]

Region bits. Indicates the Outer cacheability attributes for the memory associated with the translation table walks:

RGN	Meaning
0b00	Normal memory, Outer Non-cacheable.
0b01	Normal memory, Outer Write-Back Write-Allocate Cacheable.
0b10	Normal memory, Outer Write-Through Cacheable.
0b11	Normal memory, Outer Write-Back no Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

IMP, bit [2]

The effect of this bit is IMPLEMENTATION DEFINED. If the translation table implementation does not include any IMPLEMENTATION DEFINED features this bit is RES0.

This field resets to an architecturally UNKNOWN value.

S, bit [1]

Shareable. Indicates whether the memory associated with the translation table walks is Non-shareable:

S	Meaning
0b0	Memory is Non-shareable.
0b1	Memory is shareable. The TTBR0.NOS field indicates whether the memory is Inner Shareable or Outer Shareable.

This field resets to an architecturally UNKNOWN value.

IRGN[1], bit [0]

This field is bit[1] of IRGN[1:0].

See IRGN[0] for the field description.

When TTBCR.EAE == 1:



Bits [63:56]

Reserved, RES0.

ASID, bits [55:48]

An ASID for the translation table base address. The TTBCR.A1 field selects either TTBR0.ASID or TTBR1.ASID.

This field resets to an architecturally UNKNOWN value.

BADDR, bits [47:1]

Translation table base address, bits[47:x], Bits [x-1:1] are RES0, with the additional requirement that if bits[x-1:3] are not all zero, this is a misaligned translation table base address, with effects that are CONSTRAINED UNPREDICTABLE, and must be one of the following:

- Register bits [x-1:3] are treated as if all the bits are zero. The value read back from these bits is either the value written or zero.
- The result of the calculation of an address for a translation table walk using this register can be corrupted in those bits that are nonzero.

x is determined from the value of TTBCR.T0SZ as follows:

- If TTBCR.T0SZ is 0 or 1, x = 5 - TTBCR.T0SZ.
- If TTBCR.T0SZ is greater than 1, x = 14 - TTBCR.T0SZ.

If bits[47:40] of the translation table base address are not zero, an Address size fault is generated.

This field resets to an architecturally UNKNOWN value.

CnP, bit [0]

When ARMv8.2-TTCNP is implemented:

Common not Private. When TTBCR.EAE ==1, this bit indicates whether each entry that is pointed to by TTBR0 is a member of a common set that can be used by every PE in the Inner Shareable domain for which the value of TTBR0.CnP is 1.

CnP	Meaning
0b0	The translation table entries pointed to by this instance of TTBR0, for the current ASID, are permitted to differ from corresponding entries for this instance of TTBR0 for other PEs in the Inner Shareable domain. This is not affected by: • The value of TTBR0.CnP on those other PEs. • The value of TTBCR.EAE on those other PEs. • The value of the current ASID or, for the Non-secure instance of TTBR0, the value of the current VMID.
0b1	The translation table entries pointed to by this instance of TTBR0 are the same as the translation table entries for every other PE in the Inner Shareable domain for which the value of TTBR0.CnP is 1 for this instance of TTBR0 and all of the following apply: • The translation table entries are pointed to by this instance of TTBR0. • The value of the applicable TTBCR.EAE field is 1. • The ASID is the same as the current ASID. • For the Non-secure instance of TTBR0, the VMID is the same as the current VMID.

When a TLB combines entries from stage 1 translation and stage 2 translation into a single entry, that entry can only be shared between different PEs if the value of the CnP bit is 1 for both stage 1 and stage 2.

Note

If the value of the TTBR0.CnP bit is 1 on multiple PEs in the same Inner Shareable domain and those TTBR0s do not point to the same translation table entries when the other conditions specified for the case when the value of CnP is 1 apply, then the results of translations are CONSTRAINED UNPREDICTABLE, see 'CONSTRAINED UNPREDICTABLE behaviors due to caching of control or data values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Accessing the TTBR0

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0010	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return TTBR0_S<31:0>;
        else
            return TTBR0_NS<31:0>;
    else
        return TTBR0<31:0>;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return TTBR0_NS<31:0>;
    else
        return TTBR0<31:0>;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return TTBR0_S<31:0>;
    else
        return TTBR0_NS<31:0>;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0010	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            TTBR0_S = ZeroExtend(R[t]);
        else
            TTBR0_NS = ZeroExtend(R[t]);
    else
        TTBR0 = ZeroExtend(R[t]);
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        TTBR0_NS = ZeroExtend(R[t]);
    else
        TTBR0 = ZeroExtend(R[t]);
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            TTBR0_S = ZeroExtend(R[t]);
        else
            TTBR0_NS = ZeroExtend(R[t]);
```

MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b0010	0b0000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return TTBR0_S;
        else
            return TTBR0_NS;
    else
        return TTBR0;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return TTBR0_NS;
    else
        return TTBR0;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return TTBR0_S;
    else
        return TTBR0_NS;
```

MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b0010	0b0000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            TTBR0_S = R[t2]:R[t];
        else
            TTBR0_NS = R[t2]:R[t];
    else
        TTBR0 = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        TTBR0_NS = R[t2]:R[t];
    else
        TTBR0 = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            TTBR0_S = R[t2]:R[t];
        else
            TTBR0_NS = R[t2]:R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

TTBR1, Translation Table Base Register 1

The TTBR1 characteristics are:

Purpose

Holds the base address of the translation table for the initial lookup for stage 1 of the translation of an address from the higher VA range in the PL1&0 translation regime, and other information for this translation regime.

Configuration

AArch32 System register TTBR1 bits [63:0] are architecturally mapped to AArch64 System register TTBR1_EL1[63:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to TTBR1 are UNKNOWN.

TTBCR.EAE determines which TTBR1 format is used:

- TTBCR.EAE == 0b0: 32-bit format is used. TTBR1[63:32] are ignored.
- TTBCR.EAE == 0b1: 64-bit format is used.

Used in conjunction with the TTBCR. When the 64-bit TTBR1 format is used, cacheability and shareability information is held in the TTBCR, not in TTBR1.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

TTBR1 is a 64-bit register that can also be accessed as a 32-bit value. If it is accessed as a 32-bit register, accesses read and write bits [31:0] and do not modify bits [63:32].

Field descriptions

The TTBR1 bit assignments are:

When TTBCR.EAE == 0:



Bits [63:32]

Reserved, RES0.

TTB1, bits [31:7]

Translation table base address, bits[31:14]. Register bits [13:7] are RES0, with the additional requirement that if these bits are not all zero, this is a misaligned translation table base address, with effects that are CONSTRAINED UNPREDICTABLE, and must be one of the following:

- Register bits [13:7] are treated as if all the bits are zero. The value read back from these bits is either the value written or zero.
- The result of the calculation of an address for a translation table walk using this register can be corrupted in those bits that are nonzero.

This field resets to an architecturally UNKNOWN value.

IRGN[1], bit [6]

This field is bit[1] of IRGN[1:0].

Inner region bits. IRGN[1:0] indicate the Inner Cacheability attributes for the memory associated with the translation table walks. The possible values of IRGN[1:0] are:

IRGN	Meaning
0b00	Normal memory, Inner Non-cacheable.
0b01	Normal memory, Inner Write-Back Write-Allocate Cacheable.
0b10	Normal memory, Inner Write-Through Cacheable.
0b11	Normal memory, Inner Write-Back no Write-Allocate Cacheable.

Note

The encoding of the IRGN bits is counter-intuitive, with register bit[6] being IRGN[0] and register bit[0] being IRGN[1]. This encoding is chosen to give a consistent encoding of memory region types and to ensure that software written for Armv7 without the Multiprocessing Extensions can run unmodified on an implementation that includes the functionality introduced by the ARMv7 Multiprocessing Extensions.

The IRGN field is split as follows:

- IRGN[1] is TTBR1[6].
- IRGN[0] is TTBR1[0].

This field resets to an architecturally UNKNOWN value.

NOS, bit [5]

Not Outer Shareable. When the value of TTBR1.S is 1, indicates whether the memory associated with a translation table walk is Inner Shareable or Outer Shareable:

NOS	Meaning
0b0	Memory is Outer Shareable.
0b1	Memory is Inner Shareable.

This bit is ignored when the value of TTBR1.S is 0.

This field resets to an architecturally UNKNOWN value.

RGN, bits [4:3]

Region bits. Indicates the Outer cacheability attributes for the memory associated with the translation table walks:

RGN	Meaning
0b00	Normal memory, Outer Non-cacheable.
0b01	Normal memory, Outer Write-Back Write-Allocate Cacheable.
0b10	Normal memory, Outer Write-Through Cacheable.
0b11	Normal memory, Outer Write-Back no Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

IMP, bit [2]

The effect of this bit is IMPLEMENTATION DEFINED. If the translation table implementation does not include any IMPLEMENTATION DEFINED features this bit is RES0.

This field resets to an architecturally UNKNOWN value.

S, bit [1]

Shareable. Indicates whether the memory associated with the translation table walks is Non-shareable:

S	Meaning
0b0	Memory is Non-shareable.
0b1	Memory is shareable. The TTBR1.NOS field indicates whether the memory is Inner Shareable or Outer Shareable.

This field resets to an architecturally UNKNOWN value.

IRGN[0], bit [0]

This field is bit[0] of IRGN[1:0].

See IRGN[1] for the field description.

When TTBCR.EAE == 1:



Bits [63:56]

Reserved, RES0.

ASID, bits [55:48]

An ASID for the translation table base address. The TTBCR.A1 field selects either TTBR0.ASID or TTBR1.ASID.

This field resets to an architecturally UNKNOWN value.

BADDR, bits [47:1]

Translation table base address, bits[47:x], Bits [x-1:1] are RES0, with the additional requirement that if bits[x-1:3] are not all zero, this is a misaligned translation table base address, with effects that are CONSTRAINED UNPREDICTABLE, and must be one of the following:

- Register bits [x-1:3] are treated as if all the bits are zero. The value read back from these bits is either the value written or zero.
- The result of the calculation of an address for a translation table walk using this register can be corrupted in those bits that are nonzero.

x is determined from the value of TTBCR.T1SZ as follows:

- If TTBCR.T1SZ is 0 or 1, x = 5 - TTBCR.T1SZ.
- If TTBCR.T1SZ is greater than 1, x = 14 - TTBCR.T1SZ.

If bits[47:40] of the translation table base address are not zero, an Address size fault is generated.

This field resets to an architecturally UNKNOWN value.

CnP, bit [0]

When ARMv8.2-TTCNP is implemented:

Common not Private. When TTBCR.EAE ==1, this bit indicates whether each entry that is pointed to by TTBR1 is a member of a common set that can be used by every PE in the Inner Shareable domain for which the value of TTBR1.CnP is 1.

CnP	Meaning
0b0	The translation table entries pointed to by this instance of TTBR1, for the current ASID, are permitted to differ from corresponding entries for this instance of TTBR1 for other PEs in the Inner Shareable domain. This is not affected by: • The value of TTBR1.CnP on those other PEs. • The value of TTBCR.EAE on those other PEs. • The value of the current ASID or, for the Non-secure instance of TTBR1, the value of the current VMID.
0b1	The translation table entries pointed to by this instance of TTBR1 are the same as the translation table entries for every other PE in the Inner Shareable domain for which the value of TTBR1.CnP is 1 for this instance of TTBR1 and all of the following apply: • The translation table entries are pointed to by this instance of TTBR1. • The value of the applicable TTBCR.EAE field is 1. • The ASID is the same as the current ASID. • For the Non-secure instance of TTBR1, the VMID is the same as the current VMID.

When a TLB combines entries from stage 1 translation and stage 2 translation into a single entry, that entry can only be shared between different PEs if the value of the CnP bit is 1 for both stage 1 and stage 2.

Note

If the value of the TTBR1.CnP bit is 1 on multiple PEs in the same Inner Shareable domain and those TTBR1s do not point to the same translation table entries when the other conditions specified for the case when the value of CnP is 1 apply, then the results of translations are CONSTRAINED UNPREDICTABLE, see 'CONSTRAINED UNPREDICTABLE behaviors due to caching of control or data values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Accessing the TTBR1

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0010	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return TTBR1_S<31:0>;
        else
            return TTBR1_NS<31:0>;
    else
        return TTBR1<31:0>;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return TTBR1_NS<31:0>;
    else
        return TTBR1<31:0>;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return TTBR1_S<31:0>;
    else
        return TTBR1_NS<31:0>;
```

MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0010	0b0000	0b001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            TTBR1_S = ZeroExtend(R[t]);
        else
            TTBR1_NS = ZeroExtend(R[t]);
    else
        TTBR1 = ZeroExtend(R[t]);
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        TTBR1_NS = ZeroExtend(R[t]);
    else
        TTBR1 = ZeroExtend(R[t]);
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            TTBR1_S = ZeroExtend(R[t]);
        else
            TTBR1_NS = ZeroExtend(R[t]);
```

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b0010	0b0001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TRVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TRVM == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return TTBR1_S;
        else
            return TTBR1_NS;
    else
        return TTBR1;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return TTBR1_NS;
    else
        return TTBR1;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return TTBR1_S;
    else
        return TTBR1_NS;
```

```
MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b0010	0b0001

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif EL2Enabled() && !ELUsingAArch32(EL2) && HCR_EL2.TVM == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HCR.TVM == '1' then
        AArch32.TakeHypTrapException(0x04);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            TTBR1_S = R[t2]:R[t];
        else
            TTBR1_NS = R[t2]:R[t];
    else
        TTBR1 = R[t2]:R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        TTBR1_NS = R[t2]:R[t];
    else
        TTBR1 = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            TTBR1_S = R[t2]:R[t];
        else
            TTBR1_NS = R[t2]:R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VBAR, Vector Base Address Register

The VBAR characteristics are:

Purpose

When high exception vectors are not selected, holds the vector base address for exceptions that are not taken to Monitor mode or to Hyp mode.

Software must program VBAR(NS) with the required initial value as part of the PE boot sequence.

Configuration

AArch32 System register VBAR bits [31:0] are architecturally mapped to AArch64 System register VBAR_EL1[31:0] .

ThisSome or all RW fields of this register ishave presentdefined reset values. These apply only when AArch32if isthe supportedPE atresets anyinto an Exception level. level that is using AArch32. If the PE resets into EL3 using AArch32 they apply only to the Secure instance of the register. Otherwise, RW directfields accessesin this register reset to VBAR arearchitecturally UNKNOWN.values.

Attributes

VBAR is a 32-bit register.

Field descriptions

The VBAR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Vector Base Address																											RES0					

Bits [31:5]

Vector Base Address. Bits[31:5] of the base address of the exception vectors for exceptions taken to this Exception level. Bits[4:0] of an exception vector are the exception offset.

This field resets to an IMPLEMENTATION DEFINED value.

Bits [4:0]

Reserved, RES0.

Accessing the VBAR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            return VBAR_S;
        else
            return VBAR_NS;
    else
        return VBAR;
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        return VBAR_NS;
    else
        return VBAR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        return VBAR_S;
    else
        return VBAR_NS;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b1100	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T12 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T12 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) && SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    elsif HaveEL(EL3) && ELUsingAArch32(EL3) then
        if SCR.NS == '0' then
            VBAR_S = R[t];
        else
            VBAR_NS = R[t];
    else
        VBAR = R[t];
elsif PSTATE.EL == EL2 then
    if HaveEL(EL3) && ELUsingAArch32(EL3) then
        VBAR_NS = R[t];
    else
        VBAR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' && CP15SDISABLE == HIGH then
        UNDEFINED;
    elsif SCR.NS == '0' && CP15SDISABLE2 == HIGH then
        UNDEFINED;
    else
        if SCR.NS == '0' then
            VBAR_S = R[t];
        else
            VBAR_NS = R[t];
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VMPIDR, Virtualization Multiprocessor ID Register

The VMPIDR characteristics are:

Purpose

Holds the value of the Virtualization Multiprocessor ID. This is the value returned by Non-secure EL1 reads of MPIDR.

Configuration

AArch32 System register VMPIDR bits [31:0] are architecturally mapped to AArch64 System register VMPIDR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to VMPIDR are UNKNOWN.

If EL2 is not implemented but EL3 is implemented, this register takes the value of the MPIDR.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 with EL2 using AArch32, or into EL3 with EL3 using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VMPIDR is a 32-bit register.

Field descriptions

The VMPIDR bit assignments are:



M, bit [31]

Indicates whether this implementation includes the functionality introduced by the ARMv7 Multiprocessing Extensions. The possible values of this bit are:

M	Meaning
0b0	This implementation does not include the ARMv7 Multiprocessing Extensions functionality.
0b1	This implementation includes the ARMv7 Multiprocessing Extensions functionality.

From Armv8 this bit is RES1.

U, bit [30]

Indicates a Uniprocessor system, as distinct from PE 0 in a multiprocessor system. The possible values of this bit are:

U	Meaning
0b0	Processor is part of a multiprocessor system.
0b1	Processor is part of a uniprocessor system.

In a system where the PE resets into EL2 or EL3, this field resets to the value in MPIDR.U.

Bits [29:25]

Reserved, RES0.

MT, bit [24]

Indicates whether the lowest level of affinity consists of logical PEs that are implemented using a multithreading type approach. See the description of Aff0 for more information about affinity levels. The possible values of this bit are:

MT	Meaning
0b0	Performance of PEs at the lowest affinity level is largely independent.
0b1	Performance of PEs at the lowest affinity level is very interdependent.

In a system where the PE resets into EL2 or EL3, this field resets to the value in MPIDR.MT.

Aff2, bits [23:16]

Affinity level 2. See the description of Aff0 for more information.

In a system where the PE resets into EL2 or EL3, this field resets to the value in MPIDR.Aff2.

Aff1, bits [15:8]

Affinity level 1. See the description of Aff0 for more information.

In a system where the PE resets into EL2 or EL3, this field resets to the value in MPIDR.Aff1.

Aff0, bits [7:0]

Affinity level 0. This is the affinity level that is most significant for determining PE behavior. Higher affinity levels are increasingly less significant in determining PE behavior. The assigned value of the MPIDR.{Aff2, Aff1, Aff0} or MPIDR_EL1.{Aff3, Aff2, Aff1, Aff0} set of fields of each PE must be unique within the system as a whole.

In a system where the PE resets into EL2 or EL3, this field resets to the value in MPIDR.Aff0.

Accessing the VMPIDR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0000	0b0000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return VMPIDR;
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        return MPIDR;
    elsif SCR.NS == '0' then
        UNDEFINED;
    else
        return VMPIDR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0000	0b0000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    VMPIDR = R[t];
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        //no operation
    elsif SCR.NS == '0' then
        UNDEFINED;
    else
        VMPIDR = R[t];
```

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0000	0b101

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) then
        return VMPIDR_EL2<31:0>;
    elsif EL2Enabled() && ELUsingAArch32(EL2) then
        return VMPIDR;
    else
        return MPIDR;
elsif PSTATE.EL == EL2 then
    return MPIDR;
elsif PSTATE.EL == EL3 then
    return MPIDR;
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VPIDR, Virtualization Processor ID Register

The VPIDR characteristics are:

Purpose

Holds the value of the Virtualization Processor ID. This is the value returned by Non-secure EL1 reads of MIDR.

Configuration

AArch32 System register VPIDR bits [31:0] are architecturally mapped to AArch64 System register VPIDR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to VPIDR are UNKNOWN.

If EL2 is not implemented but EL3 is implemented, this register takes the value of the MIDR.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 with EL2 using AArch32, or into EL3 with EL3 using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VPIDR is a 32-bit register.

Field descriptions

The VPIDR bit assignments are:



Implementer, bits [31:24]

The Implementer code. This field must hold an implementer code that has been assigned by Arm. Assigned codes include the following:

Hex representation	ASCII representation	Implementer
0x41	A	Arm Limited
0x42	B	Broadcom Corporation
0x43	C	Cavium Inc.
0x44	D	Digital Equipment Corporation
0x49	I	Infineon Technologies AG
0x4D	M	Motorola or Freescale Semiconductor Inc.
0x4E	N	NVIDIA Corporation
0x50	P	Applied Micro Circuits Corporation
0x51	Q	Qualcomm Inc.
0x56	V	Marvell International Ltd.
0x69	i	Intel Corporation

Arm can assign codes that are not published in this manual. All values not assigned by Arm are reserved and must not be used.

In a system where the PE resets into EL2 or EL3, this field resets to the value in MIDR.Implementer.

Variant, bits [23:20]

An IMPLEMENTATION DEFINED variant number. Typically, this field is used to distinguish between different product variants, or major revisions of a product.

In a system where the PE resets into EL2 or EL3, this field resets to the value in MIDR.Variant.

Architecture, bits [19:16]

The permitted values of this field are:

Architecture	Meaning
0b0001	Armv4.
0b0010	Armv4T.
0b0011	Armv5 (obsolete).
0b0100	Armv5T.
0b0101	Armv5TE.
0b0110	Armv5TEJ.
0b0111	Armv6.
0b1111	Architectural features are individually identified in the ID_* registers, see 'ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K12.5.3.

All other values are reserved.

In a system where the PE resets into EL2 or EL3, this field resets to the value in MIDR.Architecture.

PartNum, bits [15:4]

An IMPLEMENTATION DEFINED primary part number for the device.

On processors implemented by Arm, if the top four bits of the primary part number are 0x0 or 0x7, the variant and architecture are encoded differently.

In a system where the PE resets into EL2 or EL3, this field resets to the value in MIDR.PartNum.

Revision, bits [3:0]

An IMPLEMENTATION DEFINED revision number for the device.

In a system where the PE resets into EL2 or EL3, this field resets to the value in MIDR.Revision.

Accessing the VPIDR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return VPIDR;
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        return MIDR;
    elsif SCR.NS == '0' then
        UNDEFINED;
    else
        return VPIDR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    VPIDR = R[t];
elsif PSTATE.EL == EL3 then
    if !HaveEL(EL2) then
        //no operation
    elsif SCR.NS == '0' then
        UNDEFINED;
    else
        VPIDR = R[t];
```

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b000	0b0000	0b0000	0b000

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T0 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T0 == '1' then
        AArch32.TakeHypTrapException(0x03);
    elsif EL2Enabled() && !ELUsingAArch32(EL2) then
        return VPIDR_EL2<31:0>;
    elsif EL2Enabled() && ELUsingAArch32(EL2) then
        return VPIDR;
    else
        return MIDR;
elsif PSTATE.EL == EL2 then
    return MIDR;
elsif PSTATE.EL == EL3 then
    return MIDR;
```

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VTCR, Virtualization Translation Control Register

The VTCR characteristics are:

Purpose

The control register for stage 2 of the Non-secure PL1&0 translation regime.

Note

This stage of translation always uses the Long-descriptor translation table format.

Configuration

AArch32 System register VTCR bits [31:0] are architecturally mapped to AArch64 System register VTCR_EL2[31:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to VTCR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VTCR is a 32-bit register.

Field descriptions

The VTCR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES1	RES0		HWU62	HWU61	HWU60	HWU59	RES0													SH0		ORGN0		IRGN0		SL0		RES0		S		T0SZ	

Bit [31]

Reserved, RES1.

Bits [30:29]

Reserved, RES0.

HWU62, bit [28]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[62] of the stage 2 translation table Block or Page entry.

HWU62	Meaning
0b0	Bit[62] of each stage 2 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[62] of each stage 2 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU61, bit [27]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[61] of the stage 2 translation table Block or Page entry.

HWU61	Meaning
0b0	Bit[61] of each stage 2 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[61] of each stage 2 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU60, bit [26]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[60] of the stage 2 translation table Block or Page entry.

HWU60	Meaning
0b0	Bit[60] of each stage 2 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[60] of each stage 2 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HWU59, bit [25]

When ARMv8.2-TTPBHA is implemented:

Hardware Use. Indicates IMPLEMENTATION DEFINED hardware use of bit[59] of the stage 2 translation table Block or Page entry.

HWU59	Meaning
0b0	Bit[59] of each stage 2 translation table Block or Page entry cannot be used by hardware for an IMPLEMENTATION DEFINED purpose.
0b1	Bit[59] of each stage 2 translation table Block or Page entry can be used by hardware for an IMPLEMENTATION DEFINED purpose.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [24:14]

Reserved, RES0.

SH0, bits [13:12]

Shareability attribute for memory associated with translation table walks using VTTBR.

SH0	Meaning
0b00	Non-shareable.
0b10	Outer Shareable.
0b11	Inner Shareable.

Other values are reserved. The effect of programming this field to a Reserved value is that behavior is CONSTRAINED UNPREDICTABLE, as described in 'Unallocated values in fields of AArch32 System registers and translation table entries' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section K1.1.11.

This field resets to an architecturally UNKNOWN value.

ORGN0, bits [11:10]

Outer cacheability attribute for memory associated with translation table walks using VTTBR.

ORGN0	Meaning
0b00	Normal memory, Outer Non-cacheable.
0b01	Normal memory, Outer Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Outer Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Outer Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

IRGN0, bits [9:8]

Inner cacheability attribute for memory associated with translation table walks using VTTBR.

IRGN0	Meaning
0b00	Normal memory, Inner Non-cacheable.
0b01	Normal memory, Inner Write-Back Read-Allocate Write-Allocate Cacheable.
0b10	Normal memory, Inner Write-Through Read-Allocate No Write-Allocate Cacheable.
0b11	Normal memory, Inner Write-Back Read-Allocate No Write-Allocate Cacheable.

This field resets to an architecturally UNKNOWN value.

SL0, bits [7:6]

Starting level for translation table walks using VTTBR.

SL0	Meaning
0b00	Start at level 2
0b01	Start at level 1

All other values are reserved. If this field is programmed to a reserved value, or to a value that is not consistent with the programming of T0SZ, then a stage 2 level 1 Translation fault is generated.

This field resets to an architecturally UNKNOWN value.

Bit [5]

Reserved, RES0.

S, bit [4]

Sign extension bit. This bit must be programmed to the value of T0SZ[3]. If it is not, then the behavior is CONSTRAINED UNPREDICTABLE and the stage 2 T0SZ value is treated as an UNKNOWN value, see 'Misprogramming VTCR.S' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to an architecturally UNKNOWN value.

T0SZ, bits [3:0]

The size offset of the memory region addressed by VTTBR. The region size is $2^{(32-T0SZ)}$ bytes.

This field holds a four-bit signed integer value, meaning it supports values from -8 to 7.

Note

This is different from the other translation control registers, where TnSZ holds a three-bit unsigned integer, supporting values from 0 to 7.

If this field is programmed to a value that is not consistent with the programming of SL0 then a stage 2 level 1 Translation fault is generated.

This field resets to an architecturally UNKNOWN value.

Accessing the VTCR

Accesses to this register use the following encodings:

```
MRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0010	0b0001	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return VTCR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return VTCR;
```

```
MCR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <CRn>, <CRm>{, {#}<opc2>}
```

coproc	opc1	CRn	CRm	opc2
0b1111	0b100	0b0010	0b0001	0b010

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x03);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x03);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    VTCR = R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        VTCR = R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

VTTBR, Virtualization Translation Table Base Register

The VTTBR characteristics are:

Purpose

Holds the base address of the translation table for the initial lookup for stage 2 of an address translation in the Non-secure PL1&0 translation regime, and other information for this translation regime.

Configuration

AArch32 System register VTTBR bits [63:0] are architecturally mapped to AArch64 System register VTTBR_EL2[63:0] .

This register is present only when AArch32 is supported at any Exception level. Otherwise, direct accesses to VTTBR are UNKNOWN.

If EL2 is not implemented, this register is RES0 from EL3.

~~Some or all RW fields of this register have defined reset values. These apply only if the PE resets into EL2 with EL2 using AArch32, or into EL3 with EL3 using AArch32. Otherwise, RW fields in this register reset to architecturally UNKNOWN values.~~

Attributes

VTTBR is a 64-bit register.

Field descriptions

The VTTBR bit assignments are:



Bits [63:56]

Reserved, RES0.

VMID, bits [55:48]

The VMID for the translation table.

In a system where the PE resets into EL2 or EL3, this field resets to `0`.

BADDR, bits [47:1]

Translation table base address, bits[47:x], Bits [x-1:1] are RES0, with the additional requirement that if bits[x-1:3] are not all zero, this is a misaligned translation table base address, with effects that are CONSTRAINED UNPREDICTABLE, and must be one of the following:

- Register bits [x-1:3] are treated as if all the bits are zero. The value read back from these bits is either the value written or zero.
- The result of the calculation of an address for a translation table walk using this register can be corrupted in those bits that are nonzero.

x is determined from the value of VTCR.SL0 and VTCR.T0SZ as follows:

- If VTCR.SL0 is `0b00`, meaning that lookup starts at level 2, then x is 14 - VTCR.T0SZ.
- If VTCR.SL0 is `0b01`, meaning that lookup starts at level 1, then x is 5 - VTCR.T0SZ.
- If VTCR.SL0 is either `0b10` or `0b11` then a stage 2 level 1 Translation fault is generated.

If bits[47:40] of the translation table base address are not zero, an Address size fault is generated.

In a system where the PE resets into EL2 or EL3, this field resets to an architecturally UNKNOWN value.

CnP, bit [0]

When ARMv8.2-TTCNP is implemented:

Common not Private. This bit indicates whether each entry that is pointed to by VTTBR is a member of a common set that can be used by every PE in the Inner Shareable domain for which the value of VTTBR.CnP is 1.

CnP	Meaning
`0b0`	The translation table entries pointed to by VTTBR are permitted to differ from the entries for VTTBR for other PEs in the Inner Shareable domain. This is not affected by the value of the current VMID.
`0b1`	The translation table entries pointed to by VTTBR are the same as the translation table entries for every other PE in the Inner Shareable domain for which the value of VTTBR.CnP is 1 and the VMID is the same as the current VMID.

When a TLB combines entries from stage 1 translation and stage 2 translation into a single entry, that entry can only be shared between different PEs if the value of the CnP bit is 1 for both stage 1 and stage 2.

Note

If the value of the VTTBR.CnP bit is 1 on multiple PEs in the same Inner Shareable domain and those VTTBRs do not point to the same translation table entries when the VMID value is the same as the current VMID, then the results of translations are CONSTRAINED UNPREDICTABLE, see 'CONSTRAINED UNPREDICTABLE behaviors due to caching of control or data values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

In a system where the PE resets into EL2 or EL3, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Accessing the VTTBR

Accesses to this register use the following encodings:

```
MRRC{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>
```

coproc	CRm	opc1
0b1111	0b0010	0b0110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x04);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    return VTTBR;
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        return VTTBR;
```

MCRR{<c>}{<q>} <coproc>, {#}<opc1>, <Rt>, <Rt2>, <CRm>

coproc	CRm	opc1
0b1111	0b0010	0b0110

```
if PSTATE.EL == EL0 then
    UNDEFINED;
elsif PSTATE.EL == EL1 then
    if EL2Enabled() && !ELUsingAArch32(EL2) && HSTR_EL2.T2 == '1' then
        AArch64.AArch32SystemAccessTrap(EL2, 0x04);
    elsif EL2Enabled() && ELUsingAArch32(EL2) && HSTR.T2 == '1' then
        AArch32.TakeHypTrapException(0x04);
    else
        UNDEFINED;
elsif PSTATE.EL == EL2 then
    VTTBR = R[t2]:R[t];
elsif PSTATE.EL == EL3 then
    if SCR.NS == '0' then
        UNDEFINED;
    else
        VTTBR = R[t2]:R[t];
```


Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

System Register index by instruction and encoding

Below are indexes for registers and operations accessed in the following ways:

For AArch32

- MCR/MRC
- MCRR/MRRC
- MRS/MSR
- VMRS/VMSR

For AArch64

- AT
- CFP
- CPP
- DC
- DVP
- IC
- MRS/MSR
- TLBI

Registers and operations in AArch32

Accessed using MCR/MRC:

		Register selectors				
coproc	opc1	CRn	CRm	opc2	Name	Description
0b1110	0b000	0b0000	0b0000	0b000	DBGDIDR	Debug ID Register
0b1110	0b000	0b0000	0b0000	0b010	DBGDTRRXext	Debug OS Lo Data Transfe Register, Receive, External View
0b1110	0b000	0b0000	0b0001	0b000	DBGDSCRint	Debug Status and Control Register, Internal View
0b1110	0b000	0b0000	0b0010	0b000	DBGDCCINT	DCC Interrup Enable Regist
0b1110	0b000	0b0000	0b0010	0b010	DBGDSCRext	Debug Status and Control Register, External View
0b1110	0b000	0b0000	0b0011	0b010	DBGDTRTXext	Debug OS Lo Data Transfe Register, Transmit
0b1110	0b000	0b0000	0b0101	0b000	DBGDTRRXint	Debug Data Transfer Register, Receive
0b1110	0b000	0b0000	0b0101	0b000	DBGDTRTXint	Debug Data Transfer Register, Transmit
0b1110	0b000	0b0000	0b0110	0b000	DBGWFAR	Debug Watchpoint

Register selectors						
coproc	opc1	CRn	CRm	opc2	Name	Description
						Fault Address Register
0b1110	0b000	0b0000	0b0110	0b010	DBGOSECCR	Debug OS Lock Exception Catch Control Register
0b1110	0b000	0b0000	0b0111	0b000	DBGVCR	Debug Vector Catch Register
0b1110	0b000	0b0000	n[3:0]	0b100	DBGBVR<n>	Debug Breakpoint Value Register
0b1110	0b000	0b0000	n[3:0]	0b101	DBGBCR<n>	Debug Breakpoint Control Registers
0b1110	0b000	0b0000	n[3:0]	0b110	DBGWVR<n>	Debug Watchpoint Value Register
0b1110	0b000	0b0000	n[3:0]	0b111	DBGWCR<n>	Debug Watchpoint Control Registers
0b1110	0b000	0b0001	0b0000	0b000	DBGDRAR	Debug ROM Address Register
0b1110	0b000	0b0001	0b0000	0b100	DBGOSLAR	Debug OS Lock Access Register
0b1110	0b000	0b0001	0b0001	0b100	DBGOSLSR	Debug OS Lock Status Register
0b1110	0b000	0b0001	0b0011	0b100	DBGOSDLR	Debug OS Double Lock Register
0b1110	0b000	0b0001	0b0100	0b100	DBGPRCR	Debug Power Control Register
0b1110	0b000	0b0001	n[3:0]	0b001	DBGBXVR<n>	Debug Breakpoint Extended Value Registers
0b1110	0b000	0b0010	0b0000	0b000	DBGDSAR	Debug Self Address Register
0b1110	0b000	0b0111	0b0000	0b111	DBGDEVID2	Debug Device ID register 2
0b1110	0b000	0b0111	0b0001	0b111	DBGDEVID1	Debug Device ID register 1
0b1110	0b000	0b0111	0b0010	0b111	DBGDEVID	Debug Device ID register 0
0b1110	0b000	0b0111	0b1000	0b110	DBGCLAIMSET	Debug CLAIM Tag Set register
0b1110	0b000	0b0111	0b1001	0b110	DBGCLAIMCLR	Debug CLAIM Tag Clear register
0b1110	0b000	0b0111	0b1110	0b110	DBGAUTHSTATUS	Debug Authentication Status register
0b1110	0b111	0b0000	0b0000	0b000	JIDR	Jazelle ID Register
0b1110	0b111	0b0001	0b0000	0b000	JOSCR	Jazelle OS Control Register

Register selectors						
coproc	opc1	CRn	CRm	opc2	Name	Description
0b1110	0b111	0b0010	0b0000	0b000	JMCR	Jazelle Main Configuration Register
0b1111	0b000	0b0000	0b0000	0b000	MIDR	Main ID Register
0b1111	0b000	0b0000	0b0000	0b001	CTR	Cache Type Register
0b1111	0b000	0b0000	0b0000	0b010	TCMTR	TCM Type Register
0b1111	0b000	0b0000	0b0000	0b011	TLBTR	TLB Type Register
0b1111	0b000	0b0000	0b0000	0b101	MPIDR	Multiprocesso Affinity Register
0b1111	0b000	0b0000	0b0000	0b110	REVIDR	Revision ID Register
0b1111	0b000	0b0000	0b0001	0b000	ID_PFR0	Processor Feature Register 0
0b1111	0b000	0b0000	0b0001	0b001	ID_PFR1	Processor Feature Register 1
0b1111	0b000	0b0000	0b0001	0b010	ID_DFR0	Debug Featur Register 0
0b1111	0b000	0b0000	0b0001	0b011	ID_AFR0	Auxiliary Feature Register 0
0b1111	0b000	0b0000	0b0001	0b100	ID_MMFR0	Memory Mod Feature Register 0
0b1111	0b000	0b0000	0b0001	0b101	ID_MMFR1	Memory Mod Feature Register 1
0b1111	0b000	0b0000	0b0001	0b110	ID_MMFR2	Memory Mod Feature Register 2
0b1111	0b000	0b0000	0b0001	0b111	ID_MMFR3	Memory Mod Feature Register 3
0b1111	0b000	0b0000	0b0010	0b000	ID_ISAR0	Instruction Se Attribute Register 0
0b1111	0b000	0b0000	0b0010	0b001	ID_ISAR1	Instruction Se Attribute Register 1
0b1111	0b000	0b0000	0b0010	0b010	ID_ISAR2	Instruction Se Attribute Register 2
0b1111	0b000	0b0000	0b0010	0b011	ID_ISAR3	Instruction Se Attribute Register 3
0b1111	0b000	0b0000	0b0010	0b100	ID_ISAR4	Instruction Se Attribute Register 4
0b1111	0b000	0b0000	0b0010	0b101	ID_ISAR5	Instruction Se Attribute Register 5
0b1111	0b000	0b0000	0b0010	0b110	ID_MMFR4	Memory Mod Feature Register 4

Register selectors					Name	Description
coproc	opc1	CRn	CRm	opc2		
0b1111	0b000	0b0000	0b0010	0b111	ID_ISAR6	Instruction Se Attribute Register 6
0b1111	0b000	0b0000	0b0011	0b100	ID_PFR2	Processor Feature Register 2
0b1111	0b000	0b0000	0b0011	0b101	ID_DFR1	Debug Featur Register 1
0b1111	0b000	0b0000	0b0011	0b110	ID_MMFR5	Memory Mod Feature Register 5
0b1111	0b000	0b0001	0b0000	0b000	SCTLR	System Contr Register
0b1111	0b000	0b0001	0b0000	0b001	ACTLR	Auxiliary Control Register
0b1111	0b000	0b0001	0b0000	0b010	CPACR	Architectural Feature Acces Control Register
0b1111	0b000	0b0001	0b0000	0b011	ACTLR2	Auxiliary Control Register 2
0b1111	0b000	0b0001	0b0001	0b000	SCR	Secure Configuration Register
0b1111	0b000	0b0001	0b0001	0b001	SDER	Secure Debug Enable Regist
0b1111	0b000	0b0001	0b0001	0b010	NSACR	Non-Secure Access Contro Register
0b1111	0b000	0b0001	0b0010	0b001	TRFCR	Trace Filter Control Register
0b1111	0b000	0b0001	0b0011	0b001	SDCR	Secure Debug Control Register
0b1111	0b000	0b0010	0b0000	0b000	TTBR0	Translation Table Base Register 0
0b1111	0b000	0b0010	0b0000	0b001	TTBR1	Translation Table Base Register 1
0b1111	0b000	0b0010	0b0000	0b010	TTBCR	Translation Table Base Control Register
0b1111	0b000	0b0010	0b0000	0b011	TTBCR2	Translation Table Base Control Register 2
0b1111	0b000	0b0011	0b0000	0b000	DACR	Domain Acces Control Register
0b1111	0b000	0b0100	0b0110	0b000	ICC_PMR	Interrupt Controller Interrupt Priority Mask Register
0b1111	0b000	0b0101	0b0000	0b000	DFSR	Data Fault Status Regist

Register selectors					Name	Description
coproc	opc1	CRn	CRm	opc2		
0b1111	0b000	0b0101	0b0000	0b001	IFSR	Instruction Fault Status Register
0b1111	0b000	0b0101	0b0001	0b000	ADFSR	Auxiliary Data Fault Status Register
0b1111	0b000	0b0101	0b0001	0b001	AIFSR	Auxiliary Instruction Fault Status Register
0b1111	0b000	0b0101	0b0011	0b000	ERRIDR	Error Record Register
0b1111	0b000	0b0101	0b0011	0b001	ERRSELR	Error Record Select Registe
0b1111	0b000	0b0101	0b0100	0b000	ERXFR	Selected Erro Record Featu Register
0b1111	0b000	0b0101	0b0100	0b001	ERXCTLR	Selected Erro Record Contr Register
0b1111	0b000	0b0101	0b0100	0b010	ERXSTATUS	Selected Erro Record Prima Status Regist
0b1111	0b000	0b0101	0b0100	0b011	ERXADDR	Selected Erro Record Addre Register
0b1111	0b000	0b0101	0b0100	0b100	ERXFR2	Selected Erro Record Featu Register 2
0b1111	0b000	0b0101	0b0100	0b101	ERXCTLR2	Selected Erro Record Contr Register 2
0b1111	0b000	0b0101	0b0100	0b111	ERXADDR2	Selected Erro Record Addre Register 2
0b1111	0b000	0b0101	0b0101	0b000	ERXMISC0	Selected Erro Record Miscellaneous Register 0
0b1111	0b000	0b0101	0b0101	0b001	ERXMISC1	Selected Erro Record Miscellaneous Register 1
0b1111	0b000	0b0101	0b0101	0b010	ERXMISC4	Selected Erro Record Miscellaneous Register 4
0b1111	0b000	0b0101	0b0101	0b011	ERXMISC5	Selected Erro Record Miscellaneous Register 5
0b1111	0b000	0b0101	0b0101	0b100	ERXMISC2	Selected Erro Record Miscellaneous Register 2
0b1111	0b000	0b0101	0b0101	0b101	ERXMISC3	Selected Erro Record Miscellaneous Register 3
0b1111	0b000	0b0101	0b0101	0b110	ERXMISC6	Selected Erro Record

Register selectors						
coproc	opc1	CRn	CRm	opc2	Name	Description
						Miscellaneous Register 6
0b1111	0b000	0b0101	0b0101	0b111	ERXMISC7	Selected Error Record Miscellaneous Register 7
0b1111	0b000	0b0110	0b0000	0b000	DFAR	Data Fault Address Register
0b1111	0b000	0b0110	0b0000	0b010	IFAR	Instruction Fault Address Register
0b1111	0b000	0b0111	0b0001	0b000	ICIALLUIS	Instruction Cache Invalidate All PoU, Inner Shareable
0b1111	0b000	0b0111	0b0001	0b110	BPIALLIS	Branch Predictor Invalidate All, Inner Shareal
0b1111	0b000	0b0111	0b0011	0b100	CFPRCTX	Control Flow Prediction Restriction by Context
0b1111	0b000	0b0111	0b0011	0b101	DVPRCTX	Data Value Prediction Restriction by Context
0b1111	0b000	0b0111	0b0011	0b111	CPPRCTX	Cache Prefetc Prediction Restriction by Context
0b1111	0b000	0b0111	0b0100	0b000	PAR	Physical Address Register
0b1111	0b000	0b0111	0b0101	0b000	ICIALLU	Instruction Cache Invalidate All PoU
0b1111	0b000	0b0111	0b0101	0b001	ICIMVAU	Instruction Cache line Invalidate by VA to PoU
0b1111	0b000	0b0111	0b0101	0b100	CP15ISB	Instruction Synchronizati Barrier Syste instruction
0b1111	0b000	0b0111	0b0101	0b110	BPIALL	Branch Predictor Invalidate All
0b1111	0b000	0b0111	0b0101	0b111	BPIMVA	Branch Predictor Invalidate by VA
0b1111	0b000	0b0111	0b0110	0b001	DCIMVAC	Data Cache li Invalidate by VA to PoC
0b1111	0b000	0b0111	0b0110	0b010	DCISW	Data Cache li Invalidate by Set/Way

Register selectors					Name	Description
coproc	opc1	CRn	CRm	opc2		
0b1111	0b000	0b0111	0b1000	0b000	ATS1CPR	Address Translate Sta 1 Current sta PL1 Read
0b1111	0b000	0b0111	0b1000	0b001	ATS1CPW	Address Translate Sta 1 Current sta PL1 Write
0b1111	0b000	0b0111	0b1000	0b010	ATS1CUR	Address Translate Sta 1 Current sta Unprivileged Read
0b1111	0b000	0b0111	0b1000	0b011	ATS1CUW	Address Translate Sta 1 Current sta Unprivileged Write
0b1111	0b000	0b0111	0b1000	0b100	ATS12NSOPR	Address Translate Stages 1 and Non-secure Only PL1 Rea
0b1111	0b000	0b0111	0b1000	0b101	ATS12NSOPW	Address Translate Stages 1 and Non-secure Only PL1 Writ
0b1111	0b000	0b0111	0b1000	0b110	ATS12NSOUR	Address Translate Stages 1 and Non-secure Only Unprivileged Read
0b1111	0b000	0b0111	0b1000	0b111	ATS12NSOUW	Address Translate Stages 1 and Non-secure Only Unprivileged Write
0b1111	0b000	0b0111	0b1001	0b000	ATS1CPRP	Address Translate Sta 1 Current sta PL1 Read PAN
0b1111	0b000	0b0111	0b1001	0b001	ATS1CPWP	Address Translate Sta 1 Current sta PL1 Write PAI
0b1111	0b000	0b0111	0b1010	0b001	DCCMVAC	Data Cache li Clean by VA t PoC
0b1111	0b000	0b0111	0b1010	0b010	DCCSW	Data Cache li Clean by Set/ Way
0b1111	0b000	0b0111	0b1010	0b100	CP15DSB	Data Synchronizati Barrier Syste instruction
0b1111	0b000	0b0111	0b1010	0b101	CP15DMB	Data Memory Barrier Syste instruction

Register selectors					Name	Description
coproc	opc1	CRn	CRm	opc2		
0b1111	0b000	0b0111	0b1011	0b001	DCCMVAU	Data Cache li Clean by VA t PoU
0b1111	0b000	0b0111	0b1110	0b001	DCCIMVAC	Data Cache li Clean and Invalidate by VA to PoC
0b1111	0b000	0b0111	0b1110	0b010	DCCISW	Data Cache li Clean and Invalidate by Set/Way
0b1111	0b000	0b1000	0b0011	0b000	TLBIALLIS	TLB Invalidat All, Inner Shareable
0b1111	0b000	0b1000	0b0011	0b001	TLBIMVAIS	TLB Invalidat by VA, Inner Shareable
0b1111	0b000	0b1000	0b0011	0b010	TLBIASIDIS	TLB Invalidat by ASID matc Inner Shareal
0b1111	0b000	0b1000	0b0011	0b011	TLBIMVAAIS	TLB Invalidat by VA, All ASI Inner Shareal
0b1111	0b000	0b1000	0b0011	0b101	TLBIMVALIS	TLB Invalidat by VA, Last level, Inner Shareable
0b1111	0b000	0b1000	0b0011	0b111	TLBIMVAALIS	TLB Invalidat by VA, All ASI Last level, Inner Shareal
0b1111	0b000	0b1000	0b0101	0b000	ITLBIALL	Instruction TI Invalidate All
0b1111	0b000	0b1000	0b0101	0b001	ITLBIMVA	Instruction TI Invalidate by VA
0b1111	0b000	0b1000	0b0101	0b010	ITLBIASID	Instruction TI Invalidate by ASID match
0b1111	0b000	0b1000	0b0110	0b000	DTLBIALL	Data TLB Invalidate All
0b1111	0b000	0b1000	0b0110	0b001	DTLBIMVA	Data TLB Invalidate by VA
0b1111	0b000	0b1000	0b0110	0b010	DTLBIASID	Data TLB Invalidate by ASID match
0b1111	0b000	0b1000	0b0111	0b000	TLBIALL	TLB Invalidat All
0b1111	0b000	0b1000	0b0111	0b001	TLBIMVA	TLB Invalidat by VA
0b1111	0b000	0b1000	0b0111	0b010	TLBIASID	TLB Invalidat by ASID matc
0b1111	0b000	0b1000	0b0111	0b011	TLBIMVAA	TLB Invalidat by VA, All ASI
0b1111	0b000	0b1000	0b0111	0b101	TLBIMVAL	TLB Invalidat by VA, Last level
0b1111	0b000	0b1000	0b0111	0b111	TLBIMVAAL	TLB Invalidat by VA, All ASI Last level

Register selectors						
coproc	opc1	CRn	CRm	opc2	Name	Description
0b1111	0b000	0b1001	0b1100	0b000	PMCR	Performance Monitors Control Register
0b1111	0b000	0b1001	0b1100	0b001	PMCNTENSET	Performance Monitors Cou Enable Set register
0b1111	0b000	0b1001	0b1100	0b010	PMCNTENCLR	Performance Monitors Cou Enable Clear register
0b1111	0b000	0b1001	0b1100	0b011	PMOVSR	Performance Monitors Overflow Flag Status Regist
0b1111	0b000	0b1001	0b1100	0b100	PMSWINC	Performance Monitors Software Increment register
0b1111	0b000	0b1001	0b1100	0b101	PMSELR	Performance Monitors Eve Counter Selection Register
0b1111	0b000	0b1001	0b1100	0b110	PMCEID0	Performance Monitors Common Eve Identification register 0
0b1111	0b000	0b1001	0b1100	0b111	PMCEID1	Performance Monitors Common Eve Identification register 1
0b1111	0b000	0b1001	0b1101	0b000	PMCCNTR	Performance Monitors Cyc Count Regist
0b1111	0b000	0b1001	0b1101	0b001	PMXEVTYPER	Performance Monitors Selected Eve Type Register
0b1111	0b000	0b1001	0b1101	0b010	PMXEVCNTR	Performance Monitors Selected Eve Count Regist
0b1111	0b000	0b1001	0b1110	0b000	PMUSERENR	Performance Monitors Use Enable Regist
0b1111	0b000	0b1001	0b1110	0b001	PMINTENSET	Performance Monitors Interrupt Enable Set register
0b1111	0b000	0b1001	0b1110	0b010	PMINTENCLR	Performance Monitors Interrupt Enable Clear register
0b1111	0b000	0b1001	0b1110	0b011	PMOVSSET	Performance Monitors Overflow Flag

Register selectors						
coproc	opc1	CRn	CRm	opc2	Name	Description
						Status Set register
0b1111	0b000	0b1001	0b1110	0b100	PMCEID2	Performance Monitors Common Even Identification register 2
0b1111	0b000	0b1001	0b1110	0b101	PMCEID3	Performance Monitors Common Even Identification register 3
0b1111	0b000	0b1001	0b1110	0b110	PMMIR	Performance Monitors Machine Identification Register
0b1111	0b000	0b1010	0b0011	0b000	AMAIR0	Auxiliary Memory Attribute Indirection Register 0
0b1111	0b000	0b1010	0b0011	0b001	AMAIR1	Auxiliary Memory Attribute Indirection Register 1
0b1111	0b000	0b1100	0b0000	0b000	VBAR	Vector Base Address Register
0b1111	0b000	0b1100	0b0000	0b010	RMR	Reset Management Register
0b1111	0b000	0b1100	0b0001	0b000	ISR	Interrupt Status Regist
0b1111	0b000	0b1100	0b0001	0b001	DISR	Deferred Interrupt Status Regist
0b1111	0b000	0b1100	0b1000	0b000	ICC_IAR0	Interrupt Controller Interrupt Acknowledge Register 0
0b1111	0b000	0b1100	0b1000	0b001	ICC_EOIR0	Interrupt Controller En Of Interrupt Register 0
0b1111	0b000	0b1100	0b1000	0b010	ICC_HPPIR0	Interrupt Controller Highest Prior Pending Interrupt Register 0
0b1111	0b000	0b1100	0b1000	0b011	ICC_BPR0	Interrupt Controller Binary Point Register 0
0b1111	0b000	0b1100	0b1000	0b1:n[1:0]	ICC_AP0R<n>	Interrupt Controller Active Priorit Group 0 Registers

Register selectors					Name	Description
coproc	opc1	CRn	CRm	opc2		
0b1111	0b000	0b1100	0b1001	0b0:n[1:0]	ICC_AP1R<n>	Interrupt Controller Active Priorit Group 1 Registers
0b1111	0b000	0b1100	0b1011	0b001	ICC_DIR	Interrupt Controller Deactivate Interrupt Register
0b1111	0b000	0b1100	0b1011	0b011	ICC_RPR	Interrupt Controller Running Priority Register
0b1111	0b000	0b1100	0b1100	0b000	ICC_IAR1	Interrupt Controller Interrupt Acknowledge Register 1
0b1111	0b000	0b1100	0b1100	0b001	ICC_EOIR1	Interrupt Controller En Of Interrupt Register 1
0b1111	0b000	0b1100	0b1100	0b010	ICC_HPPIR1	Interrupt Controller Highest Prior Pending Interrupt Register 1
0b1111	0b000	0b1100	0b1100	0b011	ICC_BPR1	Interrupt Controller Binary Point Register 1
0b1111	0b000	0b1100	0b1100	0b100	ICC_CTLR	Interrupt Controller Control Register
0b1111	0b000	0b1100	0b1100	0b101	ICC_SRE	Interrupt Controller System Register Enab register
0b1111	0b000	0b1100	0b1100	0b110	ICC_IGRPEN0	Interrupt Controller Interrupt Gro 0 Enable register
0b1111	0b000	0b1100	0b1100	0b111	ICC_IGRPEN1	Interrupt Controller Interrupt Gro 1 Enable register
0b1111	0b000	0b1101	0b0000	0b000	FCSEIDR	FCSE Process ID register
0b1111	0b000	0b1101	0b0000	0b001	CONTEXTIDR	Context ID Register
0b1111	0b000	0b1101	0b0000	0b010	TPIDRURW	PL0 Read/Wri Software Thread ID Register
0b1111	0b000	0b1101	0b0000	0b011	TPIDRURO	PL0 Read-Onl Software

Register selectors						
coproc	opc1	CRn	CRm	opc2	Name	Description
						Thread ID Register
0b1111	0b000	0b1101	0b0000	0b100	TPIDRPRW	PL1 Software Thread ID Register
0b1111	0b000	0b1101	0b0010	0b000	AMCR	Activity Monitors Control Register
0b1111	0b000	0b1101	0b0010	0b001	AMCFGR	Activity Monitors Configuration Register
0b1111	0b000	0b1101	0b0010	0b010	AMCGCR	Activity Monitors Counter Grou Configuration Register
0b1111	0b000	0b1101	0b0010	0b011	AMUSERENR	Activity Monitors Use Enable Regist
0b1111	0b000	0b1101	0b0010	0b100	AMCNTENCLR0	Activity Monitors Cou Enable Clear Register 0
0b1111	0b000	0b1101	0b0010	0b101	AMCNTENSET0	Activity Monitors Cou Enable Set Register 0
0b1111	0b000	0b1101	0b0011	0b000	AMCNTENCLR1	Activity Monitors Cou Enable Clear Register 1
0b1111	0b000	0b1101	0b0011	0b001	AMCNTENSET1	Activity Monitors Cou Enable Set Register 1
0b1111	0b000	0b1101	0b011:n[3]	n[2:0]	AMEVTYPER0<n>	Activity Monitors Eve Type Register 0
0b1111	0b000	0b1101	0b111:n[3]	n[2:0]	AMEVTYPER1<n>	Activity Monitors Eve Type Register 1
0b1111	0b000	0b1110	0b0000	0b000	CNTFRQ	Counter-timer Frequency register
0b1111	0b000	0b1110	0b0001	0b000	CNTKCTL	Counter-timer Kernel Contro register
0b1111	0b000	0b1110	0b0010	0b000	CNTP_TVAL	Counter-timer Physical Time TimerValue register
0b1111	0b000	0b1110	0b0010	0b001	CNTP_CTL	Counter-timer Physical Time Control regist
0b1111	0b000	0b1110	0b0011	0b000	CNTV_TVAL	Counter-timer Virtual Timer TimerValue register

Register selectors						
coproc	opc1	CRn	CRm	opc2	Name	Description
0b1111	0b000	0b1110	0b0011	0b001	CNTV_CTL	Counter-timer Virtual Timer Control regist
0b1111	0b000	0b1110	0b10:n[4:3]	n[2:0]	PMEVCNTR<n>	Performance Monitors Eve Count Registe
0b1111	0b000	0b1110	0b1111	0b111	PMCCFILTR	Performance Monitors Cyc Count Filter Register
0b1111	0b000	0b1110	0b11:n[4:3]	n[2:0]	PMEVTYPER<n>	Performance Monitors Eve Type Register
0b1111	0b001	0b0000	0b0000	0b000	CCSIDR	Current Cach Size ID Register
0b1111	0b001	0b0000	0b0000	0b001	CLIDR	Cache Level I Register
0b1111	0b001	0b0000	0b0000	0b010	CCSIDR2	Current Cach Size ID Register 2
0b1111	0b001	0b0000	0b0000	0b111	AIDR	Auxiliary ID Register
0b1111	0b010	0b0000	0b0000	0b000	CSSELR	Cache Size Selection Register
0b1111	0b011	0b0100	0b0101	0b000	DSPSR	Debug Saved Program Stat Register
0b1111	0b011	0b0100	0b0101	0b001	DLR	Debug Link Register
0b1111	0b100	0b0000	0b0000	0b000	VPIDR	Virtualization Processor ID Register
0b1111	0b100	0b0000	0b0000	0b101	VMPIDR	Virtualization Multiprocesso ID Register
0b1111	0b100	0b0001	0b0000	0b000	HSCTLR	Hyp System Control Register
0b1111	0b100	0b0001	0b0000	0b001	HACTLR	Hyp Auxiliary Control Register
0b1111	0b100	0b0001	0b0000	0b011	HACTLR2	Hyp Auxiliary Control Register 2
0b1111	0b100	0b0001	0b0001	0b000	HCR	Hyp Configuration Register
0b1111	0b100	0b0001	0b0001	0b001	HDCR	Hyp Debug Control Register
0b1111	0b100	0b0001	0b0001	0b010	HCPTR	Hyp Architectural Feature Trap Register
0b1111	0b100	0b0001	0b0001	0b011	HSTR	Hyp System Trap Register
0b1111	0b100	0b0001	0b0001	0b100	HCR2	Hyp Configuration Register 2

Register selectors					Name	Description
coproc	opc1	CRn	CRm	opc2		
0b1111	0b100	0b0001	0b0001	0b111	HACR	Hyp Auxiliary Configuration Register
0b1111	0b100	0b0001	0b0010	0b001	HTRFCR	Hyp Trace Filter Control Register
0b1111	0b100	0b0010	0b0000	0b010	HTCR	Hyp Translati Control Register
0b1111	0b100	0b0010	0b0001	0b010	VTCR	Virtualization Translation Control Register
0b1111	0b100	0b0101	0b0001	0b000	HADFSR	Hyp Auxiliary Data Fault Status Regist
0b1111	0b100	0b0101	0b0001	0b001	HAIFSR	Hyp Auxiliary Instruction Fault Status Register
0b1111	0b100	0b0101	0b0010	0b000	HSR	Hyp Syndrom Register
0b1111	0b100	0b0101	0b0010	0b011	VDFSR	Virtual SErro Exception Syndrome Register
0b1111	0b100	0b0110	0b0000	0b000	HDFAR	Hyp Data Fau Address Register
0b1111	0b100	0b0110	0b0000	0b010	HIFAR	Hyp Instructi Fault Address Register
0b1111	0b100	0b0110	0b0000	0b100	HPFAR	Hyp IPA Fault Address Register
0b1111	0b100	0b0111	0b1000	0b000	ATS1HR	Address Translate Sta 1 Hyp mode Read
0b1111	0b100	0b0111	0b1000	0b001	ATS1HW	Address Translate Sta 1 Hyp mode Write
0b1111	0b100	0b1000	0b0000	0b001	TLBIIPAS2IS	TLB Invalidat by Intermedia Physical Address, Stag 2, Inner Shareable
0b1111	0b100	0b1000	0b0000	0b101	TLBIIPAS2LIS	TLB Invalidat by Intermedia Physical Address, Stag 2, Last level, Inner Shareal
0b1111	0b100	0b1000	0b0011	0b000	TLBIALLHIS	TLB Invalidat All, Hyp mode Inner Shareal
0b1111	0b100	0b1000	0b0011	0b001	TLBIMVAHIS	TLB Invalidat by VA, Hyp mode, Inner Shareable

Register selectors					Name	Description
coproc	opc1	CRn	CRm	opc2		
0b1111	0b100	0b1000	0b0011	0b100	TLBIALLNSNHIS	TLB Invalidat All, Non-Secu Non-Hyp, Inn Shareable
0b1111	0b100	0b1000	0b0011	0b101	TLBIMVALHIS	TLB Invalidat by VA, Last level, Hyp mode, Inner Shareable
0b1111	0b100	0b1000	0b0100	0b001	TLBIIPAS2	TLB Invalidat by Intermedia Physical Address, Stag 2
0b1111	0b100	0b1000	0b0100	0b101	TLBIIPAS2L	TLB Invalidat by Intermedia Physical Address, Stag 2, Last level
0b1111	0b100	0b1000	0b0111	0b000	TLBIALLH	TLB Invalidat All, Hyp mode
0b1111	0b100	0b1000	0b0111	0b001	TLBIMVAH	TLB Invalidat by VA, Hyp mode
0b1111	0b100	0b1000	0b0111	0b100	TLBIALLNSNH	TLB Invalidat All, Non-Secu Non-Hyp
0b1111	0b100	0b1000	0b0111	0b101	TLBIMVALH	TLB Invalidat by VA, Last level, Hyp mo
0b1111	0b100	0b1010	0b0010	0b000	HMAIR0	Hyp Memory Attribute Indirection Register 0
0b1111	0b100	0b1010	0b0010	0b001	HMAIR1	Hyp Memory Attribute Indirection Register 1
0b1111	0b100	0b1010	0b0011	0b000	HAMAIR0	Hyp Auxiliary Memory Attribute Indirection Register 0
0b1111	0b100	0b1010	0b0011	0b001	HAMAIR1	Hyp Auxiliary Memory Attribute Indirection Register 1
0b1111	0b100	0b1100	0b0000	0b000	HVBAR	Hyp Vector Base Address Register
0b1111	0b100	0b1100	0b0000	0b010	HRMR	Hyp Reset Management Register
0b1111	0b100	0b1100	0b0001	0b001	VDISR	Virtual Deferred Interrupt Status Regist
0b1111	0b100	0b1100	0b1000	0b0:n[1:0]	ICH_AP0R<n>	Interrupt Controller Hy Active Priorit Group 0 Registers

Register selectors					Name	Description
coproc	opc1	CRn	CRm	opc2		
0b1111	0b100	0b1100	0b1001	0b0:n[1:0]	ICH_AP1R<n>	Interrupt Controller Hy Active Priorit Group 1 Registers
0b1111	0b100	0b1100	0b1001	0b101	ICC_HSRE	Interrupt Controller Hy System Register Enab register
0b1111	0b100	0b1100	0b1011	0b000	ICH_HCR	Interrupt Controller Hy Control Register
0b1111	0b100	0b1100	0b1011	0b001	ICH_VTR	Interrupt Controller VG Type Register
0b1111	0b100	0b1100	0b1011	0b010	ICH_MISR	Interrupt Controller Maintenance Interrupt Stat Register
0b1111	0b100	0b1100	0b1011	0b011	ICH_EISR	Interrupt Controller En of Interrupt Status Regist
0b1111	0b100	0b1100	0b1011	0b101	ICH_ELRSR	Interrupt Controller Empty List Register Statu Register
0b1111	0b100	0b1100	0b1011	0b111	ICH_VMCR	Interrupt Controller Virtual Machi Control Register
0b1111	0b100	0b1100	0b110:n[3]	n[2:0]	ICH_LR<n>	Interrupt Controller Lis Registers
0b1111	0b100	0b1100	0b111:n[3]	n[2:0]	ICH_LRC<n>	Interrupt Controller Lis Registers
0b1111	0b100	0b1101	0b0000	0b010	HTPIDR	Hyp Software Thread ID Register
0b1111	0b100	0b1110	0b0001	0b000	CNTHCTL	Counter-timer Hyp Control register
0b1111	0b100	0b1110	0b0010	0b000	CNTHP_TVAL	Counter-timer Hyp Physical Timer TimerValue register
0b1111	0b100	0b1110	0b0010	0b001	CNTHP_CTL	Counter-timer Hyp Physical Timer Contro register
0b1111	0b110	0b1100	0b1100	0b100	ICC_MCTLR	Interrupt Controller Monitor Cont Register
0b1111	0b110	0b1100	0b1100	0b101	ICC_MSRE	Interrupt Controller

Register selectors					Name	Description
coproc	opc1	CRn	CRm	opc2		
						Monitor Syste Register Enab register
0b1111	0b110	0b1100	0b1100	0b111	ICC_MGRPEN1	Interrupt Controller Monitor Interrupt Gro 1 Enable register

Accessed using MCRR/MRRC:

Register selectors			Name	Description
coproc	CRm	opc1		
0b1110	0b0001	0b0000	DBGDRAR	Debug ROM Address Register
0b1110	0b0010	0b0000	DBGDSAR	Debug Self Address Register
0b1111	0b000:n[3]	0b0:n[2:0]	AMEVCNTR0<n>	Activity Monitors Event Counter Registers 0
0b1111	0b0010	0b0000	TTBR0	Translation Table Base Register 0
0b1111	0b0010	0b0001	TTBR1	Translation Table Base Register 1
0b1111	0b0010	0b0100	HTTBR	Hyp Translation Table Base Register
0b1111	0b0010	0b0110	VTTBR	Virtualization Translation Table Base Register
0b1111	0b010:n[3]	0b0:n[2:0]	AMEVCNTR1<n>	Activity Monitors Event Counter Registers 1
0b1111	0b0111	0b0000	PAR	Physical Address Register
0b1111	0b1001	0b0000	PMCCNTR	Performance Monitors Cycle Count Register
0b1111	0b1100	0b0000	ICC_SGI1R	Interrupt Controller Software Generated Interrupt Group 1 Register
0b1111	0b1100	0b0001	ICC_ASGI1R	Interrupt Controller Alias Software Generated Interrupt Group 1 Register
0b1111	0b1100	0b0010	ICC_SGI0R	Interrupt Controller Software Generated Interrupt Group 0 Register
0b1111	0b1110	0b0000	CNTPCT	Counter-timer Physical Count register
0b1111	0b1110	0b0001	CNTVCT	Counter-timer Virtual Count register
0b1111	0b1110	0b0010	CNTP_CVAL	Counter-timer Physical Timer CompareValue register
0b1111	0b1110	0b0011	CNTV_CVAL	Counter-timer Virtual Timer CompareValue register
0b1111	0b1110	0b0100	CNTVOFF	Counter-timer Virtual Offset register
0b1111	0b1110	0b0110	CNTHP_CVAL	Counter-timer Hyp Physical CompareValue register
0b1111	0b1110	0b1000	CNTPCTSS	Counter-timer Self-Synchronized Physical Count register
0b1111	0b1110	0b1001	CNTVCTSS	Counter-timer Self-Synchronized Virtual Count register

Accessed using MRS/MSR:

Register selectors			Name	Description
R	M	M1		
0b0	0b1	0b1110	ELR_hyp	Exception Link Register (Hyp mode)

Register selectors			Name	Description
R	M	M1		
0b1	0b0	0b1110	SPSR_fiq	Saved Program Status Register (FIQ mode)
0b1	0b1	0b0000	SPSR_irq	Saved Program Status Register (IRQ mode)
0b1	0b1	0b0010	SPSR_svc	Saved Program Status Register (Supervisor mode)
0b1	0b1	0b0100	SPSR_abt	Saved Program Status Register (Abort mode)
0b1	0b1	0b0110	SPSR_und	Saved Program Status Register (Undefined mode)
0b1	0b1	0b1100	SPSR_mon	Saved Program Status Register (Monitor mode)
0b1	0b1	0b1110	SPSR_hyp	Saved Program Status Register (Hyp mode)

Accessed using VMRS/VMSR:

Register selectors	Name	Description
reg		
0b0000	FPSID	Floating-Point System ID register
0b0001	FPSCR	Floating-Point Status and Control Register
0b0101	MVFR2	Media and VFP Feature Register 2
0b0110	MVFR1	Media and VFP Feature Register 1
0b0111	MVFR0	Media and VFP Feature Register 0
0b1000	FPEXC	Floating-Point Exception Control register

Registers and operations in AArch64

Accessed using AT:

Register selectors					Name	Description
op0	op1	CRn	CRm	op2		
0b01	0b000	0b0111	0b1000	0b000	AT S1E1R	Address Translate Stage 1 EL1 Read
0b01	0b000	0b0111	0b1000	0b001	AT S1E1W	Address Translate Stage 1 EL1 Write
0b01	0b000	0b0111	0b1000	0b010	AT S1E0R	Address Translate Stage 1 EL0 Read
0b01	0b000	0b0111	0b1000	0b011	AT S1E0W	Address Translate Stage 1 EL0 Write
0b01	0b000	0b0111	0b1001	0b000	AT S1E1RP	Address Translate Stage 1 EL1 Read PAN
0b01	0b000	0b0111	0b1001	0b001	AT S1E1WP	Address Translate Stage 1 EL1 Write PAN
0b01	0b100	0b0111	0b1000	0b000	AT S1E2R	Address Translate Stage 1 EL2 Read
0b01	0b100	0b0111	0b1000	0b001	AT S1E2W	Address Translate Stage 1 EL2 Write
0b01	0b100	0b0111	0b1000	0b100	AT S12E1R	Address Translate Stages 1 and 2 EL1 Read
0b01	0b100	0b0111	0b1000	0b101	AT S12E1W	Address Translate Stages 1 and 2 EL1 Write
0b01	0b100	0b0111	0b1000	0b110	AT S12E0R	Address Translate Stages 1 and 2 EL0 Read
0b01	0b100	0b0111	0b1000	0b111	AT S12E0W	Address Translate Stages 1 and 2 EL0 Write
0b01	0b110	0b0111	0b1000	0b000	AT S1E3R	Address Translate Stage 1 EL3 Read
0b01	0b110	0b0111	0b1000	0b001	AT S1E3W	Address Translate Stage 1 EL3 Write

Accessed using CFP:

Register selectors					Name	Description
op0	op1	CRn	CRm	op2		
0b01	0b011	0b0111	0b0011	0b100	CFP RCTX	Control Flow Prediction Restriction by Context

Accessed using CPP:

Register selectors					Name	Description
op0	op1	CRn	CRm	op2		
0b01	0b011	0b0111	0b0011	0b111	CPP RCTX	Cache Prefetch Prediction Restriction by Context

Accessed using DC:

Register selectors					Name	Description
op0	op1	CRn	CRm	op2		
0b01	0b000	0b0111	0b0110	0b001	DC IVAC	Data or unified Cache line Invalidate by VA to PoC
0b01	0b000	0b0111	0b0110	0b010	DC ISW	Data or unified Cache line Invalidate by Set/Way
0b01	0b000	0b0111	0b0110	0b011	DC IGVAC	Data, Allocation Tag or unified Cache line Invalidate of Allocation Tags by VA to PoC
0b01	0b000	0b0111	0b0110	0b100	DC IGSW	Data, Allocation Tag or unified Cache line Invalidate of Allocation Tags by Set/Way
0b01	0b000	0b0111	0b0110	0b101	DC IGDVAC	Data, Allocation Tag or unified Cache line Invalidate of Allocation Tags by VA to PoC
0b01	0b000	0b0111	0b0110	0b110	DC IGDSW	Data, Allocation Tag or unified Cache line Invalidate of Data and Allocation Tags by Set/Way
0b01	0b000	0b0111	0b1010	0b010	DC CSW	Data or unified Cache line Clean by Set/Way
0b01	0b000	0b0111	0b1010	0b100	DC CGSW	Data, Allocation Tag or unified Cache line Clean of Allocation Tags by Set/Way
0b01	0b000	0b0111	0b1010	0b110	DC CGDSW	Data, Allocation Tag or unified Cache line Clean of Data and Allocation Tags by Set/Way
0b01	0b000	0b0111	0b1110	0b010	DC CISW	Data or unified Cache line Clean and Invalidate by Set/Way
0b01	0b000	0b0111	0b1110	0b100	DC CIGSW	Data, Allocation Tag or unified Cache line Clean and Invalidate of Allocation Tags by Set/Way
0b01	0b000	0b0111	0b1110	0b110	DC CIGDSW	Data, Allocation Tag or unified Cache line Clean and Invalidate of Data and Allocation Tags by Set/Way
0b01	0b011	0b0111	0b0100	0b001	DC ZVA	Data Cache Zero by VA
0b01	0b011	0b0111	0b0100	0b011	DC GVA	Data Cache set Allocation Tag by VA
0b01	0b011	0b0111	0b0100	0b100	DC GZVA	Data Cache set Allocation Tags and Zero by VA
0b01	0b011	0b0111	0b1010	0b001	DC CVAC	Data or unified Cache line Clean by VA to PoC

Register selectors					Name	Description
op0	op1	CRn	CRm	op2		
0b01	0b011	0b0111	0b1010	0b011	DC CGVAC	Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoC
0b01	0b011	0b0111	0b1010	0b101	DC CGDVAC	Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoC
0b01	0b011	0b0111	0b1011	0b001	DC CVAU	Data or unified Cache line Clean by VA to PoU
0b01	0b011	0b0111	0b1100	0b001	DC CVAP	Data or unified Cache line Clean by VA to PoP
0b01	0b011	0b0111	0b1100	0b011	DC CGVAP	Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoP
0b01	0b011	0b0111	0b1100	0b101	DC CGDVAP	Data, Allocation Tag or unified Cache line Clean of Data and Allocation Tags by VA to PoP
0b01	0b011	0b0111	0b1101	0b001	DC CVADP	Data or unified Cache line Clean by VA to PoDP
0b01	0b011	0b0111	0b1101	0b011	DC CGVADP	Data, Allocation Tag or unified Cache line Clean of Data and Allocation Tags by VA to PoDP
0b01	0b011	0b0111	0b1101	0b101	DC CGDVADP	Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoDP
0b01	0b011	0b0111	0b1110	0b001	DC CIVAC	Data or unified Cache line Clean and Invalidate by VA to PoC
0b01	0b011	0b0111	0b1110	0b011	DC CIGVAC	Data, Allocation Tag or unified Cache line Clean and Invalidate of Allocation Tags by VA to PoC
0b01	0b011	0b0111	0b1110	0b101	DC CIGDVAC	Data, Allocation Tag or unified Cache line Clean and Invalidate of Data and Allocation Tags by VA to PoC

Accessed using DVP:

Register selectors					Name	Description
op0	op1	CRn	CRm	op2		
0b01	0b011	0b0111	0b0011	0b101	DVP RCTX	Data Value Prediction Restriction by Context

Accessed using IC:

Register selectors						Name	Description
op0	op1	CRn	CRm	op2	Rt		
0b01	0b000	0b0111	0b0001	0b000	0b11111	IC IALLUIS	Instruction Cache Invalidate All to PoU, Inner Shareable
0b01	0b000	0b0111	0b0101	0b000	0b11111	IC IALLU	Instruction Cache Invalidate All to PoU
0b01	0b011	0b0111	0b0101	0b001	-	IC IVAU	Instruction Cache line Invalidate by VA to PoU

Accessed using MRS/MSR:

Register selectors						
op0	op1	CRn	CRm	op2	Name	Descri
0b10	0b000	0b0000	0b0000	0b010	OSDTRRX_EL1	OS Lock Transfer Register Receive
0b10	0b000	0b0000	0b0010	0b000	MDCCINT_EL1	Monitor Interrup Enable Register
0b10	0b000	0b0000	0b0010	0b010	MDSCR_EL1	Monitor Debug S Control Register
0b10	0b000	0b0000	0b0011	0b010	OSDTRTX_EL1	OS Lock Transfer Register Transmi
0b10	0b000	0b0000	0b0110	0b010	OSECCR_EL1	OS Lock Exceptio Catch C Register
0b10	0b000	0b0000	n[3:0]	0b100	DBGBVR<n>_EL1	Debug Breakpo Value Register
0b10	0b000	0b0000	n[3:0]	0b101	DBGBCR<n>_EL1	Debug Breakpo Control Register
0b10	0b000	0b0000	n[3:0]	0b110	DBGWVR<n>_EL1	Debug Watchpo Value Register
0b10	0b000	0b0000	n[3:0]	0b111	DBGWCR<n>_EL1	Debug Watchpo Control Register
0b10	0b000	0b0001	0b0000	0b000	MDRAR_EL1	Monitor Debug R Address Register
0b10	0b000	0b0001	0b0000	0b100	OSLAR_EL1	OS Lock Access Register
0b10	0b000	0b0001	0b0001	0b100	OSLSR_EL1	OS Lock Status Register
0b10	0b000	0b0001	0b0011	0b100	OSDLR_EL1	OS Doub Lock Re
0b10	0b000	0b0001	0b0100	0b100	DBGPRCR_EL1	Debug P Control Register
0b10	0b000	0b0111	0b1000	0b110	DBGCLAIMSET_EL1	Debug C Tag Set register
0b10	0b000	0b0111	0b1001	0b110	DBGCLAIMCLR_EL1	Debug C Tag Clea register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b10	0b000	0b0111	0b1110	0b110	DBGAUTHSTATUS_EL1	Debug Authenti Status re
0b10	0b011	0b0000	0b0001	0b000	MDCCSR_EL0	Monitor Status Register
0b10	0b011	0b0000	0b0100	0b000	DBGDTR_EL0	Debug D Transfer Register duplex
0b10	0b011	0b0000	0b0101	0b000	DBGDTRRX_EL0	Debug D Transfer Register Receive
0b10	0b011	0b0000	0b0101	0b000	DBGDTRTX_EL0	Debug D Transfer Register Transmi
0b10	0b100	0b0000	0b0111	0b000	DBGVCR32_EL2	Debug V Catch Re
0b11	0b000	0b0000	0b0000	0b000	MIDR_EL1	Main ID Register
0b11	0b000	0b0000	0b0000	0b101	MPIDR_EL1	Multipro Affinity Register
0b11	0b000	0b0000	0b0000	0b110	REVIDR_EL1	Revision Register
0b11	0b000	0b0000	0b0001	0b000	ID_PFR0_EL1	AArch32 Processo Feature Register
0b11	0b000	0b0000	0b0001	0b001	ID_PFR1_EL1	AArch32 Processo Feature Register
0b11	0b000	0b0000	0b0001	0b010	ID_DFR0_EL1	AArch32 Debug F Register
0b11	0b000	0b0000	0b0001	0b011	ID_AFR0_EL1	AArch32 Auxiliary Feature Register
0b11	0b000	0b0000	0b0001	0b100	ID_MMFR0_EL1	AArch32 Memory Model F Register
0b11	0b000	0b0000	0b0001	0b101	ID_MMFR1_EL1	AArch32 Memory Model F Register
0b11	0b000	0b0000	0b0001	0b110	ID_MMFR2_EL1	AArch32 Memory Model F Register
0b11	0b000	0b0000	0b0001	0b111	ID_MMFR3_EL1	AArch32 Memory Model F Register
0b11	0b000	0b0000	0b0010	0b000	ID_ISAR0_EL1	AArch32 Instructi Attribute Register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b000	0b0000	0b0010	0b001	ID_ISAR1_EL1	AArch32 Instructi Attribute Register
0b11	0b000	0b0000	0b0010	0b010	ID_ISAR2_EL1	AArch32 Instructi Attribute Register
0b11	0b000	0b0000	0b0010	0b011	ID_ISAR3_EL1	AArch32 Instructi Attribute Register
0b11	0b000	0b0000	0b0010	0b100	ID_ISAR4_EL1	AArch32 Instructi Attribute Register
0b11	0b000	0b0000	0b0010	0b101	ID_ISAR5_EL1	AArch32 Instructi Attribute Register
0b11	0b000	0b0000	0b0010	0b110	ID_MMFR4_EL1	AArch32 Memory Model F Register
0b11	0b000	0b0000	0b0010	0b111	ID_ISAR6_EL1	AArch32 Instructi Attribute Register
0b11	0b000	0b0000	0b0011	0b000	MVFR0_EL1	AArch32 Media a VFP Fea Register
0b11	0b000	0b0000	0b0011	0b001	MVFR1_EL1	AArch32 Media a VFP Fea Register
0b11	0b000	0b0000	0b0011	0b010	MVFR2_EL1	AArch32 Media a VFP Fea Register
0b11	0b000	0b0000	0b0011	0b100	ID_PFR2_EL1	AArch32 Processo Feature Register
0b11	0b000	0b0000	0b0011	0b101	ID_DFR1_EL1	Debug F Register
0b11	0b000	0b0000	0b0011	0b110	ID_MMFR5_EL1	AArch32 Memory Model F Register
0b11	0b000	0b0000	0b0100	0b000	ID_AA64PFR0_EL1	AArch64 Processo Feature Register
0b11	0b000	0b0000	0b0100	0b001	ID_AA64PFR1_EL1	AArch64 Processo Feature Register
0b11	0b000	0b0000	0b0100	0b100	ID_AA64ZFR0_EL1	SVE Fea ID regist

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b000	0b0000	0b0101	0b000	ID_AA64DFR0_EL1	AArch64 Debug F Register
0b11	0b000	0b0000	0b0101	0b001	ID_AA64DFR1_EL1	AArch64 Debug F Register
0b11	0b000	0b0000	0b0101	0b100	ID_AA64AFR0_EL1	AArch64 Auxiliary Feature Register
0b11	0b000	0b0000	0b0101	0b101	ID_AA64AFR1_EL1	AArch64 Auxiliary Feature Register
0b11	0b000	0b0000	0b0110	0b000	ID_AA64ISAR0_EL1	AArch64 Instructi Attribute Register
0b11	0b000	0b0000	0b0110	0b001	ID_AA64ISAR1_EL1	AArch64 Instructi Attribute Register
0b11	0b000	0b0000	0b0111	0b000	ID_AA64MMFR0_EL1	AArch64 Memory Model F Register
0b11	0b000	0b0000	0b0111	0b001	ID_AA64MMFR1_EL1	AArch64 Memory Model F Register
0b11	0b000	0b0000	0b0111	0b010	ID_AA64MMFR2_EL1	AArch64 Memory Model F Register
0b11	0b000	0b0001	0b0000	0b000	SCTLR_EL1	System Control Register
0b11	0b000	0b0001	0b0000	0b001	ACTLR_EL1	Auxiliary Control Register
0b11	0b000	0b0001	0b0000	0b010	CPACR_EL1	Architec Feature Access C Register
0b11	0b000	0b0001	0b0000	0b101	RGSR_EL1	Random Allocatio Seed Re
0b11	0b000	0b0001	0b0000	0b110	GCR_EL1	Tag Con Register
0b11	0b000	0b0001	0b0010	0b000	ZCR_EL1	SVE Con Register EL1
0b11	0b000	0b0001	0b0010	0b001	TRFCR_EL1	Trace Fi Control Register
0b11	0b000	0b0010	0b0000	0b000	TTBR0_EL1	Translat Table Ba Register (EL1)
0b11	0b000	0b0010	0b0000	0b001	TTBR1_EL1	Translat Table Ba

Register selectors						
op0	op1	CRn	CRm	op2	Name	Descri
						Register (EL1)
0b11	0b000	0b0010	0b0000	0b010	TCR_EL1	Translat Control Register
0b11	0b000	0b0010	0b0001	0b000	APIAKeyLo_EL1	Pointer Authenti Key A fo Instructi (bits[63:
0b11	0b000	0b0010	0b0001	0b001	APIAKeyHi_EL1	Pointer Authenti Key A fo Instructi (bits[127
0b11	0b000	0b0010	0b0001	0b010	APIBKeyLo_EL1	Pointer Authenti Key B fo Instructi (bits[63:
0b11	0b000	0b0010	0b0001	0b011	APIBKeyHi_EL1	Pointer Authenti Key B fo Instructi (bits[127
0b11	0b000	0b0010	0b0010	0b000	APDAKeyLo_EL1	Pointer Authenti Key A fo (bits[63:
0b11	0b000	0b0010	0b0010	0b001	APDAKeyHi_EL1	Pointer Authenti Key A fo (bits[127
0b11	0b000	0b0010	0b0010	0b010	APDBKeyLo_EL1	Pointer Authenti Key B fo (bits[63:
0b11	0b000	0b0010	0b0010	0b011	APDBKeyHi_EL1	Pointer Authenti Key B fo (bits[127
0b11	0b000	0b0010	0b0011	0b000	APGAKeyLo_EL1	Pointer Authenti Key A fo (bits[63:
0b11	0b000	0b0010	0b0011	0b001	APGAKeyHi_EL1	Pointer Authenti Key A fo (bits[127
0b11	0b000	0b0100	0b0000	0b000	SPSR_EL1	Saved Program Status Register
0b11	0b000	0b0100	0b0000	0b001	ELR_EL1	Exceptio Register
0b11	0b000	0b0100	0b0001	0b000	SP_EL0	Stack Po (EL0)
0b11	0b000	0b0100	0b0010	0b000	SPSel	Stack Po Select
0b11	0b000	0b0100	0b0010	0b010	CurrentEL	Current Exceptio Level

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b000	0b0100	0b0010	0b011	PAN	Privilege Access N
0b11	0b000	0b0100	0b0010	0b100	UAO	User Acc Override
0b11	0b000	0b0100	0b0110	0b000	ICC_PMR_EL1	Interrup Controll Interrup Priority Register
0b11	0b000	0b0101	0b0001	0b000	AFSR0_EL1	Auxiliary Status Register (EL1)
0b11	0b000	0b0101	0b0001	0b001	AFSR1_EL1	Auxiliary Status Register (EL1)
0b11	0b000	0b0101	0b0010	0b000	ESR_EL1	Exceptio Syndrom Register
0b11	0b000	0b0101	0b0011	0b000	ERRIDR_EL1	Error Re ID Regis
0b11	0b000	0b0101	0b0011	0b001	ERRSELR_EL1	Error Re Select Register
0b11	0b000	0b0101	0b0100	0b000	ERXFR_EL1	Selected Record Feature Register
0b11	0b000	0b0101	0b0100	0b001	ERXCTLR_EL1	Selected Record Control Register
0b11	0b000	0b0101	0b0100	0b010	ERXSTATUS_EL1	Selected Record Primary Register
0b11	0b000	0b0101	0b0100	0b011	ERXADDR_EL1	Selected Record Address Register
0b11	0b000	0b0101	0b0100	0b100	ERXPFGF_EL1	Selected Pseudo-f Generati Feature register
0b11	0b000	0b0101	0b0100	0b101	ERXPFGCTL_EL1	Selected Pseudo-f Generati Control register
0b11	0b000	0b0101	0b0100	0b110	ERXPFGCDN_EL1	Selected Pseudo-f Generati Countdo register
0b11	0b000	0b0101	0b0101	0b000	ERXMISC0_EL1	Selected Record Miscella Register
0b11	0b000	0b0101	0b0101	0b001	ERXMISC1_EL1	Selected Record

Register selectors						
op0	op1	CRn	CRm	op2	Name	Descri
						Miscella Register
0b11	0b000	0b0101	0b0101	0b010	ERXMISC2_EL1	Selected Record Miscella Register
0b11	0b000	0b0101	0b0101	0b011	ERXMISC3_EL1	Selected Record Miscella Register
0b11	0b000	0b0101	0b0110	0b000	TFSR_EL1	Tag Faul Status Register
0b11	0b000	0b0101	0b0110	0b001	TFSRE0_EL1	Tag Faul Status Register (EL0).
0b11	0b000	0b0110	0b0000	0b000	FAR_EL1	Fault Ad Register
0b11	0b000	0b0111	0b0100	0b000	PAR_EL1	Physical Address Register
0b11	0b000	0b1001	0b1001	0b000	PMSCR_EL1	Statistic Profiling Control Register
0b11	0b000	0b1001	0b1001	0b010	PMSICR_EL1	Samplin Interval Counter Register
0b11	0b000	0b1001	0b1001	0b011	PMSIRR_EL1	Samplin Interval Reload Register
0b11	0b000	0b1001	0b1001	0b100	PMSFCR_EL1	Samplin Filter Co Register
0b11	0b000	0b1001	0b1001	0b101	PMSEVFR_EL1	Samplin Event Fi Register
0b11	0b000	0b1001	0b1001	0b110	PMSLATFR_EL1	Samplin Latency Register
0b11	0b000	0b1001	0b1001	0b111	PMSIDR_EL1	Samplin Profiling Register
0b11	0b000	0b1001	0b1010	0b000	PMBLIMITR_EL1	Profiling Buffer L Address Register
0b11	0b000	0b1001	0b1010	0b001	PMBPTR_EL1	Profiling Buffer W Pointer Register
0b11	0b000	0b1001	0b1010	0b011	PMBSR_EL1	Profiling Buffer S syndrom Register
0b11	0b000	0b1001	0b1010	0b111	PMBIDR_EL1	Profiling Buffer ID Register

Register selectors						
op0	op1	CRn	CRm	op2	Name	Descri
0b11	0b000	0b1001	0b1110	0b001	PMINTENSET_EL1	Performa Monitors Interrup Enable S register
0b11	0b000	0b1001	0b1110	0b010	PMINTENCLR_EL1	Performa Monitors Interrup Enable C register
0b11	0b000	0b1001	0b1110	0b110	PMMIR_EL1	Performa Monitors Machine Identific Register
0b11	0b000	0b1010	0b0010	0b000	MAIR_EL1	Memory Attribute Indirecti Register
0b11	0b000	0b1010	0b0011	0b000	AMAIR_EL1	Auxiliary Memory Attribute Indirecti Register
0b11	0b000	0b1010	0b0100	0b000	LORSA_EL1	LORegio Start Ad (EL1)
0b11	0b000	0b1010	0b0100	0b001	LOREA_EL1	LORegio Address
0b11	0b000	0b1010	0b0100	0b010	LORN_EL1	LORegio Number
0b11	0b000	0b1010	0b0100	0b011	LORC_EL1	LORegio Control
0b11	0b000	0b1010	0b0100	0b100	MPAMIDR_EL1	MPAM I Register
0b11	0b000	0b1010	0b0100	0b111	LORID_EL1	LORegio (EL1)
0b11	0b000	0b1010	0b0101	0b000	MPAM1_EL1	MPAM1 Register
0b11	0b000	0b1010	0b0101	0b001	MPAM0_EL1	MPAM0 Register
0b11	0b000	0b1100	0b0000	0b000	VBAR_EL1	Vector B Address Register
0b11	0b000	0b1100	0b0000	0b001	RVBAR_EL1	Reset Ve Base Ad Register EL2 and not impleme
0b11	0b000	0b1100	0b0000	0b010	RMR_EL1	Reset Manage Register
0b11	0b000	0b1100	0b0001	0b000	ISR_EL1	Interrup Status Register
0b11	0b000	0b1100	0b0001	0b001	DISR_EL1	Deferred Interrup Status Register
0b11	0b000	0b1100	0b1000	0b000	ICC_IAR0_EL1	Interrup Controll

Register selectors						
op0	op1	CRn	CRm	op2	Name	Descri
						Interrup Acknowl Register
0b11	0b000	0b1100	0b1000	0b001	ICC_EOIR0_EL1	Interrup Controll Of Interr Register
0b11	0b000	0b1100	0b1000	0b010	ICC_HPPIR0_EL1	Interrup Controll Highest Priority Pending Interrup Register
0b11	0b000	0b1100	0b1000	0b011	ICC_BPR0_EL1	Interrup Controll Binary P Register
0b11	0b000	0b1100	0b1000	0b1:n[1:0]	ICC_AP0R<n>_EL1	Interrup Controll Active Prioritie Group 0 Register
0b11	0b000	0b1100	0b1001	0b0:n[1:0]	ICC_AP1R<n>_EL1	Interrup Controll Active Prioritie Group 1 Register
0b11	0b000	0b1100	0b1011	0b001	ICC_DIR_EL1	Interrup Controll Deactiva Interrup Register
0b11	0b000	0b1100	0b1011	0b011	ICC_RPR_EL1	Interrup Controll Running Priority Register
0b11	0b000	0b1100	0b1011	0b101	ICC_SGI1R_EL1	Interrup Controll Software Generat Interrup Group 1 Register
0b11	0b000	0b1100	0b1011	0b110	ICC_ASGI1R_EL1	Interrup Controll Alias So Generat Interrup Group 1 Register
0b11	0b000	0b1100	0b1011	0b111	ICC_SGI0R_EL1	Interrup Controll Software Generat Interrup Group 0 Register
0b11	0b000	0b1100	0b1100	0b000	ICC_IAR1_EL1	Interrup Controll Interrup

Register selectors						
op0	op1	CRn	CRm	op2	Name	Descri
						Acknowl Register
0b11	0b000	0b1100	0b1100	0b001	ICC_EOIR1_EL1	Interrup Controll Of Inter Register
0b11	0b000	0b1100	0b1100	0b010	ICC_HPPIR1_EL1	Interrup Controll Highest Priority Pending Interrup Register
0b11	0b000	0b1100	0b1100	0b011	ICC_BPR1_EL1	Interrup Controll Binary P Register
0b11	0b000	0b1100	0b1100	0b100	ICC_CTLR_EL1	Interrup Controll Control Register
0b11	0b000	0b1100	0b1100	0b101	ICC_SRE_EL1	Interrup Controll System Register Enable register
0b11	0b000	0b1100	0b1100	0b110	ICC_IGRPEN0_EL1	Interrup Controll Interrup Group 0 Enable register
0b11	0b000	0b1100	0b1100	0b111	ICC_IGRPEN1_EL1	Interrup Controll Interrup Group 1 Enable register
0b11	0b000	0b1101	0b0000	0b001	CONTEXTIDR_EL1	Context Register
0b11	0b000	0b1101	0b0000	0b100	TPIDR_EL1	EL1 Soft Thread I Register
0b11	0b000	0b1101	0b0000	0b111	SCXTNUM_EL1	EL1 Rea Write So Context Number
0b11	0b000	0b1110	0b0001	0b000	CNTKCTL_EL1	Counter- Kernel C register
0b11	0b001	0b0000	0b0000	0b000	CCSIDR_EL1	Current Size ID Register
0b11	0b001	0b0000	0b0000	0b001	CLIDR_EL1	Cache L ID Regis
0b11	0b001	0b0000	0b0000	0b010	CCSIDR2_EL1	Current Size ID Register
0b11	0b001	0b0000	0b0000	0b100	GMID_EL1	Multiple transfer register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b001	0b0000	0b0000	0b111	AIDR_EL1	Auxiliary Register
0b11	0b010	0b0000	0b0000	0b000	CSSELR_EL1	Cache S Selectio Register
0b11	0b011	0b0000	0b0000	0b001	CTR_EL0	Cache T Register
0b11	0b011	0b0000	0b0000	0b111	DCZID_EL0	Data Ca Zero ID register
0b11	0b011	0b0010	0b0100	0b000	RNDR	Random Number
0b11	0b011	0b0010	0b0100	0b001	RNDRRS	Reseede Random Number
0b11	0b011	0b0100	0b0010	0b000	NZCV	Conditio Flags
0b11	0b011	0b0100	0b0010	0b001	DAIF	Interrup Mask Bi
0b11	0b011	0b0100	0b0010	0b101	DIT	Data Indepen Timing
0b11	0b011	0b0100	0b0010	0b110	SSBS	Speculat Store By Safe
0b11	0b011	0b0100	0b0010	0b111	TCO	Tag Che Override
0b11	0b011	0b0100	0b0100	0b000	FPCR	Floating Control Register
0b11	0b011	0b0100	0b0100	0b001	FPSR	Floating Status Register
0b11	0b011	0b0100	0b0101	0b000	DSPSR_EL0	Debug S Program Status Register
0b11	0b011	0b0100	0b0101	0b001	DLR_EL0	Debug L Register
0b11	0b011	0b1001	0b1100	0b000	PMCR_EL0	Performa Monitors Control Register
0b11	0b011	0b1001	0b1100	0b001	PMCNTENSET_EL0	Performa Monitors Count E Set regi
0b11	0b011	0b1001	0b1100	0b010	PMCNTENCLR_EL0	Performa Monitors Count E Clear re
0b11	0b011	0b1001	0b1100	0b011	PMOVSCLR_EL0	Performa Monitors Overflow Status C Register
0b11	0b011	0b1001	0b1100	0b100	PMSWINC_EL0	Performa Monitors Software Increme register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b011	0b1001	0b1100	0b101	PMSELR_EL0	Performa Monitors Event Co Selectio Register
0b11	0b011	0b1001	0b1100	0b110	PMCEID0_EL0	Performa Monitors Commor Event Identific register
0b11	0b011	0b1001	0b1100	0b111	PMCEID1_EL0	Performa Monitors Commor Event Identific register
0b11	0b011	0b1001	0b1101	0b000	PMCCNTR_EL0	Performa Monitors Cycle Co Register
0b11	0b011	0b1001	0b1101	0b001	PMXEVTYPER_EL0	Performa Monitors Selected Type Re
0b11	0b011	0b1001	0b1101	0b010	PMXEVCNTR_EL0	Performa Monitors Selected Count R
0b11	0b011	0b1001	0b1110	0b000	PMUSERENR_EL0	Performa Monitors Enable Register
0b11	0b011	0b1001	0b1110	0b011	PMOVSSET_EL0	Performa Monitors Overflow Status S register
0b11	0b011	0b1101	0b0000	0b010	TPIDR_EL0	EL0 Rea Write So Thread I Register
0b11	0b011	0b1101	0b0000	0b011	TPIDRRO_EL0	EL0 Rea Software Thread I Register
0b11	0b011	0b1101	0b0000	0b111	SCXTNUM_EL0	EL0 Rea Write So Context Number
0b11	0b011	0b1101	0b0010	0b000	AMCR_EL0	Activity Monitors Control Register
0b11	0b011	0b1101	0b0010	0b001	AMCFGR_EL0	Activity Monitors Configur Register
0b11	0b011	0b1101	0b0010	0b010	AMCGCR_EL0	Activity Monitors Counter Configur Register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b011	0b1101	0b0010	0b011	AMUSERENR_EL0	Activity Monitors Enable Register
0b11	0b011	0b1101	0b0010	0b100	AMCNTENCLR0_EL0	Activity Monitors Count E Clear Re 0
0b11	0b011	0b1101	0b0010	0b101	AMCNTENSET0_EL0	Activity Monitors Count E Set Regi
0b11	0b011	0b1101	0b0010	0b110	AMCG1IDR_EL0	Activity Monitors Counter 1 Identific Register
0b11	0b011	0b1101	0b0011	0b000	AMCNTENCLR1_EL0	Activity Monitors Count E Clear Re 1
0b11	0b011	0b1101	0b0011	0b001	AMCNTENSET1_EL0	Activity Monitors Count E Set Regi
0b11	0b011	0b1101	0b010:n[3]	n[2:0]	AMEVCNTR0<n>_EL0	Activity Monitors Event Co Register
0b11	0b011	0b1101	0b011:n[3]	n[2:0]	AMEVTYPER0<n>_EL0	Activity Monitors Event Ty Register
0b11	0b011	0b1101	0b110:n[3]	n[2:0]	AMEVCNTR1<n>_EL0	Activity Monitors Event Co Register
0b11	0b011	0b1101	0b111:n[3]	n[2:0]	AMEVTYPER1<n>_EL0	Activity Monitors Event Ty Register
0b11	0b011	0b1110	0b0000	0b000	CNTFRQ_EL0	Counter- Frequen register
0b11	0b011	0b1110	0b0000	0b001	CNTPCT_EL0	Counter- Physical register
0b11	0b011	0b1110	0b0000	0b010	CNTVCT_EL0	Counter- Virtual C register
0b11	0b011	0b1110	0b0000	0b101	CNTPCTSS_EL0	Counter- Self-Synchro Physical register
0b11	0b011	0b1110	0b0000	0b110	CNTVCTSS_EL0	Counter- Self-Synchro Virtual C register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b011	0b1110	0b0010	0b000	CNTP_TVAL_EL0	Counter-Physical TimerVa register
0b11	0b011	0b1110	0b0010	0b001	CNTP_CTL_EL0	Counter-Physical Control register
0b11	0b011	0b1110	0b0010	0b010	CNTP_CVAL_EL0	Counter-Physical Compare register
0b11	0b011	0b1110	0b0011	0b000	CNTV_TVAL_EL0	Counter-Virtual T TimerVa register
0b11	0b011	0b1110	0b0011	0b001	CNTV_CTL_EL0	Counter-Virtual T Control register
0b11	0b011	0b1110	0b0011	0b010	CNTV_CVAL_EL0	Counter-Virtual T Compare register
0b11	0b011	0b1110	0b10:n[4:3]	n[2:0]	PMEVCNTR<n>_EL0	Performa Monitors Event Co Register
0b11	0b011	0b1110	0b1111	0b111	PMCCFILTR_EL0	Performa Monitors Cycle Co Filter Re
0b11	0b011	0b1110	0b11:n[4:3]	n[2:0]	PMEVTYPER<n>_EL0	Performa Monitors Event Ty Register
0b11	0b100	0b0000	0b0000	0b000	VPIDR_EL2	Virtualiz Processo Register
0b11	0b100	0b0000	0b0000	0b101	VMPIDR_EL2	Virtualiz Multipro ID Regis
0b11	0b100	0b0001	0b0000	0b000	SCTLR_EL2	System Control Register
0b11	0b100	0b0001	0b0000	0b001	ACTLR_EL2	Auxiliary Control Register
0b11	0b100	0b0001	0b0001	0b000	HCR_EL2	Hypervis Configur Register
0b11	0b100	0b0001	0b0001	0b001	MDCR_EL2	Monitor Debug Configur Register
0b11	0b100	0b0001	0b0001	0b010	CPTR_EL2	Architec Feature Register
0b11	0b100	0b0001	0b0001	0b011	HSTR_EL2	Hypervis System Register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b100	0b0001	0b0001	0b100	HFGRTR_EL2	Hypervis Fine-Gra Read Tra Register
0b11	0b100	0b0001	0b0001	0b101	HFGWTR_EL2	Hypervis Fine-Gra Write Tr Register
0b11	0b100	0b0001	0b0001	0b110	HFGITR_EL2	Hypervis Fine-Gra Instructi Trap Reg
0b11	0b100	0b0001	0b0001	0b111	HACR_EL2	Hypervis Auxiliary Control Register
0b11	0b100	0b0001	0b0010	0b000	ZCR_EL2	SVE Con Register EL2
0b11	0b100	0b0001	0b0010	0b001	TRFCR_EL2	Trace Fi Control Register
0b11	0b100	0b0001	0b0011	0b001	SDER32_EL2	AArch32 Secure I Enable Register
0b11	0b100	0b0010	0b0000	0b000	TTBR0_EL2	Translat Table Ba Register (EL2)
0b11	0b100	0b0010	0b0000	0b001	TTBR1_EL2	Translat Table Ba Register (EL2)
0b11	0b100	0b0010	0b0000	0b010	TCR_EL2	Translat Control Register
0b11	0b100	0b0010	0b0001	0b000	VTTBR_EL2	Virtualiz Translat Table Ba Register
0b11	0b100	0b0010	0b0001	0b010	VTCR_EL2	Virtualiz Translat Control Register
0b11	0b100	0b0010	0b0010	0b000	VNCR_EL2	Virtual N Control Register
0b11	0b100	0b0010	0b0110	0b000	VSTTBR_EL2	Virtualiz Secure Translat Table Ba Register
0b11	0b100	0b0010	0b0110	0b010	VSTCR_EL2	Virtualiz Secure Translat Control Register
0b11	0b100	0b0011	0b0000	0b000	DACR32_EL2	Domain Access C Register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b100	0b0011	0b0001	0b100	HDFGRTR_EL2	Hypervis Debug F Grained Trap Reg
0b11	0b100	0b0011	0b0001	0b101	HDFGWTR_EL2	Hypervis Debug F Grained Trap Reg
0b11	0b100	0b0011	0b0001	0b110	HAFGRTR_EL2	Hypervis Activity Monitors Grained Trap Reg
0b11	0b100	0b0100	0b0000	0b000	SPSR_EL2	Saved Program Status Register
0b11	0b100	0b0100	0b0000	0b001	ELR_EL2	Exceptio Register
0b11	0b100	0b0100	0b0001	0b000	SP_EL1	Stack Po (EL1)
0b11	0b100	0b0100	0b0011	0b000	SPSR_irq	Saved Program Status Register mode)
0b11	0b100	0b0100	0b0011	0b001	SPSR_abt	Saved Program Status Register (Abort m
0b11	0b100	0b0100	0b0011	0b010	SPSR_und	Saved Program Status Register (Undefin mode)
0b11	0b100	0b0100	0b0011	0b011	SPSR_fiq	Saved Program Status Register mode)
0b11	0b100	0b0101	0b0000	0b001	IFSR32_EL2	Instructi Fault Sta Register
0b11	0b100	0b0101	0b0001	0b000	AFSR0_EL2	Auxiliary Status Register (EL2)
0b11	0b100	0b0101	0b0001	0b001	AFSR1_EL2	Auxiliary Status Register (EL2)
0b11	0b100	0b0101	0b0010	0b000	ESR_EL2	Exceptio Syndrom Register
0b11	0b100	0b0101	0b0010	0b011	VSESR_EL2	Virtual S Exceptio Syndrom Register
0b11	0b100	0b0101	0b0011	0b000	FPEXC32_EL2	Floating Exceptio

Register selectors						
op0	op1	CRn	CRm	op2	Name	Descri
						Control register
0b11	0b100	0b0101	0b0110	0b000	TFSR_EL2	Tag Faul Status Register
0b11	0b100	0b0110	0b0000	0b000	FAR_EL2	Fault Ad Register
0b11	0b100	0b0110	0b0000	0b100	HPFAR_EL2	Hypervis Fault Ad Register
0b11	0b100	0b1001	0b1001	0b000	PMSCR_EL2	Statistic Profiling Control Register
0b11	0b100	0b1010	0b0010	0b000	MAIR_EL2	Memory Attribute Indirecti Register
0b11	0b100	0b1010	0b0011	0b000	AMAIR_EL2	Auxiliary Memory Attribute Indirecti Register
0b11	0b100	0b1010	0b0100	0b000	MPAMHCR_EL2	MPAM Hypervis Control Register
0b11	0b100	0b1010	0b0100	0b001	MPAMVPMV_EL2	MPAM V Partition Mapping Register
0b11	0b100	0b1010	0b0101	0b000	MPAM2_EL2	MPAM2 Register
0b11	0b100	0b1010	0b0110	0b000	MPAMVPM0_EL2	MPAM V PARTID Mapping Register
0b11	0b100	0b1010	0b0110	0b001	MPAMVPM1_EL2	MPAM V PARTID Mapping Register
0b11	0b100	0b1010	0b0110	0b010	MPAMVPM2_EL2	MPAM V PARTID Mapping Register
0b11	0b100	0b1010	0b0110	0b011	MPAMVPM3_EL2	MPAM V PARTID Mapping Register
0b11	0b100	0b1010	0b0110	0b100	MPAMVPM4_EL2	MPAM V PARTID Mapping Register
0b11	0b100	0b1010	0b0110	0b101	MPAMVPM5_EL2	MPAM V PARTID Mapping Register
0b11	0b100	0b1010	0b0110	0b110	MPAMVPM6_EL2	MPAM V PARTID Mapping Register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b100	0b1010	0b0110	0b111	MPAMVPM7_EL2	MPAM V PARTID Mapping Register
0b11	0b100	0b1100	0b0000	0b000	VBAR_EL2	Vector B Address Register
0b11	0b100	0b1100	0b0000	0b001	RVBAR_EL2	Reset Ve Base Ad Register EL3 not impleme
0b11	0b100	0b1100	0b0000	0b010	RMR_EL2	Reset Manage Register
0b11	0b100	0b1100	0b0001	0b001	VDISR_EL2	Virtual Deferred Interrup Status Register
0b11	0b100	0b1100	0b1000	0b0:n[1:0]	ICH_AP0R<n>_EL2	Interrup Controll Active Prioritie Group 0 Register
0b11	0b100	0b1100	0b1001	0b0:n[1:0]	ICH_AP1R<n>_EL2	Interrup Controll Active Prioritie Group 1 Register
0b11	0b100	0b1100	0b1001	0b101	ICC_SRE_EL2	Interrup Controll System Register Enable register
0b11	0b100	0b1100	0b1011	0b000	ICH_HCR_EL2	Interrup Controll Control Register
0b11	0b100	0b1100	0b1011	0b001	ICH_VTR_EL2	Interrup Controll VGIC Ty Register
0b11	0b100	0b1100	0b1011	0b010	ICH_MISR_EL2	Interrup Controll Mainten Interrup Register
0b11	0b100	0b1100	0b1011	0b011	ICH_EISR_EL2	Interrup Controll of Interr Status Register
0b11	0b100	0b1100	0b1011	0b101	ICH_ELRSR_EL2	Interrup Controll Empty L Register Status Register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b100	0b1100	0b1011	0b111	ICH_VMCR_EL2	Interrup Controll Virtual Machine Control Register
0b11	0b100	0b1100	0b110:n[3]	n[2:0]	ICH_LR<n>_EL2	Interrup Controll Register
0b11	0b100	0b1101	0b0000	0b001	CONTEXTIDR_EL2	Context Register
0b11	0b100	0b1101	0b0000	0b010	TPIDR_EL2	EL2 Soft Thread I Register
0b11	0b100	0b1101	0b0000	0b111	SCXTNUM_EL2	EL2 Rea Write So Context Number
0b11	0b100	0b1101	0b100:n[3]	n[2:0]	AMEVCNTVOFF0<n>_EL2	Activity Monitors Event Co Virtual C Register
0b11	0b100	0b1101	0b101:n[3]	n[2:0]	AMEVCNTVOFF1<n>_EL2	Activity Monitors Event Co Virtual C Register
0b11	0b100	0b1110	0b0000	0b011	CNTVOFF_EL2	Counter- Virtual C register
0b11	0b100	0b1110	0b0000	0b110	CNTPOFF_EL2	Counter- Physical register
0b11	0b100	0b1110	0b0001	0b000	CNTHCTL_EL2	Counter- Hypervis Control register
0b11	0b100	0b1110	0b0010	0b000	CNTHP_TVAL_EL2	Counter- Physical TimerVa register
0b11	0b100	0b1110	0b0010	0b001	CNTHP_CTL_EL2	Counter- Hypervis Physical Control register
0b11	0b100	0b1110	0b0010	0b010	CNTHP_CVAL_EL2	Counter- Physical Compare register
0b11	0b100	0b1110	0b0011	0b000	CNTHV_TVAL_EL2	Counter- Virtual T TimerVa Register
0b11	0b100	0b1110	0b0011	0b001	CNTHV_CTL_EL2	Counter- Virtual T Control register
0b11	0b100	0b1110	0b0011	0b010	CNTHV_CVAL_EL2	Counter- Virtual T Compare register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b100	0b1110	0b0100	0b000	CNTHVS_TVAL_EL2	Counter Secure V Timer TimerVa register
0b11	0b100	0b1110	0b0100	0b001	CNTHVS_CTL_EL2	Counter Secure V Timer C register
0b11	0b100	0b1110	0b0100	0b010	CNTHVS_CVAL_EL2	Counter Secure V Timer Compare register
0b11	0b100	0b1110	0b0101	0b000	CNTHPS_TVAL_EL2	Counter Secure Physical TimerVa register
0b11	0b100	0b1110	0b0101	0b001	CNTHPS_CTL_EL2	Counter Secure Physical Control register
0b11	0b100	0b1110	0b0101	0b010	CNTHPS_CVAL_EL2	Counter Secure Physical Compare register
0b11	0b110	0b0001	0b0000	0b000	SCTLR_EL3	System Control Register
0b11	0b110	0b0001	0b0000	0b001	ACTLR_EL3	Auxiliary Control Register
0b11	0b110	0b0001	0b0001	0b000	SCR_EL3	Secure Configur Register
0b11	0b110	0b0001	0b0001	0b001	SDER32_EL3	AArch32 Secure I Enable Register
0b11	0b110	0b0001	0b0001	0b010	CPTR_EL3	Architec Feature Register
0b11	0b110	0b0001	0b0010	0b000	ZCR_EL3	SVE Cor Register EL3
0b11	0b110	0b0001	0b0011	0b001	MDCR_EL3	Monitor Debug Configur Register
0b11	0b110	0b0010	0b0000	0b000	TTBR0_EL3	Translat Table Ba Register (EL3)
0b11	0b110	0b0010	0b0000	0b010	TCR_EL3	Translat Control Register
0b11	0b110	0b0100	0b0000	0b000	SPSR_EL3	Saved Program Status Register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b110	0b0100	0b0000	0b001	ELR_EL3	Exceptio Register
0b11	0b110	0b0100	0b0001	0b000	SP_EL2	Stack Po (EL2)
0b11	0b110	0b0101	0b0001	0b000	AFSR0_EL3	Auxiliary Status Register (EL3)
0b11	0b110	0b0101	0b0001	0b001	AFSR1_EL3	Auxiliary Status Register (EL3)
0b11	0b110	0b0101	0b0010	0b000	ESR_EL3	Exceptio Syndrom Register
0b11	0b110	0b0101	0b0110	0b000	TFSR_EL3	Tag Faul Status Register
0b11	0b110	0b0110	0b0000	0b000	FAR_EL3	Fault Ad Register
0b11	0b110	0b1010	0b0010	0b000	MAIR_EL3	Memory Attribute Indirecti Register
0b11	0b110	0b1010	0b0011	0b000	AMAIR_EL3	Auxiliary Memory Attribute Indirecti Register
0b11	0b110	0b1010	0b0101	0b000	MPAM3_EL3	MPAM3 Register
0b11	0b110	0b1100	0b0000	0b000	VBAR_EL3	Vector B Address Register
0b11	0b110	0b1100	0b0000	0b001	RVBAR_EL3	Reset Ve Base Ad Register EL3 impleme
0b11	0b110	0b1100	0b0000	0b010	RMR_EL3	Reset Manage Register
0b11	0b110	0b1100	0b1100	0b100	ICC_CTLR_EL3	Interrup Controll Control Register
0b11	0b110	0b1100	0b1100	0b101	ICC_SRE_EL3	Interrup Controll System Register Enable register
0b11	0b110	0b1100	0b1100	0b111	ICC_IGRPEN1_EL3	Interrup Controll Interrup Group 1 Enable register
0b11	0b110	0b1101	0b0000	0b010	TPIDR_EL3	EL3 Soft Thread I Register

Register selectors					Name	Descri
op0	op1	CRn	CRm	op2		
0b11	0b110	0b1101	0b0000	0b111	SCXTNUM_EL3	EL3 Rea Write So Context Number
0b11	0b111	0b1110	0b0010	0b000	CNTPS_TVAL_EL1	Counter- Physical Secure T TimerVa register
0b11	0b111	0b1110	0b0010	0b001	CNTPS_CTL_EL1	Counter- Physical Secure T Control register
0b11	0b111	0b1110	0b0010	0b010	CNTPS_CVAL_EL1	Counter- Physical Secure T Compare register

Accessed using TLBI:

Register selectors						Name	Description
op0	op1	CRn	CRm	op2	Rt		
0b01	0b000	0b1000	0b0001	0b000	0b11111	TLBI VMALLE1OS	TLB Invalidate by VMID, All at stage 1, EL1, Outer Shareable
0b01	0b000	0b1000	0b0001	0b001	-	TLBI VAE1OS	TLB Invalidate by VA, EL1, Outer Shareable
0b01	0b000	0b1000	0b0001	0b010	-	TLBI ASIDE1OS	TLB Invalidate by ASID, EL1, Outer Shareable
0b01	0b000	0b1000	0b0001	0b011	-	TLBI VAAE1OS	TLB Invalidate by VA, All ASID, EL1, Outer Shareable
0b01	0b000	0b1000	0b0001	0b101	-	TLBI VALE1OS	TLB Invalidate by VA, Last level, EL1, Outer Shareable
0b01	0b000	0b1000	0b0001	0b111	-	TLBI VAALE1OS	TLB Invalidate by VA, All ASID, Last Level, EL1, Outer Shareable
0b01	0b000	0b1000	0b0010	0b001	-	TLBI RVAE1IS	TLB Range Invalidate by VA, EL1, Inner Shareable

Register selectors						Name	Description
op0	op1	CRn	CRm	op2	Rt		
0b01	0b000	0b1000	0b0010	0b011	-	TLBI RVAAE1IS	TLB Range Invalidate by VA, All ASID, EL1, Inner Shareable
0b01	0b000	0b1000	0b0010	0b101	-	TLBI RVALE1IS	TLB Range Invalidate by VA, Last level, EL1, Inner Shareable
0b01	0b000	0b1000	0b0010	0b111	-	TLBI RVAALE1IS	TLB Range Invalidate by VA, All ASID, Last Level, EL1, Inner Shareable
0b01	0b000	0b1000	0b0011	0b000	0b11111	TLBI VMALLE1IS	TLB Invalidate by VMID, All at stage 1, EL1, Inner Shareable
0b01	0b000	0b1000	0b0011	0b001	-	TLBI VAE1IS	TLB Invalidate by VA, EL1, Inner Shareable
0b01	0b000	0b1000	0b0011	0b010	-	TLBI ASIDE1IS	TLB Invalidate by ASID, EL1, Inner Shareable
0b01	0b000	0b1000	0b0011	0b011	-	TLBI VAAE1IS	TLB Invalidate by VA, All ASID, EL1, Inner Shareable
0b01	0b000	0b1000	0b0011	0b101	-	TLBI VALE1IS	TLB Invalidate by VA, Last level, EL1, Inner Shareable
0b01	0b000	0b1000	0b0011	0b111	-	TLBI VAALE1IS	TLB Invalidate by VA, All ASID, Last Level, EL1, Inner Shareable
0b01	0b000	0b1000	0b0101	0b001	-	TLBI RVAE1OS	TLB Range Invalidate by VA, EL1, Outer Shareable
0b01	0b000	0b1000	0b0101	0b011	-	TLBI RVAAE1OS	TLB Range Invalidate by VA, All ASID, EL1, Outer Shareable
0b01	0b000	0b1000	0b0101	0b101	-	TLBI RVALE1OS	TLB Range Invalidate by VA, Last level, EL1,

Register selectors						Name	Description
op0	op1	CRn	CRm	op2	Rt		
							Outer Shareable
0b01	0b000	0b1000	0b0101	0b111	-	TLBI RVAALE1OS	TLB Range Invalidate by VA, All ASID, Last Level, EL1, Outer Shareable
0b01	0b000	0b1000	0b0110	0b001	-	TLBI RVAE1	TLB Range Invalidate by VA, EL1
0b01	0b000	0b1000	0b0110	0b011	-	TLBI RVAAE1	TLB Range Invalidate by VA, All ASID, EL1
0b01	0b000	0b1000	0b0110	0b101	-	TLBI RVALE1	TLB Range Invalidate by VA, Last level, EL1
0b01	0b000	0b1000	0b0110	0b111	-	TLBI RVAALE1	TLB Range Invalidate by VA, All ASID, Last level, EL1
0b01	0b000	0b1000	0b0111	0b000	0b11111	TLBI VMALLE1	TLB Invalidate by VMID, All at stage 1, EL1
0b01	0b000	0b1000	0b0111	0b001	-	TLBI VAE1	TLB Invalidate by VA, EL1
0b01	0b000	0b1000	0b0111	0b010	-	TLBI ASIDE1	TLB Invalidate by ASID, EL1
0b01	0b000	0b1000	0b0111	0b011	-	TLBI VAAE1	TLB Invalidate by VA, All ASID, EL1
0b01	0b000	0b1000	0b0111	0b101	-	TLBI VALE1	TLB Invalidate by VA, Last level, EL1
0b01	0b000	0b1000	0b0111	0b111	-	TLBI VAALE1	TLB Invalidate by VA, All ASID, Last level, EL1
0b01	0b100	0b1000	0b0000	0b001	-	TLBI IPAS2E1IS	TLB Invalidate by Intermediate Physical Address, Stage 2, EL1, Inner Shareable
0b01	0b100	0b1000	0b0000	0b010	-	TLBI RIPAS2E1IS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1, Inner Shareable

Register selectors						Name	Description
op0	op1	CRn	CRm	op2	Rt		
0b01	0b100	0b1000	0b0000	0b101	-	TLBI IPAS2LE1IS	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Inner Shareable
0b01	0b100	0b1000	0b0000	0b110	-	TLBI RIPAS2LE1IS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Inner Shareable
0b01	0b100	0b1000	0b0001	0b000	0b11111	TLBI ALLE2OS	TLB Invalidate All, EL2, Outer Shareable
0b01	0b100	0b1000	0b0001	0b001	-	TLBI VAE2OS	TLB Invalidate by VA, EL2, Outer Shareable
0b01	0b100	0b1000	0b0001	0b100	0b11111	TLBI ALLE1OS	TLB Invalidate All, EL1, Outer Shareable
0b01	0b100	0b1000	0b0001	0b101	-	TLBI VALE2OS	TLB Invalidate by VA, Last level, EL2, Outer Shareable
0b01	0b100	0b1000	0b0001	0b110	0b11111	TLBI VMALLS12E1OS	TLB Invalidate by VMID, All at Stage 1 and 2, EL1, Outer Shareable
0b01	0b100	0b1000	0b0010	0b001	-	TLBI RVAE2IS	TLB Range Invalidate by VA, EL2, Inner Shareable
0b01	0b100	0b1000	0b0010	0b101	-	TLBI RVALE2IS	TLB Range Invalidate by VA, Last level, EL2, Inner Shareable
0b01	0b100	0b1000	0b0011	0b000	0b11111	TLBI ALLE2IS	TLB Invalidate All, EL2, Inner Shareable
0b01	0b100	0b1000	0b0011	0b001	-	TLBI VAE2IS	TLB Invalidate by

Register selectors							
op0	op1	CRn	CRm	op2	Rt	Name	Description
							VA, EL2, Inner Shareable
0b01	0b100	0b1000	0b0011	0b100	0b11111	TLBI ALLE1IS	TLB Invalidate All, EL1, Inner Shareable
0b01	0b100	0b1000	0b0011	0b101	-	TLBI VALE2IS	TLB Invalidate by VA, Last level, EL2, Inner Shareable
0b01	0b100	0b1000	0b0011	0b110	0b11111	TLBI VMALLS12E1IS	TLB Invalidate by VMID, All at Stage 1 and 2, EL1, Inner Shareable
0b01	0b100	0b1000	0b0100	0b000	-	TLBI IPAS2E1OS	TLB Invalidate by Intermediate Physical Address, Stage 2, EL1, Outer Shareable
0b01	0b100	0b1000	0b0100	0b001	-	TLBI IPAS2E1	TLB Invalidate by Intermediate Physical Address, Stage 2, EL1
0b01	0b100	0b1000	0b0100	0b010	-	TLBI RIPAS2E1	TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1
0b01	0b100	0b1000	0b0100	0b011	-	TLBI RIPAS2E1OS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1, Outer Shareable
0b01	0b100	0b1000	0b0100	0b100	-	TLBI IPAS2LE1OS	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Outer Shareable
0b01	0b100	0b1000	0b0100	0b101	-	TLBI IPAS2LE1	TLB Invalidate by Intermediate Physical Address, Stage 2,

Register selectors							
op0	op1	CRn	CRm	op2	Rt	Name	Description
							Last level, EL1
0b01	0b100	0b1000	0b0100	0b110	-	TLBI RIPAS2LE1	TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1
0b01	0b100	0b1000	0b0100	0b111	-	TLBI RIPAS2LE1OS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Outer Shareable
0b01	0b100	0b1000	0b0101	0b001	-	TLBI RVAE2OS	TLB Range Invalidate by VA, EL2, Outer Shareable
0b01	0b100	0b1000	0b0101	0b101	-	TLBI RVALE2OS	TLB Range Invalidate by VA, Last level, EL2, Outer Shareable
0b01	0b100	0b1000	0b0110	0b001	-	TLBI RVAE2	TLB Range Invalidate by VA, EL2
0b01	0b100	0b1000	0b0110	0b101	-	TLBI RVALE2	TLB Range Invalidate by VA, Last level, EL2
0b01	0b100	0b1000	0b0111	0b000	0b11111	TLBI ALLE2	TLB Invalidate All, EL2
0b01	0b100	0b1000	0b0111	0b001	-	TLBI VAE2	TLB Invalidate by VA, EL2
0b01	0b100	0b1000	0b0111	0b100	0b11111	TLBI ALLE1	TLB Invalidate All, EL1
0b01	0b100	0b1000	0b0111	0b101	-	TLBI VALE2	TLB Invalidate by VA, Last level, EL2
0b01	0b100	0b1000	0b0111	0b110	0b11111	TLBI VMALLS12E1	TLB Invalidate by VMID, All at Stage 1 and 2, EL1
0b01	0b110	0b1000	0b0001	0b000	0b11111	TLBI ALLE3OS	TLB Invalidate All, EL3, Outer Shareable
0b01	0b110	0b1000	0b0001	0b001	-	TLBI VAE3OS	TLB Invalidate by VA, EL3,

Register selectors						Name	Description
op0	op1	CRn	CRm	op2	Rt		
							Outer Shareable
0b01	0b110	0b1000	0b0001	0b101	-	TLBI VALE3OS	TLB Invalidate by VA, Last level, EL3, Outer Shareable
0b01	0b110	0b1000	0b0010	0b001	-	TLBI RVAE3IS	TLB Range Invalidate by VA, EL3, Inner Shareable
0b01	0b110	0b1000	0b0010	0b101	-	TLBI RVALE3IS	TLB Range Invalidate by VA, Last level, EL3, Inner Shareable
0b01	0b110	0b1000	0b0011	0b000	0b11111	TLBI ALLE3IS	TLB Invalidate All, EL3, Inner Shareable
0b01	0b110	0b1000	0b0011	0b001	-	TLBI VAE3IS	TLB Invalidate by VA, EL3, Inner Shareable
0b01	0b110	0b1000	0b0011	0b101	-	TLBI VALE3IS	TLB Invalidate by VA, Last level, EL3, Inner Shareable
0b01	0b110	0b1000	0b0101	0b001	-	TLBI RVAE3OS	TLB Range Invalidate by VA, EL3, Outer Shareable
0b01	0b110	0b1000	0b0101	0b101	-	TLBI RVALE3OS	TLB Range Invalidate by VA, Last level, EL3, Outer Shareable
0b01	0b110	0b1000	0b0110	0b001	-	TLBI RVAE3	TLB Range Invalidate by VA, EL3
0b01	0b110	0b1000	0b0110	0b101	-	TLBI RVALE3	TLB Range Invalidate by VA, Last level, EL3
0b01	0b110	0b1000	0b0111	0b000	0b11111	TLBI ALLE3	TLB Invalidate All, EL3
0b01	0b110	0b1000	0b0111	0b001	-	TLBI VAE3	TLB Invalidate by VA, EL3
0b01	0b110	0b1000	0b0111	0b101	-	TLBI VALE3	TLB Invalidate by VA, Last level, EL3

1327/1209/2019 1518:1349

Copyright Â© 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

System Register index by functional group

Below are indexes for registers with the following main functional groups:

- ID
- Memory
- Other
- Exception
- Special
- PSTATE
- Cache
- Address
- TLB
- PMU
- Reset
- Thread
- IMP DEF
- Timer
- Debug
- CTI
- Virt
- Secure
- Float
- Legacy
- GIC
- GICD
- GICR
- GICC
- GICV
- GICH
- GITS
- RAS
- MPAM
- Pointer authentication
- GIC ITS registers

In the ID functional group:

Exec state	Name	Description
AArch32	CCSIDR	Current Cache Size ID Register
AArch32	CCSIDR2	Current Cache Size ID Register 2
AArch32	CLIDR	Cache Level ID Register
AArch32	CSSELR	Cache Size Selection Register
AArch32	CTR	Cache Type Register
AArch32	ID_AFR0	Auxiliary Feature Register 0
AArch32	ID_DFR0	Debug Feature Register 0
AArch32	ID_DFR1	Debug Feature Register 1
AArch32	ID_ISAR0	Instruction Set Attribute Register 0
AArch32	ID_ISAR1	Instruction Set Attribute Register 1
AArch32	ID_ISAR2	Instruction Set Attribute Register 2
AArch32	ID_ISAR3	Instruction Set Attribute Register 3
AArch32	ID_ISAR4	Instruction Set Attribute Register 4
AArch32	ID_ISAR5	Instruction Set Attribute Register 5
AArch32	ID_ISAR6	Instruction Set Attribute Register 6
AArch32	ID_MMFR0	Memory Model Feature Register 0
AArch32	ID_MMFR1	Memory Model Feature Register 1
AArch32	ID_MMFR2	Memory Model Feature Register 2
AArch32	ID_MMFR3	Memory Model Feature Register 3
AArch32	ID_MMFR4	Memory Model Feature Register 4
AArch32	ID_MMFR5	Memory Model Feature Register 5
AArch32	ID_PFR0	Processor Feature Register 0
AArch32	ID_PFR1	Processor Feature Register 1

Exec state	Name	Description
AArch32	ID_PFR2	Processor Feature Register 2
AArch32	MIDR	Main ID Register
AArch32	MPIDR	Multiprocessor Affinity Register
AArch32	REVIDR	Revision ID Register
AArch32	TCMTR	TCM Type Register
AArch32	TLBTR	TLB Type Register
AArch64	CCSIDR2_EL1	Current Cache Size ID Register 2
AArch64	CCSIDR_EL1	Current Cache Size ID Register
AArch64	CLIDR_EL1	Cache Level ID Register
AArch64	CSSELR_EL1	Cache Size Selection Register
AArch64	CTR_EL0	Cache Type Register
AArch64	DCZID_EL0	Data Cache Zero ID register
AArch64	GMID_EL1	Multiple tag transfer ID register
AArch64	ID_AA64AFR0_EL1	AArch64 Auxiliary Feature Register 0
AArch64	ID_AA64AFR1_EL1	AArch64 Auxiliary Feature Register 1
AArch64	ID_AA64DFR0_EL1	AArch64 Debug Feature Register 0
AArch64	ID_AA64DFR1_EL1	AArch64 Debug Feature Register 1
AArch64	ID_AA64ISAR0_EL1	AArch64 Instruction Set Attribute Register 0
AArch64	ID_AA64ISAR1_EL1	AArch64 Instruction Set Attribute Register 1
AArch64	ID_AA64MMFR0_EL1	AArch64 Memory Model Feature Register 0
AArch64	ID_AA64MMFR1_EL1	AArch64 Memory Model Feature Register 1
AArch64	ID_AA64MMFR2_EL1	AArch64 Memory Model Feature Register 2
AArch64	ID_AA64PFR0_EL1	AArch64 Processor Feature Register 0
AArch64	ID_AA64PFR1_EL1	AArch64 Processor Feature Register 1
AArch64	ID_AA64ZFR0_EL1	SVE Feature ID register 0
AArch64	ID_AFR0_EL1	AArch32 Auxiliary Feature Register 0
AArch64	ID_DFR0_EL1	AArch32 Debug Feature Register 0
AArch64	ID_DFR1_EL1	Debug Feature Register 1
AArch64	ID_ISAR0_EL1	AArch32 Instruction Set Attribute Register 0
AArch64	ID_ISAR1_EL1	AArch32 Instruction Set Attribute Register 1
AArch64	ID_ISAR2_EL1	AArch32 Instruction Set Attribute Register 2
AArch64	ID_ISAR3_EL1	AArch32 Instruction Set Attribute Register 3
AArch64	ID_ISAR4_EL1	AArch32 Instruction Set Attribute Register 4
AArch64	ID_ISAR5_EL1	AArch32 Instruction Set Attribute Register 5
AArch64	ID_ISAR6_EL1	AArch32 Instruction Set Attribute Register 6
AArch64	ID_MMFR0_EL1	AArch32 Memory Model Feature Register 0
AArch64	ID_MMFR1_EL1	AArch32 Memory Model Feature Register 1
AArch64	ID_MMFR2_EL1	AArch32 Memory Model Feature Register 2
AArch64	ID_MMFR3_EL1	AArch32 Memory Model Feature Register 3
AArch64	ID_MMFR4_EL1	AArch32 Memory Model Feature Register 4
AArch64	ID_MMFR5_EL1	AArch32 Memory Model Feature Register 5
AArch64	ID_PFR0_EL1	AArch32 Processor Feature Register 0
AArch64	ID_PFR1_EL1	AArch32 Processor Feature Register 1
AArch64	ID_PFR2_EL1	AArch32 Processor Feature Register 2
AArch64	MIDR_EL1	Main ID Register
AArch64	MPAMIDR_EL1	MPAM ID Register (EL1)
AArch64	MPIDR_EL1	Multiprocessor Affinity Register
AArch64	REVIDR_EL1	Revision ID Register
External	EDAA32PFR	External Debug AArch32 Processor Feature Register
External	EDDFR	External Debug Feature Register
External	EDPFR	External Debug Processor Feature Register
External	MIDR_EL1	Main ID Register

In the Memory functional group:

Exec state	Name	Description
AArch32	AMAIR0	Auxiliary Memory Attribute Indirection Register 0
AArch32	AMAIR1	Auxiliary Memory Attribute Indirection Register 1
AArch32	CONTEXTIDR	Context ID Register
AArch32	DACR	Domain Access Control Register
AArch32	HAMAIR0	Hyp Auxiliary Memory Attribute Indirection Register 0
AArch32	HAMAIR1	Hyp Auxiliary Memory Attribute Indirection Register 1
AArch32	HMAIR0	Hyp Memory Attribute Indirection Register 0

Exec state	Name	Description
AArch32	HMAIR1	Hyp Memory Attribute Indirection Register 1
AArch32	HTCR	Hyp Translation Control Register
AArch32	HTTBR	Hyp Translation Table Base Register
AArch32	MAIR0	Memory Attribute Indirection Register 0
AArch32	MAIR1	Memory Attribute Indirection Register 1
AArch32	NMRR	Normal Memory Remap Register
AArch32	PRRR	Primary Region Remap Register
AArch32	TTBCR	Translation Table Base Control Register
AArch32	TTBCR2	Translation Table Base Control Register 2
AArch32	TTBR0	Translation Table Base Register 0
AArch32	TTBR1	Translation Table Base Register 1
AArch32	VTCR	Virtualization Translation Control Register
AArch32	VTTBR	Virtualization Translation Table Base Register
AArch64	AMAIR_EL1	Auxiliary Memory Attribute Indirection Register (EL1)
AArch64	AMAIR_EL2	Auxiliary Memory Attribute Indirection Register (EL2)
AArch64	AMAIR_EL3	Auxiliary Memory Attribute Indirection Register (EL3)
AArch64	CONTEXTIDR_EL1	Context ID Register (EL1)
AArch64	CONTEXTIDR_EL2	Context ID Register (EL2)
AArch64	DACR32_EL2	Domain Access Control Register
AArch64	LORC_EL1	LORegion Control (EL1)
AArch64	LOREA_EL1	LORegion End Address (EL1)
AArch64	LORID_EL1	LORegionID (EL1)
AArch64	LORN_EL1	LORegion Number (EL1)
AArch64	LORSA_EL1	LORegion Start Address (EL1)
AArch64	MAIR_EL1	Memory Attribute Indirection Register (EL1)
AArch64	MAIR_EL2	Memory Attribute Indirection Register (EL2)
AArch64	MAIR_EL3	Memory Attribute Indirection Register (EL3)
AArch64	TCR_EL1	Translation Control Register (EL1)
AArch64	TCR_EL2	Translation Control Register (EL2)
AArch64	TCR_EL3	Translation Control Register (EL3)
AArch64	TTBR0_EL1	Translation Table Base Register 0 (EL1)
AArch64	TTBR0_EL2	Translation Table Base Register 0 (EL2)
AArch64	TTBR0_EL3	Translation Table Base Register 0 (EL3)
AArch64	TTBR1_EL1	Translation Table Base Register 1 (EL1)
AArch64	TTBR1_EL2	Translation Table Base Register 1 (EL2)
AArch64	VTCR_EL2	Virtualization Translation Control Register
AArch64	VTTBR_EL2	Virtualization Translation Table Base Register

In the Other functional group:

Exec state	Name	Description
AArch32	CPACR	Architectural Feature Access Control Register
AArch32	SCTLR	System Control Register
AArch64	CPACR_EL1	Architectural Feature Access Control Register
AArch64	SCTLR_EL1	System Control Register (EL1)
AArch64	SCTLR_EL3	System Control Register (EL3)
AArch64	ZCR_EL1	SVE Control Register for EL1
AArch64	ZCR_EL2	SVE Control Register for EL2
AArch64	ZCR_EL3	SVE Control Register for EL3

In the Exception functional group:

Exec state	Name	Description
AArch32	ADFSR	Auxiliary Data Fault Status Register
AArch32	AIFSR	Auxiliary Instruction Fault Status Register
AArch32	DFAR	Data Fault Address Register
AArch32	DFSR	Data Fault Status Register
AArch32	HADFSR	Hyp Auxiliary Data Fault Status Register
AArch32	HAIFSR	Hyp Auxiliary Instruction Fault Status Register
AArch32	HDFAR	Hyp Data Fault Address Register
AArch32	HIFAR	Hyp Instruction Fault Address Register
AArch32	HPFAR	Hyp IPA Fault Address Register

Exec state	Name	Description
AArch32	HSR	Hyp Syndrome Register
AArch32	HVBAR	Hyp Vector Base Address Register
AArch32	IFAR	Instruction Fault Address Register
AArch32	IFSR	Instruction Fault Status Register
AArch32	ISR	Interrupt Status Register
AArch32	MVBAR	Monitor Vector Base Address Register
AArch32	VBAR	Vector Base Address Register
AArch64	AFSR0_EL1	Auxiliary Fault Status Register 0 (EL1)
AArch64	AFSR0_EL2	Auxiliary Fault Status Register 0 (EL2)
AArch64	AFSR0_EL3	Auxiliary Fault Status Register 0 (EL3)
AArch64	AFSR1_EL1	Auxiliary Fault Status Register 1 (EL1)
AArch64	AFSR1_EL2	Auxiliary Fault Status Register 1 (EL2)
AArch64	AFSR1_EL3	Auxiliary Fault Status Register 1 (EL3)
AArch64	ESR_EL1	Exception Syndrome Register (EL1)
AArch64	ESR_EL2	Exception Syndrome Register (EL2)
AArch64	ESR_EL3	Exception Syndrome Register (EL3)
AArch64	FAR_EL1	Fault Address Register (EL1)
AArch64	FAR_EL2	Fault Address Register (EL2)
AArch64	FAR_EL3	Fault Address Register (EL3)
AArch64	HPFAR_EL2	Hypervisor IPA Fault Address Register
AArch64	IFSR32_EL2	Instruction Fault Status Register (EL2)
AArch64	ISR_EL1	Interrupt Status Register
AArch64	VBAR_EL1	Vector Base Address Register (EL1)
AArch64	VBAR_EL2	Vector Base Address Register (EL2)
AArch64	VBAR_EL3	Vector Base Address Register (EL3)

In the Special functional group:

Exec state	Name	Description
AArch32	DLR	Debug Link Register
AArch32	DSPSR	Debug Saved Program Status Register
AArch32	ELR_hyp	Exception Link Register (Hyp mode)
AArch32	SPSR	Saved Program Status Register
AArch32	SPSR_abt	Saved Program Status Register (Abort mode)
AArch32	SPSR_fiq	Saved Program Status Register (FIQ mode)
AArch32	SPSR_hyp	Saved Program Status Register (Hyp mode)
AArch32	SPSR_irq	Saved Program Status Register (IRQ mode)
AArch32	SPSR_mon	Saved Program Status Register (Monitor mode)
AArch32	SPSR_svc	Saved Program Status Register (Supervisor mode)
AArch32	SPSR_und	Saved Program Status Register (Undefined mode)
AArch64	ELR_EL1	Exception Link Register (EL1)
AArch64	ELR_EL2	Exception Link Register (EL2)
AArch64	ELR_EL3	Exception Link Register (EL3)
AArch64	SPSR_EL1	Saved Program Status Register (EL1)
AArch64	SPSR_EL2	Saved Program Status Register (EL2)
AArch64	SPSR_EL3	Saved Program Status Register (EL3)
AArch64	SPSR_abt	Saved Program Status Register (Abort mode)
AArch64	SPSR_fiq	Saved Program Status Register (FIQ mode)
AArch64	SPSR_irq	Saved Program Status Register (IRQ mode)
AArch64	SPSR_und	Saved Program Status Register (Undefined mode)
AArch64	SP_EL0	Stack Pointer (EL0)
AArch64	SP_EL1	Stack Pointer (EL1)
AArch64	SP_EL2	Stack Pointer (EL2)
AArch64	SP_EL3	Stack Pointer (EL3)

In the PSTATE functional group:

Exec state	Name	Description
AArch32	APSR	Application Program Status Register
AArch32	CPSR	Current Program Status Register
AArch64	CurrentEL	Current Exception Level
AArch64	DAIF	Interrupt Mask Bits

Exec state	Name	Description
AArch64	DIT	Data Independent Timing
AArch64	NZCV	Condition Flags
AArch64	PAN	Privileged Access Never
AArch64	SPSel	Stack Pointer Select
AArch64	SSBS	Speculative Store Bypass Safe
AArch64	TCO	Tag Check Override
AArch64	UAO	User Access Override

In the Cache functional group:

Exec state	Name	Description
AArch32	BPIALL	Branch Predictor Invalidate All
AArch32	BPIALLIS	Branch Predictor Invalidate All, Inner Shareable
AArch32	BPIMVA	Branch Predictor Invalidate by VA
AArch32	DCCIMVAC	Data Cache line Clean and Invalidate by VA to PoC
AArch32	DCCISW	Data Cache line Clean and Invalidate by Set/Way
AArch32	DCCMVAC	Data Cache line Clean by VA to PoC
AArch32	DCCMVAU	Data Cache line Clean by VA to PoU
AArch32	DCCSW	Data Cache line Clean by Set/Way
AArch32	DCIMVAC	Data Cache line Invalidate by VA to PoC
AArch32	DCISW	Data Cache line Invalidate by Set/Way
AArch32	ICIALLU	Instruction Cache Invalidate All to PoU
AArch32	ICIALLUIS	Instruction Cache Invalidate All to PoU, Inner Shareable
AArch32	ICIMVAU	Instruction Cache line Invalidate by VA to PoU
AArch64	DC CGDSW	Data, Allocation Tag or unified Cache line Clean of Data and Allocation Tags by Set/Way
AArch64	DC CGDVAC	Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoC
AArch64	DC CGDVADP	Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoDP
AArch64	DC CGDVAP	Data, Allocation Tag or unified Cache line Clean of Data and Allocation Tags by VA to PoP
AArch64	DC CGSW	Data, Allocation Tag or unified Cache line Clean of Allocation Tags by Set/Way
AArch64	DC CGVAC	Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoC
AArch64	DC CGVADP	Data, Allocation Tag or unified Cache line Clean of Data and Allocation Tags by VA to PoDP
AArch64	DC CGVAP	Data, Allocation Tag or unified Cache line Clean of Allocation Tags by VA to PoP
AArch64	DC CIGDSW	Data, Allocation Tag or unified Cache line Clean and Invalidate of Data and Allocation Tags by Set/Way
AArch64	DC CIGDVAC	Data, Allocation Tag or unified Cache line Clean and Invalidate of Data and Allocation Tags by VA to PoC
AArch64	DC CIGSW	Data, Allocation Tag or unified Cache line Clean and Invalidate of Allocation Tags by Set/Way
AArch64	DC CIGVAC	Data, Allocation Tag or unified Cache line Clean and Invalidate of Allocation Tags by VA to PoC
AArch64	DC CISW	Data or unified Cache line Clean and Invalidate by Set/Way
AArch64	DC CIVAC	Data or unified Cache line Clean and Invalidate by VA to PoC
AArch64	DC CSW	Data or unified Cache line Clean by Set/Way
AArch64	DC CVAC	Data or unified Cache line Clean by VA to PoC
AArch64	DC CVADP	Data or unified Cache line Clean by VA to PoDP
AArch64	DC CVAP	Data or unified Cache line Clean by VA to PoP
AArch64	DC CVAU	Data or unified Cache line Clean by VA to PoU
AArch64	DC GVA	Data Cache set Allocation Tag by VA
AArch64	DC GZVA	Data Cache set Allocation Tags and Zero by VA
AArch64	DC IGDSW	Data, Allocation Tag or unified Cache line Invalidate of Data and Allocation Tags by Set/Way
AArch64	DC IGDVAC	Data, Allocation Tag or unified Cache line Invalidate of Allocation Tags by VA to PoC
AArch64	DC IGSW	Data, Allocation Tag or unified Cache line Invalidate of Allocation Tags by Set/Way
AArch64	DC IGVAC	Data, Allocation Tag or unified Cache line Invalidate of Allocation Tags by VA to PoC
AArch64	DC ISW	Data or unified Cache line Invalidate by Set/Way
AArch64	DC IVAC	Data or unified Cache line Invalidate by VA to PoC
AArch64	DC ZVA	Data Cache Zero by VA

Exec state	Name	Description
AArch64	IC IALLU	Instruction Cache Invalidate All to PoU
AArch64	IC IALLUIS	Instruction Cache Invalidate All to PoU, Inner Shareable
AArch64	IC IVAU	Instruction Cache line Invalidate by VA to PoU

In the Address functional group:

Exec state	Name	Description
AArch32	ATS12NSOPR	Address Translate Stages 1 and 2 Non-secure Only PL1 Read
AArch32	ATS12NSOPW	Address Translate Stages 1 and 2 Non-secure Only PL1 Write
AArch32	ATS12NSOUR	Address Translate Stages 1 and 2 Non-secure Only Unprivileged Read
AArch32	ATS12NSOUW	Address Translate Stages 1 and 2 Non-secure Only Unprivileged Write
AArch32	ATS1CPR	Address Translate Stage 1 Current state PL1 Read
AArch32	ATS1CPRP	Address Translate Stage 1 Current state PL1 Read PAN
AArch32	ATS1CPW	Address Translate Stage 1 Current state PL1 Write
AArch32	ATS1CPWP	Address Translate Stage 1 Current state PL1 Write PAN
AArch32	ATS1CUR	Address Translate Stage 1 Current state Unprivileged Read
AArch32	ATS1CUW	Address Translate Stage 1 Current state Unprivileged Write
AArch32	ATS1HR	Address Translate Stage 1 Hyp mode Read
AArch32	ATS1HW	Address Translate Stage 1 Hyp mode Write
AArch32	PAR	Physical Address Register
AArch64	AT S12E0R	Address Translate Stages 1 and 2 EL0 Read
AArch64	AT S12E0W	Address Translate Stages 1 and 2 EL0 Write
AArch64	AT S12E1R	Address Translate Stages 1 and 2 EL1 Read
AArch64	AT S12E1W	Address Translate Stages 1 and 2 EL1 Write
AArch64	AT S1E0R	Address Translate Stage 1 EL0 Read
AArch64	AT S1E0W	Address Translate Stage 1 EL0 Write
AArch64	AT S1E1R	Address Translate Stage 1 EL1 Read
AArch64	AT S1E1RP	Address Translate Stage 1 EL1 Read PAN
AArch64	AT S1E1W	Address Translate Stage 1 EL1 Write
AArch64	AT S1E1WP	Address Translate Stage 1 EL1 Write PAN
AArch64	AT S1E2R	Address Translate Stage 1 EL2 Read
AArch64	AT S1E2W	Address Translate Stage 1 EL2 Write
AArch64	AT S1E3R	Address Translate Stage 1 EL3 Read
AArch64	AT S1E3W	Address Translate Stage 1 EL3 Write
AArch64	PAR_EL1	Physical Address Register

In the TLB functional group:

Exec state	Name	Description
AArch32	CFPRCTX	Control Flow Prediction Restriction by Context
AArch32	CPPRCTX	Cache Prefetch Prediction Restriction by Context
AArch32	DTLBIALL	Data TLB Invalidate All
AArch32	DTLBIASID	Data TLB Invalidate by ASID match
AArch32	DTLBIMVA	Data TLB Invalidate by VA
AArch32	DVPRCTX	Data Value Prediction Restriction by Context
AArch32	ITLBIALL	Instruction TLB Invalidate All
AArch32	ITLBIASID	Instruction TLB Invalidate by ASID match
AArch32	ITLBIMVA	Instruction TLB Invalidate by VA
AArch32	TLBIALL	TLB Invalidate All
AArch32	TLBIALLH	TLB Invalidate All, Hyp mode
AArch32	TLBIALLHIS	TLB Invalidate All, Hyp mode, Inner Shareable
AArch32	TLBIALLIS	TLB Invalidate All, Inner Shareable
AArch32	TLBIALLNSNH	TLB Invalidate All, Non-Secure Non-Hyp
AArch32	TLBIALLNSNHIS	TLB Invalidate All, Non-Secure Non-Hyp, Inner Shareable
AArch32	TLBIASID	TLB Invalidate by ASID match
AArch32	TLBIASIDIS	TLB Invalidate by ASID match, Inner Shareable
AArch32	TLBIIPAS2	TLB Invalidate by Intermediate Physical Address, Stage 2
AArch32	TLBIIPAS2IS	TLB Invalidate by Intermediate Physical Address, Stage 2, Inner Shareable
AArch32	TLBIIPAS2L	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level
AArch32	TLBIIPAS2LIS	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, Inner Shareable

Exec state	Name	Description
AArch32	TLBIMVA	TLB Invalidate by VA
AArch32	TLBIMVAA	TLB Invalidate by VA, All ASID
AArch32	TLBIMVAAIS	TLB Invalidate by VA, All ASID, Inner Shareable
AArch32	TLBIMVAAL	TLB Invalidate by VA, All ASID, Last level
AArch32	TLBIMVAALIS	TLB Invalidate by VA, All ASID, Last level, Inner Shareable
AArch32	TLBIMVAH	TLB Invalidate by VA, Hyp mode
AArch32	TLBIMVAHIS	TLB Invalidate by VA, Hyp mode, Inner Shareable
AArch32	TLBIMVAIS	TLB Invalidate by VA, Inner Shareable
AArch32	TLBIMVAL	TLB Invalidate by VA, Last level
AArch32	TLBIMVALH	TLB Invalidate by VA, Last level, Hyp mode
AArch32	TLBIMVALHIS	TLB Invalidate by VA, Last level, Hyp mode, Inner Shareable
AArch32	TLBIMVALIS	TLB Invalidate by VA, Last level, Inner Shareable
AArch64	TLBI ALLE1	TLB Invalidate All, EL1
AArch64	TLBI ALLE1IS	TLB Invalidate All, EL1, Inner Shareable
AArch64	TLBI ALLE1OS	TLB Invalidate All, EL1, Outer Shareable
AArch64	TLBI ALLE2	TLB Invalidate All, EL2
AArch64	TLBI ALLE2IS	TLB Invalidate All, EL2, Inner Shareable
AArch64	TLBI ALLE2OS	TLB Invalidate All, EL2, Outer Shareable
AArch64	TLBI ALLE3	TLB Invalidate All, EL3
AArch64	TLBI ALLE3IS	TLB Invalidate All, EL3, Inner Shareable
AArch64	TLBI ALLE3OS	TLB Invalidate All, EL3, Outer Shareable
AArch64	TLBI ASIDE1	TLB Invalidate by ASID, EL1
AArch64	TLBI ASIDE1IS	TLB Invalidate by ASID, EL1, Inner Shareable
AArch64	TLBI ASIDE1OS	TLB Invalidate by ASID, EL1, Outer Shareable
AArch64	TLBI IPAS2E1	TLB Invalidate by Intermediate Physical Address, Stage 2, EL1
AArch64	TLBI IPAS2E1IS	TLB Invalidate by Intermediate Physical Address, Stage 2, EL1, Inner Shareable
AArch64	TLBI IPAS2E1OS	TLB Invalidate by Intermediate Physical Address, Stage 2, EL1, Outer Shareable
AArch64	TLBI IPAS2LE1	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1
AArch64	TLBI IPAS2LE1IS	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Inner Shareable
AArch64	TLBI IPAS2LE1OS	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Outer Shareable
AArch64	TLBI RIPAS2E1	TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1
AArch64	TLBI RIPAS2E1IS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1, Inner Shareable
AArch64	TLBI RIPAS2E1OS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1, Outer Shareable
AArch64	TLBI RIPAS2LE1	TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1
AArch64	TLBI RIPAS2LE1IS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Inner Shareable
AArch64	TLBI RIPAS2LE1OS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Outer Shareable
AArch64	TLBI RVAAE1	TLB Range Invalidate by VA, All ASID, EL1
AArch64	TLBI RVAAE1IS	TLB Range Invalidate by VA, All ASID, EL1, Inner Shareable
AArch64	TLBI RVAAE1OS	TLB Range Invalidate by VA, All ASID, EL1, Outer Shareable
AArch64	TLBI RVAALE1	TLB Range Invalidate by VA, All ASID, Last level, EL1
AArch64	TLBI RVAALE1IS	TLB Range Invalidate by VA, All ASID, Last Level, EL1, Inner Shareable
AArch64	TLBI RVAALE1OS	TLB Range Invalidate by VA, All ASID, Last Level, EL1, Outer Shareable
AArch64	TLBI RVAE1	TLB Range Invalidate by VA, EL1
AArch64	TLBI RVAE1IS	TLB Range Invalidate by VA, EL1, Inner Shareable
AArch64	TLBI RVAE1OS	TLB Range Invalidate by VA, EL1, Outer Shareable
AArch64	TLBI RVAE2	TLB Range Invalidate by VA, EL2
AArch64	TLBI RVAE2IS	TLB Range Invalidate by VA, EL2, Inner Shareable
AArch64	TLBI RVAE2OS	TLB Range Invalidate by VA, EL2, Outer Shareable
AArch64	TLBI RVAE3	TLB Range Invalidate by VA, EL3
AArch64	TLBI RVAE3IS	TLB Range Invalidate by VA, EL3, Inner Shareable
AArch64	TLBI RVAE3OS	TLB Range Invalidate by VA, EL3, Outer Shareable
AArch64	TLBI RVALE1	TLB Range Invalidate by VA, Last level, EL1
AArch64	TLBI RVALE1IS	TLB Range Invalidate by VA, Last level, EL1, Inner Shareable
AArch64	TLBI RVALE1OS	TLB Range Invalidate by VA, Last level, EL1, Outer Shareable
AArch64	TLBI RVALE2	TLB Range Invalidate by VA, Last level, EL2
AArch64	TLBI RVALE2IS	TLB Range Invalidate by VA, Last level, EL2, Inner Shareable
AArch64	TLBI RVALE2OS	TLB Range Invalidate by VA, Last level, EL2, Outer Shareable
AArch64	TLBI RVALE3	TLB Range Invalidate by VA, Last level, EL3

Exec state	Name	Description
AArch64	TLBI RVALE3IS	TLB Range Invalidate by VA, Last level, EL3, Inner Shareable
AArch64	TLBI RVALE3OS	TLB Range Invalidate by VA, Last level, EL3, Outer Shareable
AArch64	TLBI VAAE1	TLB Invalidate by VA, All ASID, EL1
AArch64	TLBI VAAE1IS	TLB Invalidate by VA, All ASID, EL1, Inner Shareable
AArch64	TLBI VAAE1OS	TLB Invalidate by VA, All ASID, EL1, Outer Shareable
AArch64	TLBI VAALE1	TLB Invalidate by VA, All ASID, Last level, EL1
AArch64	TLBI VAALE1IS	TLB Invalidate by VA, All ASID, Last Level, EL1, Inner Shareable
AArch64	TLBI VAALE1OS	TLB Invalidate by VA, All ASID, Last Level, EL1, Outer Shareable
AArch64	TLBI VAE1	TLB Invalidate by VA, EL1
AArch64	TLBI VAE1IS	TLB Invalidate by VA, EL1, Inner Shareable
AArch64	TLBI VAE1OS	TLB Invalidate by VA, EL1, Outer Shareable
AArch64	TLBI VAE2	TLB Invalidate by VA, EL2
AArch64	TLBI VAE2IS	TLB Invalidate by VA, EL2, Inner Shareable
AArch64	TLBI VAE2OS	TLB Invalidate by VA, EL2, Outer Shareable
AArch64	TLBI VAE3	TLB Invalidate by VA, EL3
AArch64	TLBI VAE3IS	TLB Invalidate by VA, EL3, Inner Shareable
AArch64	TLBI VAE3OS	TLB Invalidate by VA, EL3, Outer Shareable
AArch64	TLBI VALE1	TLB Invalidate by VA, Last level, EL1
AArch64	TLBI VALE1IS	TLB Invalidate by VA, Last level, EL1, Inner Shareable
AArch64	TLBI VALE1OS	TLB Invalidate by VA, Last level, EL1, Outer Shareable
AArch64	TLBI VALE2	TLB Invalidate by VA, Last level, EL2
AArch64	TLBI VALE2IS	TLB Invalidate by VA, Last level, EL2, Inner Shareable
AArch64	TLBI VALE2OS	TLB Invalidate by VA, Last level, EL2, Outer Shareable
AArch64	TLBI VALE3	TLB Invalidate by VA, Last level, EL3
AArch64	TLBI VALE3IS	TLB Invalidate by VA, Last level, EL3, Inner Shareable
AArch64	TLBI VALE3OS	TLB Invalidate by VA, Last level, EL3, Outer Shareable
AArch64	TLBI VMALLE1	TLB Invalidate by VMID, All at stage 1, EL1
AArch64	TLBI VMALLE1IS	TLB Invalidate by VMID, All at stage 1, EL1, Inner Shareable
AArch64	TLBI VMALLE1OS	TLB Invalidate by VMID, All at stage 1, EL1, Outer Shareable
AArch64	TLBI VMALLS12E1	TLB Invalidate by VMID, All at Stage 1 and 2, EL1
AArch64	TLBI VMALLS12E1IS	TLB Invalidate by VMID, All at Stage 1 and 2, EL1, Inner Shareable
AArch64	TLBI VMALLS12E1OS	TLB Invalidate by VMID, All at Stage 1 and 2, EL1, Outer Shareable

In the PMU functional group:

Exec state	Name	Description
AArch32	PMCCFILTR	Performance Monitors Cycle Count Filter Register
AArch32	PMCCNTR	Performance Monitors Cycle Count Register
AArch32	PMCEID0	Performance Monitors Common Event Identification register 0
AArch32	PMCEID1	Performance Monitors Common Event Identification register 1
AArch32	PMCEID2	Performance Monitors Common Event Identification register 2
AArch32	PMCEID3	Performance Monitors Common Event Identification register 3
AArch32	PMCNTENCLR	Performance Monitors Count Enable Clear register
AArch32	PMCNTENSET	Performance Monitors Count Enable Set register
AArch32	PMCR	Performance Monitors Control Register
AArch32	PMEVCNTR<n>	Performance Monitors Event Count Registers
AArch32	PMEVTYPER<n>	Performance Monitors Event Type Registers
AArch32	PMINTENCLR	Performance Monitors Interrupt Enable Clear register
AArch32	PMINTENSET	Performance Monitors Interrupt Enable Set register
AArch32	PMMIR	Performance Monitors Machine Identification Register
AArch32	PMOVSR	Performance Monitors Overflow Flag Status Register
AArch32	PMOVSSET	Performance Monitors Overflow Flag Status Set register
AArch32	PMSELR	Performance Monitors Event Counter Selection Register
AArch32	PMSWINC	Performance Monitors Software Increment register
AArch32	PMUSERENR	Performance Monitors User Enable Register
AArch32	PMXEVCNTR	Performance Monitors Selected Event Count Register
AArch32	PMXEVTYPER	Performance Monitors Selected Event Type Register
AArch64	PMCCFILTR_EL0	Performance Monitors Cycle Count Filter Register
AArch64	PMCCNTR_EL0	Performance Monitors Cycle Count Register

Exec state	Name	Description
AArch64	PMCEID0_EL0	Performance Monitors Common Event Identification register 0
AArch64	PMCEID1_EL0	Performance Monitors Common Event Identification register 1
AArch64	PMCNTENCLR_EL0	Performance Monitors Count Enable Clear register
AArch64	PMCNTENSET_EL0	Performance Monitors Count Enable Set register
AArch64	PMCR_EL0	Performance Monitors Control Register
AArch64	PMEVCNTR<n>_EL0	Performance Monitors Event Count Registers
AArch64	PMEVTYPER<n>_EL0	Performance Monitors Event Type Registers
AArch64	PMINTENCLR_EL1	Performance Monitors Interrupt Enable Clear register
AArch64	PMINTENSET_EL1	Performance Monitors Interrupt Enable Set register
AArch64	PMMIR_EL1	Performance Monitors Machine Identification Register
AArch64	PMOVSCLR_EL0	Performance Monitors Overflow Flag Status Clear Register
AArch64	PMOVSSET_EL0	Performance Monitors Overflow Flag Status Set register
AArch64	PMSELR_EL0	Performance Monitors Event Counter Selection Register
AArch64	PMSWINC_EL0	Performance Monitors Software Increment register
AArch64	PMUSERENR_EL0	Performance Monitors User Enable Register
AArch64	PMXEVCNTR_EL0	Performance Monitors Selected Event Count Register
AArch64	PMXEVTYPER_EL0	Performance Monitors Selected Event Type Register
External	PMAUTHSTATUS	Performance Monitors Authentication Status register
External	PMCCFILTR_EL0	Performance Monitors Cycle Counter Filter Register
External	PMCCNTR_EL0	Performance Monitors Cycle Counter
External	PMCEID0	Performance Monitors Common Event Identification register 0
External	PMCEID1	Performance Monitors Common Event Identification register 1
External	PMCEID2	Performance Monitors Common Event Identification register 2
External	PMCEID3	Performance Monitors Common Event Identification register 3
External	PMCFGR	Performance Monitors Configuration Register
External	PMCID1SR	CONTEXTIDR_EL1 Sample Register
External	PMCID2SR	CONTEXTIDR_EL2 Sample Register
External	PMCIDR0	Performance Monitors Component Identification Register 0
External	PMCIDR1	Performance Monitors Component Identification Register 1
External	PMCIDR2	Performance Monitors Component Identification Register 2
External	PMCIDR3	Performance Monitors Component Identification Register 3
External	PMCNTENCLR_EL0	Performance Monitors Count Enable Clear register
External	PMCNTENSET_EL0	Performance Monitors Count Enable Set register
External	PMCR_EL0	Performance Monitors Control Register
External	PMDEVAFF0	Performance Monitors Device Affinity register 0
External	PMDEVAFF1	Performance Monitors Device Affinity register 1
External	PMDEVARCH	Performance Monitors Device Architecture register
External	PMDEVID	Performance Monitors Device ID register
External	PMDEVTYPE	Performance Monitors Device Type register
External	PMEVCNTR<n>_EL0	Performance Monitors Event Count Registers
External	PMEVTYPER<n>_EL0	Performance Monitors Event Type Registers
External	PMINTENCLR_EL1	Performance Monitors Interrupt Enable Clear register
External	PMINTENSET_EL1	Performance Monitors Interrupt Enable Set register
External	PMITCTRL	Performance Monitors Integration mode Control register
External	PMLAR	Performance Monitors Lock Access Register
External	PMLSR	Performance Monitors Lock Status Register
External	PMMIR	Performance Monitors Machine Identification Register
External	PMOVSCLR_EL0	Performance Monitors Overflow Flag Status Clear register
External	PMOVSSET_EL0	Performance Monitors Overflow Flag Status Set register
External	PMPCSR	Program Counter Sample Register
External	PMPIDR0	Performance Monitors Peripheral Identification Register 0
External	PMPIDR1	Performance Monitors Peripheral Identification Register 1
External	PMPIDR2	Performance Monitors Peripheral Identification Register 2
External	PMPIDR3	Performance Monitors Peripheral Identification Register 3
External	PMPIDR4	Performance Monitors Peripheral Identification Register 4
External	PMSWINC_EL0	Performance Monitors Software Increment register
External	PMVIDSR	VMID Sample Register

In the Reset functional group:

Exec state	Name	Description
AArch32	HRMR	Hyp Reset Management Register
AArch32	RMR	Reset Management Register

Exec state	Name	Description
AArch32	RVBAR	Reset Vector Base Address Register
AArch64	RMR_EL1	Reset Management Register (EL1)
AArch64	RMR_EL2	Reset Management Register (EL2)
AArch64	RMR_EL3	Reset Management Register (EL3)
AArch64	RVBAR_EL1	Reset Vector Base Address Register (if EL2 and EL3 not implemented)
AArch64	RVBAR_EL2	Reset Vector Base Address Register (if EL3 not implemented)
AArch64	RVBAR_EL3	Reset Vector Base Address Register (if EL3 implemented)

In the Thread functional group:

Exec state	Name	Description
AArch32	HTPIDR	Hyp Software Thread ID Register
AArch32	TPIDRPRW	PL1 Software Thread ID Register
AArch32	TPIDRURO	PL0 Read-Only Software Thread ID Register
AArch32	TPIDRURW	PL0 Read/Write Software Thread ID Register
AArch64	SCXTNUM_EL0	EL0 Read/Write Software Context Number
AArch64	SCXTNUM_EL1	EL1 Read/Write Software Context Number
AArch64	SCXTNUM_EL2	EL2 Read/Write Software Context Number
AArch64	SCXTNUM_EL3	EL3 Read/Write Software Context Number
AArch64	TPIDRRO_EL0	EL0 Read-Only Software Thread ID Register
AArch64	TPIDR_EL0	EL0 Read/Write Software Thread ID Register
AArch64	TPIDR_EL1	EL1 Software Thread ID Register
AArch64	TPIDR_EL2	EL2 Software Thread ID Register
AArch64	TPIDR_EL3	EL3 Software Thread ID Register

In the IMP DEF functional group:

Exec state	Name	Description
AArch32	ACTLR	Auxiliary Control Register
AArch32	ACTLR2	Auxiliary Control Register 2
AArch32	ADFSR	Auxiliary Data Fault Status Register
AArch32	AIDR	Auxiliary ID Register
AArch32	AIFSR	Auxiliary Instruction Fault Status Register
AArch32	AMAIR0	Auxiliary Memory Attribute Indirection Register 0
AArch32	AMAIR1	Auxiliary Memory Attribute Indirection Register 1
AArch32	HACTLR	Hyp Auxiliary Control Register
AArch32	HACTLR2	Hyp Auxiliary Control Register 2
AArch32	HADFSR	Hyp Auxiliary Data Fault Status Register
AArch32	HAIFSR	Hyp Auxiliary Instruction Fault Status Register
AArch32	HAMAIR0	Hyp Auxiliary Memory Attribute Indirection Register 0
AArch32	HAMAIR1	Hyp Auxiliary Memory Attribute Indirection Register 1
AArch64	ACTLR_EL1	Auxiliary Control Register (EL1)
AArch64	ACTLR_EL2	Auxiliary Control Register (EL2)
AArch64	ACTLR_EL3	Auxiliary Control Register (EL3)
AArch64	AFSR0_EL1	Auxiliary Fault Status Register 0 (EL1)
AArch64	AFSR0_EL2	Auxiliary Fault Status Register 0 (EL2)
AArch64	AFSR0_EL3	Auxiliary Fault Status Register 0 (EL3)
AArch64	AFSR1_EL1	Auxiliary Fault Status Register 1 (EL1)
AArch64	AFSR1_EL2	Auxiliary Fault Status Register 1 (EL2)
AArch64	AFSR1_EL3	Auxiliary Fault Status Register 1 (EL3)
AArch64	AIDR_EL1	Auxiliary ID Register
AArch64	AMAIR_EL1	Auxiliary Memory Attribute Indirection Register (EL1)
AArch64	AMAIR_EL2	Auxiliary Memory Attribute Indirection Register (EL2)
AArch64	AMAIR_EL3	Auxiliary Memory Attribute Indirection Register (EL3)
AArch64	HACR_EL2	Hypervisor Auxiliary Control Register
AArch64	S1_<op1>_<Cn>_<Cm>_<op2>	IMPLEMENTATION DEFINED maintenance instructions
AArch64	S3_<op1>_<Cn>_<Cm>_<op2>	IMPLEMENTATION DEFINED registers

In the Timer functional group:

Exec state	Name	Description
AArch32	CNTFRQ	Counter-timer Frequency register
AArch32	CNTHPS_CTL	Counter-timer Secure Physical Timer Control Register (EL2)
AArch32	CNTHPS_CVAL	Counter-timer Secure Physical Timer CompareValue Register (EL2)
AArch32	CNTHPS_TVAL	Counter-timer Secure Physical Timer TimerValue Register (EL2)
AArch32	CNTHP_CTL	Counter-timer Hyp Physical Timer Control register
AArch32	CNTHVS_CTL	Counter-timer Secure Virtual Timer Control Register (EL2)
AArch32	CNTHVS_CVAL	Counter-timer Secure Virtual Timer CompareValue Register (EL2)
AArch32	CNTHVS_TVAL	Counter-timer Secure Virtual Timer TimerValue Register (EL2)
AArch32	CNTHV_CTL	Counter-timer Virtual Timer Control register (EL2)
AArch32	CNTHV_CVAL	Counter-timer Virtual Timer CompareValue register (EL2)
AArch32	CNTHV_TVAL	Counter-timer Virtual Timer TimerValue register (EL2)
AArch32	CNTKCTL	Counter-timer Kernel Control register
AArch32	CNTPCT	Counter-timer Physical Count register
AArch32	CNTPCTSS	Counter-timer Self-Synchronized Physical Count register
AArch32	CNTP_CTL	Counter-timer Physical Timer Control register
AArch32	CNTP_CVAL	Counter-timer Physical Timer CompareValue register
AArch32	CNTP_TVAL	Counter-timer Physical Timer TimerValue register
AArch32	CNTVCT	Counter-timer Virtual Count register
AArch32	CNTVCTSS	Counter-timer Self-Synchronized Virtual Count register
AArch32	CNTV_CTL	Counter-timer Virtual Timer Control register
AArch32	CNTV_CVAL	Counter-timer Virtual Timer CompareValue register
AArch32	CNTV_TVAL	Counter-timer Virtual Timer TimerValue register
AArch64	CNTFRQ_EL0	Counter-timer Frequency register
AArch64	CNTHVS_CTL_EL2	Counter-timer Secure Virtual Timer Control register (EL2)
AArch64	CNTHVS_CVAL_EL2	Counter-timer Secure Virtual Timer CompareValue register (EL2)
AArch64	CNTHVS_TVAL_EL2	Counter-timer Secure Virtual Timer TimerValue register (EL2)
AArch64	CNTHV_CTL_EL2	Counter-timer Virtual Timer Control register (EL2)
AArch64	CNTHV_CVAL_EL2	Counter-timer Virtual Timer CompareValue register (EL2)
AArch64	CNTHV_TVAL_EL2	Counter-timer Virtual Timer TimerValue Register (EL2)
AArch64	CNTKCTL_EL1	Counter-timer Kernel Control register
AArch64	CNTPCTSS_EL0	Counter-timer Self-Synchronized Physical Count register
AArch64	CNTPCT_EL0	Counter-timer Physical Count register
AArch64	CNTPOFF_EL2	Counter-timer Physical Offset register
AArch64	CNTPS_CTL_EL1	Counter-timer Physical Secure Timer Control register
AArch64	CNTPS_CVAL_EL1	Counter-timer Physical Secure Timer CompareValue register
AArch64	CNTPS_TVAL_EL1	Counter-timer Physical Secure Timer TimerValue register
AArch64	CNTP_CTL_EL0	Counter-timer Physical Timer Control register
AArch64	CNTP_CVAL_EL0	Counter-timer Physical Timer CompareValue register
AArch64	CNTP_TVAL_EL0	Counter-timer Physical Timer TimerValue register
AArch64	CNTVCTSS_EL0	Counter-timer Self-Synchronized Virtual Count register
AArch64	CNTVCT_EL0	Counter-timer Virtual Count register
AArch64	CNTV_CTL_EL0	Counter-timer Virtual Timer Control register
AArch64	CNTV_CVAL_EL0	Counter-timer Virtual Timer CompareValue register
AArch64	CNTV_TVAL_EL0	Counter-timer Virtual Timer TimerValue register
External	CNTACR<n>	Counter-timer Access Control Registers
External	CNTCR	Counter Control Register
External	CNTCV	Counter Count Value register
External	CNTEL0ACR	Counter-timer EL0 Access Control Register
External	CNTFID0	Counter Frequency ID
External	CNTFID<n>	Counter Frequency IDs, n > 0
External	CNTFRQ	Counter-timer Frequency
External	CNTID	Counter Identification Register
External	CNTNSAR	Counter-timer Non-secure Access Register
External	CNTPCT	Counter-timer Physical Count
External	CNTP_CTL	Counter-timer Physical Timer Control
External	CNTP_CVAL	Counter-timer Physical Timer CompareValue
External	CNTP_TVAL	Counter-timer Physical Timer TimerValue
External	CNTSCR	Counter Scale Register
External	CNTSR	Counter Status Register
External	CNTTIDR	Counter-timer Timer ID Register
External	CNTVCT	Counter-timer Virtual Count
External	CNTVOFF	Counter-timer Virtual Offset

Exec state	Name	Description
External	CNTVOFF<n>	Counter-timer Virtual Offsets
External	CNTV_CTL	Counter-timer Virtual Timer Control
External	CNTV_CVAL	Counter-timer Virtual Timer CompareValue
External	CNTV_TVAL	Counter-timer Virtual Timer TimerValue
External	CounterID<n>	Counter ID registers

In the Debug functional group:

Exec state	Name	Description
AArch32	DBGAUTHSTATUS	Debug Authentication Status register
AArch32	DBGBCR<n>	Debug Breakpoint Control Registers
AArch32	DBGBVR<n>	Debug Breakpoint Value Registers
AArch32	DBGBXVR<n>	Debug Breakpoint Extended Value Registers
AArch32	DBGCLAIMCLR	Debug CLAIM Tag Clear register
AArch32	DBGCLAIMSET	Debug CLAIM Tag Set register
AArch32	DBGDCCINT	DCC Interrupt Enable Register
AArch32	DBGDEVID	Debug Device ID register 0
AArch32	DBGDEVID1	Debug Device ID register 1
AArch32	DBGDEVID2	Debug Device ID register 2
AArch32	DBGDIDR	Debug ID Register
AArch32	DBGDRAR	Debug ROM Address Register
AArch32	DBGDSAR	Debug Self Address Register
AArch32	DBGDSCRext	Debug Status and Control Register, External View
AArch32	DBGDSCRint	Debug Status and Control Register, Internal View
AArch32	DBGDTRRXext	Debug OS Lock Data Transfer Register, Receive, External View
AArch32	DBGDTRRXint	Debug Data Transfer Register, Receive
AArch32	DBGDTRTXext	Debug OS Lock Data Transfer Register, Transmit
AArch32	DBGDTRTXint	Debug Data Transfer Register, Transmit
AArch32	DBGOSDLR	Debug OS Double Lock Register
AArch32	DBGOSECCR	Debug OS Lock Exception Catch Control Register
AArch32	DBGOSLAR	Debug OS Lock Access Register
AArch32	DBGOSLSR	Debug OS Lock Status Register
AArch32	DBGPRCR	Debug Power Control Register
AArch32	DBGVCR	Debug Vector Catch Register
AArch32	DBGWCR<n>	Debug Watchpoint Control Registers
AArch32	DBGWFAR	Debug Watchpoint Fault Address Register
AArch32	DBGWVR<n>	Debug Watchpoint Value Registers
AArch32	TRFCR	Trace Filter Control Register
AArch64	DBGAUTHSTATUS_EL1	Debug Authentication Status register
AArch64	DBGBCR<n>_EL1	Debug Breakpoint Control Registers
AArch64	DBGBVR<n>_EL1	Debug Breakpoint Value Registers
AArch64	DBGCLAIMCLR_EL1	Debug CLAIM Tag Clear register
AArch64	DBGCLAIMSET_EL1	Debug CLAIM Tag Set register
AArch64	DBGDTRRX_EL0	Debug Data Transfer Register, Receive
AArch64	DBGDTRTX_EL0	Debug Data Transfer Register, Transmit
AArch64	DBGDTR_EL0	Debug Data Transfer Register, half-duplex
AArch64	DBGPRCR_EL1	Debug Power Control Register
AArch64	DBGVCR32_EL2	Debug Vector Catch Register
AArch64	DBGWCR<n>_EL1	Debug Watchpoint Control Registers
AArch64	DBGWVR<n>_EL1	Debug Watchpoint Value Registers
AArch64	DLR_EL0	Debug Link Register
AArch64	DSPSR_EL0	Debug Saved Program Status Register
AArch64	MDCCINT_EL1	Monitor DCC Interrupt Enable Register
AArch64	MDCCSR_EL0	Monitor DCC Status Register
AArch64	MDRAR_EL1	Monitor Debug ROM Address Register
AArch64	MDSCR_EL1	Monitor Debug System Control Register
AArch64	OSDLR_EL1	OS Double Lock Register
AArch64	OSDTRRX_EL1	OS Lock Data Transfer Register, Receive
AArch64	OSDTRTX_EL1	OS Lock Data Transfer Register, Transmit
AArch64	OSECCR_EL1	OS Lock Exception Catch Control Register
AArch64	OSLAR_EL1	OS Lock Access Register
AArch64	OSLSR_EL1	OS Lock Status Register
AArch64	TRFCR_EL1	Trace Filter Control Register (EL1)

Exec state	Name	Description
AArch64	TRFCR_EL2	Trace Filter Control Register (EL2)
External	DBGAUTHSTATUS_EL1	Debug Authentication Status register
External	DBGBCR<n>_EL1	Debug Breakpoint Control Registers
External	DBGBVR<n>_EL1	Debug Breakpoint Value Registers
External	DBGCLAIMCLR_EL1	Debug CLAIM Tag Clear register
External	DBGCLAIMSET_EL1	Debug CLAIM Tag Set register
External	DBGDTRRX_EL0	Debug Data Transfer Register, Receive
External	DBGDTRTX_EL0	Debug Data Transfer Register, Transmit
External	DBGWCR<n>_EL1	Debug Watchpoint Control Registers
External	DBGWVR<n>_EL1	Debug Watchpoint Value Registers
External	EDACR	External Debug Auxiliary Control Register
External	EDCIDR0	External Debug Component Identification Register 0
External	EDCIDR1	External Debug Component Identification Register 1
External	EDCIDR2	External Debug Component Identification Register 2
External	EDCIDR3	External Debug Component Identification Register 3
External	EDCIDSR	External Debug Context ID Sample Register
External	EDDEVAFF0	External Debug Device Affinity register 0
External	EDDEVAFF1	External Debug Device Affinity register 1
External	EDDEVARCH	External Debug Device Architecture register
External	EDDEVID	External Debug Device ID register 0
External	EDDEVID1	External Debug Device ID register 1
External	EDDEVID2	External Debug Device ID register 2
External	EDDEVTYPE	External Debug Device Type register
External	EDECCR	External Debug Exception Catch Control Register
External	EDECR	External Debug Execution Control Register
External	EDESR	External Debug Event Status Register
External	EDITCTRL	External Debug Integration mode Control register
External	EDITR	External Debug Instruction Transfer Register
External	EDLAR	External Debug Lock Access Register
External	EDLSR	External Debug Lock Status Register
External	EDPCSR	External Debug Program Counter Sample Register
External	EDPIDR0	External Debug Peripheral Identification Register 0
External	EDPIDR1	External Debug Peripheral Identification Register 1
External	EDPIDR2	External Debug Peripheral Identification Register 2
External	EDPIDR3	External Debug Peripheral Identification Register 3
External	EDPIDR4	External Debug Peripheral Identification Register 4
External	EDPRCR	External Debug Power/Reset Control Register
External	EDPRSR	External Debug Processor Status Register
External	EDRCR	External Debug Reserve Control Register
External	EDSCR	External Debug Status and Control Register
External	EDVIDSR	External Debug Virtual Context Sample Register
External	EDWAR	External Debug Watchpoint Address Register
External	OSLAR_EL1	OS Lock Access Register

In the CTI functional group:

Exec state	Name	Description
External	ASICCTL	CTI External Multiplexer Control register
External	CTIAPPCLEAR	CTI Application Trigger Clear register
External	CTIAPPPULSE	CTI Application Pulse register
External	CTIAPPSET	CTI Application Trigger Set register
External	CTIAUTHSTATUS	CTI Authentication Status register
External	CTICHINSTATUS	CTI Channel In Status register
External	CTICHOUTSTATUS	CTI Channel Out Status register
External	CTICIDR0	CTI Component Identification Register 0
External	CTICIDR1	CTI Component Identification Register 1
External	CTICIDR2	CTI Component Identification Register 2
External	CTICIDR3	CTI Component Identification Register 3
External	CTICLAIMCLR	CTI CLAIM Tag Clear register
External	CTICLAIMSET	CTI CLAIM Tag Set register
External	CTICONTROL	CTI Control register
External	CTIDEVAFF0	CTI Device Affinity register 0
External	CTIDEVAFF1	CTI Device Affinity register 1

Exec state	Name	Description
External	CTIDEVARCH	CTI Device Architecture register
External	CTIDEVCTL	CTI Device Control register
External	CTIDEVID	CTI Device ID register 0
External	CTIDEVID1	CTI Device ID register 1
External	CTIDEVID2	CTI Device ID register 2
External	CTIDEVTYPE	CTI Device Type register
External	CTIGATE	CTI Channel Gate Enable register
External	CTIINEN<n>	CTI Input Trigger to Output Channel Enable registers
External	CTIINTACK	CTI Output Trigger Acknowledge register
External	CTIITCTRL	CTI Integration mode Control register
External	CTILAR	CTI Lock Access Register
External	CTILSR	CTI Lock Status Register
External	CTIOUTEN<n>	CTI Input Channel to Output Trigger Enable registers
External	CTIPIDR0	CTI Peripheral Identification Register 0
External	CTIPIDR1	CTI Peripheral Identification Register 1
External	CTIPIDR2	CTI Peripheral Identification Register 2
External	CTIPIDR3	CTI Peripheral Identification Register 3
External	CTIPIDR4	CTI Peripheral Identification Register 4
External	CTITRIGINSTATUS	CTI Trigger In Status register
External	CTITRIGOUTSTATUS	CTI Trigger Out Status register

In the Virt functional group:

Exec state	Name	Description
AArch32	ATS1HR	Address Translate Stage 1 Hyp mode Read
AArch32	ATS1HW	Address Translate Stage 1 Hyp mode Write
AArch32	CNTHCTL	Counter-timer Hyp Control register
AArch32	CNTHP_CVAL	Counter-timer Hyp Physical CompareValue register
AArch32	CNTHP_TVAL	Counter-timer Hyp Physical Timer TimerValue register
AArch32	CNTVOFF	Counter-timer Virtual Offset register
AArch32	HACR	Hyp Auxiliary Configuration Register
AArch32	HACTLR	Hyp Auxiliary Control Register
AArch32	HACTLR2	Hyp Auxiliary Control Register 2
AArch32	HADFSR	Hyp Auxiliary Data Fault Status Register
AArch32	HAIFSR	Hyp Auxiliary Instruction Fault Status Register
AArch32	HAMAIR0	Hyp Auxiliary Memory Attribute Indirection Register 0
AArch32	HAMAIR1	Hyp Auxiliary Memory Attribute Indirection Register 1
AArch32	HCPTR	Hyp Architectural Feature Trap Register
AArch32	HCR	Hyp Configuration Register
AArch32	HCR2	Hyp Configuration Register 2
AArch32	HDCR	Hyp Debug Control Register
AArch32	HDFAR	Hyp Data Fault Address Register
AArch32	HIFAR	Hyp Instruction Fault Address Register
AArch32	HMAIR0	Hyp Memory Attribute Indirection Register 0
AArch32	HMAIR1	Hyp Memory Attribute Indirection Register 1
AArch32	HPFAR	Hyp IPA Fault Address Register
AArch32	HRMR	Hyp Reset Management Register
AArch32	HSCTLR	Hyp System Control Register
AArch32	HSR	Hyp Syndrome Register
AArch32	HSTR	Hyp System Trap Register
AArch32	HTCR	Hyp Translation Control Register
AArch32	HTPIDR	Hyp Software Thread ID Register
AArch32	HTRFCR	Hyp Trace Filter Control Register
AArch32	HTTBR	Hyp Translation Table Base Register
AArch32	HVBAR	Hyp Vector Base Address Register
AArch32	ICC_HSRE	Interrupt Controller Hyp System Register Enable register
AArch32	ICH_AP0R<n>	Interrupt Controller Hyp Active Priorities Group 0 Registers
AArch32	ICH_AP1R<n>	Interrupt Controller Hyp Active Priorities Group 1 Registers
AArch32	ICH_EISR	Interrupt Controller End of Interrupt Status Register
AArch32	ICH_ELRSR	Interrupt Controller Empty List Register Status Register
AArch32	ICH_HCR	Interrupt Controller Hyp Control Register
AArch32	ICH_LR<n>	Interrupt Controller List Registers

Exec state	Name	Description
AArch32	ICH_LRC<n>	Interrupt Controller List Registers
AArch32	ICH_MISR	Interrupt Controller Maintenance Interrupt State Register
AArch32	ICH_VMCR	Interrupt Controller Virtual Machine Control Register
AArch32	ICH_VTR	Interrupt Controller VGIC Type Register
AArch32	TLBIALLH	TLB Invalidate All, Hyp mode
AArch32	TLBIALLHIS	TLB Invalidate All, Hyp mode, Inner Shareable
AArch32	TLBIIPAS2	TLB Invalidate by Intermediate Physical Address, Stage 2
AArch32	TLBIIPAS2IS	TLB Invalidate by Intermediate Physical Address, Stage 2, Inner Shareable
AArch32	TLBIIPAS2L	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level
AArch32	TLBIIPAS2LIS	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, Inner Shareable
AArch32	TLBIMVAH	TLB Invalidate by VA, Hyp mode
AArch32	TLBIMVAHIS	TLB Invalidate by VA, Hyp mode, Inner Shareable
AArch32	TLBIMVALH	TLB Invalidate by VA, Last level, Hyp mode
AArch32	TLBIMVALHIS	TLB Invalidate by VA, Last level, Hyp mode, Inner Shareable
AArch32	VMPIDR	Virtualization Multiprocessor ID Register
AArch32	VPIDR	Virtualization Processor ID Register
AArch32	VTCR	Virtualization Translation Control Register
AArch32	VTTBR	Virtualization Translation Table Base Register
AArch64	ACTLR_EL2	Auxiliary Control Register (EL2)
AArch64	AFSR0_EL2	Auxiliary Fault Status Register 0 (EL2)
AArch64	AFSR1_EL2	Auxiliary Fault Status Register 1 (EL2)
AArch64	AMAIR_EL2	Auxiliary Memory Attribute Indirection Register (EL2)
AArch64	CNTHCTL_EL2	Counter-timer Hypervisor Control register
AArch64	CNTHPS_CTL_EL2	Counter-timer Secure Physical Timer Control register (EL2)
AArch64	CNTHPS_CVAL_EL2	Counter-timer Secure Physical Timer CompareValue register (EL2)
AArch64	CNTHPS_TVAL_EL2	Counter-timer Secure Physical Timer TimerValue register (EL2)
AArch64	CNTHP_CTL_EL2	Counter-timer Hypervisor Physical Timer Control register
AArch64	CNTHP_CVAL_EL2	Counter-timer Physical Timer CompareValue register (EL2)
AArch64	CNTHP_TVAL_EL2	Counter-timer Physical Timer TimerValue register (EL2)
AArch64	CNTVOFF_EL2	Counter-timer Virtual Offset register
AArch64	CPTR_EL2	Architectural Feature Trap Register (EL2)
AArch64	ESR_EL2	Exception Syndrome Register (EL2)
AArch64	FAR_EL2	Fault Address Register (EL2)
AArch64	HACR_EL2	Hypervisor Auxiliary Control Register
AArch64	HCR_EL2	Hypervisor Configuration Register
AArch64	HPFAR_EL2	Hypervisor IPA Fault Address Register
AArch64	HSTR_EL2	Hypervisor System Trap Register
AArch64	ICC_SRE_EL2	Interrupt Controller System Register Enable register (EL2)
AArch64	ICH_AP0R<n>_EL2	Interrupt Controller Hyp Active Priorities Group 0 Registers
AArch64	ICH_AP1R<n>_EL2	Interrupt Controller Hyp Active Priorities Group 1 Registers
AArch64	ICH_EISR_EL2	Interrupt Controller End of Interrupt Status Register
AArch64	ICH_ELRSR_EL2	Interrupt Controller Empty List Register Status Register
AArch64	ICH_HCR_EL2	Interrupt Controller Hyp Control Register
AArch64	ICH_LR<n>_EL2	Interrupt Controller List Registers
AArch64	ICH_MISR_EL2	Interrupt Controller Maintenance Interrupt State Register
AArch64	ICH_VMCR_EL2	Interrupt Controller Virtual Machine Control Register
AArch64	ICH_VTR_EL2	Interrupt Controller VGIC Type Register
AArch64	MAIR_EL2	Memory Attribute Indirection Register (EL2)
AArch64	MDCR_EL2	Monitor Debug Configuration Register (EL2)
AArch64	RMR_EL2	Reset Management Register (EL2)
AArch64	SCTLR_EL2	System Control Register (EL2)
AArch64	TCR_EL2	Translation Control Register (EL2)
AArch64	TLBI IPAS2E1	TLB Invalidate by Intermediate Physical Address, Stage 2, EL1
AArch64	TLBI IPAS2E1IS	TLB Invalidate by Intermediate Physical Address, Stage 2, EL1, Inner Shareable
AArch64	TLBI IPAS2E1OS	TLB Invalidate by Intermediate Physical Address, Stage 2, EL1, Outer Shareable
AArch64	TLBI IPAS2LE1	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1
AArch64	TLBI IPAS2LE1IS	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Inner Shareable
AArch64	TLBI IPAS2LE1OS	TLB Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Outer Shareable
AArch64	TLBI RIPAS2E1	TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1

Exec state	Name	Description
AArch64	TLBI RIPAS2E1IS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1, Inner Shareable
AArch64	TLBI RIPAS2E1OS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, EL1, Outer Shareable
AArch64	TLBI RIPAS2LE1	TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1
AArch64	TLBI RIPAS2LE1IS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Inner Shareable
AArch64	TLBI RIPAS2LE1OS	TLB Range Invalidate by Intermediate Physical Address, Stage 2, Last level, EL1, Outer Shareable
AArch64	TPIDR_EL2	EL2 Software Thread ID Register
AArch64	TTBR0_EL2	Translation Table Base Register 0 (EL2)
AArch64	TTBR1_EL2	Translation Table Base Register 1 (EL2)
AArch64	VBAR_EL2	Vector Base Address Register (EL2)
AArch64	VMPIDR_EL2	Virtualization Multiprocessor ID Register
AArch64	VPIDR_EL2	Virtualization Processor ID Register
AArch64	VTCR_EL2	Virtualization Translation Control Register
AArch64	VTTBR_EL2	Virtualization Translation Table Base Register

In the Secure functional group:

Exec state	Name	Description
AArch32	ICC_MCTLR	Interrupt Controller Monitor Control Register
AArch32	ICC_MSRE	Interrupt Controller Monitor System Register Enable register
AArch32	MVBAR	Monitor Vector Base Address Register
AArch32	NSACR	Non-Secure Access Control Register
AArch32	SCR	Secure Configuration Register
AArch32	SDCR	Secure Debug Control Register
AArch32	SDER	Secure Debug Enable Register
AArch64	ACTLR_EL3	Auxiliary Control Register (EL3)
AArch64	AFSR0_EL3	Auxiliary Fault Status Register 0 (EL3)
AArch64	AFSR1_EL3	Auxiliary Fault Status Register 1 (EL3)
AArch64	AMAIR_EL3	Auxiliary Memory Attribute Indirection Register (EL3)
AArch64	CPTR_EL3	Architectural Feature Trap Register (EL3)
AArch64	ICC_CTLR_EL3	Interrupt Controller Control Register (EL3)
AArch64	ICC_SRE_EL3	Interrupt Controller System Register Enable register (EL3)
AArch64	MDCR_EL3	Monitor Debug Configuration Register (EL3)
AArch64	SCR_EL3	Secure Configuration Register
AArch64	SDER32_EL3	AArch32 Secure Debug Enable Register
AArch64	VBAR_EL3	Vector Base Address Register (EL3)

In the Float functional group:

Exec state	Name	Description
AArch32	FPEXC	Floating-Point Exception Control register
AArch32	FPSCR	Floating-Point Status and Control Register
AArch32	FPSID	Floating-Point System ID register
AArch32	MVFR0	Media and VFP Feature Register 0
AArch32	MVFR1	Media and VFP Feature Register 1
AArch32	MVFR2	Media and VFP Feature Register 2
AArch64	FPCR	Floating-point Control Register
AArch64	FPEXC32_EL2	Floating-Point Exception Control register
AArch64	FPSR	Floating-point Status Register
AArch64	MVFR0_EL1	AArch32 Media and VFP Feature Register 0
AArch64	MVFR1_EL1	AArch32 Media and VFP Feature Register 1
AArch64	MVFR2_EL1	AArch32 Media and VFP Feature Register 2

In the Legacy functional group:

Exec state	Name	Description
AArch32	CP15DMB	Data Memory Barrier System instruction

Exec state	Name	Description
AArch32	CP15DSB	Data Synchronization Barrier System instruction
AArch32	CP15ISB	Instruction Synchronization Barrier System instruction
AArch32	FCSEIDR	FCSE Process ID register
AArch32	JIDR	Jazelle ID Register
AArch32	JMCR	Jazelle Main Configuration Register
AArch32	JOSCR	Jazelle OS Control Register

In the GIC functional group:

Exec state	Name	Description
AArch32	ICC_AP0R<n>	Interrupt Controller Active Priorities Group 0 Registers
AArch32	ICC_AP1R<n>	Interrupt Controller Active Priorities Group 1 Registers
AArch32	ICC_ASGI1R	Interrupt Controller Alias Software Generated Interrupt Group 1 Register
AArch32	ICC_BPR0	Interrupt Controller Binary Point Register 0
AArch32	ICC_BPR1	Interrupt Controller Binary Point Register 1
AArch32	ICC_CTLR	Interrupt Controller Control Register
AArch32	ICC_DIR	Interrupt Controller Deactivate Interrupt Register
AArch32	ICC_EOIR0	Interrupt Controller End Of Interrupt Register 0
AArch32	ICC_EOIR1	Interrupt Controller End Of Interrupt Register 1
AArch32	ICC_HPPIR0	Interrupt Controller Highest Priority Pending Interrupt Register 0
AArch32	ICC_HPPIR1	Interrupt Controller Highest Priority Pending Interrupt Register 1
AArch32	ICC_HSRE	Interrupt Controller Hyp System Register Enable register
AArch32	ICC_IAR0	Interrupt Controller Interrupt Acknowledge Register 0
AArch32	ICC_IAR1	Interrupt Controller Interrupt Acknowledge Register 1
AArch32	ICC_IGRPEN0	Interrupt Controller Interrupt Group 0 Enable register
AArch32	ICC_IGRPEN1	Interrupt Controller Interrupt Group 1 Enable register
AArch32	ICC_MCTLR	Interrupt Controller Monitor Control Register
AArch32	ICC_MGRPEN1	Interrupt Controller Monitor Interrupt Group 1 Enable register
AArch32	ICC_MSRE	Interrupt Controller Monitor System Register Enable register
AArch32	ICC_PMR	Interrupt Controller Interrupt Priority Mask Register
AArch32	ICC_RPR	Interrupt Controller Running Priority Register
AArch32	ICC_SGI0R	Interrupt Controller Software Generated Interrupt Group 0 Register
AArch32	ICC_SGI1R	Interrupt Controller Software Generated Interrupt Group 1 Register
AArch32	ICC_SRE	Interrupt Controller System Register Enable register
AArch32	ICH_AP0R<n>	Interrupt Controller Hyp Active Priorities Group 0 Registers
AArch32	ICH_AP1R<n>	Interrupt Controller Hyp Active Priorities Group 1 Registers
AArch32	ICH_EISR	Interrupt Controller End of Interrupt Status Register
AArch32	ICH_ELRSR	Interrupt Controller Empty List Register Status Register
AArch32	ICH_HCR	Interrupt Controller Hyp Control Register
AArch32	ICH_LR<n>	Interrupt Controller List Registers
AArch32	ICH_LRC<n>	Interrupt Controller List Registers
AArch32	ICH_MISR	Interrupt Controller Maintenance Interrupt State Register
AArch32	ICH_VMCR	Interrupt Controller Virtual Machine Control Register
AArch32	ICH_VTR	Interrupt Controller VGIC Type Register
AArch32	ICV_AP0R<n>	Interrupt Controller Virtual Active Priorities Group 0 Registers
AArch32	ICV_AP1R<n>	Interrupt Controller Virtual Active Priorities Group 1 Registers
AArch32	ICV_BPR0	Interrupt Controller Virtual Binary Point Register 0
AArch32	ICV_BPR1	Interrupt Controller Virtual Binary Point Register 1
AArch32	ICV_CTLR	Interrupt Controller Virtual Control Register
AArch32	ICV_DIR	Interrupt Controller Deactivate Virtual Interrupt Register
AArch32	ICV_EOIR0	Interrupt Controller Virtual End Of Interrupt Register 0
AArch32	ICV_EOIR1	Interrupt Controller Virtual End Of Interrupt Register 1
AArch32	ICV_HPPIR0	Interrupt Controller Virtual Highest Priority Pending Interrupt Register 0
AArch32	ICV_HPPIR1	Interrupt Controller Virtual Highest Priority Pending Interrupt Register 1
AArch32	ICV_IAR0	Interrupt Controller Virtual Interrupt Acknowledge Register 0
AArch32	ICV_IAR1	Interrupt Controller Virtual Interrupt Acknowledge Register 1
AArch32	ICV_IGRPEN0	Interrupt Controller Virtual Interrupt Group 0 Enable register
AArch32	ICV_IGRPEN1	Interrupt Controller Virtual Interrupt Group 1 Enable register
AArch32	ICV_PMR	Interrupt Controller Virtual Interrupt Priority Mask Register
AArch32	ICV_RPR	Interrupt Controller Virtual Running Priority Register
AArch64	ICC_AP0R<n>_EL1	Interrupt Controller Active Priorities Group 0 Registers
AArch64	ICC_AP1R<n>_EL1	Interrupt Controller Active Priorities Group 1 Registers
AArch64	ICC_ASGI1R_EL1	Interrupt Controller Alias Software Generated Interrupt Group 1 Register

Exec state	Name	Description
AArch64	ICC_BPR0_EL1	Interrupt Controller Binary Point Register 0
AArch64	ICC_BPR1_EL1	Interrupt Controller Binary Point Register 1
AArch64	ICC_CTLR_EL1	Interrupt Controller Control Register (EL1)
AArch64	ICC_CTLR_EL3	Interrupt Controller Control Register (EL3)
AArch64	ICC_DIR_EL1	Interrupt Controller Deactivate Interrupt Register
AArch64	ICC_EOIR0_EL1	Interrupt Controller End Of Interrupt Register 0
AArch64	ICC_EOIR1_EL1	Interrupt Controller End Of Interrupt Register 1
AArch64	ICC_HPPIR0_EL1	Interrupt Controller Highest Priority Pending Interrupt Register 0
AArch64	ICC_HPPIR1_EL1	Interrupt Controller Highest Priority Pending Interrupt Register 1
AArch64	ICC_IAR0_EL1	Interrupt Controller Interrupt Acknowledge Register 0
AArch64	ICC_IAR1_EL1	Interrupt Controller Interrupt Acknowledge Register 1
AArch64	ICC_IGRPEN0_EL1	Interrupt Controller Interrupt Group 0 Enable register
AArch64	ICC_IGRPEN1_EL1	Interrupt Controller Interrupt Group 1 Enable register
AArch64	ICC_IGRPEN1_EL3	Interrupt Controller Interrupt Group 1 Enable register (EL3)
AArch64	ICC_PMR_EL1	Interrupt Controller Interrupt Priority Mask Register
AArch64	ICC_RPR_EL1	Interrupt Controller Running Priority Register
AArch64	ICC_SGI0R_EL1	Interrupt Controller Software Generated Interrupt Group 0 Register
AArch64	ICC_SGI1R_EL1	Interrupt Controller Software Generated Interrupt Group 1 Register
AArch64	ICC_SRE_EL1	Interrupt Controller System Register Enable register (EL1)
AArch64	ICC_SRE_EL2	Interrupt Controller System Register Enable register (EL2)
AArch64	ICC_SRE_EL3	Interrupt Controller System Register Enable register (EL3)
AArch64	ICH_AP0R<n>_EL2	Interrupt Controller Hyp Active Priorities Group 0 Registers
AArch64	ICH_AP1R<n>_EL2	Interrupt Controller Hyp Active Priorities Group 1 Registers
AArch64	ICH_EISR_EL2	Interrupt Controller End of Interrupt Status Register
AArch64	ICH_ELRSR_EL2	Interrupt Controller Empty List Register Status Register
AArch64	ICH_HCR_EL2	Interrupt Controller Hyp Control Register
AArch64	ICH_LR<n>_EL2	Interrupt Controller List Registers
AArch64	ICH_MISR_EL2	Interrupt Controller Maintenance Interrupt State Register
AArch64	ICH_VMCR_EL2	Interrupt Controller Virtual Machine Control Register
AArch64	ICH_VTR_EL2	Interrupt Controller VGIC Type Register
AArch64	ICV_AP0R<n>_EL1	Interrupt Controller Virtual Active Priorities Group 0 Registers
AArch64	ICV_AP1R<n>_EL1	Interrupt Controller Virtual Active Priorities Group 1 Registers
AArch64	ICV_BPR0_EL1	Interrupt Controller Virtual Binary Point Register 0
AArch64	ICV_BPR1_EL1	Interrupt Controller Virtual Binary Point Register 1
AArch64	ICV_CTLR_EL1	Interrupt Controller Virtual Control Register
AArch64	ICV_DIR_EL1	Interrupt Controller Deactivate Virtual Interrupt Register
AArch64	ICV_EOIR0_EL1	Interrupt Controller Virtual End Of Interrupt Register 0
AArch64	ICV_EOIR1_EL1	Interrupt Controller Virtual End Of Interrupt Register 1
AArch64	ICV_HPPIR0_EL1	Interrupt Controller Virtual Highest Priority Pending Interrupt Register 0
AArch64	ICV_HPPIR1_EL1	Interrupt Controller Virtual Highest Priority Pending Interrupt Register 1
AArch64	ICV_IAR0_EL1	Interrupt Controller Virtual Interrupt Acknowledge Register 0
AArch64	ICV_IAR1_EL1	Interrupt Controller Virtual Interrupt Acknowledge Register 1
AArch64	ICV_IGRPEN0_EL1	Interrupt Controller Virtual Interrupt Group 0 Enable register
AArch64	ICV_IGRPEN1_EL1	Interrupt Controller Virtual Interrupt Group 1 Enable register
AArch64	ICV_PMR_EL1	Interrupt Controller Virtual Interrupt Priority Mask Register
AArch64	ICV_RPR_EL1	Interrupt Controller Virtual Running Priority Register

In the GICD functional group:

Exec state	Name	Description
External	GICD_CLRSPI_NSR	Clear Non-secure SPI Pending Register
External	GICD_CLRSPI_SR	Clear Secure SPI Pending Register
External	GICD_CPENDSGIR<n>	SGI Clear-Pending Registers
External	GICD_CTLR	Distributor Control Register
External	GICD_ICACTIVER<n>	Interrupt Clear-Active Registers
External	GICD_ICACTIVER<n>E	Interrupt Clear-Active Registers (extended SPI range)
External	GICD_ICENABLER<n>	Interrupt Clear-Enable Registers
External	GICD_ICENABLER<n>E	Interrupt Clear-Enable Registers
External	GICD_ICFGR<n>	Interrupt Configuration Registers
External	GICD_ICFGR<n>E	Interrupt Configuration Registers (Extended SPI Range)
External	GICD_ICPENDR<n>	Interrupt Clear-Pending Registers
External	GICD_ICPENDR<n>E	Interrupt Clear-Pending Registers (extended SPI range)

Exec state	Name	Description
External	GICD_IGROUPR<n>	Interrupt Group Registers
External	GICD_IGROUPR<n>E	Interrupt Group Registers (extended SPI range)
External	GICD_IGRPMODR<n>	Interrupt Group Modifier Registers
External	GICD_IGRPMODR<n>E	Interrupt Group Modifier Registers (extended SPI range)
External	GICD_IIDR	Distributor Implementer Identification Register
External	GICD_IPRIORITYR<n>	Interrupt Priority Registers
External	GICD_IPRIORITYR<n>E	Holds the priority of the corresponding interrupt for each extended SPI supported by the GIC.
External	GICD_IROUTER<n>	Interrupt Routing Registers
External	GICD_IROUTER<n>E	Interrupt Routing Registers (Extended SPI Range)
External	GICD_ISACTIVER<n>	Interrupt Set-Active Registers
External	GICD_ISACTIVER<n>E	Interrupt Set-Active Registers (extended SPI range)
External	GICD_ISENABLER<n>	Interrupt Set-Enable Registers
External	GICD_ISENABLER<n>E	Interrupt Set-Enable Registers
External	GICD_ISPENDR<n>	Interrupt Set-Pending Registers
External	GICD_ISPENDR<n>E	Interrupt Set-Pending Registers (extended SPI range)
External	GICD_ITARGETSR<n>	Interrupt Processor Targets Registers
External	GICD_NSACR<n>	Non-secure Access Control Registers
External	GICD_NSACR<n>E	Non-secure Access Control Registers
External	GICD_SETSPI_NSR	Set Non-secure SPI Pending Register
External	GICD_SETSPI_SR	Set Secure SPI Pending Register
External	GICD_SGIR	Software Generated Interrupt Register
External	GICD_SPENDSGIR<n>	SGI Set-Pending Registers
External	GICD_STATUSR	Error Reporting Status Register
External	GICD_TYPER	Interrupt Controller Type Register
External	GICD_TYPER2	Interrupt Controller Type Register 2

In the GICR functional group:

Exec state	Name	Description
External	GICR_CLRLPIR	Clear LPI Pending Register
External	GICR_CTLR	Redistributor Control Register
External	GICR_ICACTIVER0	Interrupt Clear-Active Register 0
External	GICR_ICACTIVER<n>E	Interrupt Clear-Active Registers
External	GICR_ICENABLER0	Interrupt Clear-Enable Register 0
External	GICR_ICENABLER<n>E	Interrupt Clear-Enable Registers
External	GICR_ICFGR0	Interrupt Configuration Register 0
External	GICR_ICFGR1	Interrupt Configuration Register 1
External	GICR_ICFGR<n>E	Interrupt configuration registers
External	GICR_ICPENDR0	Interrupt Clear-Pending Register 0
External	GICR_ICPENDR<n>E	Interrupt Clear-Pending Registers
External	GICR_IGROUPR0	Interrupt Group Register 0
External	GICR_IGROUPR<n>E	Interrupt Group Registers
External	GICR_IGRPMODR0	Interrupt Group Modifier Register 0
External	GICR_IGRPMODR<n>E	Interrupt Group Modifier Registers
External	GICR_IIDR	Redistributor Implementer Identification Register
External	GICR_INVALLR	Redistributor Invalidate All Register
External	GICR_INVLPIR	Redistributor Invalidate LPI Register
External	GICR_IPRIORITYR<n>	Interrupt Priority Registers
External	GICR_IPRIORITYR<n>E	Interrupt Priority Registers (extended PPI range)
External	GICR_ISACTIVER0	Interrupt Set-Active Register 0
External	GICR_ISACTIVER<n>E	Interrupt Set-Active Registers
External	GICR_ISENABLER0	Interrupt Set-Enable Register 0
External	GICR_ISENABLER<n>E	Interrupt Set-Enable Registers
External	GICR_ISPENDR0	Interrupt Set-Pending Register 0
External	GICR_ISPENDR<n>E	Interrupt Set-Pending Registers
External	GICR_MPAMIDR	Report maximum PARTID and PMG Register
External	GICR_NSACR	Non-secure Access Control Register
External	GICR_PARTIDR	Set PARTID and PMG Register
External	GICR_PENDBASER	Redistributor LPI Pending Table Base Address Register
External	GICR_PROPBASER	Redistributor Properties Base Address Register
External	GICR_SETLPIR	Set LPI Pending Register
External	GICR_STATUSR	Error Reporting Status Register

Exec state	Name	Description
External	GICR_SYNCR	Redistributor Synchronize Register
External	GICR_TYPER	Redistributor Type Register
External	GICR_VPENDBASER	Virtual Redistributor LPI Pending Table Base Address Register
External	GICR_VPROPBASER	Virtual Redistributor Properties Base Address Register
External	GICR_VSGIPENDR	Redistributor virtual SGI pending state register
External	GICR_VSGIR	Redistributor virtual SGI pending state request register
External	GICR_WAKER	Redistributor Wake Register

In the GICC functional group:

Exec state	Name	Description
External	GICC_ABPR	CPU Interface Aliased Binary Point Register
External	GICC_AEOIR	CPU Interface Aliased End Of Interrupt Register
External	GICC_AHPPIR	CPU Interface Aliased Highest Priority Pending Interrupt Register
External	GICC_AIAR	CPU Interface Aliased Interrupt Acknowledge Register
External	GICC_APR<n>	CPU Interface Active Priorities Registers
External	GICC_BPR	CPU Interface Binary Point Register
External	GICC_CTLR	CPU Interface Control Register
External	GICC_DIR	CPU Interface Deactivate Interrupt Register
External	GICC_EOIR	CPU Interface End Of Interrupt Register
External	GICC_HPPIR	CPU Interface Highest Priority Pending Interrupt Register
External	GICC_IAR	CPU Interface Interrupt Acknowledge Register
External	GICC_IIDR	CPU Interface Identification Register
External	GICC_NSAPR<n>	CPU Interface Non-secure Active Priorities Registers
External	GICC_PMR	CPU Interface Priority Mask Register
External	GICC_RPR	CPU Interface Running Priority Register
External	GICC_STATUSR	CPU Interface Status Register

In the GICV functional group:

Exec state	Name	Description
External	GICV_ABPR	Virtual Machine Aliased Binary Point Register
External	GICV_AEOIR	Virtual Machine Aliased End Of Interrupt Register
External	GICV_AHPPIR	Virtual Machine Aliased Highest Priority Pending Interrupt Register
External	GICV_AIAR	Virtual Machine Aliased Interrupt Acknowledge Register
External	GICV_APR<n>	Virtual Machine Active Priorities Registers
External	GICV_BPR	Virtual Machine Binary Point Register
External	GICV_CTLR	Virtual Machine Control Register
External	GICV_DIR	Virtual Machine Deactivate Interrupt Register
External	GICV_EOIR	Virtual Machine End Of Interrupt Register
External	GICV_HPPIR	Virtual Machine Highest Priority Pending Interrupt Register
External	GICV_IAR	Virtual Machine Interrupt Acknowledge Register
External	GICV_IIDR	Virtual Machine CPU Interface Identification Register
External	GICV_PMR	Virtual Machine Priority Mask Register
External	GICV_RPR	Virtual Machine Running Priority Register
External	GICV_STATUSR	Virtual Machine Error Reporting Status Register

In the GICH functional group:

Exec state	Name	Description
External	GICH_APR<n>	Active Priorities Registers
External	GICH_EISR	End Interrupt Status Register
External	GICH_ELRSR	Empty List Register Status Register
External	GICH_HCR	Hypervisor Control Register
External	GICH_LR<n>	List Registers
External	GICH_MISR	Maintenance Interrupt Status Register
External	GICH_VMCR	Virtual Machine Control Register
External	GICH_VTR	Virtual Type Register

In the GITS functional group:

Exec state	Name	Description
External	GITS_BASER<n>	ITS Translation Table Descriptors
External	GITS_CBASER	ITS Command Queue Descriptor
External	GITS_CREADR	ITS Read Register
External	GITS_CTLR	ITS Control Register
External	GITS_CWRITER	ITS Write Register
External	GITS_IIDR	ITS Identification Register
External	GITS_MPAMIDR	Report maximum PARTID and PMG Register
External	GITS_MPIDR	Report ITS's affinity.
External	GITS_PARTIDR	Set PARTID and PMG Register
External	GITS_SGIR	ITS SGI Register
External	GITS_TRANSLATER	ITS Translation Register
External	GITS_TYPER	ITS Type Register

In the RAS functional group:

Exec state	Name	Description
AArch32	DISR	Deferred Interrupt Status Register
AArch32	ERRIDR	Error Record ID Register
AArch32	ERRSELR	Error Record Select Register
AArch32	ERXADDR	Selected Error Record Address Register
AArch32	ERXADDR2	Selected Error Record Address Register 2
AArch32	ERXCTLR	Selected Error Record Control Register
AArch32	ERXCTLR2	Selected Error Record Control Register 2
AArch32	ERXFR	Selected Error Record Feature Register
AArch32	ERXFR2	Selected Error Record Feature Register 2
AArch32	ERXMISC0	Selected Error Record Miscellaneous Register 0
AArch32	ERXMISC1	Selected Error Record Miscellaneous Register 1
AArch32	ERXMISC2	Selected Error Record Miscellaneous Register 2
AArch32	ERXMISC3	Selected Error Record Miscellaneous Register 3
AArch32	ERXMISC4	Selected Error Record Miscellaneous Register 4
AArch32	ERXMISC5	Selected Error Record Miscellaneous Register 5
AArch32	ERXMISC6	Selected Error Record Miscellaneous Register 6
AArch32	ERXMISC7	Selected Error Record Miscellaneous Register 7
AArch32	ERXSTATUS	Selected Error Record Primary Status Register
AArch32	VDFSR	Virtual SError Exception Syndrome Register
AArch32	VDISR	Virtual Deferred Interrupt Status Register
AArch64	DISR_EL1	Deferred Interrupt Status Register
AArch64	ERRIDR_EL1	Error Record ID Register
AArch64	ERRSELR_EL1	Error Record Select Register
AArch64	ERXADDR_EL1	Selected Error Record Address Register
AArch64	ERXCTLR_EL1	Selected Error Record Control Register
AArch64	ERXFR_EL1	Selected Error Record Feature Register
AArch64	ERXMISC0_EL1	Selected Error Record Miscellaneous Register 0
AArch64	ERXMISC1_EL1	Selected Error Record Miscellaneous Register 1
AArch64	ERXMISC2_EL1	Selected Error Record Miscellaneous Register 2
AArch64	ERXMISC3_EL1	Selected Error Record Miscellaneous Register 3
AArch64	ERXPFGCDN_EL1	Selected Pseudo-fault Generation Countdown register
AArch64	ERXPFGCTL_EL1	Selected Pseudo-fault Generation Control register
AArch64	ERXPFGF_EL1	Selected Pseudo-fault Generation Feature register
AArch64	ERXSTATUS_EL1	Selected Error Record Primary Status Register
AArch64	VDISR_EL2	Virtual Deferred Interrupt Status Register
AArch64	VSESR_EL2	Virtual SError Exception Syndrome Register
External	ERR<n>ADDR	Error Record Address Register
External	ERR<n>CTLR	Error Record Control Register
External	ERR<n>FR	Error Record Feature Register
External	ERR<n>MISC0	Error Record Miscellaneous Register 0
External	ERR<n>MISC1	Error Record Miscellaneous Register 1
External	ERR<n>MISC2	Error Record Miscellaneous Register 2
External	ERR<n>MISC3	Error Record Miscellaneous Register 3
External	ERR<n>PFGCDN	Pseudo-fault Generation Countdown Register
External	ERR<n>PFGCTL	Pseudo-fault Generation Control Register

Exec state	Name	Description
External	ERR<n>PFGF	Pseudo-fault Generation Feature Register
External	ERR<n>STATUS	Error Record Primary Status Register
External	ERRCIDR0	Component Identification Register 0
External	ERRCIDR1	Component Identification Register 1
External	ERRCIDR2	Component Identification Register 2
External	ERRCIDR3	Component Identification Register 3
External	ERRCRICR0	Critical Error Interrupt Configuration Register 0
External	ERRCRICR1	Critical Error Interrupt Configuration Register 1
External	ERRCRICR2	Critical Error Interrupt Configuration Register 2
External	ERRDEVAFF	Device Affinity Register
External	ERRDEVARCH	Device Architecture Register
External	ERRDEVID	Device Configuration Register
External	ERRERICR0	Error Recovery Interrupt Configuration Register 0
External	ERRERICR1	Error Recovery Interrupt Configuration Register 1
External	ERRERICR2	Error Recovery Interrupt Configuration Register 2
External	ERRFHICR0	Fault-Handling Interrupt Configuration Register 0
External	ERRFHICR1	Fault-Handling Interrupt Configuration Register 1
External	ERRFHICR2	Fault-Handling Interrupt Configuration Register 2
External	ERRGSR	Error Group Status Register
External	ERRIIDR	Implementation Identification Register
External	ERRIRQCR<n>	Generic Error Interrupt Configuration Register
External	ERRIRQSR	Error Interrupt Status Register
External	ERRPIDR0	Peripheral Identification Register 0
External	ERRPIDR1	Peripheral Identification Register 1
External	ERRPIDR2	Peripheral Identification Register 2
External	ERRPIDR3	Peripheral Identification Register 3
External	ERRPIDR4	Peripheral Identification Register 4

In the MPAM functional group:

Exec state	Name	Description
AArch64	MPAM0_EL1	MPAM0 Register (EL1)
AArch64	MPAM1_EL1	MPAM1 Register (EL1)
AArch64	MPAM2_EL2	MPAM2 Register (EL2)
AArch64	MPAM3_EL3	MPAM3 Register (EL3)
AArch64	MPAMHCR_EL2	MPAM Hypervisor Control Register (EL2)
~~AArch64~~	~~MPAMIDR_EL1~~	~~MPAM ID Register (EL1)~~
AArch64	MPAMVPM0_EL2	MPAM Virtual PARTID Mapping Register 0
AArch64	MPAMVPM1_EL2	MPAM Virtual PARTID Mapping Register 1
AArch64	MPAMVPM2_EL2	MPAM Virtual PARTID Mapping Register 2
AArch64	MPAMVPM3_EL2	MPAM Virtual PARTID Mapping Register 3
AArch64	MPAMVPM4_EL2	MPAM Virtual PARTID Mapping Register 4
AArch64	MPAMVPM5_EL2	MPAM Virtual PARTID Mapping Register 5
AArch64	MPAMVPM6_EL2	MPAM Virtual PARTID Mapping Register 6
AArch64	MPAMVPM7_EL2	MPAM Virtual PARTID Mapping Register 7
AArch64	MPAMVPMV_EL2	MPAM Virtual Partition Mapping Valid Register
External	MPAMCFG_CMAX	MPAM Cache Maximum Capacity Partition Configuration Register
External	MPAMCFG_CPBM	MPAM Cache Portion Bitmap Partition Configuration Register
External	MPAMCFG_INTPARTID	MPAM Internal PARTID Narrowing Configuration Register

Exec state	Name	Description
External	MPAMCFG_MBW_MAX	MPAM Memory Bandwidth Maximum Partition Configuration Register
External	MPAMCFG_MBW_MIN	MPAM Cache Maximum Capacity Partition Configuration Register
External	MPAMCFG_MBW_PBM	MPAM Bandwidth Portion Bitmap Partition Configuration Register
External	MPAMCFG_MBW_PROP	MPAM Memory Bandwidth Proportional Stride Partition Configuration Register
External	MPAMCFG_MBW_WINWD	MPAM Memory Bandwidth Partitioning Window Width Configuration Register
External	MPAMCFG_PART_SEL	MPAM Partition Configuration Selection Register
External	MPAMCFG_PRI	MPAM Priority Partition Configuration Register
External	MPAMF_AIDR	MPAM Architecture Identification Register
External	MPAMF_CCAP_IDR	MPAM Features Cache Capacity Partitioning ID register
External	MPAMF_CPOR_IDR	MPAM Features Cache Portion Partitioning ID register
External	MPAMF_CSUMON_IDR	MPAM Features Cache Storage Usage Monitoring ID register
External	MPAMF_ECR	MPAM Error Control Register
External	MPAMF_ESR	MPAM Error Status Register
External	MPAMF_IDR	MPAM Features Identification Register
External	MPAMF_IIDR	MPAM Implementation Identification Register
External	MPAMF_IMPL_IDR	MPAM Implementation-Specific Partitioning Feature Identification Register
External	MPAMF_MBWUMON_IDR	MPAM Features Memory Bandwidth Usage Monitoring ID register
External	MPAMF_MBW_IDR	MPAM Memory Bandwidth Partitioning Identification Register
External	MPAMF_MSMON_IDR	MPAM Resource Monitoring Identification Register
External	MPAMF_PARTID_NRW_IDR	MPAM PARTID Narrowing ID register
External	MPAMF_PRI_IDR	MPAM Priority Partitioning Identification Register
External	MPAMF_SIDR	MPAM Features Secure Identification Register
External	MSMON_CAPT_EVNT	MPAM Capture Event Generation Register
External	MSMON_CFG_CSU_CTL	MPAM Memory System Monitor Configure Cache Storage Usage Monitor Control Register
External	MSMON_CFG_CSU_FLT	MPAM Memory System Monitor Configure Cache Storage Usage Monitor Filter Register
External	MSMON_CFG_MBWU_CTL	MPAM Memory System Monitor Configure Memory Bandwidth Usage Monitor Control Register
External	MSMON_CFG_MBWU_FLT	MPAM Memory System Monitor Configure Memory Bandwidth Usage Monitor Filter Register
External	MSMON_CFG_MON_SEL	MPAM Monitor Instance Selection Register
External	MSMON_CSU	MPAM Cache Storage Usage Monitor Register
External	MSMON_CSU_CAPTURE	MPAM Cache Storage Usage Monitor Capture Register
External	MSMON_MBWU	MPAM Memory Bandwidth Usage Monitor Register

Exec state	Name	Description
External	MSMON_MBWU_CAPTURE	MPAM Memory Bandwidth Usage Monitor Capture Register
External	MSMON_MBWU_L	MPAM Long Memory Bandwidth Usage Monitor Register
External	MSMON_MBWU_L_CAPTUREMSMON_MBWU__L_CAPTURE	MPAM Long Memory Bandwidth Usage Monitor Capture Register

In the Pointer authentication functional group:

Exec state	Name	Description
AArch64	APDAKeyHi_EL1	Pointer Authentication Key A for Data (bits[127:64])
AArch64	APDAKeyLo_EL1	Pointer Authentication Key A for Data (bits[63:0])
AArch64	APDBKeyHi_EL1	Pointer Authentication Key B for Data (bits[127:64])
AArch64	APDBKeyLo_EL1	Pointer Authentication Key B for Data (bits[63:0])
AArch64	APGAKeyHi_EL1	Pointer Authentication Key A for Code (bits[127:64])
AArch64	APGAKeyLo_EL1	Pointer Authentication Key A for Code (bits[63:0])
AArch64	APIAKeyHi_EL1	Pointer Authentication Key A for Instruction (bits[127:64])
AArch64	APIAKeyLo_EL1	Pointer Authentication Key A for Instruction (bits[63:0])
AArch64	APIBKeyHi_EL1	Pointer Authentication Key B for Instruction (bits[127:64])
AArch64	APIBKeyLo_EL1	Pointer Authentication Key B for Instruction (bits[63:0])

In the GIC ITS registers functional group:

Exec state	Name	Description
External	GITS_BASER<n>	ITS Translation Table Descriptors
External	GITS_CBASER	ITS Command Queue Descriptor
External	GITS_CREADR	ITS Read Register
External	GITS_CTLR	ITS Control Register
External	GITS_CWRITER	ITS Write Register
External	GITS_IIDR	ITS Identification Register
External	GITS_MPAMIDR	Report maximum PARTID and PMG Register
External	GITS_MPIDR	Report ITS's affinity.
External	GITS_PARTIDR	Set PARTID and PMG Register
External	GITS_SGIR	ITS SGI Register
External	GITS_TRANSLATER	ITS Translation Register
External	GITS_TYPER	ITS Type Register

13~~27~~/12~~09~~/2019 15~~18~~:13~~49~~

Copyright Â© 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

External System registers

AMCFGR: Activity Monitors Configuration Register

AMCGCR: Activity Monitors Counter Group Configuration Register

AMCIDR0: Activity Monitors Component Identification Register 0

AMCIDR1: Activity Monitors Component Identification Register 1

AMCIDR2: Activity Monitors Component Identification Register 2

AMCIDR3: Activity Monitors Component Identification Register 3

AMCNTENCLR0: Activity Monitors Count Enable Clear Register 0

AMCNTENCLR1: Activity Monitors Count Enable Clear Register 1

AMCNTENSET0: Activity Monitors Count Enable Set Register 0

AMCNTENSET1: Activity Monitors Count Enable Set Register 1

AMCR: Activity Monitors Control Register

AMDEVAFF0: Activity Monitors Device Affinity Register 0

AMDEVAFF1: Activity Monitors Device Affinity Register 1

AMDEVARCH: Activity Monitors Device Architecture Register

AMDEVTYPE: Activity Monitors Device Type Register

AMEVCNTR0<n>: Activity Monitors Event Counter Registers 0

AMEVCNTR1<n>: Activity Monitors Event Counter Registers 1

AMEVTYPER0<n>: Activity Monitors Event Type Registers 0

AMEVTYPER1<n>: Activity Monitors Event Type Registers 1

AMIIDR: Activity Monitors Implementation Identification Register

AMPIDR0: Activity Monitors Peripheral Identification Register 0

AMPIDR1: Activity Monitors Peripheral Identification Register 1

AMPIDR2: Activity Monitors Peripheral Identification Register 2

AMPIDR3: Activity Monitors Peripheral Identification Register 3

AMPIDR4: Activity Monitors Peripheral Identification Register 4

ASICCTL: CTI External Multiplexer Control register

CNTACR<n>: Counter-timer Access Control Registers

CNTCR: Counter Control Register

CNTCV: Counter Count Value register

CNTEL0ACR: Counter-timer EL0 Access Control Register

CNTFID0: Counter Frequency ID

CNTFID<n>: Counter Frequency IDs, n > 0

CNTFRQ: Counter-timer Frequency

CNTID: Counter Identification Register

CNTNSAR: Counter-timer Non-secure Access Register

CNTPCT: Counter-timer Physical Count

CNTP_CTL: Counter-timer Physical Timer Control

CNTP_CVAL: Counter-timer Physical Timer CompareValue

CNTP_TVAL: Counter-timer Physical Timer TimerValue

CNTSCR: Counter Scale Register

CNTSR: Counter Status Register

CNTTIDR: Counter-timer Timer ID Register

CNTVCT: Counter-timer Virtual Count

CNTVOFF: Counter-timer Virtual Offset

CNTVOFF<n>: Counter-timer Virtual Offsets

CNTV_CTL: Counter-timer Virtual Timer Control

CNTV_CVAL: Counter-timer Virtual Timer CompareValue

CNTV_TVAL: Counter-timer Virtual Timer TimerValue

CounterID<n>: Counter ID registers

CTIAPPCLEAR: CTI Application Trigger Clear register

CTIAPPPULSE: CTI Application Pulse register

CTIAPPSET: CTI Application Trigger Set register

CTIAUTHSTATUS: CTI Authentication Status register

CTICHINSTATUS: CTI Channel In Status register

CTICHOUTSTATUS: CTI Channel Out Status register

CTICIDR0: CTI Component Identification Register 0

CTICIDR1: CTI Component Identification Register 1

CTICIDR2: CTI Component Identification Register 2

CTICIDR3: CTI Component Identification Register 3

CTICLAIMCLR: CTI CLAIM Tag Clear register

CTICLAIMSET: CTI CLAIM Tag Set register

CTICONTROL: CTI Control register

CTIDEVAFF0: CTI Device Affinity register 0

CTIDEVAFF1: CTI Device Affinity register 1

CTIDEVARCH: CTI Device Architecture register

CTIDEVCTL: CTI Device Control register

CTIDEVID: CTI Device ID register 0

CTIDEVID1: CTI Device ID register 1

CTIDEVID2: CTI Device ID register 2

CTIDEVTYPE: CTI Device Type register

CTIGATE: CTI Channel Gate Enable register

CTIINEN<n>: CTI Input Trigger to Output Channel Enable registers

CTIINTACK: CTI Output Trigger Acknowledge register

CTIITCTRL: CTI Integration mode Control register

CTILAR: CTI Lock Access Register

CTILSR: CTI Lock Status Register

CTIOUTEN<n>: CTI Input Channel to Output Trigger Enable registers

CTIPIDR0: CTI Peripheral Identification Register 0

CTIPIDR1: CTI Peripheral Identification Register 1

CTIPIDR2: CTI Peripheral Identification Register 2

CTIPIDR3: CTI Peripheral Identification Register 3

CTIPIDR4: CTI Peripheral Identification Register 4

CTITRIGINSTATUS: CTI Trigger In Status register

CTITRIGOUTSTATUS: CTI Trigger Out Status register

~~CounterID<n>: Counter ID registers~~

DBGAUTHSTATUS_EL1: Debug Authentication Status register

DBGBCR<n>_EL1: Debug Breakpoint Control Registers

DBGBVR<n>_EL1: Debug Breakpoint Value Registers

DBGCLAIMCLR_EL1: Debug CLAIM Tag Clear register

DBGCLAIMSET_EL1: Debug CLAIM Tag Set register

DBGDTRRX_EL0: Debug Data Transfer Register, Receive

DBGDTRTX_EL0: Debug Data Transfer Register, Transmit

DBGWCR<n>_EL1: Debug Watchpoint Control Registers

DBGWVR<n>_EL1: Debug Watchpoint Value Registers

EDAA32PFR: External Debug AArch32 Processor Feature Register

EDACR: External Debug Auxiliary Control Register

EDCIDR0: External Debug Component Identification Register 0

EDCIDR1: External Debug Component Identification Register 1

EDCIDR2: External Debug Component Identification Register 2

EDCIDR3: External Debug Component Identification Register 3

EDCIDSR: External Debug Context ID Sample Register

EDDEVAFF0: External Debug Device Affinity register 0

EDDEVAFF1: External Debug Device Affinity register 1

EDDEVARCH: External Debug Device Architecture register

EDDEVID: External Debug Device ID register 0

EDDEVID1: External Debug Device ID register 1

EDDEVID2: External Debug Device ID register 2

EDDEVTYPE: External Debug Device Type register

EDDFR: External Debug Feature Register

EDECCR: External Debug Exception Catch Control Register

EDECR: External Debug Execution Control Register

EDESR: External Debug Event Status Register

EDITCTRL: External Debug Integration mode Control register

EDITR: External Debug Instruction Transfer Register

EDLAR: External Debug Lock Access Register

EDLSR: External Debug Lock Status Register

EDPCSR: External Debug Program Counter Sample Register

EDPFR: External Debug Processor Feature Register

EDPIDR0: External Debug Peripheral Identification Register 0

EDPIDR1: External Debug Peripheral Identification Register 1

EDPIDR2: External Debug Peripheral Identification Register 2

EDPIDR3: External Debug Peripheral Identification Register 3

EDPIDR4: External Debug Peripheral Identification Register 4

EDPRCR: External Debug Power/Reset Control Register

EDPRSR: External Debug Processor Status Register

EDRCR: External Debug Reserve Control Register

EDSCR: External Debug Status and Control Register

EDVIDSR: External Debug Virtual Context Sample Register

EDWAR: External Debug Watchpoint Address Register

ERR<n>ADDR: Error Record Address Register

ERR<n>CTLR: Error Record Control Register

ERR<n>FR: Error Record Feature Register

ERR<n>MISC0: Error Record Miscellaneous Register 0

ERR<n>MISC1: Error Record Miscellaneous Register 1

ERR<n>MISC2: Error Record Miscellaneous Register 2

ERR<n>MISC3: Error Record Miscellaneous Register 3

ERR<n>PFGCDN: Pseudo-fault Generation Countdown Register

ERR<n>PFGCTL: Pseudo-fault Generation Control Register

ERR<n>PFGF: Pseudo-fault Generation Feature Register

ERR<n>STATUS: Error Record Primary Status Register

ERRCIDR0: Component Identification Register 0

ERRCIDR1: Component Identification Register 1

ERRCIDR2: Component Identification Register 2

ERRCIDR3: Component Identification Register 3

ERRCRICR0: Critical Error Interrupt Configuration Register 0

ERRCRICR1: Critical Error Interrupt Configuration Register 1

ERRCRICR2: Critical Error Interrupt Configuration Register 2

ERRDEVAFF: Device Affinity Register

ERRDEVARCH: Device Architecture Register

ERRDEVID: Device Configuration Register

ERRERICR0: Error Recovery Interrupt Configuration Register 0

ERRERICR1: Error Recovery Interrupt Configuration Register 1

ERRERICR2: Error Recovery Interrupt Configuration Register 2

ERRFHICR0: Fault-Handling Interrupt Configuration Register 0

ERRFHICR1: Fault-Handling Interrupt Configuration Register 1

ERRFHICR2: Fault-Handling Interrupt Configuration Register 2

ERRGSR: Error Group Status Register

ERRIIDR: Implementation Identification Register

ERRIRQCR<n>: Generic Error Interrupt Configuration Register

ERRIRQSR: Error Interrupt Status Register

ERRPIDR0: Peripheral Identification Register 0

ERRPIDR1: Peripheral Identification Register 1

ERRPIDR2: Peripheral Identification Register 2

ERRPIDR3: Peripheral Identification Register 3

ERRPIDR4: Peripheral Identification Register 4

GICC_ABPR: CPU Interface Aliased Binary Point Register

GICC_AEOIR: CPU Interface Aliased End Of Interrupt Register

GICC_AHPPIR: CPU Interface Aliased Highest Priority Pending Interrupt Register

GICC_AIAR: CPU Interface Aliased Interrupt Acknowledge Register

GICC_APR<n>: CPU Interface Active Priorities Registers

GICC_BPR: CPU Interface Binary Point Register

GICC_CTLR: CPU Interface Control Register

GICC_DIR: CPU Interface Deactivate Interrupt Register

GICC_EOIR: CPU Interface End Of Interrupt Register

GICC_HPPIR: CPU Interface Highest Priority Pending Interrupt Register

GICC_IAR: CPU Interface Interrupt Acknowledge Register

GICC_IIDR: CPU Interface Identification Register

GICC_NSAPR<n>: CPU Interface Non-secure Active Priorities Registers

GICC_PMR: CPU Interface Priority Mask Register

GICC_RPR: CPU Interface Running Priority Register

GICC_STATUSR: CPU Interface Status Register

GICD_CLRSPI_NSR: Clear Non-secure SPI Pending Register

GICD_CLRSPI_SR: Clear Secure SPI Pending Register

GICD_CPENDSGIR<n>: SGI Clear-Pending Registers

GICD_CTLR: Distributor Control Register

GICD_ICACTIVER<n>: Interrupt Clear-Active Registers

GICD_ICACTIVER<n>E: Interrupt Clear-Active Registers (extended SPI range)

GICD_ICENABLER<n>: Interrupt Clear-Enable Registers

GICD_ICENABLER<n>E: Interrupt Clear-Enable Registers

GICD_ICFGR<n>: Interrupt Configuration Registers

GICD_ICFGR<n>E: Interrupt Configuration Registers (Extended SPI Range)

GICD_ICPENDR<n>: Interrupt Clear-Pending Registers

GICD_ICPENDR<n>E: Interrupt Clear-Pending Registers (extended SPI range)

GICD_IGROUPR<n>: Interrupt Group Registers

GICD_IGROUPR<n>E: Interrupt Group Registers (extended SPI range)

GICD_IGRPMODR<n>: Interrupt Group Modifier Registers

GICD_IGRPMODR<n>E: Interrupt Group Modifier Registers (extended SPI range)

GICD_IIDR: Distributor Implementer Identification Register

GICD_IPRIORITYR<n>: Interrupt Priority Registers

GICD_IPRIORITYR<n>E: Holds the priority of the corresponding interrupt for each extended SPI supported by the GIC.

GICD_IROUTER<n>: Interrupt Routing Registers

GICD_IROUTER<n>E: Interrupt Routing Registers (Extended SPI Range)

GICD_ISACTIVER<n>: Interrupt Set-Active Registers

GICD_ISACTIVER<n>E: Interrupt Set-Active Registers (extended SPI range)

GICD_ISENABLER<n>: Interrupt Set-Enable Registers

GICD_ISENABLER<n>E: Interrupt Set-Enable Registers

GICD_ISPENDR<n>: Interrupt Set-Pending Registers

GICD_ISPENDR<n>E: Interrupt Set-Pending Registers (extended SPI range)

GICD_ITARGETSR<n>: Interrupt Processor Targets Registers

GICD_NSACR<n>: Non-secure Access Control Registers

GICD_NSACR<n>E: Non-secure Access Control Registers

GICD_SETSPI_NSR: Set Non-secure SPI Pending Register

GICD_SETSPI_SR: Set Secure SPI Pending Register

GICD_SGIR: Software Generated Interrupt Register

GICD_SPENDSGIR<n>: SGI Set-Pending Registers

GICD_STATUSR: Error Reporting Status Register

GICD_TYPER: Interrupt Controller Type Register

GICD_TYPER2: Interrupt Controller Type Register 2

GICH_APR<n>: Active Priorities Registers

GICH_EISR: End Interrupt Status Register

GICH_ELRSR: Empty List Register Status Register

GICH_HCR: Hypervisor Control Register

GICH_LR<n>: List Registers

GICH_MISR: Maintenance Interrupt Status Register

GICH_VMCR: Virtual Machine Control Register

GICH_VTR: Virtual Type Register

GICR_CLRLPIR: Clear LPI Pending Register

GICR_CTLR: Redistributor Control Register

GICR_ICACTIVER0: Interrupt Clear-Active Register 0

GICR_ICACTIVER<n>E: Interrupt Clear-Active Registers

GICR_ICENABLER0: Interrupt Clear-Enable Register 0

GICR_ICENABLER<n>E: Interrupt Clear-Enable Registers

GICR_ICFGR0: Interrupt Configuration Register 0

GICR_ICFGR1: Interrupt Configuration Register 1

GICR_ICFGR<n>E: Interrupt configuration registers

GICR_ICPENDR0: Interrupt Clear-Pending Register 0

GICR_ICPENDR<n>E: Interrupt Clear-Pending Registers

GICR_IGROUPR0: Interrupt Group Register 0

GICR_IGROUPR<n>E: Interrupt Group Registers

GICR_IGRPMODR0: Interrupt Group Modifier Register 0

GICR_IGRPMODR<n>E: Interrupt Group Modifier Registers

GICR_IIDR: Redistributor Implementer Identification Register

GICR_INVALLR: Redistributor Invalidate All Register

GICR_INVLPIR: Redistributor Invalidate LPI Register

GICR_IPRIORITYR<n>: Interrupt Priority Registers

GICR_IPRIORITYR<n>E: Interrupt Priority Registers (extended PPI range)

GICR_ISACTIVER0: Interrupt Set-Active Register 0

GICR_ISACTIVER<n>E: Interrupt Set-Active Registers

GICR_ISENABLER0: Interrupt Set-Enable Register 0

GICR_ISENABLER<n>E: Interrupt Set-Enable Registers

GICR_ISPENDR0: Interrupt Set-Pending Register 0

GICR_ISPENDR<n>E: Interrupt Set-Pending Registers

GICR_MPAMIDR: Report maximum PARTID and PMG Register

GICR_NSACR: Non-secure Access Control Register

GICR_PARTIDR: Set PARTID and PMG Register

GICR_PENDBASER: Redistributor LPI Pending Table Base Address Register

GICR_PROPBASER: Redistributor Properties Base Address Register

GICR_SETLPIR: Set LPI Pending Register

GICR_STATUSR: Error Reporting Status Register

GICR_SYNCR: Redistributor Synchronize Register

GICR_TYPER: Redistributor Type Register

GICR_VPENDBASER: Virtual Redistributor LPI Pending Table Base Address Register

GICR_VPROPBASER: Virtual Redistributor Properties Base Address Register

GICR_VSGIPENDR: Redistributor virtual SGI pending state register

GICR_VSGIR: Redistributor virtual SGI pending state request register

GICR_WAKER: Redistributor Wake Register

GICV_ABPR: Virtual Machine Aliased Binary Point Register

GICV_AEOIR: Virtual Machine Aliased End Of Interrupt Register

GICV_AHPPIR: Virtual Machine Aliased Highest Priority Pending Interrupt Register

GICV_AIAR: Virtual Machine Aliased Interrupt Acknowledge Register

GICV_APR<n>: Virtual Machine Active Priorities Registers

GICV_BPR: Virtual Machine Binary Point Register

GICV_CTLR: Virtual Machine Control Register

GICV_DIR: Virtual Machine Deactivate Interrupt Register

GICV_EOIR: Virtual Machine End Of Interrupt Register

GICV_HPPIR: Virtual Machine Highest Priority Pending Interrupt Register

GICV_IAR: Virtual Machine Interrupt Acknowledge Register

GICV_IIDR: Virtual Machine CPU Interface Identification Register

GICV_PMR: Virtual Machine Priority Mask Register

GICV_RPR: Virtual Machine Running Priority Register

GICV_STATUSR: Virtual Machine Error Reporting Status Register

GITS_BASER<n>: ITS Translation Table Descriptors

GITS_CBASER: ITS Command Queue Descriptor

GITS_CREADR: ITS Read Register

GITS_CTLR: ITS Control Register

GITS_CWRITER: ITS Write Register

GITS_IIDR: ITS Identification Register

GITS_MPAMIDR: Report maximum PARTID and PMG Register

GITS_MPIDR: Report ITS's affinity.

GITS_PARTIDR: Set PARTID and PMG Register

GITS_SGIR: ITS SGI Register

GITS_TRANSLATER: ITS Translation Register

GITS_TYPER: ITS Type Register

MIDR_EL1: Main ID Register

MPAMCFG_CMAX: MPAM Cache Maximum Capacity Partition Configuration Register

MPAMCFG_CPBM: MPAM Cache Portion Bitmap Partition Configuration Register

MPAMCFG_INTPARTID: MPAM Internal PARTID Narrowing Configuration Register

MPAMCFG_MBW_MAX: MPAM Memory Bandwidth Maximum Partition Configuration Register

MPAMCFG_MBW_MIN: MPAM Cache Maximum Capacity Partition Configuration Register

MPAMCFG_MBW_PBM: MPAM Bandwidth Portion Bitmap Partition Configuration Register

MPAMCFG_MBW_PROP: MPAM Memory Bandwidth Proportional Stride Partition Configuration Register

MPAMCFG_MBW_WINWD: MPAM Memory Bandwidth Partitioning Window Width Configuration Register

MPAMCFG_PART_SEL: MPAM Partition Configuration Selection Register

MPAMCFG_PRI: MPAM Priority Partition Configuration Register

MPAMF_AIDR: MPAM Architecture Identification Register

MPAMF_CCAP_IDR: MPAM Features Cache Capacity Partitioning ID register

MPAMF_CPOR_IDR: MPAM Features Cache Portion Partitioning ID register

MPAMF_CSUMON_IDR: MPAM Features Cache Storage Usage Monitoring ID register

MPAMF_ECR: MPAM Error Control Register

MPAMF_ESR: MPAM Error Status Register

MPAMF_IDR: MPAM Features Identification Register

MPAMF_IIDR: MPAM Implementation Identification Register

MPAMF_IMPL_IDR: MPAM Implementation-Specific Partitioning Feature Identification Register

MPAMF_MBWUMON_IDR: MPAM Features Memory Bandwidth Usage Monitoring ID register

MPAMF_MBW_IDR: MPAM Memory Bandwidth Partitioning Identification Register

MPAMF_MSMON_IDR: MPAM Resource Monitoring Identification Register

MPAMF_PARTID_NRW_IDR: MPAM PARTID Narrowing ID register

MPAMF_PRI_IDR: MPAM Priority Partitioning Identification Register

MPAMF_SIDR: MPAM Features Secure Identification Register

MSMON_CAPT_EVNT: MPAM Capture Event Generation Register

MSMON_CFG_CSU_CTL: MPAM Memory System Monitor Configure Cache Storage Usage Monitor Control Register

MSMON_CFG_CSU_FLT: MPAM Memory System Monitor Configure Cache Storage Usage Monitor Filter Register

MSMON_CFG_MBWU_CTL: MPAM Memory System Monitor Configure Memory Bandwidth Usage Monitor Control Register

MSMON_CFG_MBWU_FLT: MPAM Memory System Monitor Configure Memory Bandwidth Usage Monitor Filter Register

MSMON_CFG_MON_SEL: MPAM Monitor Instance Selection Register

MSMON_CSU: MPAM Cache Storage Usage Monitor Register

MSMON_CSU_CAPTURE: MPAM Cache Storage Usage Monitor Capture Register

MSMON_MBWU: MPAM Memory Bandwidth Usage Monitor Register

MSMON_MBWU_CAPTURE: MPAM Memory Bandwidth Usage Monitor Capture Register

MSMON_MBWU_L: MPAM Long Memory Bandwidth Usage Monitor Register

MSMON_MBWU_L_CAPTUREMSMON_MBWU__L_CAPTURE: MPAM Long Memory Bandwidth Usage Monitor Capture Register

OSLAR_EL1: OS Lock Access Register

PMAUTHSTATUS: Performance Monitors Authentication Status register

PMCCFILTR_EL0: Performance Monitors Cycle Counter Filter Register

PMCCNTR_EL0: Performance Monitors Cycle Counter

PMCEID0: Performance Monitors Common Event Identification register 0

PMCEID1: Performance Monitors Common Event Identification register 1

PMCEID2: Performance Monitors Common Event Identification register 2

PMCEID3: Performance Monitors Common Event Identification register 3

PMCFGR: Performance Monitors Configuration Register

PMCID1SR: CONTEXTIDR_EL1 Sample Register

PMCID2SR: CONTEXTIDR_EL2 Sample Register

PMCIDR0: Performance Monitors Component Identification Register 0

PMCIDR1: Performance Monitors Component Identification Register 1

PMCIDR2: Performance Monitors Component Identification Register 2

PMCIDR3: Performance Monitors Component Identification Register 3

PMCNTENCLR_EL0: Performance Monitors Count Enable Clear register

PMCNTENSET_EL0: Performance Monitors Count Enable Set register

PMCR_EL0: Performance Monitors Control Register

PMDEVAFF0: Performance Monitors Device Affinity register 0

PMDEVAFF1: Performance Monitors Device Affinity register 1

PMDEVARCH: Performance Monitors Device Architecture register

PMDEVID: Performance Monitors Device ID register

PMDEVTYPE: Performance Monitors Device Type register

PMEVCNTR<n>_EL0: Performance Monitors Event Count Registers

PMEVTYPER<n>_EL0: Performance Monitors Event Type Registers

PMINTENCLR_EL1: Performance Monitors Interrupt Enable Clear register

PMINTENSET_EL1: Performance Monitors Interrupt Enable Set register

PMITCTRL: Performance Monitors Integration mode Control register

PMLAR: Performance Monitors Lock Access Register

PMLSR: Performance Monitors Lock Status Register

PMMIR: Performance Monitors Machine Identification Register

PMOVSCLR_EL0: Performance Monitors Overflow Flag Status Clear register

PMOVSSET_EL0: Performance Monitors Overflow Flag Status Set register

PMPCSR: Program Counter Sample Register

PMPIDR0: Performance Monitors Peripheral Identification Register 0

PMPIDR1: Performance Monitors Peripheral Identification Register 1

PMPIDR2: Performance Monitors Peripheral Identification Register 2

PMPIDR3: Performance Monitors Peripheral Identification Register 3

PMPIDR4: Performance Monitors Peripheral Identification Register 4

PMSWINC_EL0: Performance Monitors Software Increment register

PMVIDSR: VMID Sample Register

Copyright Â© 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

External register index by offset

Below are indexes for external registers in the following blocks:

- AMU
- CTI
- Debug
- GIC CPU interface
- GIC Distributor
- GIC ITS control
- GIC ITS translation
- GIC Redistributor
- GIC Virtual CPU interface
- GIC Virtual interface control
- MPAM
- PMU
- RAS
- Timer

In the AMU block:

Offset	Name	Description
0x000 + 8n	AMEVCNTR0<n>[31:0]	Activity Monitors Event Counter Registers 0
0x004 + 8n	AMEVCNTR0<n>[63:32]	Activity Monitors Event Counter Registers 0
0x100 + 8n	AMEVCNTR1<n>[31:0]	Activity Monitors Event Counter Registers 1
0x104 + 8n	AMEVCNTR1<n>[63:32]	Activity Monitors Event Counter Registers 1
0x400 + 4n	AMEVTYPER0<n>	Activity Monitors Event Type Registers 0
0x480 + 4n	AMEVTYPER1<n>	Activity Monitors Event Type Registers 1
0xC00	AMCNTENSET0	Activity Monitors Count Enable Set Register 0
0xC04	AMCNTENSET1	Activity Monitors Count Enable Set Register 1
0xC20	AMCNTENCLR0	Activity Monitors Count Enable Clear Register 0
0xC24	AMCNTENCLR1	Activity Monitors Count Enable Clear Register 1
0xCE0	AMCGCR	Activity Monitors Counter Group Configuration Register
0xE00	AMCFGR	Activity Monitors Configuration Register
0xE04	AMCR	Activity Monitors Control Register
0xE08	AMIIDR	Activity Monitors Implementation Identification Register
0xFA8	AMDEVAFF0	Activity Monitors Device Affinity Register 0
0xFAC	AMDEVAFF1	Activity Monitors Device Affinity Register 1
0xFBC	AMDEVARCH	Activity Monitors Device Architecture Register
0xFCC	AMDEVTYPE	Activity Monitors Device Type Register
0xFD0	AMPIDR4	Activity Monitors Peripheral Identification Register 4
0xFE0	AMPIDR0	Activity Monitors Peripheral Identification Register 0
0xFE4	AMPIDR1	Activity Monitors Peripheral Identification Register 1
0xFE8	AMPIDR2	Activity Monitors Peripheral Identification Register 2
0xFEC	AMPIDR3	Activity Monitors Peripheral Identification Register 3
0xFF0	AMCIDR0	Activity Monitors Component Identification Register 0
0xFF4	AMCIDR1	Activity Monitors Component Identification Register 1
0xFF8	AMCIDR2	Activity Monitors Component Identification Register 2
0xFFC	AMCIDR3	Activity Monitors Component Identification Register 3

In the CTI block:

Offset	Name	Description
0x000	CTICONTROL	CTI Control register
0x010	CTIINTACK	CTI Output Trigger Acknowledge register
0x014	CTIAPPSET	CTI Application Trigger Set register
0x018	CTIAPPCLEAR	CTI Application Trigger Clear register
0x01C	CTIAPPPULSE	CTI Application Pulse register
0x020 + 4n	CTIINEN<n>	CTI Input Trigger to Output Channel Enable registers
0x0A0 + 4n	CTIOUTEN<n>	CTI Input Channel to Output Trigger Enable registers
0x130	CTITRIGINSTATUS	CTI Trigger In Status register
0x134	CTITRIGOUTSTATUS	CTI Trigger Out Status register
0x138	CTICHINSTATUS	CTI Channel In Status register
0x13C	CTICHOUTSTATUS	CTI Channel Out Status register
0x140	CTIGATE	CTI Channel Gate Enable register
0x144	ASICCTL	CTI External Multiplexer Control register
0x150	CTIDEVCTL	CTI Device Control register
0xF00	CTIITCTRL	CTI Integration mode Control register
0xFA0	CTICLAIMSET	CTI CLAIM Tag Set register
0xFA4	CTICLAIMCLR	CTI CLAIM Tag Clear register
0xFA8	CTIDEVAFF0	CTI Device Affinity register 0
0xFAC	CTIDEVAFF1	CTI Device Affinity register 1
0xFB0	CTILAR	CTI Lock Access Register
0xFB4	CTILSR	CTI Lock Status Register
0xFB8	CTIAUTHSTATUS	CTI Authentication Status register
0xFBC	CTIDEVARCH	CTI Device Architecture register
0xFC0	CTIDEVID2	CTI Device ID register 2
0xFC4	CTIDEVID1	CTI Device ID register 1
0xFC8	CTIDEVID	CTI Device ID register 0
0xFCC	CTIDEVTYPE	CTI Device Type register
0xFD0	CTIPIDR4	CTI Peripheral Identification Register 4
0xFE0	CTIPIDR0	CTI Peripheral Identification Register 0
0xFE4	CTIPIDR1	CTI Peripheral Identification Register 1
0xFE8	CTIPIDR2	CTI Peripheral Identification Register 2
0xFEC	CTIPIDR3	CTI Peripheral Identification Register 3
0xFF0	CTICIDR0	CTI Component Identification Register 0
0xFF4	CTICIDR1	CTI Component Identification Register 1
0xFF8	CTICIDR2	CTI Component Identification Register 2
0xFFC	CTICIDR3	CTI Component Identification Register 3

In the Debug block:

Offset	Name	Description
0x020	EDESR	External Debug Event Status Register
0x024	EDECR	External Debug Execution Control Register
0x030	EDWAR[31:0]	External Debug Watchpoint Address Register
0x034	EDWAR[63:32]	External Debug Watchpoint Address Register
0x080	DBGDTRRX_EL0	Debug Data Transfer Register, Receive
0x084	EDITR	External Debug Instruction Transfer Register
0x088	EDSCR	External Debug Status and Control Register

Offset	Name	Description
0x08C	DBGDTRTX_EL0	Debug Data Transfer Register, Transmit
0x090	EDRCR	External Debug Reserve Control Register
0x094	EDACR	External Debug Auxiliary Control Register
0x098	EDECCR	External Debug Exception Catch Control Register
0x0A0	EDPCSR[31:0]	External Debug Program Counter Sample Register
0x0A4	EDCIDSR	External Debug Context ID Sample Register
0x0A8	EDVIDSR	External Debug Virtual Context Sample Register
0x0AC	EDPCSR[63:32]	External Debug Program Counter Sample Register
0x300	OSLAR_EL1	OS Lock Access Register
0x310	EDPRCR	External Debug Power/Reset Control Register
0x314	EDPRSR	External Debug Processor Status Register
0x400 + 16n	DBGBVR<n>_EL1[63:0]	Debug Breakpoint Value Registers
0x408 + 16n	DBGBCR<n>_EL1	Debug Breakpoint Control Registers
0x800 + 16n	DBGWVR<n>_EL1[63:0]	Debug Watchpoint Value Registers
0x808 + 16n	DBGWCR<n>_EL1	Debug Watchpoint Control Registers
0xD00	MIDR_EL1	Main ID Register
0xD20	EDPFR[31:0]	External Debug Processor Feature Register
0xD24	EDPFR[63:32]	External Debug Processor Feature Register
0xD28	EDDFR[31:0]	External Debug Feature Register
0xD2C	EDDFR[63:32]	External Debug Feature Register
0xD60	EDAA32PFR	External Debug AArch32 Processor Feature Register
0xF00	EDITCTRL	External Debug Integration mode Control register
0xFA0	DBGCLAIMSET_EL1	Debug CLAIM Tag Set register
0xFA4	DBGCLAIMCLR_EL1	Debug CLAIM Tag Clear register
0xFA8	EDDEVAFF0	External Debug Device Affinity register 0
0xFAC	EDDEVAFF1	External Debug Device Affinity register 1
0xFB0	EDLAR	External Debug Lock Access Register
0xFB4	EDLSR	External Debug Lock Status Register
0xFB8	DBGAUTHSTATUS_EL1	Debug Authentication Status register
0xFBC	EDDEVARCH	External Debug Device Architecture register
0xFC0	EDDEVID2	External Debug Device ID register 2
0xFC4	EDDEVID1	External Debug Device ID register 1
0xFC8	EDDEVID	External Debug Device ID register 0
0xFCC	EDDEVTYPE	External Debug Device Type register
0xFD0	EDPIDR4	External Debug Peripheral Identification Register 4
0xFE0	EDPIDR0	External Debug Peripheral Identification Register 0
0xFE4	EDPIDR1	External Debug Peripheral Identification Register 1
0xFE8	EDPIDR2	External Debug Peripheral Identification Register 2
0xFEC	EDPIDR3	External Debug Peripheral Identification Register 3
0xFF0	EDCIDR0	External Debug Component Identification Register 0
0xFF4	EDCIDR1	External Debug Component Identification Register 1
0xFF8	EDCIDR2	External Debug Component Identification Register 2
0xFFC	EDCIDR3	External Debug Component Identification Register 3

In the GIC CPU interface block:

Offset	Name	Description
0x0000	GICC_CTLR	CPU Interface Control Register
0x0004	GICC_PMR	CPU Interface Priority Mask Register

Offset	Name	Description
0x0008	GICC_BPR	CPU Interface Binary Point Register
0x000C	GICC_IAR	CPU Interface Interrupt Acknowledge Register
0x0010	GICC_EOIR	CPU Interface End Of Interrupt Register
0x0014	GICC_RPR	CPU Interface Running Priority Register
0x0018	GICC_HPPIR	CPU Interface Highest Priority Pending Interrupt Register
0x001C	GICC_ABPR	CPU Interface Aliased Binary Point Register
0x0020	GICC_AIAR	CPU Interface Aliased Interrupt Acknowledge Register
0x0024	GICC_AEOIR	CPU Interface Aliased End Of Interrupt Register
0x0028	GICC_AHPPIR	CPU Interface Aliased Highest Priority Pending Interrupt Register
0x002C	GICC_STATUSR	CPU Interface Status Register
0x002C	GICC_STATUSR	CPU Interface Status Register
0x00D0 + 4n	GICC_APR<n>	CPU Interface Active Priorities Registers
0x00E0 + 4n	GICC_NSAPR<n>	CPU Interface Non-secure Active Priorities Registers
0x00FC	GICC_IIDR	CPU Interface Identification Register
0x1000	GICC_DIR	CPU Interface Deactivate Interrupt Register

In the GIC Distributor block:

Offset	Name	Description
0x0000	GICD_CTLR	Distributor Control Register
0x0004	GICD_TYPER	Interrupt Controller Type Register
0x0008	GICD_IIDR	Distributor Implementer Identification Register
0x000C	GICD_TYPER2	Interrupt Controller Type Register 2
0x0010	GICD_STATUSR	Error Reporting Status Register
0x0010	GICD_STATUSR	Error Reporting Status Register
0x0040	GICD_SETSPI_NSR	Set Non-secure SPI Pending Register
0x0048	GICD_CLRSPI_NSR	Clear Non-secure SPI Pending Register
0x0050	GICD_SETSPI_SR	Set Secure SPI Pending Register
0x0058	GICD_CLRSPI_SR	Clear Secure SPI Pending Register
0x0080 + 4n	GICD_IGROUPR<n>	Interrupt Group Registers
0x0100 + 4n	GICD_ISENABLER<n>	Interrupt Set-Enable Registers
0x0180 + 4n	GICD_ICENABLER<n>	Interrupt Clear-Enable Registers
0x0200 + 4n	GICD_ISPENDR<n>	Interrupt Set-Pending Registers
0x0280 + 4n	GICD_ICPENDR<n>	Interrupt Clear-Pending Registers
0x0300 + 4n	GICD_ISACTIVER<n>	Interrupt Set-Active Registers
0x0380 + 4n	GICD_ICACTIVER<n>	Interrupt Clear-Active Registers
0x0400 + 4n	GICD_IPRIORITYR<n>	Interrupt Priority Registers
0x0800 + 4n	GICD_ITARGETSR<n>	Interrupt Processor Targets Registers
0x0C00 + 4n	GICD_ICFGR<n>	Interrupt Configuration Registers
0x0D00 + 4n	GICD_IGRPMODR<n>	Interrupt Group Modifier Registers
0x0E00 + 4n	GICD_NSACR<n>	Non-secure Access Control Registers
0x0F00	GICD_SGIR	Software Generated Interrupt Register
0x0F10 + 4n	GICD_CPENDSGIR<n>	SGI Clear-Pending Registers
0x0F20 + 4n	GICD_SPENDSGIR<n>	SGI Set-Pending Registers
0x1000 + 4n	GICD_IGROUPR<n>E	Interrupt Group Registers (extended SPI range)
0x1200 + 4n	GICD_ISENABLER<n>E	Interrupt Set-Enable Registers
0x1400 + 4n	GICD_ICENABLER<n>E	Interrupt Clear-Enable Registers
0x1600 + 4n	GICD_ISPENDR<n>E	Interrupt Set-Pending Registers (extended SPI range)
0x1800 + 4n	GICD_ICPENDR<n>E	Interrupt Clear-Pending Registers (extended SPI range)

Offset	Name	Description
0x1A00 + 4n	GICD_ISACTIVER<n>E	Interrupt Set-Active Registers (extended SPI range)
0x1C00 + 4n	GICD_ICACTIVER<n>E	Interrupt Clear-Active Registers (extended SPI range)
0x2000 + 4n	GICD_IPRIORITYR<n>E	Holds the priority of the corresponding interrupt for each extended SPI supported by the GIC.
0x3000 + 4n	GICD_ICFGR<n>E	Interrupt Configuration Registers (Extended SPI Range)
0x3400 + 4n	GICD_IGRPMODR<n>E	Interrupt Group Modifier Registers (extended SPI range)
0x3600 + 4n	GICD_NSACR<n>E	Non-secure Access Control Registers
0x6000 + 8n	GICD_IROUTER<n>	Interrupt Routing Registers
0x8000 + 8n	GICD_IROUTER<n>E	Interrupt Routing Registers (Extended SPI Range)

In the GIC ITS control block:

Offset	Name	Description
0x0000	GITS_CTLR	ITS Control Register
0x0004	GITS_IIDR	ITS Identification Register
0x0008	GITS_TYPER	ITS Type Register
0x0010	GITS_MPAMIDR	Report maximum PARTID and PMG Register
0x0014	GITS_PARTIDR	Set PARTID and PMG Register
0x0018	GITS_MPIDR	Report ITS's affinity.
0x0080	GITS_CBASER	ITS Command Queue Descriptor
0x0088	GITS_CWRITER	ITS Write Register
0x0090	GITS_CREADR	ITS Read Register
0x0100 + 8n	GITS_BASER<n>	ITS Translation Table Descriptors
0x20020	GITS_SGIR	ITS SGI Register

In the GIC ITS translation block:

Offset	Name	Description
0x0040	GITS_TRANSLATER	ITS Translation Register

In the GIC Redistributor block:

Frame	Offset	Name	Description
RD_base	0x0000	GICR_CTLR	Redistributor Control Register
RD_base	0x0004	GICR_IIDR	Redistributor Implementer Identification Register
RD_base	0x0008	GICR_TYPER	Redistributor Type Register
RD_base	0x0010	GICR_STATUSR	Error Reporting Status Register
RD_base	0x0010	GICR_STATUSR	Error Reporting Status Register
RD_base	0x0014	GICR_WAKER	Redistributor Wake Register
RD_base	0x0018	GICR_MPAMIDR	Report maximum PARTID and PMG Register
RD_base	0x001C	GICR_PARTIDR	Set PARTID and PMG Register
RD_base	0x0040	GICR_SETLPIR	Set LPI Pending Register
RD_base	0x0048	GICR_CLRLPIR	Clear LPI Pending Register
RD_base	0x0070	GICR_PROPBASER	Redistributor Properties Base Address Register
RD_base	0x0078	GICR_PENDBASER	Redistributor LPI Pending Table Base Address Register
RD_base	0x00A0	GICR_INVLPIR	Redistributor Invalidate LPI Register
RD_base	0x00B0	GICR_INVALLR	Redistributor Invalidate All Register
RD_base	0x00C0	GICR_SYNCR	Redistributor Synchronize Register
SGI_base	0x0080	GICR_IGROUPR0	Interrupt Group Register 0

Frame	Offset	Name	Description
SGI_base	0x0080 + 4n	GICR_IGROUPR<n>E	Interrupt Group Registers
SGI_base	0x0100	GICR_ISENABLER0	Interrupt Set-Enable Register 0
SGI_base	0x0100 + 4n	GICR_ISENABLER<n>E	Interrupt Set-Enable Registers
SGI_base	0x0180	GICR_ICENABLER0	Interrupt Clear-Enable Register 0
SGI_base	0x0180 + 4n	GICR_ICENABLER<n>E	Interrupt Clear-Enable Registers
SGI_base	0x0200	GICR_ISPENDR0	Interrupt Set-Pending Register 0
SGI_base	0x0200 + 4n	GICR_ISPENDR<n>E	Interrupt Set-Pending Registers
SGI_base	0x0280	GICR_ICPENDR0	Interrupt Clear-Pending Register 0
SGI_base	0x0280 + 4n	GICR_ICPENDR<n>E	Interrupt Clear-Pending Registers
SGI_base	0x0300	GICR_ISACTIVER0	Interrupt Set-Active Register 0
SGI_base	0x0300 + 4n	GICR_ISACTIVER<n>E	Interrupt Set-Active Registers
SGI_base	0x0380	GICR_ICACTIVER0	Interrupt Clear-Active Register 0
SGI_base	0x0380 + 4n	GICR_ICACTIVER<n>E	Interrupt Clear-Active Registers
SGI_base	0x0400 + 4n	GICR_IPRIORITYR<n>	Interrupt Priority Registers
SGI_base	0x0400 + 4n	GICR_IPRIORITYR<n>E	Interrupt Priority Registers (extended PPI range)
SGI_base	0x0C00	GICR_ICFGR0	Interrupt Configuration Register 0
SGI_base	0x0C00 + 4n	GICR_ICFGR<n>E	Interrupt configuration registers
SGI_base	0x0C04	GICR_ICFGR1	Interrupt Configuration Register 1
SGI_base	0x0D00	GICR_IGRPMODR0	Interrupt Group Modifier Register 0
SGI_base	0x0D00 + 4n	GICR_IGRPMODR<n>E	Interrupt Group Modifier Registers
SGI_base	0x0E00	GICR_NSACR	Non-secure Access Control Register
VLPI_base	0x0070	GICR_VPROPBASER	Virtual Redistributor Properties Base Address Register
VLPI_base	0x0078	GICR_VPENDBASER	Virtual Redistributor LPI Pending Table Base Address Register
VLPI_base	0x0080	GICR_VSGIR	Redistributor virtual SGI pending state request register
VLPI_base	0x0088	GICR_VSGIPENDR	Redistributor virtual SGI pending state register

In the GIC Virtual CPU interface block:

Offset	Name	Description
0x0000	GICV_CTLR	Virtual Machine Control Register
0x0004	GICV_PMR	Virtual Machine Priority Mask Register
0x0008	GICV_BPR	Virtual Machine Binary Point Register
0x000C	GICV_IAR	Virtual Machine Interrupt Acknowledge Register
0x0010	GICV_EOIR	Virtual Machine End Of Interrupt Register
0x0014	GICV_RPR	Virtual Machine Running Priority Register
0x0018	GICV_HPPIR	Virtual Machine Highest Priority Pending Interrupt Register
0x001C	GICV_ABPR	Virtual Machine Aliased Binary Point Register
0x0020	GICV_AIAR	Virtual Machine Aliased Interrupt Acknowledge Register
0x0024	GICV_AEOIR	Virtual Machine Aliased End Of Interrupt Register
0x0028	GICV_AHPPIR	Virtual Machine Aliased Highest Priority Pending Interrupt Register
0x002C	GICV_STATUSR	Virtual Machine Error Reporting Status Register
0x00D0 + 4n	GICV_APR<n>	Virtual Machine Active Priorities Registers
0x00FC	GICV_IIDR	Virtual Machine CPU Interface Identification Register
0x1000	GICV_DIR	Virtual Machine Deactivate Interrupt Register

In the GIC Virtual interface control block:

Offset	Name	Description
0x0000	GICH_HCR	Hypervisor Control Register
0x0004	GICH_VTR	Virtual Type Register
0x0008	GICH_VMCR	Virtual Machine Control Register
0x0010	GICH_MISR	Maintenance Interrupt Status Register
0x0020	GICH_EISR	End Interrupt Status Register
0x0030	GICH_ELRSR	Empty List Register Status Register
0x00F0 + 4n	GICH_APR<n>	Active Priorities Registers
0x0100 + 4n	GICH_LR<n>	List Registers

In the MPAM block:

Frame	Offset	Name	Description
MPAMF_BASE_ns	0x0000	MPAMF_IDR	MPAM Features Identification Register
MPAMF_BASE_ns	0x0018	MPAMF_IIDR	MPAM Implementation Identification Register
MPAMF_BASE_ns	0x0020	MPAMF_AIDR	MPAM Architecture Identification Register
MPAMF_BASE_ns	0x0028	MPAMF_IMPL_IDR	MPAM Implementation-Specific Partitioning Feature Identification Register
MPAMF_BASE_ns	0x0030	MPAMF_CPOR_IDR	MPAM Features Cache Portion Partitioning ID register
MPAMF_BASE_ns	0x0038	MPAMF_CCAP_IDR	MPAM Features Cache Capacity Partitioning ID register
MPAMF_BASE_ns	0x0040	MPAMF_MBW_IDR	MPAM Memory Bandwidth Partitioning Identification Register
MPAMF_BASE_ns	0x0048	MPAMF_PRI_IDR	MPAM Priority Partitioning Identification Register
MPAMF_BASE_ns	0x0050	MPAMF_PARTID_NRW_IDR	MPAM PARTID Narrowing ID register
MPAMF_BASE_ns	0x0080	MPAMF_MSMON_IDR	MPAM Resource Monitoring Identification Register
MPAMF_BASE_ns	0x0088	MPAMF_CSUMON_IDR	MPAM Features Cache Storage Usage

Frame	Offset	Name	Description
			Monitoring ID register
MPAMF_BASE_ns	0x0090	MPAMF_MBWUMON_IDR	MPAM Features Memory Bandwidth Usage Monitoring ID register
MPAMF_BASE_ns	0x00F0	MPAMF_ECR	MPAM Error Control Register
MPAMF_BASE_ns	0x00F8	MPAMF_ESR	MPAM Error Status Register
MPAMF_BASE_ns	0x0100	MPAMCFG_PART_SEL	MPAM Partition Configuration Selection Register
MPAMF_BASE_ns	0x0108	MPAMCFG_CMAX	MPAM Cache Maximum Capacity Partition Configuration Register
MPAMF_BASE_ns	0x0200	MPAMCFG_MBW_MIN	MPAM Cache Maximum Capacity Partition Configuration Register
MPAMF_BASE_ns	0x0208	MPAMCFG_MBW_MAX	MPAM Memory Bandwidth Maximum Partition Configuration Register
MPAMF_BASE_ns	0x0220	MPAMCFG_MBW_WINWD	MPAM Memory Bandwidth Partitioning Window Width Configuration Register
MPAMF_BASE_ns	0x0400	MPAMCFG_PRI	MPAM Priority Partition Configuration Register
MPAMF_BASE_ns	0x0500	MPAMCFG_MBW_PROP	MPAM Memory Bandwidth Proportional Stride Partition Configuration Register
MPAMF_BASE_ns	0x0600	MPAMCFG_INTPARTID	MPAM Internal PARTID Narrowing Configuration Register
MPAMF_BASE_ns	0x0800	MSMON_CFG_MON_SEL	MPAM Monitor Instance Selection Register
MPAMF_BASE_ns	0x0808	MSMON_CAPT_EVNT	MPAM Capture Event Generation Register

Frame	Offset	Name	Description
MPAMF_BASE_ns	0x0810	MSMON_CFG_CSU_FLT	MPAM Memory System Monitor Configure Cache Storage Usage Monitor Filter Register
MPAMF_BASE_ns	0x0818	MSMON_CFG_CSU_CTL	MPAM Memory System Monitor Configure Cache Storage Usage Monitor Control Register
MPAMF_BASE_ns	0x0820	MSMON_CFG_MBWU_FLT	MPAM Memory System Monitor Configure Memory Bandwidth Usage Monitor Filter Register
MPAMF_BASE_ns	0x0828	MSMON_CFG_MBWU_CTL	MPAM Memory System Monitor Configure Memory Bandwidth Usage Monitor Control Register
MPAMF_BASE_ns	0x0840	MSMON_CSU	MPAM Cache Storage Usage Monitor Register
MPAMF_BASE_ns	0x0848	MSMON_CSU_CAPTURE	MPAM Cache Storage Usage Monitor Capture Register
MPAMF_BASE_ns	0x0860	MSMON_MBWU	MPAM Memory Bandwidth Usage Monitor Register
MPAMF_BASE_ns	0x0868	MSMON_MBWU_CAPTURE	MPAM Memory Bandwidth Usage Monitor Capture Register
MPAMF_BASE_ns	0x0880	MSMON_MBWU_L	MPAM Long Memory Bandwidth Usage Monitor Register
MPAMF_BASE_ns	0x0890	MSMON_MBWU_L_CAPTUREMSMON_MBWU__L_CAPTURE	MPAM Long Memory Bandwidth Usage Monitor Capture Register
MPAMF_BASE_ns	0x1000	MPAMCFG_CPBM	MPAM Cache Portion Bitmap Partition Configuration Register
MPAMF_BASE_ns	0x2000	MPAMCFG_MBW_PBM	MPAM Bandwidth Portion Bitmap

Frame	Offset	Name	Description
			Partition Configuration Register
MPAMF_BASE_s	0x0000	MPAMF_IDR	MPAM Features Identification Register
MPAMF_BASE_s	0x0008	MPAMF_SIDR	MPAM Features Secure Identification Register
MPAMF_BASE_s	0x0018	MPAMF_IIDR	MPAM Implementation Identification Register
MPAMF_BASE_s	0x0020	MPAMF_AIDR	MPAM Architecture Identification Register
MPAMF_BASE_s	0x0028	MPAMF_IMPL_IDR	MPAM Implementation-Specific Partitioning Feature Identification Register
MPAMF_BASE_s	0x0030	MPAMF_CPOR_IDR	MPAM Features Cache Portion Partitioning ID register
MPAMF_BASE_s	0x0038	MPAMF_CCAP_IDR	MPAM Features Cache Capacity Partitioning ID register
MPAMF_BASE_s	0x0040	MPAMF_MBW_IDR	MPAM Memory Bandwidth Partitioning Identification Register
MPAMF_BASE_s	0x0048	MPAMF_PRI_IDR	MPAM Priority Partitioning Identification Register
MPAMF_BASE_s	0x0050	MPAMF_PARTID_NRW_IDR	MPAM PARTID Narrowing ID register
MPAMF_BASE_s	0x0080	MPAMF_MSMON_IDR	MPAM Resource Monitoring Identification Register
MPAMF_BASE_s	0x0088	MPAMF_CSUMON_IDR	MPAM Features Cache Storage Usage Monitoring ID register
MPAMF_BASE_s	0x0090	MPAMF_MBWUMON_IDR	MPAM Features Memory Bandwidth Usage Monitoring ID register
MPAMF_BASE_s	0x00F0	MPAMF_ECR	MPAM Error Control Register

Frame	Offset	Name	Description
MPAMF_BASE_s	0x00F8	MPAMF_ESR	MPAM Error Status Register
MPAMF_BASE_s	0x0100	MPAMCFG_PART_SEL	MPAM Partition Configuration Selection Register
MPAMF_BASE_s	0x0108	MPAMCFG_CMAX	MPAM Cache Maximum Capacity Partition Configuration Register
MPAMF_BASE_s	0x0200	MPAMCFG_MBW_MIN	MPAM Cache Maximum Capacity Partition Configuration Register
MPAMF_BASE_s	0x0208	MPAMCFG_MBW_MAX	MPAM Memory Bandwidth Maximum Partition Configuration Register
MPAMF_BASE_s	0x0220	MPAMCFG_MBW_WINWD	MPAM Memory Bandwidth Partitioning Window Width Configuration Register
MPAMF_BASE_s	0x0400	MPAMCFG_PRI	MPAM Priority Partition Configuration Register
MPAMF_BASE_s	0x0500	MPAMCFG_MBW_PROP	MPAM Memory Bandwidth Proportional Stride Partition Configuration Register
MPAMF_BASE_s	0x0600	MPAMCFG_INTPARTID	MPAM Internal PARTID Narrowing Configuration Register
MPAMF_BASE_s	0x0800	MSMON_CFG_MON_SEL	MPAM Monitor Instance Selection Register
MPAMF_BASE_s	0x0808	MSMON_CAPT_EVNT	MPAM Capture Event Generation Register
MPAMF_BASE_s	0x0810	MSMON_CFG_CSU_FLT	MPAM Memory System Monitor Configure Cache Storage Usage Monitor Filter Register
MPAMF_BASE_s	0x0818	MSMON_CFG_CSU_CTL	MPAM Memory System Monitor Configure Cache Storage Usage Monitor

Frame	Offset	Name	Description
			Control Register
MPAMF_BASE_s	0x0820	MSMON_CFG_MBWU_FLT	MPAM Memory System Monitor Configure Memory Bandwidth Usage Monitor Filter Register
MPAMF_BASE_s	0x0828	MSMON_CFG_MBWU_CTL	MPAM Memory System Monitor Configure Memory Bandwidth Usage Monitor Control Register
MPAMF_BASE_s	0x0840	MSMON_CSU	MPAM Cache Storage Usage Monitor Register
MPAMF_BASE_s	0x0848	MSMON_CSU_CAPTURE	MPAM Cache Storage Usage Monitor Capture Register
MPAMF_BASE_s	0x0860	MSMON_MBWU	MPAM Memory Bandwidth Usage Monitor Register
MPAMF_BASE_s	0x0868	MSMON_MBWU_CAPTURE	MPAM Memory Bandwidth Usage Monitor Capture Register
MPAMF_BASE_s	0x0880	MSMON_MBWU_L	MPAM Long Memory Bandwidth Usage Monitor Register
MPAMF_BASE_s	0x0890	MSMON_MBWU_L_CAPTUREMSMON_MBWU__L_CAPTURE	MPAM Long Memory Bandwidth Usage Monitor Capture Register
MPAMF_BASE_s	0x1000	MPAMCFG_CPBM	MPAM Cache Portion Bitmap Partition Configuration Register
MPAMF_BASE_s	0x2000	MPAMCFG_MBW_PBM	MPAM Bandwidth Portion Bitmap Partition Configuration Register

In the PMU block:

Offset	Name	Description
0x000 + 8n	PMEVCNTR<n>_EL0	Performance Monitors Event Count Registers
0x0F8	PMCCNTR_EL0[31:0]	Performance Monitors Cycle Counter

Offset	Name	Description
0x0FC	PMCCNTR_EL0[63:32]	Performance Monitors Cycle Counter
0x200	PMPCSR[31:0]	Program Counter Sample Register
0x204	PMPCSR[63:32]	Program Counter Sample Register
0x208	PMCID1SR	CONTEXTIDR_EL1 Sample Register
0x20C	PMVIDSR	VMID Sample Register
0x220	PMPCSR[31:0]	Program Counter Sample Register
0x224	PMPCSR[63:32]	Program Counter Sample Register
0x228	PMCID1SR	CONTEXTIDR_EL1 Sample Register
0x22C	PMCID2SR	CONTEXTIDR_EL2 Sample Register
0x400 + 4n	PMEVTYPER<n>_EL0	Performance Monitors Event Type Registers
0x47C	PMCCFILTR_EL0	Performance Monitors Cycle Counter Filter Register
0xC00	PMCNTENSET_EL0	Performance Monitors Count Enable Set register
0xC20	PMCNTENCLR_EL0	Performance Monitors Count Enable Clear register
0xC40	PMINTENSET_EL1	Performance Monitors Interrupt Enable Set register
0xC60	PMINTENCLR_EL1	Performance Monitors Interrupt Enable Clear register
0xC80	PMOVSCLR_EL0	Performance Monitors Overflow Flag Status Clear register
0xCA0	PMSWINC_EL0	Performance Monitors Software Increment register
0xCC0	PMOVSSET_EL0	Performance Monitors Overflow Flag Status Set register
0xE00	PMCFGR	Performance Monitors Configuration Register
0xE04	PMCR_EL0	Performance Monitors Control Register
0xE20	PMCEID0	Performance Monitors Common Event Identification register 0
0xE24	PMCEID1	Performance Monitors Common Event Identification register 1
0xE28	PMCEID2	Performance Monitors Common Event Identification register 2
0xE2C	PMCEID3	Performance Monitors Common Event Identification register 3
0xE40	PMMIR	Performance Monitors Machine Identification Register
0xF00	PMITCTRL	Performance Monitors Integration mode Control register
0xFA8	PMDEVAFF0	Performance Monitors Device Affinity register 0
0xFAC	PMDEVAFF1	Performance Monitors Device Affinity register 1
0xFB0	PMLAR	Performance Monitors Lock Access Register
0xFB4	PMLSR	Performance Monitors Lock Status Register
0xFB8	PMAUTHSTATUS	Performance Monitors Authentication Status register
0xFBC	PMDEVARCH	Performance Monitors Device Architecture register
0xFC8	PMDEVID	Performance Monitors Device ID register
0xFCC	PMDEVTYPE	Performance Monitors Device Type register
0xFD0	PMPIDR4	Performance Monitors Peripheral Identification Register 4
0xFE0	PMPIDR0	Performance Monitors Peripheral Identification Register 0
0xFE4	PMPIDR1	Performance Monitors Peripheral Identification Register 1
0xFE8	PMPIDR2	Performance Monitors Peripheral Identification Register 2
0xFEC	PMPIDR3	Performance Monitors Peripheral Identification Register 3
0xFF0	PMCIDR0	Performance Monitors Component Identification Register 0
0xFF4	PMCIDR1	Performance Monitors Component Identification Register 1
0xFF8	PMCIDR2	Performance Monitors Component Identification Register 2
0xFFC	PMCIDR3	Performance Monitors Component Identification Register 3

In the RAS block:

Offset	Name	Description
0x000 + 64n	ERR<n>FR	Error Record Feature Register
0x008 + 64n	ERR<n>CTLR	Error Record Control Register

External register index by offset

Offset	Name	Description
0x010 + 64n	ERR<n>STATUS	Error Record Primary Status Register
0x018 + 64n	ERR<n>ADDR	Error Record Address Register
0x020 + 64n	ERR<n>MISC0	Error Record Miscellaneous Register 0
0x028 + 64n	ERR<n>MISC1	Error Record Miscellaneous Register 1
0x030 + 64n	ERR<n>MISC2	Error Record Miscellaneous Register 2
0x038 + 64n	ERR<n>MISC3	Error Record Miscellaneous Register 3
0x800 + 64n	ERR<n>PFGF	Pseudo-fault Generation Feature Register
0x808 + 64n	ERR<n>PFGCTL	Pseudo-fault Generation Control Register
0x810 + 64n	ERR<n>PFGCDN	Pseudo-fault Generation Countdown Register
0xE00	ERRGSR	Error Group Status Register
0xE10	ERRIIDR	Implementation Identification Register
0xE80	ERRFHICR0	Fault-Handling Interrupt Configuration Register 0
0xE80 + 8n	ERRIRQCR<n>	Generic Error Interrupt Configuration Register
0xE88	ERRFHICR1	Fault-Handling Interrupt Configuration Register 1
0xE8C	ERRFHICR2	Fault-Handling Interrupt Configuration Register 2
0xE90	ERRERICR0	Error Recovery Interrupt Configuration Register 0
0xE98	ERRERICR1	Error Recovery Interrupt Configuration Register 1
0xE9C	ERRERICR2	Error Recovery Interrupt Configuration Register 2
0xEA0	ERRCRICR0	Critical Error Interrupt Configuration Register 0
0xEA8	ERRCRICR1	Critical Error Interrupt Configuration Register 1
0xEAC	ERRCRICR2	Critical Error Interrupt Configuration Register 2
0xEF8	ERRIRQSR	Error Interrupt Status Register
0xFA8	ERRDEVAFF	Device Affinity Register
0xFBC	ERRDEVARCH	Device Architecture Register
0xFC8	ERRDEVID	Device Configuration Register
0xFD0	ERRPIDR4	Peripheral Identification Register 4
0xFE0	ERRPIDR0	Peripheral Identification Register 0
0xFE4	ERRPIDR1	Peripheral Identification Register 1
0xFE8	ERRPIDR2	Peripheral Identification Register 2
0xFEC	ERRPIDR3	Peripheral Identification Register 3
0xFF0	ERRCIDR0	Component Identification Register 0
0xFF4	ERRCIDR1	Component Identification Register 1
0xFF8	ERRCIDR2	Component Identification Register 2
0xFFC	ERRCIDR3	Component Identification Register 3

In the Timer block:

Frame	Offset	Name	Description
CNTBaseN	0x000	CNTPCT[31:0]	Counter-timer Physical Count
CNTBaseN	0x004	CNTPCT[63:32]	Counter-timer Physical Count
CNTBaseN	0x008	CNTVCT[31:0]	Counter-timer Virtual Count
CNTBaseN	0x00C	CNTVCT[63:32]	Counter-timer Virtual Count
CNTBaseN	0x010	CNTFRQ	Counter-timer Frequency
CNTBaseN	0x014	CNTEL0ACR	Counter-timer EL0 Access Control Register
CNTBaseN	0x018	CNTVOFF[31:0]	Counter-timer Virtual Offset
CNTBaseN	0x01C	CNTVOFF[63:32]	Counter-timer Virtual Offset
CNTBaseN	0x020	CNTP_CVAL[31:0]	Counter-timer Physical Timer CompareValue
CNTBaseN	0x024	CNTP_CVAL[63:32]	Counter-timer Physical Timer CompareValue
CNTBaseN	0x028	CNTP_TVAL	Counter-timer Physical Timer TimerValue

Frame	Offset	Name	Description
CNTBaseN	0x02C	CNTP_CTL	Counter-timer Physical Timer Control
CNTBaseN	0x030	CNTV_CVAL[31:0]	Counter-timer Virtual Timer CompareValue
CNTBaseN	0x034	CNTV_CVAL[63:32]	Counter-timer Virtual Timer CompareValue
CNTBaseN	0x038	CNTV_TVAL	Counter-timer Virtual Timer TimerValue
CNTBaseN	0x03C	CNTV_CTL	Counter-timer Virtual Timer Control
CNTBaseN	0xFD0 + 4n	CounterID<n>	Counter ID registers
CNTCTLBase	0x000	CNTFRQ	Counter-timer Frequency
CNTCTLBase	0x004	CNTNSAR	Counter-timer Non-secure Access Register
CNTCTLBase	0x008	CNTTIDR	Counter-timer Timer ID Register
CNTCTLBase	0x040 + 4n	CNTACR<n>	Counter-timer Access Control Registers
CNTCTLBase	0x080 + 8n	CNTVOFF<n>[31:0]	Counter-timer Virtual Offsets
CNTCTLBase	0x084 + 8n	CNTVOFF<n>[63:32]	Counter-timer Virtual Offsets
CNTCTLBase	0xFD0 + 4n	CounterID<n>	Counter ID registers
CNTControlBase	0x000	CNTCR	Counter Control Register
CNTControlBase	0x004	CNTSR	Counter Status Register
CNTControlBase	0x008	CNTCV[63:0]	Counter Count Value register
CNTControlBase	0x020	CNTFID0	Counter Frequency ID
CNTControlBase	0x020 + 4n	CNTFID<n>	Counter Frequency IDs, n > 0
CNTControlBase	0x10	CNTSCR	Counter Scale Register
CNTControlBase	0x1C	CNTID	Counter Identification Register
CNTControlBase	0xFD0 + 4n	CounterID<n>	Counter ID registers
CNTEL0BaseN	0x000	CNTPCT[31:0]	Counter-timer Physical Count
CNTEL0BaseN	0x004	CNTPCT[63:32]	Counter-timer Physical Count
CNTEL0BaseN	0x008	CNTVCT[31:0]	Counter-timer Virtual Count
CNTEL0BaseN	0x00C	CNTVCT[63:32]	Counter-timer Virtual Count
CNTEL0BaseN	0x010	CNTFRQ	Counter-timer Frequency
CNTEL0BaseN	0x020	CNTP_CVAL[31:0]	Counter-timer Physical Timer CompareValue
CNTEL0BaseN	0x024	CNTP_CVAL[63:32]	Counter-timer Physical Timer CompareValue
CNTEL0BaseN	0x028	CNTP_TVAL	Counter-timer Physical Timer TimerValue
CNTEL0BaseN	0x02C	CNTP_CTL	Counter-timer Physical Timer Control
CNTEL0BaseN	0x030	CNTV_CVAL[31:0]	Counter-timer Virtual Timer CompareValue
CNTEL0BaseN	0x034	CNTV_CVAL[63:32]	Counter-timer Virtual Timer CompareValue
CNTEL0BaseN	0x038	CNTV_TVAL	Counter-timer Virtual Timer TimerValue
CNTEL0BaseN	0x03C	CNTV_CTL	Counter-timer Virtual Timer Control
CNTEL0BaseN	0xFD0 + 4n	CounterID<n>	Counter ID registers
CNTReadBase	0x000	CNTCV[63:0]	Counter Count Value register
CNTReadBase	0xFD0 + 4n	CounterID<n>	Counter ID registers

Copyright Â© 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMCNTENCLR0, Activity Monitors Count Enable Clear Register 0

The AMCNTENCLR0 characteristics are:

Purpose

Disable control bits for the architected s event counters, AMEVCNTR0<n>.

Configuration

External register AMCNTENCLR0 bits [31:0] are architecturally mapped to AArch64 System register AMCNTENCLR0_EL0[31:0] .

External register AMCNTENCLR0 bits [31:0] are architecturally mapped to AArch32 System register AMCNTENCLR0[31:0] .

The power domain of AMCNTENCLR0 is IMPLEMENTATION DEFINED. ~~Some or all RW fields of this register have defined reset values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMCNTENCLR0 are RES0.

Attributes

AMCNTENCLR0 is a 32-bit register.

Field descriptions

The AMCNTENCLR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
P<n>, bit [n]																															

P<n>, bit [n], for n = 0 to 31

Activity monitor event counter disable bit for AMEVCNTR0<n>.

Bits [31:N] are RAZ/WI. N is the value in AMCGCR.CG0NC.

Possible values of each bit are:

P<n>	Meaning
0b0	When read, means that AMEVCNTR0<n> is disabled. When written, has no effect.
0b1	When read, means that AMEVCNTR0<n> is enabled. When written, disables AMEVCNTR0<n>.

On a Cold reset, this field resets to 0.

Accessing the AMCNTENCLR0

AMCNTENCLR0 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance

AMU	0xC20	AMCNTENCLR0	~~AMCNTENSET0~~

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMCNTENCLR1, Activity Monitors Count Enable Clear Register 1

The AMCNTENCLR1 characteristics are:

Purpose

Disable control bits for the auxiliary activity monitors event counters, AMEVCNTR1<n>.

Configuration

External register AMCNTENCLR1 bits [31:0] are architecturally mapped to AArch64 System register AMCNTENCLR1_EL0[31:0] .

External register AMCNTENCLR1 bits [31:0] are architecturally mapped to AArch32 System register AMCNTENCLR1[31:0] .

The power domain of AMCNTENCLR1 is IMPLEMENTATION DEFINED. ~~Some or all RW fields of this register have defined reset values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMCNTENCLR1 are RES0.

Attributes

AMCNTENCLR1 is a 32-bit register.

Field descriptions

The AMCNTENCLR1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
P<n>, bit [n]																															

P<n>, bit [n], for n = 0 to 31

Activity monitor event counter disable bit for AMEVCNTR1<n>.

Bits [31:N] are RAZ/WI. N is the value in AMCGCR.CG1NC.

Possible values of each bit are:

P<n>	Meaning
0b0	When read, means that AMEVCNTR1<n> is disabled. When written, has no effect.
0b1	When read, means that AMEVCNTR1<n> is enabled. When written, disables AMEVCNTR1<n>.

On a Cold reset, this field resets to 0.

Accessing the AMCNTENCLR1

If the number of auxiliary activity monitor event counters implemented is zero, reads and writes of AMCNTENCLR1 are CONSTRAINED UNPREDICTABLE, and accesses to the register behave as RAZ/WI.

Note

The number of auxiliary activity monitor event counters implemented is zero exactly when AMCFGR.NCG == 0b0000.

AMCNTENCLR1 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
AMU	0xC24	AMCNTENCLR1

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMCNTENSET0, Activity Monitors Count Enable Set Register 0

The AMCNTENSET0 characteristics are:

Purpose

Enable control bits for the architected activity monitors event counters, AMEVCNTR0<n>.

Configuration

External register AMCNTENSET0 bits [31:0] are architecturally mapped to AArch64 System register AMCNTENSET0_EL0[31:0] .

External register AMCNTENSET0 bits [31:0] are architecturally mapped to AArch32 System register AMCNTENSET0[31:0] .

The power domain of AMCNTENSET0 is IMPLEMENTATION DEFINED. ~~Some or all RW fields of this register have defined reset values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMCNTENSET0 are RES0.

Attributes

AMCNTENSET0 is a 32-bit register.

Field descriptions

The AMCNTENSET0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
P<n>, bit [n]																															

P<n>, bit [n], for n = 0 to 31

Activity monitor event counter enable bit for AMEVCNTR0<n>.

Bits [31:N] are RAZ/WI. N is the value in AMCGCR.CG0NC.

Possible values of each bit are:

P<n>	Meaning
0b0	When read, means that AMEVCNTR0<n> is disabled. When written, has no effect.
0b1	When read, means that AMEVCNTR0<n> is enabled. When written, enables AMEVCNTR0<n>.

On a Cold reset, this field resets to 0.

Accessing the AMCNTENSET0

AMCNTENSET0 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance

AMU	0xC00	AMCNTENSET0

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMCNTENSET1, Activity Monitors Count Enable Set Register 1

The AMCNTENSET1 characteristics are:

Purpose

Enable control bits for the auxiliary activity monitors event counters, AMEVCNTR1<n>.

Configuration

External register AMCNTENSET1 bits [31:0] are architecturally mapped to AArch64 System register AMCNTENSET1_EL0[31:0] .

External register AMCNTENSET1 bits [31:0] are architecturally mapped to AArch32 System register AMCNTENSET1[31:0] .

The power domain of AMCNTENSET1 is IMPLEMENTATION DEFINED. ~~Some or all RW fields of this register have defined reset values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMCNTENSET1 are RES0.

Attributes

AMCNTENSET1 is a 32-bit register.

Field descriptions

The AMCNTENSET1 bit assignments are:



P<n>, bit [n], for n = 0 to 31

Activity monitor event counter enable bit for AMEVCNTR1<n>.

Bits [31:N] are RAZ/WI. N is the value in AMCGCR.CG1NC.

Possible values of each bit are:

P<n>	Meaning
0b0	When read, means that AMEVCNTR1<n> is disabled. When written, has no effect.
0b1	When read, means that AMEVCNTR1<n> is enabled. When written, enables AMEVCNTR1<n>.

On a Cold reset, this field resets to 0.

Accessing the AMCNTENSET1

If the number of auxiliary activity monitor event counters implemented is zero, reads and writes of AMCNTENSET1 are CONSTRAINED UNPREDICTABLE, and accesses to the register behave as RAZ/WI.

Note

The number of auxiliary activity monitor counters implemented is zero exactly when AMCFGR.NCG == 0b0000.

AMCNTENSET1 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
AMU	0xC04	AMCNTENSET1

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMDEVAFF0, Activity Monitors Device Affinity Register 0

The AMDEVAFF0 characteristics are:

Purpose

Copy of the low half of the PE MPIDR_EL1 register that allows a debugger to determine which PE in a multiprocessor system the AMU component relates to.

Configuration

The power domain of AMDEVAFF0 is IMPLEMENTATION DEFINED.

Implementation of this register is OPTIONAL.

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMDEVAFF0 are RES0.

Attributes

AMDEVAFF0 is a 32-bit register.

Field descriptions

The AMDEVAFF0 bit assignments are:



MPIDR_EL1loMPIDR_EL1 low half, bits [31:0]

MPIDR_EL1 low half. Read-only copy of the low half of MPIDR_EL1, as seen from the highest implemented Exception level.

Accessing the AMDEVAFF0

AMDEVAFF0 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
AMU	0xFA8	AMDEVAFF0

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMDEVAFF1, Activity Monitors Device Affinity Register 1

The AMDEVAFF1 characteristics are:

Purpose

Copy of the high half of the PE MPIDR_EL1 register that allows a debugger to determine which PE in a multiprocessor system the AMU component relates to.

Configuration

The power domain of AMDEVAFF1 is IMPLEMENTATION DEFINED.

Implementation of this register is OPTIONAL.

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMDEVAFF1 are RES0.

Attributes

AMDEVAFF1 is a 32-bit register.

Field descriptions

The AMDEVAFF1 bit assignments are:



MPIDR_EL1hiMPIDR_EL1 high half, bits [31:0]

MPIDR_EL1 high half. Read-only copy of the high half of MPIDR_EL1, as seen from the highest implemented Exception level.

Accessing the AMDEVAFF1

AMDEVAFF1 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
AMU	0xFAC	AMDEVAFF1

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMEVCNTR0<n>, Activity Monitors Event Counter Registers 0, n = 0 - 15

The AMEVCNTR0<n> characteristics are:

Purpose

Provides access to the architected activity monitor event counters.

Configuration

External register AMEVCNTR0<n> bits [63:0] are architecturally mapped to AArch64 System register AMEVCNTR0<n>_EL0[63:0] .

External register AMEVCNTR0<n> bits [63:0] are architecturally mapped to AArch32 System register AMEVCNTR0<n>[63:0] .

The power domain of AMEVCNTR0<n> is IMPLEMENTATION DEFINED. ~~Some or all RW fields of this register have defined reset values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMEVCNTR0<n> are RES0.

Attributes

AMEVCNTR0<n> is a 64-bit register.

Field descriptions

The AMEVCNTR0<n> bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ACNT																															
ACNT																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

ACNT, bits [63:0]

Architected activity monitor event counter n.

Value of architected activity monitor event counter n, where n is the number of this register and is a number from 0 to 15.

If the counter is enabled, writes to this register have UNPREDICTABLE results.

On a Cold reset, this field resets to `0`.

Accessing the AMEVCNTR0<n>

If <n> is greater than or equal to the number of architected activity monitor event counters, reads and writes of AMEVCNTR0<n> are CONSTRAINED UNPREDICTABLE, and accesses to the register behave as RAZ/WI.

Note

AMCGCR.CG0NC identifies the number of architected activity monitor event counters.

AMEVCNTR0<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance	Range
AMU	0x000 + 8n	AMEVCNTR0<n>	31:0

Accesses on this interface are **RO**.

Component	Offset	Instance	Range
AMU	0x004 + 8n	AMEVCNTR0<n>	63:32

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

AMEVCNTR1<n>, Activity Monitors Event Counter Registers 1, n = 0 - 15

The AMEVCNTR1<n> characteristics are:

Purpose

Provides access to the auxiliary activity monitor event counters.

Configuration

External register AMEVCNTR1<n> bits [63:0] are architecturally mapped to AArch64 System register AMEVCNTR1<n>_EL0[63:0] .

External register AMEVCNTR1<n> bits [63:0] are architecturally mapped to AArch32 System register AMEVCNTR1<n>[63:0] .

The power domain of AMEVCNTR1<n> is IMPLEMENTATION DEFINED. ~~Some or all RW fields of this register have defined reset values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

This register is present only when AMUv1 is implemented. Otherwise, direct accesses to AMEVCNTR1<n> are RES0.

Attributes

AMEVCNTR1<n> is a 64-bit register.

Field descriptions

The AMEVCNTR1<n> bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ACNT																															
ACNT																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

ACNT, bits [63:0]

Auxiliary activity monitor event counter n.

Value of auxiliary activity monitor event counter n, where n is the number of this register and is a number from 0 to 15.

If the counter is enabled, writes to this register have UNPREDICTABLE results.

On a Cold reset, this field resets to `0`.

Accessing the AMEVCNTR1<n>

If <n> is greater than or equal to the number of auxiliary activity monitor event counters, reads and writes of AMEVCNTR1<n> are CONSTRAINED UNPREDICTABLE, and accesses to the register behave as RAZ/WI.

Note

AMCGCR.CG1NC identifies the number of auxiliary activity monitor event counters.

AMEVCNTR1<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance	Range
AMU	0x100 + 8n	AMEVCNTR1<n>	31:0

Accesses on this interface are **RO**.

Component	Offset	Instance	Range
AMU	0x104 + 8n	AMEVCNTR1<n>	63:32

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTACR<n>, Counter-timer Access Control Registers, n = 0 - 7

The CNTACR<n> characteristics are:

Purpose

Provides top-level access controls for the elements of a timer frame. CNTACR<n> provides the controls for frame CNTBaseN.

In addition to the CNTACR<n> control:

- CNTNSAR controls whether CNTACR<n> is accessible by Non-secure accesses.
- If frame CNTEL0BaseN is implemented, the CNTEL0ACR in frame CNTBaseN provides additional control of accesses to frame CNTEL0BaseN.

Configuration

The power domain of CNTACR<n> is IMPLEMENTATION DEFINED.

~~The power domain of CNTACR<n> is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Implemented only if the value of CNTTIDR.Frame<n> is 1.

An implementation of the counters might not provide configurable access to some or all of the features. In this case, the associated field in the CNTACR<n> register is:

- RAZ/WI if access is always denied.
- RAO/WI if access is always permitted.

Attributes

CNTACR<n> is a 32-bit register.

Field descriptions

The CNTACR<n> bit assignments are:

31 30 29 28 27 26 25 24 23 22 21 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6	5	4	3	2	1	0
RES0	RWPT	RWVT	RVOFF	RFRQ	RVCT	RPCT

Bits [31:6]

Reserved, RES0.

RWPT, bit [5]

Read/write access to the EL1 Physical Timer registers CNTP_CVAL, CNTP_TVAL, and CNTP_CTL, in frame <n>. The possible values of this bit are:

RWPT	Meaning
0b0	No access to the EL1 Physical Timer registers in frame <n>. The registers are RES0.
0b1	Read/write access to the EL1 Physical Timer registers in frame <n>.

This field resets to an architecturally UNKNOWN value.

RWVT, bit [4]

Read/write access to the Virtual Timer register CNTV_CVAL, CNTV_TVAL, and CNTV_CTL, in frame <n>. The possible values of this bit are:

RWVT	Meaning
0b0	No access to the Virtual Timer registers in frame <n>. The registers are RES0.
0b1	Read/write access to the Virtual Timer registers in frame <n>.

This field resets to an architecturally UNKNOWN value.

RVOFF, bit [3]

Read-only access to CNTVOFF, in frame <n>. The possible values of this bit are:

RVOFF	Meaning
0b0	No access to CNTVOFF in frame <n>. The register is RES0.
0b1	Read-only access to CNTVOFF in frame <n>.

This field resets to an architecturally UNKNOWN value.

RFRQ, bit [2]

Read-only access to CNTFRQ, in frame <n>. The possible values of this bit are:

RFRQ	Meaning
0b0	No access to CNTFRQ in frame <n>. The register is RES0.
0b1	Read-only access to CNTFRQ in frame <n>.

This field resets to an architecturally UNKNOWN value.

RVCT, bit [1]

Read-only access to CNTVCT, in frame <n>. The possible values of this bit are:

RVCT	Meaning
0b0	No access to CNTVCT in frame <n>. The register is RES0.
0b1	Read-only access to CNTVCT in frame <n>.

This field resets to an architecturally UNKNOWN value.

RPCT, bit [0]

Read-only access to CNTPCT, in frame <n>. The possible values of this bit are:

RPCT	Meaning
0b0	No access to CNTPCT in frame <n>. The register is RES0.
0b1	Read-only access to CNTPCT in frame <n>.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTACR<n>

In a system that recognizes two Security states:

- CNTACR<n> is always accessible by Secure accesses.
- CNTNSAR.NS<n> determines whether CNTACR<n> is accessible by Non-secure accesses.

CNTACR<n> can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTCTLBase	0x040 + 4n	CNTACR<n>

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTCR, Counter Control Register

The CNTCR characteristics are:

Purpose

Enables the counter, controls the counter frequency setting, and controls counter behavior during debug.

Configuration

The power domain of CNTCR is IMPLEMENTATION DEFINED. ~~Some or all RW fields of this register have defined reset values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

Attributes

CNTCR is a 32-bit register.

Field descriptions

The CNTCR bit assignments are:



Bits [31:18]

Reserved, RES0.

FCREQ, bits [17:8]

Frequency change request. Indicates the number of the entry in the Frequency modes table to select.

Selecting an unimplemented entry, or an entry that contains 0, has no effect on the counter.

The maximum number of entries in the Frequency modes table is IMPLEMENTATION DEFINED up to a maximum of 1004 entries, see 'The Frequency modes table' in Chapter I1 of the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile. An implementation is only required to implement an FCREQ field that can hold values from 0 to the highest supported Frequency modes table entry. Any unrequired most-significant bits of FCREQ can be implemented as RES0.

This field resets to `0`.

Bits [7:3]

Reserved, RES0.

SCEN, bit [2]

When ARMv8.4-CNTSC is implemented:

Scale Enable.

SCEN	Meaning
0b0	Scaling is not enabled. The counter value is incremented by 0x1.0000000 for each counter tick.
0b1	Scaling is enabled. The counter is incremented by CNTSCR.ScaleVal for each counter tick.

The SCEN bit can only be changed when the counter is disabled, when CNTCR.EN == 0.

If the value of CNTCR.SCEN changes when CNTCR.EN == 1 then:

- The counter value becomes UNKNOWN.
- The counter value remains UNKNOWN on future ticks of the clock.

When the CNTCV register in the CNTControlBase frame of the memory mapped counter module is written to, the accumulated fraction information is reset to zero.

This field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HDBG, bit [1]

Halt-on-debug. Controls whether a Halt-on-debug signal halts the system counter:

HDBG	Meaning
0b0	System counter ignores Halt-on-debug.
0b1	Asserted Halt-on-debug signal halts system counter update.

This field resets to an architecturally UNKNOWN value.

EN, bit [0]

Enables the counter:

EN	Meaning
0b0	System counter disabled.
0b1	System counter enabled.

This field resets to 0.

Accessing the CNTCR

In a system that supports Secure and Non-secure memory maps the CNTControlBase frame, that includes this register, is implemented only in the Secure memory map.

CNTCR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTControlBase	0x000	CNTCR

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTCV, Counter Count Value register

The CNTCV characteristics are:

Purpose

Indicates the current count value.

Configuration

The power domain of CNTCV is IMPLEMENTATION DEFINED.

~~The power domain of CNTCV is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTCV is a 64-bit register.

Field descriptions

The CNTCV bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CountValue																															
CountValue																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CountValue, bits [63:0]

Indicates the counter value.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTCV

Frame	Accessibility
CNTControlBase	RW
CNTReadBase	RO

A write to CNTCV must be visible in the CNTPCT register of each running processor in a finite time.

For the instance of the register in the CNTControlBase frame:

- In a system that supports Secure and Non-secure memory maps the CNTControlBase frame, and therefore this register instance, is implemented only in the Secure memory map.
- If the counter is enabled, the effect of writing to the register is UNKNOWN.

In an implementation that supports 64-bit atomic memory accesses, this register must be accessible using a 64-bit atomic access.

CNTCV can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance	Range
Timer	CNTControlBase	0x008	CNTCV	63:0

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance	Range
Timer	CNTReadBase	0x000	CNTCV	63:0

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTEL0ACR, Counter-timer EL0 Access Control Register

The CNTEL0ACR characteristics are:

Purpose

An implementation of CNTEL0ACR in the frame at CNTBaseN controls whether the CNTPCT, CNTVCT, CNTFRQ, EL1 Physical Timer, and Virtual Timer registers are visible in the frame at CNTEL0BaseN.

Configuration

The power domain of CNTEL0ACR is IMPLEMENTATION DEFINED.

~~The power domain of CNTEL0ACR is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

Implementation of this register is OPTIONAL.

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTEL0ACR is a 32-bit register.

Field descriptions

The CNTEL0ACR bit assignments are:



Bits [31:10]

Reserved, RES0.

EL0PTEN, bit [9]

Second view read/write access control for the EL1 Physical Timer registers. This bit controls whether the CNTP_CVAL, CNTP_TVAL, and CNTP_CTL registers in the current CNTBaseN frame are also accessible in the corresponding CNTEL0BaseN frame. The possible values of this bit are:

EL0PTEN	Meaning
0b0	No access. Registers are RES0 in the second view.
0b1	Access permitted. If the registers are accessible in the current frame then they are accessible in the second view.

This field resets to an architecturally UNKNOWN value.

EL0VTEN, bit [8]

Second view read/write access control for the Virtual Timer registers. This bit controls whether the CNTV_CVAL, CNTV_TVAL, and CNTV_CTL registers in the current CNTBaseN frame are also accessible in the corresponding CNTEL0BaseN frame. The possible values of this bit are:

EL0VTEN	Meaning
0b0	No access. Registers are RES0 in the second view.
0b1	Access permitted. If the registers are accessible in the current frame then they are accessible in the second view.

The definition of this bit means that, if the Virtual Timer registers are not implemented in the current CNTBaseN frame, then the Virtual Timer register addresses are RES0 in the corresponding CNTEL0BaseN frame, regardless of the value of this bit.

This field resets to an architecturally UNKNOWN value.

Bits [7:2]

Reserved, RES0.

EL0VCTEN, bit [1]

Second view read access control for CNTVCT and CNTFRQ. The possible values of this bit are:

EL0VCTEN	Meaning
0b0	CNTVCT is not visible in the second view. If EL0PCTEN is set to 0, CNTFRQ is not visible in the second view.
0b1	Access permitted. If CNTVCT and CNTFRQ are visible in the current frame then they are visible in the second view.

This field resets to an architecturally UNKNOWN value.

EL0PCTEN, bit [0]

Second view read access control for CNTPCT and CNTFRQ. The possible values of this bit are:

EL0PCTEN	Meaning
0b0	CNTPCT is not visible in the second view. If EL0VCTEN is set to 0, CNTFRQ is not visible in the second view.
0b1	Access permitted. If CNTPCT and CNTFRQ are visible in the current frame then they are visible in the second view.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTEL0ACR

CNTEL0ACR can be implemented in any implemented CNTBaseN frame.

'CNTCTLBase status and control fields for the CNTBaseN and CNTEL0BaseN frames' in Chapter I1 of the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile describes the status fields that identify whether a CNTBaseN frame is implemented, and for an implemented frame:

- Whether the CNTBaseN frame has virtual timer capability.
- Whether the corresponding CNTEL0BaseN frame is implemented.
- For an implementation that recognizes two Security states, whether the CNTBaseN frame, and any corresponding CNTEL0BaseN frame, is accessible by Non-secure accesses.

If CNTEL0ACR is not implemented in an implemented CNTBaseN frame:

- The register location in that frame is RAZ/WI.
- If the corresponding CNTEL0BaseN frame is implemented, the registers CNTFRQ, CNTP_CTL, CNTP_CVAL, CNTP_TVAL, CNTPCT, CNTV_CTL, CNTV_CVAL, CNTV_TVAL, and CNTVCT are not visible in that frame.

CNTEL0ACR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTBaseN	0x014	CNTEL0ACR

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTFID0, Counter Frequency ID

The CNTFID0 characteristics are:

Purpose

Indicates the base frequency of the system counter.

Configuration

The power domain of CNTFID0 is IMPLEMENTATION DEFINED.

~~The power domain of CNTFID0 is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The possible frequencies for the system counter are stored in the Frequency modes table as 32-bit words starting with the base frequency, CNTFID0. For more information see 'The Frequency modes table' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The final entry in the Frequency modes table must be followed by a 32-bit word of zero value, to mark the end of the table.

Typically, the Frequency modes table will be in read-only memory. However, a system implementation might use read/write memory for the table, and initialize the table entries as part of its start-up sequence.

If the Frequency modes table is in read/write memory, Arm strongly recommends that the table is not updated once the system is running.

Attributes

CNTFID0 is a 32-bit register.

Field descriptions

The CNTFID0 bit assignments are:



Frequency, bits [31:0]

The base frequency of the system counter, in Hz.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTFID0

It is IMPLEMENTATION DEFINED whether this register is RO or RW

In a system that supports Secure and Non-secure memory maps the CNTControlBase frame, that includes this register, is implemented only in the Secure memory map.

CNTFID0 can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTControlBase	0x020	CNTFID0

Accesses on this interface are **RO or RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTFID<n>, Counter Frequency IDs, n > 0, n = 1 - 1003

The CNTFID<n> characteristics are:

Purpose

Indicates alternative system counter update frequencies.

Configuration

The power domain of CNTFID<n> is IMPLEMENTATION DEFINED.

~~The power domain of CNTFID<n> is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The possible frequencies for the system counter are stored in the Frequency modes table as 32-bit words starting with the base frequency, CNTFID0, see 'The Frequency modes table' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The number of CNTFID<n> registers is IMPLEMENTATION DEFINED, and the only required CNTFID<n> register is CNTFID0.

The final entry in the Frequency modes table must be followed by a 32-bit word of zero value, to mark the end of the table.

The architecture can support up to 1004 entries in the Frequency modes table, including the zero-word end marker, and the number of entries is IMPLEMENTATION DEFINED up to this limit. For an implementation that includes registers in the IMPLEMENTATION DEFINED register space `0x0C0-0x0FC`, the maximum number of entries in the Frequency modes table is 40, including the zero-word end marker.

Typically, the Frequency modes table will be in read-only memory. However, a system implementation might use read/write memory for the table, and initialize the table entries as part of its start-up sequence.

If the Frequency modes table is in read/write memory, Arm strongly recommends that the table is not updated once the system is running.

Attributes

CNTFID<n> is a 32-bit register.

Field descriptions

The CNTFID<n> bit assignments are:



Frequency, bits [31:0]

A system counter update frequency, in Hz. Must be an exact divisor of the base frequency. Arm strongly recommends that all frequency values in the Frequency modes table are integer power-of-two divisors of the base frequency.

When the system timer is operating at a lower frequency than the base frequency, the increment applied at each counter update is given by:

increment = (base frequency) / (selected frequency)

This field resets to an architecturally UNKNOWN value.

Accessing the CNTFID<n>

It is IMPLEMENTATION DEFINED whether this register is RO or RW

In a system that supports Secure and Non-secure memory maps the CNTControlBase frame, that includes these registers, is implemented only in the Secure memory map.

CNTFID<n> can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTControlBase	0x020 + 4n	CNTFID<n>

Accesses on this interface are **RO or RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTFRQ, Counter-timer Frequency

The CNTFRQ characteristics are:

Purpose

This register is provided so that software can discover the frequency of the system counter. The instance of the register in the CNTCTLBase frame must be programmed with this value as part of system initialization. The value of the register is not interpreted by hardware.

Configuration

The power domain of CNTFRQ is IMPLEMENTATION DEFINED.

~~The power domain of CNTFRQ is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTFRQ is a 32-bit register.

Field descriptions

The CNTFRQ bit assignments are:



Bits [31:0]

Clock frequency. Indicates the system counter clock frequency, in Hz.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTFRQ

CNTFRQ must be implemented as an RW register in the CNTCTLBase frame.

In a system that recognizes two Security states, the instance of the register in the CNTCTLBase frame is only accessible by Secure accesses.

CNTFRQ can be implemented as a RO register in any implemented CNTBaseN frame, and in the corresponding CNTEL0BaseN frame.

'CNTCTLBase status and control fields for the CNTBaseN and CNTEL0BaseN frames' in Chapter I2 of the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile describes the status fields that identify whether a CNTBaseN frame is implemented, and for an implemented frame:

- Whether the CNTBaseN frame has virtual timer capability.
- Whether the corresponding CNTEL0BaseN frame is implemented.
- For an implementation that recognizes two Security states, whether the CNTBaseN frame, and any corresponding CNTEL0BaseN frame, is accessible by Non-secure accesses.

For an implemented CNTBaseN frame:

- CNTFRQ is accessible in that frame, as a RO register, if the value of CNTACR<n>.RFRQ is 1.
- Otherwise, the CNTFRQ address in that frame is RAZ/WI.

For an implemented CNTEL0BaseN frame:

- CNTFRQ is accessible as a RO register in that frame if both:
  - CNTFRQ is accessible in the corresponding CNTBaseN frame.
  - Either the value of CNTEL0ACR.EL0VCTEN is 1 or the value of CNTEL0ACR.EL0PCTEN is 1.
- Otherwise, the CNTFRQ address in that frame is RAZ/WI.

CNTFRQ can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTBaseN	0x010	CNTFRQ

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance
Timer	CNTEL0BaseN	0x010	CNTFRQ

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance
Timer	CNTCTLBase	0x000	CNTFRQ

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTNSAR, Counter-timer Non-secure Access Register

The CNTNSAR characteristics are:

Purpose

Provides the highest-level control of whether frames CNTBaseN and CNTEL0BaseN are accessible by Non-secure accesses.

Configuration

The power domain of CNTNSAR is IMPLEMENTATION DEFINED.

~~The power domain of CNTNSAR is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTNSAR is a 32-bit register.

Field descriptions

The CNTNSAR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								NS7	NS6	NS5	NS4	NS3	NS2	NS1	NS0

Bits [31:8]

Reserved, RES0.

NS<n>, bit [n], for n = 0 to 7

Non-secure access to frame n. The possible values of this bit are:

NS<n>	Meaning
0b0	Secure access only. Behaves as RES0 to Non-secure accesses.
0b1	Secure and Non-secure accesses permitted.

This bit also determines whether, in the CNTCTLBase frame, CNTACR<n> and CNTVOFF<n> are accessible to Non-secure accesses.

If frame CNTBase<n>:

- Is not implemented, then NS<n> is RES0.
- Is not Configurable access, and is accessible only by Secure accesses, then NS<n> is RES0.
- Is not Configurable access, and is accessible by both Secure and Non-secure accesses, then NS<n> is RES1.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTNSAR

In a system that recognizes two Security states, this register is only accessible by Secure accesses.

CNTNSAR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTCTLBase	0x004	CNTNSAR

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTP_CTL, Counter-timer Physical Timer Control

The CNTP_CTL characteristics are:

Purpose

Control register for the EL1 physical timer.

Configuration

The power domain of CNTP_CTL is IMPLEMENTATION DEFINED.

~~The power domain of CNTP_CTL is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTP_CTL is a 32-bit register.

Field descriptions

The CNTP_CTL bit assignments are:



Bits [31:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTP_TVAL continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTP_CTL

CNTP_CTL can be implemented in any implemented CNTBaseN frame, and in the corresponding CNTEL0BaseN frame.

'CNTCTLBase status and control fields for the CNTBaseN and CNTEL0BaseN frames' in Chapter I1 of the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile describes the status fields that identify whether a CNTBaseN frame is implemented, and for an implemented frame:

- Whether the CNTBaseN frame has virtual timer capability.
- Whether the corresponding CNTEL0BaseN frame is implemented.
- For an implementation that recognizes two Security states, whether the CNTBaseN frame, and any corresponding CNTEL0BaseN frame, is accessible by Non-secure accesses.

For an implemented CNTBaseN frame:

- CNTP_CTL is accessible in that frame if the value of CNTACR<n>.RWPT is 1.
- Otherwise, the CNTP_CTL address in that frame is RAZ/WI.

For an implemented CNTEL0BaseN frame:

- CNTP_CTL is accessible in that frame if both:
  - CNTP_CTL is accessible in the corresponding CNTBaseN frame:
  - The value of CNTEL0ACR.EL0PTEN is 1.
- Otherwise, the CNTP_CTL address in that frame is RAZ/WI.

CNTP_CTL can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTBaseN	0x02C	CNTP_CTL

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
Timer	CNTEL0BaseN	0x02C	CNTP_CTL

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTP_CVAL, Counter-timer Physical Timer CompareValue

The CNTP_CVAL characteristics are:

Purpose

Holds the 64-bit compare value for the EL1 physical timer.

Configuration

The power domain of CNTP_CVAL is IMPLEMENTATION DEFINED.

~~The power domain of CNTP_CVAL is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTP_CVAL is a 64-bit register.

Field descriptions

The CNTP_CVAL bit assignments are:



CompareValue, bits [63:0]

Holds the EL1 physical timer CompareValue.

When CNTP_CTL.ENABLE is 1, the timer condition is met when (CNTPCT - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTP_CTL.ISTATUS is set to 1.
- An interrupt is generated if CNTP_CTL.IMASK is 0.

When CNTP_CTL.ENABLE is 0, the timer condition is not met, but CNTPCT continues to count.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTP_CVAL

CNTP_CVAL can be implemented in any implemented CNTBaseN frame, and in the corresponding CNTEL0BaseN frame.

'CNTCTLBase status and control fields for the CNTBaseN and CNTEL0BaseN frames' in Chapter I1 of the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile describes the status fields that identify whether a CNTBaseN frame is implemented, and for an implemented frame:

- Whether the CNTBaseN frame has virtual timer capability.
- Whether the corresponding CNTEL0BaseN frame is implemented.
- For an implementation that recognizes two Security states, whether the CNTBaseN frame, and any corresponding CNTEL0BaseN frame, is accessible by Non-secure accesses.

For an implemented CNTBaseN frame:

- CNTP_CVAL is accessible in that frame if the value of CNTACR<n>.RWPT is 1.
- Otherwise, the CNTP_CVAL address in that frame is RAZ/WI.

For an implemented CNTEL0BaseN frame:

- CNTP_CVAL is accessible in that frame if both:
  - CNTP_CVAL is accessible in the corresponding CNTBaseN frame:
  - The value of CNTEL0ACR.EL0PTEN is 1.
- Otherwise, the CNTP_CVAL address in that frame is RAZ/WI.

If the implementation supports 64-bit atomic accesses, then the CNTP_CVAL register must be accessible as an atomic 64-bit value.

CNTP_CVAL can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance	Range
Timer	CNTBaseN	0x020	CNTP_CVAL	31:0

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance	Range
Timer	CNTBaseN	0x024	CNTP_CVAL	63:32

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance	Range
Timer	CNTEL0BaseN	0x020	CNTP_CVAL	31:0

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance	Range
Timer	CNTEL0BaseN	0x024	CNTP_CVAL	63:32

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTP_TVAL, Counter-timer Physical Timer TimerValue

The CNTP_TVAL characteristics are:

Purpose

Holds the timer value for the EL1 physical timer.

Configuration

The power domain of CNTP_TVAL is IMPLEMENTATION DEFINED.

~~The power domain of CNTP_TVAL is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTP_TVAL is a 32-bit register.

Field descriptions

The CNTP_TVAL bit assignments are:



TimerValue, bits [31:0]

The TimerValue view of the EL1 physical timer.

On a read of this register:

- If CNTP_CTL.ENABLE is 0, the value returned is UNKNOWN.
- If CNTP_CTL.ENABLE is 1, the value returned is (CompareValue - CNTPCT).

On a write of this register, CompareValue is set to (CNTPCT + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTP_CTL.ENABLE is 1, the timer condition is met when (CNTPCT - CompareValue) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTP_CTL.ISTATUS is set to 1.
- If CNTP_CTL.IMASK is 0, an interrupt is generated.

When CNTP_CTL.ENABLE is 0, the timer condition is not met, but CNTPCT continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTP_TVAL

CNTP_TVAL can be implemented in any implemented CNTBaseN frame, and in the corresponding CNTEL0BaseN frame.

'CNTCTLBase status and control fields for the CNTBaseN and CNTEL0BaseN frames' in Chapter I1 of the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile describes the status fields that identify whether a CNTBaseN frame is implemented, and for an implemented frame:

- Whether the CNTBaseN frame has virtual timer capability.
- Whether the corresponding CNTEL0BaseN frame is implemented.
- For an implementation that recognizes two Security states, whether the CNTBaseN frame, and any corresponding CNTEL0BaseN frame, is accessible by Non-secure accesses.

For an implemented CNTBaseN frame:

- CNTP_TVAL is accessible in that frame if the value of CNTACR<n>.RWPT is 1.
- Otherwise, the CNTP_TVAL address in that frame is RAZ/WI.

For an implemented CNTEL0BaseN frame:

- CNTP_TVAL is accessible in that frame if both:
  - CNTP_TVAL is accessible in the corresponding CNTBaseN frame:
  - The value of CNTEL0ACR.EL0PTEN is 1.
- Otherwise, the CNTP_TVAL address in that frame is RAZ/WI.

CNTP_TVAL can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTBaseN	0x028	CNTP_TVAL

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
Timer	CNTEL0BaseN	0x028	CNTP_TVAL

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTSCR, Counter Scale Register

The CNTSCR characteristics are:

Purpose

Enables the counter, controls the counter frequency setting, and controls counter behavior during debug.

Configuration

The power domain of CNTSCR is IMPLEMENTATION DEFINED.

~~The power domain of CNTSCR is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

This register is present only when ARMv8.4-CNTSC is implemented. Otherwise, direct accesses to CNTSCR are RES0.

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTSCR is a 32-bit register.

Field descriptions

The CNTSCR bit assignments are:



ScaleVal, bits [31:0]

Scale Value

When counter scaling is enabled, ScaleVal is the amount added to the counter value for every counter tick.

Counter tick is defined as one period of the current operating frequency of the Generic counter.

ScaleVal is expressed as an unsigned fixed point number with an 8-bit integer value and a 24-bit fractional value.

CNTSCR.ScaleVal can only be changed when CNTCR.EN == 0. If the value of this field is changed when CNTCR.EN == 1:

- The counter value becomes UNKNOWN.
- The counter value remains UNKNOWN on future ticks of the clock.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTSCR

In a system that supports Secure and Non-secure memory maps the CNTControlBase frame, that includes this register, is implemented only in the Secure memory map.

CNTSCR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTControlBase	0x10	CNTSCR

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTSR, Counter Status Register

The CNTSR characteristics are:

Purpose

Provides counter frequency status information.

Configuration

The power domain of CNTSR is IMPLEMENTATION DEFINED. ~~Some or all RW fields of this register have defined reset values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTSR is a 32-bit register.

Field descriptions

The CNTSR bit assignments are:



FCACK, bits [31:8]

Frequency change acknowledge. Indicates the currently selected entry in the Frequency modes table, see 'The Frequency modes table' in Chapter I1 of the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

This field resets to `0`.

Bits [7:2]

Reserved, RES0.

DBGH, bit [1]

Indicates whether the counter is halted because the Halt-on-debug signal is asserted:

DBGH	Meaning
`0b0`	Counter is not halted.
`0b1`	Counter is halted.

This field resets to an architecturally UNKNOWN value.

Bit [0]

Reserved, RES0.

Accessing the CNTSR

In a system that supports Secure and Non-secure memory maps the CNTControlBase frame, that includes this register, is implemented only in the Secure memory map.

CNTSR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTControlBase	0x004	CNTSR

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTV_CTL, Counter-timer Virtual Timer Control

The CNTV_CTL characteristics are:

Purpose

Control register for the virtual timer.

Configuration

The power domain of CNTV_CTL is IMPLEMENTATION DEFINED.

~~The power domain of CNTV_CTL is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTV_CTL is a 32-bit register.

Field descriptions

The CNTV_CTL bit assignments are:



Bits [31:3]

Reserved, RES0.

ISTATUS, bit [2]

The status of the timer. This bit indicates whether the timer condition is met:

ISTATUS	Meaning
0b0	Timer condition is not met.
0b1	Timer condition is met.

When the value of the ENABLE bit is 1, ISTATUS indicates whether the timer condition is met. ISTATUS takes no account of the value of the IMASK bit. If the value of ISTATUS is 1 and the value of IMASK is 0 then the timer interrupt is asserted.

When the value of the ENABLE bit is 0, the ISTATUS field is UNKNOWN.

For more information see 'Operation of the CompareValue views of the timers' and 'Operation of the TimerValue views of the timers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, chapter D6.

This bit is read-only.

IMASK, bit [1]

Timer interrupt mask bit. Permitted values are:

IMASK	Meaning
0b0	Timer interrupt is not masked by the IMASK bit.
0b1	Timer interrupt is masked by the IMASK bit.

For more information, see the description of the ISTATUS bit.

This field resets to an architecturally UNKNOWN value.

ENABLE, bit [0]

Enables the timer. Permitted values are:

ENABLE	Meaning
0b0	Timer disabled.
0b1	Timer enabled.

Setting this bit to 0 disables the timer output signal, but the timer value accessible from CNTV_TVAL continues to count down.

Note

Disabling the output signal might be a power-saving option.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTV_CTL

CNTV_CTL can be implemented in any implemented CNTBaseN frame that has virtual timer capability, and in the corresponding CNTEL0BaseN frame.

'CNTCTLBase status and control fields for the CNTBaseN and CNTEL0BaseN frames' in Chapter I1 of the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile describes the status fields that identify whether a CNTBaseN frame is implemented, and for an implemented frame:

- Whether the CNTBaseN frame has virtual timer capability.
- Whether the corresponding CNTEL0BaseN frame is implemented.
- For an implementation that recognizes two Security states, whether the CNTBaseN frame, and any corresponding CNTEL0BaseN frame, is accessible by Non-secure accesses.

For an implemented CNTBaseN frame that has virtual timer capability:

- CNTV_CTL is accessible in that frame if the value of CNTACR<n>.RWVT is 1.
- Otherwise, the CNTV_CTL address in that frame is RAZ/WI.

For an implemented CNTEL0BaseN frame:

- CNTV_CTL is accessible in that frame if both:
  - CNTV_CTL is accessible in the corresponding CNTBaseN frame:
  - The value of CNTEL0ACR.EL0VTEN is 1.
- Otherwise, the CNTV_CTL address in that frame is RAZ/WI.

CNTV_CTL can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTBaseN	0x03C	CNTV_CTL

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
Timer	CNTEL0BaseN	0x03C	CNTV_CTL

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTV_CVAL, Counter-timer Virtual Timer CompareValue

The CNTV_CVAL characteristics are:

Purpose

Holds the 64-bit compare value for the virtual timer.

Configuration

The power domain of CNTV_CVAL is IMPLEMENTATION DEFINED.

~~The power domain of CNTV_CVAL is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTV_CVAL is a 64-bit register.

Field descriptions

The CNTV_CVAL bit assignments are:



CompareValue, bits [63:0]

Holds the virtual timer CompareValue.

When CNTV_CTL.ENABLE is 1, the timer condition is met when (CNTVCT - CompareValue) is greater than or equal to zero. This means that CompareValue acts like a 64-bit upcounter timer. When the timer condition is met:

- CNTV_CTL.ISTATUS is set to 1.
- An interrupt is generated if CNTV_CTL.IMASK is 0.

When CNTV_CTL.ENABLE is 0, the timer condition is not met, but CNTVCT continues to count.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTV_CVAL

CNTV_CVAL can be implemented in any implemented CNTBaseN frame that has virtual timer capability, and in the corresponding CNTEL0BaseN frame.

'CNTCTLBase status and control fields for the CNTBaseN and CNTEL0BaseN frames' in Chapter I1 of the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile describes the status fields that identify whether a CNTBaseN frame is implemented, and for an implemented frame:

- Whether the CNTBaseN frame has virtual timer capability.
- Whether the corresponding CNTEL0BaseN frame is implemented.
- For an implementation that recognizes two Security states, whether the CNTBaseN frame, and any corresponding CNTEL0BaseN frame, is accessible by Non-secure accesses.

For an implemented CNTBaseN frame that has virtual timer capability:

- CNTV_CVAL is accessible in that frame if the value of CNTACR<n>.RWVT is 1.
- Otherwise, the CNTV_CVAL address in that frame is RAZ/WI.

For an implemented CNTEL0BaseN frame:

- CNTV_CVAL is accessible in that frame if both:
  - CNTV_CVAL is accessible in the corresponding CNTBaseN frame:
  - The value of CNTEL0ACR.EL0VTEN is 1.
- Otherwise, the CNTV_CVAL address in that frame is RAZ/WI.

If the implementation supports 64-bit atomic accesses, then the CNTV_CVAL register must be accessible as an atomic 64-bit value.

CNTV_CVAL can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance	Range
Timer	CNTBaseN	0x030	CNTV_CVAL	31:0

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance	Range
Timer	CNTBaseN	0x034	CNTV_CVAL	63:32

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance	Range
Timer	CNTEL0BaseN	0x030	CNTV_CVAL	31:0

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance	Range
Timer	CNTEL0BaseN	0x034	CNTV_CVAL	63:32

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CNTV_TVAL, Counter-timer Virtual Timer TimerValue

The CNTV_TVAL characteristics are:

Purpose

Holds the timer value for the virtual timer.

Configuration

The power domain of CNTV_TVAL is IMPLEMENTATION DEFINED.

~~The power domain of CNTV_TVAL is IMPLEMENTATION DEFINED. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a reset of the reset domain in which the register is implemented. The register is not affected by a reset of any other reset domain.~~

For more information see 'Power and reset domains for the system level implementation of the Generic Timer' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Attributes

CNTV_TVAL is a 32-bit register.

Field descriptions

The CNTV_TVAL bit assignments are:



TimerValue, bits [31:0]

The TimerValue view of the virtual timer.

On a read of this register:

- If CNTV_CTL.ENABLE is 0, the value returned is UNKNOWN.
- If CNTV_CTL.ENABLE is 1, the value returned is (CompareValue - CNTVCT).

On a write of this register, CompareValue is set to (CNTVCT + TimerValue), where TimerValue is treated as a signed 32-bit integer.

When CNTV_CTL.ENABLE is 1, the timer condition is met when (CNTVCT - CompareValue) is greater than or equal to zero. This means that TimerValue acts like a 32-bit downcounter timer. When the timer condition is met:

- CNTV_CTL.ISTATUS is set to 1.
- If CNTV_CTL.IMASK is 0, an interrupt is generated.

When CNTV_CTL.ENABLE is 0, the timer condition is not met, but CNTVCT continues to count, so the TimerValue view appears to continue to count down.

This field resets to an architecturally UNKNOWN value.

Accessing the CNTV_TVAL

CNTV_TVAL can be implemented in any implemented CNTBaseN frame that has virtual timer capability, and in the corresponding CNTEL0BaseN frame.

'CNTCTLBase status and control fields for the CNTBaseN and CNTEL0BaseN frames' in Chapter I1 of the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile describes the status fields that identify whether a CNTBaseN frame is implemented, and for an implemented frame:

- Whether the CNTBaseN frame has virtual timer capability.
- Whether the corresponding CNTEL0BaseN frame is implemented.
- For an implementation that recognizes two Security states, whether the CNTBaseN frame, and any corresponding CNTEL0BaseN frame, is accessible by Non-secure accesses.

For an implemented CNTBaseN frame that has virtual timer capability:

- CNTV_TVAL is accessible in that frame if the value of CNTACR<n>.RWVT is 1.
- Otherwise, the CNTV_TVAL address in that frame is RAZ/WI.

For an implemented CNTEL0BaseN frame:

- CNTV_TVAL is accessible in that frame if both:
  - CNTV_TVAL is accessible in the corresponding CNTBaseN frame:
  - The value of CNTEL0ACR.EL0VTEN is 1.
- Otherwise, the CNTV_TVAL address in that frame is RAZ/WI.

CNTV_TVAL can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
Timer	CNTBaseN	0x038	CNTV_TVAL

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
Timer	CNTEL0BaseN	0x038	CNTV_TVAL

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTIAPPSET, CTI Application Trigger Set register

The CTIAPPSET characteristics are:

Purpose

Sets bits of the Application Trigger register.

Configuration

CTIAPPSET is in the Debug power domain.

~~CTIAPPSET is in the Debug power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on an External debug reset. The register is not affected by a Warm reset and is not affected by a Cold reset.~~

Attributes

CTIAPPSET is a 32-bit register.

Field descriptions

The CTIAPPSET bit assignments are:



APPSET<x>, bit [x], for x = 0 to 31

Application trigger <x> enable.

Bits [31:N] are RAZ/WI. N is the number of ECT channels implemented as defined by the CTIDEVID.NUMCHAN field.

Possible values of this bit are:

APPSET<x>	Meaning
0b0	Reading this means the application trigger is inactive. Writing this has no effect.
0b1	Reading this means the application trigger is active. Writing this sets the corresponding bit in CTIAPPTRIG to 1 and generates a channel event.

If the ECT does not support multicycle channel events, use of CTIAPPSET is deprecated and the debugger must only use CTIAPPPULSE.

On a External debug reset, this field resets to an architecturally UNKNOWN value.

Accessing the CTIAPPSET

CTIAPPSET can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0x014	CTIAPPSET

This interface is accessible as follows:

- When SoftwareLockStatus() accesses to this register are **RO**.

- When !SoftwareLockStatus() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTIAUTHSTATUS, CTI Authentication Status register

The CTIAUTHSTATUS characteristics are:

Purpose

Provides information about the state of the IMPLEMENTATION DEFINED authentication interface for CTI.

Configuration

CTIAUTHSTATUS is in the Debug power domain.

This register is OPTIONAL, and is required for CoreSight compliance.

Attributes

CTIAUTHSTATUS is a 32-bit register.

Field descriptions

The CTIAUTHSTATUS bit assignments are:



Bits [31:8]

Reserved, RES0.

Bits [7:4]

Reserved, RAZ.

NSNID, bits [3:2]

If EL3 is ~~not~~ implemented, this~~and~~ field~~the implemented Security state is Secure state,~~ holds the same value as DBGAUTHSTATUS_EL1.NSNID.~~SNID.~~

If EL3 is not implemented and the implemented Security state is Secure state~~Otherwise~~, this field holds the same value as DBGAUTHSTATUS_EL1.SNID.~~NSNID.~~

NSID, bits [1:0]

If EL3 is ~~not~~ implemented, this~~and~~ field~~the implemented Security state is Secure state,~~ holds the same value as DBGAUTHSTATUS_EL1.NSNID.~~SID.~~

If EL3 is not implemented and the implemented Security state is Secure state~~Otherwise~~, this field holds the same value as DBGAUTHSTATUS_EL1.SID.~~NSID.~~

Accessing the CTIAUTHSTATUS

CTIAUTHSTATUS can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0xFB8	CTIAUTHSTATUS

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTICLAIMCLR, CTI CLAIM Tag Clear register

The CTICLAIMCLR characteristics are:

Purpose

Used by software to read the values of the CLAIM bits, and to clear CLAIM tag bits to 0.

Configuration

CTICLAIMCLR is in the Debug power domain. ~~Some or all RW fields of this register have defined reset values. These apply only on an External debug reset. The register is not affected by a Warm reset and is not affected by a Cold reset.~~

Implementation of this register is OPTIONAL.

Attributes

CTICLAIMCLR is a 32-bit register.

Field descriptions

The CTICLAIMCLR bit assignments are:



CLAIM[<x>], bit [x], for x = 0 to 31

CLAIM tag clear bit.

For values of x greater than or equal to the IMPLEMENTATION DEFINED number of CLAIM tags, this bit is RAZ/SBZ. Software can rely on these bits reading as zero, and must use a Should-Be-Zero policy on writes. Implementations must ignore writes.

For other values of x, reads return the value of CLAIM[x] and the behavior on writes is:

CLAIM[<x>]	Meaning
0b0	No action.
0b1	Indirectly clear CLAIM[x] to 0.

A single write to CTICLAIMCLR can clear multiple tags to 0.

An External Debug reset clears the CLAIM tag bits to 0.

Accessing the CTICLAIMCLR

CTICLAIMCLR can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0xFA4	CTICLAIMCLR

This interface is accessible as follows:

- When SoftwareLockStatus() accesses to this register are **RO**.
- When !SoftwareLockStatus() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTICLAIMSET, CTI CLAIM Tag Set register

The CTICLAIMSET characteristics are:

Purpose

Used by software to set CLAIM bits to 1.

Configuration

CTICLAIMSET is in the Debug power domain. ~~Some or all RW fields of this register have defined reset values. These apply only on an External debug reset. The register is not affected by a Warm reset and is not affected by a Cold reset.~~

Implementation of this register is OPTIONAL.

Attributes

CTICLAIMSET is a 32-bit register.

Field descriptions

The CTICLAIMSET bit assignments are:



CLAIM[<x>], bit [x], for x = 0 to 31

CLAIM tag set bit.

For values of x greater than or equal to the IMPLEMENTATION DEFINED number of CLAIM tags, this bit is RAZ/SBZ. Software can rely on these bits reading as zero, and must use a Should-Be-Zero policy on writes. Implementations must ignore writes.

For other values of x, the bit is RAO and the behavior on writes is:

CLAIM[<x>]	Meaning
0b0	No action.
0b1	Indirectly set CLAIM[x] tag to 1.

A single write to CTICLAIMSET can set multiple tags to 1.

An External Debug reset clears the CLAIM tag bits to 0.

Accessing the CTICLAIMSET

CTICLAIMSET can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0xFA0	CTICLAIMSET

This interface is accessible as follows:

- When SoftwareLockStatus() accesses to this register are **RO**.
- When !SoftwareLockStatus() accesses to this register are **RW**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116~~134483bd14dc8e12a99c984cbfe3431cc1c9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTICONTROL, CTI Control register

The CTICONTROL characteristics are:

Purpose

Controls whether the CTI is enabled.

Configuration

CTICONTROL is in the Debug power domain. ~~Some or all RW fields of this register have defined reset values. These apply only on an External debug reset. The register is not affected by a Warm reset and is not affected by a Cold reset.~~

Attributes

CTICONTROL is a 32-bit register.

Field descriptions

The CTICONTROL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																															GLBEN

Bits [31:1]

Reserved, RES0.

GLBEN, bit [0]

Enables or disables the CTI mapping functions. Possible values of this field are:

GLBEN	Meaning
0b0	CTI mapping functions and application trigger disabled.
0b1	CTI mapping functions and application trigger enabled.

When GLBEN is 0, the input channel to output trigger, input trigger to output channel, and application trigger functions are disabled and do not signal new events on either output triggers or output channels. If a previously asserted output trigger has not been acknowledged, it remains asserted after the mapping functions are disabled. All output triggers are disabled by CTI reset.

If the ECT supports multicycle channel events any existing output channel events will be terminated.

The following resets apply:

~~On a External debug reset, this field resets to 0.~~

- On a Cold reset, the value of this field is unchanged.
- On an External debug reset, this field resets to 0.
- On a Warm reset, the value of this field is unchanged.

Accessing the CTICONTROL

CTICONTROL can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0x000	CTICONTROL

This interface is accessible as follows:

- When SoftwareLockStatus() accesses to this register are **RO**.
- When !SoftwareLockStatus() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTIDEVAFF0, CTI Device Affinity register 0

The CTIDEVAFF0 characteristics are:

Purpose

Copy of the low half of the PE MPIDR_EL1 register that allows a debugger to determine which PE in a multiprocessor system the CTI component relates to.

If the CTI is CTIv1, this register is OPTIONAL. If the CTI is CTIv2, this register is mandatory.

Arm recommends that the CTI is CTIv2.

In an Armv8.5 compliant implementation the CTI must be CTIv2.

If this register is implemented, then CTIDEVAFF1 must also be implemented. If the CTI of a PE does not implement the CTI Device Affinity registers, the CTI block of the external debug memory map must be located 64KB above the debug registers in the external debug interface.

Configuration

CTIDEVAFF0 is in the Debug power domain.

Implementation of this register is OPTIONAL.

Attributes

CTIDEVAFF0 is a 32-bit register.

Field descriptions

The CTIDEVAFF0 bit assignments are:



MPIDR_EL1loMPIDR_EL1 low half, bits [31:0]

MPIDR_EL1 low half. Read-only copy of the low half of MPIDR_EL1, as seen from the highest implemented Exception level.

Accessing the CTIDEVAFF0

CTIDEVAFF0 can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0xFA8	CTIDEVAFF0

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTIDEVAFF1, CTI Device Affinity register 1

The CTIDEVAFF1 characteristics are:

Purpose

Copy of the high half of the PE MPIDR_EL1 register that allows a debugger to determine which PE in a multiprocessor system the CTI component relates to.

If the CTI is CTIv1, this register is OPTIONAL. If the CTI is CTIv2, this register is mandatory.

Arm recommends that the CTI is CTIv2.

In an Armv8.5 compliant implementation the CTI must be CTIv2.

If this register is implemented, then CTIDEVAFF0 must also be implemented. If the CTI of a PE does not implement the CTI Device Affinity registers, the CTI block of the external debug memory map must be located 64KB above the debug registers in the external debug interface.

Configuration

CTIDEVAFF1 is in the Debug power domain.

Implementation of this register is OPTIONAL.

Attributes

CTIDEVAFF1 is a 32-bit register.

Field descriptions

The CTIDEVAFF1 bit assignments are:



MPIDR_EL1hiMPIDR_EL1 high half, bits [31:0]

MPIDR_EL1 high half. Read-only copy of the high half of MPIDR_EL1, as seen from the highest implemented Exception level.

Accessing the CTIDEVAFF1

CTIDEVAFF1 can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0xFAC	CTIDEVAFF1

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTIDEVCTL, CTI Device Control register

The CTIDEVCTL characteristics are:

Purpose

Provides target-specific device controls

Configuration

CTIDEVCTL is in the Debug power domain. ~~Some or all RW fields of this register have defined reset values. These apply only on an External debug reset. The register is not affected by a Warm reset and is not affected by a Cold reset.~~

This register is present only when ARMv8.3-DoPD is implemented. Otherwise, direct accesses to CTIDEVCTL are RES0.

Attributes

CTIDEVCTL is a 32-bit register.

Field descriptions

The CTIDEVCTL bit assignments are:



Bits [31:2]

Reserved, RES0.

RCE, bit [1]

Reset Catch Enable.

RCE	Meaning
0b0	Reset Catch debug event disabled.
0b1	Reset Catch debug event enabled.

The following resets apply:

~~On a External debug reset, this field resets to 0.~~

- On a Cold reset, the value of this field is unchanged.
- On an External debug reset, this field resets to 0.
- On a Warm reset, the value of this field is unchanged.

OSUCE, bit [0]

OS Unlock Catch Enable

OSUCE	Meaning
0b0	OS Unlock Catch debug event disabled.
0b1	OS Unlock Catch debug event enabled.

The following resets apply:

~~On a External debug reset, this field resets to 0.~~

- On a Cold reset, the value of this field is unchanged.
- On an External debug reset, this field resets to 0.
- On a Warm reset, the value of this field is unchanged.

Accessing the CTIDEVCTL

CTIDEVCTL can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0x150	CTIDEVCTL

This interface is accessible as follows:

- When SoftwareLockStatus() accesses to this register are **RO**.
- When !SoftwareLockStatus() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTIGATE, CTI Channel Gate Enable register

The CTIGATE characteristics are:

Purpose

Determines whether events on channels propagate through the CTM to other ECT components, or from the CTM into the CTI.

Configuration

CTIGATE is in the Debug power domain.

~~CTIGATE is in the Debug power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on an External debug reset. The register is not affected by a Warm reset and is not affected by a Cold reset.~~

Attributes

CTIGATE is a 32-bit register.

Field descriptions

The CTIGATE bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
GATE<x>, bit [x]																															

GATE<x>, bit [x], for x = 0 to 31

Channel <x> gate enable.

Bits [31:N] are RAZ/WI. N is the number of ECT channels implemented as defined by the CTIDEVID.NUMCHAN field.

Possible values of this bit are:

GATE<x>	Meaning
0b0	Disable output and, if CTIDEVID.INOUT == 0b01, input channel <x> propagation.
0b1	Enable output and, if CTIDEVID.INOUT == 0b01, input channel <x> propagation.

If GATE[x] is set to 0, no new events will be propagated to the ECT, and if the ECT supports multicycle channel events any existing output channel events will be terminated.

On a External debug reset, this field resets to an architecturally UNKNOWN value.

Accessing the CTIGATE

CTIGATE can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0x140	CTIGATE

This interface is accessible as follows:

- When SoftwareLockStatus() accesses to this register are **RO**.

- When !SoftwareLockStatus() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTIINEN<n>, CTI Input Trigger to Output Channel Enable registers, n = 0 - 31

The CTIINEN<n> characteristics are:

Purpose

Enables the signaling of an event on output channels when input trigger event n is received by the CTI.

Configuration

CTIINEN<n> is in the Debug power domain.

~~CTIINEN<n> is in the Debug power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on an External debug reset. The register is not affected by a Warm reset and is not affected by a Cold reset.~~

If input trigger n is not connected, the behavior of CTIINEN<n> is IMPLEMENTATION DEFINED.

Attributes

CTIINEN<n> is a 32-bit register.

Field descriptions

The CTIINEN<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
INEN<x>, bit [x]																															

INEN<x>, bit [x], for x = 0 to 31

Input trigger <n> to output channel <x> enable.

Bits [31:N] are RAZ/WI. N is the number of ECT channels implemented as defined by the CTIDEVID.NUMCHAN field.

Possible values of this bit are:

INEN<x>	Meaning
0b0	Input trigger <n> will not generate an event on output channel <x>.
0b1	Input trigger <n> will generate an event on output channel <x>.

On a External debug reset, this field resets to an architecturally UNKNOWN value.

Accessing the CTIINEN<n>

CTIINEN<n> can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0x020 + 4n	CTIINEN<n>

This interface is accessible as follows:

- When SoftwareLockStatus() accesses to this register are **RO**.

- When !SoftwareLockStatus() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTIITCTRL, CTI Integration mode Control register

The CTIITCTRL characteristics are:

Purpose

Enables the CTI to switch from its default mode into integration mode, where test software can control directly the inputs and outputs of the PE, for integration testing or topology detection.

Configuration

It is IMPLEMENTATION DEFINED whether CTIITCTRL is implemented in the Core power domain or in the Debug power domain. ~~Some or all RW fields of this register have defined reset values, and:~~

- ~~The register is not affected by a Warm reset.~~
- ~~If the register is implemented in the Core power domain the reset values apply on a Cold reset, and the register is not affected by an External debug reset.~~
- ~~If the register is implemented in the Debug power domain the reset values apply on an External debug reset, and the register is not affected by a Cold reset.~~

Implementation of this register is OPTIONAL.

Some or all RW fields of this register have defined reset values, and:

- The register is not affected by a Warm reset.
- If the register is implemented in the Core power domain, the reset values apply on a Cold reset, and the register is not affected by an External debug reset.
- If the register is implemented in the Debug power domain, the reset values apply on an External debug reset, and the register is not affected by a Cold reset.

Attributes

CTIITCTRL is a 32-bit register.

Field descriptions

The CTIITCTRL bit assignments are:



Bits [31:1]

Reserved, RES0.

IME, bit [0]

Integration mode enable. When IME == 1, the device reverts to an integration mode to enable integration testing or topology detection. The integration mode behavior is IMPLEMENTATION DEFINED.

IME	Meaning
0b0	Normal operation.
0b1	Integration mode enabled.

On a Implementation reset, this field resets to 0.

Accessing the CTIITCTRL

CTIITCTRL can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0xF00	CTIITCTRL

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register are **IMPDEF**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTILSR, CTI Lock Status Register

The CTILSR characteristics are:

Purpose

Indicates the current status of the Software Lock for CTI registers.

The optional Software Lock provides a lock to prevent memory-mapped writes to the Cross-Trigger Interface registers. Use of this lock mechanism reduces the risk of accidental damage to the contents of the Cross-Trigger Interface registers. It does not, and cannot, prevent all accidental or malicious damage.

Configuration

CTILSR is in the Debug power domain. ~~Some or all RW fields of this register have defined reset values. These apply only on an External debug reset. The register is not affected by a Warm reset and is not affected by a Cold reset.~~

If ARMv8.4-Debug is implemented, the Software Lock is not implemented.

Software uses CTILAR to set or clear the lock, and CTILSR to check the current status of the lock.

Attributes

CTILSR is a 32-bit register.

Field descriptions

The CTILSR bit assignments are:



Bits [31:3]

Reserved, RES0.

nTT, bit [2]

Not thirty-two bit access required. RAZ.

SLK, bit [1]

When the Software Lock is implemented.:

Software Lock status for this component. For an access to LSR that is not a memory-mapped access, or when the Software Lock is not implemented, this field is RES0.

For memory-mapped accesses when the Software Lock is implemented, possible values of this field are:

SLK	Meaning
0b0	Lock clear. Writes are permitted to this component's registers.
0b1	Lock set. Writes to this component's registers are ignored, and reads have no side effects.

On a External debug reset, this field resets to 1.

Otherwise:

Reserved, RAZ.

SLI, bit [0]

Software Lock implemented. For an access to LSR that is not a memory-mapped access, this field is RAZ. For memory-mapped accesses, the value of this field is IMPLEMENTATION DEFINED. Permitted values are:

SLI	Meaning
0b0	Software Lock not implemented or not memory-mapped access.
0b1	Software Lock implemented and memory-mapped access.

Accessing the CTILSR

CTILSR can be accessed through a memory-mapped access to the external debug interface:

Component	Offset	Instance
CTI	0xFB4	CTILSR

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

CTIOUTEN<n>, CTI Input Channel to Output Trigger Enable registers, n = 0 - 31

The CTIOUTEN<n> characteristics are:

Purpose

Defines which input channels generate output trigger n.

Configuration

CTIOUTEN<n> is in the Debug power domain.

~~CTIOUTEN<n> is in the Debug power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on an External debug reset. The register is not affected by a Warm reset and is not affected by a Cold reset.~~

If output trigger n is not connected, the behavior of CTIOUTEN<n> is IMPLEMENTATION DEFINED.

Attributes

CTIOUTEN<n> is a 32-bit register.

Field descriptions

The CTIOUTEN<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
OUTEN<x>, bit [x]																															

OUTEN<x>, bit [x], for x = 0 to 31

Input channel <x> to output trigger <n> enable.

Bits [31:N] are RAZ/WI. N is the number of ECT channels implemented as defined by the CTIDEVID.NUMCHAN field.

Possible values of this bit are:

OUTEN<x>	Meaning
0b0	An event on input channel <x> will not cause output trigger <n> to be asserted.
0b1	An event on input channel <x> will cause output trigger <n> to be asserted.

On a External debug reset, this field resets to an architecturally UNKNOWN value.

Accessing the CTIOUTEN<n>

CTIOUTEN<n> can be accessed through the external debug interface:

Component	Offset	Instance
CTI	0x0A0 + 4n	CTIOUTEN<n>

This interface is accessible as follows:

- When SoftwareLockStatus() accesses to this register are **RO**.
- When !SoftwareLockStatus() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGAUTHSTATUS_EL1, Debug Authentication Status register

The DBGAUTHSTATUS_EL1 characteristics are:

Purpose

Provides information about the state of the IMPLEMENTATION DEFINED authentication interface for debug.

Configuration

External register DBGAUTHSTATUS_EL1 bits [31:0] are architecturally mapped to AArch64 System register DBGAUTHSTATUS_EL1[31:0] .

External register DBGAUTHSTATUS_EL1 bits [31:0] are architecturally mapped to AArch32 System register DBGAUTHSTATUS[31:0] .

~~It is IMPLEMENTATION DEFINED whether DBGAUTHSTATUS_EL1 is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

Attributes

DBGAUTHSTATUS_EL1 is a 32-bit register.

Field descriptions

The DBGAUTHSTATUS_EL1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								SNID		SID		NSNID		NSID	

Bits [31:8]

Reserved, RES0.

SNID, bits [7:6]

When ARMv8.4-Debug is implemented:

Secure non-invasive debug.

ExternalSecureNoninvasiveDebugEnabled() == ExternalSecureInvasiveDebugEnabled().

This field has the same value as DBGAUTHSTATUS_EL1.SID.

Otherwise:

Secure non-invasive debug.

SNID	Meaning
0b00	Not implemented. EL3 is not implemented and the Effective value of SCR_EL3.NS is 1.
0b10	Implemented and disabled. ExternalSecureNoninvasiveDebugEnabled() == FALSE.
0b11	Implemented and enabled. ExternalSecureNoninvasiveDebugEnabled() == TRUE.

All other values are reserved.

SID, bits [5:4]

Secure invasive debug.

SID	Meaning
0b00	Not implemented. EL3 is not implemented and the Effective value of SCR_EL3.NS is 1.
0b10	Implemented and disabled. ExternalSecureInvasiveDebugEnabled() == FALSE.
0b11	Implemented and enabled. ExternalSecureInvasiveDebugEnabled() == TRUE.

All other values are reserved.

NSNID, bits [3:2]

When ARMv8.4-Debug is implemented:

Non-secure non-invasive debug.

NSNID	Meaning
0b00	Not implemented. EL3 is not implemented and the Effective value of SCR_EL3.NS is 0.
0b11	Implemented and enabled. ExternalNoninvasiveDebugEnabled() == TRUE.

If the Effective value of SCR_EL3.NS is 1, or if EL3 is implemented and EL2 is not implemented, this field reads as 0b11.

All other values are reserved.

Otherwise:

Non-secure non-invasive debug.

NSNID	Meaning
0b00	Not implemented. EL3 is not implemented and the Effective value of SCR_EL3.NS is 0.
0b10	Implemented and disabled. ExternalNoninvasiveDebugEnabled() == FALSE.
0b11	Implemented and enabled. ExternalNoninvasiveDebugEnabled() == TRUE.

All other values are reserved.

NSID, bits [1:0]

Non-secure invasive debug.

NSID	Meaning
0b00	Not implemented. EL3 is not implemented and the Effective value of SCR_EL3.NS is 0.
0b10	Implemented and disabled. ExternalInvasiveDebugEnabled() == FALSE.
0b11	Implemented and enabled. ExternalInvasiveDebugEnabled() == TRUE.

All other values are reserved.

Accessing the DBGAUTHSTATUS_EL1

DBGAUTHSTATUS_EL1 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFB8	DBGAUTHSTATUS_EL1

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGBCR<n>_EL1, Debug Breakpoint Control Registers, n = 0 - 15

The DBGBCR<n>_EL1 characteristics are:

Purpose

Holds control information for a breakpoint. Forms breakpoint n together with value register DBGBVR<n>_EL1.

Configuration

External register DBGBCR<n>_EL1 bits [31:0] are architecturally mapped to AArch64 System register DBGBCR<n>_EL1[31:0] .

External register DBGBCR<n>_EL1 bits [31:0] are architecturally mapped to AArch32 System register DBGBCR<n>[31:0] .

DBGBCR<n>_EL1 is in the Core power domain.

~~DBGBCR<n>_EL1 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

If breakpoint n is not implemented then accesses to this register are:

- RES0 when IsCorePowered() && !DoubleLockStatus() && !OSLockStatus() && AllowExternalDebugAccess().
- A CONSTRAINED UNPREDICTABLE choice of RES0 or ERROR otherwise.

Attributes

DBGBCR<n>_EL1 is a 32-bit register.

Field descriptions

The DBGBCR<n>_EL1 bit assignments are:

31 30 29 28 27 26 25 24	23 22 21 20	19 18 17 16	15 14	13	12 11 10 9	8 7 6 5	4 3	2 1	0
RES0	BT	LBN	SSC	HMC	RES0	BAS	RES0	PMC	E

When the E field is zero, all the other fields in the register are ignored.

Bits [31:24]

Reserved, RES0.

BT, bits [23:20]

Breakpoint Type. Possible values are:

BT	Meaning
0b0000	Unlinked instruction address match. DBGBVR<n>_EL1 is the address of an instruction.
0b0001	As 0b0000 but linked to a Context matching breakpoint.
0b0010	Unlinked Context ID match. When ARMv8.1-VHE is implemented, EL2 is using AArch64, and the Effective value of HCR_EL2.E2H is 1, if either the PE is executing at EL0 with HCR_EL2.TGE set to 1 or the PE is executing at EL2, then DBGBVR<n>_EL1.ContextID must match the CONTEXTIDR_EL2 value. Otherwise, DBGBVR<n>_EL1.ContextID must match the CONTEXTIDR_EL1 value.
0b0011	As 0b0010, with linking enabled.
0b0100	Unlinked instruction address mismatch. DBGBVR<n>_EL1 is the address of an instruction to be stepped.
0b0101	As 0b0100, with linking enabled.
0b0110	Unlinked CONTEXTIDR_EL1 match. DBGBVR<n>_EL1.ContextID is a Context ID compared against CONTEXTIDR_EL1.
0b0111	As 0b0110, with linking enabled.
0b1000	Unlinked VMID match. DBGBVR<n>_EL1.VMID is a VMID compared against VTTBR_EL2.VMID.
0b1001	As 0b1000, with linking enabled.
0b1010	Unlinked VMID and Context ID match. DBGBVR<n>_EL1.ContextID is a Context ID compared against CONTEXTIDR_EL1, and DBGBVR<n>_EL1.VMID is a VMID compared against VTTBR_EL2.VMID.
0b1011	As 0b1010, with linking enabled.
0b1100	Unlinked CONTEXTIDR_EL2 match. DBGBVR<n>_EL1.ContextID2 is a Context ID compared against CONTEXTIDR_EL2.
0b1101	As 0b1100, with linking enabled.
0b1110	Unlinked Full Context ID match. DBGBVR<n>_EL1.ContextID is compared against CONTEXTIDR_EL1, and DBGBVR<n>_EL1.ContextID2 is compared against CONTEXTIDR_EL2.
0b1111	As 0b1110, with linking enabled.

Constraints on breakpoint programming mean some values are reserved under certain conditions.

For more information on the operation of the SSC, HMC, and PMC fields, and on the effect of programming this field to a reserved value, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug) and 'Reserved DBGBCR<n>_EL1.BT values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

On a Cold reset, this field resets to an architecturally UNKNOWN value.

LBN, bits [19:16]

Linked breakpoint number. For Linked address matching breakpoints, this specifies the index of the Context-matching breakpoint linked to.

For all other breakpoint types this field is ignored and reads of the register return an UNKNOWN value.

This field is ignored when the value of DBGBCR<n>_EL1.E is 0.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

SSC, bits [15:14]

Security state control. Determines the Security states under which a Breakpoint debug event for breakpoint n is generated. This field must be interpreted along with the HMC and PMC fields, and there are constraints on the permitted values of the {HMC, SSC, PMC} fields. For more information, including the effect of programming the fields to a reserved set of values, see 'Reserved DBGBCR<n>_EL1.{SSC, HMC, PMC} values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

For more information on the operation of the SSC, HMC, and PMC fields, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

On a Cold reset, this field resets to an architecturally UNKNOWN value.

HMC, bit [13]

Higher mode control. Determines the debug perspective for deciding when a Breakpoint debug event for breakpoint n is generated. This field must be interpreted along with the SSC and PMC fields, and there are constraints on the permitted values of the {HMC, SSC, PMC} fields. For more information see DBGBCR<n>_EL1.SSC description.

For more information on the operation of the SSC, HMC, and PMC fields, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [12:9]

Reserved, RES0.

BAS, bits [8:5]

When AArch32 is supported at any Exception level:

Byte address select. Defines which half-words an address-matching breakpoint matches, regardless of the instruction set and Execution state.

~~Byte address select. Defines which half-words an address-matching breakpoint matches, regardless of the instruction set and Execution state. In an AArch64 only implementation, this field is reserved, RES1.~~

The permitted values depend on the breakpoint type.

For Address match breakpoints in either AArch32 or AArch64 state, the permitted values are:

BAS	Match instruction at	Constraint for debuggers
0b0011	DBGBVR<n>_EL1	Use for T32 instructions
0b1100	DBGBVR<n>_EL1 + 2	Use for T32 instructions
0b1111	DBGBVR<n>_EL1	Use for A64 and A32 instructions

All other values are reserved.

For more information, see 'Using the BAS field in Address Match breakpoints' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

For Address mismatch breakpoints in an AArch32 stage 1 translation regime, the permitted values are:

BAS	Match instruction at	Constraint for debuggers
0b0000	-	Use for a match anywhere breakpoint
0b0011	DBGBVR<n>_EL1	Use for stepping T32 instructions
0b1100	DBGBVR<n>_EL1 + 2	Use for stepping T32 instructions
0b1111	DBGBVR<n>_EL1	Use for stepping A64 and A32 instructions

For more information, see 'Using the BAS field in Address Match breakpoints' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

For Context matching breakpoints, this field is RES1 and ignored.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES1.

Bits [4:3]

Reserved, RES0.

PMC, bits [2:1]

Privilege mode control. Determines the Exception level or levels at which a Breakpoint debug event for breakpoint n is generated. This field must be interpreted along with the SSC and HMC fields, and there are constraints on the permitted values of the {HMC, SSC, PMC} fields. For more information see the DBGBCR<n>_EL1.SSC description.

For more information on the operation of the SSC, HMC, and PMC fields, see 'Execution conditions for which a breakpoint generates Breakpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

On a Cold reset, this field resets to an architecturally UNKNOWN value.

E, bit [0]

Enable breakpoint DBGBVR<n>_EL1. Possible values are:

E	Meaning
0b0	Breakpoint disabled.
0b1	Breakpoint enabled.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the DBGBCR<n>_EL1

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalDebugAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

DBGBCR<n>_EL1 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x408 + 16n	DBGBCR<n>_EL1

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalDebugAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalDebugAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGBVR<n>_EL1, Debug Breakpoint Value Registers, n = 0 - 15

The DBGBVR<n>_EL1 characteristics are:

Purpose

Holds a virtual address, or a VMID and/or a context ID, for use in breakpoint matching. Forms breakpoint n together with control register DBGBCR<n>_EL1.

Configuration

External register DBGBVR<n>_EL1 bits [63:0] are architecturally mapped to AArch64 System register DBGBVR<n>_EL1[63:0] .

External register DBGBVR<n>_EL1 bits [31:0] are architecturally mapped to AArch32 System register DBGBVR<n>[31:0] .

External register DBGBVR<n>_EL1 bits [63:32] are architecturally mapped to AArch32 System register DBGBXVR<n>[31:0] .

DBGBVR<n>_EL1 is in the Core power domain.

~~DBGBVR<n>_EL1 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

If breakpoint n is not implemented then accesses to this register are:

- RES0 when IsCorePowered() && !DoubleLockStatus() && !OSLockStatus() && AllowExternalDebugAccess().
- A CONSTRAINED UNPREDICTABLE choice of RES0 or ERROR otherwise.

Attributes

How this register is interpreted depends on the value of DBGBCR<n>_EL1.BT.

- When DBGBCR<n>_EL1.BT is 0b0x0x, this register holds a virtual address.
- When DBGBCR<n>_EL1.BT is 0b001x, 0b011x, or 0b110x, this register holds a Context ID.
- When DBGBCR<n>_EL1.BT is 0b100x, this register holds a VMID.
- When DBGBCR<n>_EL1.BT is 0b101x, this register holds a VMID and a Context ID.
- When DBGBCR<n>_EL1.BT is 0b111x, this register holds two Context ID values.

For other values of DBGBCR<n>_EL1.BT, this register is RES0.

Field descriptions

The DBGBVR<n>_EL1 bit assignments are:

When DBGBCR<n>_EL1.BT == 0b0x0x:



RESS[14:4], bits [63:53]

Reserved, Sign extended. Software must treat this field as RES0 if the most significant bit of VA is 0 or RES0, and as RES1 if the most significant bit of VA is 1.

Hardware always ignores the value of these bits and it is IMPLEMENTATION DEFINED whether:

- The bits are hardwired to a copy of the most significant bit of VA, meaning writes to these bits are ignored, and reads to the bits always return the hardwired value.
- The value in those bits can be written, and reads will return the last value written. The value held in those bits is ignored by hardware.

VA[52:49], bits [52:49]

When ARMv8.2-LVA is implemented:

Extension to VA[48:2]. See VA[48:2] for more details.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Extension to RESS[14:4]. See RESS[14:4] for more details.

VA[48:2], bits [48:2]

If the address is being matched in an AArch64 stage 1 translation regime:

- This field contains bits[48:2] of the address for comparison.
- When ARMv8.2-LVA is implemented, VA[52:49] forms the upper part of the address value. Otherwise, VA[52:49] are RESS.

If the address is being matched in an AArch32 stage 1 translation regime, the first 20 bits of this field are RES0, and the rest of the field contains bits[31:2] of the address for comparison.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [1:0]

Reserved, RES0.

When DBGBCR<n>_EL1.BT == 0b001x:



Bits [63:32]

Reserved, RES0.

ContextID, bits [31:0]

Context ID value for comparison.

The value is compared against CONTEXTIDR_EL2 when ARMv8.1-VHE is implemented, EL2 is using AArch64, HCR_EL2.E2H is 1, and either:

- The PE is executing at EL2.
- HCR_EL2.TGE is 1, the PE is executing at EL0, and EL2 is enabled in the current Security state.

Otherwise, the value is compared against the following:~~CONTEXTIDR when the PE is executing at AArch32, or CONTEXTIDR_EL1 when the PE is executing at AArch64.~~

- CONTEXTIDR when the PE is executing at AArch32
- CONTEXTIDR_EL1 when the PE is executing at AArch64.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

When DBGBCR<n>_EL1.BT == 0b011x, EL2 is implemented and (ARMv8.1-VHE is implemented or ARMv8.2-Debug is implemented)::

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
ContextID																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

ContextID, bits [31:0]

~~When ARMv8.1-VHE is implemented:~~

Context ID value for comparison against CONTEXTIDR_EL1.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

~~Otherwise:~~

~~Reserved, RES0.~~

When DBGBCR<n>_EL1.BT == 0b100x and ~~HaveEL(~~EL2 is implemented:~~)~~:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																VMID[15:8]								VMID[7:0]							
RES0																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:48]

Reserved, RES0.

VMID[15:8], bits [47:40]

When ARMv8.1-VHE is implemented and VTCR_EL2.VS == 1:

Extension to VMID[7:0]. See DBGBVR<n>_EL1.VMID~~VMID~~[7:0] for more details.

If EL2 is using AArch32, this field is RES0.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

VMID[7:0], bits [39:32]

VMID value for comparison.

The VMID is 8 bits when~~in~~ any of the following are true:~~cases.~~

- EL2 is using AArch32.
- VTCR_EL2.VS is 0.
- ARMv8.1-VMID16 is not implemented.

~~When ARMv8.1-VMID16 is implemented and EL2 is using AArch64, it is IMPLEMENTATION DEFINED whether the VMID is 8 bits or 16 bits.~~

~~VMID[15:8] is RES0 if any of the following applies:~~

- ~~The implementation has an 8-bit VMID.~~
- ~~VTCR_EL2.VS has a value of 0.~~
- ~~EL2 is using AArch32.~~

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [31:0]

Reserved, RES0.

When DBGBCR<n>_EL1.BT == 0b101x and ~~HaveEL(~~EL2 is implemented~~):~~



Bits [63:48]

Reserved, RES0.

VMID[15:8], bits [47:40]

When ARMv8.1-VMID16 is implemented and VTCR_EL2.VS == 1:

Extension to VMID[7:0]. See DBGBVR<n>_EL1.VMID~~VMID~~[7:0] for more details.

If EL2 is using AArch32, or if the implementation has an 8-bit VMID, this field is RES0.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

VMID[7:0], bits [39:32]

VMID value for comparison.

The VMID is 8 bits when~~in~~ any of the following are true:~~cases.~~

- EL2 is using AArch32.
- VTCR_EL2.VS is 0.
- ARMv8.1-VMID16 is not implemented.

~~When ARMv8.1-VMID16 is implemented and EL2 is using AArch64, it is IMPLEMENTATION DEFINED whether the VMID is 8 bits or 16 bits.~~

~~VMID[15:8] is RES0 if any of the following applies:~~

- The implementation has an 8-bit VMID.
- VTCR_EL2.VS has a value of 0.
- EL2 is using AArch32.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

ContextID, bits [31:0]

Context ID value for comparison against CONTEXTIDR_EL1.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

When DBGBCR<n>_EL1.BT == 0b110x, EL2 is implemented and HaveEL(ARMv8.1-VHE is implemented or ARMv8.2-Debug is implementedEL2):

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ContextID2																															
RES0																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

ContextID2, bits [63:32]

When ARMv8.1-VHE is implemented:

Context ID value for comparison against CONTEXTIDR_EL2.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [31:0]

Reserved, RES0.

When DBGBCR<n>_EL1.BT == 0b111x, EL2 is implemented and HaveEL(ARMv8.1-VHE is implemented or ARMv8.2-Debug is implementedEL2):

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
ContextID2																															
ContextID																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

ContextID2, bits [63:32]

When ARMv8.1-VHE is implemented:

Context ID value for comparison against CONTEXTIDR_EL2.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Reserved, RES0.

~~ContextID, bits [31:0]~~

~~When ARMv8.1-VHE is implemented:~~

~~Otherwise:~~
ContextID, bits [31:0]

Context ID value for comparison against CONTEXTIDR_EL1.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

~~Otherwise:~~

~~Reserved, RES0.~~

Accessing the DBGBVR<n>_EL1

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalDebugAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

DBGBVR<n>_EL1 can be accessed through the external debug interface:

Component	Offset	Instance	Range
Debug	0x400 + 16n	DBGBVR<n>_EL1	63:0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalDebugAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalDebugAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGCLAIMCLR_EL1, Debug CLAIM Tag Clear register

The DBGCLAIMCLR_EL1 characteristics are:

Purpose

Used by software to read the values of the CLAIM tag bits, and to clear CLAIM tag bits to 0.

The architecture does not define any functionality for the CLAIM tag bits.

Note

CLAIM tags are typically used for communication between the debugger and target software.

Used in conjunction with the DBGCLAIMSET_EL1 register.

Configuration

External register DBGCLAIMCLR_EL1 bits [31:0] are architecturally mapped to AArch64 System register DBGCLAIMCLR_EL1[31:0] .

External register DBGCLAIMCLR_EL1 bits [31:0] are architecturally mapped to AArch32 System register DBGCLAIMCLR[31:0] .

DBGCLAIMCLR_EL1 is in the Core power domain. ~~Some or all RW fields of this register have defined reset values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

An implementation must include eight CLAIM tag bits.

Attributes

DBGCLAIMCLR_EL1 is a 32-bit register.

Field descriptions

The DBGCLAIMCLR_EL1 bit assignments are:



Bits [31:8]

Reserved, RAZ/SBZ. Software can rely on these bits reading as zero, and must use a should-be-zero policy on writes. Implementations must ignore writes.

CLAIM, bits [7:0]

Read or clear CLAIM tag bits. Reading this field returns the current value of the CLAIM tag bits.

Writing a 1 to one of these bits clears the corresponding CLAIM tag bit to 0. This is an indirect write to the CLAIM tag bits. A single write operation can clear multiple CLAIM tag bits to 0.

Writing 0 to one of these bits has no effect.

On a Cold reset, this field resets to `0`.

Accessing the DBGCLAIMCLR_EL1

DBGCLAIMCLR_EL1 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	`0xFA4`	DBGCLAIMCLR_EL1

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDTRRX_EL0, Debug Data Transfer Register, Receive

The DBGDTRRX_EL0 characteristics are:

Purpose

Transfers data from an external debugger to the PE. For example, it is used by a debugger transferring commands and data to a debug target. See DBGDTR_EL0 for additional architectural mappings. It is a component of the Debug Communications Channel.

Configuration

External register DBGDTRRX_EL0 bits [31:0] are architecturally mapped to AArch64 System register DBGDTRRX_EL0[31:0] .

External register DBGDTRRX_EL0 bits [31:0] are architecturally mapped to AArch32 System register DBGDTRRXint[31:0] .

DBGDTRRX_EL0 is in the Core power domain.

~~DBGDTRRX_EL0 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

Attributes

DBGDTRRX_EL0 is a 32-bit register.

Field descriptions

The DBGDTRRX_EL0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Update DTRRX																															

Bits [31:0]

Update DTRRX.

Writes to this register:

- If RXfull is set to 1, set DTRRX to UNKNOWN.
- If RXfull is set to 0, update the value in DTRRX.

After the write, RXfull is set to 1.

Reads of this register:

- If RXfull is set to 1, return the last value written to DTRRX.
- If RXfull is set to 0, return an UNKNOWN value.

After the read, RXfull remains unchanged.

For the full behavior of the Debug Communications Channel, see The Debug Communication Channel and Instruction Transfer Register4.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the DBGDTRRX_EL0

If EDSCR.ITE == 0 when the PE exits Debug state on receiving a Restart request trigger event, the behavior of any operation issued by a DTR access in memory access mode that has not completed execution is CONSTRAINED UNPREDICTABLE, and must do one of the following:

- It must complete execution in Debug state before the PE executes the restart sequence.
- It must complete execution in Non-debug state before the PE executes the restart sequence.
- It must be abandoned. This means that the instruction does not execute. Any registers or memory accessed by the instruction are left in an UNKNOWN state.

DBGDTRRX_EL0 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x080	DBGDTRRX_EL0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGDTRTX_EL0, Debug Data Transfer Register, Transmit

The DBGDTRTX_EL0 characteristics are:

Purpose

Transfers data from the PE to an external debugger. For example, it is used by a debug target to transfer data to the debugger. See DBGDTR_EL0 for additional architectural mappings. It is a component of the Debug Communication Channel.

Configuration

External register DBGDTRTX_EL0 bits [31:0] are architecturally mapped to AArch64 System register DBGDTRTX_EL0[31:0] .

External register DBGDTRTX_EL0 bits [31:0] are architecturally mapped to AArch32 System register DBGDTRTXint[31:0] .

DBGDTRTX_EL0 is in the Core power domain.

~~DBGDTRTX_EL0 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

Attributes

DBGDTRTX_EL0 is a 32-bit register.

Field descriptions

The DBGDTRTX_EL0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Return DTRTX																															

Bits [31:0]

Return DTRTX.

Reads of this register:

- If TXfull is set to 1, return the last value written to DTRTX.
- If TXfull is set to 0, return an UNKNOWN value.

After the read, TXfull is cleared to 0.

Writes to this register:

- If TXfull is set to 1, set DTRTX to UNKNOWN.
- If TXfull is set to 0, update the value in DTRTX.

After the write, TXfull remains unchanged.

For the full behavior of the Debug Communications Channel, see The Debug Communication Channel and Instruction Transfer Register.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the DBGDTRTX_EL0

If EDSCR.ITE == 0 when the PE exits Debug state on receiving a Restart request trigger event, the behavior of any operation issued by a DTR access in memory access mode that has not completed execution is CONSTRAINED UNPREDICTABLE, and must do one of the following:

- It must complete execution in Debug state before the PE executes the restart sequence.
- It must complete execution in Non-debug state before the PE executes the restart sequence.
- It must be abandoned. This means that the instruction does not execute. Any registers or memory accessed by the instruction are left in an UNKNOWN state.

DBGDTRTX_EL0 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x08C	DBGDTRTX_EL0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGWCR<n>_EL1, Debug Watchpoint Control Registers, n = 0 - 15

The DBGWCR<n>_EL1 characteristics are:

Purpose

Holds control information for a watchpoint. Forms watchpoint n together with value register DBGWVR<n>_EL1.

Configuration

External register DBGWCR<n>_EL1 bits [31:0] are architecturally mapped to AArch64 System register DBGWCR<n>_EL1[31:0] .

External register DBGWCR<n>_EL1 bits [31:0] are architecturally mapped to AArch32 System register DBGWCR<n>[31:0] .

DBGWCR<n>_EL1 is in the Core power domain.

~~DBGWCR<n>_EL1 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

If watchpoint n is not implemented then accesses to this register are:

- When IsCorePowered() && !DoubleLockStatus() && !OSLockStatus() && AllowExternalDebugAccess(), RES0.
- Otherwise, a CONSTRAINED UNPREDICTABLE choice of RES0 or ERROR.

Attributes

DBGWCR<n>_EL1 is a 32-bit register.

Field descriptions

The DBGWCR<n>_EL1 bit assignments are:



When the E field is zero, all the other fields in the register are ignored.

Bits [31:29]

Reserved, RES0.

MASK, bits [28:24]

Address mask. Only objects up to 2GB can be watched using a single mask.

MASK	Meaning
0b00000	No mask.
0b00001	Reserved.
0b00010	Reserved.

If programmed with a reserved value, a watchpoint must behave as if either:

- MASK has been programmed with a defined value, which might be 0 (no mask), other than for a direct read of DBGWCRn_EL1.
- The watchpoint is disabled.

Software must not rely on this property because the behavior of reserved values might change in a future revision of the architecture.

Other values mask the corresponding number of address bits, from `0b00011` masking 3 address bits (`0x00000007` mask for address) to `0b11111` masking 31 address bits (`0x7FFFFFFF` mask for address).

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [23:21]

Reserved, RES0.

WT, bit [20]

Watchpoint type. Possible values are:

WT	Meaning
`0b0`	Unlinked data address match.
`0b1`	Linked data address match.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

LBN, bits [19:16]

Linked breakpoint number. For Linked data address watchpoints, this specifies the index of the Context-matching breakpoint linked to.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

SSC, bits [15:14]

Security state control. Determines the Security states under which a Watchpoint debug event for watchpoint n is generated. This field must be interpreted along with the HMC and PAC fields.

For more information on the operation of the SSC, HMC, and PAC fields, see 'Execution conditions for which a watchpoint generates Watchpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

On a Cold reset, this field resets to an architecturally UNKNOWN value.

HMC, bit [13]

Higher mode control. Determines the debug perspective for deciding when a Watchpoint debug event for watchpoint n is generated. This field must be interpreted along with the SSC and PAC fields.

For more information on the operation of the SSC, HMC, and PAC fields, see 'Execution conditions for which a watchpoint generates Watchpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

On a Cold reset, this field resets to an architecturally UNKNOWN value.

BAS, bits [12:5]

Byte address select. Each bit of this field selects whether a byte from within the word or double-word addressed by DBGWVR<n>_EL1 is being watched.

BAS	Description
xxxxxxx1	Match byte at DBGWVR<n>_EL1
xxxxxx1x	Match byte at DBGWVR<n>_EL1 + 1
xxxxx1xx	Match byte at DBGWVR<n>_EL1 + 2
xxxx1xxx	Match byte at DBGWVR<n>_EL1 + 3

In cases where DBGWVR<n>_EL1 addresses a double-word:

BAS	Description, if DBGWVR<n>_EL1[2] == 0
xxx1xxxx	Match byte at DBGWVR<n>_EL1 + 4
xx1xxxxx	Match byte at DBGWVR<n>_EL1 + 5
x1xxxxxx	Match byte at DBGWVR<n>_EL1 + 6
1xxxxxxx	Match byte at DBGWVR<n>_EL1 + 7

If DBGWVR<n>_EL1[2] == 1, only BAS[3:0] is used. Arm deprecates setting DBGWVR<n>_EL1[2] == 1.

The valid values for BAS are non-zero binary number all of whose set bits are contiguous. All other values are reserved and must not be used by software. See 'Reserved DBGWCR<n>.BAS values' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section G2 (AArch32 Self-hosted Debug).

On a Cold reset, this field resets to an architecturally UNKNOWN value.

LSC, bits [4:3]

Load/store control. This field enables watchpoint matching on the type of access being made. Possible values of this field are:

LSC	Meaning
0b01	Match instructions that load from a watchpointed address.
0b10	Match instructions that store to a watchpointed address.
0b11	Match instructions that load from or store to a watchpointed address.

All other values are reserved, but must behave as if the watchpoint is disabled. Software must not rely on this property as the behavior of reserved values might change in a future revision of the architecture.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

PAC, bits [2:1]

Privilege of access control. Determines the Exception level or levels at which a Watchpoint debug event for watchpoint n is generated. This field must be interpreted along with the SSC and HMC fields.

For more information on the operation of the SSC, HMC, and PAC fields, see 'Execution conditions for which a watchpoint generates Watchpoint exceptions' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug).

On a Cold reset, this field resets to an architecturally UNKNOWN value.

E, bit [0]

Enable watchpoint n. Possible values are:

E	Meaning
0b0	Watchpoint disabled.
0b1	Watchpoint enabled.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the DBGWCR<n>_EL1

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalDebugAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

DBGWCR<n>_EL1 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x808 + 16n	DBGWCR<n>_EL1

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalDebugAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalDebugAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

DBGWVR<n>_EL1, Debug Watchpoint Value Registers, n = 0 - 15

The DBGWVR<n>_EL1 characteristics are:

Purpose

Holds a data address value for use in watchpoint matching. Forms watchpoint n together with control register DBGWCR<n>_EL1.

Configuration

External register DBGWVR<n>_EL1 bits [63:0] are architecturally mapped to AArch64 System register DBGWVR<n>_EL1[63:0] .

External register DBGWVR<n>_EL1 bits [31:0] are architecturally mapped to AArch32 System register DBGWVR<n>[31:0] .

DBGWVR<n>_EL1 is in the Core power domain.

~~DBGWVR<n>_EL1 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

If watchpoint n is not implemented then accesses to this register are:

- When IsCorePowered() && !DoubleLockStatus() && !OSLockStatus() && AllowExternalDebugAccess(), RES0.
- Otherwise, a CONSTRAINED UNPREDICTABLE choice of RES0 or ERROR.

Attributes

DBGWVR<n>_EL1 is a 64-bit register.

Field descriptions

The DBGWVR<n>_EL1 bit assignments are:



RESS[14:4], bits [63:53]

Reserved, Sign extended. Hardware and software must treat this field as RES0 if the most significant bit of VA is 0 or RES0, and as RES1 if the most significant bit of VA is 1.

Hardware always ignores the value of these bits and it is IMPLEMENTATION DEFINED whether:

- The bits are hardwired to a copy of the most significant bit of VA, meaning writes to these bits are ignored, and reads to the bits always return the hardwired value.
- The value in those bits can be written, and reads will return the last value written. The value held in those bits is ignored by hardware.

VA[52:49], bits [52:49]

When ARMv8.2-LVA is implemented:

Extension to VA[48:2]. See VA[48:2] for more details.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Extension to RESS[14:4]. See RESS[14:4] for more details.

VA[48:2], bits [48:2]

Bits[48:2] of the address value for comparison.

When ARMv8.2-LVA is implemented, VA[52:49] forms the upper part of the address value. Otherwise, VA[52:49] are RESS.

Arm deprecates setting DBGWVR<n>_EL1[2] == 1.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [1:0]

Reserved, RES0.

Accessing the DBGWVR<n>_EL1

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalDebugAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

DBGWVR<n>_EL1 can be accessed through the external debug interface:

Component	Offset	Instance	Range
Debug	0x800 + 16n	DBGWVR<n>_EL1	63:0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalDebugAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalDebugAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDAA32PFR, External Debug AArch32 Processor Feature Register

The EDAA32PFR characteristics are:

Purpose

Provides information about implemented PE features.

For general information about the interpretation of the ID registers see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.4.1.

Configuration

It is IMPLEMENTATION DEFINED whether EDAA32PFR is implemented in the Core power domain or in the Debug power domain.

This register is present only when AArch32~~the~~ is~~implementation~~ supported~~only~~ at~~supports~~ any~~execution~~ Exception~~in~~ level.~~AArch32 state.~~ Otherwise, direct accesses to EDAA32PFR are RES0.

Attributes

EDAA32PFR is a 64-bit register.

Field descriptions

The EDAA32PFR bit assignments are:



Bits [63:16]

Reserved, RES0.

EL3, bits [15:12]

AArch32 EL3 Exception level handling. Defined values are:

EL3	Meaning
0b0000	EL3 is not implemented or can be executed in AArch64 state.
0b0001	EL3 can be executed in AArch32 state only.

When the value of EDPFR.EL3 is non-zero, this field must be 0b0000.

All other values are reserved.

Note

EDPFR.{EL1, EL0} indicate whether EL1 and EL0 can only be executed in AArch32 state.

EL2, bits [11:8]

AArch32 EL2 Exception level handling. Defined values are:

EL2	Meaning
0b0000	EL2 is not implemented or can be executed in AArch64 state.
0b0001	EL2 can be executed in AArch32 state only.

When the value of EDPFR.EL2 is non-zero, this field must be 0b0000.

All other values are reserved.

Note

EDPFR.{EL1, EL0} indicate whether EL1 and EL0 can only be executed in AArch32 state.

PMSA, bits [7:4]

Indicates support for a PMSA. Defined values are:

PMSA	Meaning
0b0000	PMSA not supported.
0b0100	Support for an Armv8-R PMSAv8-32.

All other values are reserved. In Armv8-A, the only permitted value is 0b0000.

VMSA, bits [3:0]

Indicates support for a VMSA. When the PMSA field is nonzero, determines support for a VMSA. When the PMSA field is 0b0000, VMSA is supported. Defined values are:

VMSA	Meaning
0b0000	VMSA not supported.

All other values are reserved. In Armv8-A, the only permitted value is 0b0000.

Accessing the EDAA32PFR

EDAA32PFR can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xD60	EDAA32PFR

This interface is accessible as follows:

- When IsCorePowered() and !DoubleLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register are **IMPDEF**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDACR, External Debug Auxiliary Control Register

The EDACR characteristics are:

Purpose

Allows implementations to support IMPLEMENTATION DEFINED controls.

Configuration

It is IMPLEMENTATION DEFINED whether EDACR is implemented in the Core power domain or in the Debug power domain.

~~It is IMPLEMENTATION DEFINED whether EDACR is implemented in the Core power domain or in the Debug power domain. RW fields in this register reset to architecturally UNKNOWN values, and:~~

- ~~The register is not affected by a Warm reset.~~
- ~~If the register is implemented in the Core power domain the reset values apply on a Cold reset, and the register is not affected by an External debug reset.~~
- ~~If the register is implemented in the Debug power domain the reset values apply on an External debug reset, and the register is not affected by a Cold reset.~~

Changing this register from its reset value causes IMPLEMENTATION DEFINED behavior, including possible deviation from the architecturally-defined behavior.

If the EDACR contains any control bits that must be preserved over power down, then these bits must be accessible by the external debug interface when the OS Lock is locked, OSLSR_EL1.OSLK == 1, and when the Core is powered off.

Attributes

EDACR is a 32-bit register.

Field descriptions

The EDACR bit assignments are:



IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

Accessing the EDACR

EDACR can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x094	EDACR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and SoftwareLockStatus() accesses to this register are **RO**.

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register are **IMPDEF**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDCIDR0, External Debug Component Identification Register 0

The EDCIDR0 characteristics are:

Purpose

Provides information to identify an external debug component.

For more information see 'About the Component identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether EDCIDR0 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

EDCIDR0 is a 32-bit register.

Field descriptions

The EDCIDR0 bit assignments are:



Bits [31:8]

Reserved, RES0.

PRMBL_0, bits [7:0]

Preamble.

~~Preamble. Must read as 0x0D.~~

Reads as 0x0D.

Accessing the EDCIDR0

EDCIDR0 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFF0	EDCIDR0

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDCIDR1, External Debug Component Identification Register 1

The EDCIDR1 characteristics are:

Purpose

Provides information to identify an external debug component.

For more information see 'About the Component identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether EDCIDR1 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

EDCIDR1 is a 32-bit register.

Field descriptions

The EDCIDR1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								CLASS				PRMBL_1			

Bits [31:8]

Reserved, RES0.

CLASS, bits [7:4]

Component class. Debug component.

~~Component class. Reads as 0x9, debug component.~~

Reads as 0b1001.

PRMBL_1, bits [3:0]

Preamble. ~~RAZ.~~

Reads as 0b0000.

Accessing the EDCIDR1

EDCIDR1 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFF4	EDCIDR1

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDCIDR2, External Debug Component Identification Register 2

The EDCIDR2 characteristics are:

Purpose

Provides information to identify an external debug component.

For more information see 'About the Component identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether EDCIDR2 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

EDCIDR2 is a 32-bit register.

Field descriptions

The EDCIDR2 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								PRMBL_2							

Bits [31:8]

Reserved, RES0.

PRMBL_2, bits [7:0]

Preamble.

~~Preamble. Must read as 0x05.~~

Reads as 0x05.

Accessing the EDCIDR2

EDCIDR2 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFF8	EDCIDR2

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDCIDR3, External Debug Component Identification Register 3

The EDCIDR3 characteristics are:

Purpose

Provides information to identify an external debug component.

For more information see 'About the Component identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether EDCIDR3 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

EDCIDR3 is a 32-bit register.

Field descriptions

The EDCIDR3 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								PRMBL_3							

Bits [31:8]

Reserved, RES0.

PRMBL_3, bits [7:0]

Preamble.

~~Preamble. Must read as 0xB1.~~

Reads as 0xB1.

Accessing the EDCIDR3

EDCIDR3 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFFC	EDCIDR3

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDCIDSR, External Debug Context ID Sample Register

The EDCIDSR characteristics are:

Purpose

Contains the sampled value of the Context ID, captured on reading EDPCSR[31:0].

Configuration

EDCIDSR is in the Core power domain.

~~EDCIDSR is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

This register is present only when ARMv8.0-PCSample is implemented and ARMv8.2-PCSample is not implemented. Otherwise, direct accesses to EDCIDSR are RES0.

Implemented only if the OPTIONAL PC Sample-based Profiling Extension is implemented in the external debug registers space.

Note

ARMv8.2-PCSample implements the PC Sample-based Profiling Extension in the Performance Monitors registers space.

Attributes

EDCIDSR is a 32-bit register.

Field descriptions

The EDCIDSR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
CONTEXTIDR																															

CONTEXTIDR, bits [31:0]

Context ID. The value of CONTEXTIDR that is associated with the most recent EDPCSR sample. When the most recent EDPCSR sample was generated:

- If EL1 is using AArch64, then the Context ID is sampled from CONTEXTIDR_EL1.
- If EL1 is using AArch32, then the Context ID is sampled from CONTEXTIDR. ~~If EL3 is implemented and is using AArch32, then CONTEXTIDR is a banked register, and EDCIDSR samples the current banked copy of CONTEXTIDR for the Security state that is associated with the most recent EDPCSR sample.~~
- If EL3 is implemented and is using AArch32, then CONTEXTIDR is a banked register, and EDCIDSR samples the current banked copy of CONTEXTIDR for the Security state that is associated with the most recent EDPCSR sample.

Because the value written to EDCIDSR is an indirect read of CONTEXTIDR, it is CONSTRAINED UNPREDICTABLE whether EDCIDSR is set to the original or new value if EDPCSR samples:

- An instruction that writes to CONTEXTIDR.
- The next Context synchronization event.
- Any instruction executed between these two instructions.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the EDCIDSR

IMPLEMENTATION DEFINED extensions to external debug might make the value of this register UNKNOWN, see 'Permitted behavior that might make the PC Sample-based profiling registers UNKNOWN' in chapter H7.

EDCIDSR can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x0A4	EDCIDSR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDDEVAFF0, External Debug Device Affinity register 0

The EDDEVAFF0 characteristics are:

Purpose

Copy of the low half of the PE MPIDR_EL1 register that allows a debugger to determine which PE in a multiprocessor system the external debug component relates to.

Configuration

~~It is IMPLEMENTATION DEFINED whether EDDEVAFF0 is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

Attributes

EDDEVAFF0 is a 32-bit register.

Field descriptions

The EDDEVAFF0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
MPIDR_EL1lo~~MPIDR_EL1 low half~~																															

MPIDR_EL1lo~~MPIDR_EL1 low half~~, bits [31:0]

MPIDR_EL1 low half. Read-only copy of the low half of MPIDR_EL1, as seen from the highest implemented Exception level.

Accessing the EDDEVAFF0

EDDEVAFF0 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFA8	EDDEVAFF0

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f211~~6134483bd14dc8c12a99c984cbfe3431cc1c9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDDEVAFF1, External Debug Device Affinity register 1

The EDDEVAFF1 characteristics are:

Purpose

Copy of the high half of the PE MPIDR_EL1 register that allows a debugger to determine which PE in a multiprocessor system the external debug component relates to.

Configuration

~~It is IMPLEMENTATION DEFINED whether EDDEVAFF1 is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

Attributes

EDDEVAFF1 is a 32-bit register.

Field descriptions

The EDDEVAFF1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
MPIDR_EL1hi~~MPIDR_EL1 high half~~																															

MPIDR_EL1hi~~MPIDR_EL1 high half~~, bits [31:0]

MPIDR_EL1 high half. Read-only copy of the high half of MPIDR_EL1, as seen from the highest implemented Exception level.

Accessing the EDDEVAFF1

EDDEVAFF1 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFAC	EDDEVAFF1

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f211~~6134483bd14dc8c12a99c984cbfe3431cc1c9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDDEVARCH, External Debug Device Architecture register

The EDDEVARCH characteristics are:

Purpose

Identifies the programmers' model architecture of the external debug component.

Configuration

~~It is IMPLEMENTATION DEFINED whether EDDEVARCH is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

Attributes

EDDEVARCH is a 32-bit register.

Field descriptions

The EDDEVARCH bit assignments are:



ARCHITECT, bits [31:21]

Defines the architecture of the component. For debug, this is Arm Limited.

Bits [31:28] are the JEP106 continuation code, `0x4`.

Bits [27:21] are the JEP106 ID code, `0x3B`.

PRESENT, bit [20]

When set to 1, indicates that the DEVARCH is present.

This field is 1 in Armv8.

REVISION, bits [19:16]

Defines the architecture revision. For architectures defined by Arm this is the minor revision.

For debug, the revision defined by Armv8-A is `0x0`.

All other values are reserved.

ARCHVER, bits [15:12]

Defines the architecture version of the component. This is the same value as ID_AA64DFR0_EL1.DebugVer and DBGDIDR.Version. The defined values of this field are:

ARCHVER	Meaning
0b0110	Armv8.0 Debug architecture.
0b0111	Armv8.0 Debug architecture with Virtualization Host Extensions.
0b1000	Armv8.2 Debug architecture.
0b1001	Armv8.4 Debug architecture.

ARMv8.4-Debug adds the functionality indicated by the value 0b1001. ARMv8.2-Debug adds the functionality indicated by the value 0b1000. If ARMv8.1-VHE is not implemented, the only permitted value is 0b0110.

The fields ARCHVER and ARCHPART together form the field ARCHID, so that ARCHVER is ARCHID[15:12].

ARCHPART, bits [11:0]

ARCHPART	Meaning
0xA15	The part number of the Armv8-A debug component.

The fields ARCHVER and ARCHPART together form the field ARCHID, so that ARCHPART is ARCHID[11:0].

Accessing the EDDEVARCH

EDDEVARCH can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFBC	EDDEVARCH

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDDEVID, External Debug Device ID register 0

The EDDEVID characteristics are:

Purpose

Provides extra information for external debuggers about features of the debug implementation.

Configuration

~~It is IMPLEMENTATION DEFINED whether EDDEVID is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

Attributes

EDDEVID is a 32-bit register.

Field descriptions

The EDDEVID bit assignments are:



Bits [31:28]

Reserved, RES0.

AuxRegs, bits [27:24]

Indicates support for Auxiliary registers. Permitted values for this field are:

AuxRegs	Meaning
0b0000	None supported.
0b0001	Support for External Debug Auxiliary Control Register, EDACR.

All other values are reserved.

Bits [23:8]

Reserved, RES0.

DebugPower, bits [7:4]

From Armv8.3:

Indicates support for the ARMv8.3-DoPD feature. Defined values of this field are:

DebugPower	Meaning
0b0000	ARMv8.3-DoPD not implemented. Registers in the external debug interface register map are implemented in a mix of the Debug and Core power domains.
0b0001	ARMv8.3-DoPD implemented. All registers in the external debug interface register map are implemented in the Core power domain.

ARMv8.3-DoPD implements the functionality added by the value 0b0001.

All other values are reserved.

Otherwise:

Reserved, RES0.

PCSample, bits [3:0]

Indicates the level of PC Sample-based Profiling support using external debug registers. Permitted values of this field are:

PCSample	Meaning
0b0000	PC Sample-based Profiling Extension is not implemented in the external debug registers space.
0b0010	Only EDPCSR and EDCIDSR are implemented. This option is only permitted if EL3 and EL2 are not implemented.
0b0011	EDPCSR, EDCIDSR, and EDVIDSR are implemented.

All other values are reserved.

When ARMv8.2-PCSample is implemented, the only permitted value is 0b0000.

Note

ARMv8.2-PCSample implements the PC Sample-based Profiling Extension in the Performance Monitors register space, as indicated by the value of PMDEVID.PCSample.

Accessing the EDDEVID

EDDEVID can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFC8	EDDEVID

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDDEVID1, External Debug Device ID register 1

The EDDEVID1 characteristics are:

Purpose

Provides extra information for external debuggers about features of the debug implementation.

Configuration

~~It is IMPLEMENTATION DEFINED whether EDDEVID1 is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

Attributes

EDDEVID1 is a 32-bit register.

Field descriptions

The EDDEVID1 bit assignments are:



Bits [31:4]

Reserved, RES0.

PCSROffset, bits [3:0]

This field indicates the offset applied to PC samples returned by reads of EDPCSR. Permitted values of this field in Armv8 are:

PCSROffset	Meaning
0b0000	EDPCSR not implemented.
0b0010	EDPCSR implemented, and samples have no offset applied and do not sample the instruction set state in AArch32 state.

When ARMv8.2-PCSample is implemented, the only permitted value is 0b0000.

Note

ARMv8.2-PCSample implements the PC Sample-based Profiling Extension in the Performance Monitors register space, as indicated by the value of PMDEVID.PCSample.

Accessing the EDDEVID1

EDDEVID1 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFC4	EDDEVID1

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDDEVID2, External Debug Device ID register 2

The EDDEVID2 characteristics are:

Purpose

Reserved for future descriptions of features of the debug implementation.

Configuration

~~It is IMPLEMENTATION DEFINED whether EDDEVID2 is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

Attributes

EDDEVID2 is a 32-bit register.

Field descriptions

The EDDEVID2 bit assignments are:



Bits [31:0]

Reserved, RES0.

Accessing the EDDEVID2

EDDEVID2 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFC0	EDDEVID2

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDDEVTYPE, External Debug Device Type register

The EDDEVTYPE characteristics are:

Purpose

Indicates to a debugger that this component is part of a PEs debug logic.

Configuration

~~It is IMPLEMENTATION DEFINED whether EDDEVTYPE is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

Attributes

EDDEVTYPE is a 32-bit register.

Field descriptions

The EDDEVTYPE bit assignments are:



Bits [31:8]

Reserved, RES0.

SUB, bits [7:4]

Subtype. Must read as `0x1` to indicate this is a component within a PE.

MAJOR, bits [3:0]

Major type. Must read as `0x5` to indicate this is a debug logic component.

Accessing the EDDEVTYPE

EDDEVTYPE can be accessed through the external debug interface:

Component	Offset	Instance
Debug	`0xFCC`	EDDEVTYPE

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDDFR, External Debug Feature Register

The EDDFR characteristics are:

Purpose

Provides top level information about the debug system.

Note

Debuggers must use EDDEVARCH to determine the Debug architecture version.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Configuration

It is IMPLEMENTATION DEFINED whether EDDFR is implemented in the Core power domain or in the Debug power domain.

Attributes

EDDFR is a 64-bit register.

Field descriptions

The EDDFR bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																				TraceFilt				UNKNOWN							
CTX_CMPs				RES0				WRPs				RES0				BRPs				PMUVer				TraceVer				UNKNOWN			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:44]

Reserved, RES0.

TraceFilt, bits [43:40]

~~From Armv8.4:~~

Armv8.4 Self-hosted Trace Extension version. Defined~~The defined~~ values ~~of this field~~ are:

TraceFilt	Meaning
0b0000	Armv8.4 Self-hosted Trace Extension is not implemented.
0b0001	Armv8.4 Self-hosted Trace Extension is implemented.

All other values are reserved.

~~Otherwise:~~

~~Reserved, RES0.~~

ARMv8.4-Trace implements the functionality added by `0b0001`.

From Armv8.4, the permitted values are `0b0000` and `0b0001`.

Bits [39:32]

Reserved, UNKNOWN.

CTX_CMPs, bits [31:28]

Number of breakpoints that are context-aware, minus 1. These are the highest numbered breakpoints.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64DFR0_EL1.CTX_CMPs.

Bits [27:24]

Reserved, RES0.

WRPs, bits [23:20]

Number of watchpoints, minus 1. The value of `0b0000` is reserved.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64DFR0_EL1.WRPs.

Bits [19:16]

Reserved, RES0.

BRPs, bits [15:12]

Number of breakpoints, minus 1. The value of `0b0000` is reserved.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64DFR0_EL1.BRPs.

PMUVer, bits [11:8]

Performance Monitors Extension version.

This field does not follow the standard ID scheme, but uses the Alternative ID scheme described in 'Alternative ID scheme used for the Performance Monitors Extension version' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D10.1.4.

Defined values are:

PMUVer	Meaning
0b0000	Performance Monitors Extension not implemented.
0b0001	Performance Monitors Extension implemented, PMUv3.
0b0100	PMUv3 for Armv8.1. As 0b0001, and also includes support for: • Extended 16-bit PMEVTYPER<n>_EL0.evtCount field. • If EL2 is implemented, the MDCR_EL2.HPMD control bit.
0b0101	PMUv3 for Armv8.4. As 0b0100, and also includes support for the PMMIR register.
0b0110	PMUv3 for Armv8.5. As 0b0101, and also includes support for: • 64-bit event counters. • If EL2 is implemented, the MDCR_EL2.HCCD control bit. • If EL3 is implemented, the MDCR_EL3.SCCD control bit.
0b1111	IMPLEMENTATION DEFINED form of performance monitors supported, PMUv3 not supported. Arm does not recommend this value in new implementations.

ARMv8.1-PMU implements the functionality added by the value 0b0100.

ARMv8.4-PMU implements the functionality added by the value 0b0101.

ARMv8.5-PMU implements the functionality added by the value 0b0110.

All other values are reserved.

From Armv8.1, the value 0b0001 is not permitted.

From Armv8.4, the value 0b0100 is not permitted.

From Armv8.5, the value 0b0101 is not permitted.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64DFR0_EL1.PMUVer.

TraceVer, bits [7:4]

Trace support. Indicates whether System register interface to a PE trace unit is implemented. Defined values are:

TraceVer	Meaning
0b0000	PE trace unit System registers not implemented.
0b0001	PE trace unit System registers implemented.

All other values are reserved.

A value of 0b0000 only indicates that no System register interface to a PE trace unit is implemented. A PE trace unit might nevertheless be implemented without a System register interface.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64DFR0_EL1.TraceVer.

Bits [3:0]

Reserved, UNKNOWN.

Accessing the EDDFR

EDDFR can be accessed through the external debug interface:

Component	Offset	Instance	Range
Debug	0xD28	EDDFR	31:0

This interface is accessible as follows:

- When IsCorePowered() and !DoubleLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register are **IMPDEF**.

Component	Offset	Instance	Range
Debug	0xD2C	EDDFR	63:32

This interface is accessible as follows:

- When IsCorePowered() and !DoubleLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register are **IMPDEF**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDECCR, External Debug Exception Catch Control Register

The EDECCR characteristics are:

Purpose

Controls Exception Catch debug events.

Configuration

External register EDECCR bits [31:0] are architecturally mapped to AArch64 System register OSECCR_EL1[31:0] .

External register EDECCR bits [31:0] are architecturally mapped to AArch32 System register DBGOSECCR[31:0] .

EDECCR is in the Core power domain. ~~Some or all RW fields of this register have defined reset values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

Attributes

EDECCR is a 32-bit register.

Field descriptions

The EDECCR bit assignments are:

When ARMv8.2-Debug is implemented:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																NSR3	NSR2	NSR1	NSR0	SR3	SR2	SR1	SR0	NSE3	NSE2	NSE1	NSE0	SE3	SE2	SE1	SE0

Bits [31:16]

Reserved, RES0.

NSR<n>, bit [n+12], for n = 0 to 3

Controls Non-secure exception catch on exception return to EL<n> in conjunction with NSE<n>. See the summary of Exception Catch debug event control for information.

~~If EL3 is not implemented and the PE behaves as if SCR_EL3.NS is set to 0, this field is reserved, RES0. Otherwise, possible values for this field are:~~

NSR<n>	Meaning
0b0	If the corresponding NSE<n> bit is 0, then Exception Catch debug events are disabled for Non-secure Exception level <n>. If the corresponding NSE<n> bit is 1, then Exception Catch debug events are enabled for exception entry, reset entry and exception return to Non-secure Exception level <n>.
0b1	If the corresponding NSE<n> bit is 0, then Exception Catch debug events are enabled for exception returns to Non-secure Exception level <n>. If the corresponding NSE<n> bit is 1, then Exception Catch debug events are enabled for exception entry and reset entry to Non-secure Exception level <n>.

If EL3 is not implemented and the PE behaves as if SCR_EL3.NS is set to 0, this field is reserved, RES0.

Note

It is IMPLEMENTATION DEFINED whether a reset entry to an Exception level is permitted to generate an Exception Catch debug event.

A value of the NSR field that enables an Exception Catch debug event for an Exception level that is not implemented is reserved. If the NSR field is programmed with a reserved value then:

- The PE behaves as if it is programmed with a defined value, other than for a read of EDECCR.
- The value returned for NSR by a read of EDECCR is UNKNOWN.

On a Cold reset, this field resets to 0.

SR<n>, bit [n+8], for n = 0 to 3

Controls Secure exception catch on exception return to EL<n> in conjunction with SE<n>. See the summary of Exception Catch debug event control for information.

~~If EL3 is not implemented and the PE behaves as if SCR_EL3.NS is set to 1, this field is reserved, RES0. Otherwise, possible values for this field are:~~

SR<n>	Meaning
0b0	If the corresponding SE<n> bit is 0, then Exception Catch debug events are disabled for Secure Exception level <n>. If the corresponding SE<n> bit is 1, then Exception Catch debug events are enabled for exception entry, reset entry and exception return to Secure Exception level <n>.
0b1	If the corresponding SE<n> bit is 0, then Exception Catch debug events are enabled for exception returns to Secure Exception level <n>. If the corresponding SE<n> bit is 1, then Exception Catch debug events are enabled for exception entry and reset entry to Secure Exception level <n>.

If EL3 is not implemented and the PE behaves as if SCR_EL3.NS is set to 1, this field is reserved, RES0.

Note

It is IMPLEMENTATION DEFINED whether a reset entry to an Exception level is permitted to generate an Exception Catch debug event.

A value of the SR field that enables an Exception Catch debug event for an Exception level that is not implemented is reserved. If the SR field is programmed with a reserved value then:

- The PE behaves as if it is programmed with a defined value, other than for a read of EDECCR.
- The value returned for SR by a read of EDECCR is UNKNOWN.

On a Cold reset, this field resets to 0.

NSE<n>, bit [n+4], for n = 0 to 3

Coarse-grained Non-secure exception catch for EL<n>. This controls whether Exception Catch debug events are enabled for Non-secure EL<n>. This also controls:

- The behavior of exception catch on exception entry to EL<n>.
- The behavior of exception catch on exception return to EL<n> in conjunction with NSR<n>.

~~If EL3 is not implemented and the PE behaves as if SCR_EL3.NS is set to 0, this field is reserved, RES0. Otherwise, possible values for this field are:~~

NSE<n>	Meaning
0b0	If the corresponding NSR<n> bit is 0, then Exception Catch debug events are disabled for Non-secure Exception level <n>. If the corresponding NSR<n> bit is 1, then Exception Catch debug events are enabled for exception returns to Non-secure Exception level <n>.
0b1	If the corresponding NSR<n> bit is 0, then Exception Catch debug events are enabled for exception entry, reset entry and exception return to Non-secure Exception level <n>. If the corresponding NSR<n> bit is 1, then Exception Catch debug events are enabled for exception entry and reset entry to Non-secure Exception level <n>.

If EL3 is not implemented and the PE behaves as if SCR_EL3.NS is set to 0, this field is reserved, RES0.

A value of the NSE field that enables an Exception Catch debug event for an Exception level that is not implemented is reserved. If the NSE field is programmed with a reserved value then:

- The PE behaves as if it is programmed with a defined value, other than for a read of EDECCR.
- The value returned for NSE by a read of EDECCR is UNKNOWN.

On a Cold reset, this field resets to 0.

SE<n>, bit [n], for n = 0 to 3

Coarse-grained Secure exception catch for EL<n>. This field controls whether Exception Catch debug events are enabled for Secure EL<n>.

- The behavior of exception catch on exception entry to EL<n>.
- The behavior of exception catch on exception return to EL<n> in conjunction with SR<n>.

~~If EL3 is not implemented and the PE behaves as if SCR_EL3.NS is set to 1, this field is reserved, RES0. Otherwise, possible values for this field are:~~

SE<n>	Meaning
0b0	If the corresponding SR<n> bit is 0, then Exception Catch debug events are disabled for Secure Exception level <n>. If the corresponding SR<n> bit is 1, then Exception Catch debug events are enabled for exception returns to Secure Exception level <n>.
0b1	If the corresponding SR<n> bit is 0, then Exception Catch debug events are enabled for exception entry, reset entry and exception return to Secure Exception level <n>. If the corresponding SR<n> bit is 1, then Exception Catch debug events are enabled for exception entry and reset entry to Secure Exception level <n>.

If EL3 is not implemented and the PE behaves as if SCR_EL3.NS is set to 1, this field is reserved, RES0.

A value of the SE field that enables an Exception Catch debug event for an Exception level that is not implemented is reserved. If the SE field is programmed with a reserved value then:

- The PE behaves as if it is programmed with a defined value, other than for a read of EDECCR.
- The value returned for SE by a read of EDECCR is UNKNOWN.

On a Cold reset, this field resets to 0.

Otherwise:



Bits [31:8]

Reserved, RES0.

NSE<n>, bit [n+4], for n = 0 to 3

Coarse-grained Non-secure exception catch. If EL3 and EL2 are not implemented and the PE behaves as if SCR_EL3.NS is set to 0, this field is reserved, RES0. Otherwise, possible values for this field are:

NSE<n>	Meaning
0b0	Exception Catch debug events are disabled for Non-secure Exception level <n>.
0b1	Exception Catch debug events are enabled for Non-secure Exception level <n>.

A value of the NSE field that enables an Exception Catch debug event for an Exception level that is not implemented is reserved. If the NSE field is programmed with a reserved value then:

- The PE behaves as if it is programmed with a defined value, other than for a read of EDECCR.
- The value returned for NSE by a read of EDECCR is UNKNOWN.

SE<n>, bit [n], for n = 0 to 3

Coarse-grained Secure exception catch.

~~Coarse-grained Secure exception catch. If EL3 is not implemented and the PE behaves as if SCR_EL3.NS is set to 1, this field is reserved, RES0. Otherwise, possible values for this field are:~~

SE<n>	Meaning
0b0	Exception Catch debug events are disabled for Secure Exception level <n>.
0b1	Exception Catch debug events are enabled for Secure Exception level <n>.

If EL3 is not implemented and the PE behaves as if SCR_EL3.NS is set to 1, this field is reserved, RES0.

A value of the SE field that enables an Exception Catch debug event for an Exception level that is not implemented is reserved. If the SE field is programmed with a reserved value then:

- The PE behaves as if it is programmed with a defined value, other than for a read of EDECCR.
- The value returned for SE by a read of EDECCR is UNKNOWN.

Accessing the EDECCR

EDECCR can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x098	EDECCR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDECR, External Debug Execution Control Register

The EDECR characteristics are:

Purpose

Controls Halting debug events.

Configuration

If ARMv8.3-DoPD is implemented, this register is in the Core power domain.

It is IMPLEMENTATION DEFINED whether EDECR is implemented in the Core power domain or in the Debug power domain. Some or all RW fields of this register have defined reset values, and:

- The register is not affected by a Warm reset.
- If the register is implemented in the Core power domain the reset values apply on a Cold reset, and the register is not affected by an External debug reset.
- If the register is implemented in the Debug power domain the reset values apply on an External debug reset, and the register is not affected by a Cold reset.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

Attributes

EDECR is a 32-bit register.

Field descriptions

The EDECR bit assignments are:



Bits [31:3]

Reserved, RES0.

SS, bit [2]

Halting step enable. Possible values of this field are:

SS	Meaning
0b0	Halting step debug event disabled.
0b1	Halting step debug event enabled.

If the value of EDECR.SS is changed when the PE is in Non-debug state, behavior is CONSTRAINED UNPREDICTABLE as described in 'Changing the value of EDECR.SS when not in Debug state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

The following resets apply:

- On a Cold reset, this field resets to:
  - If ARMv8.3-DoPD is implemented, 0.
- On ana External debug reset, this field resets to:

- If ARMv8.3-DoPD is not implemented, 0.

- On a Warm reset, this field resets to:
  - If ARMv8.3-DoPD is implemented, an unchanged value.

RCE, bit [1]

When ARMv8.3-DoPD is not implemented:

Reset Catch Enable.

RCE	Meaning
0b0	Reset Catch debug event disabled.
0b1	Reset Catch debug event enabled.

The following resets apply:

~~On a External debug reset, this field resets to 0.~~

- On an External debug reset, this field resets to 0.
- On a Warm reset, the value of this field is unchanged.

Otherwise:

Reserved, RES0.

OSUCE, bit [0]

When ARMv8.3-DoPD is not implemented:

OS Unlock Catch Enable.

OSUCE	Meaning
0b0	OS Unlock Catch debug event disabled.
0b1	OS Unlock Catch debug event enabled.

The following resets apply:

~~On a External debug reset, this field resets to 0.~~

- On an External debug reset, this field resets to 0.
- On a Warm reset, the value of this field is unchanged.

Otherwise:

Reserved, RES0.

Accessing the EDECR

EDECR can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x024	EDECR

This interface is accessible as follows:

- When (ARMv8.3-DoPD is not implemented or IsCorePowered()) and SoftwareLockStatus() accesses to this register are **RO**.
- When (ARMv8.3-DoPD is not implemented or IsCorePowered()) and !SoftwareLockStatus() accesses to this register are **RW**.

- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDESR, External Debug Event Status Register

The EDESR characteristics are:

Purpose

Indicates the status of internally pending Halting debug events.

Configuration

EDESR is in the Core power domain. ~~Some or all RW fields of this register have defined reset values. The field descriptions identify when the reset values apply.~~

Attributes

EDESR is a 32-bit register.

Field descriptions

The EDESR bit assignments are:



Bits [31:3]

Reserved, RES0.

SS, bit [2]

When ARMv8.3-DoPD is implemented:

Halting step debug event pending. Possible values of this field are:

SS	Meaning
0b0	Reading this means that a Halting step debug event is not pending. Writing this means no action.
0b1	Reading this means that a Halting step debug event is pending. Writing this clears the pending Halting step debug event.

On a Cold reset, this field resets to 0.

Otherwise:

Halting step debug event pending. Possible values of this field are:

SS	Meaning
0b0	Reading this means that a Halting step debug event is not pending. Writing this means no action.
0b1	Reading this means that a Halting step debug event is pending. Writing this clears the pending Halting step debug event.

On a Warm reset, this field resets to the value in EDECR.SS.

RC, bit [1]

Reset Catch debug event pending. Possible values of this field are:

RC	Meaning
0b0	Reading this means that a Reset Catch debug event is not pending. Writing this means no action.
0b1	Reading this means that a Reset Catch debug event is pending. Writing this clears the pending Reset Catch debug event.

On a Warm reset, this field resets to:

- If ARMv8.3-DoPD is implemented, theThe value in CTIDEVCTL.RCE.
- If ARMv8.3-DoPD is not implemented, theThe value in EDECR.RCE.

OSUC, bit [0]

OS Unlock Catch debug event pending. Possible values of this field are:

OSUC	Meaning
0b0	Reading this means that an OS Unlock Catch debug event is not pending. Writing this means no action.
0b1	Reading this means that an OS Unlock Catch debug event is pending. Writing this clears the pending OS Unlock Catch debug event.

On a Warm reset, this field resets to 0.

Accessing the EDESR

If a request to clear a pending Halting debug event is received at or about the time when halting becomes allowed, it is CONSTRAINED UNPREDICTABLE whether the event is taken.

If Core power is removed while a Halting debug event is pending, it is lost. However, it might become pending again when the Core is powered back on and Cold reset.

EDESR can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x020	EDESR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDITCTRL, External Debug Integration mode Control register

The EDITCTRL characteristics are:

Purpose

Enables the external debug to switch from its default mode into integration mode, where test software can control directly the inputs and outputs of the PE, for integration testing or topology detection.

Configuration

It is IMPLEMENTATION DEFINED whether EDITCTRL is implemented in the Core power domain or in the Debug power domain. Some or all RW fields of this register have defined reset values, and:

- The register is not affected by a Warm reset.
- If the register is implemented in the Core power domain the reset values apply on a Cold reset, and the register is not affected by an External debug reset.
- If the register is implemented in the Debug power domain the reset values apply on an External debug reset, and the register is not affected by a Cold reset.

Implementation of this register is OPTIONAL.

Attributes

EDITCTRL is a 32-bit register.

Field descriptions

The EDITCTRL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																															IME

Bits [31:1]

Reserved, RES0.

IME, bit [0]

Integration mode enable. When IME == 1, the device reverts to an integration mode to enable integration testing or topology detection. The integration mode behavior is IMPLEMENTATION DEFINED.

IME	Meaning
0b0	Normal operation.
0b1	Integration mode enabled.

On a Implementation reset, this field resets to 0.

Accessing the EDITCTRL

EDITCTRL can be accessed through the external debug interface:

Component	Offset	Instance

Debug	0xF00	EDITCTRL

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register are **IMPDEF**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDITR, External Debug Instruction Transfer Register

The EDITR characteristics are:

Purpose

Used in Debug state for passing instructions to the PE for execution.

Configuration

EDITR is in the Core power domain.

Attributes

EDITR is a 32-bit register.

Field descriptions

The EDITR bit assignments are:

When AArch32 is supported at any Exception level and in AArch32 state:



T32Second, bits [31:16]

Second halfword of the T32 instruction to be executed on the PE. When EDITR contains a 16-bit T32 instruction, this field is ignored. For more information see 'Behavior in Debug state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H2, Debug State.

T32First, bits [15:0]

First halfword of the T32 instruction to be executed on the PE.

When AArch64 is supported at any Exception level and in AArch64 state:



Bits [31:0]

A64 instruction to be executed on the PE.

Accessing the EDITR

If EDSCR.ITE == 0 when the PE exits Debug state on receiving a Restart request trigger event, the behavior of any instruction issued through the ITR in Normal access mode that has not completed execution is CONSTRAINED UNPREDICTABLE, and must do one of the following:

- It must complete execution in Debug state before the PE executes the restart sequence.
- It must complete execution in Non-debug state before the PE executes the restart sequence.

- It must be abandoned. This means that the instruction does not execute. Any registers or memory accessed by the instruction are left in an UNKNOWN state.

EDITR ignores writes if the PE is in Non-debug state.

EDITR can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x084	EDITR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and SoftwareLockStatus() accesses to this register are **WI**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and !SoftwareLockStatus() accesses to this register are **WO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDLAR, External Debug Lock Access Register

The EDLAR characteristics are:

Purpose

Allows or disallows access to the external debug registers through a memory-mapped interface.

The optional Software Lock provides a lock to prevent memory-mapped writes to the debug registers. Use of this lock mechanism reduces the risk of accidental damage to the contents of the debug registers. It does not, and cannot, prevent all accidental or malicious damage.

Configuration

~~If ARMv8.3-DoPD is implemented, then ARMv8.0-SoftwareLock is not implemented by the architecturally-defined debug components of the PE in the Core power domain.~~

If ARMv8.3-DoPD is implemented, then ARMv8.0-SoftwareLock is not implemented by the architecturally-defined debug components of the PE in the Core power domain.

~~It is IMPLEMENTATION DEFINED whether EDLAR is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is not implemented, then this register is in the Debug power domain.

Software uses EDLAR to set or clear the lock, and EDLSR to check the current status of the lock.

Attributes

EDLAR is a 32-bit register.

Field descriptions

The EDLAR bit assignments are:

When the Software Lock is implemented.:



KEY, bits [31:0]

Lock Access control. Writing the key value `0xC5ACCE55` to this field unlocks the lock, enabling write accesses to this component's registers through a memory-mapped interface.

Writing any other value to this register locks the lock, disabling write accesses to this component's registers through a memory mapped interface.

Otherwise:



Otherwise

Bits [31:0]

Reserved, RES0.

Accessing the EDLAR

EDLAR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
Debug	0xFB0	EDLAR

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **WO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDLSR, External Debug Lock Status Register

The EDLSR characteristics are:

Purpose

Indicates the current status of the software lock for external debug registers.

The optional Software Lock provides a lock to prevent memory-mapped writes to the debug registers. Use of this lock mechanism reduces the risk of accidental damage to the contents of the debug registers. It does not, and cannot, prevent all accidental or malicious damage.

Configuration

~~If ARMv8.3-DoPD is implemented, then ARMv8.0-SoftwareLock is not implemented by the architecturally-defined debug components of the PE in the Core power domain.~~

If ARMv8.3-DoPD is implemented, then ARMv8.0-SoftwareLock is not implemented by the architecturally-defined debug components of the PE in the Core power domain.

~~It is IMPLEMENTATION DEFINED whether EDLSR is implemented in the Core power domain or in the Debug power domain. Some or all RW fields of this register have defined reset values, and:~~

- ~~The register is not affected by a Warm reset.~~
- ~~If the register is implemented in the Core power domain the reset values apply on a Cold reset, and the register is not affected by an External debug reset.~~
- ~~If the register is implemented in the Debug power domain the reset values apply on an External debug reset, and the register is not affected by a Cold reset.~~

If ARMv8.3-DoPD is not implemented, then this register is in the Debug power domain.

Software uses EDLAR to set or clear the lock, and EDLSR to check the current status of the lock.

Attributes

EDLSR is a 32-bit register.

Field descriptions

The EDLSR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																													nTT	SLK	SLI

Bits [31:3]

Reserved, RES0.

nTT, bit [2]

Not thirty-two bit access required. RAZ.

SLK, bit [1]

When the Software Lock is implemented.:

Software Lock status for this component. For an access to LSR that is not a memory-mapped access, or when the Software Lock is not implemented, this field is RES0.

For memory-mapped accesses when the Software Lock is implemented, possible values of this field are:

SLK	Meaning
0b0	Lock clear. Writes are permitted to this component's registers.
0b1	Lock set. Writes to this component's registers are ignored, and reads have no side effects.

The following resets apply:

- If Armv8.3-DoPD is implemented, this register is reset by Cold reset and not affected by External debug reset. If Armv8.3-DoPD is not implemented, this register is reset by External debug reset and not affected by Cold reset.
- This field resets to 1.

Otherwise:

Reserved, RAZ.

SLI, bit [0]

Software Lock implemented. For an access to LSR that is not a memory-mapped access, this field is RAZ. For memory-mapped accesses, the value of this field is IMPLEMENTATION DEFINED. Permitted values are:

SLI	Meaning
0b0	Software Lock not implemented or not memory-mapped access.
0b1	Software Lock implemented and memory-mapped access.

Accessing the EDLSR

EDLSR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
Debug	0xFB4	EDLSR

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDPCSR, External Debug Program Counter Sample Register

The EDPCSR characteristics are:

Purpose

Holds a sampled instruction address value.

Configuration

EDPCSR is in the Core power domain.

~~EDPCSR is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

This register is present only when ARMv8.0-PCSample is implemented and ARMv8.2-PCSample is not implemented. Otherwise, direct accesses to EDPCSR are RES0.

Implemented only if the OPTIONAL PC Sample-based Profiling Extension is implemented in the external debug registers space.

Note

ARMv8.2-PCSample implements the PC Sample-based Profiling Extension in the Performance Monitors registers space.

Attributes

EDPCSR is a pair of 32-bit registers.

If ARMv8.1-VHE is implemented, the format of this register differs depending on the value of EDSCR.SC2.

Field descriptions

The EDPCSR bit assignments are:

When ARMv8.1-VHE is not implemented or EDSCR.SC2 == 0:



Bits [63:32]

PC Sample high word, EDPCSRhi. If EDVIDSR.HV == 0 then this field is RAZ, otherwise bits [63:32] of the sampled instruction address value. The translation regime that EDPCSR samples can be determined from EDVIDSR.{NS,E2,E3}.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [31:0]

PC Sample low word. EDPCSRlo, bits[31:0] of the sampled instruction address value.

EDPCSRlo reads as `0xFFFFFFFF` when any of the following are true:

- The PE is in Debug state.
- PC Sample-based profiling is prohibited.

If an instruction has retired since the PE left Reset state, then the first read of EDPCSR[31:0] is permitted but not required to return `0xFFFFFFFF`.

EDPCSRlo reads as an UNKNOWN value when any of the following are true:

- The PE is in Reset state.
- No instruction has retired since the PE left Reset state, Debug state, or a state where PC Sample-based Profiling is prohibited.
- No instruction has retired since the last read of EDPCSR[31:0].

For the cases where a read of EDPCSR[31:0] returns `0xFFFFFFFF` or an UNKNOWN value, the read has the side-effect of setting EDPCSRhi, EDCIDSR, and EDVIDSR to UNKNOWN values.

Otherwise, a read of EDPCSR[31:0] returns bits [31:0] of the sampled instruction address value and has the side-effect of indirectly writing to EDPCSRhi, EDCIDSR, and EDVIDSR. The translation regime that EDPCSR samples can be determined from EDVIDSR.{NS,E2,E3}.

For a read of EDPCSR[31:0] from the memory-mapped interface, if EDLSR.SLK == 1, meaning the OPTIONAL Software Lock is locked, then the side-effect of the access does not occur and EDPCSRhi, EDCIDSR, and EDVIDSR are unchanged.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

When ARMv8.1-VHE is implemented and EDSCR.SC2 == 1:



NS, bit [63]

Non-secure state sample. Indicates the Security state that is associated with the most recent EDPCSR sample or, when it is read as a single atomic 64-bit read, the current EDPCSR sample. The translation regime that EDPCSR samples can be determined from EDPCSR.{NS,EL}.

If EL3 is not implemented, this bit indicates the Effective value of SCR.NS.

NS	Meaning
0b0	Sample is from Secure state.
0b1	Sample is from Non-secure state.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

EL, bits [62:61]

Exception level status sample. Indicates the Exception level that is associated with the most recent EDPCSR sample or, when it is read as a single atomic 64-bit read, the current EDPCSR sample. The translation regime that EDPCSR samples can be determined from EDPCSR.{NS,EL}.

EL	Meaning
0b00	Sample is from EL0.
0b01	Sample is from EL1.
0b10	Sample is from EL2.
0b11	Sample is from EL3.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [60:56]

Reserved, RES0.

Bits [55:32]

PC Sample high word, EDPCSRhi. Bits [55:32] of the sampled instruction address value. The translation regime that EDPCSR samples can be determined from EDPCSR.{NS,EL}.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [31:0]

PC Sample low word. EDPCSRlo, bits[31:0] of the sampled instruction address value.

EDPCSRlo reads as `0xFFFFFFFF` when any of the following are true:

- The PE is in Debug state.
- PC Sample-based profiling is prohibited.

If an instruction has retired since the PE left Reset state, then the first read of EDPCSR[31:0] is permitted but not required to return `0xFFFFFFFF`.

EDPCSRlo reads as an UNKNOWN value when any of the following are true:

- The PE is in Reset state.
- No instruction has retired since the PE left Reset state, Debug state, or a state where PC Sample-based Profiling is prohibited.
- No instruction has retired since the last read of EDPCSR[31:0].

For the cases where a read of EDPCSR[31:0] returns `0xFFFFFFFF` or an UNKNOWN value, the read has the side-effect of setting EDPCSRhi, EDCIDSR, and EDVIDSR to UNKNOWN values.

Otherwise, a read of EDPCSR[31:0] returns bits [31:0] of the sampled instruction address value and has the side-effect of indirectly writing to EDPCSRhi, EDCIDSR, and EDVIDSR. The translation regime that EDPCSR samples can be determined from EDPCSR.{NS,EL}.

For a read of EDPCSR[31:0] from the memory-mapped interface, if EDLSR.SLK == 1, meaning the OPTIONAL Software Lock is locked, then the side-effect of the access does not occur and EDPCSRhi, EDCIDSR, and EDVIDSR are unchanged.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the EDPCSR

IMPLEMENTATION DEFINED extensions to external debug might make the value of this register UNKNOWN, see 'Permitted behavior that might make the PC Sample-based profiling registers UNKNOWN' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile

EDPCSR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance	Range
Debug	`0x0A0`	EDPCSR	31:0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

Component	Offset	Instance	Range
Debug	`0x0AC`	EDPCSR	63:32

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDPFR, External Debug Processor Feature Register

The EDPFR characteristics are:

Purpose

Provides information about implemented PE features.

For general information about the interpretation of the ID registers, see 'Principles of the ID scheme for fields in ID registers' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Configuration

It is IMPLEMENTATION DEFINED whether EDPFR is implemented in the Core power domain or in the Debug power domain.

Attributes

EDPFR is a 64-bit register.

Field descriptions

The EDPFR bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
UNKNOWN				UNKNOWN				RES0				UNKNOWN				AMU				UNKNOWN				SEL2				SVE			
UNKNOWN				GIC				AdvSIMD				FP				EL3				EL2				EL1				EL0			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:60]

From Armv8.5:

Reserved, UNKNOWN.

Otherwise:

Reserved, RES0.

Bits [59:56]

From Armv8.5:

Reserved, UNKNOWN.

Otherwise:

Reserved, RES0.

Bits [55:52]

Reserved, RES0.

Bits [51:48]

From Armv8.4:

Reserved, UNKNOWN.

Otherwise:

Reserved, RES0.

AMU, bits [47:44]

~~From Armv8.4:~~

Activity Monitors Extension. Defined values are:

AMU	Meaning
0b0000	Activity Monitors Extension is not implemented.
0b0001	Activity Monitors Extension version 1 is implemented.

All other values are reserved.

AMUv1~~ARMv8.4-AMUv1~~ implements the functionality identified by the value 0b0001.

In Armv8.0, Armv8.1, Armv8.2, and Armv8.3, the only permitted value is 0b0000.

From Armv8.4, the permitted values are 0b0000 and 0b0001.

~~Otherwise:~~

~~Reserved, RES0.~~

Bits [43:40]

From Armv8.2:

Reserved, UNKNOWN.

Otherwise:

Reserved, RES0.

SEL2, bits [39:36]

~~From Armv8.4:~~

Secure EL2. Defined values are:

SEL2	Meaning
0b0000	Secure EL2 is not implemented.
0b0001	Secure EL2 is implemented.

All other values are reserved.

~~Reserved, RES0.~~

SVE, bits [35:32]

From Armv8.2:

Otherwise:
SVE, bits [35:32]

Scalable Vector Extension. Defined values are:

SVE	Meaning
0b0000	SVE is not implemented.
0b0001	SVE is implemented.

All other values are reserved.

Otherwise:

Reserved, RES0.

Bits [31:28]

From Armv8.2:

Reserved, UNKNOWN.

Otherwise:

Reserved, RES0.

GIC, bits [27:24]

System register GIC interface support. Defined values are:

GIC	Meaning
0b0000	GIC CPU interface system registers not implemented.
0b0001	System register interface to versions 3.0 and 4.0 of the GIC CPU interface is supported.
0b0011	System register interface to version 4.1 of the GIC CPU interface is supported.

All other values are reserved.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64PFR0_EL1.GIC.

AdvSIMD, bits [23:20]

Advanced SIMD. Defined values are:

AdvSIMD	Meaning
0b0000	Advanced SIMD is implemented, including support for the following SISD and SIMD operations: • Integer byte, halfword, word and doubleword element operations. • Single-precision and double-precision floating-point arithmetic. • Conversions between single-precision and half-precision data types, and double-precision and half-precision data types.
0b0001	As for 0b0000, and also includes support for half-precision floating-point arithmetic.
0b1111	Advanced SIMD is not implemented.

All other values are reserved.

This field must have the same value as the FP field.

The permitted values are:

- `0b0000` in an implementation with Advanced SIMD support, that does not include the ARMv8.2-FP16 extension.
- `0b0001` in an implementation with Advanced SIMD support, that includes the ARMv8.2-FP16 extension.
- `0b1111` in an implementation without Advanced SIMD support.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64PFR0_EL1.AdvSIMD.

FP, bits [19:16]

Floating-point. Defined values are:

FP	Meaning
`0b0000`	Floating-point is implemented, and includes support for: • Single-precision and double-precision floating-point types. • Conversions between single-precision and half-precision data types, and double-precision and half-precision data types.
`0b0001`	As for `0b0000`, and also includes support for half-precision floating-point arithmetic.
`0b1111`	Floating-point is not implemented.

All other values are reserved.

This field must have the same value as the AdvSIMD field.

The permitted values are:

- `0b0000` in an implementation with floating-point support, that does not include the ARMv8.2-FP16 extension.
- `0b0001` in an implementation with floating-point support, that includes the ARMv8.2-FP16 extension.
- `0b1111` in an implementation without floating-point support.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64PFR0_EL1.FP.

EL3, bits [15:12]

AArch64 EL3 Exception level handling. Defined values are:

EL3	Meaning
`0b0000`	EL3 is not implemented or cannot be executed in AArch64 state.
`0b0001`	EL3 can be executed in AArch64 state only.
`0b0010`	EL3 can be executed in both~~either~~ Execution~~AArch64~~ states.~~or AArch32 state.~~

When the value of EDAA32PFR.EL3 is non-zero, this field must be `0b0000`.

All other values are reserved.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64PFR0_EL1.EL3.

EL2, bits [11:8]

AArch64 EL2 Exception level handling. Defined values are:

EL2	Meaning
0b0000	EL2 is not implemented or cannot be executed in AArch64 state.
0b0001	EL2 can be executed in AArch64 state only.
0b0010	EL2 can be executed in bothe~~either~~ Execution~~AArch64~~ states.~~or AArch32 state.~~

When the value of EDAA32PFR.EL2 is non-zero, this field must be 0b0000.

All other values are reserved.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64PFR0_EL1.EL2.

EL1, bits [7:4]

AArch64 EL1 Exception level handling. Defined values are:

EL1	Meaning
0b0000	EL1 cannot be executed in AArch64 state. ~~EL1 can be executed in AArch32 state only.~~ EL1 can be executed in AArch32 state only.
0b0001	EL1 can be executed in AArch64 state only.
0b0010	EL1 can be executed in bothe~~either~~ Execution~~AArch64~~ states.~~or AArch32 state.~~

All other values are reserved.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64PFR0_EL1.EL1.

EL0, bits [3:0]

AArch64 EL0 Exception level handling. Defined values are:

EL0	Meaning
0b0000	EL0 cannot be executed in AArch64 state. ~~EL0 can be executed in AArch32 state only.~~ EL0 can be executed in AArch32 state only.
0b0001	EL0 can be executed in AArch64 state only.
0b0010	EL0 can be executed in bothe~~either~~ Execution~~AArch64~~ states.~~or AArch32 state.~~

All other values are reserved.

In an Armv8-A implementation that supports AArch64 state in at least one Exception level, this field returns the value of ID_AA64PFR0_EL1.EL0.

Accessing the EDPFR

EDPFR can be accessed through the external debug interface:

Component	Offset	Instance	Range
Debug	0xD20	EDPFR	31:0

This interface is accessible as follows:

- When IsCorePowered() and !DoubleLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register are **IMPDEF**.

Component	Offset	Instance	Range
Debug	0xD24	EDPFR	63:32

This interface is accessible as follows:

- When IsCorePowered() and !DoubleLockStatus() accesses to this register are **RO**.

- Otherwise accesses to this register are **IMPDEF**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDPIDR0, External Debug Peripheral Identification Register 0

The EDPIDR0 characteristics are:

Purpose

Provides information to identify an external debug component.

For more information see 'About the Peripheral identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether EDPIDR0 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

EDPIDR0 is a 32-bit register.

Field descriptions

The EDPIDR0 bit assignments are:



Bits [31:8]

Reserved, RES0.

PART_0, bits [7:0]

Part number, least significant byte.

Accessing the EDPIDR0

EDPIDR0 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFE0	EDPIDR0

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDPIDR1, External Debug Peripheral Identification Register 1

The EDPIDR1 characteristics are:

Purpose

Provides information to identify an external debug component.

For more information see 'About the Peripheral identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether EDPIDR1 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

EDPIDR1 is a 32-bit register.

Field descriptions

The EDPIDR1 bit assignments are:



Bits [31:8]

Reserved, RES0.

DES_0, bits [7:4]

Designer, least significant nibble of JEP106 ID code. For Arm Limited, this field is `0b1011`.

PART_1, bits [3:0]

Part number, most significant nibble.

Accessing the EDPIDR1

EDPIDR1 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	`0xFE4`	EDPIDR1

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDPIDR2, External Debug Peripheral Identification Register 2

The EDPIDR2 characteristics are:

Purpose

Provides information to identify an external debug component.

For more information see 'About the Peripheral identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether EDPIDR2 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

EDPIDR2 is a 32-bit register.

Field descriptions

The EDPIDR2 bit assignments are:



Bits [31:8]

Reserved, RES0.

REVISION, bits [7:4]

Part major revision. Parts can also use this field to extend Part number to 16-bits.

JEDEC, bit [3]

RAO. Indicates a JEP106 identity code is used.

DES_1, bits [2:0]

Designer, most significant bits of JEP106 ID code. For Arm Limited, this field is `0b011`.

Accessing the EDPIDR2

EDPIDR2 can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0xFE8	EDPIDR2

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDPIDR3, External Debug Peripheral Identification Register 3

The EDPIDR3 characteristics are:

Purpose

Provides information to identify an external debug component.

For more information see 'About the Peripheral identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether EDPIDR3 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

EDPIDR3 is a 32-bit register.

Field descriptions

The EDPIDR3 bit assignments are:



Bits [31:8]

Reserved, RES0.

REVAND, bits [7:4]

Part minor revision. Parts using EDPIDR2.REVISION as an extension to the Part number must use this field as a major revision number.

CMOD, bits [3:0]

Customer modified. Indicates someone other than the Designer has modified the component.

Accessing the EDPIDR3

EDPIDR3 can be accessed through the external debug interface:

Component	Offset	Instance

Debug	0xFEC	EDPIDR3

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDPIDR4, External Debug Peripheral Identification Register 4

The EDPIDR4 characteristics are:

Purpose

Provides information to identify an external debug component.

For more information see 'About the Peripheral identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether EDPIDR4 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

EDPIDR4 is a 32-bit register.

Field descriptions

The EDPIDR4 bit assignments are:



Bits [31:8]

Reserved, RES0.

SIZE, bits [7:4]

Size of the component. RAZ. Log_2 of the number of 4KB pages from the start of the component to the end of the component ID registers.

DES_2, bits [3:0]

Designer, JEP106 continuation code, least significant nibble. For Arm Limited, this field is `0b0100`.

Accessing the EDPIDR4

EDPIDR4 can be accessed through the external debug interface:

Component	Offset	Instance

Debug	0xFD0	EDPIDR4

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDPRCR, External Debug Power/Reset Control Register

The EDPRCR characteristics are:

Purpose

Controls the PE functionality related to powerup, reset, and powerdown.

Configuration

EDPRCR contains fields that are in the Core power domain and fields that are in the Debug power domain.

~~For RW fields see the field description for a description of the behavior of the field on a reset that applies to its power domain. However:~~

- ~~Fields that are in the Core power domain are not affected by a warm reset and are not affected by an External debug reset.~~
- ~~Fields that are in the Debug power domain reset to their defined reset values on an External debug reset, and are not affected by a Warm reset and are not affected by a Cold reset.~~

If ARMv8.3-DoPD is implemented then all fields in this register are in the Core power domain.

CORENPDRQ is the only field that is mapped between the EDPRCR and DBGPRCR and DBGPRCR_EL1.

Attributes

EDPRCR is a 32-bit register.

Field descriptions

The EDPRCR bit assignments are:

When ARMv8.3-DoPD is implemented:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																														CWRR	CORENPDRQ

Bits [31:2]

Reserved, RES0.

CWRR, bit [1]

Warm reset request. Write-only bit that reads as zero.

The extent of the reset is IMPLEMENTATION DEFINED, but must be one of:

- The request is ignored.
- Only this PE is Warm reset.
- This PE and other components of the system, possibly including other PEs, are Warm reset.

Arm deprecates use of this bit, and recommends that implementations ignore the request.

CWRR	Meaning
0b0	No action.
0b1	Request Warm reset.

This field is in the Core power domain

The PE ignores writes to this bit if any of the following are true:

- ExternalInvasiveDebugEnabled() == FALSE, EL3 is not implemented, and the implemented Security state is Non-secure state.
- ExternalSecureInvasiveDebugEnabled() == FALSE, EL3 is not implemented, and the implemented Security state is Secure state.
- ExternalSecureInvasiveDebugEnabled() == FALSE and EL3 is implemented.

In an implementation that includes the recommended external debug interface, this bit drives the DBGRSTREQ signal.

On a Warm reset, this field resets to 0.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus(), or OSLockStatus() or SoftwareLockStatus(), access to this field is **WI**.
- Otherwise, access to this field is **WO**.

CORENPDRQ, bit [0]

Core no powerdown request. Requests emulation of powerdown.

This request is typically passed to an external power controller. This means that whether a request causes power up is dependent on the IMPLEMENTATION DEFINED nature of the system. The power controller must not allow the Core power domain to switch off while this bit is 1.

CORENPDRQ	Meaning
0b0	If the system responds to a powerdown request, it powers down Core power domain.
0b1	If the system responds to a powerdown request, it does not powerdown the Core power domain, but instead emulates a powerdown of that domain.

When this bit reads as UNKNOWN, the PE ignores writes to this bit.

This field is in the Core power domain, and permitted accesses to this field map to the DBGPRCR.CORENPDRQ and DBGPRCR_EL1.CORENPDRQ fields.

In an implementation that includes the recommended external debug interface, this bit drives the DBGNOPWRDWN signal.

It is IMPLEMENTATION DEFINED whether this bit is reset the Cold reset value on exit from an IMPLEMENTATION DEFINED software-visible retention state. For more information about retention states see Core power domain power states.

Note

Writes to this bit are not prohibited by the IMPLEMENTATION DEFINED authentication interface. This means that a debugger can request emulation of powerdown regardless of whether invasive debug is permitted.

The following resets apply:

- On a Cold reset, this field is set to 1 if the powerup request is implemented and the powerup request has been asserted, and is set to 0 otherwise.
- On a Warm reset, the value of this field is unchanged.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus() or OSLockStatus(), access to this field is **UNKNOWN**.
- When SoftwareLockStatus(), access to this field is **RO**.
- Otherwise, access to this field is **RW**.

Otherwise:



Bits [31:4]

Reserved, RES0.

COREPURQ, bit [3]

Core powerup request. Allows a debugger to request that the power controller power up the core, enabling access to the debug register in the Core power domain, and that the power controller emulates powerdown.

This request is typically passed to an external power controller. This means that whether a request causes power up is dependent on the IMPLEMENTATION DEFINED nature of the system. The power controller must not allow the Core power domain to switch off while this bit is 1.

COREPURQ	Meaning
0b0	Do not request power up of the Core power domain.
0b1	Request power up of the Core power domain, and emulation of powerdown.

In an implementation that includes the recommended external debug interface, this bit drives the DBGPWRUPREQ signal.

This field is in the Debug power domain and can be read and written when the Core power domain is powered off.

Note

Writes to this bit are not prohibited by the IMPLEMENTATION DEFINED authentication interface. This means that a debugger can request emulation of powerdown regardless of whether invasive debug is permitted.

On a External debug reset, this field resets to 0.

Accessing this field has the following behavior:

- When SoftwareLockStatus(), access to this field is **RO**.
- Otherwise, access to this field is **RW**.

Bit [2]

Reserved, RES0.

CWRR, bit [1]

Warm reset request. Write-only bit that reads as zero.

The extent of the reset is IMPLEMENTATION DEFINED, but must be one of:

- The request is ignored.
- Only this PE is Warm reset.
- This PE and other components of the system, possibly including other PEs, are Warm reset.

Arm deprecates use of this bit, and recommends that implementations ignore the request.

CWRR	Meaning
0b0	No action.
0b1	Request Warm reset.

This field is in the Core power domain

The PE ignores writes to this bit if any of the following are true:

- ExternalInvasiveDebugEnabled() == FALSE, EL3 is not implemented, and the implemented Security state is Non-secure state.
- ExternalSecureInvasiveDebugEnabled() == FALSE, EL3 is not implemented, and the implemented Security state is Secure state.
- ExternalSecureInvasiveDebugEnabled() == FALSE and EL3 is implemented.

In an implementation that includes the recommended external debug interface, this bit drives the DBGRSTREQ signal.

On a Warm reset, this field resets to `0`.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus(), or OSLockStatus() or SoftwareLockStatus(), access to this field is **WI**.
- Otherwise, access to this field is **WO**.

CORENPDRQ, bit [0]

Core no powerdown request. Requests emulation of powerdown.

This request is typically passed to an external power controller. This means that whether a request causes power up is dependent on the IMPLEMENTATION DEFINED nature of the system. The power controller must not allow the Core power domain to switch off while this bit is 1.

CORENPDRQ	Meaning
`0b0`	If the system responds to a powerdown request, it powers down Core power domain.
`0b1`	If the system responds to a powerdown request, it does not powerdown the Core power domain, but instead emulates a powerdown of that domain.

When this bit reads as UNKNOWN, the PE ignores writes to this bit.

This field is in the Core power domain, and permitted accesses to this field map to the DBGPRCR.CORENPDRQ and DBGPRCR_EL1.CORENPDRQ fields.

In an implementation that includes the recommended external debug interface, this bit drives the DBGNOPWRDWN signal.

It is IMPLEMENTATION DEFINED whether this bit is reset to the value of EDPRCR.COREPURQ on exit from an IMPLEMENTATION DEFINED software-visible retention state. For more information about retention states see Core power domain power states.

Note

Writes to this bit are not prohibited by the IMPLEMENTATION DEFINED authentication interface. This means that a debugger can request emulation of powerdown regardless of whether invasive debug is permitted.

The following resets apply:

- On a Cold reset, this field resets to the value in EDPRCR.COREPURQ.
- On a Warm reset, the value of this field is unchanged.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus() or OSLockStatus(), access to this field is **UNKNOWN**.
- When SoftwareLockStatus(), access to this field is **RO**.
- Otherwise, access to this field is **RW**.

Accessing the EDPRCR

On permitted accesses to the register, other access controls affect the behavior of some fields. See the field descriptions for more information.

EDPRCR can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x310	EDPRCR

This interface is accessible as follows:

- When (ARMv8.3-DoPD is not implemented or IsCorePowered()) and SoftwareLockStatus() accesses to this register are **RO**.
- When (ARMv8.3-DoPD is not implemented or IsCorePowered()) and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDPRSR, External Debug Processor Status Register

The EDPRSR characteristics are:

Purpose

Holds information about the reset and powerdown state of the PE.

Configuration

EDPRSR contains fields that are in the Core power domain and fields that are in the Debug power domain.

~~Some of the fields in the Core power domain are in the Cold reset domain and others are in the Warm reset domain. See the field descriptions for more information. However:~~

- ~~Fields that are in the Cold reset domain are not affected by a warm reset and are not affected by an External debug reset.~~
- ~~Fields in the Warm reset domain are also reset by a Cold reset but are not affected by an External debug reset.~~
- ~~Fields in the Debug power domain are not affected by a Warm reset and are not affected by a Cold reset.~~

If ARMv8.3-DoPD is implemented then all fields in this register are in the Core power domain.

Attributes

EDPRSR is a 32-bit register.

Field descriptions

The EDPRSR bit assignments are:



Bits [31:12]

Reserved, RES0.

SDR, bit [11]

Sticky Debug Restart. Set to 1 when the PE exits Debug state.

Permitted values are:

SDR	Meaning
0b0	The PE has not restarted since EDPRSR was last read.
0b1	The PE has restarted since EDPRSR was last read.

Note

If a reset occurs when the PE is in Debug state, the PE exits Debug state. SDR is UNKNOWN on Warm reset, meaning a debugger must also use the SR bit to determine whether the PE has left Debug state.

If The Core power domain is powered up, then following a read of EDPRSR:

- If ARMv8.0-DoubleLock is not implemented or DoubleLockStatus() == FALSE this bit clears to 0.
- If ARMv8.0-DoubleLock is implemented and DoubleLockStatus() == TRUE, it is CONSTRAINED UNPREDICTABLE whether this bit clears to 0 or is unchanged.

This field is in the Core power domain and the Warm reset domain.

This field resets to an architecturally UNKNOWN value.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus() or EDPRSR.R == 1, access to this field is **UNKNOWN**.
- When SoftwareLockStatus(), access to this field is **RO**.
- Otherwise, access to this field is **RC**.

SPMAD, bit [10]

When ARMv8.4-Debug is implemented:

Sticky EPMAD error. Set to 1 if an external debug interface access to a Performance Monitors register returns an error because AllowExternalPMUAccess() == FALSE.

Permitted values are:

SPMAD	Meaning
0b0	No Non-secure external debug interface accesses to the external Performance Monitors registers have failed because AllowExternalPMUAccess() == FALSE for the access since EDPRSR was last read.
0b1	At least one Non-secure external debug interface access to the external Performance Monitors register has failed and returned an error because AllowExternalPMUAccess() == FALSE for the access since EDPRSR was last read.

If the Core power domain is powered up, then, following a read of EDPRSR:

- If ARMv8.0-DoubleLock is not implemented or DoubleLockStatus() == FALSE, this bit clears to 0.
- If ARMv8.0-DoubleLock is implemented, and DoubleLockStatus() == TRUE, it is CONSTRAINED UNPREDICTABLE whether this bit clears to 0 or is unchanged.

This field is in the Core power domain.

On a Cold reset, this field resets to 0.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus() or EDPRSR.R == 1, access to this field is **UNKNOWN**.
- When SoftwareLockStatus(), access to this field is **RO**.
- Otherwise, access to this field is **RC**.

Otherwise:

Sticky EPMAD error.

SPMAD	Meaning
0b0	No external debug interface accesses to the Performance Monitors registers have failed because AllowExternalPMUAccess() == FALSE since EDPRSR was last read.
0b1	At least one external debug interface access to the Performance Monitors registers has failed and returned an error because AllowExternalPMUAccess() == FALSE since EDPRSR was last read.

If the Core power domain is powered up, then, following a read of EDPRSR:

- If ARMv8.0-DoubleLock is not implemented or DoubleLockStatus() == FALSE, this bit clears to 0.
- If ARMv8.0-DoubleLock is implemented, and DoubleLockStatus() == TRUE, it is CONSTRAINED UNPREDICTABLE whether this bit clears to 0 or is unchanged.

This field is in the Core power domain.

On a Cold reset, this field resets to `0`.

Accessing this field has the following behavior:

- When !IsCorePowered(), or OSLockStatus(), or DoubleLockStatus() or EDPRSR.R == 1, access to this field is **UNKNOWN**.
- When SoftwareLockStatus(), access to this field is **RO**.
- Otherwise, access to this field is **RC**.

EPMAD, bit [9]

When ARMv8.4-Debug is implemented:

External Performance Monitors Access Disable status.

EPMAD	Meaning
`0b0`	External Non-secure Performance Monitors access enabled. AllowExternalPMUAccess() == TRUE for a Non-secure access.
`0b1`	External Non-secure Performance Monitors access disabled. AllowExternalPMUAccess() == FALSE for a Non-secure access.

This field is in the Core power domain.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus() or EDPRSR.R == 1, access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

Otherwise:

External Performance Monitors access disable status.

EPMAD	Meaning
`0b0`	External Performance Monitors access enabled. AllowExternalPMUAccess() == TRUE.
`0b1`	External Performance Monitors access disabled. AllowExternalPMUAccess() == FALSE.

This field is in the Core power domain.

Accessing this field has the following behavior:

- When !IsCorePowered(), or OSLockStatus(), or DoubleLockStatus() or EDPRSR.R == 1, access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

SDAD, bit [8]

When ARMv8.4-Debug is implemented:

Sticky EDAD error. Set to 1 if an external debug interface access to a debug register returns an error because AllowExternalDebugAccess() == FALSE.

SDAD	Meaning
`0b0`	No Non-secure external debug interface accesses to the debug registers have failed because AllowExternalDebugAccess() == FALSE for the access since EDPRSR was last read.
`0b1`	At least one Non-secure external debug interface access to the debug registers has failed and returned an error because AllowExternalDebugAccess() == FALSE for the access since EDPRSR was last read.

If the Core power domain is powered up, then, following a read of EDPRSR:

- If ARMv8.0-DoubleLock is not implemented or DoubleLockStatus() == FALSE this bit clears to 0.
- If ARMv8.0-DoubleLock is implemented and DoubleLockStatus() == TRUE, it is CONSTRAINED UNPREDICTABLE whether this bit clears to 0 or is unchanged.

This field is in the Core power domain.

On a Cold reset, this field resets to `0`.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus() or EDPRSR.R == 1, access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

Otherwise:

Sticky EDAD error. Set to 1 if an external debug interface access to a debug register returns an error because AllowExternalDebugAccess() == FALSE.

SDAD	Meaning
`0b0`	No external debug interface accesses to the debug registers have failed because AllowExternalDebugAccess() == FALSE since EDPRSR was last read.
`0b1`	At least one external debug interface access to the debug registers has failed and returned an error because AllowExternalDebugAccess() == FALSE since EDPRSR was last read.

If the Core power domain is powered up, then, following a read of EDPRSR:

- If ARMv8.0-DoubleLock is not implemented or DoubleLockStatus() == FALSE this bit clears to 0.
- If ARMv8.0-DoubleLock is implemented and DoubleLockStatus() == TRUE, it is CONSTRAINED UNPREDICTABLE whether this bit clears to 0 or is unchanged.

This bit is UNKNOWN on reads if OSLockStatus() == TRUE and external debug writes to OSLAR_EL1 do not return an error when AllowExternalDebugAccess() == FALSE.

This field is in the Core power domain.

On a Cold reset, this field resets to `0`.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus() or EDPRSR.R == 1, access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

EDAD, bit [7]

When ARMv8.4-Debug is implemented:

External Debug Access Disable status.

EDAD	Meaning
`0b0`	External Non-secure access to breakpoint registers, watchpoint registers, and OSLAR_EL1 enabled. AllowExternalDebugAccess() == TRUE for a Non-secure access.
`0b1`	External Non-secure access to breakpoint registers, watchpoint registers, and OSLAR_EL1 disabled. AllowExternalDebugAccess() == FALSE for a Non-secure access.

This field is in the Core power domain.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus() or EDPRSR.R == 1, access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

When ARMv8.2-Debug is implemented:

External Debug Access Disable status.

EDAD	Meaning
0b0	External access to breakpoint registers, watchpoint registers, and OSLAR_EL1 enabled. AllowExternalDebugAccess() == TRUE.
0b1	External access to breakpoint registers, watchpoint registers, and OSLAR_EL1 disabled. AllowExternalDebugAccess() == FALSE.

This bit is not valid and reads UNKNOWN if OSLockStatus() == TRUE and external debug writes to OSLAR_EL1 do not return an error when AllowExternalDebugAccess() == FALSE.

This field is in the Core power domain.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus() or EDPRSR.R == 1, access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

Otherwise:

External Debug Access Disable status.

EDAD	Meaning
0b0	External access to breakpoint registers, watchpoint registers, and OSLAR_EL1 enabled. AllowExternalDebugAccess() == TRUE.
0b1	External access to breakpoint registers, watchpoint registers disabled. It is IMPLEMENTATION DEFINED whether accesses to OSLAR_EL1 are enabled or disabled. AllowExternalDebugAccess() == FALSE.

This field is in the Core power domain.

Accessing this field has the following behavior:

- When !IsCorePowered(), or DoubleLockStatus() or EDPRSR.R == 1, access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

DLK, bit [6]

When ARMv8.4-Debug is implemented:

This field is RES0.

When ARMv8.2-Debug is implemented and ARMv8.0-DoubleLock is implemented:

Double Lock.

From Armv8.2, this field is deprecated.

This field is in the Core power domain.

Accessing this field has the following behavior:

- When IsCorePowered() and !DoubleLockStatus(), access to this field is **RAZ**.
- Otherwise, access to this field is **UNKNOWN**.

When ARMv8.0-DoubleLock is implemented:

Double Lock.

This field returns the result of the pseudocode function DoubleLockStatus().

If the Core power domain is powered up and DoubleLockStatus() == TRUE, it is IMPLEMENTATION DEFINED whether:

- EDPRSR.PU reads as 1, EDPRSR.DLK reads as 1, and EDPRSR.SPD is UNKNOWN.
- EDPRSR.PU reads as 0, EDPRSR.DLK is UNKNOWN, and EDPRSR.SPD reads as 0.

This field is in the Core power domain.

DLK	Meaning
0b0	DoubleLockStatus() returns FALSE.
0b1	DoubleLockStatus() returns TRUE and the Core power domain is powered up.

Accessing this field has the following behavior:

- When !IsCorePowered(), access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

Otherwise:

Reserved, RES0.

OSLK, bit [5]

OS Lock status bit.

A read of this bit returns the value of OSLSR_EL1.OSLK.

This field is in the Core power domain.

Accessing this field has the following behavior:

- When !IsCorePowered(), DoubleLockStatus() and EDPRSR.R == 1, access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

HALTED, bit [4]

Halted status bit.

HALTED	Meaning
0b0	PE is in Non-debug state.
0b1	PE is in Debug state.

This field is in the Core power domain.

Accessing this field has the following behavior:

- When !IsCorePowered(), access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

SR, bit [3]

Sticky core Reset status bit.

Permitted values are:

SR	Meaning
0b0	The non-debug logic of the PE is not in reset state and has not been reset since the last time EDPRSR was read.
0b1	The non-debug logic of the PE is in reset state or has been reset since the last time EDPRSR was read.

If EDPRSR.PU reads as 1 and EDPRSR.R reads as 0, which means that the Core power domain is in a powerup state and that the non-debug logic of the PE is not in reset state, then following a read of EDPRSR:

- If ARMv8.0-DoubleLock is not implemented or DoubleLockStatus() == FALSE this bit clears to 0.
- If ARMv8.0-DoubleLock is implemented and DoubleLockStatus() == TRUE, it is UNPREDICTABLE whether this bit clears to 0 or is unchanged.

This field is in the Core power domain and the Warm reset domain.

This field resets to 1.

Accessing this field has the following behavior:

- When !IsCorePowered() or DoubleLockStatus(), access to this field is **UNKNOWN**.
- When SoftwareLockStatus(), access to this field is **RO**.
- Otherwise, access to this field is **RC**.

R, bit [2]

PE Reset status bit.

Permitted values are:

R	Meaning
0b0	The non-debug logic of the PE is not in reset state.
0b1	The non-debug logic of the PE is in reset state.

If ARMv8.0-DoubleLock is implemented, the PE is in reset state, and the PE entered reset state with the OS Double Lock locked this bit has a CONSTRAINED UNPREDICTABLE value. For more information see 'EDPRSR.{DLK, R} and reset state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H6 (Debug Reset and Powerdown Support)

This field is in the Core power domain.

Accessing this field has the following behavior:

- When !IsCorePowered() or DoubleLockStatus(), access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

SPD, bit [1]

Sticky core Powerdown status bit.

If ARMv8.0-DoubleLock is implemented and DoubleLockStatus() == TRUE, then:

- If ARMv8.2-Debug is implemented, this bit reads as 0.
- If ARMv8.2-Debug is not implemented, this bit might read as 0 or 1.

For more information, see EDPRSR.{DLK, SPD, PU} and the Core power domain.

SPD	Meaning
0b0	If EDPRSR.PU is 0, it is not known whether the state of the debug registers in the Core power domain is lost. If EDPRSR.PU is 1, the state of the debug registers in the Core power domain has not been lost.
0b1	The state of the debug registers in the Core power domain has been lost.

If the Core power domain is powered up, then, following a read of EDPRSR:

- If ARMv8.0-DoubleLock is not implemented or DoubleLockStatus() == FALSE this bit clears to 0.
- If ARMv8.0-DoubleLock is implemented and DoubleLockStatus() == TRUE, it is CONSTRAINED UNPREDICTABLE whether this bit clears to 0 or is unchanged.

When the Core power domain is in either retention or powerdown state, the value of EDPRSR.SPD is IMPLEMENTATION DEFINED. For more information, see 'EDPRSR.SPD when the Core domain is in either retention or powerdown state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H6 (Debug Reset and Powerdown Support).

EDPRSR.{DLK, SPD, PU} describe whether registers in the Core power domain can be accessed, and whether their state has been lost since the last time the register was read. For more information, see 'EDPRSR.{DLK, SPD, PU} bits

record accessibility and lost of state in Core power domain' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H6 (Debug Reset and Powerdown Support).

This field is in the Core power domain and the Cold reset domain.

On a Cold reset, this field resets to 1.

Accessing this field has the following behavior:

- When !IsCorePowered(), access to this field is **RAZ**.
- When IsCorePowered() and DoubleLockStatus(), access to this field is **UNKNOWN**.
- Otherwise, access to this field is **RO**.

PU, bit [0]

When ARMv8.3-DoPD is implemented:

Core powerup status bit.

Access to this field is **RAO**.

When ARMv8.2-Debug is implemented:

Core Powerup status bit. Indicates whether the debug registers in the Core power domain can be accessed.

PU	Meaning
0b0	Either the Core power domain is in a low-power or powerdown state, or ARMv8.0-DoubleLock is implemented and DoubleLockStatus() == TRUE, meaning the debug registers in the Core power domain cannot be accessed.
0b1	The Core power domain is in a powerup state, and either ARMv8.0-DoubleLock is not implemented or DoubleLockStatus() == FALSE, meaning the debug registers in the Core power domain can be accessed.

If ARMv8.0-DoubleLock is implemented, the PE is in reset state, and the PE entered reset state with the OS Double Lock locked this bit has a CONSTRAINED UNPREDICTABLE value. For more information see 'EDPRSR.{DLK, R} and reset state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H6 (Debug Reset and Powerdown Support)

EDPRSR.{DLK, SPD, PU} describe whether registers in the Core power domain can be accessed, and whether their state has been lost since the last time the register was read. For more information, see 'EDPRSR.{DLK, SPD, PU} bits record accessibility and lost of state in Core power domain' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H6 (Debug Reset and Powerdown Support)

Access to this field is **RO**.

Otherwise:

Core Powerup status bit. Indicates whether the debug registers in the Core power domain can be accessed.

When the Core power domain is powered-up and DoubleLockStatus() == TRUE, then the value of EDPRSR.PU is IMPLEMENTATION DEFINED. See the description of the DLK bit for more information.

Otherwise, permitted values are:

PU	Meaning
0b0	Core power domain is in a low-power or powerdown state where the debug registers in the Core power domain cannot be accessed.
0b1	Core power domain is in a powerup state where the debug registers in the Core power domain can be accessed.

If ARMv8.0-DoubleLock is implemented, the Core power domain is powered up, and DoubleLockStatus() == TRUE, it is IMPLEMENTATION DEFINED whether this bit reads as 0 or 1.

If ARMv8.0-DoubleLock is implemented, the PE is in reset state, and the PE entered reset state with the OS Double Lock locked this bit has a CONSTRAINED UNPREDICTABLE value. For more information see 'EDPRSR.{DLK, R} and reset

state' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H6 (Debug Reset and Powerdown Support)

EDPRSR.{DLK, SPD, PU} describe whether registers in the Core power domain can be accessed, and whether their state has been lost since the last time the register was read. For more information, see 'EDPRSR.{DLK, SPD, PU} bits record accessibility and lost of state in Core power domain' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H6 (Debug Reset and Powerdown Support)

Access to this field is **RO**.

Accessing the EDPRSR

On permitted accesses to the register, other access controls affect the behavior of some fields. See the field descriptions for more information.

If the Core power domain is powered up (EDPRSR.PU == 1), then following a read of EDPRSR:

- If ARMv8.0-DoubleLock is not implemented or DoubleLockStatus() == FALSE, then:
  - EDPRSR.{SDR, SPMAD, SDAD, SPD} are cleared to 0.
  - EDPRSR.SR is cleared to 0 if the non-debug logic of the PE is not in reset state (EDPRSR.R == 0).
- Otherwise it is CONSTRAINED UNPREDICTABLE whether or not this clearing occurs.

If the Core power domain is powered down (EDPRSR.PU == 0), then:

- EDPRSR.{SDR, SPMAD, SDAD, SR} are all UNKNOWN, and are either reset or restored on being powered up.
- EDPRSR.SPD is not cleared following a read of EDPRSR. See the SPD bit description for more information.

The clearing of bits is an indirect write to EDPRSR.

EDPRSR can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x314	EDPRSR

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDSCR, External Debug Status and Control Register

The EDSCR characteristics are:

Purpose

Main control register for the debug implementation.

Configuration

External register EDSCR bits [30:29] are architecturally mapped to AArch64 System register MDCCSR_EL0[30:29] .

EDSCR is in the Core power domain. ~~Some or all RW fields of this register have defined reset values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

Attributes

EDSCR is a 32-bit register.

Field descriptions

The EDSCR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13:12	11:10	9	8	7	6	5:4	3:2	1:0
TFO	RXfull	TXfull	ITO	RXO	TXU	PipeAdv	ITE	INTdis		TDA	MA	SC2	NS	RES0	SDD	RES0	HDE	RW		EL	A		ERR	STATUS		

TFO, bit [31]

When ARMv8.4-Trace is implemented:

Trace Filter Override. Overrides the Trace Filter controls allowing the external debugger to trace any visible Exception level.

TFO	Meaning
0b0	Trace Filter controls are not affected.
0b1	Trace Filter controls in TRFCR_EL1, TRFCR_EL2 are ignored.~~, TRFCR, and HTRFCR are ignored.~~ Trace Filter controls TRFCR and HTRFCR are ignored.

When OSLSR_EL1.OSLK == 1, this bit can be indirectly read and written through the MDSCR_EL1 and DBGDSCRext System registers.

This bit is ignored by the PE when ExternalSecureNoninvasiveDebugEnabled() == FALSE and the Effective value of MDCR_EL3.STE == 1.

On a Cold reset, this field resets to 0.

Otherwise:

Reserved, RES0.

RXfull, bit [30]

DTRRX full.

On a Cold reset, this field resets to 0.

Access to this field is **RO**.

TXfull, bit [29]

DTRTX full.

On a Cold reset, this field resets to `0`.

Access to this field is **RO**.

ITO, bit [28]

ITR overrun.

If the PE is in Non-debug state, this bit is UNKNOWN. ITO is set to 0 on entry to Debug state.

Access to this field is **RO**.

RXO, bit [27]

DTRRX overrun.

On a Cold reset, this field resets to `0`.

Access to this field is **RO**.

TXU, bit [26]

DTRTX underrun.

On a Cold reset, this field resets to `0`.

Access to this field is **RO**.

PipeAdv, bit [25]

Pipeline advance. Set to 1 every time the PE pipeline retires one or more instructions. Cleared to 0 by a write to EDRCR.CSPA.

The architecture does not define precisely when this bit is set to 1. It requires only that this happen periodically in Non-debug state to indicate that software execution is progressing.

Access to this field is **RO**.

ITE, bit [24]

ITR empty.

If the PE is in Non-debug state, this bit is UNKNOWN. It is always valid in Debug state.

Access to this field is **RO**.

INTdis, bits [23:22]

When ARMv8.4-Debug is implemented:

Interrupt disable. Disables taking interrupts in Non-Debug state.

INTdis	Meaning
0b0	Masking of interrupts is controlled by PSTATE and interrupt routing controls.
0b1	If ExternalSecureDebugEnabled() == TRUE, then all interrupts, including virtual and SError interrupts, are masked. If ExternalSecureDebugEnabled() == FALSE, then all interrupts targetting Non-secure state are masked.

When OSLSR_EL1.OSLK == 1, this field can be indirectly read and written through the MDSCR_EL1 and DBGDSCRext System registers.

This field is ignored by the PE and treated as zero when ExternalDebugEnabled() == FALSE.

On a Cold reset, this field resets to 0.

Otherwise:

Interrupt disable.

When OSLSR_EL1.OSLK == 1, this field can be indirectly read and written through the MDSCR_EL1 and DBGDSCRext System registers.

INTdis	Meaning
0b00	Do not disable interrupts.
0b01	Disable interrupts taken to Non-secure EL1.
0b10	Disable interrupts taken only to Non-secure EL1 and Non-secure EL2. If ExternalSecureInvasiveDebugEnabled() == TRUE, also disable interrupts taken to Secure EL1.
0b11	Disable interrupts taken only to Non-secure EL1 and Non-secure EL2. If ExternalSecureInvasiveDebugEnabled() == TRUE, also disable all other interrupts.

On a Cold reset, this field resets to 0.

TDA, bit [21]

Traps accesses to the following debug System registers:

- AArch64: DBGBCR<n>_EL1, DBGBVR<n>_EL1, DBGWCR<n>_EL1, DBGWVR<n>_EL1.
- AArch32: DBGBCR<n>, DBGBVR<n>, DBGBXVR<n>, DBGWCR<n>, DBGWVR<n>.

The possible values of this field are:

TDA	Meaning
0b0	Accesses to debug System registers do not generate a Software Access Debug event.
0b1	Accesses to debug System registers generate a Software Access Debug event, if OSLSR_EL1.OSLK is 0 and if halting is allowed.

On a Cold reset, this field resets to 0.

MA, bit [20]

Memory access mode. Controls the use of memory-access mode for accessing ITR and the DCC. This bit is ignored if in Non-debug state and set to zero on entry to Debug state.

Possible values of this field are:

MA	Meaning
0b0	Normal access mode.
0b1	Memory access mode.

On a Cold reset, this field resets to 0.

SC2, bit [19]

When ARMv8.0-PCSample is implemented, (ARMv8.1-VHE is implemented or ARMv8.2-Debug is implemented) and ARMv8.2-PCSample is not implemented:

Sample CONTEXTIDR_EL2. Controls whether the PC Sample-based Profiling Extension samples CONTEXTIDR_EL2 or VTTBR_EL2.VMID.

SC2	Meaning
0b0	Sample VTTBR_EL2.VMID.
0b1	Sample CONTEXTIDR_EL2.

On a Cold reset, this field resets to 0.

Otherwise:

Reserved, RES0.

NS, bit [18]

Non-secure status. When in Debug state, gives the current Security state:

NS	Meaning
0b0	Secure state, IsSecure() == TRUE.
0b1	Non-secure state, IsSecure() == FALSE.

In Non-debug state, this bit is UNKNOWN.

Access to this field is **RO**.

Bit [17]

Reserved, RES0.

SDD, bit [16]

Secure debug disabled.

On entry to Debug state:

- If entering in Secure state, SDD is set to 0.
- If entering in Non-secure state, SDD is set to the inverse of ExternalSecureInvasiveDebugEnabled().

In Debug state, the value of the SDD bit does not change, even if ExternalSecureInvasiveDebugEnabled() changes.

In Non-debug state:

- SDD returns the inverse of ExternalSecureInvasiveDebugEnabled(). If the authentication signals that control ExternalSecureInvasiveDebugEnabled() change, a context synchronization event is required to guarantee their effect.
- This bit is unaffected by the Security state of the PE.

If EL3 is not implemented and the implementation is Non-secure, this bit is RES1.

Access to this field is **RO**.

Bit [15]

Reserved, RES0.

HDE, bit [14]

Halting debug enable. The possible values of this field are:

HDE	Meaning
0b0	Halting disabled for Breakpoint, Watchpoint and Halt Instruction debug events.
0b1	Halting enabled for Breakpoint, Watchpoint and Halt Instruction debug events.

On a Cold reset, this field resets to 0.

RW, bits [13:10]

Exception level Execution state status. In Debug state, each bit gives the current Execution state of each Exception level.~~level:~~

RW	Meaning	Applies when
0b1111	All Exception levels are using AArch64 or the PE is in Non-debug state.	
0b1110	The PE is in Debug state. EL0 is using AArch32. All other Exception levels are using AArch64. Only permitted if the PE is executing at EL0.	When AArch32 is supported at any Exception level
0b110x	The PE is in Debug state. EL0 and EL1 are using AArch32. EL2 and EL3 are using AArch64. Only permitted if EL2 is implemented and enabled in the current Security state.	When AArch32 is supported at any Exception level
0b10xx	The PE is in Debug state. EL0, EL1, and, if implemented in the current Security state, EL2 are using AArch32. EL3 is using AArch64. ~~Only permitted if EL3 is implemented.~~	When AArch32 is supported at any Exception level and EL3 is implemented
0b0xxx	The PE is in Debug state. All Exception levels are using AArch32.	

In Non-debug state, this field is RAO.

Access to this field is **RO**.

EL, bits [9:8]

Exception level. In Debug state, this gives the current Exception level~~EL~~ of the PE.

In Non-debug state, this field is RAZ.

Access to this field is **RO**.

A, bit [7]

SError interrupt pending. In Debug state, indicates whether an SError interrupt is pending:

- If HCR_EL2.{AMO, TGE} = {1, 0}, EL2 is enabled in the current Security state, and the PE is executing at EL0 or EL1, a virtual SError interrupt.
- Otherwise, a physical SError interrupt.

A	Meaning
0b0	No SError interrupt pending.
0b1	SError interrupt pending.

A debugger can read EDSCR to check whether an SError interrupt is pending without having to execute further instructions. A pending SError might indicate data from target memory is corrupted.

UNKNOWN in Non-debug state.

Access to this field is **RO**.

ERR, bit [6]

Cumulative error flag. This bit is set to 1 following exceptions in Debug state and on any signaled overrun or underrun on the DTR or EDITR.

On a Cold reset, this field resets to `0`.

Access to this field is **RO**.

STATUS, bits [5:0]

Debug status flags.

STATUS	Meaning
`0b000001`	PE is restarting, exiting Debug state.
`0b000010`	PE is in Non-debug state.
`0b000111`	Breakpoint.
`0b010011`	External debug request.
`0b011011`	Halting step, normal.
`0b011111`	Halting step, exclusive.
`0b100011`	OS Unlock Catch.
`0b100111`	Reset Catch.
`0b101011`	Watchpoint.
`0b101111`	HLT instruction.
`0b110011`	Software access to debug register.
`0b110111`	Exception Catch.
`0b111011`	Halting step, no syndrome.

All other values of STATUS are reserved.

Access to this field is **RO**.

Accessing the EDSCR

EDSCR can be accessed through the external debug interface:

Component	Offset	Instance
Debug	`0x088`	EDSCR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDVIDSR, External Debug Virtual Context Sample Register

The EDVIDSR characteristics are:

Purpose

Contains sampled values captured on reading EDPCSR[31:0].

Configuration

EDVIDSR is in the Core power domain.

~~EDVIDSR is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

This register is present only when ARMv8.0-PCSample is implemented and ARMv8.2-PCSample is not implemented. Otherwise, direct accesses to EDVIDSR are RES0.

Implemented only if the OPTIONAL PC Sample-based Profiling Extension is implemented in the external debug registers space.

When the PC Sample-based Profiling Extension is implemented in the external debug registers space, if EL2 is not implemented and EL3 is not implemented, it is IMPLEMENTATION DEFINED whether EDVIDSR is implemented.

Note

ARMv8.2-PCSample implements the PC Sample-based Profiling Extension in the Performance Monitors registers space.

Attributes

If ARMv8.1-VHE is implemented, the format of this register differs depending on the value of EDSCR.SC2.

Field descriptions

The EDVIDSR bit assignments are:

When ARMv8.1-VHE is not implemented or EDSCR.SC2 == 0:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
NS	E2	E3	HV	RES0												VMID[15:8]								VMID							

This format applies in all Armv8.0 implementations.

NS, bit [31]

Non-secure state sample. Indicates the Security state associated with the most recent EDPCSR sample.

If EL3 is not implemented, this bit indicates the Effective value of SCR.NS.

NS	Meaning
0b0	Sample is from Secure state.
0b1	Sample is from Non-secure state.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

E2, bit [30]

When ~~HaveEL(~~EL2 is implemented~~):~~

Exception level 2 status sample. Indicates whether the most recent EDPCSR sample was associated with EL2.

E2	Meaning
0b0	Sample is not from EL2.
0b1	Sample is from EL2.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

E3, bit [29]

When ~~HaveEL(~~EL3~~)~~ is implemented and the highest implemented Exception level is using AArch64 state:~~!HighestELUsingAArch32():~~

Exception level 3 status sample. Indicates whether the most recent EDPCSR sample was associated with EL3 using AArch64.

E3	Meaning
0b0	Sample is not from EL3 using AArch64.
0b1	Sample is from EL3 using AArch64.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

HV, bit [28]

EDPCSRhi (EDPCSR[63:32]) valid. Indicates whether bits [63:32] of the most recent EDPCSR sample might be nonzero:

HV	Meaning
0b0	Bits[63:32] of the most recent EDPCSR sample are zero.
0b1	Bits[63:32] of the most recent EDPCSR sample might be nonzero.

An EDVIDSR.HV value of 1 does not mean that the value of EDPCSRhi is nonzero. An EDVIDSR.HV value of 0 is a hint that EDPCSRhi (EDPCSR[63:32]) does not need to be read.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [27:16]

Reserved, RES0.

VMID[15:8], bits [15:8]

When ARMv8.1-VMID16 is implemented and ~~HaveEL(~~EL2 is implemented~~):~~

Extension to VMID[7:0]. See VMID[7:0] for more details.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

VMID, bits [7:0]

When ~~HaveEL(~~EL2 is implemented~~):~~

VMID sample. The VMID associated with the most recent EDPCSRlo (EDPCSR[31:0]) sample. When the most recent EDPCSR sample was generated:

- This field is RES0 if any of the following apply:
  - The PE is executing in Secure state.
  - The PE is executing at EL2.
- Otherwise:
  - If EL2 is using AArch64 and either ARMv8.1-VMID16 is not implemented or VTCR_EL2.VS is 1, this field is set to VTTBR_EL2.VMID.
  - If EL2 is using AArch64, ARMv8.1-VMID16 is implemented, and VTCR_EL2.VS is 0, PMVIDSR.VMID[7:0] is set to VTTBR_EL2.VMID[7:0] and PMVIDSR.VMID[15:8] is RES0.
  - If EL2 is using AArch32, this field is set to VTTBR.VMID.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

When (ARMv8.1-VHE is implemented or ARMv8.2-Debug is implemented) and EDSCR.SC2 == 1:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
CONTEXTIDR_EL2																															

CONTEXTIDR_EL2, bits [31:0]

Context ID. The value of CONTEXTIDR_EL2 that is associated with the most recent EDPCSR sample. When the most recent EDPCSR sample was generated:

- If EL2 was using AArch64 and the PE was executing in Non-secure state, then this field is set to the Context ID sampled from CONTEXTIDR_EL2.
- If EL2 was using AArch32 or the PE was executing in Secure state, then this field is set to an UNKNOWN value.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the EDVIDSR

IMPLEMENTATION DEFINED extensions to external debug might make the value of this register UNKNOWN, see 'Permitted behavior that might make the PC Sample-based profiling registers UNKNOWN' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile

EDVIDSR can be accessed through the external debug interface:

Component	Offset	Instance
Debug	0x0A8	EDVIDSR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

EDWAR, External Debug Watchpoint Address Register

The EDWAR characteristics are:

Purpose

Returns the virtual data address being accessed when a Watchpoint Debug Event was triggered.

Configuration

EDWAR is in the Core power domain.

~~EDWAR is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

Attributes

EDWAR is a 64-bit register.

Field descriptions

The EDWAR bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Watchpoint address																															
Watchpoint address																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Watchpoint address. The data virtual address being accessed when a Watchpoint Debug Event was triggered and caused entry to Debug state. This address must be within a naturally-aligned block of memory of power-of-two size no larger than the DC ZVA block size.

The value of this register is UNKNOWN if the PE is in Non-debug state, or if Debug state was entered other than for a Watchpoint debug event.

The value of EDWAR[63:32] is UNKNOWN if Debug state was entered for a Watchpoint debug event taken from AArch32 state.

The EDWAR is subject to the same alignment rules as the reporting of a watchpointed address in the FAR. See 'Determining the memory location that caused a Watchpoint exception' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section D2 (AArch64 Self-hosted Debug)

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the EDWAR

EDWAR can be accessed through the external debug interface:

Component	Offset	Instance	Range
Debug	0x030	EDWAR	31:0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.

- Otherwise accesses to this register generate an error response.

Component	Offset	Instance	Range
Debug	0x034	EDWAR	63:32

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRCIDR0, Component Identification Register 0

The ERRCIDR0 characteristics are:

Purpose

Provides discovery information aboutfor the component.

For more information, see 'About the Peripheral identification scheme'.

Configuration

Implementation of this register is OPTIONAL.

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRCIDR0 are RES0.

Attributes

ERRCIDR0 is a 32-bit register.

Field descriptions

The ERRCIDR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								PRMBL_0							

Bits [31:8]

Reserved, RES0.

PRMBL_0, bits [7:0]

Component identification preamble, segment 0.

Component identification preamble, segment 0. This field reads as 0x0D.

This field reads as 0x0D.

Accessing the ERRCIDR0

ERRCIDR0 can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	0xFF0

Component	Offset	Instance
RAS	0xFF0	ERRCIDR0

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRCIDR1, Component Identification Register 1

The ERRCIDR1 characteristics are:

Purpose

Provides discovery information aboutfor the component.

For more information, see 'About the Peripheral identification scheme'.

Configuration

Implementation of this register is OPTIONAL.

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRCIDR1 are RES0.

Attributes

ERRCIDR1 is a 32-bit register.

Field descriptions

The ERRCIDR1 bit assignments are:



Bits [31:8]

Reserved, RES0.

CLASS, bits [7:4]

Component class.

CLASS	Meaning
0b1111	Generic peripheral with IMPLEMENTATION DEFINED register layout.

This field reads as 0xF.

Other values are defined by the CoreSight Architecture.

This field reads as 0xF.

PRMBL_1, bits [3:0]

Component identification preamble, segment 1.

Component identification preamble, segment 1. This field reads as 0x0.

This field reads as 0x0.

Accessing the ERRCIDR1

ERRCIDR1 can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	0xFF4

Component	Offset	Instance
RAS	0xFF4	ERRCIDR1

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRCIDR2, Component Identification Register 2

The ERRCIDR2 characteristics are:

Purpose

Provides discovery information aboutfor the component.

For more information, see 'About the Peripheral identification scheme'.

Configuration

Implementation of this register is OPTIONAL.

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRCIDR2 are RES0.

Attributes

ERRCIDR2 is a 32-bit register.

Field descriptions

The ERRCIDR2 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								PRMBL_2							

Bits [31:8]

Reserved, RES0.

PRMBL_2, bits [7:0]

Component identification preamble, segment 2.

Component identification preamble, segment 2. This field reads as 0x05.

This field reads as 0x05.

Accessing the ERRCIDR2

ERRCIDR2 can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	0xFF8

Component	Offset	Instance
RAS	0xFF8	ERRCIDR2

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRCIDR3, Component Identification Register 3

The ERRCIDR3 characteristics are:

Purpose

Provides discovery information aboutfor the component.

For more information, see 'About the Peripheral identification scheme'.

Configuration

Implementation of this register is OPTIONAL.

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRCIDR3 are RES0.

Attributes

ERRCIDR3 is a 32-bit register.

Field descriptions

The ERRCIDR3 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								PRMBL_3							

Bits [31:8]

Reserved, RES0.

PRMBL_3, bits [7:0]

Component identification preamble, segment 3.

Component identification preamble, segment 3. This field reads as 0xB1.

This field reads as 0xB1.

Accessing the ERRCIDR3

ERRCIDR3 can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	0xFFC

Component	Offset	Instance
RAS	0xFFC	ERRCIDR3

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRCRICR0, Critical Error Interrupt Configuration Register 0

The ERRCRICR0 characteristics are:

Purpose

Interrupt configuration register.

Configuration

External register ERRCRICR0 is architecturally mapped to External register ERRIRQCR4.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERRCRICR0 are RES0.

Present only if interrupt configuration registers use the recommended format. Otherwise, this register is RES0.

Attributes

ERRCRICR0 is a 64-bit register.

Field descriptions

The ERRCRICR0 bit assignments are:



Bits [63:56]

Reserved, RES0.

ADDR, bits [55:2]

Message Signaled Interrupt address.

Specifies the address that the component writes to when signaling an interrupt.

The size of a physical address is IMPLEMENTATION DEFINED. Unimplemented high-order physical address bits are RES0.

The following resets apply:

- On ana~~a~~ Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [1:0]

Reserved, RES0.

Accessing the ERRCRICR0

ERRCRICR0 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0xEA0	ERRCRICR0

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRCRICR1, Critical Error Interrupt Configuration Register 1

The ERRCRICR1 characteristics are:

Purpose

Interrupt configuration register.

Configuration

External register ERRCRICR1 bits [31:0] are architecturally mapped to External register ERRIRQCR5[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERRCRICR1 are RES0.

Present only if interrupt configuration registers use the recommended format. Otherwise, this register is RES0.

Attributes

ERRCRICR1 is a 32-bit register.

Field descriptions

The ERRCRICR1 bit assignments are:



DATA, bits [31:0]

Payload for a message signaled interrupt.

The following resets apply:

- On ana~~a~~ Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the ERRCRICR1

ERRCRICR1 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0xEA8	ERRCRICR1

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRCRICR2, Critical Error Interrupt Configuration Register 2

The ERRCRICR2 characteristics are:

Purpose

Interrupt configuration register.

Configuration

External register ERRCRICR2 bits [31:0] are architecturally mapped to External register ERRIRQCR5[63:32] .

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERRCRICR2 are RES0.

Present only if interrupt configuration registers use the recommended format. Otherwise, this register is RES0.

Attributes

ERRCRICR2 is a 32-bit register.

Field descriptions

The ERRCRICR2 bit assignments are:



Bits [31:8]

Reserved, RES0.

IRQEN, bit [7]

Message Signaled Interrupt enable.

Enables generation of message signaled interrupts.

IRQEN	Meaning
0b0	Message signaled interrupts are disabled.
0b1	Message signaled interrupts are enabled.

If the component does not support disabling message signaled interrupts, this bit is RES0.

The following resets apply:

- On ana~~a~~ Error recovery reset, this field resets to 0.
- On a Cold reset, this field resets to 0.

NSMSI, bit [6]

Security attribute.

Defines the physical address space for message signaled interrupts.

NSMSI	Meaning
0b0	Physical address space for message signaled interrupts is Secure.
0b1	Physical address space for message signaled interrupts is Non-secure.

If the component prohibits Non-secure writes and does not support configuring the Security attribute, then the Security attribute for message signaled interrupts is IMPLEMENTATION DEFINED.

If the component allows Non-secure writes, then the Security attribute used for message signaled interrupts is Non-secure.

This bit is RES0 if any of the following are true:

- The component allows Non-secure writes.
- The component does not support configuring the Security attribute.

On a Cold reset, this field resets to an IMPLEMENTATION DEFINED value.

SH, bits [5:4]

Shareability.

Defines the Shareability domain for message signaled interrupts.

SH	Meaning
0b00	Message signaled interrupts are in the Not shared Shareability domain.
0b10	Message signaled interrupts are in the Outer Shareable Shareability domain.
0b11	Message signaled interrupts are in the Inner Shareable Shareability domain.

If the component does not support configuring the Shareability domain, this field is RES0, meaning the Shareability domain for message signaled interrupts is IMPLEMENTATION DEFINED.

The following resets apply:

- On ana Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

MemAttr, bits [3:0]

Memory type.

Defines the memory type for message signaled interrupts. The values which correspond to each memory type are:

MemAttr	Meaning
0b0000	Device-nGnRnE.
0b0001	Device-nGnRE.
0b0010	Device-nGRE.
0b0011	Device-GRE.
0b0101	Outer Non-cacheable, Inner Non-cacheable.
0b0110	Outer Non-cacheable, Inner Write-Through Cacheable.
0b0111	Outer Non-cacheable, Inner Write-Back Cacheable.
0b1001	Outer Write-Through Cacheable, Inner Non-cacheable.
0b1010	Outer Write-Through Cacheable, Inner Write-Through Cacheable.
0b1011	Outer Write-Through Cacheable, Inner Write-Back Cacheable.
0b1101	Outer Write-Back Cacheable, Inner Non-cacheable.
0b1110	Outer Write-Back Cacheable, Inner Write-Through Cacheable.
0b1111	Outer Write-Back Cacheable, Inner Write-Back Cacheable.

If the component does not support configuring the memory type, this field is RES0, meaning the memory type used for message signaled interrupts is IMPLEMENTATION DEFINED.

Note

This is the same format as the VMSAv8-64 stage 2 memory region attributes.

The following resets apply:

- On ana Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the ERRCRICR2

ERRCRICR2 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0xEAC	ERRCRICR2

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRDEVAFF, Device Affinity Register

The ERRDEVAFF characteristics are:

Purpose

IfFor RAS System Architecture v1.1 is not implemented, a group of error records that ishas associated with a PE or group or PEs must have affinity with either a single PE or allcluster theof PEs, atERRDEVAFF anis affinitya level.copy ofMPIDR_EL1 or part of MPIDR_EL1:

For a group of error records that has affinity with a single PE or a group of PEs, ERRDEVAFF is a copy of MPIDR_EL1 or part of MPIDR_EL1:

- If the group of error records has affinity with a single PE, the affinity level is 0, ERRDEVAFF reads the same value as MPIDR_EL1, and ERRDEVAFF.F0V reads-as-one to indicate affinity level 0.
- If the group of error records has affinity with a groupcluster of PEs, the affinity level is 1, 2, or 3, parts of ERRDEVAFF reads the same value as parts of MPIDR_EL1, and the rest of ERRDEVAFF indicates the level.

For example, if the groupaffinity oflevel PEs is a subset of the PEs at affinity level 12 then all of the following are true:

- ERRDEVAFF.Aff1 reads as 0x80 and ERRDEVAFF.{Aff0,F0V} read-as-zero, to indicate affinity level 2.
- AllThe thegroup of error records has affinity with all PEs in the groupsystem that have the same valuesvalue in MPIDR_EL1.{Aff3,Aff2}, and these values are equal to ERRDEVAFF.{Aff3,Aff2}.
- ERRDEVAFF.Aff1ERRDEVAFF.{Aff3,Aff2} isreads nonzerothe andsame notvalue as 0x80, and ERRDEVAFF.{Aff0,F0V} read-as-zero, to indicate at least affinity level 1. The subset of PEs at level 1 that the group of error records has affinity with is indicated by the least-significant set bit in ERRDEVAFF.Aff1. In this example, if ERRDEVAFF.Aff1[2:0] is 0b100, then the group of error records has affinity with the up-to 8 PEs that have MPIDR_EL1.Aff1[7:3] == ERRDEVAFF.Aff1[7:3].{Aff3,Aff2}.

Configuration

Implementation of this register is OPTIONAL.

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRDEVAFF are RES0.

Present only if a group has affinity with a PE or cluster of PEs, and otherwise RES0.

This register is present only when the group of error records has affinity with a PE or cluster of PEs. Otherwise, direct accesses to ERRDEVAFF are RES0.

Attributes

ERRDEVAFF is a 64-bit register.

Field descriptions

The ERRDEVAFF bit assignments are:



Bits [63:40]

Reserved, RES0.

Aff3, bits [39:32]

PE affinity~~Affinity~~ level 3. The MPIDR_EL1.Aff3 field, viewed from the highest Exception level of the associated PE or PEs.

F0V, bit [31]

Indicates that the ERRDEVAFF.Aff0 field is valid.

F0V	Meaning
0b0	ERRDEVAFF.Aff0 is not valid, and the PE affinity ~~level~~ is above~~1,~~ level~~2~~ 0 or a subset of level 0.~~3.~~
0b1	ERRDEVAFF.Aff0 is valid, and the PE affinity ~~level~~ is at level 0.

U, bit [30]

When ERRDEVAFF.F0V == 0b1:

Uniprocessor. The MPIDR_EL1.U bit, viewed from the highest Exception level of the associated PE.

~~U~~	~~Meaning~~
~~0b0~~	~~The PE is part of a multiprocessor system.~~
~~0b1~~	~~The PE is part of a uniprocessor system.~~

~~If ERRDEVAFF.Aff0 is not valid, this bit is not valid and reads as UNKNOWN.~~

Otherwise:

Reserved, UNKNOWN.

Bits [29:25]

Reserved, RES0.

MT, bit [24]

When ERRDEVAFF.F0V == 0b1:

Multithreaded. The MPIDR_EL1.MT bit, viewed from the highest Exception level of the associated PE.

Otherwise:

Reserved, UNKNOWN.

Aff2, bits [23:16]

When affine with a PE or PEs at affinity level 2 or below:

PE affinity level 2. The MPIDR_EL1.Aff2 field, viewed from the highest Exception level of the associated PE or PEs.

When affine with a sub-set of PEs at affinity level 2:

PE affinity level 2. Defines part of the MPIDR_EL1.Aff2 field, viewed from the highest Exception level of the associated PEs.

Aff2MT	Meaning
0bxxxxxxx10b0	ERRDEVAFF.Aff2[7:1]Performance isof PEs at the valuelowest ofaffinity level is largely independent. MPIDR_EL1.Aff2[7:1], viewed from the highest Exception level of the associated PEs.
0bxxxxxx100b1	ERRDEVAFF.Aff2[7:2]Performance isof PEs at the valuelowest ofaffinity level is very interdependent. MPIDR_EL1.Aff2[7:2], viewed from the highest Exception level of the associated PEs.
0bxxxxx100	ERRDEVAFF.Aff2[7:3] is the value of MPIDR_EL1.Aff2[7:3], viewed from the highest Exception level of the associated PEs.
0bxxxx1000	ERRDEVAFF.Aff2[7:4] is the value of MPIDR_EL1.Aff2[7:4], viewed from the highest Exception level of the associated PEs.
0bxxx10000	ERRDEVAFF.Aff2[7:5] is the value of MPIDR_EL1.Aff2[7:5], viewed from the highest Exception level of the associated PEs.
0bxx100000	ERRDEVAFF.Aff2[7:6] is the value of MPIDR_EL1.Aff2[7:6], viewed from the highest Exception level of the associated PEs.
0bx1000000	ERRDEVAFF.Aff2[7] is the value of MPIDR_EL1.Aff2[7], viewed from the highest Exception level of the associated PEs.

If ERRDEVAFF.Aff0 is not valid, this bit is not valid and reads as UNKNOWN.

Aff2, bits [23:16]

Affinity level 2.

When the PE affinity level is 0, 1, or 2, this field is the MPIDR_EL1.Aff2 field viewed from the highest Exception level of the associated PE or PEs.

When the PE affinity level is 3, this field indicates that ERRDEVAFF.Aff3 field is valid, and the following values are defined:

Otherwise:

PE affinity level 2. Indicates whether the PE affinity is at level 3.

Aff2	Meaning
0x80	ERRDEVAFF.Aff3 is valid, and the PE affinity level is at level 3.

This field reads as 0x80.

All other values are reserved.

Aff1, bits [15:8]

When affine with a PE or PEs at affinity level 1 or below:

PEAffinity affinity level 1. The MPIDR_EL1.Aff1 field, viewed from the highest Exception level of the associated PE or PEs.

When the PE affinity level is 0 or 1, this field is the MPIDR_EL1.Aff1 field viewed from the highest Exception level of the associated PE or PEs.

When the PE affinity level is 2 or 3, this field indicates that ERRDEVAFF.Aff2 is valid, and the following values are defined:

When affine with a sub-set of PEs at affinity level 1:

PE affinity level 1. Defines part of the MPIDR_EL1.Aff1 field, viewed from the highest Exception level of the associated PEs.

Aff1	Meaning
0bxxxxxxx10x00	ERRDEVAFF.Aff1[7:1]ERRDEVAFF.Aff2 is not valid, and the valuePE ofaffinity level is 3. MPIDR_EL1.Aff1[7:1], viewed from the highest Exception level of the associated PEs.
0bxxxxxx100x80	ERRDEVAFF.Aff1[7:2]ERRDEVAFF.Aff2 is valid, and the valuePE ofaffinity level is 2. MPIDR_EL1.Aff1[7:2], viewed from the highest Exception level of the associated PEs.
0bxxxxx100	ERRDEVAFF.Aff1[7:3] is the value of MPIDR_EL1.Aff1[7:3], viewed from the highest Exception level of the associated PEs.
0bxxxx1000	ERRDEVAFF.Aff1[7:4] is the value of MPIDR_EL1.Aff1[7:4], viewed from the highest Exception level of the associated PEs.
0bxxx10000	ERRDEVAFF.Aff1[7:5] is the value of MPIDR_EL1.Aff1[7:5], viewed from the highest Exception level of the associated PEs.
0bxx100000	ERRDEVAFF.Aff1[7:6] is the value of MPIDR_EL1.Aff1[7:6], viewed from the highest Exception level of the associated PEs.
0bx1000000	ERRDEVAFF.Aff1[7] is the value of MPIDR_EL1.Aff1[7], viewed from the highest Exception level of the associated PEs.

All other values are reserved.

Aff0, bits [7:0]

Affinity level 0.

When the PE affinity level is 0, this field is the MPIDR_EL1.Aff0 field viewed from the highest Exception level of the associated PE or PEs.

When the PE affinity level is 1, 2 or 3, this field indicates that ERRDEVAFF.Aff1 is valid, and the following values are defined:

Otherwise:

PE affinity level 1. Indicates whether the PE affinity is at level 2.

Aff1Aff0	Meaning
0x00	PEERRDEVAFF.Aff1 affinity is abovenot levelvalid, 2and orthe aPE subsetaffinity of level 2.is 2 or 3.
0x80	ERRDEVAFF.Aff1 is valid, and the PE affinity level is at level 2.1.

All other values are reserved.

Aff0, bits [7:0]

When affine with a PE at affinity level 0:

PE affinity level 0. The MPIDR_EL1.Aff0 field, viewed from the highest Exception level of the associated PE.

When affine with a sub-set of PEs at affinity level 0:

PE affinity level 0. Defines part of the MPIDR_EL1.Aff0 field, viewed from the highest Exception level of the associated PEs.

Aff0	Meaning
0bxxxxxxx1	ERRDEVAFF.Aff0[7:1] is the value of MPIDR_EL1.Aff0[7:1], viewed from the highest Exception level of the associated PEs.
0bxxxxxx10	ERRDEVAFF.Aff0[7:2] is the value of MPIDR_EL1.Aff0[7:2], viewed from the highest Exception level of the associated PEs.
0bxxxxx100	ERRDEVAFF.Aff0[7:3] is the value of MPIDR_EL1.Aff0[7:3], viewed from the highest Exception level of the associated PEs.
0bxxxx1000	ERRDEVAFF.Aff0[7:4] is the value of MPIDR_EL1.Aff0[7:4], viewed from the highest Exception level of the associated PEs.
0bxxx10000	ERRDEVAFF.Aff0[7:5] is the value of MPIDR_EL1.Aff0[7:5], viewed from the highest Exception level of the associated PEs.
0bxx100000	ERRDEVAFF.Aff0[7:6] is the value of MPIDR_EL1.Aff0[7:6], viewed from the highest Exception level of the associated PEs.
0bx1000000	ERRDEVAFF.Aff0[7] is the value of MPIDR_EL1.Aff0[7], viewed from the highest Exception level of the associated PEs.

Otherwise:

PE affinity level 0. Indicates whether the PE affinity is at level 1.

Aff0	Meaning
0x00	PE affinity is above level 1 or a subset of level 1.
0x80	PE affinity is at level 1.

Accessing the ERRDEVAFF

ERRDEVAFF can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	0xFA8

~~Component~~	~~Offset~~	~~Instance~~
~~RAS~~	~~0xFA8~~	~~ERRDEVAFF~~

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRDEVARCH, Device Architecture Register

The ERRDEVARCH characteristics are:

Purpose

Provides discovery information for the component.

Configuration

~~This register is present only when RAS is implemented. Otherwise, direct accesses to ERRDEVARCH are UNDEFINED.~~

There are no configuration notes.

Attributes

ERRDEVARCH is a 32-bit register.

Field descriptions

The ERRDEVARCH bit assignments are:

31 30 29 28 27 26 25 24 23 22 21	20	19 18 17 16	15 14 13 12	11 10 9 8 7 6 5 4 3 2 1 0
ARCHITECT	PRESENT	REVISION	ARCHVER	ARCHPART

ARCHITECT, bits [31:21]

~~Defines the architect of the component. Bits [31:28] are the JEP106 continuation code (JEP106 bank ID, minus 1) and bits [27:21] are the JEP106 ID code.~~

Architect. Defines the architect of the component. Bits [31:28] are the JEP106 continuation code (JEP106 bank ID, minus 1) and bits [27:21] are the JEP106 ID code.

ARCHITECT	Meaning
0b01000111011	JEP106 continuation code 0x4, ID code 0x3B. Arm Limited.

~~This field reads as 0x23B.~~

Other values are defined by the JEDEC JEP106 standard.

This field reads as 0x23B.

PRESENT, bit [20]

~~Defines that the DEVARCH register is present.~~

DEVARCH Present. Defines that the DEVARCH register is present.

PRESENT	Meaning
0b0	Device Architecture information not present.
0b1	Device Architecture information present.

This bit reads~~is~~ as~~RAO.~~ 0b1.

REVISION, bits [19:16]

~~Defines the architecture revision of the component. The defined values of this field are:~~

Revision. Defines the architecture revision of the component.

REVISION	Meaning
0b0000	RAS System Architecture v1.0.
0b0001	RAS System Architecture v1.1. As 0b0000 and also: • Simplifies ERR<n>STATUS. • Adds support for additional ERR<n>MISC<m> registers. • Adds support for the optional RAS Timestamp Extension. • Adds support for the optional RAS Common Fault Injection Model Extension.

All other values are reserved.

ARCHVER, bits [15:12]

~~Defines the architecture version of the component. The defined values of this field are:~~

Architecture Version. Defines the architecture version of the component.

ARCHVER	Meaning
0b0000	RAS System Architecture v1.

~~This field reads as 0b0000.~~

All other values are reserved.

ARCHVER and ARCHPART are also defined as a single field, ARCHID, so that ARCHVER is ARCHID[15:12].

This field reads as 0b0000.

ARCHPART, bits [11:0]

~~Defines the architecture of the component.~~

Architecture Part. Defines the architecture of the component.

ARCHPART	Meaning
0xA00	RAS System~~system~~ Architecture.~~architecture.~~

~~This register reads as 0xA00.~~

ARCHVER and ARCHPART are also defined as a single field, ARCHID, so that ARCHPART is ARCHID[11:0].

This field reads as 0xA00.

Accessing the ERRDEVARCH

ERRDEVARCH can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	0xFBC

~~Component~~	~~Offset~~	~~Instance~~
~~RAS~~	~~0xFBC~~	~~ERRDEVARCH~~

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRDEVID, Device Configuration Register

The ERRDEVID characteristics are:

Purpose

Provides discovery information for the component.

Configuration

~~This register is present only when RAS is implemented. Otherwise, direct accesses to ERRDEVID are UNDEFINED.~~

There are no configuration notes.

Attributes

ERRDEVID is a 32-bit register.

Field descriptions

The ERRDEVID bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																NUM															

Bits [31:16]

Reserved, RES0.

NUM, bits [15:0]

IMPLEMENTATION DEFINED.

Highest numbered index of the error records in this group, plus one. Each implemented record is owned by a node. A node might own multiple records.

~~This field reads as an IMPLEMENTATION DEFINED value.~~

This manual describes ~~a~~the group~~memory-mapped view~~ of error records accessed via a standard~~group~~ 4KB~~with~~ memory-mapped~~up~~ peripheral.~~to~~ For~~56~~ a 4KB peripheral~~records~~, up~~the~~ to~~most~~ 24~~that~~ error records can be accessed~~contained~~ if~~in~~ the~~a~~ Common~~4KB~~ Fault~~component,~~ Injection~~meaning~~ Model~~the~~ is~~highest~~ implemented,~~possible~~ and~~value~~ up~~for~~ to~~this~~ 56~~field~~ otherwise.~~is 56.~~

Accessing the ERRDEVID

ERRDEVID can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	0xFC8

~~Component~~	~~Offset~~	~~Instance~~
~~RAS~~	~~0xFC8~~	~~ERRDEVID~~

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRERICR0, Error Recovery Interrupt Configuration Register 0

The ERRERICR0 characteristics are:

Purpose

Interrupt configuration register.

Configuration

External register ERRERICR0 is architecturally mapped to External register ERRIRQCR2.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRERICR0 are RES0.

Present only if interrupt configuration registers use the recommended format. Otherwise, this register is RES0.

Attributes

ERRERICR0 is a 64-bit register.

Field descriptions

The ERRERICR0 bit assignments are:



Bits [63:56]

Reserved, RES0.

ADDR, bits [55:2]

Message Signaled Interrupt address.

Specifies the address that the component writes to when signaling an interrupt.

The size of a physical address is IMPLEMENTATION DEFINED. Unimplemented high-order physical address bits are RES0.

The following resets apply:

- On ana~~a~~ Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [1:0]

Reserved, RES0.

Accessing the ERRERICR0

ERRERICR0 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0xE90	ERRERICR0

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRERICR1, Error Recovery Interrupt Configuration Register 1

The ERRERICR1 characteristics are:

Purpose

Interrupt configuration register.

Configuration

External register ERRERICR1 bits [31:0] are architecturally mapped to External register ERRIRQCR3[31:0] .

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRERICR1 are RES0.

Present only if interrupt configuration registers use the recommended format. Otherwise, this register is RES0.

Attributes

ERRERICR1 is a 32-bit register.

Field descriptions

The ERRERICR1 bit assignments are:



DATA, bits [31:0]

Payload for a message signaled interrupt.

The following resets apply:

- On ana~~a~~ Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the ERRERICR1

ERRERICR1 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0xE98	ERRERICR1

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRERICR2, Error Recovery Interrupt Configuration Register 2

The ERRERICR2 characteristics are:

Purpose

Interrupt configuration register.

Configuration

External register ERRERICR2 bits [31:0] are architecturally mapped to External register ERRIRQCR3[63:32] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRERICR2 are RES0.

Present only if interrupt configuration registers use the recommended format. Otherwise, this register is RES0.

Attributes

ERRERICR2 is a 32-bit register.

Field descriptions

The ERRERICR2 bit assignments are:



Bits [31:8]

Reserved, RES0.

IRQEN, bit [7]

Message Signaled Interrupt enable.

Enables generation of message signaled interrupts.

IRQEN	Meaning
0b0	Message signaled interrupts are disabled.
0b1	Message signaled interrupts are enabled.

If the component does not support disabling message signaled interrupts, this bit is RES0.

The following resets apply:

- On ana~~a~~ Error recovery reset, this field resets to 0.
- On a Cold reset, this field resets to 0.

NSMSI, bit [6]

Security attribute.

Defines the physical address space for message signaled interrupts.

NSMSI	Meaning
0b0	Physical address space for message signaled interrupts is Secure.
0b1	Physical address space for message signaled interrupts is Non-secure.

If the component prohibits Non-secure writes and does not support configuring the Security attribute, then the Security attribute for message signaled interrupts is IMPLEMENTATION DEFINED.

If the component allows Non-secure writes, then the Security attribute used for message signaled interrupts is Non-secure.

This bit is RES0 if any of the following are true:

- The component allows Non-secure writes.
- The component does not support configuring the Security attribute.

On a Cold reset, this field resets to an IMPLEMENTATION DEFINED value.

SH, bits [5:4]

Shareability.

Defines the Shareability domain for message signaled interrupts.

SH	Meaning
0b00	Message signaled interrupts are in the Not shared Shareability domain.
0b10	Message signaled interrupts are in the Outer Shareable Shareability domain.
0b11	Message signaled interrupts are in the Inner Shareable Shareability domain.

If the component does not support configuring the Shareability domain, this field is RES0, meaning the Shareability domain for message signaled interrupts is IMPLEMENTATION DEFINED.

The following resets apply:

- On ana Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

MemAttr, bits [3:0]

Memory type.

Defines the memory type for message signaled interrupts. The values which correspond to each memory type are:

MemAttr	Meaning
0b0000	Device-nGnRnE.
0b0001	Device-nGnRE.
0b0010	Device-nGRE.
0b0011	Device-GRE.
0b0101	Outer Non-cacheable, Inner Non-cacheable.
0b0110	Outer Non-cacheable, Inner Write-Through Cacheable.
0b0111	Outer Non-cacheable, Inner Write-Back Cacheable.
0b1001	Outer Write-Through Cacheable, Inner Non-cacheable.
0b1010	Outer Write-Through Cacheable, Inner Write-Through Cacheable.
0b1011	Outer Write-Through Cacheable, Inner Write-Back Cacheable.
0b1101	Outer Write-Back Cacheable, Inner Non-cacheable.
0b1110	Outer Write-Back Cacheable, Inner Write-Through Cacheable.
0b1111	Outer Write-Back Cacheable, Inner Write-Back Cacheable.

If the component does not support configuring the memory type, this field is RES0, meaning the memory type used for message signaled interrupts is IMPLEMENTATION DEFINED.

Note

This is the same format as the VMSAv8-64 stage 2 memory region attributes.

The following resets apply:

- On ana Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the ERRERICR2

ERRERICR2 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0xE9C	ERRERICR2

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRFHICR0, Fault-Handling Interrupt Configuration Register 0

The ERRFHICR0 characteristics are:

Purpose

Interrupt configuration register.

Configuration

External register ERRFHICR0 is architecturally mapped to External register ERRIRQCR0.

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRFHICR0 are RES0.

Present only if interrupt configuration registers use the recommended format. Otherwise, this register is RES0.

Attributes

ERRFHICR0 is a 64-bit register.

Field descriptions

The ERRFHICR0 bit assignments are:



Bits [63:56]

Reserved, RES0.

ADDR, bits [55:2]

Message Signaled Interrupt address.

Specifies the address that the component writes to when signaling an interrupt.

The size of a physical address is IMPLEMENTATION DEFINED. Unimplemented high-order physical address bits are RES0.

The following resets apply:

- On ana~~a~~ Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [1:0]

Reserved, RES0.

Accessing the ERRFHICR0

ERRFHICR0 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0xE80	ERRFHICR0

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRFHICR1, Fault-Handling Interrupt Configuration Register 1

The ERRFHICR1 characteristics are:

Purpose

Interrupt configuration register.

Configuration

External register ERRFHICR1 bits [31:0] are architecturally mapped to External register ERRIRQCR1[31:0] .

RW fields in this register reset to architecturally UNKNOWN values.

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRFHICR1 are RES0.

Present only if interrupt configuration registers use the recommended format. Otherwise, this register is RES0.

Attributes

ERRFHICR1 is a 32-bit register.

Field descriptions

The ERRFHICR1 bit assignments are:



DATA, bits [31:0]

Payload for a message signaled interrupt.

The following resets apply:

- On ana Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the ERRFHICR1

ERRFHICR1 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0xE88	ERRFHICR1

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRFHICR2, Fault-Handling Interrupt Configuration Register 2

The ERRFHICR2 characteristics are:

Purpose

Interrupt configuration register.

Configuration

External register ERRFHICR2 bits [31:0] are architecturally mapped to External register ERRIRQCR1[63:32] .

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRFHICR2 are RES0.

Present only if interrupt configuration registers use the recommended format. Otherwise, this register is RES0.

Attributes

ERRFHICR2 is a 32-bit register.

Field descriptions

The ERRFHICR2 bit assignments are:



Bits [31:8]

Reserved, RES0.

IRQEN, bit [7]

Message Signaled Interrupt enable.

Enables generation of message signaled interrupts.

IRQEN	Meaning
0b0	Message signaled interrupts are disabled.
0b1	Message signaled interrupts are enabled.

If the component does not support disabling message signaled interrupts, this bit is RES0.

The following resets apply:

- On ana~~a~~ Error recovery reset, this field resets to 0.
- On a Cold reset, this field resets to 0.

NSMSI, bit [6]

Security attribute.

Defines the physical address space for message signaled interrupts.

NSMSI	Meaning
0b0	Physical address space for message signaled interrupts is Secure.
0b1	Physical address space for message signaled interrupts is Non-secure.

If the component prohibits Non-secure writes and does not support configuring the Security attribute, then the Security attribute for message signaled interrupts is IMPLEMENTATION DEFINED.

If the component allows Non-secure writes, then the Security attribute used for message signaled interrupts is Non-secure.

This bit is RES0 if any of the following are true:

- The component allows Non-secure writes.
- The component does not support configuring the Security attribute.

On a Cold reset, this field resets to an IMPLEMENTATION DEFINED value.

SH, bits [5:4]

Shareability.

Defines the Shareability domain for message signaled interrupts.

SH	Meaning
0b00	Message signaled interrupts are in the Not shared Shareability domain.
0b10	Message signaled interrupts are in the Outer Shareable Shareability domain.
0b11	Message signaled interrupts are in the Inner Shareable Shareability domain.

If the component does not support configuring the Shareability domain, this field is RES0, meaning the Shareability domain for message signaled interrupts is IMPLEMENTATION DEFINED.

The following resets apply:

- On ana Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

MemAttr, bits [3:0]

Memory type.

Defines the memory type for message signaled interrupts. The values which correspond to each memory type are:

MemAttr	Meaning
0b0000	Device-nGnRnE.
0b0001	Device-nGnRE.
0b0010	Device-nGRE.
0b0011	Device-GRE.
0b0101	Outer Non-cacheable, Inner Non-cacheable.
0b0110	Outer Non-cacheable, Inner Write-Through Cacheable.
0b0111	Outer Non-cacheable, Inner Write-Back Cacheable.
0b1001	Outer Write-Through Cacheable, Inner Non-cacheable.
0b1010	Outer Write-Through Cacheable, Inner Write-Through Cacheable.
0b1011	Outer Write-Through Cacheable, Inner Write-Back Cacheable.
0b1101	Outer Write-Back Cacheable, Inner Non-cacheable.
0b1110	Outer Write-Back Cacheable, Inner Write-Through Cacheable.
0b1111	Outer Write-Back Cacheable, Inner Write-Back Cacheable.

If the component does not support configuring the memory type, this field is RES0, meaning the memory type used for message signaled interrupts is IMPLEMENTATION DEFINED.

Note

This is the same format as the VMSAv8-64 stage 2 memory region attributes.

The following resets apply:

- On ana Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the ERRFHICR2

ERRFHICR2 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0xE8C	ERRFHICR2

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRGSR, Error Group Status Register

The ERRGSR characteristics are:

Purpose

ShowsERRGSR shows the status for the records in the group.

Configuration

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRGSR are UNDEFINED.

This manual describes the memory-mapped view of a group with up to 56 records, the most that can be contained in a 4KB component. Extra records might be added by increasing the page size and extending ERRGSR into multiple registers.

This manual describes a group of error records accessed via a standard 4KB memory-mapped peripheral. For a 4KB peripheral, up to 24 error records can be accessed if the Common Fault Injection Model is implemented, and up to 56 otherwise.

Attributes

ERRGSR is a 64-bit register.

Field descriptions

The ERRGSR bit assignments are:



Bits [63:56]

Reserved, RES0.

S<m>, bit [m], for m = 0 to 55

The status for Error Record <m>. A read-only copy of ERR<m>STATUS.V.

S<m>	Meaning
0b0	No error.
0b1	One or more errors.

If the Commoncorresponding Faultrecord Injectionis Modelnot is implemented, up-toor 24the recordscorresponding canrecord bedoes implementednot meaningsupport bitsthis [55:24]type areof reporting, this bit is RES0.

This bit is RES0 if any of the following are true:

- The record is not implemented.
- The record does not support this type of reporting.

Accessing the ERRGSR

ERRGSR can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	0xE00

Component	Offset	Instance
RAS	0xE00	ERRGSR

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRIRQCR<n>, Generic Error Interrupt Configuration Register, n = 0 - 15

The ERRIRQCR<n> characteristics are:

Purpose

The ERRIRQCR<n> registers are IMPLEMENTATION DEFINED interrupt configuration registers.

The architecture provides a recommended format for the ERRIRQCR<n> registers. The registers provided by the recommended layout are:

- ERRFHICR0, ERRFHICR1, and ERRFHICR2, the fault-handling interrupt configuration registers. ERRFHICR<m> maps to ERRIRQCR0 and ERRIRQCR1.
- ERRERICR0, ERRERICR1, and ERRERICR2, the error recovery interrupt configuration registers. ERRERICR<m> maps to ERRIRQCR2 and ERRIRQCR3.
- If ARMv8.4-RAS is implemented, ERRCRICR0, ERRCRICR1, and ERRCRICR2, the critical error interrupt configuration registers. ERRFHICR<m> maps to ERRIRQCR4 and ERRIRQCR5.
- ERRIRQSR, the error interrupt status register. ERRIRQSR maps to ERRIRQCR15.

This register describes the generic IMPLEMENTATION DEFINED format of the interrupt configuration registers, when the recommended layout is not used.

Configuration

~~Present only if the interrupt configuration registers are implemented. Otherwise, this register is RES0.~~

This register is present only when the interrupt configuration registers are implemented. Otherwise, direct accesses to ERRIRQCR<n> are RES0.

Attributes

ERRIRQCR<n> is a 64-bit register.

Field descriptions

The ERRIRQCR<n> bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
IMPLEMENTATION DEFINED																															
IMPLEMENTATION DEFINED																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED controls. The content of these registers is IMPLEMENTATION DEFINED.

~~IMPLEMENTATION DEFINED controls. This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.~~

Accessing the ERRIRQCR<n>

ERRIRQCR<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0xE80 + 8n	ERRIRQCR<n>

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRIRQSR, Error Interrupt Status Register

The ERRIRQSR characteristics are:

Purpose

Interrupt status register.

Configuration

External register ERRIRQSR is architecturally mapped to External register ERRIRQCR15.

~~Present only if interrupt configuration registers use the recommended format. Otherwise, this register is RES0.~~

This~~RW~~ register~~fields~~ is~~in~~ present~~this~~ only when~~register~~ interrupt~~reset~~ configuration registers use the recommended format. Otherwise, direct accesses to ERRIRQSR are~~architecturally~~ RES0~~UNKNOWN~~.~~values.~~

Attributes

ERRIRQSR is a 64-bit register.

Field descriptions

The ERRIRQSR bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																										CRIERR	CRI	ERIERR	ERI	FHIERR	FHI
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:6]

Reserved, RES0.

CRIERR, bit [5]

When Critical Error Interrupt is implemented:

Critical Error~~error~~ Interrupt~~interrupt~~ error.

CRIERR	Meaning
0b0	Critical Error Interrupt write has not returned an error since this bit was last cleared to zero.~~0.~~
0b1	Critical Error Interrupt write has returned an error since this bit was last cleared to zero.~~0.~~

This bit is read/write-one-to-clear.

The following resets apply:

- On ana Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

~~CRI, bit [4]~~

Otherwise:

Reserved,~~Critical error interrupt write in progress.~~ RES0.

CRI, bit [4]

When Critical Error Interrupt is implemented:

Critical Error Interrupt write in progress.

CRI	Meaning
0b0	Critical Error Interrupt write not in progress.
0b1	Critical Error Interrupt write in progress.

Software must not disable an interrupt whilst the write is in progress.

~~This bit is read-only.~~

Note

This bit does not indicate whether an interrupt is active, but rather whether a write triggered by the interrupt is in progress.

To determine whether an interrupt is active, software must examine the individual ERR<n>STATUS registers.

~~ERIERR, bit [3]~~

~~Error recovery interrupt error.~~

Access to this field is **RO**.

Otherwise:

Reserved, RES0.

ERIERR, bit [3]

When Error Recovery Interrupt is implemented:

Error Recovery Interrupt error.

ERIERR	Meaning
0b0	Error Recovery Interrupt write has not returned an error since this bit was last cleared to zero.~~0.~~
0b1	Error Recovery Interrupt write has returned an error since this bit was last cleared to zero.~~0.~~

This bit is read/write-one-to-clear.

The following resets apply:

- On ana Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

~~ERI, bit [2]~~

Otherwise:

Reserved,~~Error recovery interrupt write in progress.~~ RES0.

ERI, bit [2]

When Error Recovery Interrupt is implemented:

Error Recovery Interrupt write in progress.

ERI	Meaning
0b0	Error Recovery Interrupt write not in progress.
0b1	Error Recovery Interrupt write in progress.

Software must not disable an interrupt whilst the write is in progress.

~~This bit is read-only.~~

Note

This bit does not indicate whether an interrupt is active, but rather whether a write triggered by the interrupt is in progress.

To determine whether an interrupt is active, software must examine the individual ERR<n>STATUS registers.

~~FHIERR, bit [1]~~

~~Fault handling interrupt error.~~

Access to this field is **RO**.

Otherwise:

Reserved, RES0.

FHIERR, bit [1]

When Fault Handling Interrupt is implemented:

Fault Handling Interrupt error.

FHIERR	Meaning
0b0	Fault Handling Interrupt write has not returned an error since this bit was last cleared to zero.~~0.~~
0b1	Fault Handling Interrupt write has returned an error since this bit was last cleared to zero.~~0.~~

This bit is read/write-one-to-clear.

The following resets apply:

- On ana Error recovery reset, this field resets to an architecturally UNKNOWN value.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

~~FHI, bit [0]~~

Otherwise:

Reserved,~~Fault handling interrupt write in progress.~~ RES0.

FHI, bit [0]

When Fault Handling Interrupt is implemented:

Fault Handling Interrupt write in progress.

FHI	Meaning
0b0	Fault Handling Interrupt write not in progress.
0b1	Fault Handling Interrupt write in progress.

Software must not disable an interrupt whilst the write is in progress.

~~This bit is read-only.~~

Note

This bit does not indicate whether an interrupt is active, but rather whether a write triggered by the interrupt is in progress.

To determine whether an interrupt is active, software must examine the individual ERR<n>STATUS registers.

Access to this field is **RO**.

Otherwise:

Reserved, RES0.

Accessing the ERRIRQSR

ERRIRQSR can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	0xEF8

~~Component~~	~~Offset~~	~~Instance~~
~~RAS~~	~~0xEF8~~	~~ERRIRQSR~~

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERR<n>ADDR, Error Record Address Register, n = 0 - 65534

The ERR<n>ADDR characteristics are:

Purpose

Software might have to reconstruct the actual physical addresses using the identity of the node and knowledge of the system.

If an addresserror ishas an associated with a detected erroraddress, then this must be written to the address register when the error is recorded. It is IMPLEMENTATION DEFINED how the recorded addresses map to the software-visible physical addresses. Software might have to reconstruct the actual physical addresses using the identity of the node and knowledge of the system.

Configuration

This register is present only when RAS is implemented. Otherwise, direct accesses to ERR<n>ADDR are UNDEFINED.

The number of error records that are implemented is IMPLEMENTATION DEFINED.

If error record <n> is not implemented, ERR<n>ADDR is RES0.

ThisSome registeror isall presentRW only whenfields errorof recordthis <n>register ishave implementeddefined andreset the error record includes an address associated with an error. Otherwise, direct accesses to ERR<n>ADDR arevalues. RES0.

ERR<q>FR describes the features implemented by the node that owns error record <n>. <q> is the index of the first error record owned by the same node as error record <n>. If the node owns a single record, then q = n.

If the error record does not record the fault address, this register is RES0.

Attributes

ERR<n>ADDR is a 64-bit register.

Field descriptions

The ERR<n>ADDR bit assignments are:



NS, bit [63]

Non-secure attribute.

NS	Meaning
0b0	The address is Secure.
0b1	The address is Non-secure.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.

- On a Cold reset, this field resets to an architecturally UNKNOWN value.

SI, bit [62]

~~Indicates whether the NS bit is valid.~~

Secure Incorrect. Indicates whether the NS bit is valid.

SI	Meaning
0b0	The NS bit is correct. That is, it matches the programmers' view of the Non-secure attribute for this recorded location.
0b1	The NS bit might not be correct, and might not match the programmers' view of the Non-secure attribute for the recorded location.

It is IMPLEMENTATION DEFINED whether this bit is read-only or read/write.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

AI, bit [61]

~~Indicates whether the PADDR field is a valid physical address that is known to match the programmers' view of the physical address for the recorded location.~~

Address Incorrect. Indicates whether the PADDR field is a valid physical address that is known to match the programmers' view of the physical address for the recorded location.

AI	Meaning
0b0	The PADDR field is a valid physical address. That is, it matches the programmers' view of the physical address for the recorded location.
0b1	The PADDR field might not be a valid physical address, and might not match the programmers' view of the physical address for the recorded location.

It is IMPLEMENTATION DEFINED whether this bit is read-only or read/write.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

VA, bit [60]

~~Indicates whether the PADDR field is a virtual address.~~

Virtual Address. Indicates whether the PADDR field is a virtual address.

VA	Meaning
0b0	The PADDR field is not a virtual address.
0b1	The PADDR field is a virtual address.

No context information is provided for the virtual address. When ~~this bit is set to 1,~~ ERR<n>ADDR.VA~~ADDR.{NS,SI,AI}~~ ==~~must read as {0,1,1}.~~ 0b1, ERR<n>ADDR.{NS,SI,AI} must read as {0,1,1}.

Support for this bit is optional. If this bit is not implemented and the PADDR field is a virtual address, then ERR<n>ADDR.{NS,SI,AI} must read as {0,1,1}.

It is IMPLEMENTATION DEFINED whether this bit is read-only or read/write.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~

- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [59:56]

Reserved, RES0.

PADDR, bits [55:0]

~~If the physical address size implemented by this component is smaller than the size of this field, then high-order bits are unimplemented and either RES0 or have a fixed read-only IMPLEMENTATION DEFINED value.~~

~~Low-order address bits might also be unimplemented and RES0, for example, if the physical address is always aligned to the size of a protection granule.~~

Physical Address. Address of the recorded location. If the physical address size implemented by this component is smaller than the size of this field, then high-order bits are unimplemented and either RES0 or have a fixed read-only IMPLEMENTATION DEFINED value. Low-order address bits might also be unimplemented and RES0, for example, if the physical address is always aligned to the size of a protection granule.

The following resets apply:

- On~~This~~ an~~field~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the ERR<n>ADDR

ERR<n>ADDR ignores writes if ~~ERR<n>STATUS.AV is set to 1.~~ ERR<n>STATUS.AV == 0b1.

ERR<n>ADDR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0x018 + 64n	ERR<n>ADDR

Accesses on this interface are **RW**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f211~~6134483bd14dc8c12a99c984cbfe3431cc1c9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERR<n>CTLR, Error Record Control Register, n = 0 - 65534

The ERR<n>CTLR characteristics are:

Purpose

The error control register contains enable bits for the node that writes to this record~~, which~~:

- ~~Enable error recovery reporting as a read or write error response.~~
- ~~When ARMv.4-RAS is implemented, enable a critical error interrupt.~~
- ~~Enable error detection and correction.~~

  Enabling error detection and correction.
- ~~Enable an error recovery interrupt.~~

  Enabling the critical error, error recovery, and fault handling interrupts.
- ~~Enable a fault handling interrupt.~~

  Enabling in-band error response for Uncorrected errors.

For each bit, if the selected node does not support the feature, then the bit is RES0. The definition of each record is IMPLEMENTATION DEFINED.

Configuration

~~The number of error records that are implemented is IMPLEMENTATION DEFINED.~~

~~If error record <n> is not implemented, or error record <n> is not the first error record owned by the node, ERR<n>CTLR is RES0.~~

This~~Some~~ register~~or~~ is~~all~~ present~~RW~~ only when~~fields~~ error~~of~~ record~~this~~ <n>~~register~~ is~~have~~ implemented~~defined~~ and~~reset~~ error record <n> is the first error record owned by a node. Otherwise, direct accesses to ERR<n>CTLR are~~values.~~ RES0.

ERR<n>FR describes the features implemented by the node.

Attributes

ERR<n>CTLR is a 64-bit register.

Field descriptions

The ERR<n>CTLR bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
IMPLEMENTATION DEFINED																															
RES0																			CI	RES0	WDUI	DUI	WCFI	CFI	WUE	WFI	WUI	UE	FI	UI	IMPLEMENTATION DEFINED							ED
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

IMPLEMENTATION DEFINED, bits [63:32]

IMPLEMENTATION DEFINED.

Reserved for IMPLEMENTATION DEFINED controls. Must permit SBZP write policy for software.

~~This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.~~

Bits [31:14]

Reserved, RES0.

CI, bit [13]

When ERR<n>FR.CI == 0b10:

~~When enabled, the critical error interrupt is generated for a critical error condition.~~

Critical error interrupt enable. When enabled, the critical error interrupt is generated for a critical error condition.

CI	Meaning
0b0	Critical error interrupt not generated for critical errors. Critical errors are treated as Uncontained errors.
0b1	Critical error interrupt generated for critical errors.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bit [12]

Reserved, RES0.

WDUI, bit [11]

When ERR<n>FR.DUI == 0b11:

Error recovery interrupt for deferred errors on writes enable.

When enabled, the error recovery interrupt is generated for ~~all~~ detected Deferred errors on writes.

WDUI	Meaning
0b0	Error recovery interrupt not generated for deferred errors on writes.
0b1	Error recovery interrupt generated for deferred errors on writes.

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

DUI, bit [10]

When ERR<n>FR.DUI == 0b10:

Error recovery interrupt for deferred errors enable. ~~This control applies to errors arising from both reads and writes.~~

When ~~enabled, an error recovery interrupt is generated for all detected Deferred errors.~~ ERR<n>FR.DUI == 0b10, this control applies to errors arising from both reads and writes.

When enabled, the error recovery interrupt is generated for all detected Deferred errors.

DUI	Meaning
0b0	Error recovery interrupt not generated for deferred errors.
0b1	Error recovery interrupt generated for deferred errors.

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

When ERR<n>FR.DUI == 0b11:

~~When ERR<n>FR.DUI == 0b11, this field is named RDUI.~~

Error recovery interrupt for deferred errors on reads enable.

When ~~enabled, the error recovery interrupt is generated for all detected Deferred errors on reads.~~ ERR<n>FR.DUI == 0b11, this bit is named RDUI.

When enabled, the error recovery interrupt is generated for detected Deferred errors on reads.

RDUI	Meaning
0b0	Error recovery interrupt not generated for deferred errors on reads.
0b1	Error recovery interrupt generated for deferred errors on reads.

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

WCFI, bit [9]

When ERR<n>FR.CFI == 0b11:

Fault handling interrupt for Corrected errors on writes enable.

When enabled:

- If the node implements Corrected error counters for writes, then the fault handling interrupt is generated when a counter overflows and the overflow bit for the counter is set to ~~1. For more information, see~~ 0b1. For more information, see ERR<n>MISC0.
- Otherwise, the fault handling interrupt is also generated for ~~all~~ detected Corrected errors onwrites.~~on writes.~~

WCFI	Meaning
0b0	Fault handling interrupt not generated for Corrected errors on writes.
0b1	Fault handling interrupt generated for Corrected errors on writes.

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

CFI, bit [8]

When ERR<n>FR.CFI == 0b10:

Fault handling interrupt for Corrected errors enable. This control applies to errors arising from both reads and writes.

When ERR<n>FR.CFI == 0b10, this control applies to errors arising from both reads and writes.

When enabled:

- If the node implements Corrected error counters, then the fault handling interrupt is generated when a counter overflows and the overflow bit for the counter is set to 1. For more information, see 0b1. For more information, see ERR<n>MISC0.
- Otherwise, the fault handling interrupt is also generated for all detected Corrected errors.

CFI	Meaning
0b0	Fault handling interrupt not generated for Corrected errors.
0b1	Fault handling interrupt generated for Corrected errors.

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

When ERR<n>FR.CFI == 0b11:

When ERR<n>FR.CFI == 0b11, this field is named RCFI.

Fault handling interrupt for Corrected errors on reads enable.

When ERR<n>FR.CFI == 0b11, this bit is named RCFI.

When enabled:

- If the node implements Corrected error counters for reads, then the fault handling interrupt is generated when a counter overflows and the overflow bit for the counter is set to 1. For more information, see 0b1. For more information, see ERR<n>MISC0.
- Otherwise, the fault handling interrupt is also generated for all detected Corrected errors onreads.on reads.

RCFI	Meaning
0b0	Fault handling interrupt not generated for Corrected errors on reads.
0b1	Fault handling interrupt generated for Corrected errors on reads.

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

WUE, bit [7]

When ERR<n>FR.UE == 0b11:

In-band Uncorrected error reporting on writes enable.

When enabled, responses to writes that detect an Uncorrected error that cannot be deferred are signaled in-band as a detected Uncorrected error (External Abort~~abort~~).

WUE	Meaning
0b0	External Abort~~abort~~ response for Uncorrected errors on~~disabled~~ writes~~for~~ disabled.~~writes.~~
0b1	External Abort~~abort~~ response for Uncorrected errors on~~enabled~~ writes~~for~~ enabled.~~writes.~~

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

WFI, bit [6]

When ERR<n>FR.FI == 0b11:

Fault handling interrupt on writes enable.

When enabled:

- The fault handling interrupt is generated for ~~all~~ detected Deferred errors and Uncorrected errors.~~errors on writes.~~
- If the corresponding fault handling interrupt for Corrected errors control is not implemented:
  - If the node implements Corrected error counters for writes, then the fault handling interrupt is also generated when a counter overflows and the overflow bit for the counter is set to ~~1.~~ 0b1.
  - Otherwise, the fault handling interrupt is also generated for ~~all~~ detected Corrected errors on writes.

WFI	Meaning
0b0	Fault handling interrupt ~~disabled~~ on writes disabled.~~writes.~~
0b1	Fault handling interrupt ~~enabled~~ on writes enabled.~~writes.~~

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

WUI, bit [5]

When ERR<n>FR.UI == 0b11:

Uncorrected error recovery interrupt on writes enable.

When enabled, the error recovery interrupt is generated for ~~all~~ detected Uncorrected errors on writes that are not deferred.

WUI	Meaning
0b0	Error recovery interrupt ~~disabled~~ on writes disabled.~~writes.~~
0b1	Error recovery interrupt ~~enabled~~ on writes enabled.~~writes.~~

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

UE, bit [4]

When ERR<n>FR.UE == 0b10:

In-band Uncorrected error reporting enable.

When ~~enabled, responses to transactions that detect an Uncorrected error that cannot be deferred are signaled in-band as a detected Uncorrected error (External abort).~~ ERR<n>FR.UE == 0b10, this control applies to errors arising from both reads and writes.

When enabled, responses to transactions that detect an Uncorrected error that cannot be deferred are signaled in-band as a detected Uncorrected error (External Abort).

UE	Meaning
0b0	External Abort~~abort~~ response for Uncorrected errors disabled.
0b1	External Abort~~abort~~ response for Uncorrected errors enabled.

~~**Note**~~

~~This control applies to errors arising from both reads and writes.~~

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

When ERR<n>FR.UE == 0b11:

~~When ERR<n>FR.UE == 0b11, this field is named RUE.~~

In-band Uncorrected error reporting on reads enable.

When enabled, responses to reads that detect an Uncorrected error that cannot be deferred are signaled in-band as a detected Uncorrected error (External abort). ERR<n>FR.UE == 0b11, this bit is named RUE.

When enabled, responses to reads that detect an Uncorrected error that cannot be deferred are signaled in-band as a detected Uncorrected error (External Abort).

RUE	Meaning
0b0	External Abortabort response for Uncorrected errors ondisabled readsfor disabled.reads.
0b1	External Abortabort response for Uncorrected errors onenabled readsfor enabled.reads.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

FI, bit [3]

When ERR<n>FR.FI == 0b10:

Fault handling interrupt enable. This control applies to errors arising from both reads and writes.

When ERR<n>FR.FI == 0b10, this control applies to errors arising from both reads and writes.

When enabled:

- The fault handling interrupt is generated for all detected Deferred errors and Uncorrected errors.
- If the fault handling interrupt for Corrected errors control is not implemented:
  - If the node implements Corrected error counters, then the fault handling interrupt is also generated when a counter overflows and the overflow bit for the counter is set to 1. 0b1.
  - Otherwise, the fault handling interrupt is also generated for all detected Corrected errors.

FI	Meaning
0b0	Fault handling interrupt disabled.
0b1	Fault handling interrupt enabled.

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

When ERR<n>FR.FI == 0b11:

When ERR<n>FR.FI == 0b11, this field is named RFI.

Fault handling interrupt on reads enable.

When ERR<n>FR.FI == 0b11, this bit is named RFI.

When enabled:

- The fault handling interrupt is generated for all detected Deferred errors and Uncorrected errors.errors on reads.
- If the corresponding fault handling interrupt for Corrected errors control is not implemented:
  - If the node implements Corrected error counters for reads, then the fault handling interrupt is also generated when a counter overflows and the overflow bit for the counter is set to 1. 0b1.
  - Otherwise, the fault handling interrupt is also generated for all detected Corrected errors on reads.

RFI	Meaning
0b0	Fault handling interrupt disabled on reads disabled.reads.
0b1	Fault handling interrupt enabled on reads enabled.reads.

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

UI, bit [2]

When ERR<n>FR.UI == 0b10:

Uncorrected error recovery interrupt enable. This control applies to errors arising from both reads and writes.

When ERR<n>FR.UI == 0b10, this control applies to errors arising from both reads and writes.

When enabled, the error recovery interrupt is generated for all detected Uncorrected errors that are not deferred.

UI	Meaning
0b0	Error recovery interrupt disabled.
0b1	Error recovery interrupt enabled.

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

When ERR<n>FR.UI == 0b11:

When ERR<n>FR.UI == 0b11, this field is named RUI.

Uncorrected error recovery interrupt on reads enable.

When enabled, the error recovery interrupt is generated for all detected Uncorrected errors on reads that are not deferred. ERR<n>FR.UI == 0b11, this bit is named RUI.

When enabled, the error recovery interrupt is generated for detected Uncorrected errors on reads that are not deferred.

RUI	Meaning
0b0	Error recovery interrupt disabled on reads disabled.reads.
0b1	Error recovery interrupt enabled on reads enabled.reads.

The interrupt is generated even if the error syndrome is discarded because the error record already records a higher priority error.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

IMPLEMENTATION DEFINED, bit [1]

IMPLEMENTATION DEFINED.

Reserved for IMPLEMENTATION DEFINED controls. Must permit SBZP write policy for software.

~~This bit reads as an IMPLEMENTATION DEFINED value and writes to this bit have IMPLEMENTATION DEFINED behavior.~~

ED, bit [0]

When ERR<n>FR.ED == 0b10:

~~When disabled, the node behaves as if error detection and correction are disabled, and no errors are recorded or signaled by the node. Arm recommends that, when disabled, correct error detection and correction codes are written for writes, unless disabled by an IMPLEMENTATION DEFINED control for error injection.~~

Error reporting and logging enable. When disabled, the node behaves as if error detection and correction are disabled, and no errors are recorded or signaled by the node. Arm recommends that, when disabled, correct error detection and correction codes are written for writes, unless disabled by an IMPLEMENTATION DEFINED control for error injection.

ED	Meaning
0b0	Error reporting disabled.
0b1	Error reporting enabled.

It is IMPLEMENTATION DEFINED whether the node fully disables error detection and correction when reporting is disabled. That is, even with error reporting disabled, the node might continue to silently correct errors. Uncorrectable errors might result in corrupt data being silently propagated by the node.

Note

If this node requires initialization after Cold reset to prevent signaling false errors, then Arm recommends this bit is set to ~~0 on Cold reset. This allows boot software to initialize a node without signaling errors. Software can enable error reporting after the node is initialized. If the Cold reset value is 1, the reset values of other controls in this register are~~ 0b0 on Cold reset, meaning errors are not reported from Cold reset. This allows boot software to initialize a node without signaling errors. Software can enable error reporting after the node is initialized. Otherwise, the Cold reset value is IMPLEMENTATION DEFINED. If the Cold reset value is 0b1, the reset values of other controls in this register are also IMPLEMENTATION DEFINED and should not be UNKNOWN.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an IMPLEMENTATION DEFINED value.

Otherwise:

Reserved, RES0.

Accessing the ERR<n>CTLR

ERR<n>CTLR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0x008 + 64n	ERR<n>CTLR

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERR<n>FR, Error Record Feature Register, n = 0 - 65534

The ERR<n>FR characteristics are:

Purpose

Defines whether <n> is the first record owned by a ~~node. If <n> is the first record owned by the~~ node~~, also defines which of the common architecturally-defined features are implemented by the node and, of the implemented features, which are software programmable.~~

- If <n> is the first error record owned by a node, then ERR<n>FR.ED != 0b00.
- If <n> is not the first error record owned by a node, then ERR<n>FR.ED == 0b00.

If <n> is the first record owned by the node, defines which of the common architecturally-defined features are implemented by the node and, of the implemented features, which are software programmable.

Configuration

~~This register is present only when RAS is implemented. Otherwise, direct accesses to ERR<n>FR are RES0.~~

~~Present only if error record <n> is implemented. Otherwise, this register is RES0.~~

~~The number of error records that are implemented is IMPLEMENTATION DEFINED.~~

~~If <n> is the first error record owned by a node, then ERR<n>FR.ED != 0b00.~~

~~If <n> is not the first error record owned by a node, then ERR<n>FR.ED == 0b00.~~

This register is present only when error record <n> is implemented. Otherwise, direct accesses to ERR<n>FR are RES0.

Attributes

ERR<n>FR is a 64-bit register.

Field descriptions

The ERR<n>FR bit assignments are:

When ERR<n>FR.ED != 0b00:



IMPLEMENTATION DEFINED, bits [63:55~~32~~]

When ERR<n>FR.FRX == 0b0:

IMPLEMENTATION DEFINED.

Reserved for identifying IMPLEMENTATION DEFINED controls.

This field reads as an IMPLEMENTATION DEFINED value.

Bits [31:26]

Otherwise:

Reserved, RES0.

Indicates whether, for each error record <m> owned by this node, ERR<m>MISC3 is used as the timestamp register, and, if it is, the timebase used by the timestamp.

CETS, bits [54:53]

When ERR<n>FR.FRX==0b1:

CorrectedTimestamp Error recording. Describes the types of Corrected Error the node can record.Extension.

CETS	Meaning
0b00	The node does not recordsupport anya typetimestamp of Corrected Error.register.
0b01	**Note** For an error record which has an affinity to a PE, this is the same timer that is visible through CNTPCT_EL0 at the highest Exception level on that PE. The node canimplements recorda transienttimestamp orregister. persistentThe Correctedtimestamp Errorsuses (Correctedthe Errorssame thattimebase areas recordedthe assystem Generic Timer. ERR<n>STATUS.CE == 0b01 and 0b11).
0b10	The node can record of a non-specific Corrected Error (a Corrected Error that is recorded as ERR<n>STATUS.CE == 0b10). The node implements a timestamp register. The timebase for the timestamp is IMPLEMENTATION DEFINED.
0b11	The node can record any type of Corrected Error.

All other values are reserved.

When ERR<n>FR.FRX == 0b0:

IMPLEMENTATION DEFINED.

Reserved for identifying IMPLEMENTATION DEFINED controls.

Otherwise:

Reserved, RES0.

DE, bit [52]

When ERR<n>FR.FRX == 0b1:

Deferred Error recording. Describes whether the node can record this type of error.

DE	Meaning
0b0	The node does not record this type of error.
0b1	The node can record this type of error.

When ERR<n>FR.FRX == 0b0:

IMPLEMENTATION DEFINED.

Reserved for identifying IMPLEMENTATION DEFINED controls.

Otherwise:

Reserved, RES0.

UEO, bit [51]

When ERR<n>FR.FRX == 0b1:

Latent or Restartable Error recording. Describes whether the node can record this type of error.

UEO	Meaning
0b0	The node does not record this type of error.
0b1	The node can record this type of error.

When ERR<n>FR.FRX == 0b0:

IMPLEMENTATION DEFINED.

Reserved for identifying IMPLEMENTATION DEFINED controls.

Otherwise:

Reserved, RES0.

UER, bit [50]

When ERR<n>FR.FRX == 0b1:

Signaled or Recoverable Error recording. Describes whether the node can record this type of error.

UER	Meaning
0b0	The node does not record this type of error.
0b1	The node can record this type of error.

When ERR<n>FR.FRX == 0b0:

IMPLEMENTATION DEFINED.

Reserved for identifying IMPLEMENTATION DEFINED controls.

Otherwise:

Reserved, RES0.

UEU, bit [49]

When ERR<n>FR.FRX == 0b1:

Unrecoverable Error recording. Describes whether the node can record this type of error.

UEU	Meaning
0b0	The node does not record this type of error.
0b1	The node can record this type of error.

When ERR<n>FR.FRX == 0b0:

IMPLEMENTATION DEFINED.

Reserved for identifying IMPLEMENTATION DEFINED controls.

Otherwise:

Reserved, RES0.

UC, bit [48]

When ERR<n>FR.FRX == 0b1:

Uncontainable Error recording. Describes whether the node can record this type of error.

UC	Meaning
0b0	The node does not record this type of error.
0b1	The node can record this type of error.

When ERR<n>FR.FRX == 0b0:

IMPLEMENTATION DEFINED.

Reserved for identifying IMPLEMENTATION DEFINED controls.

Otherwise:

Reserved, RES0.

IMPLEMENTATION DEFINED, bits [47:32]

IMPLEMENTATION DEFINED.

Reserved for identifying IMPLEMENTATION DEFINED controls.

FRX, bit [31]

Feature Register extension. Defines whether ERR<n>FR[63:48] are architecturally defined.

FRX	Meaning
0b0	ERR<n>FR[63:48] are IMPLEMENTATION DEFINED.
0b1	ERR<n>FR[63:48] are defined by the architecture.

Bits [30:26]

Reserved, RES0.

TS, bits [25:24]

Timestamp Extension. Indicates whether, for each error record <m> owned by this node, ERR<m>MISC3 is used as the timestamp register, and, if it is, the timebase used by the timestamp.

TS	Meaning
0b00	The node does not support a timestamp register.
0b01	The node implements a timestamp register. The timestamp uses the same timebase as the system Generic Timer. **Note** For an error record which has an affinity to a PE, this is the same timer that is visible through CNTPCT_EL0 at the highest Exception level on that PE.
0b10	The node implements a timestamp register. The timebase for the timestamp is IMPLEMENTATION DEFINED.

All other values are reserved.

CI, bits [23:22]

~~Indicates whether the critical error interrupt and associated controls are implemented.~~

Critical error interrupt. Indicates whether the critical error interrupt and associated controls are implemented.

CI	Meaning
0b00	Does not support the critical error interrupt. ERR<n>CTLR.CI is RES0.
0b01	Critical error interrupt is supported and ~~is~~ always enabled. ERR<n>CTLR.CI is RES0.
0b10	Critical error interrupt is supported and controllable~~it can be enabled~~ using ~~associated controls.~~ ERR<n>CTLR.CI.

All other values are reserved.

~~Indicates whether the RAS Common Fault Injection Model Extension is implemented.~~

INJ, bits [21:20]

~~When ARMv8.4-RAS is implemented:~~

Fault Injection Extension. Indicates whether the RAS Common Fault Injection Model Extension is implemented.

INJ	Meaning
0b00	The node does not support the RAS Common Fault Injection Model Extension.
0b01	The node implements the RAS Common Fault Injection Model Extension. See ERR<n>PFGF for more information.

All other values are reserved.

~~Otherwise:~~

~~Reserved, RES0.~~

CEO, bits [19:18]

When ERR<n>FR.CEC != 0b00:

~~Indicates the behavior when a second Corrected error is detected after a first Corrected error has been recorded by an error record <m> owned by the node.~~

Corrected Error overwrite. Indicates the behavior when a second Corrected error is detected after a first Corrected error has been recorded by an error record <m> owned by the node.

CEO	Meaning
0b00	Counts Corrected errors if a counter is implemented. Keeps the previous error syndrome. If the counter overflows, or no counter is implemented, then ERR<m>STATUS.OF is set to ~~1.~~ 0b1.
0b01	Counts Corrected errors. If ERR<m>STATUS.OF == ~~1 before the Corrected error is counted, then keeps the previous syndrome. Otherwise, the previous syndrome is overwritten. If the counter overflows, then~~ 0b1 before the Corrected error is counted, then keeps the previous syndrome. Otherwise the previous syndrome is overwritten. If the counter overflows, then ERR<m>STATUS.OF is set to 0b1.~~OF is set to 1.~~

All other values are reserved.

Otherwise:

Reserved, RES0.

DUI, bits [17:16]

When ERR<n>FR.UI != 0b00:

~~Indicates whether the node implements a control for enabling error recovery interrupts on deferred errors.~~

Error recovery interrupt for deferred errors control. Indicates whether the control for enabling error recovery interrupts on deferred errors are implemented.~~errors.~~

DUI	Meaning
0b00	Does not support the control for enabling error recovery interrupts on deferred errors.~~feature.~~ ERR<n>CTLR.DUI is RES0.
0b10	Control~~Feature~~ for enabling error recovery interrupts on deferred errors is supported and controllable using ERR<n>CTLR.DUI.
0b11	Control~~Feature~~ for enabling error recovery interrupts on deferred errors is supported and controllable using ERR<n>CTLR.WDUI for writes and ERR<n>CTLR.RDUI for reads.

All other values are reserved.

Otherwise:

Reserved, RES0.

RP, bit [15]

When ERR<n>FR.CEC != 0b00:

~~Indicates whether the node implements a repeat Corrected error counter in ERR<m>MISC0 for each error record <m> owned by the node that implements a standard Corrected error counter.~~

Repeat counter. Indicates whether the node implements the repeat Corrected error counter in ERR<m>MISC0 for each error record <m> owned by the node that implements the standard Corrected error counter.

RP	Meaning
0b0	A single CE counter is implemented.
0b1	A first (repeat) counter and a second (other) counter are implemented. The repeat counter is the same size as the primary error counter.

Otherwise:

Reserved, RES0.

CEC, bits [14:12]

~~Indicates whether the node implements standard Corrected error counter (CE counter) mechanisms in ERR<m>MISC0 for each error record <m> owned by the node that can record countable errors.~~

Corrected Error Counter. Indicates whether the node implements the standard Corrected error counter (CE counter) mechanisms in ERR<m>MISC0 for each error record <m> owned by the node that can record countable errors.

CEC	Meaning
0b000	Does not implement the standard Corrected error counter model.
0b010	Implements an 8-bit Corrected error counter in ERR<m>MISC0[39:32].
0b100	Implements a 16-bit Corrected error counter in ERR<m>MISC0[47:32].

All other values are reserved.

Note

Implementations might include other error counter models, or might include the standard model and not indicate this in ERR<n>FR.

CFI, bits [11:10]

When ERR<n>FR.FI != 0b00:

~~Indicates whether the node implements a control for enabling fault handling interrupts on corrected errors.~~

Fault handling interrupt for corrected errors. Indicates whether the control for enabling fault handling interrupts on corrected errors are implemented.

CFI	Meaning
0b00	Does not support the control for enabling fault handling interrupts on corrected errors.~~feature.~~ ERR<n>CTLR.CFI is RES0.
0b10	Control~~Feature~~ for enabling fault handling interrupts on corrected errors is supported and controllable using ERR<n>CTLR.CFI.
0b11	Control~~Feature~~ for enabling fault handling interrupts on corrected errors is supported and controllable using ERR<n>CTLR.WCFI for writes and ERR<n>CTLR.RCFI for reads.

All other values are reserved.

Otherwise:

Reserved, RES0.

UE, bits [9:8]

~~Indicates whether the node implements in-band uncorrected error reporting (External aborts), and, if so, whether the node implements controls for enabling and disabling the reporting.~~

In-band uncorrected error reporting. Indicates whether the in-band uncorrected error reporting (External Aborts) and associated controls are implemented.

UE	Meaning
0b00	Does not support the in-band uncorrected error reporting (External Aborts).~~feature.~~ ERR<n>CTLR.UE is RES0.
0b01	In-band uncorrected error reporting (External Aborts) is supported and~~Feature~~ always enabled. ERR<n>CTLR.UE is RES0.
0b10	In-band~~Feature~~ uncorrected error reporting (External Aborts) is supported and controllable using ERR<n>CTLR.UE.
0b11	In-band~~Feature~~ uncorrected error reporting (External Aborts) is supported and controllable using ERR<n>CTLR.WUE for writes and ERR<n>CTLR.RUE for reads.

FI, bits [7:6]

~~Indicates whether the node implements a fault handling interrupt, and, if so, whether the node implements controls for enabling and disabling the interrupt.~~

Fault handling interrupt. Indicates whether the fault handling interrupt and associated controls are implemented.

FI	Meaning
0b00	Does not support the fault handling interrupt.~~feature.~~ ERR<n>CTLR.FI is RES0.
0b01	Fault handling interrupt is supported and~~Feature~~ always enabled. ERR<n>CTLR.FI is RES0.
0b10	Fault~~Feature~~ handling interrupt is supported and controllable using ERR<n>CTLR.FI.
0b11	Fault~~Feature~~ handling interrupt is supported and controllable using ERR<n>CTLR.WFI for writes and ERR<n>CTLR.RFI for reads.

UI, bits [5:4]

~~Indicates whether the node implements an error recovery interrupt, and, if so, whether the node implements controls for enabling and disabling the interrupt.~~

Error recovery interrupt for uncorrected errors. Indicates whether the error handling interrupt and associated controls are implemented.

UI	Meaning
0b00	Does not support the error handling interrupt.~~feature.~~ ERR<n>CTLR.UI is RES0.
0b01	Error handling interrupt is supported and~~Feature~~ always enabled. ERR<n>CTLR.UI is RES0.
0b10	Error~~Feature~~ handling interrupt is supported and controllable using ERR<n>CTLR.UI.
0b11	Error~~Feature~~ handling interrupt is supported and controllable using ERR<n>CTLR.WUI for writes and ERR<n>CTLR.RUI for reads.

IMPLEMENTATION DEFINED, bits [3:2]

IMPLEMENTATION DEFINED.

~~This field reads as an IMPLEMENTATION DEFINED value.~~

ED, bits [1:0]

~~Indicates whether <n> is the first record owned by the node, and, if it is, whether the node implements controls for enabling and disabling error reporting and logging.~~

Error reporting and logging. Indicates whether error record <n> is the first record owned the node, and, if so, whether it implements the controls for enabling and disabling error reporting and logging.

ED	Meaning
0b01	Error reporting and loggingFeature always enabled. ERR<n>CTLR.ED is RES0.
0b10	Error reporting and loggingFeature is controllable using ERR<n>CTLR.ED.

All other values are reserved.

The value 0b11 is reserved.

When ERR<n>FR.ED == 0b00:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0																														ED	
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:2]

Reserved, RES0.

ED, bits [1:0]

Indicates whether <n> is the first record owned by the node, and, if it is, whether the node implements controls for enabling and disabling error reporting and logging.

Error reporting and logging. Indicates error record <n> is not the first record owned the node.

ED	Meaning
0b00	Error record <n> is not the first record owned by the node.

This field reads as 0b00.

Accessing the ERR<n>FR

ERR<n>FR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0x000 + 64n	ERR<n>FR

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERR<n>MISC0, Error Record Miscellaneous Register 0, n = 0 - 65534

The ERR<n>MISC0 characteristics are:

Purpose

IMPLEMENTATION DEFINED error syndrome register. The miscellaneous syndrome registers might contain:

- ~~A Corrected error counter or counters.~~

  Information to identify the FRU in which the error was detected, and might contain enough information to locate the error within that FRU.

- ~~Information to identify the FRU in which the error was detected, and might contain enough information to locate the error within that FRU.~~

  A Corrected error counter or counters.

- ~~Other state information not present in the corresponding status and address registers.~~

  Other state information not present in the corresponding status and address registers.

If the node ~~<q>~~ that owns error record <n> implements architecturally-defined error counters~~,~~ (~~so that~~ERR<q>FR.CEC != `0b000`)~~,~~ and error record <n> can record countable errors, then ERR<n>MISC0 implements the architecturally-defined error counter or counters.

Configuration

~~The number of error records that are implemented is IMPLEMENTATION DEFINED.~~

~~If error record <n> is not implemented, ERR<n>MISC0 is RES0.~~

This~~Some~~ register~~or~~ is~~all~~ present~~RW~~ only when~~fields~~ error~~of~~ record~~this~~ <n>~~register~~ is~~have~~ implemented. Otherwise,~~defined~~ direct~~reset~~ accesses to ERR<n>MISC0 are~~values.~~ RES0.

ERR<q>FR describes the features implemented by the node that owns error record <n>. <q> is the index of the first error record owned by the same node as error record <n>. If the node owns a single record, then q = n.

For IMPLEMENTATION DEFINED fields in ERR<n>MISC0~~this register~~, writing zero must always be supported to return the error record to an initial quiescent state.

In particular, if any IMPLEMENTATION DEFINED syndrome fields might generate a Fault Handling or Error Recovery Interrupt request, writing zero is sufficient to deactivate the Interrupt request.

Fields that are read-only, non-zero, and ignore writes are compliant with this requirement.

Note

Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL.~~CTRL, where q is the index of the first error record owned by the same node as error record n. If the node owns a single record then q = n.~~

Attributes

ERR<n>MISC0 is a 64-bit register.

Field descriptions

The ERR<n>MISC0 bit assignments are:

When ERR<q>FR.CEC == 0b000:



IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED syndrome.

~~IMPLEMENTATION DEFINED~~ syndrome. ~~This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.~~

When ERR<q>FR.CEC == 0b100 and ERR<q>FR.RP == 0:



IMPLEMENTATION DEFINED, bits [63:48]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED syndrome.

~~IMPLEMENTATION DEFINED~~ syndrome. ~~This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.~~

OF, bit [47]

~~Set to 1 when the Corrected error count field is incremented and wraps through zero.~~

Sticky overflow bit. Set to 1 when the Corrected error count field is incremented and wraps through zero.

OF	Meaning
0b0	Counter has not overflowed.
0b1	Counter has overflowed.

A direct write that modifies this bit might indirectly set ERR<n>STATUS.OF to an UNKNOWN value and a direct write to ERR<n>STATUS.OF that clears it to zero might indirectly set this bit to an UNKNOWN value.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ thean value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

CEC, bits [46:32]

~~Incremented for each Corrected error. It is IMPLEMENTATION DEFINED and might be UNPREDICTABLE whether Deferred and Uncorrected errors are counted.~~

Corrected error count. Incremented for each Corrected error. It is IMPLEMENTATION DEFINED and might be UNPREDICTABLE whether Deferred and Uncorrected errors are counted.

The following resets apply:

- On~~This~~ an~~field~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED syndrome.

~~IMPLEMENTATION DEFINED syndrome. This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.~~

When ERR<q>FR.CEC == 0b010 and ERR<q>FR.RP == 0:



IMPLEMENTATION DEFINED, bits [63:40]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED syndrome.

~~IMPLEMENTATION DEFINED syndrome. This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.~~

OF, bit [39]

~~Set to 1 when the Corrected error count field is incremented and wraps through zero.~~

Sticky overflow bit. Set to 1 when the Corrected error count field is incremented and wraps through zero.

OF	Meaning
0b0	Counter has not overflowed.
0b1	Counter has overflowed.

A direct write that modifies this bit might indirectly set ERR<n>STATUS.OF to an UNKNOWN value and a direct write to ERR<n>STATUS.OF that clears it to zero might indirectly set this bit to an UNKNOWN value.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

CEC, bits [38:32]

~~Incremented for each Corrected error. It is IMPLEMENTATION DEFINED and might be UNPREDICTABLE whether Deferred and Uncorrected errors are counted.~~

Corrected error count. Incremented for each Corrected error. It is IMPLEMENTATION DEFINED and might be UNPREDICTABLE whether Deferred and Uncorrected errors are counted.

The following resets apply:

- OnThis anfield Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED syndrome.

IMPLEMENTATION DEFINED syndrome. This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.

When ERR<q>FR.CEC == 0b100 and ERR<q>FR.RP == 1:



OFO, bit [63]

Set to 1 when the Corrected error count, other, field is incremented and wraps through zero.

Sticky overflow bit, other. Set to 1 when the Corrected error count, other, field is incremented and wraps through zero.

OFO	Meaning
0b0	Other counter has not overflowed.
0b1	Other counter has overflowed.

A direct write that modifies this bit might indirectly set ERR<n>STATUS.OF to an UNKNOWN value and a direct write to ERR<n>STATUS.OF that clears it to zero might indirectly set this bit to an UNKNOWN value.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

CECO, bits [62:48]

Incremented for each countable error that is not accounted for by incrementing ERR<n>MISC0.CECR.

Corrected error count, other. Incremented for each countable error that is not accounted for by incrementing CECR.

The following resets apply:

- OnThis anfield Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

OFR, bit [47]

Set to 1 when the Corrected error count, repeat, field is incremented and wraps through zero.

Sticky overflow bit, repeat. Set to 1 when the Corrected error count, repeat, field is incremented and wraps through zero.

OFR	Meaning
0b0	Repeat counter has not overflowed.
0b1	Repeat counter has overflowed.

A direct write that modifies this bit might indirectly set ERR<n>STATUS.OF to an UNKNOWN value and a direct write to ERR<n>STATUS.OF that clears it to zero might indirectly set this bit to an UNKNOWN value.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

CECR, bits [46:32]

Corrected error count, repeat. Incremented for the first countable error, which also records other syndrome for the error, and subsequently for each countable error that matches the recorded other syndrome. Corrected errors are countable errors. It is IMPLEMENTATION DEFINED and might be UNPREDICTABLE whether Deferred and Uncorrected errors are countable errors.

Incremented for the first countable error, which also records other syndrome for the error, and subsequently for each countable error that matches the recorded other syndrome. Corrected errors are countable errors. It is IMPLEMENTATION DEFINED and might be UNPREDICTABLE whether Deferred and Uncorrected errors are countable errors.

Note

For example, the other syndrome might include the set and way information for an error detected in a cache. This might be recorded in the IMPLEMENTATION DEFINED ERR<n>MISC<m> fields on a first Corrected error. ERR<n>MISC0.CECR is then incremented for each subsequent Corrected Error in the same set and way.

Note

For example, the other syndrome might include the set and way information for an error detected in a cache. This might be recorded in the IMPLEMENTATION DEFINED ERR<n>MISC<m> fields on a first Corrected error. CECR is then incremented for each subsequent Corrected Error in the same set and way.

The following resets apply:

- OnThis anfield Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED syndrome.

IMPLEMENTATION DEFINED syndrome. This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.

When ERR<q>FR.CEC == 0b010 and ERR<q>FR.RP == 1:



IMPLEMENTATION DEFINED, bits [63:48]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED syndrome.

IMPLEMENTATION DEFINED syndrome. This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.

OFO, bit [47]

~~Set to 1 when the Corrected error count, other, field is incremented and wraps through zero.~~

Sticky overflow bit, other. Set to 1 when the Corrected error count, other, field is incremented and wraps through zero.

OFO	Meaning
0b0	Other counter has not overflowed.
0b1	Other counter has overflowed.

A direct write that modifies this bit might indirectly set ERR<n>STATUS.OF to an UNKNOWN value and a direct write to ERR<n>STATUS.OF that clears it to zero might indirectly set this bit to an UNKNOWN value.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

CECO, bits [46:40]

~~Incremented for each countable error that is not accounted for by incrementing ERR<n>MISC0.CECR.~~

Corrected error count, other. Incremented for each countable error that is not accounted for by incrementing CECR.

The following resets apply:

- On~~This~~ an~~field~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

OFR, bit [39]

~~Set to 1 when the Corrected error count, repeat, field is incremented and wraps through zero.~~

Sticky overflow bit, repeat. Set to 1 when the Corrected error count, repeat, field is incremented and wraps through zero.

OFR	Meaning
0b0	Repeat counter has not overflowed.
0b1	Repeat counter has overflowed.

A direct write that modifies this bit might indirectly set ERR<n>STATUS.OF to an UNKNOWN value and a direct write to ERR<n>STATUS.OF that clears it to zero might indirectly set this bit to an UNKNOWN value.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

CECR, bits [38:32]

Corrected error count, repeat. Incremented for the first countable error, which also records other syndrome for the error, and subsequently for each countable error that matches the recorded other syndrome. Corrected errors are countable errors. It is IMPLEMENTATION DEFINED and might be UNPREDICTABLE whether Deferred and Uncorrected errors are countable errors.

~~Incremented for the first countable error, which also records other syndrome for the error, and subsequently for each countable error that matches the recorded other syndrome. Corrected errors are countable errors. It is IMPLEMENTATION DEFINED and might be UNPREDICTABLE whether Deferred and Uncorrected errors are countable errors.~~

~~Note~~

~~For example, the other syndrome might include the set and way information for an error detected in a cache. This might be recorded in the~~

IMPLEMENTATION DEFINED ERR<n>MISC<m> fields on a first Corrected error. ERR<n>MISC0.CECR is then incremented for each subsequent Corrected Error in the same set and way.

Note

For example, the other syndrome might include the set and way information for an error detected in a cache. This might be recorded in the IMPLEMENTATION DEFINED ERR<n>MISC<m> fields on a first Corrected error. CECR is then incremented for each subsequent Corrected Error in the same set and way.

The following resets apply:

- OnThis anfield Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

IMPLEMENTATION DEFINED, bits [31:0]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED syndrome.

IMPLEMENTATION DEFINED syndrome. This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.

Accessing the ERR<n>MISC0

ReadsArm fromrecommends ERR<n>MISC0that returna anmiscellaneous syndrome for multiple errors, such as a corrected error counter, is read/write. IMPLEMENTATION DEFINED value and writes have IMPLEMENTATION DEFINED behavior.

Arm recommends that miscellaneous syndrome for multiple errors, such as a corrected error counter, is read/write.WhenERR<n>STATUS.MV is set to 1, the miscellaneous syndrome for the most recently recorded error should ignore writes.

When ERR<n>STATUS.MV == 0b1, the miscellaneous syndrome specific to the most recently recorded error should ignore writes.

Note

These recommendations allow a counter to be reset in the presence of a persistent error, while preventing specific information, such as that identifying a FRU, from being lost if an error is detected while the previous error is being logged.

ERR<n>MISC0 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0x020 + 64n	ERR<n>MISC0

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERR<n>MISC1, Error Record Miscellaneous Register 1, n = 0 - 65534

The ERR<n>MISC1 characteristics are:

Purpose

IMPLEMENTATION DEFINED error syndrome register. The miscellaneous syndrome registers mightcan contain:

- A Corrected error counter or counters.

  Information to identify the FRU in which the error was detected, and might contain enough information to locate the error within that FRU.

- Information to identify the FRU in which the error was detected, and might contain enough information to locate the error within that FRU.

  A Corrected error counter or counters.

- Other state information not present in the corresponding status and address registers.

  Other state information not present in the corresponding status and address registers.

Configuration

This register is present only when RAS is implemented. Otherwise, direct accesses to ERR<n>MISC1 are UNDEFINED.

The number of error records that are implemented is IMPLEMENTATION DEFINED.

If error record <n> is not implemented, ERR<n>MISC1 is RES0.

This register is present only when error record <n> is implemented. Otherwise, direct accesses to ERR<n>MISC1 are RES0.

ERR<q>FR describes the features implemented by the node that owns error record <n>. <q> is the index of the first error record owned by the same node as error record <n>. If the node owns a single record, then q = n.

For IMPLEMENTATION DEFINED fields in ERR<n>MISC1this register, writing zero must always be supported to return the error record to an initial quiescent state.

In particular, if any IMPLEMENTATION DEFINED syndrome fields might generate a Fault Handling or Error Recovery Interrupt request, writing zero is sufficient to deactivate the Interrupt request.

Fields that are read-only, non-zero, and ignore writes are compliant with this requirement.

Note

Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL.CTRL, where q is the index of the first error record owned by the same node as error record n. If the node owns a single record then q = n.

Attributes

ERR<n>MISC1 is a 64-bit register.

Field descriptions

The ERR<n>MISC1 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
IMPLEMENTATION DEFINED																															
IMPLEMENTATION DEFINED																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED syndrome.

~~IMPLEMENTATION DEFINED syndrome. This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.~~

Accessing the ERR<n>MISC1

ReadsArm fromrecommends ERR<n>MISC1that returna anmiscellaneous syndrome for multiple errors, such as a corrected error counter, is read/write. IMPLEMENTATION DEFINED value and writes have IMPLEMENTATION DEFINED behavior.

Arm recommends that miscellaneous syndrome for multiple errors, such as a corrected error counter, is read/write.WhenERR<n>STATUS.MV is set to 1, the miscellaneous syndrome for the most recently recorded error should ignore writes.

When ERR<n>STATUS.MV == 0b1, the miscellaneous syndrome specific to the most recently recorded error should ignore writes.

Note

These recommendations allow a counter to be reset in the presence of a persistent error, while preventing specific information, such as that identifying a FRU, from being lost if an error is detected while the previous error is being logged.

ERR<n>MISC1 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0x028 + 64n	ERR<n>MISC1

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERR<n>MISC2, Error Record Miscellaneous Register 2, n = 0 - 65534

The ERR<n>MISC2 characteristics are:

Purpose

IMPLEMENTATION DEFINED error syndrome register. The miscellaneous syndrome registers mightcan contain:

- A Corrected error counter or counters.

  Information to identify the FRU in which the error was detected, and might contain enough information to locate the error within that FRU.

- Information to identify the FRU in which the error was detected, and might contain enough information to locate the error within that FRU.

  A Corrected error counter or counters.

- Other state information not present in the corresponding status and address registers.

  Other state information not present in the corresponding status and address registers.

Configuration

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERR<n>MISC2 are RES0.

The number of error records that are implemented is IMPLEMENTATION DEFINED.

If error record <n> is not implemented, ERR<n>MISC2 is RES0.

This register is present only when error record <n> is implemented. Otherwise, direct accesses to ERR<n>MISC2 are RES0.

ERR<q>FR describes the features implemented by the node that owns error record <n>. <q> is the index of the first error record owned by the same node as error record <n>. If the node owns a single record, then q = n.

For IMPLEMENTATION DEFINED fields in ERR<n>MISC2this register, writing zero must always be supported to return the error record to an initial quiescent state.

In particular, if any IMPLEMENTATION DEFINED syndrome fields might generate a Fault Handling or Error Recovery Interrupt request, writing zero is sufficient to deactivate the Interrupt request.

Fields that are read-only, non-zero, and ignore writes are compliant with this requirement.

Note

Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL, where q is the index of the first error record owned by the same node as error record n. If the node owns a single record then q = n.

If RAS System Architecture v1.1 is not implemented, Arm recommendeds that ERR<n>MISC2 does not require zeroing to return the record to a quiescent state.

Note

Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL.

It is IMPLEMENTATION DEFINED whether ERR<n>MISC2 is present if RAS System Architecture v1.1 is not implemented. ERR<n>MISC2 is RES0 if not present.

Attributes

ERR<n>MISC2 is a 64-bit register.

Field descriptions

The ERR<n>MISC2 bit assignments are:



IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED syndrome.

~~IMPLEMENTATION DEFINED syndrome. This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.~~

Accessing the ERR<n>MISC2

Reads~~Arm~~ from~~recommends~~ ERR<n>MISC2~~that~~ return~~a~~ an~~miscellaneous syndrome for multiple errors, such as a corrected error counter, is read/write.~~ IMPLEMENTATION DEFINED value and writes have IMPLEMENTATION DEFINED behavior.

Arm recommends that miscellaneous syndrome for multiple errors, such as a corrected error counter, is read/write.~~When~~ERR<n>STATUS.~~MV is set to 1, the miscellaneous syndrome for the most recently recorded error should ignore writes.~~

When ERR<n>STATUS.MV == 0b1, the miscellaneous syndrome specific to the most recently recorded error should ignore writes.

Note

These recommendations allow a counter to be reset in the presence of a persistent error, while preventing specific information, such as that identifying a FRU, from being lost if an error is detected while the previous error is being logged.

ERR<n>MISC2 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0x030 + 64n	ERR<n>MISC2

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERR<n>MISC3, Error Record Miscellaneous Register 3, n = 0 - 65534

The ERR<n>MISC3 characteristics are:

Purpose

IMPLEMENTATION DEFINED error syndrome register. The miscellaneous syndrome registers mightcan contain:

- A Corrected error counter or counters.

  Information to identify the FRU in which the error was detected, and might contain enough information to locate the error within that FRU.

- Information to identify the FRU in which the error was detected, and might contain enough information to locate the error within that FRU.

  A Corrected error counter or counters.

- Other state information not present in the corresponding status and address registers.

  Other state information not present in the corresponding status and address registers.

If the node <q> that owns error record <n> supports the RAS Timestamp Extension, (then ERR<n>MISC3 contains the timestamp value for error record <n> when the error was detected. Otherwise the contents of ERR<n>MISC3 areERR<q>FR.TS != 0b00), then ERR<n>MISC3 contains the timestamp value for error record n when the error was detected. Otherwise the contents of ERR<n>MISC3 are IMPLEMENTATION DEFINED.

Configuration

External register ERR<n>MISC3 bits [31:0] are architecturally mapped to AArch32 System register ERXMISC6[31:0] when ERRSELR_EL1.SEL == n.

External register ERR<n>MISC3 bits [63:32] are architecturally mapped to AArch32 System register ERXMISC7[31:0] when ERRSELR_EL1.SEL == n.

RW fields in this register reset to architecturally UNKNOWN values.

This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERR<n>MISC3 are RES0.

The number of error records that are implemented is IMPLEMENTATION DEFINED.

If error record <n> is not implemented, ERR<n>MISC3 is RES0.

This register is present only when error record <n> is implemented. Otherwise, direct accesses to ERR<n>MISC3 are RES0.

External register ERR<n>MISC3 is architecturally mapped to AArch64 System register ERXMISC3_EL1 when ERRSELR_EL1.SEL == n.

ERR<q>FR describes the features implemented by the node that owns error record <n>. <q> is the index of the first error record owned by the same node as error record <n>. If the node owns a single record, then q = n.

For IMPLEMENTATION DEFINED fields in ERR<n>MISC3this register, writing zero must always be supported to return the error record to an initial quiescent state.

In particular, if any IMPLEMENTATION DEFINED syndrome fields might generate a Fault Handling or Error Recovery Interrupt request, writing zero is sufficient to deactivate the Interrupt request.

Fields that are read-only, non-zero, and ignore writes are compliant with this requirement.

Note

Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL, where q is the index of the first error record owned by the same node as error record n. If the node owns a single record then q = n.

If RAS System Architecture v1.1 is not implemented, Arm recommendeds that ERR<n>MISC3 does not require zeroing to return the record to a quiescent state.

Note

Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL.

It is IMPLEMENTATION DEFINED whether ERR<n>MISC3 is present if RAS System Architecture v1.1 is not implemented. ERR<n>MISC3 is RES0 if not present.

Attributes

ERR<n>MISC3 is a 64-bit register.

Field descriptions

The ERR<n>MISC3 bit assignments are:

When ERR<q>FR.TS != 0b00:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
TS																															
TS																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

TS, bits [63:0]

Timestamp. Timestamp value recorded when the error was detected. Valid only if ERR<n>STATUS.V == 0b1.

TheTimestamp followingvalue resetsrecorded apply:when the error was detected. Valid only ifERR<n>STATUS.V == 1.

See ERR<n>FR.TS.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Access to this field is **RO or RW**.

When ERR<q>FR.TS == 0b00:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
IMPLEMENTATION DEFINED																															
IMPLEMENTATION DEFINED																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

IMPLEMENTATION DEFINED, bits [63:0]

IMPLEMENTATION DEFINED.

IMPLEMENTATION DEFINED syndrome.

~~IMPLEMENTATION DEFINED~~ syndrome. ~~This field reads as an IMPLEMENTATION DEFINED value and writes to this field have IMPLEMENTATION DEFINED behavior.~~

Accessing the ERR<n>MISC3

ReadsArm fromrecommends ERR<n>MISC3that returna anmiscellaneous syndrome for multiple errors, such as a corrected error counter, is read/write. IMPLEMENTATION DEFINED value and writes have IMPLEMENTATION DEFINED behavior.

Arm recommends that miscellaneous syndrome for multiple errors, such as a corrected error counter, is read/write.WhenERR<n>STATUS.MV is set to 1, the miscellaneous syndrome for the most recently recorded error should ignore writes.

When ERR<n>STATUS.MV == 0b1, the miscellaneous syndrome specific to the most recently recorded error should ignore writes.

Note

These recommendations allow a counter to be reset in the presence of a persistent error, while preventing specific information, such as that identifying a FRU, from being lost if an error is detected while the previous error is being logged.

ERR<n>MISC3 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0x038 + 64n	ERR<n>MISC3

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERR<n>PFGCDN, Pseudo-fault Generation Countdown Register, n = 0 - 65534

The ERR<n>PFGCDN characteristics are:

Purpose

Generates one of the errors enabled in the corresponding ERR<n>PFGCTL register.

Configuration

~~This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERR<n>PFGCDN are RES0.~~

~~Present only when the RAS Common Fault Injection Model Extension is implemented by this node so that ERR<n>FR.INJ != 0b00, error record <n> is implemented, and error record <n> is the first error record owned by a node. Otherwise, RES0.~~

This~~RW~~ register~~fields~~ is~~in~~ present~~this~~ only when~~register~~ error~~reset~~ record <n> is implemented, the node implements the RAS Common Fault Injection Model Extension (ERR<n>FR.INJ != 0b00) and error record <n> is the first error record owned by a node. Otherwise, direct accesses to ERR<n>PFGCDN are~~architecturally~~ RES0~~UNKNOWN~~.~~values.~~

ERR<n>FR describes the features implemented by the node.

Attributes

ERR<n>PFGCDN is a 64-bit register.

Field descriptions

The ERR<n>PFGCDN bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
CDN																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

CDN, bits [31:0]

Countdown value.

This field is copied to Error Generation Counter when either:

- Software writes ERR<n>PFGCTL.CDNEN with 1.
- The Error Generation Counter decrements to zero and ERR<n>PFGCTL.R ==~~ 1.~~ 0b1.

While ERR<n>PFGCTL.CDNEN ==~~ 1 and the Error Generation Counter is nonzero, the counter decrements by 1 for each cycle at an~~ 0b1 and the Error Generation Counter is nonzero, the counter decrements by 1 for each cycle at an IMPLEMENTATION DEFINED clock rate. When the counter reaches 0, one of the errors enabled in the ERR<n>PFGCTL register is generated.

Note

The current Error Generation Counter value is not visible to software.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the ERR<n>PFGCDN

ERR<n>PFGCDN can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0x810 + 64n	ERR<n>PFGCDN

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERR<n>PFGCTL, Pseudo-fault Generation Control Register, n = 0 - 65534

The ERR<n>PFGCTL characteristics are:

Purpose

Enables controlled fault generation.

Configuration

~~This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERR<n>PFGCTL are RES0.~~

~~Present only when the RAS Common Fault Injection Model Extension is implemented by this node so that ERR<n>FR.INJ != 0b00, error record <n> is implemented, and error record <n> is the first error record owned by a node. Otherwise, RES0.~~

This~~Some~~ register~~or~~ is~~all~~ present~~RW~~ only when~~fields~~ error~~of~~ record~~this~~ <n>~~register~~ is~~have~~ implemented,~~defined~~ the~~reset~~ node implements the RAS Common Fault Injection Model Extension (ERR<n>FR.INJ != 0b00) and error record <n> is the first error record owned by a node. Otherwise, direct accesses to ERR<n>PFGCTL are~~values.~~ RES0.

ERR<n>FR describes the features implemented by the node.

Attributes

ERR<n>PFGCTL is a 64-bit register.

Field descriptions

The ERR<n>PFGCTL bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
CDNEN	R	RES0																		MV	AV	PN	ER	CI	CE		DE	UEO	UER	UEU	UC	OF
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

CDNEN, bit [31]

Countdown Enable. Controls transfers from the value that is held in the ERR<n>PFGCDN into the Error Generation Counter~~,~~ and enables this counter.

CDNEN	Meaning
0b0	The Error Generation Counter is disabled.
0b1	The Error Generation Counter is enabled. On a write of ~~1 to this bit, the Error Generation Counter is set to~~ 0b1 to this bit, the Error Generation Counter is set to ERR<n>PFGCDN.CDN.

The following resets apply:

~~On a Cold reset, this field resets to 0.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to `0`.

R, bit [30]

Restart. Controls whether, upon~~on~~ reaching zero, the Error Generation Counter restarts from the ERR<n>PFGCDN value~~,~~ or stops.

R	Meaning
`0b0`	On reaching 0, the Error Generation Counter will stop.~~stops.~~
`0b1`	On reaching 0, the Error Generation Counter is set to ERR<n>PFGCDN.CDN.

This bit is RES0 if the node does not support this control.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [29:13]

Reserved, RES0.

MV, bit [12]

Miscellaneous syndrome. The value that is written to ERR<n>STATUS.MV when an injected error is recorded.

MV	Meaning
`0b0`	ERR<n>STATUS.MV is set to ~~0 when an injected error is recorded.~~ `0b0` when an injected error is recorded.
`0b1`	ERR<n>STATUS.MV is set to ~~1 when an injected error is recorded.~~ `0b1` when an injected error is recorded.

This bit reads-as-one if the node always records some syndrome in ERR<n>MISC<m>, setting ERR<n>STATUS.MV to 1, when an injected error is recorded. This bit is RES0 if the node does not support this control.

The following resets apply:

~~This bit is RES0 if the node does not support this control.~~

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

AV, bit [11]

Address syndrome. The value that is written to ERR<n>STATUS.AV when an injected error is recorded.

AV	Meaning
`0b0`	ERR<n>STATUS.AV is set to ~~0 when an injected error is recorded.~~ `0b0` when an injected error is recorded.
`0b1`	ERR<n>STATUS.AV is set to ~~1 when an injected error is recorded,~~ `0b1` when an injected error is recorded.

This bit reads-as-one if the node always sets ERR<n>STATUS.AV to ~~1 when an injected error is recorded.~~ `0b1` when an injected error is recorded. This bit is RES0 if the node does not support this control.

The following resets apply:

~~This bit is RES0 if the node does not support this control.~~

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

PN, bit [10]

Poison flag. The value that is written to ERR<n>STATUS.PN when an injected error is recorded.

PN	Meaning
0b0	ERR<n>STATUS.PN is set to ~~0 when an injected error is recorded.~~ 0b0 when an injected error is recorded.
0b1	ERR<n>STATUS.PN is set to ~~1 when an injected error is recorded.~~ 0b1 when an injected error is recorded.

This bit is RES0 if the node does not support this control.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

ER, bit [9]

Error Reported flag. The value that is written to ERR<n>STATUS.ER when an injected error is recorded.

ER	Meaning
0b0	ERR<n>STATUS.ER is set to ~~0 when an injected error is recorded.~~ 0b0 when an injected error is recorded.
0b1	ERR<n>STATUS.ER is set to ~~1 when an injected error is recorded.~~ 0b1 when an injected error is recorded.

This bit is RES0 if the node does not support this control.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

CI, bit [8]

Critical Error flag. The value that is written to ERR<n>STATUS.CI when an injected error is recorded.

CI	Meaning
0b0	ERR<n>STATUS.CI is set to ~~0 when an injected error is recorded.~~ 0b0 when an injected error is recorded.
0b1	ERR<n>STATUS.CI is set to ~~1 when an injected error is recorded.~~ 0b1 when an injected error is recorded.

This bit is RES0 if the node does not support this control.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

CE, bits [7:6]

Corrected Error generation enable. Controls the type of Corrected Error condition that might be generated.

CE	Meaning
0b00	No error of this type will beis generated.
0b01	A non-specific Corrected Error, that is, a Corrected Error that is recorded as ERR<n>STATUS.CE == 0b10, might be generated when the Error Generation Counter decrements to zero.
0b10	A transient Corrected Error, that is, a Corrected Error that is recorded as ERR<n>STATUS.CE == 0b01, might be generated when the Error Generation Counter decrements to zero.
0b11	A persistent Corrected Error, that is, a Corrected Error that is recorded as ERR<n>STATUS.CE == 0b11, might be generated when the Error Generation Counter decrements to zero.

The set of permitted values for this field is defined by ERR<n>PFGF.CE.

This field is RES0 if the node does not support this control.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

DE, bit [5]

Deferred Error generation enable. Controls whether this type of error condition might be generated. It is IMPLEMENTATION DEFINED whether the error is generated if the data is not consumed.

DE	Meaning
0b0	No error of this type will beis generated.
0b1	An error of this type might be generated when the Error Generation Counter decrements to zero.

This bit is RES0 if the node does not support this control.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

UEO, bit [4]

Latent or Restartable Error generation enable. Controls whether this type of error condition might be generated. It is IMPLEMENTATION DEFINED whether the error is generated if the data is not consumed.

UEO	Meaning
0b0	No error of this type will beis generated.
0b1	An error of this type might be generated when the Error Generation Counter decrements to zero.

This bit is RES0 if the node does not support this control.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

UER, bit [3]

Signaled or Recoverable Error generation enable. Controls whether this type of error condition might be generated. It is IMPLEMENTATION DEFINED whether the error is generated if the data is not consumed.

UER	Meaning
0b0	No error of this type will beis generated.
0b1	An error of this type might be generated when the Error Generation Counter decrements to zero.

This bit is RES0 if the node does not support this control.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

UEU, bit [2]

Unrecoverable Error generation enable. Controls whether this type of error condition might be generated. It is IMPLEMENTATION DEFINED whether the error is generated if the data is not consumed.

UEU	Meaning
0b0	No error of this type will beis generated.
0b1	An error of this type might be generated when the Error Generation Counter decrements to zero.

This bit is RES0 if the node does not support this control.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

UC, bit [1]

Uncontainable Error generation enable. Controls whether this type of error condition might be generated. It is IMPLEMENTATION DEFINED whether the error is generated if the data is not consumed.

UC	Meaning
0b0	No error of this type will beis generated.
0b1	An error of this type might be generated when the Error Generation Counter decrements to zero.

This bit is RES0 if the node does not support this control.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

OF, bit [0]

Overflow flag. The value that is written to ERR<n>STATUS.OF when an injected error is recorded.

OF	Meaning
0b0	ERR<n>STATUS.OF is set to ~~0 when an injected error is recorded.~~ 0b0 when an injected error is recorded.
0b1	ERR<n>STATUS.OF is set to ~~1 when an injected error is recorded.~~ 0b1 when an injected error is recorded.

This bit is RES0 if the node does not support this control.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On an Error recovery reset, the value of this field is unchanged.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the ERR<n>PFGCTL

ERR<n>PFGCTL can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0x808 + 64n	ERR<n>PFGCTL

Accesses on this interface are **RW**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERR<n>PFGF, Pseudo-fault Generation Feature Register, n = 0 - 65534

The ERR<n>PFGF characteristics are:

Purpose

Defines which common architecturally-defined fault generation features are implemented.

Configuration

~~This register is present only when ARMv8.4-RAS is implemented. Otherwise, direct accesses to ERR<n>PFGF are RES0.~~

~~Present only when the RAS Common Fault Injection Model Extension is implemented by this node so that ERR<n>FR.INJ != 0b00, error record <n> is implemented, and error record <n> is the first error record owned by a node. Otherwise, RES0.~~

This register is present only when error record <n> is implemented, the node implements the RAS Common Fault Injection Model Extension (ERR<n>FR.INJ != 0b00) and error record <n> is the first error record owned by a node. Otherwise, direct accesses to ERR<n>PFGF are RES0.

ERR<n>FR describes the features implemented by the node.

Attributes

ERR<n>PFGF is a 64-bit register.

Field descriptions

The ERR<n>PFGF bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
RES0	R	SYN	RES0																MV	AV	PN	ER	CI	CE		DE	UEO	UER	UEU	UC	OF
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:31]

Reserved, RES0.

R, bit [30]

Restartable. Support for Error Generation Counter restart mode.

R	Meaning
0b0	The node does not support this feature.
0b1	Feature controllable.

SYN, bit [29]

Syndrome. Fault syndrome injection.

SYN	Meaning
0b0	When an injected error is recorded, the node sets ERR<n>STATUS.{IERR, SERR} to IMPLEMENTATION DEFINED values. ERR<n>STATUS.{IERR, SERR} are UNKNOWN when ERR<n>STATUS.V ==~~ 0.~~ 0b0.
0b1	When an injected error is recorded, the node does not update the ERR<n>STATUS.{IERR, SERR} fields. ERR<n>STATUS.{IERR, SERR} are writable when ERR<n>STATUS.V ==~~ 0.~~ 0b0.

Note

If ERR<n>PFGF.SYN~~this ==bit is 1, software can write specific values into the~~ 0b1, software can write specific values into the ERR<n>STATUS.{IERR, SERR} fields when setting up a fault injection event. The sets of values that can be written to these fields is IMPLEMENTATION DEFINED.

Bits [28:13]

Reserved, RES0.

MV, bit [12]

Miscellaneous syndrome.

Additional syndrome injection. Defines whether software can control all or part of the syndrome recorded in the ERR<n>MISC<m> registers when an injected error is recorded.

It is IMPLEMENTATION DEFINED which syndrome fields in ERR<n>MISC<m> this refers to, as some fields might always be recorded by an error. For example, a Corrected Error counter.

MV	Meaning
0b0	When an injected error is recorded, the node might record IMPLEMENTATION DEFINED additional syndrome in ERR<n>MISC<m>. If any syndrome is recorded in ERR<n>MISC<m>, then ERR<n>STATUS.MV is set to ~~1.~~ 0b1.
0b1	When an injected error is recorded, the node does not update all the syndrome fields in the ERR<n>MISC<m> and does one of: • The node does not update any fields in ERR<n>MISC<m> and sets ERR<n>STATUS.MV to ERR<n>PFGCTL.MV. • The node records some syndrome in ERR<n>MISC<m> and sets ERR<n>STATUS.MV to ~~1. ERR<n>PGFCTL.MV is RAO.~~ 0b1. ERR<n>PGFCTL.MV is RAO. The syndrome fields that the node does not update are unchanged and must be writable when ERR<n>STATUS.MV ==~~is set to 0.~~ 0b0.

Note

If ~~this bit is 1, software can write specific values into the~~ ERR<n>PFGF.MV~~MISC<m> ==registers when setting up a fault injection event. The values that can be written to these registers are~~ 0b1, software can write specific values into the ERR<n>MISC<m> registers when setting up a fault injection event. The values that can be written to these registers are IMPLEMENTATION DEFINED.

AV, bit [11]

Address syndrome. Address syndrome injection.

AV	Meaning
0b0	When an injected error is recorded, the node either sets ERR<n>ADDR and ERR<n>STATUS.AV for the access, or leaves these unchanged.
0b1	When an injected error is recorded, the node does not update ERR<n>ADDR and does one of: • Sets ERR<n>STATUS.AV to ERR<n>PFGCTL.AV. • Sets ERR<n>STATUS.AV to 0b1. ERR<n>PFGCTL.AV is RAO. • ~~Sets ERR<n>STATUS.AV to 1. ERR<n>PFGCTL.AV is RAO.~~ ~~ERR<n>ADDR must be writable when ERR<n>STATUS.AV is set to 0.~~ ERR<n>ADDR must be writable when ERR<n>STATUS.AV == 0b0.

Note

If ERR<n>PFGF.AV~~this~~ ==~~bit is 1, software can write a specific value into~~ 0b1, software can write a specific value into ERR<n>ADDR when setting up a fault injection event.

PN, bit [10]

Poison flag. Describes how the fault generation feature of the node sets the ERR<n>STATUS.PN status flag.

PN	Meaning
0b0	When an injected error is recorded, it is IMPLEMENTATION DEFINED whether the node sets ERR<n>STATUS.PN to ~~1.~~ 0b1.
0b1	When an injected error is recorded, ERR<n>STATUS.PN is set to ERR<n>PFGCTL.PN.

This behavior replaces the architecture-defined rules for setting the PN bit.

This bit reads-as-zero if the node does not support this flag.

ER, bit [9]

Error Reported flag. Describes how the fault generation feature of the node sets the ERR<n>STATUS.ER status flag.

ER	Meaning
0b0	When an injected error is recorded, the node sets ERR<n>STATUS.ER according to the architecture-defined rules for setting the ER bit.
0b1	~~This behavior replaces the architecture-defined rules for setting the ER bit.~~ When an injected error is recorded, ERR<n>STATUS.ER is set to ERR<n>PFGCTL.ER. This behavior replaces the architecture-defined rules for setting the ER bit.

This bit reads-as-zero if the node does not support this flag.

CI, bit [8]

Critical Error flag. Describes how the fault generation feature of the node sets the ERR<n>STATUS.CI status flag.

CI	Meaning
0b0	When an injected error is recorded, it is IMPLEMENTATION DEFINED whether the node sets ERR<n>STATUS.CI to ~~1.~~ 0b1.
0b1	When an injected error is recorded, ERR<n>STATUS.CI is set to ERR<n>PFGCTL.CI.

This behavior replaces the architecture-defined rules for setting the CI bit.

This bit reads-as-zero if the node does not support this flag.

CE, bits [7:6]

Corrected Error generation. Describes the types of Corrected Error that the fault generation feature of the node can generate.

CE	Meaning
0b00	The fault generation feature of the node cannot generate this type of error.
0b01	The fault generation feature of the node allows generation of a non-specific Corrected Error, that is, a Corrected Error that is recorded as ERR<n>STATUS.CE == 0b10.
0b11	The fault generation feature of the node allows generation of transient or persistent Corrected Errors, that is, Corrected Errors that are recorded as ERR<n>STATUS.CE == 0b01 and 0b11.

All other values are reserved.

This fieldbit reads-as-zerosreads-as-zero if the node does not support this type of error.

DE, bit [5]

Deferred Error generation. Describes whether the fault generation feature of the node can generate this type of error.

DE	Meaning
0b0	The fault generation feature of the node cannot generate this type of error.
0b1	The fault generation feature of the node allows generation of this type of error.

This bit reads-as-zero if the node does not support this type of error.

UEO, bit [4]

Latent or Restartable Error generation. Describes whether the fault generation feature of the node can generate this type of error.

UEO	Meaning
0b0	The fault generation feature of the node cannot generate this type of error.
0b1	The fault generation feature of the node allows generation of this type of error.

This bit reads-as-zero if the node does not support this type of error.

UER, bit [3]

Signaled or Recoverable Error generation. Describes whether the fault generation feature of the node can generate this type of error.

UER	Meaning
0b0	The fault generation feature of the node cannot generate this type of error.
0b1	The fault generation feature of the node allows generation of this type of error.

This bit reads-as-zero if the node does not support this type of error.

UEU, bit [2]

Unrecoverable Error generation. Describes whether the fault generation feature of the node can generate this type of error.

UEU	Meaning
0b0	The fault generation feature of the node cannot generate this type of error.
0b1	The fault generation feature of the node allows generation of this type of error.

This bit reads-as-zero if the node does not support this type of error.

UC, bit [1]

Uncontainable Error generation. Describes whether the fault generation feature of the node can generate this type of error.

UC	Meaning
0b0	The fault generation feature of the node cannot generate this type of error.
0b1	The fault generation feature of the node allows generation of this type of error.

This bit reads-as-zero if the node does not support this type of error.

OF, bit [0]

Overflow flag. Describes how the fault generation feature of the node sets the ERR<n>STATUS.OF status flag.

OF	Meaning
0b0	When an injected error is recorded, the node sets ERR<n>STATUS.OF according to the architecture-defined rules for setting the OF bit.
0b1	When an injected error is recorded, ERR<n>STATUS.OF is set to ERR<n>PFGCTL.OF. This behavior replaces the architecture-defined rules for setting the OF bit.

This bit reads-as-zero if the node does not support this flag.

Accessing the ERR<n>PFGF

ERR<n>PFGF can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	0x800 + 64n	ERR<n>PFGF

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERR<n>STATUS, Error Record Primary Status Register, n = 0 - 65534

The ERR<n>STATUS characteristics are:

Purpose

Contains status information for the error record, including:

- ~~Whether any error has been detected (valid).~~

  Whether any error has been detected (valid).

- ~~Whether any detected error was not corrected, and returned to a master.~~

  Whether any detected error was not corrected, and returned to a master.

- ~~Whether any detected error was not corrected and deferred.~~

  Whether any detected error was not corrected and deferred.

- ~~Whether an error record has been discarded because additional errors have been detected before the first error was handled by software (overflow).~~

  Whether an error record has been discarded because additional errors have been detected before the first error was handled by software (overflow).

- ~~Whether any error has been reported.~~

  Whether any error has been reported.

- ~~Whether the other error record registers contain valid information.~~

  Whether the other error record registers contain valid information.

- ~~Whether the error was recorded because poison data was detected or because a corrupt value was detected by an error detection code.~~

  Whether the error was reported because poison data was detected or because a corrupt value was detected by an error detection code.

- ~~A primary error code.~~

  A primary error code.

- An IMPLEMENTATION DEFINED extended error code.

- ~~An IMPLEMENTATION DEFINED extended error code.~~

Within this register:

- ~~The {AV, V, MV} bits are valid bits that define whether the error record registers are valid.~~

  The {AV, V, MV} bits are valid bits that define whether the error record registers are valid.

- ~~The {UE, OF, CE, DE, UET} bits encode the type of error or errors recorded.~~

  The {UE, OF, CE, DE, UET} bits encode the types of error or errors recorded.

- ~~The {CI, ER, PN, IERR, SERR} fields are syndrome fields.~~

  The {CI, ER, PN, IERR, SERR} fields are syndrome fields.

Configuration

This register is present only when RAS is implemented. Otherwise, direct accesses to ERR<n>STATUS are UNDEFINED.

The number of error records that are implemented is IMPLEMENTATION DEFINED.

If error record <n> is not implemented, ERR<n>STATUS is RES0.

ThisSome registeror isall presentRW only whenfields errorof recordthis <n>register ishave implemented. Otherwise,defined directreset accesses to ERR<n>STATUS arevalues. RES0.

ERR<q>FR describes the features implemented by the node that owns error record <n>. <q> is the index of the first error record owned by the same node as error record <n>. If the node owns a single record, then q = n.

For IMPLEMENTATION DEFINED fields in ERR<n>STATUSthis register, writing zero must always be supported to return the error record to an initial quiescent state.

In particular, if any IMPLEMENTATION DEFINED syndrome fields might generate a Fault Handling or Error Recovery Interrupt request, writing zero is sufficient to deactivate the Interrupt request.

Fields that are read-only, non-zero, and ignore writes are compliant with this requirement.

Note

Arm recommends that any IMPLEMENTATION DEFINED syndrome fields that can generate a Fault Handling, Error Recovery, Critical, or IMPLEMENTATION DEFINED, interrupt request are disabled at Cold reset and are enabled by software writing an IMPLEMENTATION DEFINED non-zero value to an IMPLEMENTATION DEFINED field in ERR<q>CTRL.CTRL, where q is the index of the first error record owned by the same node as error record n. If the node owns a single record then q = n.

Attributes

ERR<n>STATUS is a 64-bit register.

Field descriptions

The ERR<n>STATUS bit assignments are:

When RAS System Architecture v1.1ARMv8.4-RAS is implemented:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
AV	V	UE	ER	OF	MV	CE			DE	PN	UET		CI	RES0				IERR										SERR			
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

AV, bit [31]

When the error record includes an address associated with an error:

Address Valid.

AV	Meaning
0b0	ERR<n>ADDR not valid.
0b1	ERR<n>ADDR contains an address associated with the highest priority error recorded by this record.

This bit is read/write-one-to-clear.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to 0.

Otherwise:

Reserved, RES0.

V, bit [30]

Status Register Valid.

V	Meaning
0b0	ERR<n>STATUS not valid.
0b1	ERR<n>STATUS valid. At least one error has been recorded.

This bit is read/write-one-to-clear.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to 0.

UE, bit [29]

Uncorrected Error.error.

UE	Meaning
0b0	No errors have been detected, or all detected errors have been either corrected or deferred.
0b1	At least one detected error was not corrected and not deferred.

When clearing ERR<n>STATUS.V to 0, if this bit is nonzero, then software must write one to this bit to clear this bit to zero. 0b0, if this bit is nonzero, then software must write 0b1 to this bit to clear this bit to zero.

This bit is not valid and reads UNKNOWN if ERR<n>STATUS.V ==is set to 0. 0b0.

This bit is read/write-one-to-clear.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

ER, bit [28]

Error Reported.

ER	Meaning
0b0	No in-band error (External Abortabort) reported.
0b1	An External Abortabort was signaled by the node to the master making the access or other transaction. This can be because any of the following are true: • The applicable one of the ERR<q>CTLR.{WUE,RUE,UE} bits is implemented and was set to 0b1 when an Uncorrected error was detected. • The applicable one of the ERR<q>CTLR.{WUE,RUE,UE} bits is implemented, and was set to 1 when an Uncorrected error was detected. • The applicable one of the ERR<q>CTLR.{WUE,RUE,UE} bits is not implemented. The applicable one of the ERR<q>CTLR.{WUE,RUE,UE} bits is not implemented and the node always reports errors.

It is IMPLEMENTATION DEFINED whether this bit can be set to 1 by a Deferred error. 0b1 by a Deferred error.

When clearing ERR<n>STATUS.V to 0, if this bit is nonzero, then software must write one to this bit to clear this bit to zero. 0b0, if this bit is nonzero, then software must write 0b1 to this bit to clear this bit to zero.

This bit is not valid and reads UNKNOWN if any of the following are true:

- ERR<n>STATUS.V == 0b0.
- ERR<n>STATUS.V is set to 0.
- ERR<n>STATUS.UE == 0b0 and this bit is never set to 0b1 by a Deferred error.
- ERR<n>STATUS.UE is set to 0 and this bit is never set to 1 by a Deferred error.
- ERR<n>STATUS.{UE,DE} == {0,0} and this bit can be set to 0b1 by a Deferred error.
- ERR<n>STATUS.{UE, DE} are both set to 0, and this bit can be set to 1 by a Deferred error.

This bit is read/write-one-to-clear.

Note

An External Abortabort signaled by the node might be masked and not generate any exception.

The following resets apply:

- OnThis anbit Errorís recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

OF, bit [27]

Overflow.

Indicates that multiple errors have been detected. This bit is set to 1 when one of the following occurs: 0b1 when one of the following occurs:

- A Corrected error counter is implemented, an error is counted, and the counter overflows.
- A Corrected error counter is implemented, an error is counted, and the counter overflows.
- ERR<n>STATUS.V was previously set to 0b1, a Corrected error counter is not implemented, and a Corrected error is recorded.
- ERR<n>STATUS.V was previously set to 1, a Corrected error counter is not implemented, and a Corrected error is recorded.
- ERR<n>STATUS.V was previously set to 0b1, and a type of error other than a Corrected error is recorded.
- ERR<n>STATUS.V was previously set to 1, and a type of error other than a Corrected error is recorded.

Otherwise, this bit is unchanged when an error is recorded.

If a Corrected error counter is implemented:

- A direct write that modifies the counter overflow flag indirectly might set this bit to an UNKNOWN value.
- A direct write that modifies the counter overflow flag indirectly might set this bit to an UNKNOWN value.
- A direct write to this bit that clears this bit to zero might indirectly set the counter overflow flag to an UNKNOWN value.
- A direct write to this bit that clears this bit to zero might indirectly set the counter overflow flag to an UNKNOWN value.

OF	Meaning
0b0	Since this bit was last cleared to zero, no error syndrome has been discarded and, if a Corrected error counter is implemented, it has not overflowed.
0b1	Since this bit was last cleared to zero, at least one error syndrome has been discarded or, if a Corrected error counter is implemented, it might have overflowed.

WhenIf this bit is nonzero, then software must write 1 to this bit, to clear this bit to zero, when clearing ERR<n>STATUS.V to 0. 0b0, if this bit is nonzero, then software must write 0b1 to this bit to clear this bit to zero.

This bit is not valid and reads UNKNOWN if ERR<n>STATUS.V ==is set to 0. 0b0.

This bit is read/write-one-to-clear.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

MV, bit [26]

When the error record includes an additional information for an error:

Miscellaneous Registers Valid.

MV	Meaning
0b0	ERR<n>MISC0, ERR<n>MISC1, ERR<n>MISC2, and ERR<n>MISC3ERR<n>MISC<m>are not valid.
0b1	The IMPLEMENTATION DEFINED contents of the ERR<n>MISC<m> registers contains additional information for an error recorded by this record.ERR<n>MISC0, ERR<n>MISC1, ERR<n>MISC2, and ERR<n>MISC3 registers contain additional information for an error recorded by this record.

This bit is read/write-one-to-clear.

Note

If the ERR<n>MISC<m> registers can contain additional information for a previously recorded error, then the contents must be self-describing to software or a user. For example, certain fields might relate only to Corrected errors, and other fields only to the most recent error that was not discarded.ERR<n>MISC0, ERR<n>MISC1, ERR<n>MISC2, and ERR<n>MISC3 registers can contain additional information for a previously recorded error, then the contents must be self-describing to software or a user. For example, certain fields might relate only to Corrected errors, and other fields only to the most recent error that was not discarded.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to 0.

Otherwise:

Reserved, RES0.

CE, bits [25:24]

Corrected Error.

CE	Meaning
0b00	No errors were corrected.
0b01	At least one transient error was corrected.
0b10	At least one error was corrected.
0b11	At least one persistent error was corrected.

The mechanism by which a node detects whether a correctable error is transient or persistent is IMPLEMENTATION DEFINED. If no such mechanism is implemented, then the node sets this field to 0b10 when an error is corrected.

When clearing ERR<n>STATUS.V to ~~0, if this field is nonzero, then software must write ones to this field to clear this field to zero.~~ 0b0, if this field is nonzero, then software must write ones to this field to clear this field to zero.

This~~If ERR<n>STATUS.V is set to 0, this~~ field is not valid and reads UNKNOWN if ERR<n>STATUS.V ==~~.~~ 0b0.

This field is read/write-ones-to-clear.~~write-one-to-clear.~~ Writing a value other than all-zeros or all-ones sets this field to an UNKNOWN value.

The following resets apply:

- On~~This~~ an~~field~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

DE, bit [23]

Deferred Error.

DE	Meaning
0b0	No errors were deferred.
0b1	At least one error was not corrected and deferred.

Support for deferring errors is IMPLEMENTATION DEFINED.

When clearing ERR<n>STATUS.V to ~~0, if this bit is nonzero, then software must write 1 to this bit to clear this bit to zero.~~ 0b0, if this bit is nonzero, then software must write 0b1 to this bit to clear this bit to zero.

This~~If ERR<n>STATUS.V is set to 0, this~~ bit is not valid and reads UNKNOWN if ERR<n>STATUS.V ==~~.~~ 0b0.

This bit is read/write-one-to-clear.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

PN, bit [22]

Poison.

PN	Meaning
0b0	Uncorrected error or Deferred error recorded because a corrupt value was detected, for example, by an error detection code (EDC). **Note** If a producer node detects a corrupt value and defers the error by producing a poison value, then this bit is set to ~~0 at the producer node.~~ 0b0 at the producer node.
0b1	Uncorrected error or Deferred error recorded because a poison value was detected. **Note** This might only be an indication of poison, because, in some EDC schemes, a poison value is encoded as an unlikely form of corrupt data, meaning it is possible to mistake a corrupt value as a poison value.

It is IMPLEMENTATION DEFINED whether a node can distinguish a poison value from a corrupt value.

When clearing ERR<n>STATUS.V to ~~0, if this bit is nonzero, then software must write 1 to this bit to clear this bit to zero.~~ 0b0, if this bit is nonzero, then software must write 0b1 to this bit to clear this bit to zero.

This bit is not valid and reads UNKNOWN if any of the following are true:

- ERR<n>STATUS.V == 0b0.
- ~~ERR<n>STATUS.V is set to 0.~~
- ~~ERR<n>STATUS.{DE, UE} are both set to 0.~~

  ERR<n>STATUS.{DE,UE} == {0,0}.

This bit is read/write-one-to-clear.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

UET, bits [21:20]

~~Describes the state of the component after detecting or consuming an Uncorrected error.~~

Uncorrected Error Type. Describes the state of the component after detecting or consuming an Uncorrected error.

UET	Meaning
0b00	Uncorrected error, Uncontainable error (UC).
0b01	Uncorrected error, Unrecoverable error (UEU).
0b10	Uncorrected error, Latent or Restartable error (UEO).
0b11	Uncorrected error, Signaled or Recoverable error (UER).

When clearing ERR<n>STATUS.V to ~~0, if this field is nonzero, then software must write ones to this field to clear this field to zero.~~ 0b0, if this field is nonzero, then software must write ones to this field to clear this field to zero.

This field is not valid and reads UNKNOWN if any of the following are true:

- ERR<n>STATUS.V == 0b0.
- ~~ERR<n>STATUS.V is set to 0.~~
- ERR<n>STATUS.UE == 0b0.
- ~~ERR<n>STATUS.UE is set to 0.~~

This field is read/write-ones-to-clear.~~write-one-to-clear.~~ Writing a value other than all-zeros or all-ones sets this field to an UNKNOWN value.

Note

Software might use the information in the error record registers to determine what recovery is necessary.

The following resets apply:

- OnThis anfield Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

CI, bit [19]

Indicates whether a critical error condition has been recorded.

Critical Error. Indicates whether a critical error condition has been recorded.error.

CI	Meaning
0b0	No critical error condition.condition recorded.
0b1	Critical error condition.condition recorded.

When clearing ERR<n>STATUS.V to 0, if this bit is nonzero, then software must write 1 to this bit to clear this bit to zero. 0b0, if this bit is nonzero, then software must write 0b1 to this bit to clear this bit to zero.

This bit is not valid and reads UNKNOWN if ERR<n>STATUS.V ==is set to 0. 0b0.

This bit is read/write-one-to-clear.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [18:16]

Reserved, RES0.

IERR, bits [15:8]

This field is not valid and reads UNKNOWN if ERR<n>STATUS.V is set to 0.

IMPLEMENTATION DEFINED error code. Used with any primary error code SERR value. Further IMPLEMENTATION DEFINED information can be placed in the MISC registers.

ThisUsed fieldwith isany notprimary validerror andcode readsSERR value. Further UNKNOWNIMPLEMENTATION DEFINED if ERR<n>STATUS.V == 0b0.information can be placed in the MISC registers.

The following resets apply:

- OnThis anfield Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

SERR, bits [7:0]

Indicates the type of error. The primary error code might be used by a fault handling agent to triage an error without requiring device-specific code. For example, to count and threshold corrected errors in software, or generate a short log entry.

Architecturally-defined primary error code. The primary error code might be used by a fault handling agent to triage an error without requiring device-specific code. For example, to count and threshold corrected errors in software, or generate a short log entry.

SERR	Meaning
0x00	No error.
0x01	IMPLEMENTATION DEFINED error.
0x02	Data value from (non-associative) internal memory. For example, ECC from on-chip SRAM or buffer.
0x03	IMPLEMENTATION DEFINED pin. For example, **nSEI** pin.
0x04	Assertion failure. For example, consistency failure.
0x05	Error detected on internal data path. For example, parity on ALU result.
0x06	Data value from associative memory. For example, ECC error on cache data.
0x07	Address/control value from associative memory. For example, ECC error on cache tag.
0x08	Data value from a TLB. For example, ECC error on TLB data.
0x09	Address/control value from a TLB. For example, ECC error on TLB tag.
0x0A	Data value from producer. For example, parity error on write data bus.
0x0B	Address/control value from producer. For example, parity error on address bus.
0x0C	Data value from (non-associative) external memory. For example, ECC error in SDRAM.
0x0D	Illegal address (software fault). For example, access to unpopulated memory.
0x0E	Illegal access (software fault). For example, byte write to word register.
0x0F	Illegal state (software fault). For example, device not ready.
0x10	Internal data register. For example, parity on a SIMD&FP register. For a PE, all general-purpose, stack pointer, SIMD&FP, and SVE registers are data registers.
0x11	Internal control register. For example, Parity on a System register. For a PE, all registers other than general-purpose, stack pointer, SIMD&FP, and SVE registers are control registers.
0x12	Error response from slave. For example, error response from cache write-back.
0x13	External timeout. For example, timeout on interaction with another node.
0x14	Internal timeout. For example, timeout on interface within the node.
0x15	Deferred error from slave not supported at master. For example, poisoned data received from a slave by a master that cannot defer the error further.
0x16	Deferred error from master not supported at slave. For example, poisoned data received from a master by a slave that cannot defer the error further.
0x17	Deferred error from slave passed through. For example, poisoned data received from a slave and returned to a master.
0x18	Deferred error from master passed through. For example, poisoned data received from a master and deferred to a slave.
0x19	Error recorded by PCIe error logs. Indicates that the node has recorded an error in a PCIe error log. This might be the PCIe device status register, AER, DVSEC, or other mechanisms defined by PCIe.

All other values are reserved. ~~Reserved values might be defined in a future version of the architecture.~~

This field is not valid and reads UNKNOWN if ERR<n>STATUS.V ==~~is set to 0.~~ 0b0.

The following resets apply:

- On~~This~~ an~~field~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

When RAS System Architecture v1.0 is implemented~~Otherwise~~:



Bits [63:32]

Reserved, RES0.

AV, bit [31]

When the error record includes an address associated with an error:

Address Valid.

AV	Meaning
0b0	ERR<n>ADDR not valid.
0b1	ERR<n>ADDR contains an address associated with the highest priority error recorded by this record.

This bit ignores writes if ~~any of~~ ERR<n>STATUS.{CE, DE, UE} !=~~are~~ ~~{set to 1, and the highest priority of these is not being cleared to 0 in the same write.~~0b00,0,0}, and the highest priority of these is not being cleared to zero in the same write.

This bit is read/write-one-to-clear.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to 0.

~~Otherwise:~~

Reserved, RES0.

V, bit [30]

Status Register Valid.

V	Meaning
0b0	ERR<n>STATUS not valid.
0b1	ERR<n>STATUS valid. At least one error has been recorded.

This bit ignores writes if ~~any of~~ ERR<n>STATUS.{CE, DE, UE} !=~~are~~ ~~{set to 1, and and is not being cleared to 0 in the same write.~~0b00,0,0}, and is not being cleared to 0b0 in the same write.

This bit is read/write-one-to-clear.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to 0.

UE, bit [29]

Uncorrected Error.~~error.~~

UE	Meaning
0b0	No errors have been detected, or all detected errors have been either corrected or deferred.
0b1	At least one detected error was not corrected and not deferred.

This bit is not valid and reads UNKNOWN if ERR<n>STATUS.V is set to 0.

When clearing ERR<n>STATUS.V to 0, if this bit is nonzero, then software must write one to this bit to clear this bit to zero. 0b0, if this bit is nonzero, then software must write 0b1 to this bit to clear this bit to zero.

ThisIf bitERR<n>STATUS.OF is notset validto 1 and readsis not being cleared to 0 in the same write, this bit ignores writes. UNKNOWN if ERR<n>STATUS.V == 0b0. This bit ignores writes if ERR<n>STATUS.OF == 0b1 and is not being cleared to 0b0 in the same write.

This bit is read/write-one-to-clear.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

ER, bit [28]

Error Reported.

ER	Meaning
0b0	No in-band error (External Abortabort) reported.
0b1	An External Abortabort was signaled by the node to the master making the access or other transaction. This can be because any of the following are true: • The applicable one of the ERR<q>CTLR.{WUE,RUE,UE} bits is implemented and was set to 0b1 when an Uncorrected error was detected. • The applicable one of the ERR<q>CTLR.{WUE,RUE,UE} bits is implemented, and was set to 1 when an Uncorrected error was detected. • The applicable one of the ERR<q>CTLR.{WUE,RUE,UE} bits is not implemented. The applicable one of the ERR<q>CTLR.{WUE,RUE,UE} bits is not implemented and the node always reports errors.

It is IMPLEMENTATION DEFINED whether this bit can be set to 1 by a Deferred error. 0b1 by a Deferred error.

If this bit is nonzero, then software must write 1 to this bit, to clear this bit to zero, when: 0b1 to this bit to clear this bit to zero, when any of:

- Clearing ERR<n>STATUS.V to 0b0.
- Clearing ERR<n>STATUS.V to 0.
- Clearing ERR<n>STATUS.UE to 0b0, if this bit is never set to 0b1 by a Deferred error.
- Clearing ERR<n>STATUS.UE to 0, if this bit is never set to 1 by a Deferred error.
- Clearing ERR<n>STATUS.{UE,DE} to {0,0}, if this bit can be set to 0b1 by a Deferred error.
- Clearing both ERR<n>STATUS.{UE, DE} to 0, if this bit can be set to 1 by a Deferred error.

This bit is not valid and reads UNKNOWN if any of the following are true:

- ERR<n>STATUS.V == 0b0.
- ERR<n>STATUS.V is set to 0.
- ERR<n>STATUS.UE == 0b0 and this bit is never set to 0b1 by a Deferred error.
- ERR<n>STATUS.UE is set to 0 and this bit is never set to 1 by a Deferred error.
- ERR<n>STATUS.{UE,DE} == {0,0} and this bit can be set to 0b1 by a Deferred error.

- ~~ERR<n>STATUS.{UE, DE} are both set to 0, and this bit can be set to 1 by a Deferred error.~~

This bit ignores writes if ~~any of~~ ERR<n>STATUS.{CE, DE, UE} !=~~are~~ {~~set to 1, and the highest priority of these is not being cleared to 0 in the same write.~~`0b00`,0,0}, and the highest priority of these is not being cleared to zero in the same write.

This bit is read/write-one-to-clear.

Note

An External Abort~~abort~~ signaled by the node might be masked and not generate any exception.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

OF, bit [27]

Overflow.

Indicates that multiple errors have been detected. This bit is set to ~~1 when one of the following occurs:~~ `0b1` when one of the following occurs:

- An Uncorrected error is detected and ERR<n>STATUS.UE == `0b1`.
  - ~~An Uncorrected error is detected and ERR<n>STATUS.UE == 1.~~
- A Deferred error is detected, ERR<n>STATUS.UE == `0b0` and ERR<n>STATUS.DE == `0b1`.
  - ~~A Deferred error is detected, ERR<n>STATUS.UE == 0 and ERR<n>STATUS.DE == 1.~~
- A Corrected error is detected, no Corrected error counter is implemented, ERR<n>STATUS.UE == `0b0`, ERR<n>STATUS.DE == `0b0`, and ERR<n>STATUS.CE != `0b00`. ERR<n>STATUS.CE might be updated for the new Corrected error.
  - ~~A Corrected error is detected, no Corrected error counter is implemented, ERR<n>STATUS.UE == 0, ERR<n>STATUS.DE == 0, and ERR<n>STATUS.CE != `0b00`. ERR<n>STATUS.CE might be updated for the new Corrected error.~~
- A Corrected error counter is implemented, ERR<n>STATUS.UE == `0b0`, ERR<n>STATUS.DE == `0b0`, and the counter overflows.
  - ~~A Corrected error counter is implemented, ERR<n>STATUS.UE == 0, ERR<n>STATUS.DE == 0, and the counter overflows.~~

It is IMPLEMENTATION DEFINED whether this bit is set to ~~1 when one of the following occurs:~~ `0b1` when one of the following occurs:

- A Deferred error is detected and ERR<n>STATUS.UE == `0b1`.
  - ~~A Deferred error is detected and ERR<n>STATUS.UE == 1.~~
- A Corrected error is detected, no Corrected error counter is implemented, and either or both the ERR<n>STATUS.UE or ERR<n>STATUS.DE bits are set to `0b1`.
  - ~~A Corrected error is detected, no Corrected error counter is implemented, and either or both the ERR<n>STATUS.UE or ERR<n>STATUS.DE bits are set to 1.~~
- A Corrected error counter is implemented, either or both the ERR<n>STATUS.UE or ERR<n>STATUS.DE bits are set to `0b1`, and the counter overflows.
  - ~~A Corrected error counter is implemented, either or both the ERR<n>STATUS.UE or ERR<n>STATUS.DE bits are set to 1, and the counter overflows.~~

It is IMPLEMENTATION DEFINED whether this bit is cleared~~set~~ to ~~0 when one of the following occurs:~~ `0b0` when one of the following occurs:

- An Uncorrected error is detected and ERR<n>STATUS.UE == 0b0.
- ~~An Uncorrected error is detected and ERR<n>STATUS.UE == 0.~~
- A Deferred error is detected, ERR<n>STATUS.UE == 0b0 and ERR<n>STATUS.DE == 0b0.
- ~~A Deferred error is detected, ERR<n>STATUS.UE == 0 and ERR<n>STATUS.DE == 0.~~
- A Corrected error is detected, ERR<n>STATUS.UE == 0b0, ERR<n>STATUS.DE == 0b0 and ERR<n>STATUS.CE == 0b00.
- ~~A Corrected error is detected, ERR<n>STATUS.UE == 0, ERR<n>STATUS.DE == 0 and ERR<n>STATUS.CE == 0b00.~~

The IMPLEMENTATION DEFINED clearing of this bit might also depend on the value of the other error status bits.

If a Corrected error counter is implemented:

- A direct write that modifies the counter overflow flag indirectly might set this bit to an UNKNOWN value.
- ~~A direct write that modifies the counter overflow flag indirectly might set this bit to an UNKNOWN value.~~
- A direct write to this bit that clears this bit to 0b0 might indirectly set the counter overflow flag to an UNKNOWN value.
- ~~A direct write to this bit that clears this bit to 0 might indirectly set the counter overflow flag to an UNKNOWN value.~~

OF	Meaning
0b0	If ERR<n>STATUS.UE == ~~1, then no error syndrome for an Uncorrected error has been discarded.~~ 0b1, then no error syndrome for an Uncorrected error has been discarded. If ERR<n>STATUS.UE == ~~0 and ERR<n>STATUS.DE == 1, then no error syndrome for a Deferred error has been discarded.~~ 0b0 and ERR<n>STATUS.DE == 0b1, then no error syndrome for a Deferred error has been discarded. If ERR<n>STATUS.UE == ~~0, ERR<n>STATUS.DE == 0, and a Corrected error counter is implemented, then the counter has not overflowed.~~ 0b0, ERR<n>STATUS.DE == 0b0, and a Corrected error counter is implemented, then the counter has not overflowed. If ERR<n>STATUS.UE == ~~0, ERR<n>STATUS.DE == 0, ERR<n>STATUS.CE !=~~ 0b0, ERR<n>STATUS.DE == 0b0, ERR<n>STATUS.CE != 0b00, and no Corrected error counter is implemented, then no error syndrome for a Corrected error has been discarded. **Note** This bit might have been set to ~~1 when an error syndrome was discarded and later cleared to 0 when a higher priority syndrome was recorded.~~ 0b1 when an error syndrome was discarded and later cleared to 0b0 when a higher priority syndrome was recorded.
0b1	At least one error syndrome has been discarded or, if a Corrected error counter is implemented, it might have overflowed.

When~~If this bit is nonzero, then software must write 1 to this bit, to clear this bit to zero, when~~ clearing ERR<n>STATUS.V to ~~0.~~ 0b0, if this bit is nonzero, then software must write 0b1 to this bit to clear this bit to zero.

This bit is not valid and reads UNKNOWN if ERR<n>STATUS.V ==~~is set to 0.~~ 0b0.

This bit is read/write-one-to-clear.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

MV, bit [26]

When the error record includes an additional information for an error:

Miscellaneous Registers Valid.

MV	Meaning
0b0	ERR<n>MISC0 and ERR<n>MISC1ERR<n>MISC<m> not valid.
0b1	The IMPLEMENTATION DEFINED contents of the ERR<n>MISC<m> registers contains additional information for an error recorded by this record.ERR<n>MISC0 and ERR<n>MISC1 registers contains additional information for an error recorded by this record.

This bit ignores writes if any of ERR<n>STATUS.{CE, DE, UE} !=are {set to 1, and the highest priority of these is not being cleared to 0 in the same write.0b00,0,0}, and the highest priority of these is not being cleared to zero in the same write.

This bit is read/write-one-to-clear.

Note

If the ERR<n>MISC<m> registers can contain additional information for a previously recorded error, then the contents must be self-describing to software or a user. For example, certain fields might relate only to Corrected errors, and other fields only to the most recent error that was not discarded.ERR<n>MISC0 and ERR<n>MISC1 registers can contain additional information for a previously recorded error, then the contents must be self-describing to software or a user. For example, certain fields might relate only to Corrected errors, and other fields only to the most recent error that was not discarded.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to 0.

Otherwise:

Reserved, RES0.

CE, bits [25:24]

Corrected Error.

CE	Meaning
0b00	No errors were corrected.
0b01	At least one transient error was corrected.
0b10	At least one error was corrected.
0b11	At least one persistent error was corrected.

The mechanism by which a node detects whether a correctable error is transient or persistent is IMPLEMENTATION DEFINED. If no such mechanism is implemented, then the node sets this field to 0b10 when an error is corrected.

If ERR<n>STATUS.V is set to 0, this field is not valid and reads UNKNOWN.

When clearing ERR<n>STATUS.V to 0, if this field is nonzero, then software must write ones to this field to clear this field to zero. 0b0, if this field is nonzero, then software must write ones to this field to clear this field to zero.

ThisIf fieldERR<n>STATUS.OF is notset validto 1 and readsis not being cleared to 0 in the same write, this field ignores writes. UNKNOWN if ERR<n>STATUS.V == 0b0. This field ignores writes if ERR<n>STATUS.OF == 0b1 and is not being cleared to 0b0 in the same write.

This field is read/write-ones-to-clear. Writing a value other than all-zeros or all-ones sets this field to an UNKNOWN value.

The following resets apply:

- OnThis anfield Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

DE, bit [23]

Deferred Error.

DE	Meaning
0b0	No errors were deferred.
0b1	At least one error was not corrected and deferred.

Support for deferring errors is IMPLEMENTATION DEFINED.

If ERR<n>STATUS.V is set to 0, this bit is not valid and reads UNKNOWN.

When clearing ERR<n>STATUS.V to 0, if this bit is nonzero, then software must write 1 to this bit to clear this bit to zero. 0b0, if this bit is nonzero, then software must write 0b1 to this bit to clear this bit to zero.

ThisIf bitERR<n>STATUS.OF is notset validto 1 and readsis not being cleared to 0 in the same write, this bit ignores writes. UNKNOWN if ERR<n>STATUS.V == 0b0. This bit ignores writes if ERR<n>STATUS.OF == 0b1 and is not being cleared to 0b0 in the same write.

This bit is read/write-one-to-clear.

The following resets apply:

- OnThis anbit Erroris recoverypreserved reset,on thean valueError ofRecovery this field is unchanged.reset.
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

PN, bit [22]

Poison.

PN	Meaning
0b0	Uncorrected error or Deferred error recorded because a corrupt value was detected, for example, by an error detection code (EDC). **Note** If a producer node detects a corrupt value and defers the error by producing a poison value, then this bit is set to 0 at the producer node. 0b0 at the producer node.
0b1	Uncorrected error or Deferred error recorded because a poison value was detected. **Note** This might only be an indication of poison, because, in some EDC schemes, a poison value is encoded as an unlikely form of corrupt data, meaning it is possible to mistake a corrupt value as a poison value.

It is IMPLEMENTATION DEFINED whether a node can distinguish a poison value from a corrupt value.

IfWhen clearing ERR<n>STATUS.V to 0, if this bit is nonzero, then software must write 1 to this bit to clear this bit to zero. 0b1 to this bit to clear this bit to zero, when any of:

When clearing both ERR<n>STATUS.{DE, UE} to 0, if this bit is nonzero, then software must write 1 to this bit to clear this bit to zero.

- Clearing ERR<n>STATUS.V to 0b0.
- Clearing both ERR<n>STATUS.{DE, UE} to 0b0.

This bit is not valid and reads UNKNOWN if any of the following are true:

- ERR<n>STATUS.V == 0b0.
  - ~~ERR<n>STATUS.V is set to 0.~~
  - ~~ERR<n>STATUS.{DE, UE} are both set to 0.~~

  ERR<n>STATUS.{DE,UE} == {0,0}.

This~~When~~ bit~~any~~ ignores~~of~~ writes if ERR<n>STATUS.{CE, DE, UE} !=~~are~~ {~~set to 1, and the highest priority of these is not being cleared to 0 in the same write, this bit ignores writes.~~0b00,0,0}, and the highest priority of these is not being cleared to zero in the same write.

This bit is read/write-one-to-clear.

The following resets apply:

- On~~This~~ an~~bit~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

UET, bits [21:20]

~~Describes the state of the component after detecting or consuming an Uncorrected error.~~

Uncorrected Error Type. Describes the state of the component after detecting or consuming an Uncorrected error.

UET	Meaning
0b00	Uncorrected error, Uncontainable error (UC).
0b01	Uncorrected error, Unrecoverable error (UEU).
0b10	Uncorrected error, Latent or Restartable error (UEO).
0b11	Uncorrected error, Signaled or Recoverable error (UER).

If~~When~~ ~~clearing ERR<n>STATUS.V to 0, if~~ this field is nonzero, then software must write ones to this field to clear this field to zero, when any of:~~zero.~~

~~When clearing ERR<n>STATUS.UE to 0, if this field is nonzero, then software must write ones to this field to clear this field to zero.~~

- Clearing ERR<n>STATUS.V to 0b0.
- Clearing ERR<n>STATUS.UE to 0b0.

This field is not valid and reads UNKNOWN if any of the following are true:

- ERR<n>STATUS.V == 0b0.
  - ~~ERR<n>STATUS.V is set to 0.~~
- ERR<n>STATUS.UE == 0b0.
  - ~~ERR<n>STATUS.UE is set to 0.~~

This~~When~~ field~~any~~ ignores~~of~~ writes if ERR<n>STATUS.{CE, DE, UE} !=~~are~~ {~~set to 1, and the highest priority of these is not being cleared to 0 in the same write, this field ignores writes.~~0b00,0,0}, and the highest priority of these is not being cleared to zero in the same write.

This field is read/write-ones-to-clear. Writing a value other than all-zeros or all-ones sets this field to an UNKNOWN value.

Note

Software might use the information in the error record registers to determine what recovery is necessary.

The following resets apply:

- On~~This~~ an~~field~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [19:16]

Reserved, RES0.

IERR, bits [15:8]

~~This field is not valid and reads UNKNOWN if ERR<n>STATUS.V is set to 0.~~

~~When any of ERR<n>STATUS.{CE, DE, UE} are set to 1, and the highest priority of these is not being cleared to 0 in the same write, this field ignores writes.~~

IMPLEMENTATION DEFINED error code. Used with any primary error code SERR value. Further IMPLEMENTATION DEFINED information can be placed in the MISC registers.

~~This~~Used ~~field~~with ~~is~~any ~~not~~primary ~~valid~~error ~~and~~code ~~reads~~SERR value. Further ~~UNKNOWN~~IMPLEMENTATION DEFINED if ERR<n>STATUS.V == `0b0`. This field ignores writes if ERR<n>STATUS.{CE,DE,UE} != {`0b00`,0,0}, ~~information~~ ~~and~~can ~~the~~be highest~~placed~~ priority of these is not being cleared to zero in the same ~~MISC~~ write. ~~registers.~~

The following resets apply:

- On~~This~~ an~~field~~ Error~~is~~ recovery~~preserved~~ reset, ~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged. ~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

SERR, bits [7:0]

~~Indicates the type of error. The primary error code might be used by a fault handling agent to triage an error without requiring device-specific code. For example, to count and threshold corrected errors in software, or generate a short log entry.~~

Architecturally-defined primary error code. The primary error code might be used by a fault handling agent to triage an error without requiring device-specific code. For example, to count and threshold corrected errors in software, or generate a short log entry.

SERR	Meaning
0x00	No error.
0x01	IMPLEMENTATION DEFINED error.
0x02	Data value from (non-associative) internal memory. For example, ECC from on-chip SRAM or buffer.
0x03	IMPLEMENTATION DEFINED pin. For example, **nSEI** pin.
0x04	Assertion failure. For example, consistency failure.
0x05	Error detected on internal data path. For example, parity on ALU result.
0x06	Data value from associative memory. For example, ECC error on cache data.
0x07	Address/control value from associative memory. For example, ECC error on cache tag.
0x08	Data value from a TLB. For example, ECC error on TLB data.
0x09	Address/control value from a TLB. For example, ECC error on TLB tag.
0x0A	Data value from producer. For example, parity error on write data bus.
0x0B	Address/control value from producer. For example, parity error on address bus.
0x0C	Data value from (non-associative) external memory. For example, ECC error in SDRAM.
0x0D	Illegal address (software fault). For example, access to unpopulated memory.
0x0E	Illegal access (software fault). For example, byte write to word register.
0x0F	Illegal state (software fault). For example, device not ready.
0x10	Internal data register. For example, parity on a SIMD&FP register. For a PE, all general-purpose, stack pointer, ~~and~~ SIMD&FP, and SVE registers are data registers.
0x11	Internal control register. For example, Parity on a System register. For a PE, all registers other than general-purpose, stack pointer, ~~and~~ SIMD&FP, and SVE registers are control registers.
0x12	Error response from slave. For example, error response from cache write-back.
0x13	External timeout. For example, timeout on interaction with another node.
0x14	Internal timeout. For example, timeout on interface within the node.
0x15	Deferred error from slave not supported at master. For example, poisoned data received from a slave by a master that cannot defer the error further.
0x16	Deferred error from master not supported at slave. For example, poisoned data received from a master by a slave that cannot defer the error further.
0x17	Deferred error from slave passed through. For example, poisoned data received from a slave and returned to a master.
0x18	Deferred error from master passed through. For example, poisoned data received from a master and deferred to a slave.
0x19	Error recorded by PCIe error logs. Indicates that the node has recorded an error in a PCIe error log. This might be the PCIe device status register, AER, DVSEC, or other mechanisms defined by PCIe.

~~When any of ERR<n>STATUS.{CE, DE, UE} are set to 1, and the highest priority of these is not being cleared to 0 in the same write, this field ignores writes.~~

All other values are reserved. ~~Reserved values might be defined in a future version of the architecture.~~

This field is not valid and reads UNKNOWN if ERR<n>STATUS.V ==~~is set to 0.~~ 0b0. This field ignores writes if ERR<n>STATUS.{CE,DE,UE} != {0b00,0,0}, and the highest priority of these is not being cleared to zero in the same write.

The following resets apply:

- On~~This~~ an~~field~~ Error~~is~~ recovery~~preserved~~ reset,~~on~~ the~~an~~ value~~Error~~ of~~Recovery~~ this field is unchanged.~~reset.~~
- On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the ERR<n>STATUS

TheAfter {AV,reading V,the UE,status ERregister, OF,software MV,must CE,clear DE,the PN,valid UET,bits CI} fields are write-one-to-clear, meaning writes of zero are ignored, and a write of one or all-ones to theallow fieldnew clearserrors the field to zero. The {IERR, SERR} fields are read/write fields, although the set of permitted values that can be written to the fields isrecorded. IMPLEMENTATION DEFINED.

AfterBetween reading ERR<n>STATUS, software must clear the valid bits in the register to allow new errors to be recorded. However, between reading the register and clearing the valid bits, a new error might have overwritten the register. To prevent this new error being lost by software, the register prevents updates to fields that might have been updated by a new error.:

When RAS System Architecture v1.0 is implemented:

- When ARMv8.4-RAS is not implemented, some control bits use a form of read/write-one-to-clear and ignore writes depending on the values of other bits and which bits are being cleared.

  Writes to the {UE, DE, CE} fields are ignored if the OF bit is set and is not being cleared.

- When ARMv8.4-RAS is implemented, a write to ERR<n>STATUS is ignored if both:
  - Any of the ERR<n>STATUS.{V, UE, OF, CE, DE} fields are nonzero before the write.
  - The write does not clear the nonzero ERR<n>STATUS.{V, UE, OF, CE, DE} field(s) to zero by writing one(s) to the applicable field(s).

  Writes to the V bit are ignored if any of the {UE, DE, CE} fields are nonzero and are not being cleared.
- Writes to the {AV, MV} bits and {ER, PN, UET, IERR, SERR} syndrome fields are ignored if the highest priority error status field is nonzero and not being cleared. The error status fields in priority order from highest to lowest, are UE, DE, and CE.

WhenSoftware RASmust Systemwrite Architectureones v1.1to isthe implemented{ER, aPN, writeUET, toCI} thefields registerwhen isclearing ignoredERR<n>STATUS.{V, ifUE, allOF, of:CE, DE}.

- Any of {V, UE, OF, CE, DE} fields are nonzero before the write.
- The write does not clear the nonzero {V, UE, OF, CE, DE} fields to zero by writing ones to the applicable field or fields.

To ensure correct and portable operation, when software is clearing the valid bits in the register to allow new errors to be recorded, software must:

- Determine which fields must be cleared to zero by reading ERR<n>STATUS.
- Write ones to all the write-one-to-clear fields that are nonzero.
- Write zero to all the read/write fields.
- Write zero to all the write-one-to-clear fields that are zero.

ERR<n>STATUS can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
RAS	`0x010 + 64n`	ERR<n>STATUS

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRPIDR0, Peripheral Identification Register 0

The ERRPIDR0 characteristics are:

Purpose

Provides discovery information about the component.

For more information, see 'About the Peripheral identification scheme'.~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Configuration

Implementation of this register is OPTIONAL.

~~This register is present only when RAS is implemented. Otherwise, direct accesses to ERRPIDR0 are RES0.~~

Attributes

ERRPIDR0 is a 32-bit register.

Field descriptions

The ERRPIDR0 bit assignments are:



Bits [31:8]

Reserved, RES0.

PART_0, bits [7:0]

IMPLEMENTATION DEFINED.

Part number, bits [7:0].

The part number is selected by the designer of the component. The designer chooses whether to use a 12-bit or a 16-bit part number~~, and~~:

- ~~If a 12-bit part number is used, it is stored in ERRPIDR1.PART_1 and this field.~~

  If a 12-bit part number is used, it is stored in ERRPIDR1.PART_1 and ERRPIDR0.PART_0. There are 8 bits, ERRPIDR2.REVISION and ERRPIDR3.REVAND, available to define the revision of the component.

- ~~If a 16-bit part number is used, it is stored in ERRPIDR2.PART_2, ERRPIDR1.PART_1 and this field.~~

  If a 16-bit part number is used, it is stored in ERRPIDR2.PART_2, ERRPIDR1.PART_1 and ERRPIDR0.PART_0. There are 4 bits, ERRPIDR3.REVISION, available to define the revision of the component.

~~This field reads as an IMPLEMENTATION DEFINED value.~~

Accessing the ERRPIDR0

ERRPIDR0 can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	0xFE0

Component	Offset	Instance
RAS	0xFE0	ERRPIDR0

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRPIDR1, Peripheral Identification Register 1

The ERRPIDR1 characteristics are:

Purpose

Provides discovery information about the component.

For more information, see 'About the Peripheral identification scheme'.in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Configuration

Implementation of this register is OPTIONAL.

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRPIDR1 are RES0.

Attributes

ERRPIDR1 is a 32-bit register.

Field descriptions

The ERRPIDR1 bit assignments are:



Bits [31:8]

Reserved, RES0.

DES_0, bits [7:4]

IMPLEMENTATION DEFINED.

Designer, JEP106 identification code, bits [3:0]. This field and ERRPIDR2.DES_1 together form the JEDEC-assigned JEP106 identification code for the designer of the component.

Designer,The JEP106code identificationidentifies codethe designer of the component, bitswhich [3:0].might ERRPIDR1.DES_0not andbe not the same as the implementer of the device containing the component. ERRPIDR2.DES_1 together form the JEDEC-assigned JEP106 identification code for the designer of the component. The parity bit in the JEP106 identification code is not included. The code identifies the designer of the component, which might not be not the same as the implementer of the device containing the component. To obtain a number, or to see the assignment of these codes, contact JEDEC http://www.jedec.org.

Note

For a component designed by Arm Limited, the JEP106 identification code is `0x3B`.

This field reads as an IMPLEMENTATION DEFINED value.

PART_1, bits [3:0]

IMPLEMENTATION DEFINED.~~Part number, bits [11:8]~~

Part~~The part~~ number ~~is selected by the designer of the component. The designer chooses whether to use a 12-bit or a 16-bit part number~~, bits [11~~and~~:8].

The part number is selected by the designer of the component. The designer chooses whether to use a 12-bit or a 16-bit part number:

- ~~If a 12-bit part number is used, it is stored in this field and~~ ERRPIDR0.~~PART_0.~~

  If a 12-bit part number is used, it is stored in ERRPIDR1.PART_1 and ERRPIDR0.PART_0. There are 8 bits, ERRPIDR2.REVISION and ERRPIDR3.REVAND, available to define the revision of the component.

- ~~If a 16-bit part number is used, it is stored in~~ ERRPIDR2.~~PART_2, this field, and~~ ERRPIDR0.~~PART_0.~~

  If a 16-bit part number is used, it is stored in ERRPIDR2.PART_2, ERRPIDR1.PART_1 and ERRPIDR0.PART_0. There are 4 bits, ERRPIDR3.REVISION, available to define the revision of the component.

~~This field reads as an IMPLEMENTATION DEFINED value.~~

Accessing the ERRPIDR1

ERRPIDR1 can be accessed through the memory-mapped interfaces:

Component	**Offset**
RAS	0xFE4

~~**Component**~~	~~**Offset**~~	~~**Instance**~~
~~RAS~~	~~0xFE4~~	~~ERRPIDR1~~

Accesses on this interface are **RO**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRPIDR2, Peripheral Identification Register 2

The ERRPIDR2 characteristics are:

Purpose

Provides discovery information about the component.

For more information, see 'About the Peripheral identification scheme'.~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Configuration

Implementation of this register is OPTIONAL.

~~This register is present only when RAS is implemented. Otherwise, direct accesses to ERRPIDR2 are RES0.~~

Attributes

ERRPIDR2 is a 32-bit register.

Field descriptions

The ERRPIDR2 bit assignments are:

When the component uses a 12-bit part number:



Bits [31:8]

Reserved, RES0.

REVISION, bits [7:4]

IMPLEMENTATION DEFINED.

~~Component major revision. This field and ERRPIDR3.REVAND together form the revision number of the component, with REVISION being the most significant part and REVAND the least significant part.~~

Component major revision. ERRPIDR2.REVISION and ERRPIDR3.REVAND together form the revision number of the component, with ERRPIDR2.REVISION being the most significant part and ERRPIDR3.REVAND the least significant part. When a component is changed, ERRPIDR2.REVISION or ERRPIDR3.REVAND must be increased to ensure that software can differentiate the different revisions of the component. If ERRPIDR2.REVISION is increased then ERRPIDR3.REVAND should be set to `0b0000`.

~~This field reads as an IMPLEMENTATION DEFINED value.~~

JEDEC, bit [3]

JEDEC-assigned JEP106 implementer code is used.~~ This bit is RAO.~~

This bit reads as one.

DES_1, bits [2:0]

IMPLEMENTATION DEFINED.

~~Designer, JEP106 identification code, bits [6:4]. ERRPIDR1.DES_0 and this field together form the JEDEC-assigned JEP106 identification code for the designer of the component.~~

Designer, JEP106 identification code, bits [6:4]. ERRPIDR1.DES_0 and ERRPIDR2.DES_1 together form the JEDEC-assigned JEP106 identification code for the designer of the component. The parity bit in the JEP106 identification code is not included. The code identifies the designer of the component, which might not be not the same as the implementer of the device containing the component. To obtain a number, or to see the assignment of these codes, contact JEDEC http://www.jedec.org.

~~This field reads as an IMPLEMENTATION DEFINED value.~~

Note

For a component designed by Arm Limited, the JEP106 identification code is `0x3B`.

When the component uses a 16-bit part number:



Bits [31:8]

Reserved, RES0.

PART_2, bits [7:4]

IMPLEMENTATION DEFINED.~~Part number, bits [15:12]~~

Part~~The part~~ number~~,~~ bits~~is~~ [15:12].~~selected by the designer of the component. It is stored in this field,~~ERRPIDR1.PART_1 ~~and~~ ERRPIDR0.PART_0.

The part number is selected by the designer of the component. The designer chooses whether to use a 12-bit or a 16-bit part number:

~~This field reads as an IMPLEMENTATION DEFINED value.~~

- If a 12-bit part number is used, it is stored in ERRPIDR1.PART_1 and ERRPIDR0.PART_0. There are 8 bits, ERRPIDR2.REVISION and ERRPIDR3.REVAND, available to define the revision of the component.
- If a 16-bit part number is used, it is stored in ERRPIDR2.PART_2, ERRPIDR1.PART_1 and ERRPIDR0.PART_0. There are 4 bits, ERRPIDR3.REVISION, available to define the revision of the component.

JEDEC, bit [3]

JEDEC-assigned JEP106 implementer code is used.~~ This bit is RAO.~~

This bit reads as one.

DES_1, bits [2:0]

IMPLEMENTATION DEFINED.

~~Designer, JEP106 identification code, bits [6:4]. ERRPIDR1.DES_0 and this field together form the JEDEC-assigned JEP106 identification code for the designer of the component.~~

Designer, JEP106 identification code, bits [6:4]. ERRPIDR1.DES_0 and ERRPIDR2.DES_1 together form the JEDEC-assigned JEP106 identification code for the designer of the component. The parity bit in the JEP106 identification code is not included. The code identifies the designer of the component, which might not be not the same as the implementer of the device containing the component. To obtain a number, or to see the assignment of these codes, contact JEDEC http://www.jedec.org.

~~This field reads as an IMPLEMENTATION DEFINED value.~~

Note

For a component designed by Arm Limited, the JEP106 identification code is `0x3B`.

Accessing the ERRPIDR2

ERRPIDR2 can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	0xFE8

~~Component~~	~~Offset~~	~~Instance~~
~~RAS~~	~~0xFE8~~	~~ERRPIDR2~~

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRPIDR3, Peripheral Identification Register 3

The ERRPIDR3 characteristics are:

Purpose

Provides discovery information about the component.

For more information, see 'About the Peripheral identification scheme'.~~in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.~~

Configuration

Implementation of this register is OPTIONAL.

~~This register is present only when RAS is implemented. Otherwise, direct accesses to ERRPIDR3 are RES0.~~

Attributes

ERRPIDR3 is a 32-bit register.

Field descriptions

The ERRPIDR3 bit assignments are:

When the component uses a 12-bit part number:



Bits [31:8]

Reserved, RES0.

~~**When the component uses a 16-bit part number:**~~

~~Component revision.~~

~~This field reads as an IMPLEMENTATION DEFINED value.~~

~~**Otherwise:**~~

~~Reserved, RES0.~~

REVAND, bits [7:4]

~~**When the component uses a 12-bit part number:**~~

IMPLEMENTATION DEFINED.

~~Component minor revision. ERRPIDR2.REVISION and this field together form the revision number of the component, with REVISION being the most significant part and REVAND the least significant part.~~

Component minor revision. ERRPIDR2.REVISION and ERRPIDR3.REVAND together form the revision number of the component, with ERRPIDR2.REVISION being the most significant part and ERRPIDR3.REVAND the least significant part. When a component is changed, ERRPIDR2.REVISION or ERRPIDR3.REVAND must be increased to ensure that software can differentiate the different revisions of the component. If ERRPIDR2.REVISION is increased then ERRPIDR3.REVAND should be set to `0b0000`.

~~This field reads as an IMPLEMENTATION DEFINED value.~~

CMOD, bits [3:0]

~~Customer Modified. If the value of this field is non-zero, then the component has~~ IMPLEMENTATION DEFINED. ~~modifications.~~

Customer Modified.

Indicates the component has been modified.

A value of `0b0000` means the component is not modified from the original design.

Any other value means the component has been modified in an IMPLEMENTATION DEFINED way.

For any two components with the same Unique Component Identifier:

- If the value of the CMOD fields of both components equals zero, the components are identical.
- If the CMOD fields of both components have the same non-zero value, it does not necessarily mean that they have the same modifications.
- If the value of the CMOD field of either of the two components is non-zero, they might not be identical, even though they have the same Unique Component Identifier.

When the component uses a 16-bit part number:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								REVISION				CMOD			

~~CMOD~~	~~Meaning~~
~~0b0000~~	~~The component is not modified from the original design.~~

Bits [31:8]

Reserved, RES0.

REVISION, bits [7:4]

IMPLEMENTATION DEFINED.

Component revision. When a component is changed, ERRPIDR3.REVISION must be increased to ensure that software can differentiate the different revisions of the component.

CMOD, bits [3:0]

IMPLEMENTATION DEFINED.

Customer Modified.

Indicates the component has been modified.

A value of `0b0000` means the component is not modified from the original design.

Any other value means the component has been modified in an IMPLEMENTATION DEFINED way.

For any two components with the same Unique Component Identifier:

- ~~If the value of the CMOD fields of both components equals zero, the components are identical.~~

  If the value of the CMOD fields of both components equals zero, the components are identical.

- ~~If the value of the CMOD field of either of the two components is non-zero, they might not be identical, even though they have the same Unique Component Identifier.~~

  If the CMOD fields of both components have the same non-zero value, it does not necessarily mean that they have the same modifications.

- ~~If the CMOD fields of both components have the same non-zero value, it does not necessarily mean that they have the same modifications.~~

  If the value of the CMOD field of either of the two components is non-zero, they might not be identical, even though they have the same Unique Component Identifier.

~~This field reads as an IMPLEMENTATION DEFINED value.~~

Accessing the ERRPIDR3

ERRPIDR3 can be accessed through the memory-mapped interfaces:

Component	**Offset**
RAS	0xFEC

~~**Component**~~	~~**Offset**~~	~~**Instance**~~
~~RAS~~	~~0xFEC~~	~~ERRPIDR3~~

Accesses on this interface are **RO**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

ERRPIDR4, Peripheral Identification Register 4

The ERRPIDR4 characteristics are:

Purpose

Provides discovery information about the component.

For more information, see 'About the Peripheral identification scheme'.in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

Configuration

Implementation of this register is OPTIONAL.

This register is present only when RAS is implemented. Otherwise, direct accesses to ERRPIDR4 are RES0.

Attributes

ERRPIDR4 is a 32-bit register.

Field descriptions

The ERRPIDR4 bit assignments are:



Bits [31:8]

Reserved, RES0.

SIZE, bits [7:4]

IMPLEMENTATION DEFINED.Size of the component. The distance from the start of the address space used by this component to the end of the component identification registers.

Size of the component.

If the value of this field is non-zero, then the component occupies $2^{ERRPIDR4.SIZE}$ 4KB blocks.

SIZE	Meaning
0b0000	One of the following is true: • The component uses a single 4KB block. • The component uses an IMPLEMENTATION DEFINED number of 4KB blocks.

Using this bit field to indicate the size of the component is deprecated. This bit field might not correctly indicate the size of the component.

Arm recommends that software determine the size of the component from the Unique Component Identifier fields, and other IMPLEMENTATION DEFINED registers in the component.

This register reads as an IMPLEMENTATION DEFINED value.

The distance from the start of the address space used by this component to the end of the component identification registers.

A value of `0b0000` means one of the following is true:

- The component uses a single 4KB block.
- The component uses an IMPLEMENTATION DEFINED number of 4KB blocks.

Any other value means the component occupies $2^{ERRPIDR4.SIZE}$ 4KB blocks.

Using this field to indicate the size of the component is deprecated. This field might not correctly indicate the size of the component. Arm recommends that software determine the size of the component from the Unique Component Identifier fields, and other IMPLEMENTATION DEFINED registers in the component.

DES_2, bits [3:0]

~~This field reads as an IMPLEMENTATION DEFINED value.~~

IMPLEMENTATION DEFINED.~~Designer, JEP106 continuation code. This is the JEDEC-assigned JEP106 bank identifier for the designer of the component, minus 1.~~

Designer, JEP106 continuation code. This is the JEDEC-assigned JEP106 bank identifier for the designer of the component, minus 1. The code identifies the designer of the component, which might not be not the same as the implementer of the device containing the component. To obtain a number, or to see the assignment of these codes, contact JEDEC http://www.jedec.org.

Note

For a component designed by Arm Limited, the JEP106 bank is 5, meaning this field has the value `0x4`.

Accessing the ERRPIDR4

ERRPIDR4 can be accessed through the memory-mapped interfaces:

Component	Offset
RAS	`0xFD0`

~~Component~~	~~Offset~~	~~Instance~~
~~RAS~~	~~`0xFD0`~~	~~ERRPIDR4~~

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICC_ABPR, CPU Interface Aliased Binary Point Register

The GICC_ABPR characteristics are:

Purpose

Defines the point at which the priority value fields split into two parts, the group priority field and the subpriority field. The group priority field determines Group 1 interrupt preemption.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

In systems that support two Security states:

- This register is an alias of the Non-secure copy of GICC_BPR.
- Non-secure accesses to this register return a shifted value of the binary point.
- If ICC_CTLR_EL3.CBPR_EL1NS == 1, Secure accesses to this register access ICC_BPR0_EL1.

Attributes

The reset value of this register is defined as (minimum GICC_BPR.Binary_Point + 1), resulting in a permitted range of `0x1-0x4`.

Field descriptions

The GICC_ABPR bit assignments are:



Bits [31:3]

Reserved, RES0.

Binary_Point, bits [2:0]

Controls how the 8-bit interrupt priority field is split into a group priority field, that determines interrupt preemption, and a subpriority field. The following list describes how this field determines the interrupt priority bits assigned to the group priority field:

- Priority grouping for Group 1 interrupts when CBPR==0, for the processing of Group 1 interrupts in a GIC implementation that supports interrupt grouping, when GICC_CTLR.CBPR == 0.
- Priority grouping for Group 0 interrupts, or Group 1 interrupts when CBPR==1, for all other cases.

This field resets to an architecturally UNKNOWN value.

Accessing the GICC_ABPR

This register is used only when System register access is not enabled. When System register access is enabled, the System registers ICC_BPR0_EL1 and ICC_BPR1_EL1 provide equivalent functionality.

GICC_ABPR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC CPU interface	0x001C	GICC_ABPR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICC_BPR, CPU Interface Binary Point Register

The GICC_BPR characteristics are:

Purpose

Defines the point at which the priority value fields split into two parts, the group priority field and the subpriority field.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

In systems that support two Security states:

- This register is Banked.
- The Secure instance of this register determines Group 0 interrupt preemption.
- The Non-secure instance of this register determines Group 1 interrupt preemption.

In systems that support only one Security state, when GICC_CTLR.CBPR == 0, this register determines only Group 0 interrupt preemption.

When GICC_CTLR.CBPR == 1, this register determines interrupt preemption for both Group 0 and Group 1 interrupts.

Attributes

GICC_BPR is a 32-bit register.

Field descriptions

The GICC_BPR bit assignments are:



Bits [31:3]

Reserved, RES0.

Binary_Point, bits [2:0]

Controls how the 8-bit interrupt priority field is split into a group priority field, that determines interrupt preemption, and a subpriority field. The following list describes how this field determines the interrupt priority bits assigned to the group priority field:

- Priority grouping for Group 1 interrupts when CBPR==0, for the processing of Group 1 interrupts in a GIC implementation that supports interrupt grouping, when GICC_CTLR.CBPR == 0.
- Priority grouping for Group 0 interrupts, or Group 1 interrupts when CBPR==1, for all other cases.

This field resets to an architecturally UNKNOWN value.

Note

Aliasing the Non-secure GICC_BPR as GICC_ABPR in a multiprocessor system permits a PE that can make only Secure accesses to configure the preemption setting for Group 1 interrupts by accessing GICC_ABPR.

Accessing the GICC_BPR

This register is used only when System register access is not enabled. When System register access is enabled this register is RAZ/WI, and the System registers ICC_BPR0_EL1 and ICC_BPR1_EL1 provide equivalent functionality.

GICC_BPR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC CPU interface	0x0008	GICC_BPR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICC_CTLR, CPU Interface Control Register

The GICC_CTLR characteristics are:

Purpose

Controls the CPU interface, including enabling of interrupt groups, interrupt signal bypass, binary point registers used, and separation of priority drop and interrupt deactivation.

Note

If the GIC implementation supports two Security states, independent EOI controls are provided for accesses from each Security state. Secure accesses handle both Group 0 and Group 1 interrupts, and Non-secure accesses handle Group 1 interrupts only.

Configuration

In a GIC implementation that supports two Security states:

- This register is Banked.
- The register bit assignments are different in the Secure and Non-secure copies.

Attributes

GICC_CTLR is a 32-bit register.

Field descriptions

The GICC_CTLR bit assignments are:

When GICD_CTLR.DS==0, Non-secure access:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																						EOImodeNS	RES0	IRQBypDisGrp1	FIQBypDisGrp1	RES0	EnableGrp1				

Bits [31:10]

Reserved, RES0.

EOImodeNS, bit [9]

Controls the behavior of Non-secure accesses to GICC_EOIR, GICC_AEOIR, and GICC_DIR.

EOImodeNS	Meaning
0b0	GICC_EOIR and GICC_AEOIR provide both priority drop and interrupt deactivation functionality. Accesses to GICC_DIR are UNPREDICTABLE.
0b1	GICC_EOIR and GICC_AEOIR provide priority drop functionality only. GICC_DIR provides interrupt deactivation functionality.

Note

An implementation is permitted to make this bit RAO/WI.

This field resets to `0`.

Bits [8:7]

Reserved, RES0.

IRQBypDisGrp1, bit [6]

When the signaling of IRQs by the CPU interface is disabled, this field partly controls whether the bypass IRQ signal is signaled to the PE for Group 1:

IRQBypDisGrp1	Meaning
`0b0`	The bypass IRQ signal is signaled to the PE.
`0b1`	The bypass IRQ signal is not signaled to the PE.

If System register access is enabled for EL3 and ICC_SRE_EL3.DIB == 1, this field is RAO/WI.

If System register access is enabled for EL1, this field is ignored.

If an implementation does not support legacy interrupts, this bit is permitted to be RAO/WI.

See Interrupt signal bypass and bypass disable for more information.

This field resets to `0`.

FIQBypDisGrp1, bit [5]

When the signaling of FIQs by the CPU interface is disabled, this field partly controls whether the bypass FIQ signal is signaled to the PE for Group 1:

FIQBypDisGrp1	Meaning
`0b0`	The bypass FIQ signal is signaled to the PE.
`0b1`	The bypass FIQ signal is not signaled to the PE.

If System register access is enabled for EL3 and ICC_SRE_EL3.DFB == 1, this field is RAO/WI.

If System register access is enabled for EL1, this field is ignored.

If an implementation does not support legacy interrupts, this bit is permitted to be RAO/WI.

See Interrupt signal bypass and bypass disable for more information.

This field resets to `0`.

Bits [4:1]

Reserved, RES0.

EnableGrp1, bit [0]

This Non-secure field enables the signaling of Group 1 interrupts by the CPU interface to a target PE:

EnableGrp1	Meaning
`0b0`	Group 1 interrupt signaling is disabled.
`0b1`	Group 1 interrupt signaling is enabled.

This field resets to `0`.

When GICD_CTLR.DS==0, Secure access:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6
RES0																					EOImodeNS	EOImodeS	IRQBypDisGrp1	FIQBypDisGrp1	IRQBypDisGrp0	F

Bits [31:11]

Reserved, RES0.

EOImodeNS, bit [10]

Controls the behavior of Non-secure accesses to GICC_EOIR, GICC_AEOIR, and GICC_DIR.

EOImodeNS	Meaning
0b0	GICC_EOIR and GICC_AEOIR provide both priority drop and interrupt deactivation functionality. Accesses to GICC_DIR are UNPREDICTABLE.
0b1	GICC_EOIR and GICC_AEOIR provide priority drop functionality only. GICC_DIR provides interrupt deactivation functionality.

Note

An implementation is permitted to make this bit RAO/WI.

This field resets to 0.

EOImodeS, bit [9]

Controls the behavior of Secure accesses to GICC_EOIR, GICC_AEOIR, and GICC_DIR.

EOImodeS	Meaning
0b0	GICC_EOIR and GICC_AEOIR provide both priority drop and interrupt deactivation functionality. Accesses to GICC_DIR are UNPREDICTABLE.
0b1	GICC_EOIR and GICC_AEOIR provide priority drop functionality only. GICC_DIR provides interrupt deactivation functionality.

Note

An implementation is permitted to make this bit RAO/WI.

This field shares state with GICC_CTLR.EOImode.

This field resets to 0.

IRQBypDisGrp1, bit [8]

When the signaling of IRQs by the CPU interface is disabled, this field partly controls whether the bypass IRQ signal is signaled to the PE for Group 1:

IRQBypDisGrp1	Meaning
0b0	The bypass IRQ signal is signaled to the PE.
0b1	The bypass IRQ signal is not signaled to the PE.

If System register access is enabled for EL3 and ICC_SRE_EL3.DIB == 1, this field is RAO/WI.

If System register access is enabled for EL1, this field is ignored.

If an implementation does not support legacy interrupts, this bit is permitted to be RAO/WI.

See Interrupt signal bypass and bypass disable for more information.

This field resets to 0.

FIQBypDisGrp1, bit [7]

When the signaling of FIQs by the CPU interface is disabled, this field partly controls whether the bypass FIQ signal is signaled to the PE for Group 1:

FIQBypDisGrp1	Meaning
0b0	The bypass FIQ signal is signaled to the PE.
0b1	The bypass FIQ signal is not signaled to the PE.

If System register access is enabled for EL3 and ICC_SRE_EL3.DFB == 1, this field is RAO/WI.

If System register access is enabled for EL1, this field is ignored.

If an implementation does not support legacy interrupts, this bit is permitted to be RAO/WI.

See Interrupt signal bypass and bypass disable for more information.

This field resets to 0.

IRQBypDisGrp0, bit [6]

When the signaling of IRQs by the CPU interface is disabled, this field partly controls whether the bypass IRQ signal is signaled to the PE for Group 0:

IRQBypDisGrp0	Meaning
0b0	The bypass IRQ signal is signaled to the PE.
0b1	The bypass IRQ signal is not signaled to the PE.

If System register access is enabled for EL3 and ICC_SRE_EL3.DIB == 1, this field is RAO/WI.

If System register access is enabled for EL1, this field is ignored.

If an implementation does not support legacy interrupts, this bit is permitted to be RAO/WI.

See Interrupt signal bypass and bypass disable for more information.

This field resets to 0.

FIQBypDisGrp0, bit [5]

When the signaling of FIQs by the CPU interface is disabled, this field partly controls whether the bypass FIQ signal is signaled to the PE for Group 0:

FIQBypDisGrp0	Meaning
0b0	The bypass FIQ signal is signaled to the PE.
0b1	The bypass FIQ signal is not signaled to the PE.

If System register access is enabled for EL3 and ICC_SRE_EL3.DIB == 1, this field is RAO/WI.

If System register access is enabled for EL1, this field is ignored.

If an implementation does not support legacy interrupts, this bit is permitted to be RAO/WI.

See Interrupt signal bypass and bypass disable for more information.

This field resets to 0.

CBPR, bit [4]

Controls whether GICC_BPR provides common control of preemption to Group 0 and Group 1 interrupts:

CBPR	Meaning
0b0	GICC_BPR determines preemption for Group 0 interrupts only. GICC_ABPR determines preemption for Group 1 interrupts.
0b1	GICC_BPR determines preemption for both Group 0 and Group 1 interrupts.

This field is an alias of ICC_CTLR_EL3.CBPR_EL1NS.

In a GIC that supports two Security states, when CBPR == 1:

- A Non-secure read of GICC_BPR returns the value of Secure GICC_BPR.Binary_Point~~BinaryPoint~~, incremented by 1, and saturated to 0b111.
- Non-secure writes of GICC_BPR are ignored.

This field resets to 0.

FIQEn, bit [3]

Controls whether the CPU interface signals Group 0 interrupts to a target PE using the FIQ or IRQ signal:

FIQEn	Meaning
0b0	Group 0 interrupts are signaled using the IRQ signal.
0b1	Group 0 interrupts are signaled using the FIQ signal.

Group 1 interrupts are signaled using the IRQ signal only.

If an implementation supports two Security states, this bit is permitted to be RAO/WI.

This field resets to 0.

Bit [2]

Reserved, RES0.

EnableGrp1, bit [1]

This Non-secure field enables the signaling of Group 1 interrupts by the CPU interface to a target PE:

EnableGrp1	Meaning
0b0	Group 1 interrupt signaling is disabled.
0b1	Group 1 interrupt signaling is enabled.

This field resets to 0.

EnableGrp0, bit [0]

Enables the signaling of Group 0 interrupts by the CPU interface to a target PE:

EnableGrp0	Meaning
0b0	Group 0 interrupt signaling is disabled.
0b1	Group 0 interrupt signaling is enabled.

This field resets to 0.

When GICD_CTLR.DS == 0b1:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5
RES0																						EOImode	IRQBypDisGrp1	FIQBypDisGrp1	IRQBypDisGrp0	FIQBypDisGr

Bits [31:10]

Reserved, RES0.

EOImode, bit [9]

Controls the behavior of accesses to GICC_EOIR, GICC_AEOIR, and GICC_DIR.

EOImode	Meaning
0b0	GICC_EOIR and GICC_AEOIR provide both priority drop and interrupt deactivation functionality. Accesses to GICC_DIR are UNPREDICTABLE.
0b1	GICC_EOIR and GICC_AEOIR provide priority drop functionality only. GICC_DIR provides interrupt deactivation functionality.

Note

An implementation is permitted to make this bit RAO/WI.

This field shares state with GICC_CTLR.EOImodeS.

This field resets to 0.

IRQBypDisGrp1, bit [8]

When the signaling of IRQs by the CPU interface is disabled, this field partly controls whether the bypass IRQ signal is signaled to the PE for Group 1:

IRQBypDisGrp1	Meaning
0b0	The bypass IRQ signal is signaled to the PE.
0b1	The bypass IRQ signal is not signaled to the PE.

If System register access is enabled for EL3 and ICC_SRE_EL3.DIB == 1, this field is RAO/WI.

If System register access is enabled for EL1, this field is ignored.

If an implementation does not support legacy interrupts, this bit is permitted to be RAO/WI.

See Interrupt signal bypass and bypass disable for more information.

This field resets to 0.

FIQBypDisGrp1, bit [7]

When the signaling of FIQs by the CPU interface is disabled, this field partly controls whether the bypass FIQ signal is signaled to the PE for Group 1:

FIQBypDisGrp1	Meaning
0b0	The bypass FIQ signal is signaled to the PE.
0b1	The bypass FIQ signal is not signaled to the PE.

If System register access is enabled for EL3 and ICC_SRE_EL3.DFB == 1, this field is RAO/WI.

If System register access is enabled for EL1, this field is ignored.

If an implementation does not support legacy interrupts, this bit is permitted to be RAO/WI.

See Interrupt signal bypass and bypass disable for more information.

This field resets to 0.

IRQBypDisGrp0, bit [6]

When the signaling of IRQs by the CPU interface is disabled, this field partly controls whether the bypass IRQ signal is signaled to the PE for Group 0:

IRQBypDisGrp0	Meaning
0b0	The bypass IRQ signal is signaled to the PE.
0b1	The bypass IRQ signal is not signaled to the PE.

If System register access is enabled for EL3 and ICC_SRE_EL3.DIB == 1, this field is RAO/WI.

If System register access is enabled for EL1, this field is ignored.

If an implementation does not support legacy interrupts, this bit is permitted to be RAO/WI.

See Interrupt signal bypass and bypass disable for more information.

This field resets to `0`.

FIQBypDisGrp0, bit [5]

When the signaling of FIQs by the CPU interface is disabled, this field partly controls whether the bypass FIQ signal is signaled to the PE for Group 0:

FIQBypDisGrp0	Meaning
`0b0`	The bypass FIQ signal is signaled to the PE.
`0b1`	The bypass FIQ signal is not signaled to the PE.

If System register access is enabled for EL3 and ICC_SRE_EL3.DIB == 1, this field is RAO/WI.

If System register access is enabled for EL1, this field is ignored.

If an implementation does not support legacy interrupts, this bit is permitted to be RAO/WI.

See Interrupt signal bypass and bypass disable for more information.

This field resets to `0`.

CBPR, bit [4]

Controls whether GICC_BPR provides common control of preemption to Group 0 and Group 1 interrupts:

CBPR	Meaning
`0b0`	GICC_BPR determines preemption for Group 0 interrupts only. GICC_ABPR determines preemption for Group 1 interrupts.
`0b1`	GICC_BPR determines preemption for both Group 0 and Group 1 interrupts.

This field is an alias of ICC_CTLR_EL3.CBPR_EL1NS.

In a GIC that supports two Security states, when CBPR == 1:

- A Non-secure read of GICC_BPR returns the value of Secure GICC_BPR.Binary_Point~~BinaryPoint~~, incremented by 1, and saturated to `0b111`.
- Non-secure writes of GICC_BPR are ignored.

This field resets to `0`.

FIQEn, bit [3]

Controls whether the CPU interface signals Group 0 interrupts to a target PE using the FIQ or IRQ signal:

FIQEn	Meaning
`0b0`	Group 0 interrupts are signaled using the IRQ signal.
`0b1`	Group 0 interrupts are signaled using the FIQ signal.

Group 1 interrupts are signaled using the IRQ signal only.

If an implementation supports two Security states, this bit is permitted to be RAO/WI.

This field resets to `0`.

Bit [2]

Reserved, RES0.

EnableGrp1, bit [1]

This Non-secure field enables the signaling of Group 1 interrupts by the CPU interface to a target PE:

EnableGrp1	Meaning
0b0	Group 1 interrupt signaling is disabled.
0b1	Group 1 interrupt signaling is enabled.

This field resets to 0.

EnableGrp0, bit [0]

Enables the signaling of Group 0 interrupts by the CPU interface to a target PE:

EnableGrp0	Meaning
0b0	Group 0 interrupt signaling is disabled.
0b1	Group 0 interrupt signaling is enabled.

This field resets to 0.

Accessing the GICC_CTLR

This register is used only when System register access is not enabled. When System register access is enabled:

- For AArch32 implementations, ICC_CTLR and ICC_MCTLR provide equivalent functionality.
- For AArch64 implementations, ICC_CTLR_EL1 and ICC_CTLR_EL3 provide equivalent functionality.

GICC_CTLR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC CPU interface	0x0000	GICC_CTLR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICC_PMR, CPU Interface Priority Mask Register

The GICC_PMR characteristics are:

Purpose

This register provides an interrupt priority filter. Only interrupts with a higher priority than the value in this register are signaled to the PE.

Note

Higher interrupt priority corresponds to a lower value of the Priority field.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is available in all configurations of the GIC. If the GIC implementation supports two Security states this register is Common.

Attributes

GICC_PMR is a 32-bit register.

Field descriptions

The GICC_PMR bit assignments are:



Bits [31:8]

Reserved, RES0.

Priority, bits [7:0]

The priority mask level for the CPU interface. If the priority of the interrupt is higher than the value indicated by this field, the interface signals the interrupt to the PE.

If the GIC implementation supports fewer than 256 priority levels some bits might be RAZ/WI, as follows:

- For 128 supported levels, bit [0] = `0b0`.
- For 64 supported levels, bits [1:0] = `0b00`.
- For 32 supported levels, bits [2:0] = `0b000`.
- For 16 supported levels, bits [3:0] = `0b0000`.

See Interrupt prioritization for more information.

This field resets to an architecturally UNKNOWN value.

Accessing the GICC_PMR

If the GIC implementation supports two Security states:

- Non-secure accesses to this register can only read or write values corresponding to the lower half of the priority range.
- If a Secure write has programmed the register with a value that corresponds to a value in the upper half of the priority range then:
    - Any Non-secure read of the register returns `0x00`, regardless of the value held in the register.
    - Non-secure writes are ignored.

See 'Priority control of Secure and Non-secure interrupts' in the GICv3 Architecture Specification for more information.

GICC_PMR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC CPU interface	`0x0004`	GICC_PMR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_ICACTIVER<n>E, Interrupt Clear-Active Registers (extended SPI range), n = 0 - 31

The GICD_ICACTIVER<n>E characteristics are:

Purpose

Removes the active state from the corresponding SPI in the extended SPI range.

Configuration

This register is present only when GICv3.1 is implemented. Otherwise, direct accesses to GICD_ICACTIVER<n>E are RES0.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1, the number of implemented GICD_ICACTIVER<n>E registers is (GICD_TYPER.ESPI_range+1). Registers are numbered from 0.

Attributes

GICD_ICACTIVER<n>E is a 32-bit register.

Field descriptions

The GICD_ICACTIVER<n>E bit assignments are:



Clear_active_bit<x>, bit [x], for x = 0 to 31

For the extended SPIs, removes the active state to interrupt number x. Reads and writes have the following behavior:

Clear_active_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not active, and is not active and pending. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is active, or is active and pending. If written, deactivates the corresponding interrupt, if the interrupt is active. If the interrupt is already deactivated, the write has no effect.

This field resets to 0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_ICACTIVER<n>E number, n, is given by n = (m-4096) DIV 32.
- The offset of the required GICD_ICACTIVER<n>E is (0x1C00 + (4*n)).
- The bit number of the required group modifier bit in this register is (m-4096) MOD 32.

Accessing the GICD_ICACTIVER<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICD_ICACTIVER<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure SPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICD_ICACTIVER<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	0x1C00 + 4n	GICD_ICACTIVER<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_ICENABLER<n>, Interrupt Clear-Enable Registers, n = 0 - 31

The GICD_ICENABLER<n> characteristics are:

Purpose

Disables forwarding of the corresponding interrupt to the CPU interfaces.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

These registers are available in all GIC configurations. If GICD_CTLR.DS==0, these registers are Common.

The number of implemented GICD_ICENABLER<n> registers is (GICD_TYPER.ITLinesNumber+1). Registers are numbered from 0.

GICD_ICENABLER0 is Banked for each connected PE with GICR_TYPER.Processor_Number < 8.

Accessing GICD_ICENABLER0 from a PE with GICR_TYPER.Processor_Number > 7 is CONSTRAINED UNPREDICTABLE:

- Register is RAZ/WI.
- An UNKNOWN banked copy of the register is accessed.

Attributes

GICD_ICENABLER<n> is a 32-bit register.

Field descriptions

The GICD_ICENABLER<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Clear_enable_bit<x>, bit [x], for x = 0 to 31																															

Clear_enable_bit<x>, bit [x], for x = 0 to 31

For SPIs and PPIs, controls the forwarding of interrupt number 32n + x to the CPU interfaces. Reads and writes have the following behavior:

Clear_enable_bit<x>	Meaning
0b0	If read, indicates that forwarding of the corresponding interrupt is disabled. If written, has no effect.
0b1	If read, indicates that forwarding of the corresponding interrupt is enabled. If written, disables forwarding of the corresponding interrupt. After a write of 1 to this bit, a subsequent read of this bit returns 0.

For SGIs, the behavior of this bit is IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_ICENABLER<n> number, n, is given by n = m DIV 32.
- The offset of the required GICD_ICENABLER is (`0x180` + (4*n)).
- The bit number of the required group modifier bit in this register is m MOD 32.

Note

Writing a 1 to a GICD_ICENABLER<n> bit only disables the forwarding of the corresponding interrupt from the Distributor to any CPU interface. It does not prevent the interrupt from changing state, for example becoming pending or active and pending if it is already active.

Accessing the GICD_ICENABLER<n>

For SGIs and PPIs:

- When ARE is 1 for the Security state of an interrupt, the field for that interrupt is RES0 and an implementation is permitted to make the field RAZ/WI in this case.
- Equivalent functionality is provided by GICR_ICENABLER0.

Bits corresponding to unimplemented interrupts are RAZ/WI.

When GICD_CTLR.DS==0, bits corresponding to Group 0 and Secure Group 1 interrupts are RAZ/WI to Non-secure accesses.

It is IMPLEMENTATION DEFINED whether implemented SGIs are permanently enabled, or can be enabled and disabled by writes to GICD_ISENABLER<n> and GICD_ICENABLER<n> where n=0.

Completion of a write to this register does not guarantee that the effects of the write are visible throughout the affinity hierarchy. To ensure an enable has been cleared, software must write to the register with bits set to 1 to clear the required enables. Software must then poll GICD_CTLR.RWP until it has the value zero.

GICD_ICENABLER<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	`0x0180` + 4n	GICD_ICENABLER<n>

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_ICENABLER<n>E, Interrupt Clear-Enable Registers, n = 0 - 31

The GICD_ICENABLER<n>E characteristics are:

Purpose

Disables forwarding of the corresponding SPI in the extended SPI range to the CPU interfaces.

Configuration

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICD_ICENABLER<n>E are RES0.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1, the number of implemented GICD_ICENABLER<n>E registers is (GICD_TYPER.ESPI_range+1). Registers are numbered from 0.

Attributes

GICD_ICENABLER<n>E is a 32-bit register.

Field descriptions

The GICD_ICENABLER<n>E bit assignments are:



Clear_enable_bit<x>, bit [x], for x = 0 to 31

For the extended SPI range, controls the forwarding of interrupt number x to the CPU interface. Reads and writes have the following behavior:

Clear_enable_bit<x>	Meaning
0b0	If read, indicates that forwarding of the corresponding interrupt is disabled. If written, has no effect.
0b1	If read, indicates that forwarding of the corresponding interrupt is enabled. If written, enables forwarding of the corresponding interrupt. After a write of 1 to this bit, a subsequent read of this bit returns 0.

This field resets to 0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_ICENABLER<n>E number, n, is given by n = (m-4096) DIV 32.
- The offset of the required GICD_ICENABLER<n>E is (0x1400 + (4*n)).
- The bit number of the required group modifier bit in this register is (m-4096) MOD 32.

Accessing the GICD_ICENABLER<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICD_ICENABLER<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure SPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICD_ICENABLER<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	`0x1400 + 4n`	GICD_ICENABLER<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_ICFGR<n>, Interrupt Configuration Registers, n = 0 - 63

The GICD_ICFGR<n> characteristics are:

Purpose

Determines whether the corresponding interrupt is edge-triggered or level-sensitive.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

These registers are available in all GIC configurations. If the GIC implementation supports two Security states, these registers are Common.

GICD_ICFGR1 is Banked for each connected PE with GICR_TYPER.Processor_Number < 8.

Accessing GICD_ICFGR1 from a PE with GICR_TYPER.Processor_Number > 7 is CONSTRAINED UNPREDICTABLE:

- Register is RAZ/WI.
- An UNKNOWN banked copy of the register is accessed.

For SGIs and PPIs:

- When ARE is 1 for the Security state of an interrupt, the field for that interrupt is RES0 and an implementation is permitted to make the field RAZ/WI in this case.
- Equivalent functionality is provided by GICR_ICFGR<n>

For each supported PPI, it is IMPLEMENTATION DEFINED whether software can program the corresponding Int_config field.

For SGIs, Int_config fields are RO, meaning that GICD_ICFGR0 is RO.

Changing Int_config when the interrupt is individually enabled is UNPREDICTABLE.

Changing the interrupt configuration between level-sensitive and edge-triggered (in either direction) at a time when there is a pending interrupt will leave the interrupt in an UNKNOWN pending state.

Fields corresponding to unimplemented interrupts are RAZ/WI.

Attributes

GICD_ICFGR<n> is a 32-bit register.

Field descriptions

The GICD_ICFGR<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Int_config<x>, bits [2x+1:2x], for x = 0 to 15																															

Int_config<x>, bits [2x+1:2x], for x = 0 to 15

Indicates whether the interrupt with ID 16n + x is level-sensitive or edge-triggered.

Int_config[0] (bit [2x]) is RES0.

Possible values of Int_config[1] (bit [2x+1]) are:

Int_config<x>	Meaning
0b00	Corresponding interrupt is level-sensitive.
0b01	Corresponding interrupt is edge-triggered.

For SGIs, Int_config[1] is RAO/WI.

For SPIs and PPIs, Int_config[1] is programmable unless the implementation supports two Security states and the bit corresponds to a Group 0 or Secure Group 1 interrupt, in which case the bit is RAZ/WI to Non-secure accesses.

This field resets to an architecturally UNKNOWN value.

Accessing the GICD_ICFGR<n>

GICD_ICFGR<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	0x0C00 + 4n	GICD_ICFGR<n>

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_ICFGR<n>E, Interrupt Configuration Registers (Extended SPI Range), n = 0 - 63

The GICD_ICFGR<n>E characteristics are:

Purpose

Determines whether the corresponding SPI in the extended SPI range is edge-triggered or level-sensitive.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICD_ICFGR<n>E are RES0.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1, the number of implemented GICD_ICFGR<n>E registers is ((GICD_TYPER.ESPI_range+1)*2). Registers are numbered from 0.

Attributes

GICD_ICFGR<n>E is a 32-bit register.

Field descriptions

The GICD_ICFGR<n>E bit assignments are:



Int_config<x>, bits [2x+1:2x], for x = 0 to 15

Indicates whether the interrupt with ID 16n + x is level-sensitive or edge-triggered.

Int_config[0] (bit[2x]) is RES0.

Possible values of Int_config[1] (bit[2x+1]) are:

Int_config<x>	Meaning
0b00	Corresponding interrupt is level-sensitive.
0b01	Corresponding interrupt is edge-triggered.

This field resets to an architecturally UNKNOWN value.

Accessing the GICD_ICFGR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICD_ICFGR<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, a register bit that corresponds to a Group 0 or Secure Group 1 interrupt is RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICD_ICFGR<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	0x3000 + 4n	GICD_ICFGR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_ICPENDR<n>E, Interrupt Clear-Pending Registers (extended SPI range), n = 0 - 31

The GICD_ICPENDR<n>E characteristics are:

Purpose

Removes the pending state to the corresponding SPI in the extended SPI range.

Configuration

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICD_ICPENDR<n>E are RES0.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1, the number of implemented GICD_ICPENDR<n>E registers is (GICD_TYPER.ESPI_range+1). Registers are numbered from 0.

Attributes

GICD_ICPENDR<n>E is a 32-bit register.

Field descriptions

The GICD_ICPENDR<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Clear_pending_bit<x>, bit [x], for x = 0 to 31																															

Clear_pending_bit<x>, bit [x], for x = 0 to 31

For the extended PPIs, removes the pending state to interrupt number x. Reads and writes have the following behavior:

Clear_pending_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not pending. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is pending, or active and pending. If written, changes the state of the corresponding interrupt from pending to inactive, or from active and pending to active. This has no effect in the following cases: • If the interrupt is not pending and is not active and pending. • If the interrupt is a level-sensitive interrupt that is pending or active and pending for a reason other than a write to GICD_ISPENDR<n>E. In this case, if the interrupt signal continues to be asserted, the interrupt remains pending or active and pending.

This field resets to 0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_ICPENDR<n>E number, n, is given by n = (m-4096) DIV 32.
- The offset of the required GICD_ICPENDR<n>E is (`0x1800` + (4*n)).
- The bit number of the required group modifier bit in this register is (m-4096) MOD 32.

Accessing the GICD_ICPENDR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICD_ICPENDR<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure SPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICD_ICPENDR<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	`0x1800 + 4n`	GICD_ICPENDR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_IGROUPR<n>, Interrupt Group Registers, n = 0 - 31

The GICD_IGROUPR<n> characteristics are:

Purpose

Controls whether the corresponding interrupt is in Group 0 or Group 1.

Configuration

~~GICD_IGROUPR0 resets to an IMPLEMENTATION DEFINED value, that might be UNKNOWN.~~

~~GICD_IGROUPR<n> where n is greater than 0 resets to 0x00000000.~~

These registers are available in all GIC configurations. If GICD_CTLR.DS==0, these registers are Secure.

The number of implemented GICD_IGROUPR<n> registers is (GICD_TYPER.ITLinesNumber+1). Registers are numbered from 0.

GICD_IGROUPR0 is Banked for each connected PE with GICR_TYPER.Processor_Number < 8.

Accessing GICD_IGROUPR0 from a PE with GICR_TYPER.Processor_Number > 7 is CONSTRAINED UNPREDICTABLE:

- Register is RAZ/WI.
- An UNKNOWN banked copy of the register is accessed.

Attributes

GICD_IGROUPR<n> is a 32-bit register.

Field descriptions

The GICD_IGROUPR<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Group_status_bit<x>, bit [x], for x = 0 to 31																															

Group_status_bit<x>, bit [x], for x = 0 to 31

Group status bit.

Group_status_bit<x>	Meaning
0b0	When GICD_CTLR.DS==1, the corresponding interrupt is Group 0. When GICD_CTLR.DS==0, the corresponding interrupt is Secure.
0b1	When GICD_CTLR.DS==1, the corresponding interrupt is Group 1. When GICD_CTLR.DS==0, the corresponding interrupt is Non-secure Group 1.

If affinity routing is enabled for the Security state of an interrupt, the bit that corresponds to the interrupt is concatenated with the equivalent bit in GICD_IGRPMODR<n> to form a 2-bit field that defines an interrupt group. The encoding of this field is described in GICD_IGRPMODR<n>.

If affinity routing is disabled for the Security state of an interrupt, then:

- The corresponding GICD_IGRPMODR<n> bit is RES0.
- For Secure interrupts, the interrupt is Secure Group 0.
- For Non-secure interrupts, the interrupt is Non-secure Group 1.

This field resets to:

- If n == 0, an UNKNOWN value.
- If n > 0, 0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_IGROUP<n> number, n, is given by n = m DIV 32.
- The offset of the required GICD_IGROUP is (0x080 + (4*n)).
- The bit number of the required group modifier bit in this register is m MOD 32.

Accessing the GICD_IGROUPR<n>

For SGIs and PPIs:

- When ARE is 1 for the Security state of an interrupt, the field for that interrupt is RES0 and an implementation is permitted to make the field RAZ/WI in this case.
- Equivalent functionality is provided by GICR_IGROUPR0.

When GICD_CTLR.DS==0, the register is RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

Note

Accesses to GICD_IGROUPR0 when affinity routing is not enabled for a Security state access the same state as GICR_IGROUPR0, and must update Redistributor state associated with the PE performing the accesses. Implementations must ensure that an interrupt that is pending at the time of the write uses either the old value or the new value and must ensure that the interrupt is neither lost nor handled more than one time. The effect of the change must be visible in finite time.

GICD_IGROUPR<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	0x0080 + 4n	GICD_IGROUPR<n>

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_IGROUPR<n>E, Interrupt Group Registers (extended SPI range), n = 0 - 31

The GICD_IGROUPR<n>E characteristics are:

Purpose

Controls whether the corresponding SPI in the extended SPI range is in Group 0 or Group 1.

Configuration

This register is present only when GICv3.1 is implemented. Otherwise, direct accesses to GICD_IGROUPR<n>E are RES0.

GICD_IGROUPR<n>E resets to `0x00000000`.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1:

- The number of implemented GICD_IGROUPR<n>E registers is (GICD_TYPER.ESPI_range+1). Registers are numbered from 0.
- When GICD_CTLRGICD_CLTR.DS==0, this register is Secure.

Attributes

GICD_IGROUPR<n>E is a 32-bit register.

Field descriptions

The GICD_IGROUPR<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Group_status_bit<x>, bit [x], for x = 0 to 31																															

Group_status_bit<x>, bit [x], for x = 0 to 31

Group status bit.

Group_status_bit<x>	Meaning
0b0	When GICD_CTLR.DS==1, the corresponding interrupt is Group 0. When GICD_CTLR.DS==0, the corresponding interrupt is Secure.
0b1	When GICD_CTLR.DS==1, the corresponding interrupt is Group 1. When GICD_CTLR.DS==0, the corresponding interrupt is Non-secure Group 1.

If affinity routing is enabled for the Security state of an interrupt, the bit that corresponds to the interrupt is concatenated with the equivalent bit in GICD_IGRPMODR<n>E to form a 2-bit field that defines an interrupt group. The encoding of this field is described in GICD_IGRPMODR<n>E.

If affinity routing is disabled for the Security state of an interrupt, the bit is RES0:

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_IGROUPR<n>E number, n, is given by n = (m-4096) DIV 32.
- The offset of the required GICD_IGROUPR<n>E is (`0x1000` + (4*n)).
- The bit number of the required group modifier bit in this register is (m-4096) MOD 32.

Accessing the GICD_IGROUPR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICD_IGROUPR<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure SPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICD_IGROUPR<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	`0x1000` + 4n	GICD_IGROUPR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_IGRPMODR<n>, Interrupt Group Modifier Registers, n = 0 - 31

The GICD_IGRPMODR<n> characteristics are:

Purpose

When GICD_CTLR.DS==0, this register together with the GICD_IGROUPR<n> registers, controls whether the corresponding interrupt is in:

- Secure Group 0.
- Non-secure Group 1.
- Secure Group 1.

Configuration

When ~~GICD_CLTR.DS==0, these registers are Secure.~~ GICD_CTLR.DS==0, these registers are Secure.

The number of implemented GICD_IGROUPR<n> registers is (GICD_TYPER.ITLinesNumber+1). Registers are numbered from 0.

When GICD_CTLR.ARE_S==0 or GICD_CTLR.DS==1, the GICD_IGRPMODR<n> registers are RES0. An implementation can make these registers RAZ/WI in this case.

Attributes

GICD_IGRPMODR<n> is a 32-bit register.

Field descriptions

The GICD_IGRPMODR<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Group_modifier_bit<x>, bit [x], for x = 0 to 31																															

Group_modifier_bit<x>, bit [x], for x = 0 to 31

Group modifier bit. When affinity routing is enabled for the Security state of an interrupt, the bit that corresponds to the interrupt is concatenated with the equivalent bit in GICD_IGROUPR<n> to form a 2-bit field that defines an interrupt group:

Group modifier bit	Group status bit	Definition	Short name
0b0	0b0	Secure Group 0	G0S
0b0	0b1	Non-secure Group 1	G1NS
0b1	0b0	Secure Group 1	G1S
0b1	0b1	Reserved, treated as Non-secure Group 1	-

This field resets to 0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_IGRPMODR<n> number, n, is given by n = m DIV 32.
- The offset of the required GICD_IGRPMODR is (0x080 + (4*n)).
- The bit number of the required group modifier bit in this register is m MOD 32.

See GICD_IGROUPR<n> for information about the GICD_IGRPMODR0 reset value.

Accessing the GICD_IGRPMODR<n>

When affinity routing is enabled for Secure state, GICD_IGRPMODR0 is RES0 and equivalent functionality is proved by GICR_IGRPMODR0.

When GICD_CTLR.DS==0, the register is RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

Note

Implementations must ensure that an interrupt that is pending at the time of the write uses either the old value or the new value and must ensure that the interrupt is neither lost nor handled more than one time. The effect of the change must be visible in finite time.

GICD_IGRPMODR<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	`0x0D00 + 4n`	GICD_IGRPMODR<n>

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_IGRPMODR<n>E, Interrupt Group Modifier Registers (extended SPI range), n = 0 - 31

The GICD_IGRPMODR<n>E characteristics are:

Purpose

When GICD_CTLR.DS==0, this register together with the GICD_IGROUPR<n>E registers, controls whether the corresponding interrupt is in:

- Secure Group 0.
- Non-secure Group 1.
- When System register access is enabled, Secure Group 1.

Configuration

This register is present only when GICv3.1 is implemented. Otherwise, direct accesses to GICD_IGRPMODR<n>E are RES0.

GICD_IGRPMODR<n>E resets to `0x00000000`.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1:

- The number of implemented GICD_IGRPMODR<n>E registers is (GICD_TYPER.ESPI_range+1). Registers are numbered from 0.
- When GICD_CTLR~~GICD_CLTR~~.DS==0, this register is Secure.

Attributes

GICD_IGRPMODR<n>E is a 32-bit register.

Field descriptions

The GICD_IGRPMODR<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Group_modifier_bit<x>, bit [x], for x = 0 to 31																															

Group_modifier_bit<x>, bit [x], for x = 0 to 31

Group modifier bit. In implementations where affinity routing is enabled for the Security state of an interrupt, the bit that corresponds to the interrupt is concatenated with the equivalent bit in GICD_IGROUPR<n>E to form a 2-bit field that defines an interrupt group:

Group modifier bit	Group status bit	Definition	Short name
0b0	0b0	Secure Group 0	G0S
0b0	0b1	Non-secure Group 1	G1NS
0b1	0b0	Secure Group 1	G1S
0b1	0b1	Reserved, treated as Non-secure Group 1	-

This field resets to 0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_IGRPMODR<n>E number, n, is given by n = (m-4096) DIV 32.
- The offset of the required GICD_IGRPMODR<n>E is (`0x3400` + (4*n)).
- The bit number of the required group modifier bit in this register is (m-4096) MOD 32.

Accessing the GICD_IGRPMODR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICD_IGRPMODR<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure SPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICD_IGRPMODR<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	`0x3400` + 4n	GICD_IGRPMODR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_IPRIORITYR<n>E, Holds the priority of the corresponding interrupt for each extended SPI supported by the GIC., n = 0 - 255

The GICD_IPRIORITYR<n>E characteristics are:

Purpose

Holds the priority of the corresponding interrupt for each extended SPI supported by the GIC.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICD_IPRIORITYR<n>E are RES0.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1, the number of implemented GICD_IPRIORITYR<n>E registers is ((GICD_TYPER.ESPI_range+1)*8). Registers are numbered from 0.

Attributes

GICD_IPRIORITYR<n>E is a 32-bit register.

Field descriptions

The GICD_IPRIORITYR<n>E bit assignments are:

31 30 29 28 27 26 25 24	23 22 21 20 19 18 17 16	15 14 13 12 11 10 9 8	7 6 5 4 3 2 1 0
Priority_offset_3B	Priority_offset_2B	Priority_offset_1B	Priority_offset_0B

Priority_offset_3B, bits [31:24]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 3. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

Priority_offset_2B, bits [23:16]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 2. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

Priority_offset_1B, bits [15:8]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 1. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

Priority_offset_0B, bits [7:0]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 0. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

For interrupt ID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_IPRIORITYR<n> number, n, is given by n = (m-4096) DIV 4.
- The offset of the required GICD_IPRIORITYR<n>E register is (`0x2000` + (4*n)).
- The byte offset of the required Priority field in this register is m MOD 4, where:
  - Byte offset 0 refers to register bits [7:0].
  - Byte offset 1 refers to register bits [15:8].
  - Byte offset 2 refers to register bits [23:16].
  - Byte offset 3 refers to register bits [31:24].

Accessing the GICD_IPRIORITYR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICD_ISACTIVER<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0:

- A field that corresponds to a Group 0 or Secure Group 1 interrupt is RAZ/WI to Non-secure accesses.
- A Non-secure access to a field that corresponds to a Non-secure Group 1 interrupt behaves as described in Software accesses of interrupt priority.

Bits corresponding to unimplemented interrupts are RAZ/WI.

Note

Implementations must ensure that an interrupt that is pending at the time of the write uses either the old value or the new value and must ensure that the interrupt is neither lost nor handled more than once. The effect of the change must be visible in finite time.

GICD_IPRIORITYR<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	`0x2000` + 4n	GICD_IPRIORITYR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_IROUTER<n>, Interrupt Routing Registers, n = 32 - 1019

The GICD_IROUTER<n> characteristics are:

Purpose

When affinity routing is enabled, provides routing information for the SPI with INTID n.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

These registers are available in all configurations of the GIC. If the GIC implementation supports two Security states, these registers are Common.

The maximum value of n is given by (32*(GICD_TYPER.ITLinesNumber+1) - 1). GICD_IROUTER<n> registers where n=0 to 31 are reserved.

Attributes

GICD_IROUTER<n> is a 64-bit register.

Field descriptions

The GICD_IROUTER<n> bit assignments are:



Bits [63:40]

Reserved, RES0.

Aff3, bits [39:32]

Affinity level 3, the least significant affinity level field.

This field resets to an architecturally UNKNOWN value.

Interrupt_Routing_Mode, bit [31]

Interrupt Routing Mode. Defines how SPIs are routed in an affinity hierarchy:

Interrupt_Routing_Mode	Meaning
0b0	Interrupts routed to the PE specified by a.b.c.d. In this routing, a, b, c, and d are the values of fields Aff3, Aff2, Aff1, and Aff0 respectively.
0b1	Interrupts routed to any PE defined as a participating node.

If GICD_IROUTER<n>.IRM == 0 and the affinity path does not correspond to an implemented PE, then if the corresponding interrupt becomes pending it will not be forwarded to any PE and will remain pending.

In implementations that do not require 1 of N distribution of SPIs, this bit might be RAZ/WI.

When this bit is set to 1, GICD_IROUTER<n>.{Aff3, Aff2, Aff1, Aff0} are UNKNOWN.

Note

An implementation might choose to make the Aff<n> fields RO when this field is 1.

This field resets to an architecturally UNKNOWN value.

Bits [30:24]

Reserved, RES0.

Aff2, bits [23:16]

Affinity level 2, an intermediate affinity level field.

This field resets to an architecturally UNKNOWN value.

Aff1, bits [15:8]

Affinity level 1, an intermediate affinity level field.

This field resets to an architecturally UNKNOWN value.

Aff0, bits [7:0]

Affinity level 0, the most significant affinity level field.

This field resets to an architecturally UNKNOWN value.

For an SPI with INTID m:

- The corresponding GICD_IROUTER<n> register number, n, is given by n = m.
- The offset of the GICD_IROUTER<n> register is `0x6000` + 8n.

Accessing the GICD_IROUTER<n>

These registers are used only when affinity routing is enabled. When affinity routing is not enabled:

- These registers are RES0. An implementation is permitted to make the register RAZ/WI in this case.
- The GICD_ITARGETSR<n> registers provide interrupt routing information.

Note

When affinity routing becomes enabled for a Security state (for example, following a reset or following a write to GICD_CTLR) the value of all writeable fields in this register is UNKNOWN for that Security state. When the group of an interrupt changes so the ARE setting for the interrupt changes to 1, the value of this register is UNKNOWN for that interrupt.

If GICD_CTLR.DS==0, unless the GICD_NSACR<n> registers permit Non-secure software to control Group 0 and Secure Group 1 interrupts, any GICD_IROUTER<n> registers that correspond to Group 0 or Secure Group 1 interrupts are accessible only by Secure accesses and are RAZ/WI to Non-secure accesses.

Note

For each interrupt, a GIC implementation might support fewer than 256 values for an affinity level. In this case, some bits of the corresponding affinity level field might be RO. Implementations must ensure that an interrupt that is pending at the time of the write uses either the old value or the new value and must ensure that the interrupt is neither lost nor handled more than one time. The effect of the change must be visible in finite time.

GICD_IROUTER<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	0x6000 + 8n	GICD_IROUTER<n>

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_IROUTER<n>E, Interrupt Routing Registers (Extended SPI Range), n = 0 - 1023

The GICD_IROUTER<n>E characteristics are:

Purpose

When affinity routing is enabled, provides routing information for the corresponding SPI in the extended SPI range.

Configuration

This register is present only when GICv3.1 is implemented. Otherwise, direct accesses to GICD_IROUTER<n>E are RES0.

RW fields in this register reset to architecturally UNKNOWN values.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1, the number of implemented GICD_IROUTER<n>E registers is (((GICD_TYPER.ESPI_range+1)*32)-1). Registers are numbered from 0.

Attributes

GICD_IROUTER<n>E is a 32-bit register.

Field descriptions

The GICD_IROUTER<n>E bit assignments are:



Bits [63:40]

Reserved, RES0.

Aff3, bits [39:32]

Affinity level 3, the least significant affinity level field.

Interrupt_Routing_Mode, bit [31]

Interrupt Routing Mode. Defines how SPIs are routed in an affinity hierarchy:

Interrupt_Routing_Mode	Meaning
0b0	Interrupts routed to the PE specified by a.b.c.d. In this routing, a, b, c, and d are the values of fields Aff3, Aff2, Aff1, and Aff0 respectively.
0b1	Interrupts routed to any PE defined as a participating node.

If GICD_IROUTER<n>E.IRM == 0 and the affinity path does not correspond to an implemented PE, then if the corresponding interrupt becomes pending it will not be forwarded to any PE and will remain pending.

In implementations that do not require 1 of N distribution of SPIs, this bit might be RAZ/WI.

When this bit is set to 1, GICD_IROUTER<n>E.{Aff3, Aff2, Aff1, Aff0} are UNKNOWN.

Note

An implementation might choose to make the Aff<n> fields RO when this field is 1.

Bits [30:24]

Reserved, RES0.

Aff2, bits [23:16]

Affinity level 2, an intermediate affinity level field.

Aff1, bits [15:8]

Affinity level 1, an intermediate affinity level field.

Aff0, bits [7:0]

Affinity level 0, the most significant affinity level field.

For an SPI with INTID m:

- The corresponding GICD_IROUTER<n>E register number, n, is given by n = m.
- The offset of the GICD_IROUTER<n>E register is `0x6000` + 8n.

Accessing the GICD_IROUTER<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICD_IROUTER<n>E, the register is RES0.

When GICD_CTLR.DS==0, a register that corresponds to a Group 0 or Secure Group 1 interrupt is RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICD_IROUTER<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	`0x8000` + 8n	GICD_IROUTER<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_ISACTIVER<n>E, Interrupt Set-Active Registers (extended SPI range), n = 0 - 31

The GICD_ISACTIVER<n>E characteristics are:

Purpose

Adds the active state to the corresponding SPI in the extended SPI range.

Configuration

This register is present only when GICv3.1 is implemented. Otherwise, direct accesses to GICD_ISACTIVER<n>E are RES0.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1, the number of implemented GICD_ISACTIVER<n>E registers is (GICD_TYPER.ESPI_range+1). Registers are numbered from 0.

Attributes

GICD_ISACTIVER<n>E is a 32-bit register.

Field descriptions

The GICD_ISACTIVER<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Set_active_bit<x>, bit [x], for x = 0 to 31																															

Set_active_bit<x>, bit [x], for x = 0 to 31

For the extended SPIs, adds the active state to interrupt number x. Reads and writes have the following behavior:

Set_active_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not active, and is not active and pending. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is active, or active and pending on this PE. If written, activates the corresponding interrupt, if the interrupt is not already active. If the interrupt is already active, the write has no effect. After a write of 1 to this bit, a subsequent read of this bit returns 1.

This field resets to 0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_ISACTIVER<n>E number, n, is given by n = (m-4096) DIV 32.
- The offset of the required GICD_ISACTIVER<n>E is (0x1A00 + (4*n)).
- The bit number of the required group modifier bit in this register is (m-4096) MOD 32.

Accessing the GICD_ISACTIVER<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICD_ISACTIVER<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure SPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICD_ISACTIVER<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	0x1A00 + 4n	GICD_ISACTIVER<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_ISENABLER<n>, Interrupt Set-Enable Registers, n = 0 - 31

The GICD_ISENABLER<n> characteristics are:

Purpose

Enables forwarding of the corresponding interrupt to the CPU interfaces.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

These registers are available in all GIC configurations. If GICD_CTLR.DS==0, these registers are Common.

The number of implemented GICD_ISENABLER<n> registers is (GICD_TYPER.ITLinesNumber+1). Registers are numbered from 0.

GICD_ISENABLER0 is Banked for each connected PE with GICR_TYPER.Processor_Number < 8.

Accessing GICD_ISENABLER0 from a PE with GICR_TYPER.Processor_Number > 7 is CONSTRAINED UNPREDICTABLE:

- Register is RAZ/WI.
- An UNKNOWN banked copy of the register is accessed.

Attributes

GICD_ISENABLER<n> is a 32-bit register.

Field descriptions

The GICD_ISENABLER<n> bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Set_enable_bit<x>, bit [x], for x = 0 to 31																															

Set_enable_bit<x>, bit [x], for x = 0 to 31

For SPIs and PPIs, controls the forwarding of interrupt number 32n + x to the CPU interfaces. Reads and writes have the following behavior:

Set_enable_bit<x>	Meaning
0b0	If read, indicates that forwarding of the corresponding interrupt is disabled. If written, has no effect.
0b1	If read, indicates that forwarding of the corresponding interrupt is enabled. If written, enables forwarding of the corresponding interrupt. After a write of 1 to this bit, a subsequent read of this bit returns 1.

For SGIs, the behavior of this bit is IMPLEMENTATION DEFINED.

This field resets to an architecturally UNKNOWN value.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_ISENABLER<n> number, n, is given by n = m DIV 32.
- The offset of the required GICD_ISENABLER is (`0x100` + (4*n)).
- The bit number of the required group modifier bit in this register is m MOD 32.

At start-up, and after a reset, a PE can use this register to discover which peripheral INTIDs the GIC supports. If GICD_CTLR.DS==0 in a system that supports EL3, the PE must do this for the Secure view of the available interrupts, and Non-secure software running on the PE must do this discovery after the Secure software has configured interrupts as Group 0/Secure Group 1 and Non-secure Group 1.

Accessing the GICD_ISENABLER<n>

For SGIs and PPIs:

- When ARE is 1 for the Security state of an interrupt, the field for that interrupt is RES0 and an implementation is permitted to make the field RAZ/WI in this case.
- Equivalent functionality is provided by GICR_ISENABLER0.

Bits corresponding to unimplemented interrupts are RAZ/WI.

When GICD_CTLR.DS==0, bits corresponding to Group 0 or Secure Group 1 interrupts are RAZ/WI to Non-secure accesses.

It is IMPLEMENTATION DEFINED whether implemented SGIs are permanently enabled, or can be enabled and disabled by writes to GICD_ISENABLER<n> and GICD_ICENABLER<n> where n=0.

For SPIs and PPIs, each bit controls the forwarding of the corresponding interrupt from the Distributor to the CPU interfaces.

GICD_ISENABLER<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	`0x0100 + 4n`	GICD_ISENABLER<n>

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_ISENABLER<n>E, Interrupt Set-Enable Registers, n = 0 - 31

The GICD_ISENABLER<n>E characteristics are:

Purpose

Enables forwarding of the corresponding SPI in the extended SPI range to the CPU interfaces.

Configuration

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICD_ISENABLER<n>E are RES0.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1, the number of implemented GICD_ISENABLER<n>E registers is (GICD_TYPER.ESPI_range+1). Registers are numbered from 0.

Attributes

GICD_ISENABLER<n>E is a 32-bit register.

Field descriptions

The GICD_ISENABLER<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Set_enable_bit<x>, bit [x], for x = 0 to 31																															

Set_enable_bit<x>, bit [x], for x = 0 to 31

For the extended SPI range, controls the forwarding of interrupt number x to the CPU interface. Reads and writes have the following behavior:

Set_enable_bit<x>	Meaning
0b0	If read, indicates that forwarding of the corresponding interrupt is disabled. If written, has no effect.
0b1	If read, indicates that forwarding of the corresponding interrupt is enabled. If written, enables forwarding of the corresponding interrupt. After a write of 1 to this bit, a subsequent read of this bit returns 1.

This field resets to 0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_ISENABLER<n>E number, n, is given by n = (m-4096) DIV 32.
- The offset of the required GICD_ISENABLER<n>E is (0x1200 + (4*n)).
- The bit number of the required group modifier bit in this register is (m-4096) MOD 32.

Accessing the GICD_ISENABLER<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICD_ISENABLER<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure SPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICD_ISENABLER<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	0x1200 + 4n	GICD_ISENABLER<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_ISPENDR<n>E, Interrupt Set-Pending Registers (extended SPI range), n = 0 - 31

The GICD_ISPENDR<n>E characteristics are:

Purpose

Adds the pending state to the corresponding SPI in the extended SPI range.

Configuration

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICD_ISPENDR<n>E are RES0.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1, the number of implemented GICD_ISPENDR<n>E registers is (GICD_TYPER.ESPI_range+1). Registers are numbered from 0.

Attributes

GICD_ISPENDR<n>E is a 32-bit register.

Field descriptions

The GICD_ISPENDR<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Set_pending_bit<x>, bit [x], for x = 0 to 31																															

Set_pending_bit<x>, bit [x], for x = 0 to 31

For the extended SPIs, adds the pending state to interrupt number x. Reads and writes have the following behavior:

Set_pending_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not pending. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is pending, or active and pending. If written, changes the state of the corresponding interrupt from inactive to pending, or from active to active and pending. This has no effect in the following cases: • If the interrupt is already pending because of a write to GICD_ISPENDR<n>E. • If the interrupt is already pending because the corresponding interrupt signal is asserted. In this case, the interrupt remains pending if the interrupt signal is deasserted.

This field resets to 0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_ISPENDR<n>E number, n, is given by n = (m-4096) DIV 32.
- The offset of the required GICD_ISPENDR<n>E is (`0x1600` + (4*n)).
- The bit number of the required group modifier bit in this register is (m-4096) MOD 32.

Accessing the GICD_ISPENDR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICD_ISPENDR<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure SPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICD_ISPENDR<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	`0x1600 + 4n`	GICD_ISPENDR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_ITARGETSR<n>, Interrupt Processor Targets Registers, n = 0 - 254

The GICD_ITARGETSR<n> characteristics are:

Purpose

When affinity routing is not enabled, holds the list of target PEs for the interrupt. That is, it holds the list of CPU interfaces to which the Distributor forwards the interrupt if it is asserted and has sufficient priority.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

These registers are available in all configurations of the GIC. When GICD_CTLR.DS==0, these registers are Common.

The number of implemented GICD_ITARGETSR<n> registers is 8*(GICD_TYPER.ITLinesNumber+1). Registers are numbered from 0.

GICD_ITARGETSR0 to GICD_ITARGETSR7 are Banked for each connected PEwith GICR_TYPER.Processor_Number < 8.

Accessing GICD_ITARGETSR0 to GICD_ITARGETSR7 from a PE with GICR_TYPER.Processor_Number > 7 is CONSTRAINED UNPREDICTABLE:

- Register is RAZ/WI.
- An UNKNOWN banked copy of the register is accessed.

Attributes

GICD_ITARGETSR<n> is a 32-bit register.

Field descriptions

The GICD_ITARGETSR<n> bit assignments are:



PEs in the system number from 0, and each bit in a PE targets field refers to the corresponding PE. For example, a value of 0x3 means that the Pending interrupt is sent to PEs 0 and 1. For GICD_ITARGETSR0-GICD_ITARGETSR7, a read of any targets field returns the number of the PE performing the read.

CPU_targets_offset_3B, bits [31:24]

PE targets for an interrupt, at byte offset 3.

This field resets to an architecturally UNKNOWN value.

CPU_targets_offset_2B, bits [23:16]

PE targets for an interrupt, at byte offset 2.

This field resets to an architecturally UNKNOWN value.

CPU_targets_offset_1B, bits [15:8]

PE targets for an interrupt, at byte offset 1.

This field resets to an architecturally UNKNOWN value.

CPU_targets_offset_0B, bits [7:0]

PE targets for an interrupt, at byte offset 0.

This field resets to an architecturally UNKNOWN value.

The bits that are set to 1 in the PE targets field determine which PEs are targeted:

Value of PE targets field	Interrupt targets
0bxxxxxxx1	CPU interface 0
0bxxxxxx1x	CPU interface 1
0bxxxxx1xx	CPU interface 2
0bxxxx1xxx	CPU interface 3
0bxxx1xxxx	CPU interface 4
0bxx1xxxxx	CPU interface 5
0bx1xxxxxx	CPU interface 6
0b1xxxxxxx	CPU interface 7

For interrupt ID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_ITARGETSR<n> number, n, is given by n = m DIV 4.
- The offset of the required GICD_ITARGETSR<n> register is (0x800 + (4*n)).
- The byte offset of the required Priority field in this register is m MOD 4, where:
  - Byte offset 0 refers to register bits [7:0].
  - Byte offset 1 refers to register bits [15:8].
  - Byte offset 2 refers to register bits [23:16].
  - Byte offset 3 refers to register bits [31:24].

Software can write to these registers at any time. Any change to a targets field value:

- Has no effect on any active interrupt. This means that removing a CPU interface from a targets list does not cancel an active state for interrupts on that CPU interface. There is no effect on interrupts that are active and pending until the active status is cleared, at which time it is treated as a pending interrupt.
- Has an effect on any pending interrupts. This means:
  - Enables the CPU interface to be chosen as a target for the pending interrupt using an IMPLEMENTATION DEFINED mechanism.
  - Removing a CPU interface from the target list of a pending interrupt removes the pending state of the interrupt on that CPU interface.

Accessing the GICD_ITARGETSR<n>

These registers are used when affinity routing is not enabled. When affinity routing is enabled for the Security state of an interrupt, the target PEs for an interrupt are defined by GICD_IROUTER<n> and the associated byte in GICD_ITARGETSR<n> is RES0. An implementation is permitted to make the byte RAZ/WI in this case.

- These registers are byte-accessible.
- A register field corresponding to an unimplemented interrupt is RAZ/WI.
- A field bit corresponding to an unimplemented CPU interface is RAZ/WI.
- GICD_ITARGETSR0-GICD_ITARGETSR7 are read-only. Each field returns a value that corresponds only to the PE reading the register.
- It is IMPLEMENTATION DEFINED which, if any, SPIs are statically configured in hardware. The field for such an SPI is read-only, and returns a value that indicates the PE targets for the interrupt.
- If GICD_CTLR.DS==0, unless the GICD_NSACR<n> registers permit Non-secure software to control Group 0 and Secure Group 1 interrupts, any bits that correspond to Group 0 or Secure Group 1 interrupts are accessible only by Secure accesses and are RAZ/WI to Non-secure accesses.

In a single connected PE implementation, all interrupts target one PE, and these registers are RAZ/WI.

Note

Implementations must ensure that an interrupt that is pending at the time of the write uses either the old value or the new value and must ensure that the interrupt is neither lost nor handled more than one time. The effect of the change must be visible in finite time.

GICD_ITARGETSR<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	0x0800 + 4n	GICD_ITARGETSR<n>

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_NSACR<n>E, Non-secure Access Control Registers, n = 0 - 63

The GICD_NSACR<n>E characteristics are:

Purpose

Enables Secure software to permit Non-secure software on a particular PE to create and control Group 0 interrupts.

Configuration

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICD_NSACR<n>E are RES0.

When GICD_TYPER.ESPI==0, these registers are RES0.

When GICD_TYPER.ESPI==1, the number of implemented GICD_ICFGR<n>E registers is ((GICD_TYPER.ESPI_range+1)*2). Registers are numbered from 0.

Attributes

GICD_NSACR<n>E is a 32-bit register.

Field descriptions

The GICD_NSACR<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
NS_access<x>, bits [2x+1:2x], for x = 0 to 15																															

NS_access<x>, bits [2x+1:2x], for x = 0 to 15

Controls Non-secure access of the interrupt with ID 16n + x.

If the corresponding interrupt does not support configurable Non-secure access, the field is RAZ/WI.

Otherwise, the field is RW and determines the level of Non-secure control permitted if the interrupt is a Secure interrupt. If the interrupt is a Non-secure interrupt, this field is ignored.

The possible values of each 2-bit field are:

NS_access<x>	Meaning
0b00	No Non-secure access is permitted to fields associated with the corresponding interrupt.
0b01	Non-secure read and write access is permitted to set-pending bits in GICD_ISPENDR<n>E associated with the corresponding interrupt. A Non-secure write access to GICD_SETSPI_NSR is permitted to set the pending state of the corresponding interrupt.
0b10	As 0b01, but adds Non-secure read and write access permission to fields associated with the corresponding interrupt in the GICD_ICPENDR<n>E registers. A Non-secure write access to GICD_CLRSPI_NSR is permitted to clear the pending state of the corresponding interrupt. Also adds Non-secure read access permission to fields associated with the corresponding interrupt in the GICD_ISACTIVER<n>E and GICD_ICACTIVER<n>E registers.
0b11	This encoding is treated as 0b10, but adds Non-secure read and write access permission to GICD_IROUTER<n>E fields associated with the corresponding interrupt.

This field resets to 0.

For interrupt ID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICD_NSACR<n>E number, n, is given by n = (m - 4096) DIV 16.
- The offset of the required GICD_NSACR<n>E register is (0x3600 + (4*n)).

Accessing the GICD_NSACR<n>E

GICD_NSACR<n>E can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	0x3600 + 4n	GICD_NSACR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RAZ/WI**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RAZ/WI**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICD_TYPER, Interrupt Controller Type Register

The GICD_TYPER characteristics are:

Purpose

Provides information about what features the GIC implementation supports. It indicates:

- Whether the GIC implementation supports two Security states.
- The maximum number of INTIDs that the GIC implementation supports.
- The number of PEs that can be used as interrupt targets.

Configuration

This register is available in all configurations of the GIC. When GICD_CTLR.DS==0, this register is Common.

Attributes

GICD_TYPER is a 32-bit register.

Field descriptions

The GICD_TYPER bit assignments are:



ESPI_range ~~field~~, bits [31:27]

When GICD_TYPER.ESPI == 1:

Indicates the maximum INTID in the Extended SPI range.

- Maximum Extended SPI INTID is (32*(ESPI_range + 1) + 4095)

Otherwise:

Reserved, RES0.

RSS, bit [26]

Range Selector Support. ~~Possible values are:~~

RSS	Meaning
0b0	The IRI supports targeted SGIs with affinity level 0 values of 0 - 15.
0b1	The IRI supports targeted SGIs with affinity level 0 values of 0 - 255.

No1N, bit [25]

Indicates whether 1 of N SPI interrupts are supported.

No1N	Meaning
0b0	1 of N SPI interrupts are supported.
0b1	1 of N SPI interrupts are not supported.

A3V, bit [24]

Affinity 3 valid. Indicates whether the Distributor supports nonzero values of Affinity level 3. ~~Possible values are:~~

A3V	Meaning
0b0	The Distributor only supports zero values of Affinity level 3.
0b1	The Distributor supports nonzero values of Affinity level 3.

IDbits, bits [23:19]

The number of interrupt identifier bits supported, minus one.

DVIS, bit [18]

Indicates whether the implementation supports Direct Virtual LPI injection.

DVIS	Meaning
0b0	The implementation does not support Direct Virtual LPI injection.
0b1	The implementation supports Direct Virtual LPI injection.

For GICv3, this field is RES0.

LPIS, bit [17]

Indicates whether the implementation supports LPIs.

LPIS	Meaning
0b0	The implementation does not support LPIs.
0b1	The implementation supports LPIs.

MBIS, bit [16]

Indicates whether the implementation supports message-based interrupts by writing to Distributor registers.

MBIS	Meaning
0b0	The implementation does not support message-based interrupts by writing to Distributor registers. The GICD_CLRSPI_NSR, GICD_SETSPI_NSR, GICD_CLRSPI_SR, and GICD_SETSPI_SR registers are reserved.
0b1	The implementation supports message-based interrupts by writing to the GICD_CLRSPI_NSR, GICD_SETSPI_NSR, GICD_CLRSPI_SR, or GICD_SETSPI_SR registers.

num_LPIs, bits [15:11]

Number of supported LPIs.

- 0b00000 Number of LPIs as indicated by GICD_TYPER.IDbits.
- All other values Number of LPIs supported is 2^(num_LPIs+1) .
    - Available LPI INTIDs are 8192..(8192 + 2^(num_LPIs+1) - 1).
    - This field cannot indicate a maximum LPI INTID greater than that indicated by GICD_TYPER.IDbits.

When the supported INTID width is less than 14 bits, this field is RES0 and no LPIs are supported.

SecurityExtn, bit [10]

Indicates whether the GIC implementation supports two Security states:

When GICD_CTLR.DS == 1, this field is RAZ.

SecurityExtn	Meaning
0b0	The GIC implementation supports only a single Security state.
0b1	The GIC implementation supports two Security states.

Bit [9]

Reserved, RES0.

ESPI, bit [8]

Extended SPI

ESPI	Meaning
0b0	Extended SPI range not implemented.
0b1	Extended SPI range implemented.

CPUNumber, bits [7:5]

Reports the number of PEs that can be used when affinity routing is not enabled, minus 1.

These PEs must be numbered contiguously from zero, but the relationship between this number and the affinity hierarchy from MPIDR is IMPLEMENTATION DEFINED. If the implementation does not support ARE being zero, this field is 000.

ITLinesNumber, bits [4:0]

Indicates the maximum SPI INTID that the GIC implementation supports. If the value of this field is N, the maximum SPI INTID is 32(N+1)-1. For example, 00011 specifies that the maximum SPI INTID is 127.

The maximum SPI INTID an implementation might support is 1019 (field value 11111). Regardless of the range of INTIDs defined by this field, interrupt IDs 1020-1023 are reserved for special purposes.

A value of 0 indicates no SPIs are support.

Note

The value derived from this field specifies the maximum number of SPIs that the GIC implementation might support. An implementation might not implement all SPIs up to this maximum.

The ITLinesNumber field only indicates the maximum number of SPIs that the GIC implementation might support. This value determines the number of instances of the following interrupt registers:

- GICD_IGROUPR<n>.
- GICD_ISENABLER<n>.
- GICD_ICENABLER<n>.
- GICD_ISPENDR<n>.
- GICD_ICPENDR<n>.
- GICD_ISACTIVER<n>.
- GICD_ICACTIVER<n>.
- GICD_IPRIORITYR<n>.
- GICD_ITARGETSR<n>.
- GICD_ICFGR<n>.

The GIC architecture does not require a GIC implementation to support a continuous range of SPI interrupt IDs. Software must check which SPI INTIDs are supported, up to the maximum value indicated by GICD_TYPER.ITLinesNumber.

Accessing the GICD_TYPER

GICD_TYPER can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Distributor	0x0004	GICD_TYPER

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RO**.
- When IsAccessSecure() accesses to this register are **RO**.
- When !IsAccessSecure() accesses to this register are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

no old file htmldiff from- (new)

GICD_TYPER2, Interrupt Controller Type Register 2

The GICD_TYPER2 characteristics are:

Purpose

Provides information about which features the GIC implementation supports.

Configuration

This register is present only when GICv4.1 is implemented. Otherwise, direct accesses to GICD_TYPER2 are RES0.

When GICD_CTLR.DS == 0, this register is Common.

Attributes

GICD_TYPER2 is a 32-bit register.

Field descriptions

The GICD_TYPER2 bit assignments are:



Bits [31:8]

Reserved, RES0.

VIL, bit [7]

Indicates whether 16 bits of vPEID are implemented.

VIL	Meaning
0b0	GIC supports 16-bit vPEID.
0b1	GIC supports GICD_TYPER2.VID + 1 bits of vPEID.

Bits [6:5]

Reserved, RES0.

VID, bits [4:0]

When GICD_TYPER2.VIL == 1, the number of bits is equal to the bits of vPEID minus one.

When GICD_TYPER2.VIL == 0, this field is RES0.

Accessing the GICD_TYPER2

GICD_TYPER2 can be accessed through the memory-mapped interfaces:

Component	Offset	Instance

GIC Distributor	0x000C	GICD_TYPER2

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RO**.
- When IsAccessSecure() accesses to this register are **RO**.
- When !IsAccessSecure() accesses to this register are **RO**.

13/12/2019 15:13; 391b5248b29fb2f001ef74792eaacbd6fc72f211

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

no old file htmldiff from- (new)

(old) htmldiff from- (new)

GICH_EISR, End Interrupt Status Register

The GICH_EISR characteristics are:

Purpose

Indicates which List registers have outstanding EOI maintenance interrupts.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is available when the GIC implementation supports interrupt virtualization.

Attributes

GICH_EISR is a 32-bit register.

Field descriptions

The GICH_EISR bit assignments are:



Bits [31:16]

Reserved, RES0.

Status<n>, bit [n], for n = 0 to 15

EOI maintenance interrupt status for List register <n>:

Status<n>	Meaning
0b0	GICH_LR<n> does not have an EOI maintenance interrupt.
0b1	GICH_LR<n> has an EOI maintenance interrupt that has not been handled.

For any GICH_LR<n> register, the corresponding status bit is set to 1 if all of the following are true:

- GICH_LR<n>.State is 0b00.
- GICH_LR<n>.HW == 0.
- GICH_LR<n>.EOI == 1.

This field resets to an architecturally UNKNOWN value.

Accessing the GICH_EISR

This register is used only when System register access is not enabled. When System register access is enabled:

- For AArch32 implementations, ICH_EISR provides equivalent functionality.
- For AArch64 implementations, ICH_EISR_EL2 provides equivalent functionality.

Bits corresponding to unimplemented List registers are RAZ.

GICH_EISR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Virtual interface control	0x0020	GICH_EISR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RO**.
- When IsAccessSecure() accesses to this register are **RO**.
- When !IsAccessSecure() accesses to this register are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICH_HCR, Hypervisor Control Register

The GICH_HCR characteristics are:

Purpose

Controls the virtual CPU interface.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is available when the GIC implementation supports interrupt virtualization.

Attributes

GICH_HCR is a 32-bit register.

Field descriptions

The GICH_HCR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
EOICount					RES0																			VGrp1DIE	VGrp1EIE	VGrp0DIE	VGrp0EIE	NPIE	LRENPIE	UIE	En

EOICount, bits [31:27]

Counts the number of EOIs received that do not have a corresponding entry in the List registers. The virtual CPU interface increments this field automatically when a matching EOI is received. EOIs that do not clear a bit in GICH_APR<n> do not cause an increment. If an EOI occurs when the value of this field is 31, then the field wraps to 0.

The maintenance interrupt is asserted whenever this field is nonzero and GICH_HCR.LRENPIE == 1.

This field resets to an architecturally UNKNOWN value.

Bits [26:8]

Reserved, RES0.

VGrp1DIE, bit [7]

VM Group 1 Disabled Interrupt Enable.

Enables the signaling of a maintenance interrupt while signaling of Group 1 interrupts from the virtual CPU interface to the connected virtual machine is disabled:

VGrp1DIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when GICV_CTLR.EnableGrp1 == 0.

This field resets to an architecturally UNKNOWN value.

VGrp1EIE, bit [6]

VM Group 1 Enabled Interrupt Enable.

Enables the signaling of a maintenance interrupt while signaling of Group 1 interrupts from the virtual CPU interface to the connected virtual machine is enabled:

VGrp1EIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when GICV_CTLR.EnableGrp1 == 1.

This field resets to an architecturally UNKNOWN value.

VGrp0DIE, bit [5]

VM Group 0 Disabled Interrupt Enable.

Enables the signaling of a maintenance interrupt while signaling of Group 0 interrupts from the virtual CPU interface to the connected virtual machine is disabled:

VGrp0DIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when GICV_CTLR.EnableGrp0 == 0.

This field resets to an architecturally UNKNOWN value.

VGrp0EIE, bit [4]

VM Group 0 Enabled Interrupt Enable.

Enables the signaling of a maintenance interrupt while signaling of Group 0 interrupts from the virtual CPU interface to the connected virtual machine is enabled:

VGrp0EIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled when GICV_CTLR.EnableGrp0 == 1.

This field resets to an architecturally UNKNOWN value.

NPIE, bit [3]

No Pending Interrupt Enable.

Enables the signaling of a maintenance interrupt while no pending interrupts are present in the List registers:

NPIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled while the List registers contain no interrupts in the pending state.

This field resets to an architecturally UNKNOWN value.

LRENPIE, bit [2]

List Register Entry Not Present Interrupt Enable.

Enables the signaling of a maintenance interrupt while the virtual CPU interface does not have a corresponding valid List register for an EOI request:

LRENPIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	Maintenance interrupt signaled while GICH_HCR.EOICount is not 0.

This field resets to an architecturally UNKNOWN value.

UIE, bit [1]

Underflow Interrupt Enable.

Enables the signaling of a maintenance interrupt when the List registers are either empty or hold only one valid entry.

UIE	Meaning
0b0	Maintenance interrupt disabled.
0b1	A maintenance interrupt is signaled if zero or one of the List register entries are marked as a valid interrupt.

This field resets to an architecturally UNKNOWN value.

En, bit [0]

Enable.

Global enable bit for the virtual CPU interface.

En	Meaning
0b0	Virtual CPU interface operation is disabled.
0b1	Virtual CPU interface operation is enabled.

When this field is 0:

- The virtual CPU interface does not signal any maintenance interrupts.
- The virtual CPU interface does not signal any virtual interrupts.
- A read of GICV_IAR or GICV_AIAR returns a spurious interrupt ID.

This field resets to an architecturally UNKNOWN value.

The VGrp1DIE, VGrp1EIE, VGrp0DIE, and VGrp0EIE fields permit the hypervisor to track the virtual CPU interfaces that are enabled. The hypervisor can then route interrupts that have multiple targets correctly and efficiently, without having to read the virtual CPU interface status.

See Maintenance interrupts and GICH_MISR for more information.

Accessing the GICH_HCR

This register is used only when System register access is not enabled. When System register access is enabled:

- For AArch32 implementations, ICH_HCR provides equivalent functionality.
- For AArch64 implementations, ICH_HCR_EL2 provides equivalent functionality.

GICH_HCR.En must be set to 1 for any virtual or maintenance interrupt to be asserted.

GICH_HCR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Virtual interface control	0x0000	GICH_HCR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICH_LR<n>, List Registers, n = 0 - 15

The GICH_LR<n> characteristics are:

Purpose

These registers provide context information for the virtual CPU interface.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is available when the GIC implementation supports interrupt virtualization.

A maximum of 16 List registers can be provided. GICH_VTR.ListRegs defines the number implemented. Unimplemented List registers are RAZ/WI.

Attributes

GICH_LR<n> is a 32-bit register.

Field descriptions

The GICH_LR<n> bit assignments are:



HW, bit [31]

Indicates whether this virtual interrupt is a hardware interrupt, meaning that it corresponds to a physical interrupt. Deactivation of the virtual interrupt also causes the deactivation of the physical interrupt corresponding to the INTID:

HW	Meaning
0b0	This interrupt is triggered entirely in software. No notification is sent to the Distributor when the virtual interrupt is deactivated.
0b1	A hardware interrupt. A deactivate interrupt request is sent to the Distributor when the virtual interrupt is deactivated, using GICH_LR<n>.pINTID to indicate the physical interrupt identifier. If GICV_CTLR.EOImode == 0, this request corresponds to a write to GICV_EOIR or GICV_AEOIR, otherwise it corresponds to a write to GICV_DIR.

This field resets to an architecturally UNKNOWN value.

Group, bit [30]

Indicates whether the interrupt is Group 0 or Group 1:

Group	Meaning
0b0	Group 0 virtual interrupt. GICV_CTLR.FIQEn determines whether it is signaled as a virtual IRQ or as a virtual FIQ, and GICV_CTLR.EnableGrp0 enables signaling of this interrupt to the virtual machine.
0b1	Group 1 virtual interrupt, signaled as a virtual IRQ. GICV_CTLR.EnableGrp1 enables signaling of this interrupt to the virtual machine.

Note

GICV_CTLR.CBPR controls whether GICV_BPR or GICV_ABPR determines if a pending Group 1 interrupt has sufficient priority to preempt current execution.

This field resets to an architecturally UNKNOWN value.

State, bits [29:28]

The state of the interrupt. This field has one of the following values:

State	Meaning
0b00	Inactive
0b01	Pending
0b10	Active
0b11	Active and pending

The GIC updates these state bits as virtual interrupts proceed through the interrupt life cycle. Entries in the inactive state are ignored, except for the purpose of generating virtual maintenance interrupts.

Note

For hardware interrupts, the active and pending state is held in the Distributor rather than the virtual CPU interface. A hypervisor must only use the active and pending state for software originated interrupts, which are typically associated with virtual devices, or for SGIs.

This field resets to an architecturally UNKNOWN value.

Priority, bits [27:23]

The priority of this interrupt.

This field resets to an architecturally UNKNOWN value.

Bits [22:20]

Reserved, RES0.

pINTID, bits [19:10]

The function of this field depends on the value of GICH_LR<n>.HW.

When GICH_LR<n>.HW == 0:

- Bit [19] indicates whether the interrupt triggers an EOI maintenance interrupt. If this bit is 1, then when the interrupt identified by vINTID is deactivated, an EOI maintenance interrupt is asserted.
- Bits [18:13] are reserved, SBZ.
- If the vINTID field value corresponds to an SGI (that is, 0-15), bits [12:10] contain the number of the requesting PE. This appears in the corresponding field of GICV_IAR or GICV_AIAR. If the vINTID field value is not 0-15, this field must be cleared to 0.

When GICH_LR<n>.HW == 1:

- This field indicates the pINTID that the hypervisor forwards to the Distributor. This field is only required to implement enough bits to hold a valid value for the ID configuration. Any unused higher order bits are RAZ/WI.
- If the value of pINTID is 0-15 or 1020-1023, behavior is UNPREDICTABLE. If the value of pINTID is 16-31, this field applies to the PPI associated with this same PE as the virtual CPU interface requesting the deactivation.

This field resets to an architecturally UNKNOWN value.

vINTID, bits [9:0]

This INTID is returned to the VM when the interrupt is acknowledged through GICV_IAR. Each valid interrupt stored in the List registers must have a unique vINTID for that virtual CPU interface. If the value of vINTID is 1020-1023, behavior is UNPREDICTABLE.

This field resets to an architecturally UNKNOWN value.

Accessing the GICH_LR<n>

This register is used only when System register access is not enabled. When System register access is enabled:

- For AArch32 implementations, ICH_LR<n> provides equivalent functionality.
- For AArch64 implementations, ICH_LR<n>_EL2 provides equivalent functionality.

GICH_LR<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Virtual interface control	0x0100 + 4n	GICH_LR<n>

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICH_VMCR, Virtual Machine Control Register

The GICH_VMCR characteristics are:

Purpose

Enables the hypervisor to save and restore the virtual machine view of the GIC state. This register is updated when a virtual machine updates the virtual CPU interface registers.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is available when the GIC implementation supports interrupt virtualization.

Attributes

GICH_VMCR is a 32-bit register.

Field descriptions

The GICH_VMCR bit assignments are:



VPMR, bits [31:24]

Virtual priority mask. The priority mask level for the CPU interface. If the priority of an interrupt is higher than the value indicated by this field, the interface signals the interrupt to the PE.

This alias field is updated when a VM updates GICV_PMR.Priority.

This field resets to an architecturally UNKNOWN value.

VBPR0, bits [23:21]

Virtual Binary Point Register, Group 0. Defines the point at which the priority value fields split into two parts, the Group priority field and the subpriority field. The Group priority field determines Group 0 interrupt preemption, and also determines Group 1 interrupt preemption if GICH_VMCR.VCBPR == 1.

This alias field is updated when a VM updates GICV_BPR.Binary_Point.

This field resets to an architecturally UNKNOWN value.

VBPR1, bits [20:18]

Virtual Binary Point Register, Group 1. Defines the point at which the priority value fields split into two parts, the Group priority field and the subpriority field. The Group priority field determines Group 1 interrupt preemption if GICH_VMCR.VCBPR == 0.

This alias field is updated when a VM updates GICV_ABPR.Binary_Point.

This field resets to an architecturally UNKNOWN value.

Bits [17:10]

Reserved, RES0.

VEOIM, bit [9]

Virtual EOImode. Possible values of this bit are:

VEOIM	Meaning
0b0	A write of an INTID to GICV_EOIR or GICV_AEOIR drops the priority of the interrupt with that INTID, and also deactivates that interrupt.
0b1	A write of an INTID to GICV_EOIR or GICV_AEOIR only drops the priority of the interrupt with that INTID. Software must write to GICV_DIR to deactivate the interrupt.

This alias field is updated when a VM updates GICV_CTLR.EOImode.

This field resets to an architecturally UNKNOWN value.

Bits [8:5]

Reserved, RES0.

VCBPR, bit [4]

Virtual Common Binary Point Register. Possible values of this bit are:

VCBPR	Meaning
0b0	GICV_ABPR determines the preemption group for Group 1 interrupts.
0b1	GICV_BPR determines the preemption group for Group 1 interrupts.

This alias field is updated when a VM updates GICV_CTLR.CBPR.

This field resets to an architecturally UNKNOWN value.

VFIQEn, bit [3]

Virtual FIQ enable. Possible values of this bit are:

VFIQEn	Meaning
0b0	Group 0 virtual interrupts are presented as virtual IRQs.
0b1	Group 0 virtual interrupts are presented as virtual FIQs.

This alias field is updated when a VM updates GICV_CTLR.FIQEn.

This field resets to an architecturally UNKNOWN value.

VAckCtl, bit [2]

Virtual AckCtl. Possible values of this bit are:

VAckCtl	Meaning
0b0	If the highest priority pending interrupt is Group 1, a read of GICV_IAR or GICV_HPPIR returns an INTID of 1022.
0b1	If the highest priority pending interrupt is Group 1, a read of GICV_IAR or GICV_HPPIR returns the INTID of the corresponding interrupt.

This alias field is updated when a VM updates GICV_CTLR.AckCtl.

This field is supported for backwards compatibility with GICv2. Arm deprecates the use of this field.

This field resets to an architecturally UNKNOWN value.

VENG1, bit [1]

Virtual interrupt enable, Group 1. Possible values of this bit are:

VENG1	Meaning
0b0	Group 1 virtual interrupts are disabled.
0b1	Group 1 virtual interrupts are enabled.

This alias field is updated when a VM updates GICV_CTLR.EnableGrp1.

This field resets to an architecturally UNKNOWN value.

VENG0, bit [0]

Virtual interrupt enable, Group 0. Possible values of this bit are:

VENG0	Meaning
0b0	Group 0 virtual interrupts are disabled.
0b1	Group 0 virtual interrupts are enabled.

This alias field is updated when a VM updates GICV_CTLR.EnableGrp0.

This field resets to an architecturally UNKNOWN value.

Note

A List register is in the pending state only if the corresponding GICH_LR<n> value is 0b01, that is, pending. The active and pending state is not included.

Accessing the GICH_VMCR

This register is used only when System register access is not enabled. When System register access is enabled:

- For AArch32 implementations, ICH_VMCR provides equivalent functionality.
- For AArch64 implementations, ICH_VMCR_EL2 provides equivalent functionality.

GICH_VMCR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Virtual interface control	0x0008	GICH_VMCR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_CLRLPIR, Clear LPI Pending Register

The GICR_CLRLPIR characteristics are:

Purpose

Clears the pending state of the specified LPI.

Configuration

This register is present only when GICv4.1 is implemented. Otherwise, direct accesses to GICR_CLRLPIR are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_CLRLPIR is a 64-bit register.

Field descriptions

The GICR_CLRLPIR bit assignments are:



Bits [63:32]

Reserved, RES0.

pINTID, bits [31:0]

The INTID of the physical LPI.

Note

The size of this field is IMPLEMENTATION DEFINED, and is specified by the GICD_TYPER.IDbits~~Idbits~~ field. Unimplemented bits are RES0.

Accessing the GICR_CLRLPIR

When written with a 32-bit write the data is zero-extended to 64 bits.

This register is mandatory in an implementation that supports LPIs and does not include an ITS. The functionality of this register is IMPLEMENTATION DEFINED in an implementation that does include an ITS.

Writes to this register have no effect if any of the following apply:

- GICR_CTLR.EnableLPIs == 0.
- The pINTID value specifies an unimplemented LPI.
- The pINTID value specifies an LPI that is not pending.

GICR_CLRLPIR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	RD_base	0x0048	GICR_CLRLPIR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **WO**.
- When IsAccessSecure() accesses to this register are **WO**.
- When !IsAccessSecure() accesses to this register are **WO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_CTLR, Redistributor Control Register

The GICR_CTLR characteristics are:

Purpose

Controls the operation of a Redistributor, and enables the signaling of LPIs by the Redistributor to the connected PE.

Configuration

A copy of this register is provided for each Redistributor.

Attributes

GICR_CTLR is a 32-bit register.

Field descriptions

The GICR_CTLR bit assignments are:

31	30:27	26	25	24	23:22:21:20:19:18:17:16:15:14:13:12:11:10:9	8	7	6	5	4	3	2	1	0
UWP	RES0	DPG1S	DPG1NS	DPG0	RES0						RWP	RES0	CES	EnableLPIs

UWP, bit [31]

Upstream Write Pending. Read-only. Indicates whether all upstream writes have been communicated to the Distributor.

UWP	Meaning
0b0	The effects of all upstream writes have been communicated to the Distributor, including any Generate SGI packets.
0b1	Not all the effects of upstream writes, including any Generate SGI packets, have been communicated to the Distributor.

Bits [30:27]

Reserved, RES0.

DPG1S, bit [26]

Disable Processor selection for Group 1 Secure interrupts. When GICR_TYPER.DPGS == 1:

DPG1S	Meaning
0b0	A Group 1 Secure SPI configured to use the 1 of N distribution model can select this PE, if the PE is not asleep and if Secure Group 1 interrupts are enabled.
0b1	A Group 1 Secure SPI configured to use the 1 of N distribution model cannot select this PE.

When GICR_TYPER.DPGS == 0 this bit is RAZ/WI.

When GICD_CTLR.DS==1, this field is RAZ/WI. In GIC implementations that support two Security states, this field is only accessible by Secure accesses, and is RAZ/WI to Non-secure accesses.

It is IMPLEMENTATION DEFINED whether these~~this~~ bits affect the selection of PEs for interrupts using the 1 of N distribution model when GICD_CTLR.ARE_S==0.

This field resets to 0.

DPG1NS, bit [25]

Disable Processor selection for Group 1 Non-secure interrupts. When GICR_TYPER.DPGS == 1:

DPG1NS	Meaning
0b0	A Group 1 Non-secure SPI configured to use the 1 of N distribution model can select this PE, if the PE is not asleep and if Non-secure Group 1 interrupts are enabled.
0b1	A Group 1 Non-secure SPI configured to use the 1 of N distribution model cannot select this PE.

When GICR_TYPER.DPGS == 0 this bit is RAZ/WI.

It is IMPLEMENTATION DEFINED whether thesethis bits affect the selection of PEs for interrupts using the 1 of N distribution model when GICD_CTLR.ARE_NS==0.

This field resets to 0.

DPG0, bit [24]

Disable Processor selection for Group 0 interrupts. When GICR_TYPER.DPGS == 1:

DPG0	Meaning
0b0	A Group 0 SPI configured to use the 1 of N distribution model can select this PE, if the PE is not asleep and if Group 0 interrupts are enabled.
0b1	A Group 0 SPI configured to use the 1 of N distribution model cannot select this PE.

When GICR_TYPER.DPGS == 0 this bit is RAZ/WI.

When GICD_CTLR.DS == 1, this field is always accessible. In GIC implementations that support two Security states, this field is RAZ/WI to Non-secure accesses.

It is IMPLEMENTATION DEFINED whether thesethis bits affect the selection of PEs for interrupts using the 1 of N distribution model when GICD_CTLR.ARE_S == 0.

This field resets to 0.

Bits [23:4]

Reserved, RES0.

RWP, bit [3]

Register Write Pending. This bit indicates whether a register write for the current Security state is in progress or not.

RWP	Meaning
0b0	The effect of all previous writes to the following registers are visible to all agents in the system: • GICR_ICENABLER0 • GICR_CTLR.DPG1S • GICR_CTLR.DPG1NS • GICR_CTLR.DPG0 • GICR_CTLR, which clears EnableLPIs from 1 to 0. • In GICv4.1, GICR_VPROPBASER, which clears Valid from 1 to 0.
0b1	The effect of all previous writes to the following registers are not guaranteed by the architecture to be visible ~~yet~~ to ~~the~~ all agents in the system ~~while~~as the changes are still being propagated: • GICR_ICENABLER0 • GICR_CTLR.DPG1S • GICR_CTLR.DPG1NS • GICR_CTLR.DPG0 • GICR_CTLR, which clears EnableLPIs from 1 to 0. • In GICv4.1, GICR_VPROPBASER, which clears Valid from 1 to 0.

Bit [2]

Reserved, RES0.

CES, bit [1]

Clear Enable Supported.

This bit is read-only.

CES	Meaning
0b0	The IRI does not indicate whether GICR_CTLR.EnableLPIs is RES1 once set.
0b1	GICR_CTLR.EnableLPIs is not RES1 once set.

Implementing GICR_CTLR.EnableLPIs as programmable and not reporting GICR_CLTR.CES~~CES~~ == 1 is deprecated.

Implementing GICR_CTLR.EnableLPIs as RES1 once set is deprecated.

When GICR_CLTR.CES == 0, software cannot assume that GICR_CTLR.EnableLPIs is programmable without observing the bit being cleared.

EnableLPIs, bit [0]

In implementations where affinity routing is enabled for the Security state:

EnableLPIs	Meaning
0b0	LPI support is disabled. Any doorbell interrupt generated as a result of a write to a virtual LPI register must be discarded, and any ITS translation requests or commands involving LPIs in this Redistributor are ignored.
0b1	LPI support is enabled.

Note

If GICR_TYPER.PLPIS~~LPIS~~ == 0, this field is RES0. If GICD_CTLR.ARE_NS is written from 1 to 0 when this bit is 1, behavior is an IMPLEMENTATION DEFINED choice between clearing GICR_CTLR.EnableLPIs to 0 or maintaining its current value.

When affinity routing is not enabled for the Non-secure state, this bit is RES0.

When written from 0 to 1, the Redistributor loads the LPI Pending table from memory to check for any pending interrupts.

After it has been written to 1, it is IMPLEMENTATION DEFINED whether the bit becomes RES1 or can be cleared by to 0.

Where the bit remains programmable:

- Software must observe GICR_CTLR.RWP==0 after clearing GICR_CTLR.EnableLPIs from 1 to 0 before writing GICR_PENDBASER or GICR_PROPBASER, otherwise behavior is UNPREDICTABLE.
- Software must observe GICR_CTLR.RWP==0 after clearing GICR_CTLR.EnableLPIs from 1 to 0 before setting GICR_CTLR.EnableLPIs to 1, otherwise behavior is UNPREDICTABLE.

Note

If one or more ITS is implemented, Arm strongly recommends that all LPIs are mapped to another Redistributor before GICR_CTLR.EnableLPIs is cleared to 0.

This field resets to `0`.

The participation of a PE in the 1 of N distribution model for a given interrupt group is governed by the concatenation of GICR_WAKER.ProcessorSleep, the appropriate GICR_CTLR.DPG{1, 0} bit, and the PE interrupt group enable. The behavior options are:

PS	DPG{1S, 1NS, 0}	Enable	PE Behavior
0b0	0b0	0b0	The PE cannot be selected.
0b0	0b0	0b1	The PE can be selected.
0b0	0b1	*	The PE cannot be selected.
0b1	*	*	The PE cannot be selected when GICD_CTLR.E1NWF == 0. When GICD_CTLR.E1NWF == 1, the mechanism by which PEs are selected is IMPLEMENTATION DEFINED.

If an SPI using the 1 of N distribution model has been forwarded to the PE, and a write to GICR_CTLR occurs that changes the DPG bit for the interrupt group of the SPI, the IRI must attempt to select a different target PE for the SPI. This might have no effect on the forwarded SPI if it has already been activated.

Accessing the GICR_CTLR

GICR_CTLR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	RD_base	0x0000	GICR_CTLR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ICACTIVER0, Interrupt Clear-Active Register 0

The GICR_ICACTIVER0 characteristics are:

Purpose

Deactivates the corresponding SGI or PPI. These registers are used when saving and restoring GIC state.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

A copy of this register is provided for each Redistributor.

Attributes

GICR_ICACTIVER0 is a 32-bit register.

Field descriptions

The GICR_ICACTIVER0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Clear_active_bit<x>, bit [x], for x = 0 to 31																															

Clear_active_bit<x>, bit [x], for x = 0 to 31

Removes the active state from interrupt number x. Reads and writes have the following behavior:

Clear_active_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not active, and is not active and pending. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is active, or is active and pending. If written, deactivates the corresponding interrupt, if the interrupt is active. If the interrupt is already deactivated, the write has no effect.

This field resets to an architecturally UNKNOWN value.

Accessing the GICR_ICACTIVER0

When affinity routing is not enabled for the Security state of an interrupt in GICR_ICACTIVER0, the corresponding bit is RAZ/WI and equivalent functionality is provided by GICD_ICACTIVER<n> with n=0.

This register only applies to SGIs (bits [15:0]) and PPIs (bits [31:16]). For SPIs, this functionality is provided by GICD_ICACTIVER<n>.

When GICD_CTLR.DS == 0, bits corresponding to Secure SGIs and PPIs are RAZ/WI to Non-secure accesses.

GICR_ICACTIVER0 can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0380	GICR_ICACTIVER0

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ICACTIVER<n>E, Interrupt Clear-Active Registers, n = 1 - 2

The GICR_ICACTIVER<n>E characteristics are:

Purpose

Removes the active state from the corresponding PPI.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_ICACTIVER<n>E are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_ICACTIVER<n>E is a 32-bit register.

Field descriptions

The GICR_ICACTIVER<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Clear_active_bit<x>, bit [x], for x = 0 to 31																															

Clear_active_bit<x>, bit [x], for x = 0 to 31

For the extended PPIs, removes the active state to interrupt number x. Reads and writes have the following behavior:

Clear_active_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not active, and is not active and pending. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is active, or is active and pending. If written, deactivates the corresponding interrupt, if the interrupt is active. If the interrupt is already deactivated, the write has no effect.

This field resets to an architecturally UNKNOWN value.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICR_ICACTIVER<n>E number, n, is given by n = (m-1024) DIV 32.
- The offset of the required GICR_ICACTIVER<n>E is (0x200 + (4*n)).
- The bit number of the required group modifier bit in this register is (m-1024) MOD 32.

Accessing the GICR_ICACTIVER<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICR_ICACTIVER<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure PPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICR_ICACTIVER<n>E can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0380 + 4n	GICR_ICACTIVER<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ICENABLER0, Interrupt Clear-Enable Register 0

The GICR_ICENABLER0 characteristics are:

Purpose

Disables forwarding of the corresponding SGI or PPI to the CPU interfaces.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

A copy of this register is provided for each Redistributor.

Attributes

GICR_ICENABLER0 is a 32-bit register.

Field descriptions

The GICR_ICENABLER0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Clear_enable_bit<x>, bit [x], for x = 0 to 31																															

Clear_enable_bit<x>, bit [x], for x = 0 to 31

For PPIs and SGIs, controls the forwarding of interrupt number x to the CPU interfaces. Reads and writes have the following behavior:

Clear_enable_bit<x>	Meaning
0b0	If read, indicates that forwarding of the corresponding interrupt is disabled. If written, has no effect.
0b1	If read, indicates that forwarding of the corresponding interrupt is enabled. If written, disables forwarding of the corresponding interrupt. After a write of 1 to this bit, a subsequent read of this bit returns 0.

This field resets to an architecturally UNKNOWN value.

Accessing the GICR_ICENABLER0

When affinity routing is not enabled for the Security state of an interrupt in GICR_ICENABLER0, the corresponding bit is RAZ/WI and equivalent functionality is provided by GICD_ICENABLER<n> with n=0.

This register only applies to SGIs (bits [15:0]) and PPIs (bits [31:16]). For SPIs, this functionality is provided by GICD_ICENABLER<n>.

When GICD_CTLR.DS == 0, bits corresponding to Secure SGIs and PPIs are RAZ/WI to Non-secure accesses.

GICR_ICENABLER0 can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0180	GICR_ICENABLER0

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ICENABLER<n>E, Interrupt Clear-Enable Registers, n = 1 - 2

The GICR_ICENABLER<n>E characteristics are:

Purpose

Disables forwarding of the corresponding PPI to the CPU interfaces.

Configuration

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_ICENABLER<n>E are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_ICENABLER<n>E is a 32-bit register.

Field descriptions

The GICR_ICENABLER<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Clear_enable_bit<x>, bit [x], for x = 0 to 31																															

Clear_enable_bit<x>, bit [x], for x = 0 to 31

For the extended PPI range, controls the forwarding of interrupt number x to the CPU interface. Reads and writes have the following behavior:

Clear_enable_bit<x>	Meaning
0b0	If read, indicates that forwarding of the corresponding interrupt is disabled. If written, has no effect.
0b1	If read, indicates that forwarding of the corresponding interrupt is enabled. If written, disables forwarding of the corresponding interrupt. After a write of 1 to this bit, a subsequent read of this bit returns 0.

This field resets to 0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICR_ICENABLER<n>E number, n, is given by n = (m-1024) DIV 32.
- The offset of the required GICR_ICENABLER<n>E is (0x180 + (4*n)).
- The bit number of the required group modifier bit in this register is (m-1024) MOD 32.

Accessing the GICR_ICENABLER<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICR_ICENABLER<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure PPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICR_ICENABLER<n>E can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0180 + 4n	GICR_ICENABLER<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ICFGR0, Interrupt Configuration Register 0

The GICR_ICFGR0 characteristics are:

Purpose

Determines whether the corresponding SGI is edge-triggered or level-sensitive.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

A copy of this register is provided for each Redistributor.

Attributes

GICR_ICFGR0 is a 32-bit register.

Field descriptions

The GICR_ICFGR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Int_config<x>, bits [2x+1:2x], for x = 0 to 15																															

Int_config<x>, bits [2x+1:2x], for x = 0 to 15

Indicates whether the interrupt with ID 16n + x is level-sensitive or edge-triggered.

Int_config[0] (bit [2x]) is RES0.

Possible values of Int_config[1] (bit [2x+1]) are:

Int_config<x>	Meaning
0b00	Corresponding interrupt is level-sensitive.
0b01	Corresponding interrupt is edge-triggered.

For SGIs, Int_config[1] is RAO/WI.

A read of this bit always returns the correct value to indicate the interrupt triggering method.

This field resets to an architecturally UNKNOWN value.

Accessing the GICR_ICFGR0

This register is used when affinity routing is enabled.

When affinity routing is disabled for the Security state of an interrupt, the field for that interrupt is RES0 and an implementation is permitted to make the field RAZ/WI in this case. Equivalent functionality is provided by GICD_ICFGR<n> with n=0.

When GICD_CTLR.DS==0, a register bit that corresponds to a Group 0 or Secure Group 1 interrupt is RAZ/WI to Non-secure accesses.

GICR_ICFGR0 can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0C00	GICR_ICFGR0

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ICFGR1, Interrupt Configuration Register 1

The GICR_ICFGR1 characteristics are:

Purpose

Determines whether the corresponding PPI is edge-triggered or level-sensitive.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

A copy of this register is provided for each Redistributor.

For each supported PPI, it is IMPLEMENTATION DEFINED whether software can program the corresponding Int_config field.

Changing Int_config when the interrupt is individually enabled is UNPREDICTABLE.

Changing the interrupt configuration between level-sensitive and edge-triggered (in either direction) at a time when there is a pending interrupt will leave the interrupt in an UNKNOWN pending state.

Attributes

GICR_ICFGR1 is a 32-bit register.

Field descriptions

The GICR_ICFGR1 bit assignments are:



Int_config<x>, bits [2x+1:2x], for x = 0 to 15

Indicates whether the interrupt with ID 16n + x is level-sensitive or edge-triggered.

Int_config[0] (bit [2x]) is RES0.

Possible values of Int_config[1] (bit [2x+1]) are:

Int_config<x>	Meaning
0b00	Corresponding interrupt is level-sensitive.
0b01	Corresponding interrupt is edge-triggered.

A read of this bit always returns the correct value to indicate the interrupt triggering method.

For PPIs, Int_config[1] is programmable unless the implementation supports two Security states and the bit corresponds to a Group 0 or Secure Group 1 interrupt, in which case the bit is RAZ/WI to Non-secure accesses.

This field resets to an architecturally UNKNOWN value.

Accessing the GICR_ICFGR1

This register is used when affinity routing is enabled.

When affinity routing is disabled for the Security state of an interrupt, the field for that interrupt is RES0 and an implementation is permitted to make the field RAZ/WI in this case. Equivalent functionality is provided by GICD_ICFGR<n> with n=1 .

GICR_ICFGR1 can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0C04	GICR_ICFGR1

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ICFGR<n>E, Interrupt configuration registers, n = 2 - 5

The GICR_ICFGR<n>E characteristics are:

Purpose

Determines whether the corresponding PPI in the extended PPI range is edge-triggered or level-sensitive.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_ICFGR<n>E are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_ICFGR<n>E is a 32-bit register.

Field descriptions

The GICR_ICFGR<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Int_config<x>, bit [x], for x = 0 to 31																															

Int_config<x>, bit [x], for x = 0 to 31

Indicates whether the interrupt with ID 16n + x is level-sensitive or edge-triggered.

Int_config[0] (bit [2x]) is RES0.

Possible values of Int_config[1] (bit [2x+1]) are:

Int_config<x>	Meaning
0b0	The corresponding interrupt is level-sensitive.
0b1	The corresponding interrupt is edge-triggered.

This field resets to an architecturally UNKNOWN value.

For each supported extended PPI, it is IMPLEMENTATION DEFINED whether software can program the corresponding Int_config field.

Accessing the GICR_ICFGR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICR_ICFGR<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, a register bit that corresponds to a Group 0 or Secure Group 1 interrupt is RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICR_ICFGR<n>E can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0C00 + 4n	GICR_ICFGR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ICPENDR0, Interrupt Clear-Pending Register 0

The GICR_ICPENDR0 characteristics are:

Purpose

Removes the pending state from the corresponding SGI or PPI.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

A copy of this register is provided for each Redistributor.

Attributes

GICR_ICPENDR0 is a 32-bit register.

Field descriptions

The GICR_ICPENDR0 bit assignments are:



Clear_pending_bit<x>, bit [x], for x = 0 to 31

Removes the pending state from interrupt number x. Reads and writes have the following behavior:

Clear_pending_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not pending. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is pending, or active and pending. If written, changes the state of the corresponding interrupt from pending to inactive, or from active and pending to active. This has no effect in the following cases: • If the interrupt is not pending and is not active and pending. • If the interrupt is a level-sensitive interrupt that is pending or active and pending for a reason other than a write to GICD_ISPENDR<n>. In this case, if the interrupt signal continues to be asserted, the interrupt remains pending or active and pending.

This field resets to an architecturally UNKNOWN value.

Accessing the GICR_ICPENDR0

When affinity routing is not enabled for the Security state of an interrupt in GICR_ICPENDR0, the corresponding bit is RAZ/WI and equivalent functionality is provided by GICD_ICPENDR<n> with n=0.

This register only applies to SGIs (bits [15:0]) and PPIs (bits [31:16]). For SPIs, this functionality is provided by GICD_ICENABLER<n>.

When GICD_CTLR.DS == 0, bits corresponding to Secure SGIs and PPIs are RAZ/WI to Non-secure accesses.

GICR_ICPENDR0 can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0280	GICR_ICPENDR0

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ICPENDR<n>E, Interrupt Clear-Pending Registers, n = 1 - 2

The GICR_ICPENDR<n>E characteristics are:

Purpose

Removes the pending state from the corresponding PPI.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_ICPENDR<n>E are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_ICPENDR<n>E is a 32-bit register.

Field descriptions

The GICR_ICPENDR<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Clear_pending_bit<x>, bit [x], for x = 0 to 31																															

Clear_pending_bit<x>, bit [x], for x = 0 to 31

For the extended PPIs, removes the pending state to interrupt number x. Reads and writes have the following behavior:

Clear_pending_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not pending on this PE. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is pending, or active and pending on this PE. If written, changes the state of the corresponding interrupt from pending to inactive, or from active and pending to active. This has no effect in the following cases: • If the interrupt is not pending and is not active and pending. • If the interrupt is a level-sensitive interrupt that is pending or active and pending for a reason other than a write to GICR_ISPENDR<n>E. In this case, if the interrupt signal continues to be asserted, the interrupt remains pending or active and pending.

This field resets to an architecturally UNKNOWN value.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICR_ICPENDR<n>E number, n, is given by n = (m-1024) DIV 32.
- The offset of the required GICR_ICPENDR<n>E is (0x200 + (4*n)).
- The bit number of the required group modifier bit in this register is (m-1024) MOD 32.

Accessing the GICR_ICPENDR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICR_ICPENDR<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure PPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICR_ICPENDR<n>E can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0280 + 4n	GICR_ICPENDR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_IGROUPR0, Interrupt Group Register 0

The GICR_IGROUPR0 characteristics are:

Purpose

Controls whether the corresponding SGI or PPI is in Group 0 or Group 1.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is available in all GIC configurations. If the GIC implementation supports two Security states, this register is Secure.

A copy of this register is provided for each Redistributor.

Attributes

GICR_IGROUPR0 is a 32-bit register.

Field descriptions

The GICR_IGROUPR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Redistributor_group_status_bit<x>, bit [x], for x = 0 to 31																															

Redistributor_group_status_bit<x>, bit [x], for x = 0 to 31

Group status bit. In this register:

- Bits [31:16] are group status bits for PPIs.
- Bits [15:0] are group status bits for SGIs.

Redistributor_group_status_bit<x>	Meaning
0b0	When GICD_CTLR.DS==1, the corresponding interrupt is Group 0. When GICD_CTLR.DS==0, the corresponding interrupt is Secure.
0b1	When GICD_CTLR.DS==1, the corresponding interrupt is Group 1. When GICD_CTLR.DS==0, the corresponding interrupt is Non-secure Group 1.

When GICD_CTLR.DS == 0, the bit that corresponds to the interrupt is concatenated with the equivalent bit in GICR_IGRPMODR0 to form a 2-bit field that defines an interrupt group. The encoding of this field is at GICR_IGRPMODR0.

This field resets to an architecturally UNKNOWN value.

The considerations for the reset value of this register are the same as those for GICD_IGROUPR<n> with n=0.

Accessing the GICR_IGROUPR0

When affinity routing is not enabled for the Security state of an interrupt in GICR_IGROUPR0, the corresponding bit is RES0 and equivalent functionality is provided by GICD_IGROUPR<n> with n=0.

When GICD_CTLR.DS == 0, the register is RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

Note

Implementations must ensure that an interrupt that is pending at the time of the write uses either the old value or the new value and must ensure that the interrupt is neither lost nor handled more than one time. The effect of the change must be visible in finite time.

GICR_IGROUPR0 can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0080	GICR_IGROUPR0

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_IGROUPR<n>E, Interrupt Group Registers, n = 1 - 2

The GICR_IGROUPR<n>E characteristics are:

Purpose

Controls whether the corresponding PPI is in Group 0 or Group 1.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_IGROUPR<n>E are RES0.

When ~~GICD_CLTR.DS==0, this register is Secure.~~ GICD_CTLR.DS==0, this register is Secure.

A copy of this register is provided for each Redistributor.

Attributes

GICR_IGROUPR<n>E is a 32-bit register.

Field descriptions

The GICR_IGROUPR<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Group_status_bit<x>, bit [x], for x = 0 to 31																															

Group_status_bit<x>, bit [x], for x = 0 to 31

Group status bit.

Group_status_bit<x>	Meaning
0b0	When GICD_CTLR.DS==1, the corresponding interrupt is Group 0. When GICD_CTLR.DS==0, the corresponding interrupt is Secure.
0b1	When GICD_CTLR.DS==1, the corresponding interrupt is Group 1. When GICD_CTLR.DS==0, the corresponding interrupt is Non-secure Group 1.

This field resets to an architecturally UNKNOWN value.

If affinity routing is enabled for the Security state of an interrupt, the bit that corresponds to the interrupt is concatenated with the equivalent bit in GICR_IGRPMODR<n>E to form a 2-bit field that defines an interrupt group. The encoding of this field is described in GICR_IGRPMODR<n>E.

If affinity routing is disabled for the Security state of an interrupt, the bit is RES0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICR_IGROUPR<n>E number, n, is given by n = (m-1024) DIV 32.
- The offset of the required GICR_IGROUPR<n>E is (0x080 + (4*n)).

- The bit number of the required group modifier bit in this register is (m-1024) MOD 32.

Accessing the GICR_IGROUPR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICR_IGROUPR<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, the register is RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICR_IGROUPR<n>E can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0080 + 4n	GICR_IGROUPR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_IGRPMODR0, Interrupt Group Modifier Register 0

The GICR_IGRPMODR0 characteristics are:

Purpose

When GICD_CTLR.DS==0, this register together with the GICR_IGROUPR0 register, controls whether the corresponding interrupt is in:

- Secure Group 0.
- Non-secure Group 1.
- When System register access is enabled, Secure Group 1.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

When ~~GICD_CLTR.DS==0, this register is Secure.~~ GICD_CTLR.DS==0, this register is Secure.

A copy of this register is provided for each Redistributor.

Attributes

GICR_IGRPMODR0 is a 32-bit register.

Field descriptions

The GICR_IGRPMODR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Group_modifier_bit<x>, bit [x], for x = 0 to 31																															

Group_modifier_bit<x>, bit [x], for x = 0 to 31

Group modifier bit. In implementations where affinity routing is enabled for the Security state of an interrupt, the bit that corresponds to the interrupt is concatenated with the equivalent bit in GICR_IGROUPR0 to form a 2-bit field that defines an interrupt group:

Group modifier bit	Group status bit	Definition	Short name
0b0	0b0	Secure Group 0	G0S
0b0	0b1	Non-secure Group 1	G1NS
0b1	0b0	Secure Group 1	G1S
0b1	0b1	Reserved, treated as Non-secure Group 1	-

This field resets to an architecturally UNKNOWN value.

Accessing the GICR_IGRPMODR0

When affinity routing is not enabled for the Security state of an interrupt in GICR_IGRPMODR0, the corresponding bit is RES0 and equivalent functionality is provided by GICD_IGRPMODR<n> with n=0.

This register only applies to SGIs (bits [15:0]) and PPIs (bits [31:16]). For SPIs, this functionality is provided by GICD_IGRPMODR<n>.

When GICD_CTLR.ARE_S == 0 or GICD_CTLR.DS == 1, GICR_IGRPMODR0 is RES0. An implementation can make this register RAZ/WI in this case.

When GICD_CTLR.DS==0, the register is RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

Note

Implementations must ensure that an interrupt that is pending at the time of the write uses either the old value or the new value and must ensure that the interrupt is neither lost nor handled more than one time. The effect of the change must be visible in finite time.

GICR_IGRPMODR0 can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0D00	GICR_IGRPMODR0

This interface is accessible as follows:

- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_IGRPMODR<n>E, Interrupt Group Modifier Registers, n = 1 - 2

The GICR_IGRPMODR<n>E characteristics are:

Purpose

When GICD_CTLR.DS==0, this register together with the GICR_IGROUPR<n>E registers, controls whether the corresponding interrupt is in:

- Secure Group 0.
- Non-secure Group 1.
- When System register access is enabled, Secure Group 1.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_IGRPMODR<n>E are RES0.

When ~~GICD_CLTR.DS==0, this register is Secure.~~ GICD_CTLR.DS==0, this register is Secure.

A copy of this register is provided for each Redistributor.

Attributes

GICR_IGRPMODR<n>E is a 32-bit register.

Field descriptions

The GICR_IGRPMODR<n>E bit assignments are:



Group_modifier_bit<x>, bit [x], for x = 0 to 31

Group modifier bit. In implementations where affinity routing is enabled for the Security state of an interrupt, the bit that corresponds to the interrupt is concatenated with the equivalent bit in GICR_IGROUPR<n>E to form a 2-bit field that defines an interrupt group:

Group modifier bit	Group status bit	Definition	Short name
0b0	0b0	Secure Group 0	G0S
0b0	0b1	Non-secure Group 1	G1NS
0b1	0b0	Secure Group 1	G1S
0b1	0b1	Reserved, treated as Non-secure Group 1	-

This field resets to an architecturally UNKNOWN value.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICR_IGRPMODR<n>E number, n, is given by n = (m-1024) DIV 32.
- The offset of the required GICR_IGRPMODR<n>E is (0xD00 + (4*n)).
- The bit number of the required group modifier bit in this register is (m-1024) MOD 32.

Accessing the GICR_IGRPMODR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICR_IGRPMODR<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, the register is RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICR_IGRPMODR<n>E can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0D00 + 4n	GICR_IGRPMODR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_INVALLR, Redistributor Invalidate All Register

The GICR_INVALLR characteristics are:

Purpose

Invalidates any cached configuration data of all physical LPIs, causing the GIC to reload the interrupt configuration from the physical LPI Configuration table at the address specified by GICR_PROPBASER.

Configuration

A copy of this register is provided for each Redistributor.

Attributes

GICR_INVALLR is a 64-bit register.

Field descriptions

The GICR_INVALLR bit assignments are:



V,Bits bit [63:0]

When GICv4.1 is implemented:

Indicates whether the INTID is virtual or physical.

V	Meaning
0b0	Invalidate is for a physical INTID.
0b1	Invalidate is for a virtual INTID.

Otherwise:

Reserved, RES0.

Bits [62:48]

Reserved, RES0.

V, bits [47:32]

When GICv4.1 is implemented:

When GICR_INVLPIR.V == 0, this field is RES0

When GICR_INVLPIR.V == 1, this field is the target vPEID of the invalidate.

Note

The size of this field is IMPLEMENTATION DEFINED, and is specified by the GICD_TYPER2.VIL and GICD_TYPER2.VID fields. Unimplemented bits are RES0.

Otherwise:

Reserved, RES0.

Bits [31:0]

Reserved, RES0.

Note

If any LPI has been forwarded to the PE and a valid write to GICR_INVALLR is received, the Redistributor must ensure it reloads its properties from memory. This has no effect on the forwarded LPI if it has already been activated.

Accessing the GICR_INVALLR

This register is mandatory in an implementation that supports LPIs and does not include an ITS. The functionality is IMPLEMENTATION DEFINED in an implementation that does include an ITS.

Writes to this register have no effect if no physical LPIs are currently stored in the local Redistributor cache.

GICR_INVALLR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	RD_base	0x00B0	GICR_INVALLR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **WO**.
- When IsAccessSecure() accesses to this register are **WO**.
- When !IsAccessSecure() accesses to this register are **WO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_INVLPIR, Redistributor Invalidate LPI Register

The GICR_INVLPIR characteristics are:

Purpose

Invalidates the cached configuration data of a specified LPI, causing the GIC to reload the interrupt configuration from the physical LPI Configuration table at the address specified by GICR_PROPBASER.

Configuration

A copy of this register is provided for each Redistributor.

Attributes

GICR_INVLPIR is a 64-bit register.

Field descriptions

The GICR_INVLPIR bit assignments are:



V,Bits bit [63:32]

When GICv4.1 is implemented:

Indicates whether the INTID is virtual or physical.

V	Meaning
0b0	Invalidate is for a physical INTID.
0b1	Invalidate is for a virtual INTID.

Otherwise:

Reserved, RES0.

BitspINTID, bits [6231:480]

Reserved, RES0.

vPEID, bits [47:32]

When GICv4.1 is implemented:

When GICR_INVLPIR.V == 0, this field is RES0

When GICR_INVLPIR.V == 1, this field is the target vPEID of the invalidate.

Note

The size of this field is IMPLEMENTATION DEFINED, and is specified by the GICD_TYPER2.VIL and GICD_TYPER2.VID fields. Unimplemented bits are RES0.

Otherwise:

Reserved, RES0.

INTID, bits [31:0]

The INTID of the physical LPI to be cleaned.

Note

The size of this field is IMPLEMENTATION DEFINED, and is specified by the GICD_TYPER.IDbits field. Unimplemented bits are RES0.

Note

If any LPI has been forwarded to the PE and a valid write to GICR_INVLPIR is received, the Redistributor must ensure it reloads its properties from memory and apply any changes by retrieving and reforwarding the LPI as required. This has no effect on the forwarded LPI if it has already been activated.

Accessing the GICR_INVLPIR

When written with a 32-bit write the data is zero-extended to 64 bits.

This register is mandatory in an implementation that supports LPIs and does not include an ITS. The functionality is IMPLEMENTATION DEFINED in an implementation that does include an ITS.

Writes to this register have no effect if either:

- The specified LPI is not currently stored in the local Redistributor.
- The pINTID field corresponds to an unimplemented LPI.

GICR_INVLPIR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	RD_base	0x00A0	GICR_INVLPIR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **WO**.
- When IsAccessSecure() accesses to this register are **WO**.
- When !IsAccessSecure() accesses to this register are **WO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_IPRIORITYR<n>, Interrupt Priority Registers, n = 0 - 7

The GICR_IPRIORITYR<n> characteristics are:

Purpose

Holds the priority of the corresponding interrupt for each SGI and PPI supported by the GIC.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

A copy of these registers is provided for each Redistributor.

These registers are configured as follows:

- GICR_IPRIORITYR0-GICR_IPRIORITYR3 store the priority of SGIs.
- GICR_IPRIORITYR4-GICR_IPRIORITYR7 store the priority of PPIs.

Attributes

GICR_IPRIORITYR<n> is a 32-bit register.

Field descriptions

The GICR_IPRIORITYR<n> bit assignments are:



Priority_offset_3B, bits [31:24]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 3. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

Priority_offset_2B, bits [23:16]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 2. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

Priority_offset_1B, bits [15:8]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 1. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

Priority_offset_0B, bits [7:0]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 0. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

Accessing the GICR_IPRIORITYR<n>

These registers are used when affinity routing is enabled for the Security state of the interrupt. When affinity routing is not enabled the bits corresponding to the interrupt are RAZ/WI and GICD_IPRIORITYR<n> provides equivalent functionality.

These registers are used for SGIs and PPIs only. Equivalent functionality for SPIs is provided by GICD_IPRIORITYR<n>.

These registers are byte-accessible.

When GICD_CTLR.DS == 0:

- A field that corresponds to a Group 0 or Secure Group 1 interrupt is RAZ/WI to Non-secure accesses.
- A Non-secure access to a field that corresponds to a Non-secure Group 1 interrupt behaves as described in Software accesses of interrupt priority.

Note

Implementations must ensure that an interrupt that is pending at the time of the write uses either the old value or the new value and must ensure that the interrupt is neither lost nor handled more than one time. The effect of the change must be visible in finite time.

GICR_IPRIORITYR<n> can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0400 + 4n	GICR_IPRIORITYR<n>

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_IPRIORITYR<n>E, Interrupt Priority Registers (extended PPI range), n = 8 - 23

The GICR_IPRIORITYR<n>E characteristics are:

Purpose

Holds the priority of the corresponding interrupt for each extended PPI supported by the GIC.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_IPRIORITYR<n>E are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_IPRIORITYR<n>E is a 32-bit register.

Field descriptions

The GICR_IPRIORITYR<n>E bit assignments are:

31 30 29 28 27 26 25 24	23 22 21 20 19 18 17 16	15 14 13 12 11 10 9 8	7 6 5 4 3 2 1 0
Priority_offset_3B	Priority_offset_2B	Priority_offset_1B	Priority_offset_0B

Priority_offset_3B, bits [31:24]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 3. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

Priority_offset_2B, bits [23:16]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 2. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

Priority_offset_1B, bits [15:8]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 1. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

Priority_offset_0B, bits [7:0]

Interrupt priority value from an IMPLEMENTATION DEFINED range, at byte offset 0. Lower priority values correspond to greater priority of the interrupt.

This field resets to an architecturally UNKNOWN value.

For interrupt ID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICR_IPRIORITYR<n> number, n, is given by n = (m-1024) DIV 4.
- The offset of the required GICR_IPRIORITYR<n>E register is (`0x400` + (4*n)).
- The byte offset of the required Priority field in this register is m MOD 4, where:
  - Byte offset 0 refers to register bits [7:0].
  - Byte offset 1 refers to register bits [15:8].
  - Byte offset 2 refers to register bits [23:16].
  - Byte offset 3 refers to register bits [31:24].

Accessing the GICR_IPRIORITYR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICR_ISACTIVER<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0:

- A field that corresponds to a Group 0 or Secure Group 1 interrupt is RAZ/WI to Non-secure accesses.
- A Non-secure access to a field that corresponds to a Non-secure Group 1 interrupt behaves as described in Software accesses of interrupt priority.

Bits corresponding to unimplemented interrupts are RAZ/WI.

Note

Implementations must ensure that an interrupt that is pending at the time of the write uses either the old value or the new value and must ensure that the interrupt is neither lost nor handled more than once. The effect of the change must be visible in finite time.

GICR_IPRIORITYR<n>E can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	`0x0400` + 4n	GICR_IPRIORITYR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ISACTIVER0, Interrupt Set-Active Register 0

The GICR_ISACTIVER0 characteristics are:

Purpose

Activates the corresponding SGI or PPI. These registers are used when saving and restoring GIC state.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

A copy of this register is provided for each Redistributor.

Attributes

GICR_ISACTIVER0 is a 32-bit register.

Field descriptions

The GICR_ISACTIVER0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Set_active_bit<x>, bit [x], for x = 0 to 31																															

Set_active_bit<x>, bit [x], for x = 0 to 31

Adds the active state to interrupt number x. Reads and writes have the following behavior:

Set_active_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not active, and is not active and pending. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is active, or is active and pending. If written, activates the corresponding interrupt, if the interrupt is not already active. If the interrupt is already active, the write has no effect. After a write of 1 to this bit, a subsequent read of this bit returns 1.

This field resets to an architecturally UNKNOWN value.

Accessing the GICR_ISACTIVER0

When affinity routing is not enabled for the Security state of an interrupt in GICR_ISACTIVER0, the corresponding bit is RAZ/WI and equivalent functionality is provided by GICD_ISACTIVER<n> with n=0.

This register only applies to SGIs (bits [15:0]) and PPIs (bits [31:16]). For SPIs, this functionality is provided by GICD_ISACTIVER<n>.

When GICD_CTLR.DS == 0, bits corresponding to Secure SGIs and PPIs are RAZ/WI to Non-secure accesses.

GICR_ISACTIVER0 can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0300	GICR_ISACTIVER0

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ISACTIVER<n>E, Interrupt Set-Active Registers, n = 1 - 2

The GICR_ISACTIVER<n>E characteristics are:

Purpose

Adds the active state to the corresponding PPI.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_ISACTIVER<n>E are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_ISACTIVER<n>E is a 32-bit register.

Field descriptions

The GICR_ISACTIVER<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Set_active_bit<x>, bit [x], for x = 0 to 31																															

Set_active_bit<x>, bit [x], for x = 0 to 31

For the extended PPIs, adds the active state to interrupt number x. Reads and writes have the following behavior:

Set_active_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not active, and is not active and pending. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is active, or active and pending on this PE. If written, activates the corresponding interrupt, if the interrupt is not already active. If the interrupt is already active, the write has no effect. After a write of 1 to this bit, a subsequent read of this bit returns 1.

This field resets to an architecturally UNKNOWN value.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICR_ISACTIVER<n>E number, n, is given by n = (m-1024) DIV 32.
- The offset of the required GICR_ISACTIVER<n>E is (0x200 + (4*n)).
- The bit number of the required group modifier bit in this register is (m-1024) MOD 32.

Accessing the GICR_ISACTIVER<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICR_ISACTIVER<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure PPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICR_ISACTIVER<n>E can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0300 + 4n	GICR_ISACTIVER<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ISENABLER<n>E, Interrupt Set-Enable Registers, n = 1 - 2

The GICR_ISENABLER<n>E characteristics are:

Purpose

Enables forwarding of the corresponding PPI to the CPU interfaces.

Configuration

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_ISENABLER<n>E are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_ISENABLER<n>E is a 32-bit register.

Field descriptions

The GICR_ISENABLER<n>E bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Set_enable_bit<x>, bit [x], for x = 0 to 31																															

Set_enable_bit<x>, bit [x], for x = 0 to 31

For the extended PPI range, controls the forwarding of interrupt number x to the CPU interface. Reads and writes have the following behavior:

Set_enable_bit<x>	Meaning
0b0	If read, indicates that forwarding of the corresponding interrupt is disabled. If written, has no effect.
0b1	If read, indicates that forwarding of the corresponding interrupt is enabled. If written, enables forwarding of the corresponding interrupt. After a write of 1 to this bit, a subsequent read of this bit returns 1.

This field resets to 0.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICR_ISENABLER<n>E number, n, is given by n = (m-1024) DIV 32.
- The offset of the required GICR_ISENABLER<n>E is (0x100 + (4*n)).
- The bit number of the required group modifier bit in this register is (m-1024) MOD 32.

Accessing the GICR_ISENABLER<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICR_ISENABLER<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure PPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICR_ISENABLER<n>E can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0100 + 4n	GICR_ISENABLER<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ISPENDR0, Interrupt Set-Pending Register 0

The GICR_ISPENDR0 characteristics are:

Purpose

Adds the pending state to the corresponding SGI or PPI.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

A copy of this register is provided for each Redistributor.

Attributes

GICR_ISPENDR0 is a 32-bit register.

Field descriptions

The GICR_ISPENDR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Set_pending_bit<x>, bit [x], for x = 0 to 31																															

Set_pending_bit<x>, bit [x], for x = 0 to 31

For PPIs and SGIs, adds the pending state to interrupt number x. Reads and writes have the following behavior:

Set_pending_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not pending on this PE. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is pending, or active and pending on this PE. If written, changes the state of the corresponding interrupt from inactive to pending, or from active to active and pending. This has no effect in the following cases: • If the interrupt is already pending because of a write to GICR_ISPENDR0. • If the interrupt is already pending because the corresponding interrupt signal is asserted. In this case, the interrupt remains pending if the interrupt signal is deasserted.

This field resets to an architecturally UNKNOWN value.

Accessing the GICR_ISPENDR0

When affinity routing is not enabled for the Security state of an interrupt in GICR_ISPENDR0, the corresponding bit is RAZ/WI and equivalent functionality is provided by GICD_ISPENDR<n> with n=0.

This register only applies to SGIs (bits [15:0]) and PPIs (bits [31:16]). For SPIs, this functionality is provided by GICD_ISPENDR<n>.

When GICD_CTLR.DS == 0, bits corresponding to Secure SGIs and PPIs are RAZ/WI to Non-secure accesses.

GICR_ISPENDR0 can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0200	GICR_ISPENDR0

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_ISPENDR<n>E, Interrupt Set-Pending Registers, n = 1 - 2

The GICR_ISPENDR<n>E characteristics are:

Purpose

Adds the pending state to the corresponding PPI.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_ISPENDR<n>E are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_ISPENDR<n>E is a 32-bit register.

Field descriptions

The GICR_ISPENDR<n>E bit assignments are:



Set_pending_bit<x>, bit [x], for x = 0 to 31

For the extended PPIs, adds the pending state to interrupt number x. Reads and writes have the following behavior:

Set_pending_bit<x>	Meaning
0b0	If read, indicates that the corresponding interrupt is not pending on this PE. If written, has no effect.
0b1	If read, indicates that the corresponding interrupt is pending, or active and pending on this PE. If written, changes the state of the corresponding interrupt from inactive to pending, or from active to active and pending. This has no effect in the following cases: • If the interrupt is already pending because of a write to GICR_ISPENDR<n>E. • If the interrupt is already pending because the corresponding interrupt signal is asserted. In this case, the interrupt remains pending if the interrupt signal is deasserted.

This field resets to an architecturally UNKNOWN value.

For INTID m, when DIV and MOD are the integer division and modulo operations:

- The corresponding GICR_ISPENDR<n>E number, n, is given by n = (m-1024) DIV 32.
- The offset of the required GICR_ISPENDR<n>E is (`0x200` + (4*n)).
- The bit number of the required group modifier bit in this register is (m-1024) MOD 32.

Accessing the GICR_ISPENDR<n>E

When affinity routing is not enabled for the Security state of an interrupt in GICR_ISPENDR<n>E, the corresponding bit is RES0.

When GICD_CTLR.DS==0, bits corresponding to Secure PPIs are RAZ/WI to Non-secure accesses.

Bits corresponding to unimplemented interrupts are RAZ/WI.

GICR_ISPENDR<n>E can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	`0x0200` + 4n	GICR_ISPENDR<n>E

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_MPAMIDR, Report maximum PARTID and PMG Register

The GICR_MPAMIDR characteristics are:

Purpose

Reports the maximum support PARTID and PMG values.

Configuration

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_MPAMIDR are RES0.

A copy of this register is provided for each Redistributor.

When GICR_TYPER.MPAM==0, this register is RES0.

Attributes

GICR_MPAMIDR is a 32-bit register.

Field descriptions

The GICR_MPAMIDR bit assignments are:



Bits [31:24]

Reserved, RES0.

PMGmax, bits [23:16]

Maximum PMG value supported.

PARTIDmax, bits [15:0]

Maximum PARTID value supported.

Accessing the GICR_MPAMIDR

GICR_MPAMIDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	RD_base	0x0018	GICR_MPAMIDR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RO**.
- When IsAccessSecure() accesses to this register are **RO**.

- When !IsAccessSecure() accesses to this register are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_NSACR, Non-secure Access Control Register

The GICR_NSACR characteristics are:

Purpose

Enables Secure software to permit Non-secure software to create SGIs targeting the PE connected to this Redistributor by writing to ICC_SGI1R_EL1, ICC_ASGI1R_EL1 or ICC_SGI0R_EL1.

See Forwarding an SGI to a target PE for more information.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

For a description on when a write to ICC_SGI0R_EL1, ICC_SGI1R_EL1 or ICC_ASGI1R_EL1 is permitted to generate an interrupt see Use of control registers for SGI forwarding.

Attributes

GICR_NSACR is a 32-bit register.

Field descriptions

The GICR_NSACR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
NS_access<x>, bits [2x+1:2x], for x = 0 to 15																															

NS_access<x>, bits [2x+1:2x], for x = 0 to 15

Configures the level of Non-secure access permitted when the SGI is in Secure Group 0 or Secure Group 1, as defined from GICR_IGROUPR0 and GICR_IGRPMODR0. A field is provided for each SGI. The possible values of each 2-bit field are:

NS_access<x>	Meaning
0b00	Non-secure writes are not permitted to generate Secure Group 0 SGIs or Secure Group 1 SGIs.
0b01	Non-secure writes are permitted to generate a Secure Group 0 SGI.
0b10	As 0b01, but additionally Non-secure writes to are permitted to generate a Secure Group 1 SGI.
0b11	Reserved. If the field is programmed to the reserved value, then the hardware will treat the field as if it has been programmed to an IMPLEMENTATION DEFINED choice of the valid values. However, to maintain the principle that as the value increases additional accesses are permitted Arm strongly recommends that implementations treat this value as 0b10. It is IMPLEMENTATION DEFINED whether the value read back is the value programmed or the valid value chosen.

This field resets to an architecturally UNKNOWN value.

Accessing the GICR_NSACR

When GICD_CTLR.DS == 1, this register is RAZ/WI.

When GICD_CTLR.DS == 0, this register is Secure, and is RAZ/WI to Non-secure accesses.

This register is used when affinity routing is enabled. When affinity routing is not enabled for the Security state of the interrupt, GICD_NSACR<n> with n=0 provides equivalent functionality.

This register does not support PPIs.

GICR_NSACR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	SGI_base	0x0E00	GICR_NSACR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_PARTIDR, Set PARTID and PMG Register

The GICR_PARTIDR characteristics are:

Purpose

Sets the PARTID and PMG values used for memory accesses by the Redistributor.

Configuration

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GICR_PARTIDR are RES0.

A copy of this register is provided for each Redistributor.

When GICR_TYPER.MPAM==0, this register is RES0.

Attributes

GICR_PARTIDR is a 32-bit register.

Field descriptions

The GICR_PARTIDR bit assignments are:



Bits [31:24]

Reserved, RES0.

PMG, bits [23:16]

PMG value used when Redistributor accesses memory.

It is IMPLEMENTATION DEFINED whether bits not needed to represent PMG values in the range 0 to PMG_MAX are stateful or RES0.

PARTID, bits [15:0]

PARTID value used when Redistributor accesses memory.

It is IMPLEMENTATION DEFINED whether bits not needed to represent PARTID values in the range 0 to PARTID_MAX are stateful or RES0.

Accessing the GICR_PARTIDR

GICR_PARTIDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	RD_base	0x001C	GICR_PARTIDR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_PENDBASER, Redistributor LPI Pending Table Base Address Register

The GICR_PENDBASER characteristics are:

Purpose

Specifies the base address of the LPI Pending table, and the Shareability and Cacheability of accesses to the LPI Pending table.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

A copy of this register is provided for each Redistributor.

Attributes

GICR_PENDBASER is a 64-bit register.

Field descriptions

The GICR_PENDBASER bit assignments are:



Bit [63]

Reserved, RES0.

PTZ, bit [62]

Pending Table Zero. Indicates to the Redistributor whether the LPI Pending table is zero when GICR_CTLR.EnableLPIs == 1.

This field is WO, and reads as 0.

PTZ	Meaning
0b0	The LPI Pending table is not zero, and contains live data.
0b1	The LPI Pending table is zero. Software must ensure the LPI Pending table is zero before this value is written.

Bits [61:59]

Reserved, RES0.

OuterCache, bits [58:56]

Indicates the Outer Cacheability attributes of accesses to the LPI Pending table. The possible values of this field are:

OuterCache	Meaning
0b000	Memory type defined in InnerCache field. For Normal memory, Outer Cacheability is the same as Inner Cacheability.
0b001	Normal Outer Non-cacheable.
0b010	Normal Outer Cacheable Read-allocate, Write-through.
0b011	Normal Outer Cacheable Read-allocate, Write-back.
0b100	Normal Outer Cacheable Write-allocate, Write-through.
0b101	Normal Outer Cacheable Write-allocate, Write-back.
0b110	Normal Outer Cacheable Read-allocate, Write-allocate, Write-through.
0b111	Normal Outer Cacheable Read-allocate, Write-allocate, Write-back.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

This field resets to an architecturally UNKNOWN value.

Bits [55:52]

Reserved, RES0.

Physical_Address, bits [51:16]

Bits [51:16] of the physical address containing the LPI Pending table.

In implementations supporting fewer than 52 bits of physical address, unimplemented upper bits are RES0.

This field resets to an architecturally UNKNOWN value.

Bits [15:12]

Reserved, RES0.

Shareability, bits [11:10]

Indicates the Shareability attributes of accesses to the LPI Pending table. The possible values of this field are:

Shareability	Meaning
0b00	Non-shareable.
0b01	Inner Shareable.
0b10	Outer Shareable.
0b11	Reserved. Treated as 0b00.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

This field resets to an architecturally UNKNOWN value.

InnerCache, bits [9:7]

Indicates the Inner Cacheability attributes of accesses to the LPI Pending table. The possible values of this field are:

InnerCache	Meaning
0b000	Device-nGnRnE.
0b001	Normal Inner Non-cacheable.
0b010	Normal Inner Cacheable Read-allocate, Write-through.
0b011	Normal Inner Cacheable Read-allocate, Write-back.
0b100	Normal Inner Cacheable Write-allocate, Write-through.
0b101	Normal Inner Cacheable Write-allocate, Write-back.
0b110	Normal Inner Cacheable Read-allocate, Write-allocate, Write-through.
0b111	Normal Inner Cacheable Read-allocate, Write-allocate, Write-back.

This field resets to an architecturally UNKNOWN value.

Bits [6:0]

Reserved, RES0.

Accessing the GICR_PENDBASER

Having the GICR_PENDBASER OuterCache, Shareability or InnerCache fields programmed to different values on different Redistributors with GICR_CTLR.EnableLPIs == 1 in the system is UNPREDICTABLE.

Changing GICR_PENDBASER with GICR_CTLR.EnableLPIs == 1 is UNPREDICTABLE.

GICR_PENDBASER can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	RD_base	0x0078	GICR_PENDBASER

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_PROPBASER, Redistributor Properties Base Address Register

The GICR_PROPBASER characteristics are:

Purpose

Specifies the base address of the LPI Configuration table, and the Shareability and Cacheability of accesses to the LPI Configuration table.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

A copy of this register is provided for each Redistributor.

An implementation might make this register RO, for example to correspond to an LPI Configuration table in read-only memory.

Attributes

GICR_PROPBASER is a 64-bit register.

Field descriptions

The GICR_PROPBASER bit assignments are:



Bits [63:59]

Reserved, RES0.

OuterCache, bits [58:56]

Indicates the Outer Cacheability attributes of accesses to the LPI Configuration table. The possible values of this field are:

OuterCache	Meaning
0b000	Memory type defined in InnerCache field. For Normal memory, Outer Cacheability is the same as Inner Cacheability.
0b001	Normal Outer Non-cacheable.
0b010	Normal Outer Cacheable Read-allocate, Write-through.
0b011	Normal Outer Cacheable Read-allocate, Write-back.
0b100	Normal Outer Cacheable Write-allocate, Write-through.
0b101	Normal Outer Cacheable Write-allocate, Write-back.
0b110	Normal Outer Cacheable Read-allocate, Write-allocate, Write-through.
0b111	Normal Outer Cacheable Read-allocate, Write-allocate, Write-back.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

This field resets to an architecturally UNKNOWN value.

Bits [55:52]

Reserved, RES0.

Physical_Address, bits [51:12]

Bits [51:12] of the physical address containing the LPI Configuration table.

In implementations supporting fewer than 52 bits of physical address, unimplemented upper bits are RES0.

This field resets to an architecturally UNKNOWN value.

Shareability, bits [11:10]

Indicates the Shareability attributes of accesses to the LPI Configuration table. The possible values of this field are:

Shareability	Meaning
0b00	Non-shareable.
0b01	Inner Shareable.
0b10	Outer Shareable.
0b11	Reserved. Treated as 0b00.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

This field resets to an architecturally UNKNOWN value.

InnerCache, bits [9:7]

Indicates the Inner Cacheability attributes of accesses to the LPI Configuration table. The possible values of this field are:

InnerCache	Meaning
0b000	Device-nGnRnE.
0b001	Normal Inner Non-cacheable.
0b010	Normal Inner Cacheable Read-allocate, Write-through.
0b011	Normal Inner Cacheable Read-allocate, Write-back.
0b100	Normal Inner Cacheable Write-allocate, Write-through.
0b101	Normal Inner Cacheable Write-allocate, Write-back.
0b110	Normal Inner Cacheable Read-allocate, Write-allocate, Write-through.
0b111	Normal Inner Cacheable Read-allocate, Write-allocate, Write-back.

This field resets to an architecturally UNKNOWN value.

Bits [6:5]

Reserved, RES0.

IDbits, bits [4:0]

The number of bits of LPI INTID supported, minus one, by the LPI Configuration table starting at Physical_Address.

If the value of this field is larger than the value of GICD_TYPER.IDbits, the GICD_TYPER.IDbits value applies.

If the value of this field is less than 0b1101, indicating that the largest INTID is less than 8192 (the smallest LPI interrupt ID), the GIC will behave as if all physical LPIs are out of range.

This field resets to an architecturally UNKNOWN value.

Accessing the GICR_PROPBASER

It is IMPLEMENTATION DEFINED whether GICR_PROPBASER can be set to different values on different Redistributors. GICR_TYPER.CommonLPIAff identifies the Redistributors that must have GICR_PROPBASER set to the same values whenever GICR_CTLR.EnableLPIs == 1.

Setting different values in different copies of GICR_PROPBASER on Redistributors that are required to use a common LPI Configuration table when GICR_CTLR.EnableLPIs == 1 leads to UNPREDICTABLE behavior.

Other restrictions apply when a Redistributor caches information from GICR_PROPBASER. See LPI Configuration tables for more information.

GICR_PROPBASER can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	RD_base	0x0070	GICR_PROPBASER

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f211~~6134483bd14dc8e12a99e984cbfe3431cc1e9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_SETLPIR, Set LPI Pending Register

The GICR_SETLPIR characteristics are:

Purpose

Generates an LPI by setting the pending state of the specified LPI.

Configuration

This register is present only when GICv4.1 is implemented. Otherwise, direct accesses to GICR_SETLPIR are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_SETLPIR is a 64-bit register.

Field descriptions

The GICR_SETLPIR bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
RES0																															
pINTID																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:32]

Reserved, RES0.

pINTID, bits [31:0]

The INTID of the physical LPI to be generated.

Note

The size of this field is IMPLEMENTATION DEFINED, and is specified by the GICD_TYPER.IDbits field. Unimplemented bits are RES0.

Accessing the GICR_SETLPIR

When written with a 32-bit write the data is zero-extended to 64 bits.

This register is mandatory in an implementation that supports LPIs and does not include an ITS. The functionality is IMPLEMENTATION DEFINED in an implementation that does include an ITS.

Writes to this register have no effect if either:

- The pINTID field corresponds to an LPI that is already pending.
- The pINTID field corresponds to an unimplemented LPI.
- GICR_CTLR.EnableLPIs == 0.

GICR_SETLPIR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	RD_base	0x0040	GICR_SETLPIR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **WO**.
- When IsAccessSecure() accesses to this register are **WO**.
- When !IsAccessSecure() accesses to this register are **WO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_SYNCR, Redistributor Synchronize Register

The GICR_SYNCR characteristics are:

Purpose

Indicates completion of register~~physical~~ based invalidate~~Redistributor~~ operations.

Configuration

A copy of this register is provided for each Redistributor.

Attributes

GICR_SYNCR is a 32-bit register.

Field descriptions

The GICR_SYNCR bit assignments are:



Bits [31:1]

Reserved, RES0.

Busy, bit [0]

Indicates completion of invalidation~~any~~ ~~Redistributor~~ operations ~~as follows:~~

Busy	Meaning
0b0	No operations are in progress.
0b1	A write is in progress to one or more of the following registers: • GICR_INVLPIR~~GICR_CLRLPIR~~. • GICR_INVALLR~~GICR_INVLPIR~~. • ~~GICR_INVALLR~~GICv3, GICR_CLRLPIR.

This field tracks~~also indicates completion of any~~ operations initiated on~~by~~ the~~writes~~ same Redistributor.~~to~~GICR_PENDBASER ~~or~~ GICR_PROPBASER.

Accessing the GICR_SYNCR

When~~Optionally,~~ ~~when~~ this register is accessed, it is optional that an implementation might wait until all operations are complete before returning a value, in which case GICR_SYNCR.Busy is always 0.

This register is mandatory in an implementation that supports LPIs and does not include an ITS. The functionality is IMPLEMENTATION DEFINED in an implementation that does include an ITS.

GICR_SYNCR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	RD_base	0x00C0	GICR_SYNCR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RO**.
- When IsAccessSecure() accesses to this register are **RO**.
- When !IsAccessSecure() accesses to this register are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_TYPER, Redistributor Type Register

The GICR_TYPER characteristics are:

Purpose

Provides information about the configuration of this Redistributor.

Configuration

A copy of this register is provided for each Redistributor.

Attributes

GICR_TYPER is a 64-bit register.

Field descriptions

The GICR_TYPER bit assignments are:



Affinity_Value, bits [63:32]

The identity of the PE associated with this Redistributor.

Bits [63:56] provide Aff3, the Affinity level 3 value for the Redistributor.

Bits [55:48] provide Aff2, the Affinity level 2 value for the Redistributor.

Bits [47:40] provide Aff1, the Affinity level 1 value for the Redistributor.

Bits [39:32] provide Aff0, the Affinity level 0 value for the Redistributor.

PPInum, bits [31:27]

When GICv3.1~~GIC, >=3.1~~ is implemented:

The value derived from this field specifies the maximum PPI INTID that a GIC implementation can~~might~~ support. An implementation might not implement all PPIs up to this maximum.

PPInum	Meaning
0b00000	Maximum PPI INTID is 31.
0b00001	Maximum PPI INTID is 1087.
0b00010	Maximum PPI INTID is 1119.

All other values are reserved.

Otherwise:

Reserved, RES0.

VSGI, bitBit [26]

When GICv4.1 is implemented:

Indicates whether vSGIs are supported.

VSGI	Meaning
0b0	Direct injection of SGIs not supported.
0b1	Direct injection of SGIs supported.

Otherwise:

Reserved, RES0.

CommonLPIAff, bits [25:24]

The affinity level at which Redistributors share ana LPI Configuration table.

CommonLPIAff	Meaning
0b00	All Redistributors must share an LPI Configuration table.
0b01	All Redistributors with the same Aff3 value must share an LPI Configuration table.
0b10	All Redistributors with the same Aff3.Aff2 value must share an LPI Configuration table.
0b11	All Redistributors with the same Aff3.Aff2.Aff1 value must share an LPI Configuration table.

Processor_Number, bits [23:8]

A unique identifier for the PE. When GITS_TYPER.PTA == 0, an ITS uses this field to identify the interrupt target.

When affinity routing is disabled for a Security state, this field indicates which GICD_ITARGETSR<n> corresponds to this Redistributor.

RVPEID, bitBit [7]

When GICv4.1 is implemented:

Indicates how the resident vPE is specified.

RVPEID	Meaning
0b0	GICR_VPENDBASER records the address of the vPE's Virtual Pending Table.
0b1	GICR_VPENDBASER records vPEID.

Otherwise:

Reserved, RES0.

MPAM, bit [6]

When GICv3.1GIC, >=3.1 is implemented:

MPAM

MPAM	Meaning
0b0	MPAM not supported.
0b1	MPAM supported.

Otherwise:

Reserved, RES0.

DPGS, bit [5]

Sets support for GICR_CTLR.DPG* bits.

DPGS	Meaning
0b0	GICR_CTLR.DPG* bits are not supported.
0b1	GICR_CTLR.DPG* bits are supported.

Last, bit [4]

Indicates whether this Redistributor is the highest-numbered Redistributor in a series of contiguous Redistributor pages.

Last	Meaning
0b0	This Redistributor is not the highest-numbered Redistributor in a series of contiguous Redistributor pages.
0b1	This Redistributor is the highest-numbered Redistributor in a series of contiguous Redistributor pages.

DirectLPI, bit [3]

Indicates whether this Redistributor supports direct injection of LPIs.

DirectLPI	Meaning
0b0	This Redistributor does not support direct injection of LPIs. The GICR_SETLPIR, GICR_CLRLPIR, GICR_INVLPIR, GICR_INVALLR, and GICR_SYNCR registers are either not implemented, or have an IMPLEMENTATION DEFINED purpose.
0b1	This Redistributor supports direct injection of LPIs. The GICR_SETLPIR, GICR_CLRLPIR, GICR_INVLPIR, GICR_INVALLR, and GICR_SYNCR registers are implemented.

Dirty, bit [2]

Controls the functionality of GICR_VPENDBASER.Dirty.

Dirty	Meaning
0b0	GICR_VPENDBASER.Dirty is UNKNOWN when GICR_VPENDBASER.Valid == 1.
0b1	GICR_VPENDBASER.Dirty indicates when the Virtual Pending Table has been parsed when GICR_VPENDBASER.Valid is written from 0 to 1.

When GICR_TYPER.VLPIS == 0, this field is RES0.

Note

In GICv4.1 implementations this field is RES1.

VLPIS, bit [1]

Indicates whether the GIC implementation supports virtual LPIs and the direct injection of virtual LPIs.

VLPIS	Meaning
0b0	The implementation does not support virtual LPIs or the direct injection of virtual LPIs.
0b1	The implementation supports virtual LPIs and the direct injection of virtual LPIs.

Note

In GICv3 implementations this field is RES0.

PLPIS, bit [0]

Indicates whether the GIC implementation supports physical LPIs.

PLPIS	Meaning
0b0	The implementation does not support physical LPIs.
0b1	The implementation supports physical LPIs.

Accessing the GICR_TYPER

GICR_TYPER can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	RD_base	0x0008	GICR_TYPER

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RO**.
- When IsAccessSecure() accesses to this register are **RO**.
- When !IsAccessSecure() accesses to this register are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_VPENDBASER, Virtual Redistributor LPI Pending Table Base Address Register

The GICR_VPENDBASER characteristics are:

Purpose

Specifies the base address of the memory that holds the virtual LPI Pending table for the currently scheduled virtual machine.

Configuration

~~This register is provided only in GICv4 implementations.~~

Attributes

GICR_VPENDBASER is a 64-bit register.

Field descriptions

The GICR_VPENDBASER bit assignments are:

When GICv4 is implemented:



Valid, bit [63]

This bit controls whether the virtual LPI Pending table is valid:

Valid	Meaning
0b0	The virtual LPI Pending table is not valid. No vPE is scheduled.
0b1	The virtual LPI Pending table is valid. A vPE is scheduled.

Setting GICR_VPENDBASER.Valid == 1 when the associated CPU interface does not implement GICv4 is UNPREDICTABLE.

Note

Software can determine whether a PE supports GICv3 or GICv4 by reading ID_AA64PFR0_EL1.

Writing a new value to any bit of GICR_VPENDBASER, other than GICR_VPENDBASER.Valid, when GICR_VPENDBASER.Valid==1 is UNPREDICTABLE.

This field resets to 0.

IDAI, bit [62]

Implementation Defined Area Invalid. Indicates whether the IMPLEMENTATION DEFINED area in the virtual LPI Pending table is valid:

IDAI	Meaning
0b0	The IMPLEMENTATION DEFINED area is valid.
0b1	The IMPLEMENTATION DEFINED area is invalid and all pending interrupt information is held in the architecturally defined part of the virtual LPI Pending table.

For more information, see LPI Pending tables and Virtual LPI Configuration tables and virtual LPI Pending tables.

This field resets to an architecturally UNKNOWN value.

PendingLast, bit [61]

Indicates whether there are pending and enabled interrupts for the last scheduled vPE.

This value is set by the implementation when GICR_VPENDBASER.Valid has been written from 1 to 0 and is otherwise UNKNOWN.

PendingLast	Meaning
0b0	There are no pending and enabled interrupts for the last scheduled vPE.
0b1	There is at least one pending interrupt for the last scheduled vPE. It is IMPLEMENTATION DEFINED whether this bit is set when the only pending interrupts for the last scheduled vPE are not enabled. Arm deprecates setting PendingLast to 1 when the only pending interrupts for the last scheduled virtual machine are not enabled.

When the GICR_VPENDBASER.Valid bit is written from 0 to 1, this bit is RES1.

This field resets to 0.

Dirty, bit [60]

When GICR_VPENDBASER.Valid == 0b0:

~~This is field is read-only.~~ Indicates whether a de-scheduling operation is in progress.

This field is read-only.

Dirty	Meaning
0b0	No de-scheduling operation in process.
0b1	De-scheduling operation in process.

Writing 1 to GICR_VPENDBASER.Valid is UNPREDICTABLE while GICR_VPENDBASER.Dirty==1.

This field resets to 0.

When GICR_VPENDBASER.Valid == 0b1 and GICR_TYPER.Dirty == 0b1:

This field is read-only. Reports whether the Virtual Pending table has been parsed.

Dirty	Meaning
0b0	Parsing of the Virtual Pending Table has completed.
0b1	Parsing of the Virtual Pending Table has not completed.

Writing 1 to GICR_VPENDBASER.Valid is UNPREDICTABLE while GICR_VPENDBASER.Dirty == 1.

This field resets to 0.

Otherwise:

This field is read-only. This fields is UNKNOWN.

This field resets to 0.

Bit [59]

Reserved, RES0.

OuterCache, bits [58:56]

Indicates the Outer Cacheability attributes of accesses to virtual LPI Pending tables of vPEs targeting this Redistributor. The possible values of this field are:

OuterCache	Meaning
0b000	Memory type defined in InnerCache field. For Normal memory, Outer Cacheability is the same as Inner Cacheability.
0b001	Normal Outer Non-cacheable.
0b010	Normal Outer Cacheable Read-allocate, Write-through.
0b011	Normal Outer Cacheable Read-allocate, Write-back.
0b100	Normal Outer Cacheable Write-allocate, Write-through.
0b101	Normal Outer Cacheable Write-allocate, Write-back.
0b110	Normal Outer Cacheable Read-allocate, Write-allocate, Write-through.
0b111	Normal Outer Cacheable Read-allocate, Write-allocate, Write-back.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

The Cacheability, Outer Cacheability and Shareability fields are used for accesses to the virtual LPI Pending table of resident and non-resident vPEs.

If the OuterCacheabilty attribute of the virtual LPI Pending tables that are associated with vPEs targeting the same Redistributor are different, behavior is UNPREDICTABLE.

This field resets to an architecturally UNKNOWN value.

Bits [55:52]

Reserved, RES0.

Physical_Address, bits [51:16]

Bits [51:16] of the physical address containing the virtual LPI Pending table.

In implementations supporting fewer than 52 bits of physical address, unimplemented upper bits are RES0.

This field resets to an architecturally UNKNOWN value.

Bits [15:12]

Reserved, RES0.

Shareability, bits [11:10]

Indicates the Shareability attributes of accesses to the virtual LPI Pending table. The possible values of this field are:

Shareability	Meaning
0b00	Non-shareable.
0b01	Inner Shareable.
0b10	Outer Shareable.
0b11	Reserved. Treated as 0b00.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

The Cacheability, Outer Cacheability and Shareability fields are used for accesses to the virtual LPI Pending table of resident and non-resident vPEs.

If the Shareability attribute of the virtual LPI Pending tables that are associated with vPEs targeting the same Redistributor are different, behavior is UNPREDICTABLE.

This field resets to an architecturally UNKNOWN value.

InnerCache, bits [9:7]

Indicates the Inner Cacheability attributes of accesses to the virtual LPI Pending table. The possible values of this field are:

InnerCache	Meaning
0b000	Device-nGnRnE.
0b001	Normal Inner Non-cacheable.
0b010	Normal Inner Cacheable Read-allocate, Write-through.
0b011	Normal Inner Cacheable Read-allocate, Write-back.
0b100	Normal Inner Cacheable Write-allocate, Write-through.
0b101	Normal Inner Cacheable Write-allocate, Write-back.
0b110	Normal Inner Cacheable Read-allocate, Write-allocate, Write-through.
0b111	Normal Inner Cacheable Read-allocate, Write-allocate, Write-back.

The Cacheability, Outer Cacheability and Shareability fields are used for accesses to the virtual LPI Pending table of resident and non-resident vPEs.

If the InnerCacheabilty attribute of the virtual LPI Pending tables that are associated with vPEs targeting the same Redistributor are different, behavior is UNPREDICTABLE.

This field resets to an architecturally UNKNOWN value.

Bits [6:0]

Reserved, RES0.

When GICv4.1 is implemented:



Valid, bit [63]

This bit controls whether a vPE is scheduled:

Valid	Meaning
0b0	The virtual LPI Pending table is not valid. No vPE is scheduled.
0b1	The virtual LPI Pending table is valid. A vPE is scheduled.

Setting GICR_VPENDBASER.Valid == 1 when the associated CPU interface does not implement GICv4 is UNPREDICTABLE.

Note

Software can determine whether a PE supports GICv3 or GICv4 by reading ID_AA64PFR0_EL1.

Writing a new value to any bit of GICR_VPENDBASER, other than GICR_VPENDBASER.Valid, when GICR_VPENDBASER.Valid==1 is UNPREDICTABLE.

Setting GICR_VPENDBASER.Valid to 1 is UNPREDICTABLE if GICR_VPROPBASER.Valid == 0.

This field resets to 0.

Doorbell, bit [62]

When GICR_VPENDBASER.Valid is written from 1 to 0, this bit controls whether a default doorbell interrupt is requested for the descheduled vPE.

Doorbell	Meaning
0b0	Default doorbell requested.
0b1	No default doorbell requested.

When GICR_VPENDBASER.Valid is written from 1 to 0, if there are outstanding enabled pending interrupts then this bit is treated as 0.

When GICR_VPENDBASER.Valid is written from 1 to 0, if GICR_VPENDBASER.PendingLast is written as 1 then this bit is treated as 0.

When GICR_VPENDBASER.Valid == 1, reads return an UNKNOWN value.

This field resets to an UNKNOWN value.

PendingLast, bit [61]

Indicates whether there are pending and enabled interrupts for the last scheduled vPE.

This value is set by the implementation when GICR_VPENDBASER.Valid is written from 1 to 0 and is otherwise UNKNOWN.

PendingLast	Meaning
0b0	There are no pending and enabled interrupts for the last scheduled vPE.
0b1	There is at least one pending and enabled interrupt for the last scheduled vPE.

When the GICR_VPENDBASER.Valid bit is written from 0 to 1, this bit is RES1.

When GICR_VPENDBASER.Valid is written from 1 to 0, if GICR_VPENDBASER.PendingLast is written as 1, then this bit is set to an UNKNOWN value.

This field resets to an UNKNOWN value.

Dirty, bit [60]

When GICR_VPENDBASER.Valid == 0b0:

Read-only. Indicates whether a de-scheduling operation is in progress.

Dirty	Meaning
0b0	No de-scheduling operation in progess.
0b1	De-scheduling operation in progess.

Writing 1 to GICR_VPENDBASER.Valid is UNPREDICTABLE while GICR_VPENDBASER.Dirty == 1.

This field resets to 0.

Otherwise:

Read-only. Reports whether the Virtual Pending table has been parsed.

Dirty	Meaning
0b0	Parsing of the Virtual Pending Table is complete.
0b1	Parsing of the Virtual Pending Table has not completed.

Writing 1 to GICR_VPENDBASER.Valid is UNPREDICTABLE while GICR_VPENDBASER.Dirty == 1.

This field resets to 0.

VGrp0En, bit [59]

Enable virtual Group 0 interrupts.

VGrp0En	Meaning
0b0	Forwarding of virtual Group 0 interrupts disabled.
0b1	Forwarding of virtual Group 0 interrupts enabled.

This field resets to an UNKNOWN value.

VGrp1En, bit [58]

Enable virtual Group 1 interrupts.

VGrp1En	Meaning
0b0	Forwarding of virtual Group 1 interrupts disabled.
0b1	Forwarding of virtual Group 1 interrupts enabled.

This field resets to an UNKNOWN value.

Bits [57:16]

Reserved, RES0.

vPEID, bits [15:0]

When GICR_VPENDBASER.Valid == 1, ID of scheduled vPE.

When GICR_VPENDBASER.Valid == 1, if GICR_VPENDBASER.vPEID is set to a value greater than the configured vPEID width, the behavior of this field is CONSTRAINED UNPREDICTABLE:

- GICR_VPENDBASER.vPEID is treated as having an UNKNOWN valid value for all purposes other than a direct read of the register.
- GICR_VPENDBASER.Valid is treated as being set to 0 for all purposes other than a direct read of the register.

The size of this field is IMPLEMENTATION DEFINED, and is specified by the GICD_TYPER2.VIL and GICD_TYPER2.VID fields, unimplemented bits are RES0.

Accessing the GICR_VPENDBASER

The effect of a write to this register is not guaranteed to be visible throughout the affinity hierarchy, as indicated by GICR_CTLR.RWP == 0.

GICR_VPENDBASER can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	VLPI_base	0x0078	GICR_VPENDBASER

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICR_VPROPBASER, Virtual Redistributor Properties Base Address Register

The GICR_VPROPBASER characteristics are:

Purpose

Specifies the base address of the memory that holds the virtual LPI Configuration table for the currently scheduled virtual machine.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is provided in GICv4 implementations only.

Attributes

GICR_VPROPBASER is a 64-bit register.

Field descriptions

The GICR_VPROPBASER bit assignments are:

When GICv4 is implemented:



Bits [63:59]

Reserved, RES0.

OuterCache, bits [58:56]

Indicates the Outer Cacheability attributes of accesses to the LPI Configuration table. The possible values of this field are:

OuterCache	Meaning
0b000	Memory type defined in InnerCache field. For Normal memory, Outer Cacheability is the same as Inner Cacheability.
0b001	Normal Outer Non-cacheable.
0b010	Normal Outer Cacheable Read-allocate, Write-through.
0b011	Normal Outer Cacheable Read-allocate, Write-back.
0b100	Normal Outer Cacheable Write-allocate, Write-through.
0b101	Normal Outer Cacheable Write-allocate, Write-back.
0b110	Normal Outer Cacheable Read-allocate, Write-allocate, Write-through.
0b111	Normal Outer Cacheable Read-allocate, Write-allocate, Write-back.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

This field resets to an architecturally UNKNOWN value.

Bits [55:52]

Reserved, RES0.

Physical_Address, bits [51:12]

Bits [51:12] of the physical address containing the virtual LPI Configuration table.

In implementations supporting fewer than 52 bits of physical address, unimplemented upper bits are RES0.

This field resets to an architecturally UNKNOWN value.

Shareability, bits [11:10]

Indicates the Shareability attributes of accesses to the LPI Configuration table. The possible values of this field are:

Shareability	Meaning
0b00	Non-shareable.
0b01	Inner Shareable.
0b10	Outer Shareable.
0b11	Reserved. Treated as 0b00.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

This field resets to an architecturally UNKNOWN value.

InnerCache, bits [9:7]

Indicates the Inner Cacheability attributes of accesses to the LPI Configuration table. The possible values of this field are:

InnerCache	Meaning
0b000	Device-nGnRnE.
0b001	Normal Inner Non-cacheable.
0b010	Normal Inner Cacheable Read-allocate, Write-through.
0b011	Normal Inner Cacheable Read-allocate, Write-back.
0b100	Normal Inner Cacheable Write-allocate, Write-through.
0b101	Normal Inner Cacheable Write-allocate, Write-back.
0b110	Normal Inner Cacheable Read-allocate, Write-allocate, Write-through.
0b111	Normal Inner Cacheable Read-allocate, Write-allocate, Write-back.

This field resets to an architecturally UNKNOWN value.

Bits [6:5]

Reserved, RES0.

IDbits, bits [4:0]

The number of bits of virtual LPI INTID supported, minus one.

If the value of this field is less than 0b1101, indicating that the largest INTID is less than 8192 (the smallest LPI interrupt ID), the GIC will behave as if all virtual LPIs are out of range.

This field resets to an architecturally UNKNOWN value.

When GICv4.1 is implemented:



Valid, bit [63]

This bit controls whether the vPE Configuration Table is valid:

Valid	Meaning
0b0	The vPE Configuration table is not valid.
0b1	The vPE Configuration table is valid.

TBC

This field resets to 0.

Bit [62]

Reserved, RES0.

Entry_Size, bits [61:59]

Specifies the number of bytes per table entry, minus one.

This bit is read-only.

OuterCache, bits [58:56]

Indicates the Outer Cacheability attributes of accesses to the table. The possible values of this field are:

OuterCache	Meaning
0b000	Memory type defined in InnerCache field. For Normal memory, Outer Cacheability is the same as Inner Cacheability.
0b001	Normal Outer Non-cacheable.
0b010	Normal Outer Cacheable Read-allocate, Write-through.
0b011	Normal Outer Cacheable Read-allocate, Write-back.
0b100	Normal Outer Cacheable Write-allocate, Write-through.
0b101	Normal Outer Cacheable Write-allocate, Write-back.
0b110	Normal Outer Cacheable Read-allocate, Write-allocate, Write-through.
0b111	Normal Outer Cacheable Read-allocate, Write-allocate, Write-back.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

This field resets to an UNKNOWN value.

Indirect, bit [55]

This field indicates whether GICR_VPROPBASER specifies a single, flat table or a two-level table where the first level contains a list of descriptors.

Indirect	Meaning
0b0	Single Level. The Size field indicates the number of pages used to store data associated with each table entry.
0b1	Two Level. The Size field indicates the number of pages that contain an array of 64-bit descriptors to pages that are used to store the data associated with each table entry. A little endian memory order model is used.

This field is RES0 for GIC implementations that only support flat tables.

This field resets to an UNKNOWN value.

Page_Size, bits [54:53]

The following values indicate the size of page that the translation table uses:

Page_Size	Meaning
0b00	4KB.
0b01	16KB.
0b10	64KB.
0b11	Reserved. Treated as 0b10.

Note

If the GIC implementation supports only a single, fixed page size, this field might be RO.

This field resets to an UNKNOWN value.

Z, bit [52]

When GICR_VPROPBASER.Valid is written from 0 to 1, GICR_VPROPBASER.Z indicates whether the vPE Configuration table is known to contain all zeros.

Z	Meaning
0b0	The vPE Configutation table is not zero, and contains live data.
0b1	The vPE Configuration table is zero.

Setting GICR_VPROPBASER.Z to 0 causes the IRI to reload configuration from memory

When GICR_VPROPBASER.Valid is written from 0 to 1, if GICR_VPROPBASER.Z==1 behavior is UNPREDICTABLE if the allocated memory does not contain all zeros.

This field is WO, and reads as 0.

Physical_Address, bits [51:12]

Bits [51:12] of the physical address containing the LPI Configuration table.

In implementations supporting fewer than 52 bits of physical address, unimplemented upper bits are RES0.

This field resets to an UNKNOWN value.

Shareability, bits [11:10]

Indicates the Shareability attributes of accesses to the LPI Configuration table. The possible values of this field are:

Shareability	Meaning
0b00	Non-shareable.
0b01	Inner Shareable.
0b10	Outer Shareable.
0b11	Reserved. Treated as 0b00.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

This field resets to an UNKNOWN value.

InnerCache, bits [9:7]

Indicates the Inner Cacheability attributes of accesses to the LPI Configuration table. The possible values of this field are:

InnerCache	Meaning
0b000	Device-nGnRnE.
0b001	Normal Inner Non-cacheable.
0b010	Normal Inner Cacheable Read-allocate, Write-through.
0b011	Normal Inner Cacheable Read-allocate, Write-back.
0b100	Normal Inner Cacheable Write-allocate, Write-through.
0b101	Normal Inner Cacheable Write-allocate, Write-back.
0b110	Normal Inner Cacheable Read-allocate, Write-allocate, Write-through.
0b111	Normal Inner Cacheable Read-allocate, Write-allocate, Write-back.

This field resets to an UNKNOWN value.

Size, bits [6:0]

The number of pages of physical memory allocated to the table, minus one.

GICR_VPROPBASER.Page_Size specifies the size of each page.

This field resets to an UNKNOWN value.

Accessing the GICR_VPROPBASER

GICR_VPROPBASER can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	VLPI_base	0x0070	GICR_VPROPBASER

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f211~~6134483bd14dc8e12a99e984cbfe3431cc1e9707~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

no old file htmldiff from- (new)

GICR_VSGIPENDR, Redistributor virtual SGI pending state register

The GICR_VSGIPENDR characteristics are:

Purpose

Requests the pending state of virtual SGIs for a specified vPE.

Configuration

This register is present only when GICv4.1 is implemented. Otherwise, direct accesses to GICR_VSGIPENDR are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_VSGIPENDR is a 32-bit register.

Field descriptions

The GICR_VSGIPENDR bit assignments are:



Busy, bit [31]

ID of target vPEID

Busy	Meaning
0b0	Query of virtual SGI state not in progress.
0b1	Query of virtual SGI state in progress.

Bits [30:16]

Reserved, RES0.

Pending, bits [15:0]

Pending state of virtual SGIs for requested vPEID.

This field is UNKNOWN when GICR_VSGIPENDR.Busy == 1

Accessing the GICR_VSGIPENDR

64-bit access only.

GICR_VSGIPENDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance

GIC Redistributor	VLPI_base	0x0088	GICR_VSGIPENDR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RO**.
- When IsAccessSecure() accesses to this register are **RO**.
- When !IsAccessSecure() accesses to this register are **RO**.

13/12/2019 15:13; 391b5248b29fb2f001ef74792eaacbd6fc72f211

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

no old file htmldiff from- (new)

no old file htmldiff from- (new)

GICR_VSGIR, Redistributor virtual SGI pending state request register

The GICR_VSGIR characteristics are:

Purpose

Requests the pending state of virtual SGIs for a specified vPE.

Configuration

This register is present only when GICv4.1 is implemented. Otherwise, direct accesses to GICR_VSGIR are RES0.

A copy of this register is provided for each Redistributor.

Attributes

GICR_VSGIR is a 32-bit register.

Field descriptions

The GICR_VSGIR bit assignments are:



Bits [31:16]

Reserved, RES0.

vPEID, bits [15:0]

ID of target vPE

Writing this field is CONSTRAINED UNPREDICTABLE when GICR_VSGIPENDR.Busy == 1, with either the write ignored or a new query started.

Writing a value greater than the configured vPEID width behaviur is CONSTRAINED UNPREDICTABLE:

- GICR_VPENDBASER.vPEID is treated as having an UNKNOWN valid value for all purposes other than a direct read of the register.
- GICR_VPENDBASER.Valid is treated as being set to 0 for all purposes other than a direct read of the register.

The size of this field is IMPLEMENTATION DEFINED, and is specified by the GICD_TYPER2.VIL and GICD_TYPER2.VID fields. Unimplemented bits are RES0.

Accessing the GICR_VSGIR

64-bit access only.

GICR_VSGIR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
GIC Redistributor	VLPI_base	0x0080	GICR_VSGIR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **WO**.
- When IsAccessSecure() accesses to this register are **WO**.
- When !IsAccessSecure() accesses to this register are **WO**.

13/12/2019 15:13; 391b5248b29fb2f001ef74792eaacbd6fc72f211

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

no old file htmldiff from- (new)

(old) htmldiff from- (new)

GICV_BPR, Virtual Machine Binary Point Register

The GICV_BPR characteristics are:

Purpose

Defines the point at which the priority value fields split into two parts, the group priority field and the subpriority field. The group priority field determines Group 0 interrupt preemption.

This register corresponds to GICC_BPR in the physical CPU interface.

Note

GICH_LR<n>.Group determines whether a virtual interrupt is Group 0 or Group 1.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is available when the GIC implementation supports interrupt virtualization.

When GICV_CTLR.CBPR == 1, this register determines interrupt preemption for both Group 0 and Group 1 interrupts.

Attributes

GICV_BPR is a 32-bit register.

Field descriptions

The GICV_BPR bit assignments are:



Bits [31:3]

Reserved, RES0.

Binary_Point, bits [2:0]

Controls how the 8-bit interrupt priority field is split into a group priority field, that determines interrupt preemption, and a subpriority field.

For information about how this field determines the interrupt priority bits assigned to the group priority field, see Priority grouping for Group 0 interrupts, or Group 1 interrupts when CBPR==1

This field resets to an architecturally UNKNOWN value.

The Binary_Point field of this register is aliased to GICH_VMCR.VBPR0.

Accessing the GICV_BPR

This register is used only when System register access is not enabled. When System register access is enabled:

- For AArch32 implementations, ICC_BPR0 provides equivalent functionality.
- For AArch64 implementations, ICC_BPR0_EL1 provides equivalent functionality.

GICV_BPR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Virtual CPU interface	0x0008	GICV_BPR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICV_CTLR, Virtual Machine Control Register

The GICV_CTLR characteristics are:

Purpose

Controls the behavior of virtual interrupts.

This register corresponds to the physical CPU interface register GICC_CTLR.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is available when a GIC implementation supports interrupt virtualization.

Attributes

GICV_CTLR is a 32-bit register.

Field descriptions

The GICV_CTLR bit assignments are:



Bits [31:10]

Reserved, RES0.

EOImode, bit [9]

Controls the behavior associated with the GICV_EOIR, GICV_AEOIR, and GICV_DIR registers:

EOImode	Meaning
0b0	Writes to GICV_EOIR and GICV_AEOIR perform priority drop and deactivate interrupt operations simultaneously. Behavior on a write to GICV_DIR is unpredictable. When it has completed processing the interrupt, the virtual machine writes to GICV_EOIR or GICV_AEOIR to deactivate the interrupt. The write updates the List registers and causes the virtual CPU interface to signal the interrupt completion to the physical Distributor.
0b1	Writes to GICV_EOIR and GICV_AEOIR perform priority drop operation only. Writes to GICV_DIR perform deactivate interrupt operation only. When it has completed processing the interrupt, the virtual machine writes to GICV_DIR to deactivate the interrupt. The write updates the List registers and causes the virtual CPU interface to signal the interrupt completion to the Distributor.

This field resets to an architecturally UNKNOWN value.

Bits [8:5]

Reserved, RES0.

CBPR, bit [4]

Controls whether GICV_BPR affects both Group 0 and Group 1 interrupts:

CBPR	Meaning
0b0	GICV_BPR affects Group 0 virtual interrupts only. GICV_ABPR affects Group 1 virtual interrupts only.
0b1	GICV_BPR affects both Group 0 and Group 1 virtual interrupts.

See Priority grouping for more information.

This field resets to an architecturally UNKNOWN value.

FIQEn, bit [3]

FIQ Enable. Controls whether Group 0 virtual interrupts are presented as virtual FIQs:

FIQEn	Meaning
0b0	Group 0 virtual interrupts are presented as virtual IRQs.
0b1	Group 0 virtual interrupts are presented as virtual FIQs.

This field resets to an architecturally UNKNOWN value.

AckCtl, bit [2]

Arm deprecates use of this bit. Arm strongly recommends that software is written to operate with this bit always cleared to 0.

Acknowledge control. When the highest priority interrupt is Group 1, determines whether GICV_IAR causes the CPU interface to acknowledge the interrupt or returns the spurious identifier 1022, and whether GICV_HPPIR returns the interrupt ID or the special identifier 1022.

AckCtl	Meaning
0b0	If the highest priority pending interrupt is Group 1, a read of GICV_IAR or GICV_HPPIR returns an interrupt ID of 1022.
0b1	If the highest priority pending interrupt is Group 1, a read of GICV_IAR or GICV_HPPIR returns the interrupt ID of the corresponding interrupt.

This field resets to an architecturally UNKNOWN value.

EnableGrp1, bit [1]

Enables the signaling of Group 1 virtual interrupts by the virtual CPU interface to the virtual machine:

EnableGrp1	Meaning
0b0	Signaling of Group 1 interrupts is disabled.
0b1	Signaling of Group 1 interrupts is enabled.

This field resets to an architecturally UNKNOWN value.

EnableGrp0, bit [0]

Enables the signaling of Group 0 virtual interrupts by the virtual CPU interface to the virtual machine:

EnableGrp0	Meaning
0b0	Signaling of Group 0 interrupts is disabled.
0b1	Signaling of Group 0 interrupts is enabled.

This field resets to an architecturally UNKNOWN value.

Accessing the GICV_CTLR

This register is used only when System register access is not enabled. When System register access is enabled:

- For AArch32 implementations, ICC_CTLR provides equivalent functionality.
- For AArch64 implementations, ICC_CTLR_EL1 provides equivalent functionality.

GICV_CTLR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Virtual CPU interface	0x0000	GICV_CTLR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICV_DIR, Virtual Machine Deactivate Interrupt Register

The GICV_DIR characteristics are:

Purpose

Deactivates a specified virtual interrupt in the GICH_LR<n> List registers.

This register corresponds to the physical CPU interface register GICC_DIR.

Configuration

This register is available when the GIC implementation supports interrupt virtualization.

Attributes

GICV_DIR is a 32-bit register.

Field descriptions

The GICV_DIR bit assignments are:



Bits [31:25]

Reserved, RES0.

INTID, bits [24:0]

The INTID of the signaled interrupt.

Note

INTIDs 1020-1023 are reserved and convey additional information such as spurious interrupts.

When affinity routing is not enabled:

- Bits [23:13] are RES0.
- For SGIs, bits [12:10] identify the CPU interface corresponding to the source PE. For all other interrupts these bits are RES0.

When the virtual machine writes to this register, the specified interrupt in the List registers is changed from active to inactive, or from active and pending to pending. If the specified interrupt is present in the List registers but is not in either the active or active and pending states, the effect is UNPREDICTABLE. If the specified interrupt is not present in the List registers, GICH_HCR.EOICount~~EOIcount~~ is incremented, potentially generating a maintenance interrupt.

Note

If the specified interrupt is not present in the List registers, the virtual machine cannot recover the INTID. Therefore, the hypervisor must ensure

---

that, when GICV_CTLR.EOImode == 1, no more than one active interrupt is transferred from the List registers into a software list. If more than one active interrupt that is not stored in the List registers exists, the hypervisor must handle accesses to GICV_DIR in software, typically by trapping these accesses.

If the corresponding GICH_LR<n>.HW == 1, indicating a hardware interrupt, then a deactivate request is sent to the physical Distributor, identifying the physical INTID from the corresponding field in the List register. This effect is identical to a Non-secure write to GICC_DIR from the PE having that physical INTID. This means that if the corresponding physical interrupt is marked as Group 0, the request is ignored.

Note

Interrupt deactivation using this register is based on the provided INTID, with no requirement to deactivate interrupts in any particular order. A single register is therefore used to deactivate both Group 0 and Group 1 interrupts.

Accessing the GICV_DIR

This register is used only when System register access is not enabled. When System register access is enabled:

- For AArch32 implementations, ICC_DIR provides equivalent functionality.
- For AArch64 implementations, ICC_DIR_EL1 provides equivalent functionality.

Writes to this register are valid only when GICV_CTLR.EOImode == 1. Writes to this register are otherwise UNPREDICTABLE.

When affinity routing is enabled, it is a programming error to use memory-mapped registers to access the GIC.

GICV_DIR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Virtual CPU interface	0x1000	GICV_DIR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **WO**.
- When IsAccessSecure() accesses to this register are **WO**.
- When !IsAccessSecure() accesses to this register are **WO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GICV_PMR, Virtual Machine Priority Mask Register

The GICV_PMR characteristics are:

Purpose

This register provides a virtual interrupt priority filter. Only virtual interrupts with a higher priority than the value in this register are signaled to the PE.

Note

Higher interrupt priority corresponds to a lower value of the Priority field.

This register corresponds to the physical CPU interface register GICC_PMR.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

This register is available when the GIC implementation supports interrupt virtualization.

The Priority field of this register is aliased to GICH_VMCR.VMPR, to enable state to be switched easily between virtual machines during context-switching.

Attributes

GICV_PMR is a 32-bit register.

Field descriptions

The GICV_PMR bit assignments are:



Bits [31:8]

Reserved, RES0.

Priority, bits [7:0]

The priority mask level for the virtual CPU interface. If the priority of the interrupt is higher than the value indicated by this field, the interface signals the interrupt to the PE.

If the GIC implementation supports fewer than 256 priority levels some bits might be RAZ/WI, as follows:

- For 128 supported levels, bit [0] = `0b0`.
- For 64 supported levels, bits [1:0] = `0b00`.
- For 32 supported levels, bits [2:0] = `0b000`.
- For 16 supported levels, bits [3:0] = `0b0000`.

See Interrupt prioritization, section 4.8 of the GICv3 Architecture Specification for more information.

This field resets to an architecturally UNKNOWN value.

Accessing the GICV_PMR

This register is used only when System register access is not enabled. When System register access is enabled:

- For AArch32 implementations, ICC_PMR provides equivalent functionality.
- For AArch64 implementations, ICC_PMR_EL1 provides equivalent functionality.

GICV_PMR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC Virtual CPU interface	0x0004	GICV_PMR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GITS_BASER<n>, ITS Translation Table Descriptors, n = 0 - 7

The GITS_BASER<n> characteristics are:

Purpose

Specifies the base address and size of the ITS translation tables.

Configuration

A copy of this register is provided for each ITS translation table.

Bits [63:32] and bits [31:0] are accessible independently.

A maximum of 8 GITS_BASER<n> registers can be provided. Unimplemented registers are RES0.

When GITS_CTLR.Enabled == 1 or GITS_CTLR.Quiescent == 0, writing this register is UNPREDICTABLE.

Attributes

GITS_BASER<n> is a 64-bit register.

Field descriptions

The GITS_BASER<n> bit assignments are:



Valid, bit [63]

Indicates whether software has allocated memory for the translation table:

Valid	Meaning
0b0	No memory is allocated for the translation table. The ITS discards any writes to the interrupt translation page when either: • GITS_BASER<n>.Type specifies any valid table entry type other than interrupt collections, that is, any value other than 0b100. • GITS_BASER<n>.Type specifies an interrupt collection and GITS_TYPER.HCC == 0.
0b1	Memory is allocated to the translation table.

This field resets to 0.

Indirect, bit [62]

This field indicates whether an implemented register specifies a single, flat table or a two-level table where the first level contains a list of descriptors.

Indirect	Meaning
0b0	Single Level. The Size field indicates the number of pages used by the ITS to store data associated with each table entry.
0b1	Two Level. The Size field indicates the number of pages which contain an array of 64-bit descriptors to pages that are used to store the data associated with each table entry. A little endian memory order model is used.

See The ITS tables for more information.

This field is RAZ/WI for GIC implementations that only support flat tables. If the maximum width of the scaling factor that is identified by GITS_BASER<n>.Type and the smallest page size that is supported result in a single level table that requires multiple pages, then implementing this bit as RAZ/WI is DEPRECATED.

This field resets to an architecturally UNKNOWN value.

InnerCache, bits [61:59]

Indicates the Inner Cacheability attributes of accesses to the table. The possible values of this field are:

InnerCache	Meaning
0b000	Device-nGnRnE.
0b001	Normal Inner Non-cacheable.
0b010	Normal Inner Cacheable Read-allocate, Write-through.
0b011	Normal Inner Cacheable Read-allocate, Write-back.
0b100	Normal Inner Cacheable Write-allocate, Write-through.
0b101	Normal Inner Cacheable Write-allocate, Write-back.
0b110	Normal Inner Cacheable Read-allocate, Write-allocate, Write-through.
0b111	Normal Inner Cacheable Read-allocate, Write-allocate, Write-back.

This field resets to an architecturally UNKNOWN value.

Type, bits [58:56]

Read only. Specifies the type of entity that requires entries in the corresponding translation table. The possible values of the field are:

Type	Meaning
0b000	Unimplemented. This register does not correspond to a translation table.
0b001	Devices. This register corresponds to a translation table that scales with the width of the DeviceID. Only a single GITS_BASER<n> register reports this type.
0b010	vPEs. GICv4 only. This register corresponds to a translation table that scales with the number of vPEs in the system. The translation table requires (ENTRY_SIZE * N) bytes of memory, where N is the number of vPEs in the system. Only a single GITS_BASER<n> register reports this type.
0b100	Interrupt collections. This register corresponds to a translation table that scales with the number of interrupt collections in the system. The translation table requires (ENTRY_SIZE * N) bytes of memory, where N is the number of interrupt collections. Not more than one GITS_BASER<n> register will report this type.

Other values are reserved.

Note

The minimum number of entries that an ITS must support is N+1, where N is the number of physical PEs in the system.

Arm recommends that the GITS_BASER<n> registers are allocated as follows:

For GICv4.1, the registers are allocated as follows:

- GITS_BASER0.Type is `0b001` (Device).
- GITS_BASER1.Type is either `0b100` (Collection Table) or `0b000` (Unimplemented).
- GITS_BASER2.Type is either `0b010` (vPE) or `0b000` (Unimplemented).
- GITS_BASER<n>.Type, where 'n' is in the range 3 to 7, is `0b000` (Unimplemented).

For GICv3.x and GICv4.0, Arm recommends that the GITS_BASER<n> use the same allocations.

Other allocations of Type values are deprecated.

This field resets to an architecturally UNKNOWN value.

OuterCache, bits [55:53]

Indicates the Outer Cacheability attributes of accesses to the table. The possible values of this field are:

OuterCache	Meaning
`0b000`	Memory type defined in InnerCache field. For Normal memory, Outer Cacheability is the same as Inner Cacheability.
`0b001`	Normal Outer Non-cacheable.
`0b010`	Normal Outer Cacheable Read-allocate, Write-through.
`0b011`	Normal Outer Cacheable Read-allocate, Write-back.
`0b100`	Normal Outer Cacheable Write-allocate, Write-through.
`0b101`	Normal Outer Cacheable Write-allocate, Write-back.
`0b110`	Normal Outer Cacheable Read-allocate, Write-allocate, Write-through.
`0b111`	Normal Outer Cacheable Read-allocate, Write-allocate, Write-back.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

This field resets to an architecturally UNKNOWN value.

Entry_Size, bits [52:48]

Read-only. Specifies the number of bytes per translation table entry, minus one.

Physical_Address, bits [47:12]

Physical Address. When Page_Size is 4KB or 16KB:

- Bits [51:48] of the base physical address are zero.
- This field provides bits[47:12] of the base physical address of the table.
- Bits[11:0] of the base physical address are zero.
- The address must be aligned to the size specified in the Page Size field. Otherwise the effect is CONSTRAINED UNPREDICTABLE, and can be one of the following:
  - Bits[X:12], where X is derived from the page size, are treated as zero.
  - The value of bits[X:12] are used when calculating the address of a table access.

When Page_Size is 64KB:

- Bits[47:16] of the register provide bits[47:16] of the base physical address of the table.
- Bits[15:12] of the register provide bits[51:48] of the base physical address of the table.
- Bits[15:0] of the base physical address are 0.

In implementations that support fewer than 52 bits of physical address, any unimplemented upper bits might be RAZ/WI.

This field resets to an architecturally UNKNOWN value.

Shareability, bits [11:10]

Indicates the Shareability attributes of accesses to the table. The possible values of this field are:

Shareability	Meaning
0b00	Non-shareable.
0b01	Inner Shareable.
0b10	Outer Shareable.
0b11	Reserved. Treated as 0b00.

It is IMPLEMENTATION DEFINED whether this field has a fixed value or can be programmed by software. Implementing this field with a fixed value is deprecated.

This field resets to an architecturally UNKNOWN value.

Page_Size, bits [9:8]

The size of page that the translation table uses:

Page_Size	Meaning
0b00	4KB.
0b01	16KB.
0b10	64KB.
0b11	Reserved. Treated as 0b10.

Note

If the GIC implementation supports only a single, fixed page size, this field might be RO.

This field resets to an architecturally UNKNOWN value.

Size, bits [7:0]

The number of pages of physical memory allocated to the table, minus one. GITS_BASER<n>.Page_Size specifies the size of each page.

If GITS_BASER<n>.Type == 0, this field is RAZ/WI.

This field resets to an architecturally UNKNOWN value.

Accessing the GITS_BASER<n>

GITS_BASER<n> can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC ITS control	0x0100 + 8n	GITS_BASER<n>

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GITS_CTLR, ITS Control Register

The GITS_CTLR characteristics are:

Purpose

Controls the operation of an ITS.

Configuration

The ITS_Number (bits [7:4]) and bit [1] fields apply only in GICv4 implementations, and are RES0 in GICv3 implementations.

Attributes

GITS_CTLR is a 32-bit register.

Field descriptions

The GITS_CTLR bit assignments are:



Quiescent, bit [31]

Read-only. Indicates completion of all ITS operations when GITS_CTLR.Enabled == 0.

Quiescent	Meaning
0b0	The ITS is not quiescent and cannot be powered down.
0b1	The ITS is quiescent and can be powered down.

For the ITS to be considered inactive~~quiescent~~, there must be no transactions in progress. In addition, all operations required to ensure that mapping data is consistent with external memory must be complete.

Note

In distributed GIC implementations, this bit is set to 1 only after the ITS forwards any operations that have not yet been completed to the Redistributors and receives confirmation that all such operations have reached the appropriate Redistributor.

In GICv4.0 and GICv3.x, when~~When~~ GITS_CTLR.Enabled==1 the value of GITS_CTLR.Quiescent is UNKNOWN.

In GICv4.1, when GITS_CTLR.Enabled==1 the value of GITS_CTLR.Quiescent reads as 1 until the write to Enabled has taken effect and then reads as 0.

This field resets to 1.

Bits [30:8]

Reserved, RES0.

ITS_Number, bits [7:4]

In GICv3 implementations this field is RES0.

In GICv4 implementations with more than one ITS instance, this field indicates the ITS number for use with VMOVP.

It is IMPLEMENTATION DEFINED whether this field is programmable or RO.

If this field is programmable, changing this field when GITS_CTLR.Quiescent == 0 or GITS_CTLR.Enabled == 1 is UNPREDICTABLE.

This field resets to an architecturally UNKNOWN value.

Bits [3:2]

Reserved, RES0.

ImDe, bit [1]

In GICv3 implementations this bit is RES0.

In GICv4 implementations this bit is IMPLEMENTATION DEFINED.

This field resets to `0`.

Enabled, bit [0]

Controls whether the ITS is enabled:

Enabled	Meaning
`0b0`	The ITS is not enabled. Writes to GITS_TRANSLATER are ignored and no further command queue entries are processed.
`0b1`	The ITS is enabled. Writes to GITS_TRANSLATER result in interrupt translations and the command queue is processed.

If a write to this register changes this field from 1 to 0, the ITS must ensure that both:

- Any caches containing mapping data are made consistent with external memory.
- GITS_CTLR.Quiescent == 0 until all caches are consistent with external memory.

Changing GITS_CTLR.Enabled from 0 to 1 when GITS_CTLR.Quiescent is 0 results in UNPREDICTABLE behavior.

This field resets to `0`.

Accessing the GITS_CTLR

GITS_CTLR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC ITS control	`0x0000`	GITS_CTLR

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GITS_CWRITER, ITS Write Register

The GITS_CWRITER characteristics are:

Purpose

Specifies the offset from GITS_CBASER where software writes the next ITS command.

Configuration

~~RW fields in this register reset to architecturally UNKNOWN values.~~

Bits [63:32] and bits [31:0] are accessible separately.

Attributes

GITS_CWRITER is a 64-bit register.

Field descriptions

The GITS_CWRITER bit assignments are:



Bits [63:20]

Reserved, RES0.

Offset, bits [19:5]

Bits [19:5] of the offset from GITS_CBASER. Bits [4:0] of the offset are zero.

This field resets to an architecturally UNKNOWN value.

Bits [4:1]

Reserved, RES0.

Retry, bit [0]

Writing this bit has the following effects:

Retry	Meaning
0b0	No effect on the processing commands by the ITS.
0b1	Restarts the processing of commands by the ITS if it stalled because of a command error. **Note** If the processing of commands is not stalled because of a command error, writing 1 to this bit has no effect.

When read, this bit is RES0.

See The ITS Command Interface for more information.

If GITS_CWRITER is written with a value outside of the valid range specified by GITS_CBASER.Physical_Address and GITS_CBASER.Size, behavior is a CONSTRAINED UNPREDICTABLE choice, as follows:

- The command queue is considered invalid, and no further commands are processed until GITS_CWRITER is written with a value that is in the valid range.
- The value is treated as a valid UNKNOWN value.

An implementation might choose to report a system error in an IMPLEMENTATION DEFINED manner.

Accessing the GITS_CWRITER

GITS_CWRITER can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC ITS control	0x0088	GITS_CWRITER

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99e984cbfe3431cc1e9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

GITS_MPAMIDR, Report maximum PARTID and PMG Register

The GITS_MPAMIDR characteristics are:

Purpose

Reports the maximum support PARTID and PMG values.

Configuration

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GITS_MPAMIDR are RES0.

A copy of this register is provided for each ITS.

When GITS_TYPER.MPAM==0, this register is RES0.

Attributes

GITS_MPAMIDR is a 32-bit register.

Field descriptions

The GITS_MPAMIDR bit assignments are:



Bits [31:24]

Reserved, RES0.

PMGmax, bits [23:16]

Maximum PMG value supported.

PARTIDmax, bits [15:0]

Maximum PARTID value supported.

Accessing the GITS_MPAMIDR

GITS_MPAMIDR can be accessed through the memory-mapped interfaces:

Component	Offset
GIC ITS control	0x0010

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RO**.
- When IsAccessSecure() accesses to this register are **RO**.
- When !IsAccessSecure() accesses to this register are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

no old file htmldiff from- (new)

GITS_MPIDR, Report ITS's affinity.

The GITS_MPIDR characteristics are:

Purpose

Reports ITS's affinity when the vPE Table is shared with Redistributors.

Configuration

This register is present only when GICv4.1 is implemented. Otherwise, direct accesses to GITS_MPIDR are RES0.

A copy of this register is provided for each ITS.

When GITS_TYPER.SVPET==0, this register is RES0.

Attributes

GITS_MPIDR is a 32-bit register.

Field descriptions

The GITS_MPIDR bit assignments are:



Aff3, bits [31:24]

Aff2, bits [23:16]

Aff1, bits [15:8]

Bits [7:0]

Reserved, RES0.

Accessing the GITS_MPIDR

GITS_MPIDR can be accessed through the memory-mapped interfaces:

Component	Offset
GIC ITS control	0x0018

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RO**.
- When IsAccessSecure() accesses to this register are **RO**.
- When !IsAccessSecure() accesses to this register are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

no old file htmldiff from- (new)

(old) htmldiff from- (new)

GITS_PARTIDR, Set PARTID and PMG Register

The GITS_PARTIDR characteristics are:

Purpose

Sets the PARTID and PMG values used for memory accesses by the ITS.

Configuration

This register is present only when GICv3.1~~GIC, >=3.1~~ is implemented. Otherwise, direct accesses to GITS_PARTIDR are RES0.

A copy of this register is provided for each ITS.

When GITS_TYPER.MPAM==0, this register is RES0.

Attributes

GITS_PARTIDR is a 32-bit register.

Field descriptions

The GITS_PARTIDR bit assignments are:



Bits [31:24]

Reserved, RES0.

PMG, bits [23:16]

PMG value used when ITS accesses memory.

It is IMPLEMENTATION DEFINED whether bits not needed to represent PMG values in the range 0 to PMG_MAX are stateful or RES0.

PARTID, bits [15:0]

PARTID value used when ITS accesses memory.

It is IMPLEMENTATION DEFINED whether bits not needed to represent PARTID values in the range 0 to PARTID_MAX are stateful or RES0.

Accessing the GITS_PARTIDR

GITS_PARTIDR can be accessed through the memory-mapped interfaces:

Component	Offset
GIC ITS control	0x0014

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RW**.
- When IsAccessSecure() accesses to this register are **RW**.
- When !IsAccessSecure() accesses to this register are **RW**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

no old file htmldiff from- (new)

GITS_SGIR, ITS SGI Register

The GITS_SGIR characteristics are:

Purpose

Written by software to signal a virtual SGI for translation by the ITS.

Configuration

This register is present only when GICv4.1 is implemented. Otherwise, direct accesses to GITS_SGIR are RES0.

This register is provided only in GICv4.1 implementations.

Attributes

GITS_SGIR is a 64-bit register.

Field descriptions

The GITS_SGIR bit assignments are:



Bits [63:48]

Reserved, RES0.

vPEID, bits [47:32]

ID of target vPEID.

The size of this field is IMPLEMENTATION DEFINED, and is specified by the GICD_TYPER2.VIL and GICD_TYPER2.VID fields. Unimplemented bits are RES0.

Bits [31:4]

Reserved, RES0.

vINTID, bits [3:0]

INTID of virtual SGI.

Accessing the GITS_SGIR

64-bit access only.

GITS_SGIR can be accessed through the memory-mapped interfaces:

Component	Offset
GIC ITS control	0x20020

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **WO**.
- When IsAccessSecure() accesses to this register are **WO**.
- When !IsAccessSecure() accesses to this register are **WO**.

13/12/2019 15:13; 391b5248b29fb2f001ef74792eaacbd6fc72f211

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

no old file htmldiff from- (new)

(old) htmldiff from- (new)

GITS_TYPER, ITS Type Register

The GITS_TYPER characteristics are:

Purpose

Specifies the features that an ITS supports.

Configuration

Attributes

GITS_TYPER is a 64-bit register.

Field descriptions

The GITS_TYPER bit assignments are:



Bits [63:4439]

Reserved, RES0.

nID, bit [43]

When GICv4.1 is implemented:

nID

nID	Meaning
0b0	Individual doorbell interrupt supported.
0b1	Individual doorbell interrupt not supported.

Otherwise:

Reserved, RES0.

SVPET, bits [42:41]

When GICv4.1 is implemented:

SVPET

SVPET	Meaning
0b00	vPE Table is not shared with Redistributors.
0b01	vPE Table is shared with the groups of Redistributors indicated by GITS_MPIDR.Aff3.
0b10	vPE Table is shared with the groups of Redistributors indicated by GITS_MPIDR fields Aff3 and Aff2.
0b11	vPE Table is shared with the groups of Redistributors indicated by GITS_MPIDR fields Aff3, Aff2 and Aff1.

Otherwise:

Reserved, RES0.

VMAPP, bit [40]

When GICv4.1 is implemented:

VMAPP

VMAPP	Meaning
0b0	GICv4.0 VMAPP command layout.
0b1	GICv4.1 VMAPP command layout.

Otherwise:

Reserved, RES0.

VSGI, bit [39]

When GICv4.1 is implemented:

VSGI

VSGI	Meaning
0b0	Direct injection of SGIs is not supported.
0b1	Direct injection of SGIs is supported.

Otherwise:

Reserved, RES0.

MPAM, bit [38]

When GIC, >=3.1 is implemented:

MPAM

MPAM	Meaning
0b0	MPAM is not supported.
0b1	MPAM is supported.

Otherwise:

Reserved, RES0.

VMOVP, bit [37]

Indicates the form of the VMOVP command.

VMOVP	Meaning
0b0	When moving a vPE, software must issue a VMOVP on all ITSs that have mappings for that vPE. The ITSList and Sequence Number fields in the VMOVP command must ensure synchronization, otherwise behavior is UNPREDICTABLE.
0b1	When moving a vPE, software must only issue a VMOVP on one of the ITSs that has a mapping for that vPE. The ITSList and Sequence Number fields in the VMOVP command are RES0.

CIL, bit [36]

Collection ID Limit.

CIL	Meaning
0b0	ITS supports 16-bit Collection ID, GITS_TYPER.CIDbits is RES0.
0b1	GITS_TYPER.CIDbits indicates supported Collection ID size

In implementations that do not support Collections in external memory, this bit is RES0 and the number of Collections supported is reported by GITS_TYPER.HCC.

CIDbits, bits [35:32]

Number of Collection ID bits.

- The number of bits of Collection ID minus- one.~~1.~~
- When GITS_TYPER.CIL == 0, this field is RES0.

HCC, bits [31:24]

Hardware Collection Count. The number of interrupt collections supported by the ITS without provisioning of external memory.

Note

Collections held in hardware are unmapped at reset.

Bits [23:20]

Reserved, RES0.

PTA, bit [19]

Physical Target Addresses. Indicates the format of the target address:

PTA	Meaning
0b0	The target address corresponds to the PE number specified by GICR_TYPER.Processor_Number.
0b1	The target address corresponds to the base physical address of the required Redistributor.

See Target addresses for more information.

SEIS, bit [18]

SEI support. Indicates whether the virtual CPU interface supports generation of SEIs:

SEIS	Meaning
0b0	The ITS does not support local generation of SEIs.
0b1	The ITS supports local generation of SEIs.

Devbits, bits [17:13]

The number of DeviceID bits implemented, minus one.

ID_bits, bits [12:8]

The number of EventID bits implemented, minus one.

ITT_entry_size, bits [7:4]

Read-only. Indicates the number of bytes per translation table entry, minus one.

See the ITS command 'MAPD' for more information.

IMPLEMENTATION DEFINED, bit [3]

IMPLEMENTATION DEFINED.

CCT, bit [2]

Cumulative Collection Tables.

CCT	Meaning
0b0	The total number of supported collections is determined by the number of collections held in memory only.
0b1	The total number of supported collections is determined by number of collections that are held in memory and the number indicated by GITS_TYPER.HCC.

If GITS_TYPER.HCC == 0, or if memory backed collections are not supported (all GITS_BASER<n>.Type != 100), this bit is RES0.

Virtual, bit [1]

Indicates whether the ITS supports virtual LPIs and direct injection of virtual LPIs:

Virtual	Meaning
0b0	The ITS does not support virtual LPIs or direct injection of virtual LPIs.
0b1	The ITS supports virtual LPIs and direct injection of virtual LPIs.

This field is RES0 in GICv3 implementations.

Physical, bit [0]

Indicates whether the ITS supports physical LPIs:

Physical	Meaning
0b0	The ITS does not support physical LPIs.
0b1	The ITS supports physical LPIs.

This field is RES1, indicating that the ITS supports physical LPIs.

Accessing the GITS_TYPER

GITS_TYPER can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
GIC ITS control	0x0008	GITS_TYPER

This interface is accessible as follows:

- When GICD_CTLR.DS == 0b0 accesses to this register are **RO**.
- When IsAccessSecure() accesses to this register are **RO**.
- When !IsAccessSecure() accesses to this register are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMCFG_CPBM, MPAM Cache Portion Bitmap Partition Configuration Register

The MPAMCFG_CPBM characteristics are:

Purpose

The MPAMCFG_CPBM register is a read-write register that configures the cache portions that a PARTID is allowed to allocate. After setting MPAMCFG_PART_SEL with a PARTID, software (usually a hypervisor) writes to the MPAMCFG_CPBM register to configure which cache portions the PARTID is allowed to allocate.

MPAMCFG_CPBM_s controls cache portions for the Secure PARTID selected by the Secure instance of MPAMCFG_PART_SEL. MPAMCFG_CPBM_ns controls the cache portions for the Non-secure PARTID selected by the Non-secure instance of MPAMCFG_PART_SEL.

Configuration

The power domain of MPAMCFG_CPBM is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_CPOR_PART~~MPAMF_IDR.HAS_CPOR~~ == 1. Otherwise, direct accesses to MPAMCFG_CPBM are RES0.

Attributes

MPAMCFG_CPBM is a 32768-bit register.

Field descriptions

The MPAMCFG_CPBM bit assignments are:

CPBM<n>, bit [n], for n = 0 to 32767

Each bit, CPBM<n>, grants permission to the PARTID to allocate cache lines within cache portion n.

CPBM<n>	Meaning
0b0	The PARTID is not permitted to allocate into cache portion n.
0b1	The PARTID is permitted to allocate within cache portion n.

The number of bits in the cache portion partitioning bit map of this component is given in MPAMF_CPOR_IDR.CPBM_WD. CPBM_WD contains a value from 1 to 2^{15}, inclusive. Values of CPBM_WD greater than 32 require a group of 32-bit registers to access the CPBM, up to 1024 registers.

Bits CPBM<n>, where n is greater than CPBM_WD, are not required to be implemented.

Accessing the MPAMCFG_CPBM

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMCFG_CPBM_s must be accessible from the Secure MPAM feature page. MPAMCFG_CPBM_ns must be accessible from the Non-secure MPAM feature page.

MPAMCFG_CPBM_s and MPAMCFG_CPBM_ns must be separate registers. The Secure instance (MPAMCFG_CPBM_s) accesses the cache portion bitmaps used for Secure PARTIDs, and the Non-secure instance (MPAMCFG_CPBM_ns) accesses the cache portion bitmaps used for Non-secure PARTIDs.

MPAMCFG_CPBM can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x1000	MPAMCFG_CPBM_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x1000	MPAMCFG_CPBM_ns

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMCFG_PART_SEL, MPAM Partition Configuration Selection Register

The MPAMCFG_PART_SEL characteristics are:

Purpose

Selects a partition ID to configure. MPAMCFG_PART_SEL_s selects a Secure PARTID to configure. MPAMCFG_PART_SEL_ns selects a Non-secure PARTID to configure.

After setting this register with a PARTID, software (usually a hypervisor) can perform a series of accesses to MPAMCFG registers to configure parameters for MPAM resource controls to use when requests have that PARTID.

Configuration

The power domain of MPAMCFG_PART_SEL is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_CCAP_PART == 1, or MPAMF_IDR.HAS_CPOR_PART == 1, or MPAMF_IDR.HAS_MBW_PART == 1, or MPAMF_IDR.HAS_PRI_PART == 1, or MPAMF_IDR.HAS_PARTID_NRW == 1, or (MPAMF_IDR.EXT == 0 and MPAMF_IDR.HAS_IMPL_IDR == 1) or (MPAMF_IDR.EXT == 1, MPAMF_IDR.HAS_IMPL_IDR == 1 and MPAMF_IDR.NO_IMPL_PART == 0). Otherwise, direct accesses to MPAMCFG_PART_SEL are RES0.

Attributes

MPAMCFG_PART_SEL is a 32-bit register.

Field descriptions

The MPAMCFG_PART_SEL bit assignments are:

31 30 29 28	27 26 25 24	23 22 21 20 19 18 17	16	15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 0
RES0	RIS	RES0	INTERNAL	PARTID_SEL

Bits [31:28]

Reserved, RES0.

RIS, bits [27:24]

When ARMv8.6-MPAM is implemented, MPAMF_IDR.EXT == 1 and MPAMF_IDR.HAS_RISMAPMF_IDR.HAS_RIS == 1:

Resource Instance Selector. RIS selects one resource to configure through MPAMCFG registers and describe with MPAMF ID registers.

Otherwise:

Reserved, RES0.

Bits [23:17]

Reserved, RES0.

INTERNAL, bit [16]

Internal PARTID.

If MPAMF_IDR.HAS_PARTID_NRW =0, this field is RAZ/WI.

If MPAMF_IDR.HAS_PARTID_NRW = 1:

INTERNAL	Meaning
0b0	PARTID_SEL is interpreted as a request PARTID and ignored except for use with MPAMCFG_INTPARTID register access.
0b1	PARTID_SEL is interpreted as an internal PARTID and used for access to MPAMCFG control settings except for MPAMCFG_INTPARTID.

If PARTID narrowing is implemented as indicated by MPAMF_IDR.HAS_PARTID_NRW = 1, when accessing other MPAMCFG registers the value of the MPAMCFG_PART_SEL.INTERNAL bit is checked for these conditions:

- When the MPAMCFG_INTPARTID register is read or written, if the value of MPAMCFG_PART_SEL.INTERNAL is not 0, an Unexpected_INTERNAL error is set in MPAMF_ESR.
- When an MPAMCFG register other than MPAMCFG_INTPARTID is read or written, if the value of MPAMCFG_PART_SEL.INTERNAL is not 1, MPAMF_ESR is set to indicate an intPARTID_Range error.

In either error case listed here, the value returned by a read operation is UNPREDICTABLE, and the control settings are not affected by a write.

PARTID_SEL, bits [15:0]

Selects the partition ID to configure.

Reads and writes to other MPAMCFG registers are indexed by PARTID_SEL and by the NS bit used to access MPAMCFG_PART_SEL to access the configuration for a single partition.

Accessing the MPAMCFG_PART_SEL

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMCFG_PART_SEL_s must be accessible from the Secure MPAM feature page. MPAMCFG_PART_SEL_ns must be accessible from the Non-secure MPAM feature page.

MPAMCFG_PART_SEL_s and MPAMCFG_PART_SEL_ns must be separate registers. The Secure instance (MPAMCFG_PART_SEL_s) accesses the PARTID selector used for Secure PARTIDs, and the Non-secure instance (MPAMCFG_PART_SEL_ns) accesses the PARTID selector used for Non-secure PARTIDs.

MPAMCFG_PART_SEL can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0100	MPAMCFG_PART_SEL_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0100	MPAMCFG_PART_SEL_ns

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMCFG_PRI, MPAM Priority Partition Configuration Register

The MPAMCFG_PRI characteristics are:

Purpose

Controls~~MPAMCFG_PRI is a 32-bit read-write register that controls~~ the internal and downstream priority of requests attributed to the PARTID selected by MPAMCFG_PART_SEL. MPAMCFG_PRI_s controls the priorities for the Secure PARTID selected by the Secure instance of MPAMCFG_PART_SEL. MPAMCFG_PRI_ns controls the priorities for the Non-secure PARTID selected by the Non-secure instance of MPAMCFG_PART_SEL.

Configuration

The power domain of MPAMCFG_PRI is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_PRI_PART == 1. Otherwise, direct accesses to MPAMCFG_PRI are RES0.

Attributes

MPAMCFG_PRI is a 32-bit register.

Field descriptions

The MPAMCFG_PRI bit assignments are:



DSPRI, bits [31:16]

Downstream priority.

If MPAMF_PRI_IDR.HAS_DSPRI == 0, bits of this field are RES0 ~~,~~as this field is not used.

If MPAMF_PRI_IDR.HAS_DSPRI == 1, this field is a priority value applied to downstream communications from this MSC for transactions of the partition selected by MPAMCFG_PART_SEL.

The implemented width of this field is MPAMF_PRI_IDR.DSPRI_WD bits. If the implemented width is less than the width of this field, the least significant bits are used.

The encoding of priority is 0-as-lowest or 0-as-highest priority according to the value of MPAMF_PRI_IDR.DSPRI_0_IS_LOW.

INTPRI, bits [15:0]

Internal priority.

If MPAMF_PRI_IDR.HAS_INTPRI == 0, bits of this field are RES0 as this field is not used.

If MPAMF_PRI_IDR.HAS_INTPRI == 1, this field is a priority value applied internally inside this MSC for transactions of the partition selected by Mext-PAMCFG_PART_SEL.

The implemented width of this field is MPAMF_PRI_IDR.INTPRI_WD bits. If the implemented width is less than the width of this field, the least significant bits are used.

The encoding of priority is 0-as-lowest or 0-as-highest priority according to the value of MPAMF_PRI_IDR.INTPRI_0_IS_LOW.

Accessing the MPAMCFG_PRI

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMCFG_PRI_s must be accessible from the Secure MPAM feature page. MPAMCFG_PRI_ns must be accessible from the Non-secure MPAM feature page.

MPAMCFG_PRI_s and MPAMCFG_PRI_ns must be separate registers. The Secure instance (MPAMCFG_PRI_s) accesses the priority partitioning used for Secure PARTIDs, and the Non-secure instance (MPAMCFG_PRI_ns) accesses the priority partitioning used for Non-secure PARTIDs.

MPAMCFG_PRI can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0400	MPAMCFG_PRI_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0400	MPAMCFG_PRI_ns

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMF_CCAP_IDR, MPAM Features Cache Capacity Partitioning ID register

The MPAMF_CCAP_IDR characteristics are:

Purpose

IndicatesThe MPAMF_CCAP_IDR is a 32-bit read-only register that indicates the number of fractional bits in MPAMCFG_CMAX for this MSC. MPAMF_CCAP_IDR_s indicates the number of fractional bits in the Secure instance of MPAMCFG_CMAX. MPAMF_CCAP_IDR_ns indicates the number of fractional bits in the Non-secure instance of MPAMCFG_CMAX.

Configuration

The power domain of MPAMF_CCAP_IDR is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_CCAP_PART == 1. Otherwise, direct accesses to MPAMF_CCAP_IDR are RES0.

Attributes

MPAMF_CCAP_IDR is a 32-bit register.

Field descriptions

The MPAMF_CCAP_IDR bit assignments are:



Bits [31:6]

Reserved, RES0.

CMAX_WD, bits [5:0]

Number of fractional bits implemented in the cache capacity partitioning control, MPAMCFG_CMAX.CMAX, of this device. See MPAMCFG_CMAX.

This field must contain a value from 1 to 16, inclusive.

Accessing the MPAMF_CCAP_IDR

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMF_CCAP_IDR is read-only.

MPAMF_CCAP_IDR must be readable from the Non-secure and Secure MPAM feature pages.

MPAMF_CCAP_IDR is permitted to have the same contents when read from either the Secure and Non-secure MPAM feature pages unless the register contents is different for Secure and Non-secure versions, when there must be separate registers in the Secure (MPAMF_CCAP_IDR_s) and Non-secure (MPAMF_CCAP_IDR_ns) MPAM feature pages.

MPAMF_CCAP_IDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0038	MPAMF_CCAP_IDR_s

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0038	MPAMF_CCAP_IDR_ns

Accesses on this interface are **RO**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMF_CPOR_IDR, MPAM Features Cache Portion Partitioning ID register

The MPAMF_CPOR_IDR characteristics are:

Purpose

IndicatesThe MPAMF_CPOR_IDR is a 32-bit read-only register that indicates the number of bits in MPAMCFG_CPBM for this MSC. MPAMF_CPOR_IDR_s indicates the number of bits in the Secure instance of MPAMCFG_CPBM. MPAMF_CPOR_IDR_ns indicates the number of bits in the Non-secure instance of MPAMCFG_CPBM.

Configuration

The power domain of MPAMF_CPOR_IDR is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_CPOR_PARTMPAMF_IDR.HAS_CPOR == 1. Otherwise, direct accesses to MPAMF_CPOR_IDR are RES0.

Attributes

MPAMF_CPOR_IDR is a 32-bit register.

Field descriptions

The MPAMF_CPOR_IDR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																CPBM_WD															

Bits [31:16]

Reserved, RES0.

CPBM_WD, bits [15:0]

Number of bits in the cache portion partitioning bit map of this device. See MPAMCFG_CPBM.

This field must contain a value from 1 to 32768, inclusive. Values greater than 32 require a group of 32-bit registers to access the CPBM, up to 1024 if CPBM_WD is the largest value.

Accessing the MPAMF_CPOR_IDR

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMF_CPOR_IDR is read-only.

MPAMF_CPOR_IDR must be readable from the Non-secure and Secure MPAM feature pages.

MPAMF_CPOR_IDR is permitted to have the same contents when read from either the Secure and Non-secure MPAM feature pages unless the register contents is different for Secure and Non-secure versions, when there must be separate registers in the Secure (MPAMF_CPOR_IDR_s) and Non-secure (MPAMF_CPOR_IDR_ns) MPAM feature pages.

MPAMF_CPOR_IDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0030	MPAMF_CPOR_IDR_s

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0030	MPAMF_CPOR_IDR_ns

Accesses on this interface are **RO**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMF_CSUMON_IDR, MPAM Features Cache Storage Usage Monitoring ID register

The MPAMF_CSUMON_IDR characteristics are:

Purpose

IndicatesThe MPAMF_CSUMON_IDR is a 32-bit read-only register that indicates the number of cache storage usage monitors for this MSC. MPAMF_CSUMON_IDR_s indicates the number of Secure cache storage usage monitors. MPAMF_CSUMON_IDR_ns indicates the number of Non-secure cache storage usage monitors.

Configuration

The power domain of MPAMF_CSUMON_IDR is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1 and MPAMF_MSMON_IDR.MSMON_CSU == 1. Otherwise, direct accesses to MPAMF_CSUMON_IDR are RES0.

Attributes

MPAMF_CSUMON_IDR is a 32-bit register.

Field descriptions

The MPAMF_CSUMON_IDR bit assignments are:

31	30 29 28 27 26 25 24 23 22 21 20 19 18 17 16	15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 0
HAS_CAPTURE	RES0	NUM_MON

HAS_CAPTURE, bit [31]

The implementation of this MSC supports copying an MSMON_CSU to the corresponding MSMON_CSU_CAPTURE on a capture event.

HAS_CAPTURE	Meaning
0b0	MSMON_CSU_CAPTURE is not implemented and there is no support for capture events in the CSU monitor.
0b1	The MSMON_CSU_CAPTURE register is implemented and the CSU monitor supports the capture event behavior.

Bits [30:16]

Reserved, RES0.

NUM_MON, bits [15:0]

The number of cache storage usage monitors implemented in this MSC.

Accessing the MPAMF_CSUMON_IDR

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMF_CSUMON_IDR is read-only.

MPAMF_CSUMON_IDR must be readable from the Non-secure and Secure MPAM feature pages.

MPAMF_CSUMON_IDR is permitted to have the same contents when read from either the Secure and Non-secure MPAM feature pages unless the register contents is different for Secure and Non-secure versions, when there must be separate registers in the Secure (MPAMF_CSUMON_IDR_s) and Non-secure (MPAMF_CSUMON_IDR_ns) MPAM feature pages.

MPAMF_CSUMON_IDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0088	MPAMF_CSUMON_IDR_s

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0088	MPAMF_CSUMON_IDR_ns

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMF_IDR, MPAM Features Identification Register

The MPAMF_IDR characteristics are:

Purpose

Indicates which memory partitioning and monitoring features are present on this MSC. MPAMF_IDR_s indicates the MPAM features accessed from the Secure MPAM feature page. MPAMF_IDR_ns indicates the MPAM features accessed from the Non-secure MPAM feature page.

Configuration

The power domain of MPAMF_IDR is IMPLEMENTATION DEFINED.

Attributes

MAMPF_IDR is 64-bit register when ARMv8.6-MPAM is implemented.

Otherwise, MAMPF_IDR is a 32-bit register.

Field descriptions

The MPAMF_IDR bit assignments are:

When ARMv8.6-MPAM is implemented:



Bits [63:60]

Reserved, RES0.

RIS_MAX, bits [59:56]

When MPAMF_IDR.EXT == 1 and MPAMF_IDR.HAS_RIS == 1:

Maximum RIS value supported in MPAMCFG_PART_SEL. Must be `0b0000` if MPAMF_IDR.HAS_RIS == 0.

Otherwise:

Reserved, RES0.

Bits [55:40]

Reserved, RES0.

HAS_ESR, bit [39]

When MPAMF_IDR.EXT == 1:

MPAMF_ESR is implemented.

HAS_ESR	Meaning
0b0	MPAMF_ESR, MPAM_ECR and MPAM error handling are not implemented.
0b1	MPAMF_ESR, MPAM_ECR and MPAM error handling are implemented.

Otherwise:

Reserved, RES0.

HAS_EXTD_ESR, bit [38]

When MPAMF_IDR.EXT == 1:

MPAMF_ESR is 64 bits.

HAS_EXTD_ESR	Meaning
0b0	MPAMF_ESR is 32 bits.
0b1	MPAMF_ESR is 64 bits.

Otherwise:

Reserved, RES0.

NO_IMPL_MSMON, bit [37]

When MPAMF_IDR.EXT == 1 and MPAMF_IDR.HAS_IMPL_IDR == 1:

MPAMF_IMPL_IDR defines no IMPLEMENTATION DEFINED resource monitors.

NO_IMPL_MSMON	Meaning
0b0	MPAMF_IMPL_IDR defines at least one IMPLEMENTATION DEFINED resource monitor.
0b1	MPAMF_IMPL_IDR does not define any IMPLEMENTATION DEFINED resource monitors.

Otherwise:

Reserved, RES0.

NO_IMPL_PART, bit [36]

When MPAMF_IDR.EXT == 1 and MPAMF_IDR.HAS_IMPL_IDR == 1:

MPAMF_IMPL_IDR defines no IMPLEMENTATION DEFINED resource controls.

NO_IMPL_PART	Meaning
0b0	MPAMF_IMPL_IDR defines at least one IMPLEMENTATION DEFINED resource control.
0b1	MPAMF_IMPL_IDR does not define any IMPLEMENTATION DEFINED resource controls.

Otherwise:

Reserved, RES0.

Bits [35:33]

Reserved, RES0.

HAS_RIS, bit [32]

When MPAMF_IDR.EXT == 1:

Has resource instance selector. Indicates that MPAMCFG_PART_SEL contains the RIS field that selects a resource instance to control.

HAS_RIS	Meaning
0b0	MPAMCFG_PART_SEL does not implement the MPAMFCFG_PART_SEL.RIS field or multiple resource instance suport.
0b1	MPAMCFG_PART_SEL implements the MPAMFCFG_PART_SEL.RIS field and MPAM resource instance numbers up to and including MPAMF_IDR.RIS_MAX.

Otherwise:

Reserved, RES0.

HAS_PARTID_NRW, bit [31]

Has PARTID narrowing.

HAS_PARTID_NRW	Meaning
0b0	Does not have MPAMF_PARTID_NRW_IDR, MPAMCFG_INTPARTID or intPARTID mapping support.
0b1	Supports the MPAMF_PARTID_NRW_IDR, MPAMCFG_INTPARTID registers.

HAS_MSMON, bit [30]

Has resource monitors. Indicates whether this MSC has MPAM resource monitors.

HAS_MSMON	Meaning
0b0	Does not support MPAM resource monitoring by groups or MPAMF_MSMON_IDR.
0b1	Supports resource monitoring by matching a combination of PARTID and PMG. See MPAMF_MSMON_IDR.

HAS_IMPL_IDR, bit [29]

Has MPAMF_IMPL_IDR. Indicates whether this MSC has the implementation-specific MPAM features register, MPAMF_IMPL_IDR.

HAS_IMPL_IDR	Meaning
0b0	Does not have MPAMF_IMPL_IDR.
0b1	Has MPAMF_IMPL_IDR.

EXT, bit [28]

From Armv8.6:

Extended MPAMF_IDR.

EXT	Meaning
0b0	MPAMF_IDR has no defined bits in [63:32]. The register is effectively 32 bits.
0b1	MPAMF_IDR has bits defined in [63:32]. The register is 64-bits.

Otherwise:

Reserved, RES0.

HAS_PRI_PART, bit [27]

Has priority partitioning. Indicates whether this MSC implements MPAM priority partitioning and MPAMF_PRI_IDR.

HAS_PRI_PART	Meaning
0b0	Does not support priority partitioning or have MPAMF_PRI_IDR.
0b1	Has MPAMF_PRI_IDR.

HAS_MBW_PART, bit [26]

Has memory bandwidth partitioning. Indicates whether this MSC implements MPAM memory bandwidth partitioning and MPAMF_MBW_IDR.

HAS_MBW_PART	Meaning
0b0	Does not support memory bandwidth partitioning or have MPAMF_MBW_IDR register.
0b1	Has MPAMF_MBW_IDR register.

HAS_CPOR_PART, bit [25]

Has cache portion partitioning. Indicates whether this MSC implements MPAM cache portion partitioning and MPAMF_CPOR_IDR.

HAS_CPOR_PART	Meaning
0b0	Does not support cache portion partitioning or have MPAMF_CPOR_IDR or MPAMCFG_CPBM registers.
0b1	Has MPAMF_CPOR_IDR and MPAMCFG_CPBM registers.

HAS_CCAP_PART, bit [24]

Has cache capacity partitioning. Indicates whether this MSC implements MPAM cache capacity partitioning and the MPAMF_CCAP_IDR and MPAMCFG_CMAX registers.

HAS_CCAP_PART	Meaning
0b0	Does not support cache capacity partitioning or have MPAMF_CCAP_IDR and MPAMCFG_CMAX registers.
0b1	Has MPAMF_CCAP_IDR and MPAMCFG_CMAX registers.

PMG_MAX, bits [23:16]

Maximum value of Non-secure PMG supported by this component.

PARTID_MAX, bits [15:0]

Maximum value of Non-secure PARTID supported by this component.

Otherwise:



HAS_PARTID_NRW, bit [31]

Has PARTID narrowing.

HAS_PARTID_NRW	Meaning
0b0	Does not have MPAMF_PARTID_NRW_IDR, MPAMCFG_INTPARTID or intPARTID mapping support.
0b1	Supports the MPAMF_PARTID_NRW_IDR, MPAMCFG_INTPARTID registers.

HAS_MSMON, bit [30]

Has resource monitors. Indicates whether this MSC has MPAM resource monitors.

HAS_MSMON	Meaning
0b0	Does not support MPAM resource monitoring by groups or MPAMF_MSMON_IDR.
0b1	Supports resource monitoring by matching a combination of PARTID and PMG. See MPAMF_MSMON_IDR.

HAS_IMPL_IDR, bit [29]

Has MPAMF_IMPL_IDR. Indicates whether this MSC has the implementation-specific MPAM features register, MPAMF_IMPL_IDR.

HAS_IMPL_IDR	Meaning
0b0	Does not have MPAMF_IMPL_IDR.
0b1	Has MPAMF_IMPL_IDR.

EXT, bit [28]

From Armv8.6:

Extended MPAMF_IDR.

EXT	Meaning
0b0	MPAMF_IDR has no defined bits in [63:32]. The register is effectively 32 bits.
0b1	MPAMF_IDR has bits defined in [63:32]. The register is 64-bits.

Otherwise:

Reserved, RES0.

HAS_PRI_PART, bit [27]

Has priority partitioning. Indicates whether this MSC implements MPAM priority partitioning and MPAMF_PRI_IDR.

HAS_PRI_PART	Meaning
0b0	Does not support priority partitioning or have MPAMF_PRI_IDR.
0b1	Has MPAMF_PRI_IDR.

HAS_MBW_PART, bit [26]

Has memory bandwidth partitioning. Indicates whether this MSC implements MPAM memory bandwidth partitioning and MPAMF_MBW_IDR.

HAS_MBW_PART	Meaning
0b0	Does not support memory bandwidth partitioning or have MPAMF_MBW_IDR register.
0b1	Has MPAMF_MBW_IDR register.

HAS_CPOR_PART, bit [25]

Has cache portion partitioning. Indicates whether this MSC implements MPAM cache portion partitioning and MPAMF_CPOR_IDR.

HAS_CPOR_PART	Meaning
0b0	Does not support cache portion partitioning or have MPAMF_CPOR_IDR or MPAMCFG_CPBM registers.
0b1	Has MPAMF_CPOR_IDR and MPAMCFG_CPBM registers.

HAS_CCAP_PART, bit [24]

Has cache capacity partitioning. Indicates whether this MSC implements MPAM cache capacity partitioning and the MPAMF_CCAP_IDR and MPAMCFG_CMAX registers.

HAS_CCAP_PART	Meaning
0b0	Does not support cache capacity partitioning or have MPAMF_CCAP_IDR and MPAMCFG_CMAX registers.
0b1	Has MPAMF_CCAP_IDR and MPAMCFG_CMAX registers.

PMG_MAX, bits [23:16]

Maximum value of Non-secure PMG supported by this component.

PARTID_MAX, bits [15:0]

Maximum value of Non-secure PARTID supported by this component.

Accessing the MPAMF_IDR

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMF_IDR is read-only.

MPAMF_IDR must be readable from the Non-secure and Secure MPAM feature pages.

MPAMF_IDR is permitted to have the same contents when read from either the Secure and Non-secure MPAM feature pages unless the register contents is different for Secure and Non-secure versions, when there must be separate registers in the Secure (MPAMF_IDR_s) and Non-secure (MPAMF_IDR_ns) MPAM feature pages.

MPAMF_IDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0000	MPAMF_IDR_s

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance

MPAM	MPAMF_BASE_ns	0x0000	MPAMF_IDR_ns

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMF_IMPL_IDR, MPAM Implementation-Specific Partitioning Feature Identification Register

The MPAMF_IMPL_IDR characteristics are:

Purpose

IndicatesThe MPAMF_IMPL_IDR is a 32-bit read-only register that indicates the implementation-defined partitioning and monitoring features and parameters of the MSC. MPAMF_IMPL_IDR_s indicates implementation-defined partitioning and monitoring features accessed from the Secure MPAM feature page. MPAMF_IMPL_IDR_ns indicates those accessed from the Non-secure MPAM feature page.

Configuration

The power domain of MPAMF_IMPL_IDR is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_IMPL_IDR == 1. Otherwise, direct accesses to MPAMF_IMPL_IDR are RES0.

Attributes

MPAMF_IMPL_IDR is a 32-bit register.

Field descriptions

The MPAMF_IMPL_IDR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
IMPLEMENTATION DEFINEDIMP DEF																															

IMPLEMENTATIONIMP DEFINEDDEF, bits [31:0]

IMPLEMENTATION DEFINED.

All 32 bits of this register are available to be used as the implementer sees fit to indicate the presence of implementation-defined MPAM features in this MSC and to give additional implementation-specific read-only information about the parameters of implementation-specific MPAM features to software.

Accessing the MPAMF_IMPL_IDR

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMF_IMPL_IDR is read-only.

MPAMF_IMPL_IDR must be readable from the Non-secure and Secure MPAM feature pages.

MPAMF_IMPL_IDR is permitted to have the same contents when read from either the Secure and Non-secure MPAM feature pages unless the register contents is different for Secure and Non-secure versions, when there must be separate registers in the Secure (MPAMF_IMPL_IDR_s) and Non-secure (MPAMF_IMPL_IDR_ns) MPAM feature pages.

MPAMF_IMPL_IDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance

MPAM	MPAMF_BASE_s	0x0028	MPAMF_IMPL_IDR_s

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0028	MPAMF_IMPL_IDR_ns

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMF_MBW_IDR, MPAM Memory Bandwidth Partitioning Identification Register

The MPAMF_MBW_IDR characteristics are:

Purpose

IndicatesThe MPAMF_MBW_IDR is a 32-bit read-only register that indicates which MPAM bandwidth partitioning features are present on this MSC. MPAMF_MBW_IDR_s indicates bandwidth partitioning features accessed from the Secure MPAM feature page. MPAMF_MBW_IDR_ns indicates bandwidth partitioning features accessed from the Non-secure MPAM feature page.

Configuration

The power domain of MPAMF_MBW_IDR is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MBW_PART == 1. Otherwise, direct accesses to MPAMF_MBW_IDR are RES0.

Attributes

MPAMF_MBW_IDR is a 32-bit register.

Field descriptions

The MPAMF_MBW_IDR bit assignments are:

31	30:29	28:27	26:25	24:23	22:21	20:19	18:17	16	15	14	13	12	11	10	9:8	7:6	5:4	3:2	1:0
RES0	BWPBM_WD								RES0	WINDWR	HAS_PROP	HAS_PBM	HAS_MAX	HAS_MIN	RES0			BWA_WD	

Bits [31:29]

Reserved, RES0.

BWPBM_WD, bits [28:16]

Bandwidth portion bitmap width.

The number of bandwidth portion bits in MPAMCFG_MBW_PBM.BWPBM.

This field must contain a value from 1 to 4096, inclusive. Values greater than 32 require a group of 32-bit registers to access the BWPBM, up to 128 if BWPBM_WD is the largest value.

Bit [15]

Reserved, RES0.

WINDWR, bit [14]

Indicates the bandwidth accounting period register is writable.

WINDWR	Meaning
0b0	The bandwidth accounting period is readable from MPAMCFG_MBW_WINWD which might be fixed or vary due to clock rate reconfiguration of the memory channel or memory controller.
0b1	The bandwidth accounting width is readable and writable per partition in MPAMCFG_MBW_WINWD.

HAS_PROP, bit [13]

Indicates that this MSC implements proportional stride bandwidth partitioning and the MPAMCFG_MBW_PROP register.

HAS_PROP	Meaning
0b0	There is no memory bandwidth proportional stride control and no MPAMCFG_MBW_PROP register.
0b1	The MPAMCFG_MBW_PROP register exists and the proportional stride memory bandwidth allocation scheme is supported.

HAS_PBM, bit [12]

Indicates that this MSC implements bandwidth portion partitioning and the MPAMCFG_MBW_PBM register.

HAS_PBM	Meaning
0b0	There is no memory bandwidth portion control and no MPAMCFG_MBW_PBM register.
0b1	The MPAMCFG_MBW_PBM register exists and the memory bandwidth portion allocation scheme exists.

HAS_MAX, bit [11]

Indicates that this MSC implements maximum bandwidth partitioning and the MPAMCFG_MBW_MAX register.

HAS_MAX	Meaning
0b0	There is no maximum memory bandwidth control and no MPAMCFG_MBW_MAX register.
0b1	The MPAMCFG_MBW_MAX register exists and the maximum memory bandwidth allocation scheme is supported.

HAS_MIN, bit [10]

Indicates that this MSC implements minimum bandwidth partitioning.

HAS_MIN	Meaning
0b0	There is no minimum memory bandwidth control and no MPAMCFG_MBW_MIN register.
0b1	The MPAMCFG_MBW_MIN register exists and the minimum memory bandwidth allocation scheme is supported.

Bits [9:6]

Reserved, RES0.

BWA_WD, bits [5:0]

Number of implemented bits in the bandwidth allocation fields: MIN, MAX and STRIDE. See MPAMCFG_MBW_MIN, MPAMCFG_MBW_MAX and MPAMCFG_MBW_PROP.

This field must have a value from 1 to 16, inclusive.

Accessing the MPAMF_MBW_IDR

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMF_MBW_IDR is read-only.

MPAMF_MBW_IDR must be readable from the Non-secure and Secure MPAM feature pages.

MPAMF_MBW_IDR is permitted to have the same contents when read from either the Secure and Non-secure MPAM feature pages unless the register contents is different for Secure and Non-secure versions, when there must be separate registers in the Secure (MPAMF_MBW_IDR_s) and Non-secure (MPAMF_MBW_IDR_ns) MPAM feature pages.

MPAMF_MBW_IDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0040	MPAMF_MBW_IDR_s

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0040	MPAMF_MBW_IDR_ns

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMF_MBWUMON_IDR, MPAM Features Memory Bandwidth Usage Monitoring ID register

The MPAMF_MBWUMON_IDR characteristics are:

Purpose

IndicatesThe ~~MPAMF_MBWUMON_IDR is a 32-bit read-only register that indicates~~ the number of memory bandwidth usage monitors for this MSC. ThisMPAMF_MBWUMON_IDR_s register also indicates several~~the~~ propertiesnumber of theSecure MBWU~~memory~~ monitors,~~bandwidth~~ includingusage whether~~monitor~~ theyinstances. supportMPAMF_MBWUMON_IDR_ns capture,~~indicates~~ scalingthe or~~number~~ longof counters.~~Non-secure memory bandwidth usage monitor instances.~~

MPAMF_MBWUMON_IDR_s indicates the number of Secure memory bandwidth usage monitor instances.
MPAMF_MBWUMON_IDR_ns indicates the number of Non-secure memory bandwidth usage monitor instances.

Configuration

The power domain of MPAMF_MBWUMON_IDR is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1 and MPAMF_MSMON_IDR.MSMON_MBWU == 1. Otherwise, direct accesses to MPAMF_MBWUMON_IDR are RES0.

Attributes

MPAMF_MBWUMON_IDR is a 32-bit register.

Field descriptions

The MPAMF_MBWUMON_IDR bit assignments are:

31	30	29	28 27 26 25 24 23 22 21	20 19 18 17 16	15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 0
HAS_CAPTURE	HAS_LONG	LWD	RES0	SCALE	NUM_MON

HAS_CAPTURE, bit [31]

The implementation of this MSC supports copying an MSMON_MBWU to the corresponding MSMON_MBWU_CAPTURE on a capture event.

HAS_CAPTURE	Meaning
0b0	MSMON_MBWU_CAPTURE is not implemented and there is no support for capture events in the MBWU monitor.
0b1	The MSMON_MBWU_CAPTURE register is implemented and the MBWU monitor supports the capture event behavior.

HAS_LONG, bit [30]

When ARMv8.6-MPAM is implemented:

Indicates whether MSMON_MBWU_L is implemented.

If HAS_CAPTURE == 1, indicates whether MSMON_MBWU_L_CAPTURE is implemented.

HAS_LONG	Meaning
0b0	Does not implement MSMON_MBWU_L or MSMON_MBWU_L_CAPTURE.
0b1	Implements MSMON_MBWU_L. If HAS_CAPTURE == 1, MSMON_MBWU_L_CAPTURE is also implemented.

Otherwise:

Reserved, RES0.

LWD, bit [29]

When ARMv8.6-MPAM is implemented:

Long register VALUE width.

If MPAMF_MBWUMON_IDR.HAS_LONG == 0, MPAMF_MBWUMON_IDR.LWD must also be 0.

LWD	Meaning
0b0	If MPAMF_MBWUMON_IDR.HAS_LONG == 1, MSMON_MBWU_L has 44-bit VALUE field in bits [43:0]. Bits [62:44] are RES0. If HAS_LONG == 1 and MSMON_MBWU_IDR.HAS_CAPTURE == 1, MSMON_MBWU_L_CAPTURE also has 44-bit VALUE field in bits [43:0].
0b1	MSMON_MBWU_L has 63-bit VALUE field in bits [62:0]. If MPAMF_MBWUMON_IDR.HAS_CAPTURE == 1, MSMON_MBWU_L_CAPTURE also has 63-bit VALUE field in bits [62:0].

Otherwise:

Reserved, RES0.

Bits [28:21]

Reserved, RES0.

SCALE, bits [20:16]

Scaling of MSMON_MBWU.VALUE in bits. If scaling is enabled by MSMON_CFG_MBWU_CTL.SCLEN, the byte count in the VALUE field has been shifted by SCALE bits to the right.

SCALE	Meaning
0b00000	Scaling is not implemented.
0bxxxxx	Other values are right shift count when scaling is enabled.

NUM_MON, bits [15:0]

The number of memory bandwidth usage monitors implemented in this MSC.

Accessing the MPAMF_MBWUMON_IDR

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMF_MBWUMON_IDR is read-only.

MPAMF_MBWUMON_IDR must be readable from the Non-secure and Secure MPAM feature pages.

MPAMF_MBWUMON_IDR is permitted to have the same contents when read from either the Secure and Non-secure MPAM feature pages unless the register contents is different for Secure and Non-secure versions, when there must be

separate registers in the Secure (MPAMF_MBWUMON_IDR_s) and Non-secure (MPAMF_MBWUMON_IDR_ns) MPAM feature pages.

MPAMF_MBWUMON_IDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0090	MPAMF_MBWUMON_IDR_s

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0090	MPAMF_MBWUMON_IDR_ns

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMF_MSMON_IDR, MPAM Resource Monitoring Identification Register

The MPAMF_MSMON_IDR characteristics are:

Purpose

IndicatesThe MPAMF_MSMON_IDR is a 32-bit read-only register that indicates which MPAM monitoring features are present on this MSC. MPAMF_MSMON_IDR_s indicates Secure monitoring features. MPAMF_MSMON_IDR_ns indicates Non-secure monitoring features.

Configuration

The power domain of MPAMF_MSMON_IDR is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1. Otherwise, direct accesses to MPAMF_MSMON_IDR are RES0.

Attributes

MPAMF_MSMON_IDR is a 32-bit register.

Field descriptions

The MPAMF_MSMON_IDR bit assignments are:

31	30:18	17	16	15:0
HAS_LOCAL_CAPT_EVNT	RES0	MSMON_MBWU	MSMON_CSU	RES0

HAS_LOCAL_CAPT_EVNT, bit [31]

Has local capture event generator. Indicates whether this MSC has the MPAM local capture event generator and the MSMON_CAPT_EVNT register.

HAS_LOCAL_CAPT_EVNT	Meaning
0b0	Does not support MPAM local capture event generator or MSMON_CAPT_EVNT.
0b1	Supports the MPAM local capture event generator and the MSMON_CAPT_EVNT register.

Bits [30:18]

Reserved, RES0.

MSMON_MBWU, bit [17]

Memory bandwidth usage monitoring. Indicates whether this MSC has MPAM monitoring for Memory Bandwidth Usage by PARTID and PMG and uses the following bandwidth usage registers:PMG.

- MPAMF_MBWUMON_IDR, MSMON_CFG_MBWU_CTL, MSMON_CFG_MBWU_FLT, MSMON_MBWU.
- The optional MSMON_MBWU_CAPTURE.

MSMON_MBWU	Meaning
0b0	Does not have monitoring for memory bandwidth usage and~~or~~ does not use the bandwidth usage registers.~~MPAMF_MBWUMON_IDR, MSMON_CFG_MBWU_CTL, MSMON_CFG_MBWU_FLT, MSMON_MBWU or MSMON_MBWU_CAPTURE registers.~~
0b1	Has monitoring of memory bandwidth~~bandwdith~~ usage and uses the bandwidth usage registers.~~MPAMF_MBWUMON_IDR, MSMON_CFG_MBWU_CTL, MSMON_CFG_MBWU_FLT, MSMON_MBWU and optional MSMON_MBWU_CAPTURE registers.~~

MSMON_CSU, bit [16]

Cache storage usage monitoring. Indicates whether this MSC has MPAM monitoring of cache storage usage by PARTID and PMG.

MSMON_CSU	Meaning
0b0	Does not have monitoring for cache storage usage or the MPAMF_CSUMON_IDR, MSMON_CFG_CSU_CTL, MSMON_CFG_CSU_FLT, MSMON_CSU or MSMON_CSU_CAPTURE registers.
0b1	Has monitoring of cache storage usage and the MPAMF_CSUMON_IDR, MSMON_CFG_CSU_CTL, MSMON_CFG_CSU_FLT, MSMON_CSU and optional MSMON_CSU_CAPTURE registers.

Bits [15:0]

Reserved, RES0.

Accessing the MPAMF_MSMON_IDR

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMF_MSMON_IDR is read-only.

MPAMF_MSMON_IDR must be readable from the Non-secure and Secure MPAM feature pages.

MPAMF_MSMON_IDR is permitted to have the same contents when read from either the Secure and Non-secure MPAM feature pages unless the register contents is different for Secure and Non-secure versions, when there must be separate registers in the Secure (MPAMF_MSMON_IDR_s) and Non-secure (MPAMF_MSMON_IDR_ns) MPAM feature pages.

MPAMF_MSMON_IDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0080	MPAMF_MSMON_IDR_s

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0080	MPAMF_MSMON_IDR_ns

Accesses on this interface are **RO**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMF_PARTID_NRW_IDR, MPAM PARTID Narrowing ID register

The MPAMF_PARTID_NRW_IDR characteristics are:

Purpose

Indicates~~The MPAMF_PARTID_NRW_IDR is a 32-bit read-only register that indicates~~ the largest internal PARTID for this MSC. MPAMF_PARTID_NRW_IDR_s indicates the largest Secure internal PARTID. MPAMF_PARTID_NRW_IDR_ns indicates the largest Non-secure internal PARTID.

Configuration

The power domain of MPAMF_PARTID_NRW_IDR is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_PARTID_NRW == 1. Otherwise, direct accesses to MPAMF_PARTID_NRW_IDR are RES0.

Attributes

MPAMF_PARTID_NRW_IDR is a 32-bit register.

Field descriptions

The MPAMF_PARTID_NRW_IDR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																INTPARTID_MAX															

Bits [31:16]

Reserved, RES0.

INTPARTID_MAX, bits [15:0]

The largest intPARTID supported in this MSC.

Accessing the MPAMF_PARTID_NRW_IDR

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMF_PARTID_NRW_IDR is read-only.

MPAMF_PARTID_NRW_IDR must be readable from the Non-secure and Secure MPAM feature pages.

MPAMF_PARTID_NRW_IDR is permitted to have the same contents when read from either the Secure and Non-secure MPAM feature pages unless the register contents is different for Secure and Non-secure versions, when there must be separate registers in the Secure (MPAMF_PARTID_NRW_IDR_s) and Non-secure (MPAMF_PARTID_NRW_IDR_ns) MPAM feature pages.

MPAMF_PARTID_NRW_IDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance

MPAM	MPAMF_BASE_s	0x0050	MPAMF_PARTID_NRW_IDR_s

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0050	MPAMF_PARTID_NRW_IDR_ns

Accesses on this interface are **RO**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MPAMF_PRI_IDR, MPAM Priority Partitioning Identification Register

The MPAMF_PRI_IDR characteristics are:

Purpose

Indicates~~The MPAMF_PRI_IDR is a 32-bit read-only register that indicates~~ which MPAM priority partitioning features are present on this MSC. MPAMF_PRI_IDR_s indicates priority partitioning features accessed from the Secure MPAM feature page. MPAMF_PRI_IDR_ns indicates priority partitioning features accessed from the Non-secure MPAM feature page.

Configuration

The power domain of MPAMF_PRI_IDR is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_PRI_PART == 1. Otherwise, direct accesses to MPAMF_PRI_IDR are RES0.

Attributes

MPAMF_PRI_IDR is a 32-bit register.

Field descriptions

The MPAMF_PRI_IDR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0						DSPRI_WD						RES0		DSPRI_0_IS_LOW	HAS_DSPRI	RES0						INTPRI_WD					RES0			INTPRI_0_IS_LOW	HAS_INTP

Bits [31:26]

Reserved, RES0.

DSPRI_WD, bits [25:20]

Number of implemented bits in the downstream priority field (DSPRI) of MPAMCFG_PRI.

If HAS_DSPRI == 1, this field must contain a value from 1 to 32, inclusive.

If HAS_DSPRI == 0, this field must be 0.

Bits [19:18]

Reserved, RES0.

DSPRI_0_IS_LOW, bit [17]

Indicates whether 0 in MPAMCFG_PRI.DSPRI is the lowest or the highest priority.

DSPRI_0_IS_LOW	Meaning
0b0	In the MPAMCFG_PRI.DSPRI field, a value of 0 means the highest priority.
0b1	In the MPAMCFG_PRI.DSPRI field, a value of 0 means the lowest priority.

HAS_DSPRI, bit [16]

Indicates that this MSC implements the DSPRI field in the MPAMCFG_PRI register.

HAS_DSPRI	Meaning
0b0	This MSC supports priority partitioning, but does not implement a downstream priority (DSPRI) field in the MPAMCFG_PRI register.
0b1	This MSC supports downstream priority partitioning and implements the downstream priority (DSPRI) field in the MPAMCFG_PRI register.

Bits [15:10]

Reserved, RES0.

INTPRI_WD, bits [9:4]

Number of implemented bits in the internal priority field (INTPRI) in the MPAMCFG_PRI register.

If HAS_INTPRI == 1, this field must contain a value from 1 to 32, inclusive.

If HAS_INTPRI == 0, this field must be 0.

Bits [3:2]

Reserved, RES0.

INTPRI_0_IS_LOW, bit [1]

Indicates whether 0 in MPAMCFG_PRI.INTPRI is the lowest or the highest priority.

INTPRI_0_IS_LOW	Meaning
0b0	In the MPAMCFG_PRI.INTPRI field, a value of 0 means the highest priority.
0b1	In the MPAMCFG_PRI.INTPRI field, a value of 0 means the lowest priority.

HAS_INTPRI, bit [0]

Indicates that this MSC implements the INTPRI field in the MPAMCFG_PRI register.

HAS_INTPRI	Meaning
0b0	This MSC supports priority partitioning, but does not implement the internal priority (INTPRI) field in the MPAMCFG_PRI register.
0b1	This MSC supports internal priority partitioning and implements the internal priority (INTPRI) field in the MPAMCFG_PRI register.

Accessing the MPAMF_PRI_IDR

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MPAMF_PRI_IDR is read-only.

MPAMF_PRI_IDR must be readable from the Non-secure and Secure MPAM feature pages.

MPAMF_PRI_IDR is permitted to have the same contents when read from either the Secure and Non-secure MPAM feature pages unless the register contents is different for Secure and Non-secure versions, when there must be separate registers in the Secure (MPAMF_PRI_IDR_s) and Non-secure (MPAMF_PRI_IDR_ns) MPAM feature pages.

MPAMF_PRI_IDR can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0048	MPAMF_PRI_IDR_s

Accesses on this interface are **RO**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0048	MPAMF_PRI_IDR_ns

Accesses on this interface are **RO**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MSMON_CAPT_EVNT, MPAM Capture Event Generation Register

The MSMON_CAPT_EVNT characteristics are:

Purpose

GeneratesMSMON_CAPT_EVNT is a 32-bit read-write register that generates a local capture event when written with bit[0] as 1. MSMON_CAPT_EVNT_s generates local capture events for Secure monitors only or for Secure and Non-secure monitors. MSMON_CAPT_EVNT_ns generates local capture events for Non-secure monitors only.

Configuration

The power domain of MSMON_CAPT_EVNT is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1 and MPAMF_MSMON_IDR.HAS_LOCAL_CAPT_EVNT == 1. Otherwise, direct accesses to MSMON_CAPT_EVNT are RES0.

Attributes

MSMON_CAPT_EVNT is a 32-bit register.

Field descriptions

The MSMON_CAPT_EVNT bit assignments are:



Bits [31:2]

Reserved, RES0.

ALL, bit [1]

In the Secure instance of this register, if ALL written as 1 and NOW is also written as 1, signal a capture event to Secure and Non-secure monitor instances in this MSC that are configured with CAPT_EVNT = 7.

If written as 0 and NOW is written as 1, signal a capture event to Secure monitor instances in this MSC that are configured with CAPT_EVNT = 7.

In the Non-secure instance of this register, this bit is RAZ/WI.

This bit always reads as zero.

ALL	Meaning
0b0	Send capture event to Secure monitors only.
0b1	Send capture event to both Secure and Non-secure monitors.

NOW, bit [0]

When written as 1, this bit causes an event to all monitors in this MSC with CAPT_EVNT set to the value of 7.

When this bit is written as 0, no event is signaled.

This bit always reads as zero.

Accessing the MSMON_CAPT_EVNT

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MSMON_CAPT_EVNT_s must be accessible from the Secure MPAM feature page. MSMON_CAPT_EVENT_ns must be accessible from the Non-secure MPAM feature page.

The two instances of MSMON_CAPT_EVNT must be separate registers. The Secure instance (MSMON_CAPT_EVNT_s) can generate capture events for both Secure and Non-secure PARTID monitors, and the Non-secure instance (MSMON_CAPT_EVNT_ns) can generate capture events for Non-secure PARTID monitors only.

MSMON_CAPT_EVNT can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0808	MSMON_CAPT_EVNT_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0808	MSMON_CAPT_EVNT_ns

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MSMON_CFG_CSU_CTL, MPAM Memory System Monitor Configure Cache Storage Usage Monitor Control Register

The MSMON_CFG_CSU_CTL characteristics are:

Purpose

Controls~~MSMON_CFG_CSU_CTL is a 32-bit read-write register that controls~~ the CSU monitor selected by MSMON_CFG_MON_SEL. MSMON_CFG_CSU_CTL_s controls the Secure cache storage usage monitor instance selected by the Secure instance of MSMON_CFG_MON_SEL. MSMON_CFG_CSU_CTL_ns controls Non-secure cache storage usage monitor instance selected by the Non-secure instance of MSMON_CFG_MON_SEL.

Configuration

The power domain of MSMON_CFG_CSU_CTL is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1 and MPAMF_MSMON_IDR.MSMON_CSU == 1. Otherwise, direct accesses to MSMON_CFG_CSU_CTL are RES0.

Attributes

MSMON_CFG_CSU_CTL is a 32-bit register.

Field descriptions

The MSMON_CFG_CSU_CTL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14
EN	CAPT_EVNT			CAPT_RESET	OFLOW_STATUS	OFLOW_INTR	OFLOW_FRZ	SUBTYPE				RES0		MATCH_PMG	MATCH_PARTID		

EN, bit [31]

Enabled.

EN	Meaning
0b0	The monitor instance is disabled and must not collect any information.
0b1	The monitor instance is enabled to collect information according to the configuration of the instance.

CAPT_EVNT, bits [30:28]

Capture event selector.

Select the event that triggers capture from the following:

CAPT_EVNT	Meaning
0b000	No capture event is triggered.
0b001	External capture event 1 (optional but recommended)
0b010	External capture event 2 (optional)
0b011	External capture event 3 (optional)
0b100	External capture event 4 (optional)
0b101	External capture event 5 (optional)
0b110	External capture event 6 (optional)
0b111	Capture occurs when a MSMON_CAPT_EVNT register in this MSC is written and causes a capture event for the security state of this monitor. (optional)

The values marked as optional indicate capture event sources that can be omitted in an implementation. Those values representing non-implemented event sources must~~should~~ not trigger a capture event.

If capture is not implemented for the CSU monitor type as indicated by MPAMF_CSUMON_IDR.HAS_CAPTURE = 0, this field is RAZ/WI.

CAPT_RESET, bit [27]

Reset after capture.

Controls whether the value of MSMON_CSU is reset to zero immediately after being copied to MSMON_CSU_CAPTURE.

CAPT_RESET	Meaning
0b0	Monitor is not reset on capture.
0b1	Monitor is reset on capture.

If capture is not implemented for the CSU monitor type as indicated by MPAMF_CSUMON_IDR.HAS_CAPTURE = 0, this field is RAZ/WI.

Because the CSU monitor type produces a measurement rather than a count, it might not make sense to ever reset the value after a capture. If there is no reason to ever reset a CSU monitor, this field is RAZ/WI.

OFLOW_STATUS, bit [26]

Overflow status.

Indicates whether the value of MSMON_CSU has overflowed.

OFLOW_STATUS	Meaning
0b0	No overflow has occurred.
0b1	At least one overflow has occurred since this bit was last written to zero.

If overflow is not possible for a CSU monitor in the implementation, this field is RAZ/WI.

OFLOW_INTR, bit [25]

Overflow Interrupt.

Controls whether an overflow interrupt is generated when the value of MSMON_CSU has overflowed.

OFLOW_INTR	Meaning
0b0	No interrupt is signaled on an overflow of MSMON_CSU.
0b1	On overflow, an implementation-specific interrupt is signaled.

If OFLOW_INTR is not supported by the implementation, this field is RAZ/WI.

OFLOW_FRZ, bit [24]

Freeze Monitor on Overflow.

Controls whether the value of MSMON_CSU freezes on an overflow.

OFLOW_FRZ	Meaning
0b0	Monitor count wraps on overflow.
0b1	Monitor count freezes on overflow. The frozen value might be 0 or another value if the monitor overflowed with an increment larger than 1.

If overflow is not possible for a CSU monitor in the implementation, this field is RAZ/WI.

SUBTYPE, bits [23:20]

Subtype.

A monitor can have other event matching criteria.

This field is not currently used for CSU monitors, but reserved for future use.

This field is RAZ/WI.

Bits [19:18]

Reserved, RES0.

MATCH_PMG, bit [17]

Match PMG.

Controls whether the monitor measures only storage used with PMG matching MSMON_CFG_CSU_FLT.PMG.

MATCH_PMG	Meaning
0b0	The monitor measures storage used with any PMG value.
0b1	The monitor only measures storage used with the PMG value matching MSMON_CFG_CSU_FLT.PMG.

If MATCH_PMG == 1 and MATCH_PARTID == 0, it is CONSTRAINED UNPREDICTABLE whether the monitor instance:

- Measures the storage used with matching PMG and with any PARTID.
- Measures no storage usage, that is, MSMON_CSU.VALUE is zero.
- Measures the storage used with matching PMG and PARTID, that is, treats MATCH_PARTID as == 1.

MATCH_PARTID, bit [16]

Match PARTID.

Controls whether the monitor measures only storage used with PARTID matching MSMON_CFG_CSU_FLT.PARTID.

MATCH_PARTID	Meaning
0b0	The monitor measures storage used with any PARTID value.
0b1	The monitor only measures storage used with the PARTID value matching MSMON_CFG_CSU_FLT.PARTID.

Bits [15:8]

Reserved, RES0.

TYPE, bits [7:0]

Monitor Type Code.

Constant type indicating the type of the monitor.

Read-only.

CSU monitor is TYPE = 0x43.

Accessing the MSMON_CFG_CSU_CTL

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MSMON_CFG_CSU_CTL_s must be accessible from the Secure MPAM feature page. MSMON_CFG_CSU_CTL_ns must be accessible from the Non-secure MPAM feature page.

MSMON_CFG_CSU_CTL_s and MSMON_CFG_CSU_CTL_ns must be separate registers. The Secure instance (MSMON_CFG_CSU_CTL_s) accesses the cache storage usage monitor controls used for Secure PARTIDs, and the Non-secure instance (MSMON_CFG_CSU_CTL_ns) accesses the cache storage usage monitor controls used for Non-secure PARTIDs.

MSMON_CFG_CSU_CTL can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0818	MSMON_CFG_CSU_CTL_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0818	MSMON_CFG_CSU_CTL_ns

Accesses on this interface are **RW**.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707~~~~

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MSMON_CFG_CSU_FLT, MPAM Memory System Monitor Configure Cache Storage Usage Monitor Filter Register

The MSMON_CFG_CSU_FLT characteristics are:

Purpose

Configures~~MSMON_CFG_CSU_FLT is a 32-bit read-write register that sets~~ PARTID and PMG to measure or count in the CSU monitor selected by MSMON_CFG_MON_SEL. MSMON_CFG_CSU_FLT_s sets filter conditions for the Secure cache storage usage monitor instance selected by the Secure instance of MSMON_CFG_MON_SEL. MSMON_CFG_CSU_CTL_ns sets filter conditions for the Non-secure cache storage usage monitor instance selected by the Non-secure instance of MSMON_CFG_MON_SEL.

Configuration

The power domain of MSMON_CFG_CSU_FLT is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1 and MPAMF_MSMON_IDR.MSMON_CSU == 1. Otherwise, direct accesses to MSMON_CFG_CSU_FLT are RES0.

Attributes

MSMON_CFG_CSU_FLT is a 32-bit register.

Field descriptions

The MSMON_CFG_CSU_FLT bit assignments are:

31 30 29 28 27 26 25 24	23 22 21 20 19 18 17 16	15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 0
RES0	PMG	PARTID

Bits [31:24]

Reserved, RES0.

PMG, bits [23:16]

Performance monitoring group to filter cache storage usage monitoring.

If MSMON_CFG_CSU_CTL.MATCH_PMG == 0, this field is not used to match cache storage to a PMG and the contents of this field is ignored.

If MSMON_CFG_CSU_CTL.MATCH_PMG == 1 and MSMON_CFG_CSU_CTL.MATCH_PARTID == 1, the monitor instance selected by MSMON_CFG_MON_SEL measures or counts cache storage labeled with PMG equal to this field and PARTID equal to the PARTID field.

If MSMON_CFG_CSU_CTL.MATCH_PMG == 1 and MSMON_CFG_CSU_CTL.MATCH_PARTID == 0, the behavior of the monitor instance selected by MSMON_CFG_MON_SEL is CONSTRAINED UNPREDICTABLE. See MSMON_CFG_CSU_CTL.MATCH_PMG for more information.

PARTID, bits [15:0]

Partition ID to filter cache storage usage monitoring.

If MSMON_CFG_CSU_CTL.MATCH_PARTID == 0 and MSMON_CFG_CSU_CTL.MATCH_PMG == 0, the monitor measures all allocated cache storage.

If MSMON_CFG_CSU_CTL.MATCH_PARTID == 0 and MSMON_CFG_CSU_CTL.MATCH_PMG == 1, the behavior of the monitor is CONSTRAINED UNPREDICTABLE. See the description of MSMON_CFG_CSU_CTL.MATCH_PMG.

If MSMON_CFG_CSU_CTL.MATCH_PARTID == 1 and MSMON_CFG_CSU_CTL.MATCH_PMG == 0, the monitor selected by MSMON_CFG_MON_SEL measures or counts cache storage labeled with PARTID equal to this field.

If MSMON_CFG_CSU_CTL.MATCH_PARTID == 1 and MSMON_CFG_CSU_CTL.MATCH_PMG == 1, the monitor selected by MSMON_CFG_MON_SEL measures or counts cache storage labeled with PARTID equal to this field and PMG equal to the PMG field.

Accessing the MSMON_CFG_CSU_FLT

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MSMON_CFG_CSU_FLT_s must be accessible from the Secure MPAM feature page. MSMON_CFG_CSU_FLT_ns must be accessible from the Non-secure MPAM feature page.

MSMON_CFG_CSU_FLT_s and MSMON_CFG_CSU_FLT_ns must be separate registers. The Secure instance (MSMON_CFG_CSU_FLT_s) accesses the PARTID and PMG matching for a cache storage usage monitor used for Secure PARTIDs, and the Non-secure instance (MSMON_CFG_CSU_FLT_ns) accesses the PARTID and PMG matching for a cache storage usage monitor used for Non-secure PARTIDs.

MSMON_CFG_CSU_FLT can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0810	MSMON_CFG_CSU_FLT_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0810	MSMON_CFG_CSU_FLT_ns

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MSMON_CFG_MBWU_CTL, MPAM Memory System Monitor Configure Memory Bandwidth Usage Monitor Control Register

The MSMON_CFG_MBWU_CTL characteristics are:

Purpose

Controls the MBWU monitor selected by MSMON_CFG_MON_SEL. MSMON_CFG_MBWU_CTL_s controls the Secure memory bandwidth usage monitor instance selected by the Secure instance of MSMON_CFG_MON_SEL. MSMON_CFG_MBWU_CTL_ns controls Non-secure memory bandwidth usage monitor instance selected by the Non-secure instance of MSMON_CFG_MON_SEL.

Configuration

The power domain of MSMON_CFG_MBWU_CTL is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1 and MPAMF_MSMON_IDR.MSMON_MBWU == 1. Otherwise, direct accesses to MSMON_CFG_MBWU_CTL are RES0.

Attributes

MSMON_CFG_MBWU_CTL is a 32-bit register.

Field descriptions

The MSMON_CFG_MBWU_CTL bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16
EN	CAPT_EVNT			CAPT_RESET	OFLOW_STATUS	OFLOW_INTR	OFLOW_FRZ	SUBTYPE				SCLEN	RES0	MATCH_PMG	MATCH_PART

EN, bit [31]

Enabled.

EN	Meaning
0b0	The monitor instance is disabled and must not collect any information.
0b1	The monitor instance is enabled to collect information according to the configuration of the instance.

CAPT_EVNT, bits [30:28]

Capture event selector.

When the selected capture event occurs, MSMON_MBWU of the monitor instance is copied to MSMON_MBWU_CAPTURE of the same instance. If the long counter is also implemented, MSMON_MBWU_L is also copied to MSMON_MBWU_L_CAPTURE.

Select the event that triggers capture from the following:

CAPT_EVNT	Meaning
0b000	No capture event is triggered.
0b001	External capture event 1 (optional but recommended)
0b010	External capture event 2 (optional)
0b011	External capture event 3 (optional)
0b100	External capture event 4 (optional)
0b101	External capture event 5 (optional)
0b110	External capture event 6 (optional)
0b111	Capture occurs when a MSMON_CAPT_EVNT register in this MSC is written and causes a capture event for the security state of this monitor. (optional)

The values marked as optional indicate capture event sources that can be omitted in an implementation. Those values representing non-implemented event sources must~~should~~ not trigger a capture event.

If capture is not implemented for the MBWU monitor type as indicated by MPAMF_MBWUMON_IDR.HAS_CAPTURE = 0, this field is RAZ/WI.

CAPT_RESET, bit [27]

Reset MSMON_MBWU.VALUE after capture.

Controls whether the VALUE field of the monitor instance is reset to zero immediately after being copied to the corresponding capture register.

CAPT_RESET	Meaning
0b0	MSMON_MBWU.VALUE field of the monitor instance is not reset on capture.
0b1	MSMON_MBWU.VALUE field of the monitor instance is reset on capture.

If capture is not implemented for the MBWU monitor type as indicated by MPAMF_MBWUMON_IDR.HAS_CAPTURE = 0, this field is RAZ/WI.

This control bit affects both MSMON_MBWU and MSMON_MBWU_L in implementations that include MSMON_MBWU_L.

OFLOW_STATUS, bit [26]

Overflow status.

Indicates whether the value of MSMON_MBWU has overflowed.

OFLOW_STATUS	Meaning
0b0	MSMON_MBWU has not overflowed.
0b1	MSMON_MBUW has overflowed at least once since this bit was last written to zero.

If overflow is not possible for a MBWU monitor in the implementation, this field is RAZ/WI.

OFLOW_INTR, bit [25]

Overflow status of the MSMON_MBWU_L instance.

Indicates that the value of MSMON_MBWU overflow has overflowed.

OFLOW_INTR	Meaning
0b0	No interrupt is signaled on an overflow of MSMON_MBWU.
0b1	An implementation-specific interrupt is signaled on an overflow of MSMON_MBWU.

OFLOW_FRZ, bit [24]

Freeze monitor instance on overflow.

Controls whether MSMON_MBWU.VALUE field of the monitor instance freezes on an overflow.

OFLOW_FRZ	Meaning
0b0	MSMON_MBWU.VALUE field of the monitor instance wraps on overflow.
0b1	MSMON_MBWU.VALUE field of the monitor instance freezes on overflow. If the increment that caused the overflow was 1, the frozen value is the post-increment value of 0. If the increment that caused the overflow was larger than 1, the frozen value of the monitor might be 0 or a larger value less than the final increment.

If overflow is not possible for the instance of the MBWU monitor in the implementation, this field is RAZ/WI.

This control bit affects both MSMON_MBWU and MSMON_MBWU_L in implementations that include MSMON_MBWU_L.

SUBTYPE, bits [23:20]

Subtype.

A monitor can have other event matching criteria.

This field is not currently used for MBWU monitors, but reserved for future use.

This field is RAZ/WI.

SCLEN, bit [19]

MSMON_MBWU.VALUE Scaling Enable.

Enables scaling of MSMON_MBWU.VALUE by MPAMF_MBWUMON_IDR.SCALE.

SCLEN	Meaning
0b0	MSMON_MBWU.VALUE has bytes counted by the monitor instance.
0b1	MSMON_MBWU.VALUE has bytes counted by the monitor instance, shifted right by MPAMF_MBWUMON_IDR.SCALE.

Bit [18]

Reserved, RES0.

MATCH_PMG, bit [17]

Match PMG.

Controls whether the monitor instance only counts data transferred with PMG matching MSMON_CFG_MBWU_FLT.PMG.

MATCH_PMG	Meaning
0b0	The monitor instance counts data transferred with any PMG value.
0b1	The monitor instance only counts data transferred with the PMG value matching MSMON_CFG_MBWU_FLT.PMG.

MATCH_PARTID, bit [16]

Match PARTID.

Controls whether the monitor instance counts only data transferred with PARTID matching MSMON_CFG_MBWU_FLT.PARTID.

MATCH_PARTID	Meaning
0b0	The monitor instance counts data transferred with any PARTID value.
0b1	The monitor instance only counts data transferred with the PARTID value matching MSMON_CFG_MBWU_FLT.PARTID.

OFLOW_STATUS_L, bit [15]

When ARMv8.6-MPAM is implemented:

Overflow Status of the MSMON_MBWU_L instance.

Indicates whether an MPAM overflow interrupt is generated when the value of MSMON_MBWU_L has overflowed.

OFLOW_STATUS_L	Meaning
0b0	MSMON_MBWU_L has not overflowed.
0b1	MSMON_MBWU_L has overflowed at least once since this bit was last written to zero.

If MPAMF_MBWUMON_IDR.HAS_LONG == 0, this bit is RES0.

Otherwise:

Reserved, RES0.

OFLOW_INTR_L, bit [14]

When ARMv8.6-MPAM is implemented:

Overflow Interrupt for MSMON_MBWU_L.

Controls whether an MPAM overflow interrupt is generated when the value of MSMON_MBWU_L overflows.

OFLOW_INTR_L	Meaning
0b0	No interrupt is signaled on an overflow of MSMON_MBWU_L.
0b1	An implementation-specific interrupt is signalled on overflow of MSMON_MBWU_L.

If OFLOW_INTR is not supported by the implementation, this field is RAZ/WI.

If MPAMF_MBWUMON_IDR.HAS_LONG == 0, this bit is RES0.

Otherwise:

Reserved, RES0.

Bits [13:8]

Reserved, RES0.

TYPE, bits [7:0]

Monitor Type Code.

Constant type indicating the type of the monitor.

Read-only.

MBWU monitor is TYPE = 0x42.

Accessing the MSMON_CFG_MBWU_CTL

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MSMON_CFG_MBWU_CTL_s must be accessible from the Secure MPAM feature page. MSMON_CFG_MBWU_CTL_ns must be accessible from the Non-secure MPAM feature page.

MSMON_CFG_MBWU_CTL_s and MSMON_CFG_MBWU_CTL_ns must be separate registers. The Secure instance (MSMON_CFG_MBWU_CTL_s) accesses the memory bandwidth usage monitor controls used for Secure PARTIDs, and the Non-secure instance (MSMON_CFG_MBWU_CTL_ns) accesses the memory bandwidth usage monitor controls used for Non-secure PARTIDs.

MSMON_CFG_MBWU_CTL can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0828	MSMON_CFG_MBWU_CTL_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0828	MSMON_CFG_MBWU_CTL_ns

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MSMON_CFG_MBWU_FLT, MPAM Memory System Monitor Configure Memory Bandwidth Usage Monitor Filter Register

The MSMON_CFG_MBWU_FLT characteristics are:

Purpose

Controls~~MSMON_CFG_MBWU_FLT is a 32-bit read-write register that sets~~ PARTID and PMG to measure or count in the MBWU monitor selected by MSMON_CFG_MON_SEL. MSMON_CFG_MBWU_FLT_s sets filter conditions for the Secure memory bandwidth usage monitor instance selected by the Secure instance of MSMON_CFG_MON_SEL. MSMON_CFG_MBWU_CTL_ns sets filter conditions for the Non-secure memory bandwidth usage monitor instance selected by the Non-secure instance of MSMON_CFG_MON_SEL.

Configuration

The power domain of MSMON_CFG_MBWU_FLT is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1 and MPAMF_MSMON_IDR.MSMON_MBWU == 1. Otherwise, direct accesses to MSMON_CFG_MBWU_FLT are RES0.

Attributes

MSMON_CFG_MBWU_FLT is a 32-bit register.

Field descriptions

The MSMON_CFG_MBWU_FLT bit assignments are:



Bits [31:24]

Reserved, RES0.

PMG, bits [23:16]

Performance monitoring group to filter memory bandwidth usage monitoring.

If MSMON_CFG_MBWU_CTL.MATCH_PMG == 0, this field is not used to match memory bandwidth to a PMG and the contents of this field is ignored.

If MSMON_CFG_MBWU_CTL.MATCH_PMG == 1, the monitor selected by MSMON_CFG_MON_SEL measures or counts memory bandwidth labeled with PMG equal to this field.

PARTID, bits [15:0]

Partition ID to filter memory bandwidth usage monitoring.

If MSMON_CFG_MBWU_CTL.MATCH_PARTID == 0, this field is not used to match memory bandwidth to a PARTID and the contents of this field is ignored.

If MSMON_CFG_MBWU_CTL.MATCH_PARTID == 1, the monitor selected by MSMON_CFG_MON_SEL measures or counts memory bandwidth labeled with PARTID equal to this field.

Accessing the MSMON_CFG_MBWU_FLT

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MSMON_CFG_MBWU_FLT_s must be accessible from the Secure MPAM feature page. MSMON_CFG_MBWU_FLT_ns must be accessible from the Non-secure MPAM feature page.

MSMON_CFG_MBWU_FLT_s and MSMON_CFG_MBWU_FLT_ns must be separate registers. The Secure instance (MSMON_CFG_MBWU_FLT_s) accesses the PARTID and PMG matching for a memory bandwidth usage monitor used for Secure PARTIDs, and the Non-secure instance (MSMON_CFG_MBWU_FLT_ns) accesses the PARTID and PMG matching for a memory bandwidth usage monitor used for Non-secure PARTIDs.

MSMON_CFG_MBWU_FLT can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0820	MSMON_CFG_MBWU_FLT_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0820	MSMON_CFG_MBWU_FLT_ns

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MSMON_CFG_MON_SEL, MPAM Monitor Instance Selection Register

The MSMON_CFG_MON_SEL characteristics are:

Purpose

Selects a monitor instance to access through the MSMON configuration and counter registers.
MSMON_CFG_MON_SEL_s selects a Secure monitor instance to access via the Secure MPAM feature page.
MSMON_CFG_MON_SEL_ns selects a Non-secure monitor instance to access via the Non-secure MPAM feature page.

Note

Different performance monitoring features within a MSC could have different numbers of monitor instances. See the NUM_MON field in the corresponding ID register. This means that a monitor out-of-bounds error might be signaled when an MSMON_CFG register is accessed because the value in MSMON_CFG_MON_SEL.MON_SEL is too large for the particular monitoring feature.

To configure a monitor, set MON_SEL in this register to the index of the monitor instance to configure, then write to the MSMON_CFG_x register to set the configuration of the monitor. At a later time, read the monitor register (for example MSMON_MBWU) to get the value of the monitor.

Configuration

The power domain of MSMON_CFG_MON_SEL is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1, or (MPAMF_IDR.HAS_IMPL_IDR == 1 and MPAMF_IDR.EXT == 0) or (MPAMF_IDR.HAS_IMPL_IDR~~MPAMF_HAS_IMPL_IDR~~ == 1, MPAMF_IDR.EXT == 1 and MPAMF_IDR.NO_IMPL_MSMON == 01). Otherwise, direct accesses to MSMON_CFG_MON_SEL are RES0.

Attributes

MSMON_CFG_MON_SEL is a 32-bit register.

Field descriptions

The MSMON_CFG_MON_SEL bit assignments are:



Bits [31:28]

Reserved, RES0.

RIS, bits [27:24]

When ARMv8.6-MPAM is implemented, MPAMF_IDR.EXT == 1 and MPAMF_IDR.HAS_RIS~~MAPMF_IDR.HAS_RIS~~ == 1:

Resource Instance Selector. RIS selects one resource to configure through MSMON_CFG registers.

Otherwise:

Reserved, RES0.

Bits [23:16]

Reserved, RES0.

MON_SEL, bits [15:0]

Selects the monitor instance to configure or read.

Reads and writes to other MSMON registers are indexed by MON_SEL and by the NS bit used to access MSMON_CFG_MON_SEL to access the configuration for a single monitor.

Accessing the MSMON_CFG_MON_SEL

This register is part of the MPAMF_BASE memory frame. In a system that supports Secure and Non-secure memory maps, the MPAMF_BASE frame must be accessible in both Secure and Non-secure memory address maps.

MSMON_CFG_MON_SEL must be accessible from the Non-secure and Secure address maps.

MSMON_CFG_MON_SEL must be banked for the Secure and Non-secure address maps. The Secure instance is used with accesses to other MSMON registers to configure monitors for Secure PARTIDs, and the Non-secure instance is used with accesses to other MSMON registers to configure monitors for Non-secure PARTIDs.

MSMON_CFG_MON_SEL can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0800	MSMON_CFG_MON_SEL_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0800	MSMON_CFG_MON_SEL_ns

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MSMON_CSU, MPAM Cache Storage Usage Monitor Register

The MSMON_CSU characteristics are:

Purpose

AccessesMSMON_CSU is a 32-bit read-write register that accesses the CSU monitor selected by MSMON_CFG_MON_SEL. MSMON_CSU_s is the Secure cache storage usage monitor instance selected by the Secure instance of MSMON_CFG_MON_SEL. MSMON_CSU_ns is the Non-secure cache storage usage monitor instance selected by the Non-secure instance of MSMON_CFG_MON_SEL.

Configuration

The power domain of MSMON_CSU is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1 and MPAMF_MSMON_IDR.MSMON_CSU == 1. Otherwise, direct accesses to MSMON_CSU are RES0.

Attributes

MSMON_CSU is a 32-bit register.

Field descriptions

The MSMON_CSU bit assignments are:



NRDY, bit [31]

Not Ready. Indicates whether the monitor has possibly inaccurate data.

NRDY	Meaning
0b0	The monitor is not ready and the contents of the VALUE field might be inaccurate or otherwise not represent the actual cache storage usage.
0b1	The monitor is ready and the VALUE fields is accurate.

VALUE, bits [30:0]

Cache storage usage value if NRDY == 0. Invalid if NRDY == 1.

VALUE is the cache storage usage in bytes meeting the criteria set in MSMON_CFG_CSU_FLT and MSMON_CFG_CSU_CTL for the monitor instance selected by MSMON_CFG_MON_SEL.

Accessing the MSMON_CSU

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MSMON_CSU_s must be accessible from the Secure MPAM feature page. MSMON_CSU_ns must be accessible from the Non-secure MPAM feature page.

MSMON_CSU_s and MSMON_CSU_ns must be separate registers. The Secure instance (MSMON_CSU_s) accesses the cache storage usage monitor used for Secure PARTIDs, and the Non-secure instance (MSMON_CSU_ns) accesses the cache storage usage monitor used for Non-secure PARTIDs.

MSMON_CSU can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0840	MSMON_CSU_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0840	MSMON_CSU_ns

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MSMON_MBWU, MPAM Memory Bandwidth Usage Monitor Register

The MSMON_MBWU characteristics are:

Purpose

AccessesMSMON_MBWU is a 32-bit read-write register that accesses the monitor instance selected by MSMON_CFG_MON_SEL. MSMON_MBWU_s is the Secure memory bandwidth usage monitor instance selected by MSMON_CFG_MON_SEL_s. MSMON_MBWU_ns is the Non-secure memory bandwidth usage monitor instance selected by MSMON_CFG_MON_SEL_ns.

Configuration

The power domain of MSMON_MBWU is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1 and MPAMF_MSMON_IDR.MSMON_MBWU == 1. Otherwise, direct accesses to MSMON_MBWU are RES0.

Attributes

MSMON_MBWU is a 32-bit register.

Field descriptions

The MSMON_MBWU bit assignments are:



NRDY, bit [31]

Not Ready. Indicates whether the monitor has possibly inaccurate data.

NRDY	Meaning
0b0	The monitor is not ready and the contents of the VALUE field might be inaccurate or otherwise not represent the actual memory bandwidth usage.
0b1	The monitor is ready and the VALUE fields is accurate.

VALUE, bits [30:0]

Memory bandwidth usage counter value if NRDY == 0. Invalid if NRDY == 1.

VALUE is the scaled count of bytes transferred since the monitor was last reset that meet the criteria set in MSMON_CFG_MBWU_FLT and MSMON_CFG_MBWU_CTL for the monitor instance selected by MSMON_CFG_MON_SEL.

If MSMON_CFG_MBWU_CTL.SCLEN enables== scaling1, the count in VALUE is the number of bytes shifted right by MPAMF_MBWUMON_IDR.SCALE bit positions and rounded.

Accessing the MSMON_MBWU

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MSMON_MBWU_s must be accessible from the Secure MPAM feature page. MSMON_MBWU_ns must be accessible from the Non-secure MPAM feature page.

MSMON_MBWU_s and MSMON_MBWU_ns must be separate registers. The Secure instance (MSMON_MBWU_s) accesses the memory bandwidth usage monitor used for Secure PARTIDs, and the Non-secure instance (MSMON_MBWU_ns) accesses the memory bandwidth usage monitor used for Non-secure PARTIDs.

MSMON_MBWU can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0860	MSMON_MBWU_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0860	MSMON_MBWU_ns

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- no new file

MSMON_MBWU__L_CAPTURE, MPAM Long Memory Bandwidth Usage Monitor Capture Register

The MSMON_MBWU__L_CAPTURE characteristics are:

Purpose

MSMON_MBWU_L_CAPTURE is a 64-bit read-write register that accesses the captured MSMON_MBWU_L monitor instance selected by MSMON_CFG_MON_SEL.

MSMON_MBWU_L_CAPTURE_s is the Secure memory bandwidth usage monitor capture instance selected by the Secure instance of MSMON_CFG_MON_SEL.

MSMON_MBWU_L_CAPTURE_ns is the Non-secure memory bandwidth usage monitor capture instance selected by the Non-secure instance of MSMON_CFG_MON_SEL.

Configuration

The power domain of MSMON_MBWU__L_CAPTURE is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1, MPAMF_MSMON_IDR.MSMON_MBWU == 1, MPAMF_MBWUMON_IDR.HAS_CAPTURE == 1 and MPAMF_MBWUMON_IDR.HAS_LONG == 1. Otherwise, direct accesses to MSMON_MBWU__L_CAPTURE are IMPLEMENTATION DEFINED.

Attributes

MSMON_MBWU__L_CAPTURE is a 64-bit register.

Field descriptions

The MSMON_MBWU__L_CAPTURE bit assignments are:

When MPAMF_MBWUMON_IDR.LWD == 0:



NRDY, bit [63]

Not Ready. Indicates whether the monitor has possibly inaccurate data.

NRDY	Meaning
0b0	The monitor is not ready and the contents of the MSMON_MBWU_L_CAPTURE.VALUE field might be inaccurate or otherwise not represent the actual memory bandwidth usage.
0b1	The monitor is ready and the MSMON_MBWU_L_CAPTURE.VALUE field is accurate.

Bits [62:44]

Reserved, RES0.

VALUE, bits [43:0]

Memory bandwidth usage counter value if MSMON_MBWU_L_CAPTURE.NRDY == 0. Invalid if MSMON_MBWU_L_CAPTURE.NRDY == 1.

MSMON_MBWU_L_CAPTURE.VALUE is the 44-bit count of bytes transferred since the monitor was last reset that meet the criteria set in MSMON_CFG_MBWU_FLT and MSMON_CFG_MBWU_CTL for the monitor instance selected by MSMON_CFG_MON_SEL.

When MPAMF_MBWUMON_IDR.LWD == 1:



NRDY, bit [63]

Not Ready. Indicates whether the monitor has possibly inaccurate data.

NRDY	Meaning
0b0	The monitor is not ready and the contents of the MSMON_MBWU_L_CAPTURE.VALUE field might be inaccurate or otherwise not represent the actual memory bandwidth usage.
0b1	The monitor is ready and the MSMON_MBWU_L_CAPTURE.VALUE fields is accurate.

VALUE, bits [62:0]

Memory bandwidth usage counter value if MSMON_MBWU_L_CAPTURE.NRDY == 0. Invalid if MSMON_MBWU_L_CAPTURE.NRDY == 1.

MSMON_MBWU_L_CAPTURE.VALUE is the 63-bit count of bytes transferred since the monitor was last reset that meet the criteria set in MSMON_CFG_MBWU_FLT and MSMON_CFG_MBWU_CTL for the monitor instance selected by MSMON_CFG_MON_SEL.

Accessing the MSMON_MBWU__L_CAPTURE

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MSMON_MBWU_L_CAPTURE_s must be accessible from the Secure MPAM feature page.
MSMON_MBWU_L_CAPTURE_ns must be accessible from the Non-secure MPAM feature page.

MSMON_MBWU_L_CAPTURE_s and MSMON_MBWU_L_CAPTURE_ns must be separate registers. The Secure instance (MSMON_MBWU_L_CAPTURE_s) accesses the captured long memory bandwidth usage monitor used for Secure PARTIDs, and the Non-secure instance (MSMON_MBWU_L_CAPTURE_ns) accesses the captured long memory bandwidth usage monitor used for Non-secure PARTIDs.

MSMON_MBWU__L_CAPTURE can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0890	MSMON_MBWU_CAPTURE_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0890	MSMON_MBWU_CAPTURE_ns

Accesses on this interface are **RW**.

27/09/2019 18:48; 6134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- no new file

(old) htmldiff from- (new)

MSMON_MBWU_CAPTURE, MPAM Memory Bandwidth Usage Monitor Capture Register

The MSMON_MBWU_CAPTURE characteristics are:

Purpose

AccessesMSMON_MBWU_CAPTURE is a 32-bit read-write register that accesses the captured MSMON_MBWU monitor instance selected by MSMON_CFG_MON_SEL. MSMON_MBWU_CAPTURE_s is the Secure memory bandwidth usage monitor capture instance selected by the Secure instance of MSMON_CFG_MON_SEL. MSMON_MBWU_CAPTURE_ns is the Non-secure memory bandwidth usage monitor capture instance selected by the Non-secure instance of MSMON_CFG_MON_SEL.

Configuration

The power domain of MSMON_MBWU_CAPTURE is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1, MPAMF_MSMON_IDR.MSMON_MBWU == 1 and MPAMF_MBWUMON_IDR.HAS_CAPTURE == 1. Otherwise, direct accesses to MSMON_MBWU_CAPTURE are RES0.

Attributes

MSMON_MBWU_CAPTURE is a 32-bit register.

Field descriptions

The MSMON_MBWU_CAPTURE bit assignments are:

31	30 29 28 27 26 25 24 23 22 21 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 0
NRDY	VALUE

NRDY, bit [31]

Not Ready. The captured NRDY bit from the corresponding instance of MSMON_MBWU. This bit indicates whether the captured monitor value has possibly inaccurate data.

NRDY	Meaning
0b0	The captured monitor was not ready and the contents of the VALUE field might be inaccurate or otherwise not represent the actual memory bandwidth usage.
0b1	The captured monitor was ready and the VALUE fields is accurate.

VALUE, bits [30:0]

Captured memory bandwidth usage counter value if NRDY == 0. Invalid if NRDY == 1.

VALUE is the captured VALUE field from the corresponding instance of MSMON_MBWU, the count of bytes transferred since the monitor was last reset that meet the criteria set in MSMON_CFG_MBWU_FLT and MSMON_CFG_MBWU_CTL for the monitor instance selected by MSMON_CFG_MON_SEL.

VALUE captures the MSMON_MBWU.VALUE and preserves any scaling that had been performed on the VALUE field in that register.

Accessing the MSMON_MBWU_CAPTURE

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MSMON_MBWU_CAPTURE_s must be accessible from the Secure MPAM feature page. MSMON_MBWU_CAPTURE_ns must be accessible from the Non-secure MPAM feature page.

MSMON_MBWU_CAPTURE_s and MSMON_MBWU_CAPTURE_ns must be separate registers. The Secure instance (MSMON_MBWU_CAPTURE_s) accesses the captured memory bandwidth usage monitor used for Secure PARTIDs, and the Non-secure instance (MSMON_MBWU_CAPTURE_ns) accesses the captured memory bandwidth usage monitor used for Non-secure PARTIDs.

MSMON_MBWU_CAPTURE can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0868	MSMON_MBWU_CAPTURE_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0868	MSMON_MBWU_CAPTURE_ns

Accesses on this interface are **RW**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

MSMON_MBWU_L, MPAM Long Memory Bandwidth Usage Monitor Register

The MSMON_MBWU_L characteristics are:

Purpose

AccessesMSMON_MBWU_L is a 64-bit read-write register that accesses the monitor instance selected by MSMON_CFG_MON_SEL. MSMON_MBWU_L_s is the Secure memory bandwidth usage monitor instance selected by the Secure instance of MSMON_CFG_MON_SEL. MSMON_MBWU_L_ns is the Non-secure memory bandwidth usage monitor instance selected by the Non-secure instance of MSMON_CFG_MON_SEL.

Configuration

The power domain of MSMON_MBWU_L is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1, MPAMF_MSMON_IDR.MSMON_MBWU == 1 and MPAMF_MBWUMON_IDR.HAS_LONG == 1. Otherwise, direct accesses to MSMON_MBWU_L are IMPLEMENTATION DEFINED.

Attributes

MSMON_MBWU_L is a 64-bit register.

Field descriptions

The MSMON_MBWU_L bit assignments are:

When MPAMF_MBWUMON_IDR.LWD == 0:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
NRDY	RES0																			VALUE											
VALUE																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

NRDY, bit [63]

Not Ready. Indicates whether the monitor has possibly inaccurate data.

NRDY	Meaning
0b0	The monitor is not ready and the contents of the VALUE field might be inaccurate or otherwise not represent the actual memory bandwidth usage.
0b1	The monitor is ready and the VALUE fields is accurate.

Bits [62:44]

Reserved, RES0.

VALUE, bits [43:0]

Long (44-bit) memory bandwidth usage counter value if NRDY == 0. Invalid if NRDY == 1.

VALUE is the long count of bytes transferred since the monitor was last reset that meet the criteria set in MSMON_CFG_MBWU_FLT and MSMON_CFG_MBWU_CTL for the monitor instance selected by MSMON_CFG_MON_SEL.

When MPAMF_MBWUMON_IDR.LWD == 1:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
NRDY	VALUE																														
VALUE																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

NRDY, bit [63]

Not Ready. Indicates whether the monitor has possibly inaccurate data.

NRDY	Meaning
0b0	The monitor is not ready and the contents of the VALUE field might be inaccurate or otherwise not represent the actual memory bandwidth usage.
0b1	The monitor is ready and the VALUE fields is accurate.

VALUE, bits [62:0]

Long (63-bit) memory bandwidth usage counter value if NRDY == 0. Invalid if NRDY == 1.

VALUE is the long count of bytes transferred since the monitor was last reset that meet the criteria set in MSMON_CFG_MBWU_FLT and MSMON_CFG_MBWU_CTL for the monitor instance selected by MSMON_CFG_MON_SEL.

Accessing the MSMON_MBWU_L

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MSMON_MBWU_L_s must be accessible from the Secure MPAM feature page. MSMON_MBWU_L_ns must be accessible from the Non-secure MPAM feature page.

MSMON_MBWU_L_s and MSMON_MBWU_L_ns must be separate registers. The Secure instance (MSMON_MBWU_L_s) accesses the long memory bandwidth usage monitor used for Secure PARTIDs, and the Non-secure instance (MSMON_MBWU_L_ns) accesses the long memory bandwidth usage monitor used for Non-secure PARTIDs.

MSMON_MBWU_L can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0880	MSMON_MBWU_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0880	MSMON_MBWU_ns

Accesses on this interface are **RW**.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

no old file htmldiff from- (new)

MSMON_MBWU_L_CAPTURE, MPAM Long Memory Bandwidth Usage Monitor Capture Register

The MSMON_MBWU_L_CAPTURE characteristics are:

Purpose

Accesses the captured MSMON_MBWU_L monitor instance selected by MSMON_CFG_MON_SEL.

MSMON_MBWU_L_CAPTURE_s is the Secure memory bandwidth usage monitor capture instance selected by the Secure instance of MSMON_CFG_MON_SEL.

MSMON_MBWU_L_CAPTURE_ns is the Non-secure memory bandwidth usage monitor capture instance selected by the Non-secure instance of MSMON_CFG_MON_SEL.

Configuration

The power domain of MSMON_MBWU_L_CAPTURE is IMPLEMENTATION DEFINED.

This register is present only when MPAMF_IDR.HAS_MSMON == 1, MPAMF_MSMON_IDR.MSMON_MBWU == 1, MPAMF_MBWUMON_IDR.HAS_CAPTURE == 1 and MPAMF_MBWUMON_IDR.HAS_LONG == 1. Otherwise, direct accesses to MSMON_MBWU_L_CAPTURE are IMPLEMENTATION DEFINED.

Attributes

MSMON_MBWU_L_CAPTURE is a 64-bit register.

Field descriptions

The MSMON_MBWU_L_CAPTURE bit assignments are:

When MPAMF_MBWUMON_IDR.LWD == 0:



NRDY, bit [63]

Not Ready. Indicates whether the monitor has possibly inaccurate data.

NRDY	Meaning
0b0	The monitor is not ready and the contents of the MSMON_MBWU_L_CAPTURE.VALUE field might be inaccurate or otherwise not represent the actual memory bandwidth usage.
0b1	The monitor is ready and the MSMON_MBWU_L_CAPTURE.VALUE field is accurate.

Bits [62:44]

Reserved, RES0.

VALUE, bits [43:0]

Memory bandwidth usage counter value if MSMON_MBWU_L_CAPTURE.NRDY == 0. Invalid if MSMON_MBWU_L_CAPTURE.NRDY == 1.

MSMON_MBWU_L_CAPTURE.VALUE is the 44-bit count of bytes transferred since the monitor was last reset that meet the criteria set in MSMON_CFG_MBWU_FLT and MSMON_CFG_MBWU_CTL for the monitor instance selected by MSMON_CFG_MON_SEL.

When MPAMF_MBWUMON_IDR.LWD == 1:



NRDY, bit [63]

Not Ready. Indicates whether the monitor has possibly inaccurate data.

NRDY	Meaning
0b0	The monitor is not ready and the contents of the MSMON_MBWU_L_CAPTURE.VALUE field might be inaccurate or otherwise not represent the actual memory bandwidth usage.
0b1	The monitor is ready and the MSMON_MBWU_L_CAPTURE.VALUE fields is accurate.

VALUE, bits [62:0]

Memory bandwidth usage counter value if MSMON_MBWU_L_CAPTURE.NRDY == 0. Invalid if MSMON_MBWU_L_CAPTURE.NRDY == 1.

MSMON_MBWU_L_CAPTURE.VALUE is the 63-bit count of bytes transferred since the monitor was last reset that meet the criteria set in MSMON_CFG_MBWU_FLT and MSMON_CFG_MBWU_CTL for the monitor instance selected by MSMON_CFG_MON_SEL.

Accessing the MSMON_MBWU_L_CAPTURE

This register is within the MPAM feature page memory frames. In a system that supports Secure and Non-secure memory maps, there must be both Secure and Non-secure MPAM feature pages.

MSMON_MBWU_L_CAPTURE_s must be accessible from the Secure MPAM feature page.
MSMON_MBWU_L_CAPTURE_ns must be accessible from the Non-secure MPAM feature page.

MSMON_MBWU_L_CAPTURE_s and MSMON_MBWU_L_CAPTURE_ns must be separate registers. The Secure instance (MSMON_MBWU_L_CAPTURE_s) accesses the captured long memory bandwidth usage monitor used for Secure PARTIDs, and the Non-secure instance (MSMON_MBWU_L_CAPTURE_ns) accesses the captured long memory bandwidth usage monitor used for Non-secure PARTIDs.

MSMON_MBWU_L_CAPTURE can be accessed through the memory-mapped interfaces:

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_s	0x0890	MSMON_MBWU_CAPTURE_s

Accesses on this interface are **RW**.

Component	Frame	Offset	Instance
MPAM	MPAMF_BASE_ns	0x0890	MSMON_MBWU_CAPTURE_ns

Accesses on this interface are **RW**.

13/12/2019 15:13; 391b5248b29fb2f001ef74792eaacbd6fc72f211

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

no old file htmldiff from- (new)

(old) htmldiff from- (new)

PMAUTHSTATUS, Performance Monitors Authentication Status register

The PMAUTHSTATUS characteristics are:

Purpose

Provides information about the state of the IMPLEMENTATION DEFINED authentication interface for Performance Monitors.

Configuration

~~It is IMPLEMENTATION DEFINED whether PMAUTHSTATUS is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is OPTIONAL, and is required for CoreSight compliance. Arm recommends that this register is implemented.

Attributes

PMAUTHSTATUS is a 32-bit register.

Field descriptions

The PMAUTHSTATUS bit assignments are:



Bits [31:8]

Reserved, RES0.

SNID, bits [7:6]

Holds the same value as DBGAUTHSTATUS_EL1.SNID.

SID, bits [5:4]

Secure invasive debug. Possible values of this field are:

SID	Meaning
0b00	Not implemented.

All other values are reserved.

NSNID, bits [3:2]

Holds the same value as DBGAUTHSTATUS_EL1.NSNID.

NSID, bits [1:0]

Non-secure invasive debug. Possible values of this field are:

NSID	Meaning
0b00	Not implemented.

All other values are reserved.

Accessing the PMAUTHSTATUS

PMAUTHSTATUS can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFB8	PMAUTHSTATUS

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCCFILTR_EL0, Performance Monitors Cycle Counter Filter Register

The PMCCFILTR_EL0 characteristics are:

Purpose

Determines the modes in which the Cycle Counter, PMCCNTR_EL0, increments.

Configuration

External register PMCCFILTR_EL0 bits [31:0] are architecturally mapped to AArch64 System register PMCCFILTR_EL0[31:0] .

External register PMCCFILTR_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMCCFILTR[31:0] .

PMCCFILTR_EL0 is in the Core power domain.

On a Warm or Cold reset, RW fields in this register reset:

- To architecturally UNKNOWN values if the reset is to an Exception level that is using AArch64.
- To 0 if the reset is to an Exception level that is using AArch32.

The register is not affected by an External debug reset.

Attributes

PMCCFILTR_EL0 is a 32-bit register.

Field descriptions

The PMCCFILTR_EL0 bit assignments are:



P, bit [31]

Privileged filtering bit. Controls counting in EL1.

If EL3 is implemented, then counting in Non-secure EL1 is further controlled by the PMCCFILTR_EL0.NSK bit.

P	Meaning
0b0	Count cycles in EL1.
0b1	Do not count cycles in EL1.

U, bit [30]

User filtering bit. Controls counting in EL0.

If EL3 is implemented, then counting in Non-secure EL0 is further controlled by the PMCCFILTR_EL0.NSU bit.

U	Meaning
0b0	Count cycles in EL0.
0b1	Do not count cycles in EL0.

NSK, bit [29]

When ~~HaveEL(~~EL3 is implemented~~):~~

Non-secure EL1 (kernel) modes filtering bit. Controls counting in Non-secure EL1.

If the value of this bit is equal to the value of the PMCCFILTR_EL0.P bit, cycles in Non-secure EL1 are counted.

Otherwise, cycles in Non-secure EL1 are not counted.

Otherwise:

Reserved, RES0.

NSU, bit [28]

When ~~HaveEL(~~EL3 is implemented~~):~~

Non-secure EL0 (Unprivileged) filtering bit. Controls counting in Non-secure EL0.

If the value of this bit is equal to the value of the PMCCFILTR_EL0.U bit, cycles in Non-secure EL0 are counted.

Otherwise, cycles in Non-secure EL0 are not counted.

Otherwise:

Reserved, RES0.

NSH, bit [27]

When ~~HaveEL(~~EL2 is implemented~~):~~

EL2 (Hypervisor) filtering bit. Controls counting in EL2.

If Secure EL2 is implemented, counting in Secure EL2 is further controlled by the PMCCFILTR_EL0.SH bit.

NSH	Meaning
0b0	Do not count cycles in EL2.
0b1	Count cycles in EL2.

Otherwise:

Reserved, RES0.

M, bit [26]

When ~~HaveEL(~~EL3 is implemented~~):~~

Secure EL3 filtering bit.

If the value of this bit is equal to the value of the PMCCFILTR_EL0.P bit, cycles in Secure EL3 are counted.

Otherwise, cycles in Secure EL3 are not counted.

Most applications can ignore this field and set its value to 0.

Note

This field is not visible in the AArch32 PMCCFILTR System register.

Otherwise:

Reserved, RES0.

Bit [25]

Reserved, RES0.

SH, bit [24]

When ARMv8.4-SecEL2 is implemented:

Secure EL2 filtering.

If the value of this bit is not equal to the value of the PMCCFILTR_EL0.NSH bit, cycles in Secure EL2 are counted.

Otherwise, cycles in Secure EL2 are not counted.

If Secure EL2 is not implemented or is disabled, this field is RES0.

Note

This field is not visible in the AArch32 PMCCFILTR System register.

Otherwise:

Reserved, RES0.

Bits [23:0]

Reserved, RES0.

Accessing the PMCCFILTR_EL0

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMCCFILTR_EL0 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0x47C	PMCCFILTR_EL0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCCNTR_EL0, Performance Monitors Cycle Counter

The PMCCNTR_EL0 characteristics are:

Purpose

Holds the value of the processor Cycle Counter, CCNT, that counts processor clock cycles. See 'Time as measured by the Performance Monitors cycle counter' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile for more information.

PMCCFILTR_EL0 determines the modes and states in which the PMCCNTR_EL0 can increment.

Configuration

External register PMCCNTR_EL0 bits [63:0] are architecturally mapped to AArch64 System register PMCCNTR_EL0[63:0] .

External register PMCCNTR_EL0 bits [63:0] are architecturally mapped to AArch32 System register PMCCNTR[63:0] .

PMCCNTR_EL0 is in the Core power domain.

~~PMCCNTR_EL0 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply on a Warm or Cold reset. The register is not affected by an External debug reset.~~

Attributes

PMCCNTR_EL0 is a 64-bit register.

Field descriptions

The PMCCNTR_EL0 bit assignments are:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
CCNT																															
CCNT																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

CCNT, bits [63:0]

Cycle count. Depending on the values of PMCR_EL0.{LC,D}, the cycle count increments in one of the following ways:

- Every processor clock cycle.
- Every 64th processor clock cycle.

Writing 1 to PMCR_EL0.C sets this field to 0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMCCNTR_EL0

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMCCNTR_EL0 can be accessed through the external debug interface:

Component	Offset	Instance	Range
PMU	0x0F8	PMCCNTR_EL0	31:0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

Component	Offset	Instance	Range
PMU	0x0FC	PMCCNTR_EL0	63:32

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCFGR, Performance Monitors Configuration Register

The PMCFGR characteristics are:

Purpose

Contains PMU-specific configuration data.

Configuration

PMCFGR is in the Core power domain.

Attributes

PMCFGR is a 32-bit register.

Field descriptions

The PMCFGR bit assignments are:



NCG, bits [31:28]

This feature is not supported, so this field is RAZ.

Bits [27:20]

Reserved, RES0.

UEN, bit [19]

User-mode Enable Register supported. PMUSERENR_EL0 is not visible in the external debug interface, so this bit is RAZ.

WT, bit [18]

This feature is not supported, so this bit is RAZ.

NA, bit [17]

This feature is not supported, so this bit is RAZ.

EX, bit [16]

Export supported. Value is IMPLEMENTATION DEFINED.

EX	Meaning
0b0	PMCR_EL0.X is RES0.
0b1	PMCR_EL0.X is read/write.

CCD, bit [15]

Cycle counter has prescale.

~~Cycle counter has prescale. This is RES1 if AArch32 is supported at any EL, and RAZ otherwise.~~

This is RES1 if AArch32 is supported at any Exception level, and RAZ otherwise.

CCD	Meaning
0b0	PMCR_EL0.D is RES0.
0b1	PMCR_EL0.D is read/write.

CC, bit [14]

Dedicated cycle counter (counter 31) supported. This bit is RAO.

SIZE, bits [13:8]

Size of counters, minus one. This field defines the size of the largest counter implemented by the Performance Monitors Unit.

From Armv8, the largest counter is 64-bits, so the value of this field is 0b111111.

This field is used by software to determine the spacing of the counters in the memory-map. From Armv8, the counters are a doubleword-aligned addresses.

N, bits [7:0]

Number of counters implemented in addition to the cycle counter, PMCCNTR_EL0. The maximum number of event counters is 31.

N	Meaning
0x00	Only PMCCNTR_EL0 implemented.
0x01	PMCCNTR_EL0 plus one event counter implemented.

and so on up to 0b00011111, which indicates PMCCNTR_EL0 and 31 event counters implemented.

Accessing the PMCFGR

Note

AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMCFGR can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xE00	PMCFGR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and AllowExternalPMUAccess() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCID1SR, CONTEXTIDR_EL1 Sample Register

The PMCID1SR characteristics are:

Purpose

Contains the sampled value of CONTEXTIDR_EL1, captured on reading PMPCSR[31:0].

Configuration

PMCID1SR is in the Core power domain.

~~PMCID1SR is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

This register is present only when ARMv8.2-PCSample is implemented. Otherwise, direct accesses to PMCID1SR are RES0.

Note

Before Armv8.2, the PC Sample-based Profiling Extension can be implemented in the external debug register space, as indicated by the value of EDDEVID.PCSample.

Attributes

PMCID1SR is a 32-bit register.

Field descriptions

The PMCID1SR bit assignments are:



CONTEXTIDR_EL1, bits [31:0]

Context ID. The value of CONTEXTIDR that is associated with the most recent PMPCSR sample. When the most recent PMPCSR sample was generated:

- If EL1 is using AArch64, then the Context ID is sampled from CONTEXTIDR_EL1.
- If EL1 is using AArch32, then the Context ID is sampled from CONTEXTIDR. ~~If EL3 is implemented and is using AArch32, then CONTEXTIDR is a banked register and PMCID1SR samples the current banked copy of CONTEXTIDR for the Security state that is associated with the most recent PMPCSR sample.~~
- If EL3 is implemented and is using AArch32, then CONTEXTIDR is a banked register and PMCID1SR samples the current banked copy of CONTEXTIDR for the Security state that is associated with the most recent PMPCSR sample.

Because the value written to PMCID1SR is an indirect read of CONTEXTIDR, it is CONSTRAINED UNPREDICTABLE whether PMCID1SR is set to the original or new value if PMPCSR samples:

- An instruction that writes to CONTEXTIDR.
- The next Context synchronization event.
- Any instruction executed between these two instructions.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On an External debug reset, the value of this field is unchanged.
- On a Warm reset, the value of this field is unchanged.

Accessing the PMCID1SR

IMPLEMENTATION DEFINED extensions to external debug might make the value of this register UNKNOWN, see 'Permitted behavior that might make the PC Sample-based profiling registers UNKNOWN' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile

PMCID1SR can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0x208	PMCID1SR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

Component	Offset	Instance
PMU	0x228	PMCID1SR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCID2SR, CONTEXTIDR_EL2 Sample Register

The PMCID2SR characteristics are:

Purpose

Contains the sampled value of CONTEXTIDR_EL2, captured on reading PMPCSR[31:0].

Configuration

PMCID2SR is in the Core power domain.

~~PMCID2SR is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

This register is present only when ARMv8.2-PCSample is implemented and ~~HaveEL(~~EL2 is implemented.~~).~~ Otherwise, direct accesses to PMCID2SR are RES0.

Note

~~If~~Before ARMv8.2-PCSample is not implemented~~Armv8.2~~, the PC Sample-based Profiling Extension can be implemented in the external debug register space, as indicated by the value of EDDEVID.PCSample.

Attributes

PMCID2SR is a 32-bit register.

Field descriptions

The PMCID2SR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
CONTEXTIDR_EL2																															

CONTEXTIDR_EL2, bits [31:0]

Context ID. The value of CONTEXTIDR_EL2 that is associated with the most recent PMPCSR sample. When the most recent PMPCSR sample was generated:

- If EL2 is using AArch64, then this field is set to the Context ID sampled from CONTEXTIDR_EL2.
- If EL2 is using AArch32, then this field is set to an UNKNOWN value.

Because the value written to PMCID2SR is an indirect read of CONTEXTIDR_EL2, it is CONSTRAINED UNPREDICTABLE whether PMCID2SR is set to the original or new value if PMPCSR samples:

- An instruction that writes to CONTEXTIDR_EL2.
- The next Context synchronization event.
- Any instruction executed between these two instructions.

The following resets apply:

~~On a Cold reset, this field resets to an architecturally UNKNOWN value.~~

- On a Cold reset, this field resets to an architecturally UNKNOWN value.
- On an External debug reset, the value of this field is unchanged.

- On a Warm reset, the value of this field is unchanged.

Accessing the PMCID2SR

IMPLEMENTATION DEFINED extensions to external debug might make the value of this register UNKNOWN, see 'Permitted behavior that might make the PC Sample-based profiling registers UNKNOWN' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile

PMCID2SR can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0x22C	PMCID2SR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCIDR0, Performance Monitors Component Identification Register 0

The PMCIDR0 characteristics are:

Purpose

Provides information to identify a Performance Monitor component.

For more information see 'About the Component identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether PMCIDR0 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

PMCIDR0 is a 32-bit register.

Field descriptions

The PMCIDR0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								PRMBL_0							

Bits [31:8]

Reserved, RES0.

PRMBL_0, bits [7:0]

Preamble. Must read as `0x0D`.

Accessing the PMCIDR0

PMCIDR0 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFF0	PMCIDR0

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCIDR1, Performance Monitors Component Identification Register 1

The PMCIDR1 characteristics are:

Purpose

Provides information to identify a Performance Monitor component.

For more information see 'About the Component identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether PMCIDR1 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

PMCIDR1 is a 32-bit register.

Field descriptions

The PMCIDR1 bit assignments are:



Bits [31:8]

Reserved, RES0.

CLASS, bits [7:4]

Component class. Reads as 0x9, debug component.

PRMBL_1, bits [3:0]

Preamble. RAZ.

Accessing the PMCIDR1

PMCIDR1 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFF4	PMCIDR1

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCIDR2, Performance Monitors Component Identification Register 2

The PMCIDR2 characteristics are:

Purpose

Provides information to identify a Performance Monitor component.

For more information see 'About the Component identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether PMCIDR2 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

PMCIDR2 is a 32-bit register.

Field descriptions

The PMCIDR2 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																								PRMBL_2							

Bits [31:8]

Reserved, RES0.

PRMBL_2, bits [7:0]

Preamble. Must read as `0x05`.

Accessing the PMCIDR2

PMCIDR2 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFF8	PMCIDR2

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCIDR3, Performance Monitors Component Identification Register 3

The PMCIDR3 characteristics are:

Purpose

Provides information to identify a Performance Monitor component.

For more information see 'About the Component identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether PMCIDR3 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

PMCIDR3 is a 32-bit register.

Field descriptions

The PMCIDR3 bit assignments are:



Bits [31:8]

Reserved, RES0.

PRMBL_3, bits [7:0]

Preamble. Must read as `0xB1`.

Accessing the PMCIDR3

PMCIDR3 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFFC	PMCIDR3

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCNTENCLR_EL0, Performance Monitors Count Enable Clear register

The PMCNTENCLR_EL0 characteristics are:

Purpose

Disables the Cycle Count Register, PMCCNTR_EL0, and any implemented event counters PMEVCNTR<n>. Reading this register shows which counters are enabled.

Configuration

External register PMCNTENCLR_EL0 bits [31:0] are architecturally mapped to AArch64 System register PMCNTENCLR_EL0[31:0] .

External register PMCNTENCLR_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMCNTENCLR[31:0] .

PMCNTENCLR_EL0 is in the Core power domain.

~~PMCNTENCLR_EL0 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply on a Warm or Cold reset. The register is not affected by an External debug reset.~~

Attributes

PMCNTENCLR_EL0 is a 32-bit register.

Field descriptions

The PMCNTENCLR_EL0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
C	P<n>, bit [n]																														

C, bit [31]

PMCCNTR_EL0 disable bit. Disables the cycle counter register. Possible values are:

C	Meaning
0b0	When read, means the cycle counter is disabled. When written, has no effect.
0b1	When read, means the cycle counter is enabled. When written, disables the cycle counter.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter disable bit for PMEVCNTR<n>_EL0.

If PMCFGR.N is less than 31, bits [30:PMCFGR.N] are RAZ/WI.

P<n>	Meaning
0b0	When read, means that PMEVCNTR<n>_EL0 is disabled. When written, has no effect.
0b1	When read, means that PMEVCNTR<n>_EL0 is enabled. When written, disables PMEVCNTR<n>_EL0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMCNTENCLR_EL0

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMCNTENCLR_EL0 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xC20	PMCNTENCLR_EL0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCNTENSET_EL0, Performance Monitors Count Enable Set register

The PMCNTENSET_EL0 characteristics are:

Purpose

Enables the Cycle Count Register, PMCCNTR_EL0, and any implemented event counters PMEVCNTR<n>. Reading this register shows which counters are enabled.

Configuration

External register PMCNTENSET_EL0 bits [31:0] are architecturally mapped to AArch64 System register PMCNTENSET_EL0[31:0] .

External register PMCNTENSET_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMCNTENSET[31:0] .

PMCNTENSET_EL0 is in the Core power domain.

~~PMCNTENSET_EL0 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply on a Warm or Cold reset. The register is not affected by an External debug reset.~~

Attributes

PMCNTENSET_EL0 is a 32-bit register.

Field descriptions

The PMCNTENSET_EL0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
C	P<n>, bit [n]																														

C, bit [31]

PMCCNTR_EL0 enable bit. Enables the cycle counter register. Possible values are:

C	Meaning
0b0	When read, means the cycle counter is disabled. When written, has no effect.
0b1	When read, means the cycle counter is enabled. When written, enables the cycle counter.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter enable bit for PMEVCNTR<n>_EL0.

If PMCFGR.N is less than 31, bits [30:PMCFGR.N] are RAZ/WI.

P<n>	Meaning
0b0	When read, means that PMEVCNTR<n>_EL0 is disabled. When written, has no effect.
0b1	When read, means that PMEVCNTR<n>_EL0 event counter is enabled. When written, enables PMEVCNTR<n>_EL0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMCNTENSET_EL0

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMCNTENSET_EL0 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xC00	PMCNTENSET_EL0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMCR_EL0, Performance Monitors Control Register

The PMCR_EL0 characteristics are:

Purpose

Provides details of the Performance Monitors implementation, including the number of counters implemented, and configures and controls the counters.

Configuration

External register PMCR_EL0 bits [7:0] are architecturally mapped to AArch32 System register PMCR[7:0] .

External register PMCR_EL0 bits [7:0] are architecturally mapped to AArch64 System register PMCR_EL0[7:0] .

PMCR_EL0 is in the Core power domain. ~~Some or all RW fields of this register have defined reset values. The field descriptions identify when the reset values apply.~~

This register is only partially mapped to the internal PMCR System register. An external agent must use other means to discover the information held in PMCR[31:11], such as accessing PMCFGR and the ID registers.

Attributes

PMCR_EL0 is a 32-bit register.

Field descriptions

The PMCR_EL0 bit assignments are:



Bits [31:11]

Reserved, RAZ/WI.

Hardware must implement this field as RAZ/WI. Software must not rely on the register reading as zero, and must use a read-modify-write sequence to write to the register.

Bits [10:8]

Reserved, RES0.

LP, bit [7]

When ARMv8.5-PMU is implemented:

Long event counter enable. Determines when unsigned overflow is recorded by a counter overflow bit.

LP	Meaning
0b0	Event counter overflow on increment that causes unsigned overflow of PMEVCNTR<n>_EL0[31:0].
0b1	Event counter overflow on increment that causes unsigned overflow of PMEVCNTR<n>_EL0[63:0].

If EL2 is implemented and MDCR_EL2.HPMN is less than PMCR_EL0.N, this bit does not affect the operation of event counters in the range [orHDCR.HPMN is less than PMCR_EL0.N, this bit does not affect the operation of event counters in the range [HDCR.HPMN..(PMCR_EL0.N-1)] or [MDCR_EL2.HPMN:(PMCR_EL0.N-1)].

If EL2 is implemented and HDCR.HPMN is less than PMCR_EL0.N, this bit does not affect the operation of event counters in the range [HDCR.HPMN..(PMCR_EL0.N-1)].

Note

The effect of MDCR_EL2.HPMN or HDCR.HPMN on the operation of this bit always applies if EL2 is implemented, at all Exception levels including EL2 and EL3, and regardless of whether EL2 is enabled in the current Security state. For more information, see the description of MDCR_EL2.HPMN or HDCR.HPMN.

If the highest implemented Exception level is using AArch32, it is IMPLEMENTATION DEFINED whether this bit is RW or RAZ/WI.

Otherwise:

Reserved, RES0.

LC, bit [6]

When AArch32 is supported at any Exception level:

Long cycle counter enable. Determines when unsigned overflow is recorded by the cycle counter overflow bit.

LC	Meaning
0b0	Cycle counter overflow on increment that causes unsigned overflow of PMCCNTR_EL0[31:0].
0b1	Cycle counter overflow on increment that causes unsigned overflow of PMCCNTR_EL0[63:0].

Arm deprecates use of PMCR_EL0.LC = 0.

In an AArch64 only implementation, this field is RES1.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

DP, bit [5]

When HaveEL(EL3) or (ARMv8.1-PMU is implemented and HaveEL(EL2)):

Otherwise:

Reserved, RES1.

DP, bit [5]

When EL3 is implemented or (ARMv8.1-PMU is implemented and EL2 is implemented):

Disable cycle counter when event counting is prohibited. The possible values of this bit are:

DP	Meaning
0b0	Cycle counting by PMCCNTR_EL0 is not affected by this bit.
0b1	When event counting for counters in the range [0..(MDCR_EL2.HPMN-1)] is prohibited, cycle counting by PMCCNTR_EL0 is disabled.

For more information about the interaction between the Performance Monitors and EL3, see 'Effect of EL3 and EL2' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile.

When this register has an architecturally-defined reset value, if this field is implemented as an RW field it resets to:

- A value that is architecturally UNKNOWN if the reset is into an Exception level that is using AArch64.

- 0 if the reset is into an Exception level that is using AArch32.

Otherwise:

Reserved, RES0.

X, bit [4]

When the implementation includes a PMU event export bus:

Enable export of events in an IMPLEMENTATION DEFINED PMU event export bus.

X	Meaning
0b0	Do not export events.
0b1	Export events where not prohibited.

This field enables the exporting of events over an IMPLEMENTATION DEFINED PMU event export bus to another device, for example to an OPTIONAL PE trace unit.

No events are exported when counting is prohibited.

This field does not affect the generation of Performance Monitors overflow interrupt requests or signaling to a cross-trigger interface (CTI) that can be implemented as signals exported from the PE.

When this register has an architecturally-defined reset value, if this field is implemented as an RW field it resets to:

- A value that is architecturally UNKNOWN if the reset is into an Exception level that is using AArch64.
- 0 if the reset is into an Exception level that is using AArch32.

Otherwise:

Reserved, RAZ/WI.

D, bit [3]

When AArch32 is supported at any Exception level:

Clock divider.

D	Meaning
0b0	When enabled, PMCCNTR_EL0 counts every clock cycle.
0b1	When enabled, PMCCNTR_EL0 counts once every 64 clock cycles.

If PMCR_EL0.LC == 1, this bit is ignored and the cycle counter counts every clock cycle.

Arm deprecates use of PMCR_EL0.D = 1.

When this register has an architecturally-defined reset value, if this field is implemented as an RW field it resets to:

- A value that is architecturally UNKNOWN if the reset is into an Exception level that is using AArch64.
- 0 if the reset is into an Exception level that is using AArch32.

Otherwise:

Reserved, RES0.

C, bit [2]

Cycle counter reset. The effects of writing to this bit are:

C	Meaning
0b0	No action.
0b1	Reset PMCCNTR_EL0 to zero.

This bit is always RAZ.

Note

Resetting PMCCNTR_EL0 does not change the cycle counter overflow bit.

Access to this field is **WO**.

P, bit [1]

Event counter reset. The effects of writing to this bit are:

P	Meaning
0b0	No action.
0b1	Reset all event counters, not including PMCCNTR_EL0, to zero.

This bit is always RAZ.

Note

Resetting the event counters does not change the event counter overflow bits.

If ARMv8.5-PMU is implemented, the value of MDCR_EL2.HLP, or PMCR_EL0.LP is ignored and bits [63:0] of all event counters are reset.

Access to this field is **WO**.

E, bit [0]

Enable.

E	Meaning
0b0	All event counters in the range [0..(PMN-1)] and PMCCNTR_EL0, are disabled.
0b1	All event counters in the range [0..(PMN-1)] and PMCCNTR_EL0, are enabled by PMCNTENSET_EL0.

If EL2 is implemented then:

- If EL2 is using AArch32, PMN is HDCR.HPMN.
- If EL2 is using AArch64, PMN is MDCR_EL2.HPMN.
- If PMN is less than PMCR_EL0.N, this bit does not affect the operation of event counters in the range [PMN..(PMCR_EL0.N-1)].

If EL2 is not implemented, PMN is PMCR_EL0.N.

Note

The effect of the following fields on the operation of this bit applies if EL2 is implemented regardless of whether EL2 is enabled in the current Security state:~~MDCR_EL2.HPMN or HDCR.HPMN on the operation of this bit applies if EL2 is implemented regardless of whether EL2 is enabled in the current Security state. For more information, see the description of MDCR_EL2.HPMN or HDCR.HPMN.~~

- HDCR.HPMN. See the description of HDCR.HPMN for more information.
- MDCR_EL2.HPMN. See the description of MDCR_EL2.HPMN for more information.

On a Warm reset, this field resets to 0.

Accessing the PMCR_EL0

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMCR_EL0 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xE04	PMCR_EL0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMDEVAFF0, Performance Monitors Device Affinity register 0

The PMDEVAFF0 characteristics are:

Purpose

Copy of the low half of the PE MPIDR_EL1 register that allows a debugger to determine which PE in a multiprocessor system the Performance Monitor component relates to.

Configuration

~~It is IMPLEMENTATION DEFINED whether PMDEVAFF0 is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required if the external interface to the PMU is implemented.

Attributes

PMDEVAFF0 is a 32-bit register.

Field descriptions

The PMDEVAFF0 bit assignments are:



MPIDR_EL1loMPIDR_EL1 low half, bits [31:0]

MPIDR_EL1 low half. Read-only copy of the low half of MPIDR_EL1, as seen from the highest implemented Exception level.

Accessing the PMDEVAFF0

PMDEVAFF0 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFA8	PMDEVAFF0

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMDEVAFF1, Performance Monitors Device Affinity register 1

The PMDEVAFF1 characteristics are:

Purpose

Copy of the high half of the PE MPIDR_EL1 register that allows a debugger to determine which PE in a multiprocessor system the Performance Monitor component relates to.

Configuration

~~It is IMPLEMENTATION DEFINED whether PMDEVAFF1 is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required if the external interface to the PMU is implemented.

Attributes

PMDEVAFF1 is a 32-bit register.

Field descriptions

The PMDEVAFF1 bit assignments are:



MPIDR_EL1hi~~MPIDR_EL1 high half~~, bits [31:0]

MPIDR_EL1 high half. Read-only copy of the high half of MPIDR_EL1, as seen from the highest implemented Exception level.

Accessing the PMDEVAFF1

PMDEVAFF1 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFAC	PMDEVAFF1

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMDEVARCH, Performance Monitors Device Architecture register

The PMDEVARCH characteristics are:

Purpose

Identifies the programmers' model architecture of the Performance Monitor component.

Configuration

~~It is IMPLEMENTATION DEFINED whether PMDEVARCH is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

Attributes

PMDEVARCH is a 32-bit register.

Field descriptions

The PMDEVARCH bit assignments are:



ARCHITECT, bits [31:21]

Defines the architecture of the component. For Performance Monitors, this is Arm Limited.

Bits [31:28] are the JEP106 continuation code, `0x4`.

Bits [27:21] are the JEP106 ID code, `0x3B`.

PRESENT, bit [20]

When set to 1, indicates that the DEVARCH is present.

This field is 1 in Armv8.

REVISION, bits [19:16]

Defines the architecture revision. For architectures defined by Arm this is the minor revision.

For Performance Monitors, the revision defined by Armv8 is `0x0`.

All other values are reserved.

ARCHID, bits [15:0]

Defines this part to be an Armv8 debug component. For architectures defined by Arm this is further subdivided.

For Performance Monitors:

- Bits [15:12] are the architecture version, `0x2`.
- Bits [11:0] are the architecture part number, `0xA16`.

This corresponds to Performance Monitors architecture version PMUv3.

Note

The PMUv3 memory-mapped programmers' model can be used by devices other than Armv8 processors. Software must determine whether the PMU is attached to an Armv8 processor by using the PMDEVAFF0 and PMDEVAFF1 registers to discover the affinity of the PMU to any Armv8 processors.

Accessing the PMDEVARCH

PMDEVARCH can be accessed through the external debug interface:

Component	Offset	Instance
PMU	`0xFBC`	PMDEVARCH

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMDEVID, Performance Monitors Device ID register

The PMDEVID characteristics are:

Purpose

Provides information about features of the Performance Monitors implementation.

Configuration

~~It is IMPLEMENTATION DEFINED whether PMDEVID is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required from Armv8.2 and in any implementation that includes ARMv8.2-PCSample. Otherwise, its location is RES0.

Note

Before Armv8.2, the PC Sample-based Profiling Extension can be implemented in the external debug register space, as indicated by the value of EDDEVID.PCSample.

Attributes

PMDEVID is a 32-bit register.

Field descriptions

The PMDEVID bit assignments are:



Bits [31:4]

Reserved, RES0.

PCSample, bits [3:0]

Indicates the level of PC Sample-based Profiling support using Performance Monitors registers. Permitted values of this field are:

PCSample	Meaning
0b0000	PC Sample-based Profiling Extension is not implemented in the Performance Monitors register space.
0b0001	PC Sample-based Profiling Extension is implemented in the Performance Monitors register space.

All other values are reserved.

ARMv8.2-PCSample implements the functionality identified by the value 0b0001.

Accessing the PMDEVID

PMDEVID can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFC8	PMDEVID

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMDEVTYPE, Performance Monitors Device Type register

The PMDEVTYPE characteristics are:

Purpose

Indicates to a debugger that this component is part of a PEs performance monitor interface.

Configuration

~~It is IMPLEMENTATION DEFINED whether PMDEVTYPE is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

Attributes

PMDEVTYPE is a 32-bit register.

Field descriptions

The PMDEVTYPE bit assignments are:



Bits [31:8]

Reserved, RES0.

SUB, bits [7:4]

Subtype. Must read as `0x1` to indicate this is a component within a PE.

MAJOR, bits [3:0]

Major type. Must read as `0x6` to indicate this is a performance monitor component.

Accessing the PMDEVTYPE

PMDEVTYPE can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFCC	PMDEVTYPE

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMEVCNTR<n>_EL0, Performance Monitors Event Count Registers, n = 0 - 30

The PMEVCNTR<n>_EL0 characteristics are:

Purpose

Holds event counter n, which counts events, where n is 0 to 30.

Configuration

External register PMEVCNTR<n>_EL0 bits [31:0] are architecturally mapped to AArch64 System register PMEVCNTR<n>_EL0[31:0] .

External register PMEVCNTR<n>_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMEVCNTR<n>[31:0] .

PMEVCNTR<n>_EL0 is in the Core power domain.

~~PMEVCNTR<n>_EL0 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. The field descriptions identify when the reset values apply.~~

Attributes

PMEVCNTR<n>_EL0 is a 64-bit register.

Field descriptions

The PMEVCNTR<n>_EL0 bit assignments are:

When ARMv8.5-PMU is implemented:

63	62	61	60	59	58	57	56	55	54	53	52	51	50	49	48	47	46	45	44	43	42	41	40	39	38	37	36	35	34	33	32
Event counter n																															
Event counter n																															
31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

Bits [63:0]

Event counter n. Value of event counter n, where n is the number of this register and is a number from 0 to 30.

If the highest implemented Exception level is using AArch32, the optional external interface to the performance monitors is implemented, and the PMCR.LP and HDCR.HLP bits are RAZ/WI, then locations in the external interface to the performance monitors that map to PMEVCNTR<n>_EL0[63:32] return UNKNOWN values on reads.

If the implementation does not support AArch64 at any Exception level, bits [63:32] of the event counters are not required to be implemented.

This field resets to an architecturally UNKNOWN value.

Otherwise:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Event counter n																															

Bits [31:0]

Event counter n. Value of event counter n, where n is the number of this register and is a number from 0 to 30.

This field resets to an architecturally UNKNOWN value.

Accessing the PMEVCNTR<n>_EL0

External accesses to the performance monitors ignore PMUSERENR_EL0 and, if implemented, MDCR_EL2.{TPM, TPMCR, HPMN} and MDCR_EL3.TPM. This means that all counters are accessible regardless of the current Exception level or privilege of the access.

If ARMv8.5-PMU is not implemented, when IsCorePowered(), DoubleLockStatus(), OSLockStatus() or !AllowExternalPMUAccess(), 32-bit accesses to `0x004+8×n` have a CONSTRAINED UNPREDICTABLE behavior.

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMEVCNTR<n>_EL0 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	`0x000 + 8n`	PMEVCNTR<n>_EL0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMEVTYPER<n>_EL0, Performance Monitors Event Type Registers, n = 0 - 30

The PMEVTYPER<n>_EL0 characteristics are:

Purpose

Configures event counter n, where n is 0 to 30.

Configuration

External register PMEVTYPER<n>_EL0 bits [31:0] are architecturally mapped to AArch64 System register PMEVTYPER<n>_EL0[31:0] .

External register PMEVTYPER<n>_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMEVTYPER<n>[31:0] .

PMEVTYPER<n>_EL0 is in the Core power domain.

~~PMEVTYPER<n>_EL0 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply on a Warm or Cold reset. The register is not affected by an External debug reset.~~

If event counter n is not implemented then accesses to this register are:

- RES0 when IsCorePowered() && !DoubleLockStatus() && !OSLockStatus() && AllowExternalPMUAccess().
- A CONSTRAINED UNPREDICTABLE choice of RES0 or ERROR otherwise.

Attributes

PMEVTYPER<n>_EL0 is a 32-bit register.

Field descriptions

The PMEVTYPER<n>_EL0 bit assignments are:

31	30	29	28	27	26	25	24	23 22 21 20 19 18 17 16	15 14 13 12 11 10	9 8 7 6 5 4 3 2 1 0
P	U	NSK	NSU	NSH	M	MT	SH	RES0	evtCount[15:10]	evtCount[9:0]

P, bit [31]

Privileged filtering bit. Controls counting in EL1.

If EL3 is implemented, then counting in Non-secure EL1 is further controlled by the PMEVTYPER<n>_EL0.NSK bit.

P	Meaning
0b0	Count events in EL1.
0b1	Do not count events in EL1.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

U, bit [30]

User filtering bit. Controls counting in EL0.

If EL3 is implemented, then counting in Non-secure EL0 is further controlled by the PMEVTYPER<n>_EL0.NSU bit.

U	Meaning
0b0	Count events in EL0.
0b1	Do not count events in EL0.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

NSK, bit [29]

When ~~HaveEL(~~EL3 is implemented~~):~~

Non-secure EL1 (kernel) modes filtering bit. Controls counting in Non-secure EL1.

If the value of this bit is equal to the value of the PMEVTYPER<n>_EL0.P bit, events in Non-secure EL1 are counted.

Otherwise, events in Non-secure EL1 are not counted.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NSU, bit [28]

When ~~HaveEL(~~EL3 is implemented~~):~~

Non-secure EL0 (Unprivileged) filtering bit. Controls counting in Non-secure EL0.

If the value of this bit is equal to the value of the PMEVTYPER<n>_EL0.U bit, events in Non-secure EL0 are counted.

Otherwise, events in Non-secure EL0 are not counted.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

NSH, bit [27]

When ~~HaveEL(~~EL2 is implemented~~):~~

EL2 (Hypervisor) filtering bit. Controls counting in EL2.

If Secure EL2 is implemented, counting in Secure EL2 is further controlled by the PMEVTYPER<n>_EL0.SH bit.

NSH	Meaning
0b0	Do not count events in EL2.
0b1	Count events in EL2.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

M, bit [26]

When ~~HaveEL(~~EL3 is implemented~~):~~

Secure EL3 filtering bit.

If the value of this bit is equal to the value of the PMEVTYPER<n>_EL0.P bit, events in Secure EL3 are counted.

Otherwise, events in Secure EL3 are not counted.

Most applications can ignore this field and set its value to `0b0`.

Note

This field is not visible in the AArch32 PMEVTYPER<n> System register.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

MT, bit [25]

When (ARMv8.6-MTPMU is implemented and enabled) or an IMPLEMENTATION DEFINED multi-threaded PMU Extension is implemented:

Multithreading.

MT	Meaning
`0b0`	Count events only on controlling PE.
`0b1`	Count events from any PE with the same affinity at level 1 and above as this PE.

Note

- When the lowest level of affinity consists of logical PEs that are implemented using a multi-threading type approach, an implementation is described as multi-threaded. That is, the performance of PEs at the lowest affinity level is highly interdependent.
- Events from a different thread of a multithreaded implementation are not Attributable to the thread counting the event.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

SH, bit [24]

When ARMv8.4-SecEL2 is implemented:

Secure EL2 filtering.

If the value of this bit is not equal to the value of the PMEVTYPER<n>_EL0.NSH bit, events in Secure EL2 are counted.

Otherwise, events in Secure EL2 are not counted.

Note

This field is not visible in the AArch32 PMEVTYPER<n> System register.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

Bits [23:16]

Reserved, RES0.

evtCount[15:10], bits [15:10]

When ARMv8.1-PMU is implemented:

Extension to evtCount[9:0]. See evtCount[9:0] for more details.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

evtCount[9:0], bits [9:0]

Event to count. The event number of the event that is counted by event counter PMEVCNTR<n>_EL0.

Software must program this field with an event that is supported by the PE being programmed.

The ranges of event numbers allocated to each type of event are shown in Allocation of the PMU event number space.

If evtCount is programmed to an event that is reserved or not supported by the PE, the behavior depends on the value written:

- For the range `0x0000` to `0x003F`, no events are counted, and the value returned by a direct or external read of the evtCount field is the value written to the field.
- If 16-bit evtCount is implemented, for the range `0x4000` to `0x403F`, no events are counted, and the value returned by a direct or external read of the evtCount field is the value written to the field.
- For IMPLEMENTATION DEFINED events, it is UNPREDICTABLE what event, if any, is counted, and the value returned by a direct or external read of the evtCount field is UNKNOWN.

Note

UNPREDICTABLE means the event must not expose privileged information.

Arm recommends that the behavior across a family of implementations is defined such that if a given implementation does not include an event from a set of common IMPLEMENTATION DEFINED events, then no event is counted and the value read back on evtCount is the value written.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMEVTYPER<n>_EL0

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMEVTYPER<n>_EL0 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	`0x400 + 4n`	PMEVTYPER<n>_EL0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMINTENCLR_EL1, Performance Monitors Interrupt Enable Clear register

The PMINTENCLR_EL1 characteristics are:

Purpose

Disables the generation of interrupt requests on overflows from the Cycle Count Register, PMCCNTR_EL0, and the event counters PMEVCNTR<n>_EL0. Reading the register shows which overflow interrupt requests are enabled.

Configuration

External register PMINTENCLR_EL1 bits [31:0] are architecturally mapped to AArch64 System register PMINTENCLR_EL1[31:0] .

External register PMINTENCLR_EL1 bits [31:0] are architecturally mapped to AArch32 System register PMINTENCLR[31:0] .

PMINTENCLR_EL1 is in the Core power domain.

~~PMINTENCLR_EL1 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply on a Warm or Cold reset. The register is not affected by an External debug reset.~~

Attributes

PMINTENCLR_EL1 is a 32-bit register.

Field descriptions

The PMINTENCLR_EL1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
C	P<n>, bit [n]																														

C, bit [31]

PMCCNTR_EL0 overflow interrupt request disable bit. Possible values are:

C	Meaning
0b0	When read, means the cycle counter overflow interrupt request is disabled. When written, has no effect.
0b1	When read, means the cycle counter overflow interrupt request is enabled. When written, disables the cycle count overflow interrupt request.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter overflow interrupt request disable bit for PMEVCNTR<n>_EL0.

If PMCFGR.N is less than 31, bits [30:PMCFGR.N] are RAZ/WI.

P<n>	Meaning
0b0	When read, means that the PMEVCNTR<n>_EL0 event counter interrupt request is disabled. When written, has no effect.
0b1	When read, means that the PMEVCNTR<n>_EL0 event counter interrupt request is enabled. When written, disables the PMEVCNTR<n>_EL0 interrupt request.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMINTENCLR_EL1

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMINTENCLR_EL1 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xC60	PMINTENCLR_EL1

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMINTENSET_EL1, Performance Monitors Interrupt Enable Set register

The PMINTENSET_EL1 characteristics are:

Purpose

Enables the generation of interrupt requests on overflows from the Cycle Count Register, PMCCNTR_EL0, and the event counters PMEVCNTR<n>_EL0. Reading the register shows which overflow interrupt requests are enabled.

Configuration

External register PMINTENSET_EL1 bits [31:0] are architecturally mapped to AArch64 System register PMINTENSET_EL1[31:0] .

External register PMINTENSET_EL1 bits [31:0] are architecturally mapped to AArch32 System register PMINTENSET[31:0] .

PMINTENSET_EL1 is in the Core power domain.

~~PMINTENSET_EL1 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply on a Warm or Cold reset. The register is not affected by an External debug reset.~~

Attributes

PMINTENSET_EL1 is a 32-bit register.

Field descriptions

The PMINTENSET_EL1 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
C	P<n>, bit [n]																														

C, bit [31]

PMCCNTR_EL0 overflow interrupt request enable bit. Possible values are:

C	Meaning
0b0	When read, means the cycle counter overflow interrupt request is disabled. When written, has no effect.
0b1	When read, means the cycle counter overflow interrupt request is enabled. When written, enables the cycle count overflow interrupt request.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter overflow interrupt request enable bit for PMEVCNTR<n>_EL0.

If PMCFGR.N is less than 31, bits [30:PMCFGR.N] are RAZ/WI.

P<n>	Meaning
0b0	When read, means that the PMEVCNTR<n>_EL0 event counter interrupt request is disabled. When written, has no effect.
0b1	When read, means that the PMEVCNTR<n>_EL0 event counter interrupt request is enabled. When written, enables the PMEVCNTR<n>_EL0 interrupt request.

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMINTENSET_EL1

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMINTENSET_EL1 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xC40	PMINTENSET_EL1

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMITCTRL, Performance Monitors Integration mode Control register

The PMITCTRL characteristics are:

Purpose

Enables the Performance Monitors to switch from default mode into integration mode, where test software can control directly the inputs and outputs of the PE, for integration testing or topology detection.

Configuration

It is IMPLEMENTATION DEFINED whether PMITCTRL is implemented in the Core power domain or in the Debug power domain. Some or all RW fields of this register have defined reset values, and:

- The register is not affected by a Warm reset.
- If the register is implemented in the Core power domain the reset values apply on a Cold reset, and the register is not affected by an External debug reset.
- If the register is implemented in the Debug power domain the reset values apply on an External debug reset, and the register is not affected by a Cold reset.

Implementation of this register is OPTIONAL.

Attributes

PMITCTRL is a 32-bit register.

Field descriptions

The PMITCTRL bit assignments are:



Bits [31:1]

Reserved, RES0.

IME, bit [0]

Integration mode enable. When IME == 1, the device reverts to an integration mode to enable integration testing or topology detection. The integration mode behavior is IMPLEMENTATION DEFINED.

IME	Meaning
0b0	Normal operation.
0b1	Integration mode enabled.

On a Implementation reset, this field resets to 0.

Accessing the PMITCTRL

PMITCTRL can be accessed through the external debug interface:

Component	Offset	Instance

PMU	0xF00	PMITCTRL

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register are **IMPDEF**.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMLAR, Performance Monitors Lock Access Register

The PMLAR characteristics are:

Purpose

Allows or disallows access to the Performance Monitors registers through a memory-mapped interface.

The optional Software Lock provides a lock to prevent memory-mapped writes to the Performance Monitors registers. Use of this lock mechanism reduces the risk of accidental damage to the contents of the Performance Monitors registers. It does not, and cannot, prevent all accidental or malicious damage.

Configuration

~~If ARMv8.3-DoPD is implemented, then ARMv8.0-SoftwareLock is not implemented by the architecturally-defined debug components of the PE in the Core power domain.~~

If ARMv8.3-DoPD is implemented, then ARMv8.0-SoftwareLock is not implemented by the architecturally-defined debug components of the PE in the Core power domain.

~~It is IMPLEMENTATION DEFINED whether PMLAR is implemented in the Core power domain or in the Debug power domain.~~

If ARMv8.3-DoPD is not implemented, then this register is in the Debug power domain.

Software uses PMLAR to set or clear the lock, and PMLSR to check the current status of the lock.

Attributes

PMLAR is a 32-bit register.

Field descriptions

The PMLAR bit assignments are:

When the Software Lock is implemented.:



KEY, bits [31:0]

Lock Access control. Writing the key value `0xC5ACCE55` to this field unlocks the lock, enabling write accesses to this component's registers through a memory-mapped interface.

Writing any other value to this register locks the lock, disabling write accesses to this component's registers through a memory mapped interface.

Otherwise:



Otherwise

Bits [31:0]

Reserved, RES0.

Accessing the PMLAR

PMLAR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
PMU	0xFB0	PMLAR

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **WO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMLSR, Performance Monitors Lock Status Register

The PMLSR characteristics are:

Purpose

Indicates the current status of the software lock for Performance Monitors registers.

The optional Software Lock provides a lock to prevent memory-mapped writes to the Performance Monitors registers. Use of this lock mechanism reduces the risk of accidental damage to the contents of the Performance Monitors registers. It does not, and cannot, prevent all accidental or malicious damage.

Configuration

~~If ARMv8.3-DoPD is implemented, then ARMv8.0-SoftwareLock is not implemented by the architecturally-defined debug components of the PE in the Core power domain.~~

If ARMv8.3-DoPD is implemented, then ARMv8.0-SoftwareLock is not implemented by the architecturally-defined debug components of the PE in the Core power domain.

~~It is IMPLEMENTATION DEFINED whether PMLSR is implemented in the Core power domain or in the Debug power domain. Some or all RW fields of this register have defined reset values, and:~~

- ~~The register is not affected by a Warm reset.~~
- ~~If the register is implemented in the Core power domain the reset values apply on a Cold reset, and the register is not affected by an External debug reset.~~
- ~~If the register is implemented in the Debug power domain the reset values apply on an External debug reset, and the register is not affected by a Cold reset.~~

If ARMv8.3-DoPD is not implemented, then this register is in the Debug power domain.

Software uses PMLAR to set or clear the lock, and PMLSR to check the current status of the lock.

Attributes

PMLSR is a 32-bit register.

Field descriptions

The PMLSR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																													nTT	SLK	SLI

Bits [31:3]

Reserved, RES0.

nTT, bit [2]

Not thirty-two bit access required. RAZ.

SLK, bit [1]

When the Software Lock is implemented.:

Software Lock status for this component. For an access to LSR that is not a memory-mapped access, or when the Software Lock is not implemented, this field is RES0.

For memory-mapped accesses when the software lock is implemented, possible values of this field are:

SLK	Meaning
0b0	Lock clear. Writes are permitted to this component's registers.
0b1	Lock set. Writes to this component's registers are ignored, and reads have no side effects.

The following resets apply:

- If Armv8.3-DoPD is implemented, this register is reset by Cold reset and not affected by External debug reset. If Armv8.3-DoPD is not implemented, this register is reset by External debug reset and not affected by Cold reset.
- On a Cold reset, this~~This~~ field resets to 1.

Otherwise:

Reserved, RAZ.

SLI, bit [0]

Software Lock implemented. For an access to LSR that is not a memory-mapped access, this field is RAZ. For memory-mapped accesses, the value of this field is IMPLEMENTATION DEFINED. Permitted values are:

SLI	Meaning
0b0	Software Lock not implemented or not memory-mapped access.
0b1	Software Lock implemented and memory-mapped access.

Accessing the PMLSR

PMLSR can be accessed through the memory-mapped interfaces:

Component	Offset	Instance
PMU	0xFB4	PMLSR

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMOVSCLR_EL0, Performance Monitors Overflow Flag Status Clear register

The PMOVSCLR_EL0 characteristics are:

Purpose

Contains the state of the overflow bit for the Cycle Count Register, PMCCNTR_EL0, and each of the implemented event counters PMEVCNTR<n>. Writing to this register clears these bits.

Configuration

External register PMOVSCLR_EL0 bits [31:0] are architecturally mapped to AArch64 System register PMOVSCLR_EL0[31:0] .

External register PMOVSCLR_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMOVSR[31:0] .

PMOVSCLR_EL0 is in the Core power domain.

~~PMOVSCLR_EL0 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply on a Warm or Cold reset. The register is not affected by an External debug reset.~~

Attributes

PMOVSCLR_EL0 is a 32-bit register.

Field descriptions

The PMOVSCLR_EL0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
C	P<n>, bit [n]																														

C, bit [31]

Cycle counter overflow clear bit.

C	Meaning
0b0	When read, means the cycle counter has not overflowed since this bit was last cleared. When written, has no effect.
0b1	When read, means the cycle counter has overflowed since this bit was last cleared. When written, clears the cycle counter overflow bit to 0.

PMCR_EL0.LC controls whether an overflow is detected from unsigned overflow of PMCCNTR_EL0[31:0] or unsigned overflow of PMCCNTR_EL0[63:0].

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter overflow clear bit for PMEVCNTR<n>_EL0.

If PMCFGR.N is less than 31, bits [30:PMCFGR.N] are RAZ/WI.

P<n>	Meaning
0b0	When read, means that PMEVCNTR<n>_EL0 has not overflowed since this bit was last cleared. When written, has no effect.
0b1	When read, means that PMEVCNTR<n>_EL0 has overflowed since this bit was last cleared. When written, clears the PMEVCNTR<n>_EL0 overflow bit to 0.

If ARMv8.5-PMU is implemented, MDCR_EL2.HLP and PMCR_EL0.LP control whether an overflow is detected from unsigned overflow of PMEVCNTR<n>_EL0[31:0] or unsigned overflow of PMEVCNTR<n>_EL0[63:0].

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMOVSCLR_EL0

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMOVSCLR_EL0 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xC80	PMOVSCLR_EL0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMOVSSET_EL0, Performance Monitors Overflow Flag Status Set register

The PMOVSSET_EL0 characteristics are:

Purpose

Sets the state of the overflow bit for the Cycle Count Register, PMCCNTR_EL0, and each of the implemented event counters PMEVCNTR<n>.

Configuration

External register PMOVSSET_EL0 bits [31:0] are architecturally mapped to AArch64 System register PMOVSSET_EL0[31:0] .

External register PMOVSSET_EL0 bits [31:0] are architecturally mapped to AArch32 System register PMOVSSET[31:0] .

PMOVSSET_EL0 is in the Core power domain.

~~PMOVSSET_EL0 is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply on a Warm or Cold reset. The register is not affected by an External debug reset.~~

Attributes

PMOVSSET_EL0 is a 32-bit register.

Field descriptions

The PMOVSSET_EL0 bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
C	P<n>, bit [n]																														

C, bit [31]

Cycle counter overflow set bit.

C	Meaning
0b0	When read, means the cycle counter has not overflowed since this bit was last cleared. When written, has no effect.
0b1	When read, means the cycle counter has overflowed since this bit was last cleared. When written, sets the cycle counter overflow bit to 1.

PMCR_EL0.LC controls whether an overflow is detected from unsigned overflow of PMCCNTR_EL0[31:0] or unsigned overflow of PMCCNTR_EL0[63:0].

On a Warm reset, this field resets to an architecturally UNKNOWN value.

P<n>, bit [n], for n = 0 to 30

Event counter overflow set bit for PMEVCNTR<n>_EL0.

If PMCFGR.N is less than 31, bits [30:PMCFGR.N] are RAZ/WI.

P<n>	Meaning
0b0	When read, means that PMEVCNTR<n>_EL0 has not overflowed since this bit was last cleared. When written, has no effect.
0b1	When read, means that PMEVCNTR<n>_EL0 has overflowed since this bit was last cleared. When written, sets the PMEVCNTR<n>_EL0 overflow bit to 1.

If ARMv8.5-PMU is implemented, MDCR_EL2.HLP and PMCR_EL0.LP control whether an overflow is detected from unsigned overflow of PMEVCNTR<n>_EL0[31:0] or unsigned overflow of PMEVCNTR<n>_EL0[63:0].

On a Warm reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMOVSSET_EL0

Note

SoftwareLockStatus() depends on the type of access attempted and AllowExternalPMUAccess() has a new definition from Armv8.4. Refer to the Pseudocode definitions for more information.

PMOVSSET_EL0 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xCC0	PMOVSSET_EL0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and SoftwareLockStatus() accesses to this register are **RO**.
- When IsCorePowered(), !DoubleLockStatus(), !OSLockStatus(), AllowExternalPMUAccess() and !SoftwareLockStatus() accesses to this register are **RW**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMPCSR, Program Counter Sample Register

The PMPCSR characteristics are:

Purpose

Holds a sampled instruction address value.

Configuration

PMPCSR is in the Core power domain.

~~PMPCSR is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

This register is present only when ARMv8.2-PCSample is implemented. Otherwise, direct accesses to PMPCSR are RES0.

Note

Before Armv8.2, the PC Sample-based Profiling Extension can be implemented in the external debug register space, as indicated by the value of EDDEVID.PCSample.

Support for 64-bit atomic reads is IMPLEMENTATION DEFINED. If 64-bit atomic reads are implemented, a 64-bit read of PMPCSR has the same side-effect as a 32-bit read of PMCSR[31:0] followed by a 32-bit read of PMPCSR[63:32], returning the combined value. For example, if the PE is in Debug state then a 64-bit atomic read returns bits[31:0] == `0xFFFFFFFF` and bits[63:32] UNKNOWN.

Attributes

PMPCSR is a 64-bit register.

Field descriptions

The PMPCSR bit assignments are:



NS, bit [63]

Non-secure state sample. Indicates the Security state that is associated with the most recent PMPCSR sample or, when it is read as a single atomic 64-bit read, the current PMPCSR sample.

If EL3 is not implemented, this bit indicates the Effective value of SCR.NS.

NS	Meaning
`0b0`	Sample is from Secure state.
`0b1`	Sample is from Non-secure state.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

EL, bits [62:61]

Exception level status sample. Indicates the Exception level that is associated with the most recent PMPCSR sample or, when it is read as a single atomic 64-bit read, the current PMPCSR sample.

EL	Meaning
0b00	Sample is from EL0.
0b01	Sample is from EL1.
0b10	Sample is from EL2.
0b11	Sample is from EL3.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Bits [60:56]

Reserved, RES0.

PCSamplePC Sample[55:32], bits [55:32]

Bits[55:32] of the sampled instruction address value. The translation regime that PMPCSR samples can be determined from PMPCSR.{NS,EL}.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

PCSamplePC Sample[31:0], bits [31:0]

Bits[31:0] of the sampled instruction address value.

PMPCSR[31:0] reads as 0xFFFFFFFF when any of the following are true:

- The PE is in Debug state.
- PC Sample-based profiling is prohibited.

If an instruction has retired since the PE left Reset state, then the first read of PMPCSR[31:0] is permitted but not required to return 0xFFFFFFFF.

PMPCSR[31:0] reads as an UNKNOWN value when any of the following are true:

- The PE is in Reset state.
- No instruction has retired since the PE left Reset state, Debug state, or a state where PC Sample-based Profiling is prohibited.
- No instruction has retired since the last read of PMPCSR[31:0].

For the cases where a read of PMPCSR[31:0] returns 0xFFFFFFFF or an UNKNOWN value, the read has the side-effect of setting PMPCSR[63:32], PMCID1SR, PMCID2SR, and PMVIDSR to UNKNOWN values.

Otherwise, a read of PMPCSR[31:0] returns bits [31:0] of the sampled instruction address value and has the side-effect of indirectly writing to PMPCSR[63:32], PMCID1SR, PMCID2SR, and PMVIDSR. The translation regime that PMPCSR samples can be determined from PMPCSR.{NS,EL}.

For a read of PMPCSR[31:0] from the memory-mapped interface, if PMLSR.SLK == 1, meaning the OPTIONAL Software Lock is locked, then the side-effect of the access does not occur and PMPCSR[63:32], PMCID1SR, PMCID2SR, and PMVIDSR are unchanged.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMPCSR

IMPLEMENTATION DEFINED extensions to external debug might make the value of this register UNKNOWN, see 'Permitted behavior that might make the PC Sample-based profiling registers UNKNOWN' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile

PMPCSR can be accessed through the external debug interface:

Component	Offset	Instance	Range
PMU	0x200	PMPCSR	31:0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

Component	Offset	Instance	Range
PMU	0x204	PMPCSR	63:32

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

Component	Offset	Instance	Range
PMU	0x220	PMPCSR	31:0

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

Component	Offset	Instance	Range
PMU	0x224	PMPCSR	63:32

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

13~~27~~/12~~09~~/2019 15~~18~~:13~~48~~; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMPIDR0, Performance Monitors Peripheral Identification Register 0

The PMPIDR0 characteristics are:

Purpose

Provides information to identify a Performance Monitor component.

For more information see 'About the Peripheral identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether PMPIDR0 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

PMPIDR0 is a 32-bit register.

Field descriptions

The PMPIDR0 bit assignments are:



Bits [31:8]

Reserved, RES0.

PART_0, bits [7:0]

Part number, least significant byte.

Accessing the PMPIDR0

PMPIDR0 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFE0	PMPIDR0

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMPIDR1, Performance Monitors Peripheral Identification Register 1

The PMPIDR1 characteristics are:

Purpose

Provides information to identify a Performance Monitor component.

For more information see 'About the Peripheral identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether PMPIDR1 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

PMPIDR1 is a 32-bit register.

Field descriptions

The PMPIDR1 bit assignments are:



Bits [31:8]

Reserved, RES0.

DES_0, bits [7:4]

Designer, least significant nibble of JEP106 ID code. For Arm Limited, this field is `0b1011`.

PART_1, bits [3:0]

Part number, most significant nibble.

Accessing the PMPIDR1

PMPIDR1 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFE4	PMPIDR1

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMPIDR2, Performance Monitors Peripheral Identification Register 2

The PMPIDR2 characteristics are:

Purpose

Provides information to identify a Performance Monitor component.

For more information see 'About the Peripheral identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether PMPIDR2 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

PMPIDR2 is a 32-bit register.

Field descriptions

The PMPIDR2 bit assignments are:



Bits [31:8]

Reserved, RES0.

REVISION, bits [7:4]

Part major revision. Parts can also use this field to extend Part number to 16-bits.

JEDEC, bit [3]

RAO. Indicates a JEP106 identity code is used.

DES_1, bits [2:0]

Designer, most significant bits of JEP106 ID code. For Arm Limited, this field is `0b011`.

Accessing the PMPIDR2

PMPIDR2 can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0xFE8	PMPIDR2

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMPIDR3, Performance Monitors Peripheral Identification Register 3

The PMPIDR3 characteristics are:

Purpose

Provides information to identify a Performance Monitor component.

For more information see 'About the Peripheral identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether PMPIDR3 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

PMPIDR3 is a 32-bit register.

Field descriptions

The PMPIDR3 bit assignments are:



Bits [31:8]

Reserved, RES0.

REVAND, bits [7:4]

Part minor revision. Parts using PMPIDR2.REVISION as an extension to the Part number must use this field as a major revision number.

CMOD, bits [3:0]

Customer modified. Indicates someone other than the Designer has modified the component.

Accessing the PMPIDR3

PMPIDR3 can be accessed through the external debug interface:

Component	Offset	Instance

PMU	0xFEC	PMPIDR3

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMPIDR4, Performance Monitors Peripheral Identification Register 4

The PMPIDR4 characteristics are:

Purpose

Provides information to identify a Performance Monitor component.

For more information see 'About the Peripheral identification scheme' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile, section H8 (About the External Debug Registers).

Configuration

~~It is IMPLEMENTATION DEFINED whether PMPIDR4 is implemented in the Core power domain or in the Debug power domain.~~

Implementation of this register is OPTIONAL.

If ARMv8.3-DoPD is implemented, this register is in the Core power domain. If ARMv8.3-DoPD is not implemented, this register is in the Debug power domain.

This register is required for CoreSight compliance.

Attributes

PMPIDR4 is a 32-bit register.

Field descriptions

The PMPIDR4 bit assignments are:



Bits [31:8]

Reserved, RES0.

SIZE, bits [7:4]

Size of the component. RAZ. Log_2 of the number of 4KB pages from the start of the component to the end of the component ID registers.

DES_2, bits [3:0]

Designer, JEP106 continuation code, least significant nibble. For Arm Limited, this field is `0b0100`.

Accessing the PMPIDR4

PMPIDR4 can be accessed through the external debug interface:

Component	Offset	Instance

PMU	0xFD0	PMPIDR4

This interface is accessible as follows:

- When ARMv8.3-DoPD is not implemented or IsCorePowered() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8c12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)

(old) htmldiff from- (new)

PMVIDSR, VMID Sample Register

The PMVIDSR characteristics are:

Purpose

Contains the sampled VMID value that is captured on reading PMPCSR[31:0].

Configuration

PMVIDSR is in the Core power domain.

~~PMVIDSR is in the Core power domain. RW fields in this register reset to architecturally UNKNOWN values. These apply only on a Cold reset. The register is not affected by a Warm reset and is not affected by an External debug reset.~~

This register is present only when ARMv8.2-PCSample is implemented and ~~HaveEL(~~EL2 is implemented.~~).~~ Otherwise, direct accesses to PMVIDSR are RES0.

Note

Before Armv8.2, the PC Sample-based Profiling Extension can be implemented in the external debug register space, as indicated by the value of EDDEVID.PCSample.

Attributes

PMVIDSR is a 32-bit register.

Field descriptions

The PMVIDSR bit assignments are:

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RES0																VMID[15:8]								VMID							

Bits [31:16]

Reserved, RES0.

VMID[15:8], bits [15:8]

When ARMv8.1-VMID16 is implemented:

Extension to VMID[7:0]. See VMID[7:0] for more details.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Otherwise:

Reserved, RES0.

VMID, bits [7:0]

VMID sample. The VMID associated with the most recent PMPCSR sample. When the most recent PMPCSR sample was generated:

- This field is set to an UNKNOWN value if any of the following apply:
  - EL2 is disabled in the current Security state.
  - The PE is executing at EL2.
  - EL2 is enabled in the current Security state, the PE is executing at EL0, EL2 is using AArch64, HCR_EL2.E2H == 1, and HCR_EL2.TGE == 1.
- Otherwise:
  - If EL2 is using AArch64 and either ARMv8.1-VMID16 is not implemented or VTCR_EL2.VS is 1, this field is set to VTTBR_EL2.VMID.
  - If EL2 is using AArch64, ARMv8.1-VMID16 is implemented, and VTCR_EL2.VS is 0, PMVIDSR.VMID[7:0] is set to VTTBR_EL2.VMID[7:0] and PMVIDSR.VMID[15:8] is RES0.
  - If EL2 is using AArch32, this field is set to VTTBR.VMID.

Because the value written to PMVIDR is an indirect read of the VMID value, it is CONSTRAINED UNPREDICTABLE whether PMVIDSR is set to the original or new value if PMPCSR samples:

- An instruction that writes to the VMID value.
- The next Context synchronization event.
- Any instruction executed between these two instructions.

On a Cold reset, this field resets to an architecturally UNKNOWN value.

Accessing the PMVIDSR

IMPLEMENTATION DEFINED extensions to external debug might make the value of this register UNKNOWN, see 'Permitted behavior that might make the PC Sample-based profiling registers UNKNOWN' in the Arm® Architecture Reference Manual, Armv8, for Armv8-A architecture profile

PMVIDSR can be accessed through the external debug interface:

Component	Offset	Instance
PMU	0x20C	PMVIDSR

This interface is accessible as follows:

- When IsCorePowered(), !DoubleLockStatus() and !OSLockStatus() accesses to this register are **RO**.
- Otherwise accesses to this register generate an error response.

1327/1209/2019 1518:1348; 391b5248b29fb2f001ef74792eaacbd6fc72f2116134483bd14dc8e12a99c984cbfe3431cc1c9707

Copyright © 2010-2019 Arm Limited or its affiliates. All rights reserved. This document is Non-Confidential.

(old) htmldiff from- (new)