

Arm Licence Server User Guide

Version 20.0

The Arm logo, consisting of the lowercase letters 'arm' in a bold, blue, sans-serif font.

Non-Confidential Proprietary Notice

This document is protected by copyright and other related rights and the practice or implementation of the information contained in this document may be protected by one or more patents or pending patent applications. No part of this document may be reproduced in any form by any means without the express prior written permission of Arm. **No license, express or implied, by estoppel or otherwise to any intellectual property rights is granted by this document unless specifically stated.**

Your access to the information in this document is conditional upon your acceptance that you will not use or permit others to use the information for the purposes of determining whether implementations infringe any third party patents.

THIS DOCUMENT IS PROVIDED “AS IS”. ARM PROVIDES NO REPRESENTATIONS AND NO WARRANTIES, EXPRESS, IMPLIED OR STATUTORY, INCLUDING, WITHOUT LIMITATION, THE IMPLIED WARRANTIES OF MERCHANTABILITY, SATISFACTORY QUALITY, NON-INFRINGEMENT OR FITNESS FOR A PARTICULAR PURPOSE WITH RESPECT TO THE DOCUMENT. For the avoidance of doubt, Arm makes no representation with respect to, and has undertaken no analysis to identify or understand the scope and content of, third party patents, copyrights, trade secrets, or other rights.

This document may include technical inaccuracies or typographical errors.

TO THE EXTENT NOT PROHIBITED BY LAW, IN NO EVENT WILL ARM BE LIABLE FOR ANY DAMAGES, INCLUDING WITHOUT LIMITATION ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, ARISING OUT OF ANY USE OF THIS DOCUMENT, EVEN IF ARM HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

This document consists solely of commercial items. You shall be responsible for ensuring that any use, duplication or disclosure of this document complies fully with any relevant export laws and regulations to assure that this document or any portion thereof is not exported, directly or indirectly, in violation of such export laws. Use of the word “partner” in reference to Arm’s customers is not intended to create or refer to any partnership relationship with any other company. Arm may make changes to this document at any time and without notice.

If any of the provisions contained in these terms conflict with any of the provisions of any click through or signed written agreement covering this document with Arm, then the click through or signed written agreement prevails over and supersedes the conflicting provisions of these terms. This document may be translated into other languages for convenience, and you agree that if there is any conflict between the English version of this document and any translation, the terms of the English version of the Agreement shall prevail.

The Arm corporate logo and words marked with ® or ™ are registered trademarks or trademarks of Arm Limited (or its subsidiaries) in the US and/or elsewhere. All rights reserved. Other brands and names mentioned in this document may be the trademarks of their respective owners. Please follow Arm’s trademark usage guidelines at <http://www.arm.com/company/policies/trademarks>.

Copyright ©2018, 2019 Arm Limited (or its affiliates). All rights reserved. Arm Limited. Company 02557590 registered in England. 110 Fulbourn Road, Cambridge, England CB1 9NJ. LES-PRE-20349

Confidentiality Status

This document is Non-Confidential. The right to use, copy and disclose this document may be subject to license restrictions in accordance with the terms of the agreement entered into by Arm and the party that Arm delivered this document to.

Unrestricted Access is an Arm internal classification.

Product Status

The information in this document is Final, that is for a developed product.

Web Address

<http://www.arm.com>

Contents

Contents	3
1 Introduction	4
1.1 Online resources	4
1.2 Obtaining help	4
2 Installation	5
2.1 Linux installation	5
3 Using Arm Licence Server	6
3.1 Running Arm Licence Server	6
3.1.1 Systemd-based distributions	6
3.1.2 SysVinit-based distributions	7
3.2 Logging	7
3.3 Adding a new license	8
3.4 Example	8
3.5 Running product clients	9
3.6 Architecture licensing	10
3.6.1 Using multiple architecture licenses	10
3.7 Accessing Arm Licence Server behind a firewall	11
3.8 Querying status	11
3.9 Handling lost clients	12
3.10 Troubleshooting	13

Introduction

Welcome to the Arm Licence Server user guide. This guide covers installation and use of Arm Licence Server.

There are several license types available for Arm products. These can be summarized as:

- Evaluation licenses
- Workstation licenses
- Supercomputing cluster licenses

For the case where evaluation and workstation licenses are used, the license file is simply copied to the Arm product installation directory, *{installation-directory}/licences*, and Arm Licence Server is not required.

In the case of supercomputing cluster scenarios where evaluation licenses are not being used, the use of Arm Licence Server is a requirement.

Note that when the remote clients for Mac OS X , Windows and Linux are used, the license file in this case is installed on the target system that the remote client connects to for the purposes of debugging or analysis. This applies whether or not an evaluation license is being used. For example, a remote client for Mac OS X needs to debug a remote system for evaluation purposes. In this case the evaluation license needs to be installed on the system to be debugged, and not where the remote client is installed. Once the evaluation period ends, new licenses should be purchased, and Arm Licence Server should be installed to handle licensing.

Installation of licenses is discussed further in the [Adding a new license](#) section.

Once you have determined that Arm Licence Server is a requirement for your site, you can proceed with [Installation](#).

Online resources

You can find links to tutorials, training material, webinars and white papers in our online knowledge center:

Knowledge Center [Arm help and tutorials](#)

Known issues and the latest version of this user guide may be found on the support web pages:

Support [Arm Developer website](#)

Obtaining help

You can contact Arm support at [Arm support](#).

Installation

A release of Arm Licence Server may be downloaded from the [Arm Developer website](#).

Linux installation

Arm Licence Server is only available for Linux systems. The install script `textinstall.sh` should be used:

```
tar xf arm-licence server-20.0-<distro>-<arch>.tar  
cd arm-licence server-20.0-<distro>-<arch>  
./textinstall.sh
```

replacing `<distro>` and `<arch>` with the OS distribution and architecture of your tar package, respectively. For example, the tarball package for Redhat 7.4 OS and Armv8-A (AArch64) architecture is: `arm-licence server-20.0 -Redhat-7.4-aarch64.tar`

Press *Return* to read the license when prompted and then enter the directory where you would like to install Arm Licence Server.

Alternatively, to run the text-mode install script `textinstall.sh`, accept the license, and point to an installation directory in one step, pass the arguments `--accept-licence` and `{installation-directory}` when executing `textinstall.sh`. For example:

```
./textinstall.sh --accept-licence <installation_directory>
```

replacing the `<installation_directory>` with a directory of your choice.

Using Arm Licence Server

Arm Licence Server is capable of serving several different types of license, enabling one server to serve all Arm software in an organization.

It should be pointed out that Arm Licence Server is not required to serve evaluation licenses and workstation licenses, only floating licenses for HPC clusters.

Running Arm Licence Server

To ensure security, Arm Licence Server should only be run as an unprivileged user. For example, `no-body`, or preferably a dedicated user.

If run without arguments, Arm Licence Server uses licenses in the current directory, that is, files matching `Licence*` and `License*`. An optional argument specifies the directory to be used instead of the current directory.

Typically floating license server files are stored in the Arm Licence Server installation directory, for example, `/opt/arm/licenceserver/licenses`. This is also the directory the `systemd` unit and Sys-V style `init` script use by default.

System administrators typically configure the license server to start automatically during system boot. Arm Licence Server includes a `systemd` unit configuration file for Red Hat Enterprise Linux 7 and SUSE Linux Enterprise Server 12, and a SysV-style `init` script for Debian, Ubuntu, and previous Red Hat and SUSE releases.

Before configuring Arm Licence Server to start automatically, an unprivileged user should be created, and a log directory allocated, as shown in the following example (these commands must be run as `root`):

```
adduser --system --user-group --no-create-home \
        --home-dir /opt/arm/licenceserver allinea
mkdir /var/log/allinea
chown allinea: /var/log/allinea
```

This creates the user `allinea`, creates the log directory `/var/log/allinea`, and finally the user is assigned ownership of the log directory.

Note that `/opt/arm/licenceserver` is the location of the Arm Licence Server installation.

The license server log file is `/var/log/allinea/allinea.log` by default.

Systemd-based distributions

This section shows you how to run Arm Licence Server on `Systemd`-based systems.

For Red Hat Enterprise Linux 7 and SUSE Linux Enterprise Server 12, a `systemd` unit configuration file can be used to start Arm Licence Server. To use it, follow the procedure below (as `root`):

1. Edit `lib/systemd/system/allinea-licenceserver.service` in your Arm Licence Server installation. Make sure that the `Environment`, `ExecStart` and `User` settings in the `[Service]` section are correct for your system.
2. Enable the license server on future boots:

```
systemctl enable \
lib/systemd/system/allinea-licenceserver.service
```

3. Start the license server:

```
systemctl start allinea-licenceserver
```

4. Check that it started properly:

```
systemctl status allinea-licenceserver
```

SysVinit-based distributions

This section shows you how to run Arm Licence Server on SysVinit-based systems.

`bin/allinea_licensing_init` is a SysV-style `init` script for both Debian and Ubuntu, and previous Red Hat Enterprise Linux and SUSE Linux Enterprise Server releases. To use the script, follow the procedure below (as `root`):

1. Set `ALLINEA_TOOLS_PATH` at the top of the script to point to the Arm Licence Server installation, for example, `/opt/arm/licenceserver`.
2. Set `ALLINEA_LICENCE_USER` to the name of the user to run the license server as. This should be the user already created for this purpose, for example, `allinea`.
3. Install the script to `/etc/init.d`:

```
ln -s /opt/arm/licenceserver/bin/allinea_licensing_init \
/etc/init.d/
```

4. Enable the service at boot time:

```
# On Red Hat or SUSE systems:
chkconfig --add allinea_licensing_init

# On Debian or Ubuntu systems:
update-rc.d allinea_licensing_init defaults
```

5. Start the service:

```
service allinea_licensing_init start
```

6. Check that it started correctly:

```
service allinea_licensing_init status
```

Logging

This section shows you how to enable logging.

Set the environment variable `ALLINEA_LICENCE_LOGFILE` to the file that you wish to append log information to.

Set `ALLINEA_LICENCE_LOGLEVEL` to specify the amount of information required. These steps must be done prior to starting the server.

The following list specifies the available log levels:

- Level 0: no logging.
- Level 1: client licenses issued are shown, served licenses are listed.
- Level 2: stale licenses are shown when removed, licenses still being served are listed if there is no spare license.
- Level 3: full request strings received are displayed.
- Level 6: is the maximum.

In level 1 and above, the MAC address, user name, process ID, and IP address of the clients are logged.

Adding a new license

This section shows you how to add a floating license to Arm Licence Server.

A floating license consists of two files: the server license (a file named `Licence.xxxx`) and a client license file, `Licence`.

The following procedure demonstrates how to add a new floating license:

- Copy the server license file to the `licences` subdirectory of the Arm Licence Server installation. For example, `/opt/arm/licenceserver/licences`.
- Copy the client license file to the `licences` subdirectory in the installation of the licensed product, `{forge-or-reports-installation-directory}/licences`. For example, `/opt/arm/forge/licences/Licence`.
- Edit the client license file to specify the hostname of the license server in use.
- Restart Arm Licence Server for the new floating license to be picked up. Existing clients should not experience disruption if the restart is completed promptly.

It is permissible to have multiple floating licenses being served from the same `licences` directory. For example, you may have one server license file for Arm DDT and another for Arm Performance Reports. If you have multiple licenses for the same product the license with the most tokens will be preferred.

Note: Workstation and Evaluation license files do not need a license server and should be copied directly to the Arm Forge or Arm Performance Reports `licences` subdirectory, for example, `/home/user/arm/forge/licences/Licence.ddt`.

Example

In this example it is assumed that there is a dedicated license server machine running Red Hat Enterprise Linux 6. The Arm Licence Server is installed in `/opt/arm/licenceserver` and the server license files are stored in `/opt/arm/licenceserver/licences`.

Note: If you install the Arm Licence Server to a different installation path you will need to edit the `ALLINEA_TOOLS_PATH` variable in the `allinea_licensing_init` script.

To run Arm Licence Server program as the dedicated `allinea` user, serving all licenses in `/opt/arm/licenceserver/licences`, and logging most events to the `/var/log/allinea/allinea.log`, use the following procedure:

```
$ su - root
% adduser --system --user-group --no-create-home \
    --home-dir /opt/arm/licenceserver allinea
```

```
% mkdir /var/log/allinea
% chown allinea: /var/log/allinea
% ln -s /opt/arm/licenceserver/bin/allinea_licensing_init \
  /etc/init.d/
% chkconfig --add allinea_licensing_init
% service allinea_licensing_init start
```

If the server license file is `/opt/arm/licenceserver/licences/Licence.server.physics` and is served by the machine `server.physics.acme.edu`, on port 4252, the server license file would resemble the following:

```
type=3
serial_number=1014
max_processes=48
expires=2004-04-01 00:00:00
support_expires=2004-04-01 00:00:00
mac=00:E0:81:03:6C:DB
interface=eth0
debuggers=gdb
serverport=4252
max_users=2
beat=60
retry_limit=4
hash2=c18101680ae9f8863266d4aa7544de58562ea858
```

Then the client license could be stored at `/opt/arm/forgelicences/Licence.client.physics` and contain:

```
type=2
serial_number=1014
hostname=server.physics.acme.edu
serverport=4252
```

Note that the client file `hostname` parameter has been edited to reference Arm Licence Server.

Running product clients

Before you begin

- License file names must begin with either `License`, or the variant spelling `Licence`.
- License file names are not case-sensitive.
- You can append any other characters to the name, such as the server license serial number and other identifiers, such as "client", to give unique names to multiple licenses stored in the same directory, for example, `license.client.1234`.

Procedure

1. For each floating license, copy the corresponding client license file to the relevant `licences` subdirectory in the product installation directory, `{forge_or_reports_installation_directory}/licences`. For example, copy the forge client license to `/opt/arm/forgelicences`.
2. Edit `hostname` in the client license file to include the hostname or IP address of the machine on which the Arm Licence Server runs.

3. If your `Licenses` directory is not in the product installation directory, you can specify the directory path to point to the location of the product licenses using the environment variable `ALLINEA_LICENCE_DIR`.

Notes

- If you include a specific license file name in the `ALLINEA_LICENCE_DIR` path, the Arm Licence Server always attempts to serve that specific license.
- You can set the environment variable in a *module* file for the product. For example:

```
export ALLINEA_LICENCE_DIR=${HOME}/SomeOtherLicenceDir
forge
```

The fields in the client license file are:

Name	Required	Description
hostname	Yes	The hostname, or IP address of the license server
ports	No	A comma separated list of ports to be tried locally for GUI-backend communication, Defaults to 4242,4243,4244,4244,4245
serial_number	Yes	The serial number of the server license to be used
serverport	Yes	The port the server listens on
type	Yes	Must have value 2—this indicates that the license requires a server to run correctly

Note: The serial number of the server license is specified as this enables a user to be tied to a particular license.

Architecture licensing

Licenses issued after the release of Arm Licence Server 6.1 specify the compute node architectures that they may be used with. Licences issued prior to this release will enable the `x86_64` architecture by default. Existing users for other architectures will be supplied with new licenses that will enable their architectures.

If there is any problem then contact Arm support at [Arm support](#).

Using multiple architecture licenses

If you are using multiple license files to specify multiple architectures, Arm recommends that you follow these steps.

Procedure

1. Ensure that the default licenses directory is empty.
2. Create a directory for each architecture.
3. When you want to target a specific architecture, set `ALLINEA_LICENSE_DIR` to the relevant directory.
Alternatively, set `ALLINEA_LICENSE_FILE` to specify the license file.

Example

On a site that targets two architectures, x86_64 and AArch64, create a directory for each architecture, and name them `licenses_x86_64` and `licenses_aarch64`. Then, to target the architectures, set the license directories as follows:

To target AArch64:

```
export ALLINEA_LICENSE_DIR=/path/to/licenses/licenses_aarch64
```

To target x86_64:

```
export ALLINEA_LICENSE_DIR=/path/to/licenses/licenses_x86_64
```

Accessing Arm Licence Server behind a firewall

In some scenarios Arm Licence Server may be located behind a firewall. This is the case if you are accessing a license server hosted by Arm. You may also be debugging a system that is not on the same network as the license server. In this case SSH forwarding can be used to access the license server that is behind the firewall.

A local client license file is created or modified to specify `localhost` as the `hostname` parameter:

```
type=2  
serial_number=1014  
hostname=localhost  
serverport=4252
```

Communication is then forwarded over the secure SSH connection to Arm Licence Server, which is listening on port 4252.

An example of the command to set up the SSH forwarding is shown here:

```
ssh -C -L 4252:server.physics.acme.edu:4242 login.physics.acme.edu
```

The `-C` switch is optional, and enables compression for the situation where communication takes place over relatively slow links.

Querying status

Arm Licence Server provides a simple HTML interface to allow for querying of the current state of the licenses being served. This can be accessed in a web browser at the following URL:

```
http://<hostname>:<serverport>/status.html
```

For example, using the values described in the section [Example](#), the URL would be:

```
http://server.physics.acme.edu:4252/status.html
```

Initially, no licenses are being served, and the output in your browser window would be similar to the following:

```
[Licences start]  
[Licence Serial Number: 1014]  
[No licences allocated - 2 available]  
[Licences end]
```

You can see that two licenses are available in this example.

As licenses are served and released, the information displayed will change. To update the status display, simply refresh your web browser window. For example, after one Arm product is started, the output is updated:

```
[Licences start]
[Licence Serial Number: 1014]
[1 licences available]
[Client 1]
[mac=00:04:23:99:79:65; uname=gwh; pid=14007; licence=1014]
[Latest heartbeat: 2004-04-13 11:59:15]
[Licences end]
```

Then, after another Arm product is started and the web browser window is refreshed (notice the value for number of licences available), the output is updated:

```
[Licences start]
[Licence Serial Number: 1014]
[0 licences available]
[Client 1]
[mac=00:04:23:99:79:65; uname=gwh; pid=14007; licence=1014]
[Latest heartbeat: 2004-04-13 12:04:15]
[Client 2]
[mac=00:40:F4:6C:4A:71; uname=graham; pid=3700; licence
=1014]
[Latest heartbeat: 2004-04-13 12:04:59]
[Licences end]
```

Finally, after the first Arm product finishes:

```
[Licences start]
[Licence Serial Number: 1014]
[1 licences available]
[Client 1]
[mac=00:40:F4:6C:4A:71; uname=graham; pid=3700; licence
=1014]
[Latest heartbeat: 2004-04-13 12:07:59]
[Licences end]
```

Handling lost clients

Should Arm Licence Server lose communication with an instance of a client, the license allocated to that client is made unavailable for new clients until a timeout period has expired. The length of this timeout period can be calculated from the license server file values for `beat` and `retry_limit`:

$$\text{lost_client_timeout_period} = (\text{beat seconds}) * (\text{retry_limit} + 1)$$

For the example license files above, the timeout period would be:

$$60 * (4 + 1) = 300 \text{ seconds}$$

During this timeout period, details of the 'lost' client continue to be output by the status display. As long as additional licenses are available, new clients can be started. However, once all of these additional licenses have been allocated, new clients are refused a license while this timeout period is active.

After this timeout period has expired, the status continues to display details of the 'lost' client until another client is started. Arm Licence Server grants a license to the new client and the status display then reflects the details of the new client.

Troubleshooting

Licenses are plain-text which enables you to see the parameters that are set. A checksum verifies the validity of the license.

If problems arise, the first step is to check the parameters specified in the license file are consistent with the machine that is being used (MAC and IP address), and that the number of users is as expected.

A port which is already used can not be used by Arm Licence Server. Check that you have specified an unused port.

Only privileged users can use ports below 1024, so you should use port 1024 or higher. You should not launch Arm Licence Server as root due to security issues.

Index

Arm Licence Server

Running, [6](#)

Using, [6](#)

Architecture licensing, [10](#)

Multiple licenses, [10](#)

Distributions

Systemd, [6](#)

SysVinit, [7](#)

Example, [8](#)

Firewall, [11](#)

Installation, [5](#)

Linux, [5](#)

License

Adding, [8](#)

Logging, [7](#)

Lost clients, [12](#)

Obtaining help, [4](#)

Online resources, [4](#)

Product clients, [9](#)

Status, [11](#)

Troubleshooting, [13](#)